



# CipherTrust Data Security Platform

## CipherTrust Data Security Event and Log Messages Guide

Release 7.2.0

Document Version 1

**February 4, 2022**

*CipherTrust Data Security CipherTrust Transparent Encryption  
CipherTrust Data Security CipherTrust Data Security Event and Log Messages Guide*

Release 7.2.0

February 2, 2022

Document Version 1

All information herein is either public information or is the property of and owned solely by Thales DIS France S.A. and/or its subsidiaries or affiliates who shall have and keep the sole right to file patent applications or any other kind of intellectual property protection in connection with such information.

Nothing herein shall be construed as implying or granting to you any rights, by license, grant or otherwise, under any intellectual and/or industrial property rights of or concerning any of Thales DIS France S.A. and any of its subsidiaries and affiliates (collectively referred to herein after as "Thales") information.

This document can be used for informational, non-commercial, internal and personal use only provided that:

- The copyright notice below, the confidentiality and proprietary legend and this full warning notice appear in all copies.
- This document shall not be posted on any network computer or broadcast in any media and no modification of any part of this document shall be made.

Use for any other purpose is expressly prohibited and may result in severe civil and criminal liabilities.

The information contained in this document is provided "AS IS" without any warranty of any kind. Unless otherwise expressly agreed in writing, Thales makes no warranty as to the value or accuracy of information contained herein.

The document could include technical inaccuracies or typographical errors. Changes are periodically added to the information herein. Furthermore, Thales reserves the right to make any change or improvement in the specifications data, information, and the like described herein, at any time.

Thales hereby disclaims all warranties and conditions with regard to the information contained herein, including all implied warranties of merchantability, fitness for a particular purpose, title and non-infringement. In no event shall Thales be liable, whether in contract, tort or otherwise, for any indirect, special or consequential damages or any damages whatsoever including but not limited to damages resulting from loss of use, data, profits, revenues, or customers, arising out of or in connection with the use or performance of information contained in this document.

Thales does not and shall not warrant that this product will be resistant to all possible attacks and shall not incur, and disclaims, any liability in this respect. Even if each product is compliant with current security standards in force on the date of their design, security mechanisms' resistance necessarily evolves according to the state of the art in security and notably under the emergence of new attacks. Under no circumstances, shall Thales be held liable for any third party actions and in particular in case of any successful attack against systems or equipment incorporating Thales products. Thales disclaims any liability with respect to security for direct, indirect, incidental or consequential damages that result from any use of its products. It is further stressed that independent testing and verification by the person using the product is particularly encouraged, especially in any application in which defective, incorrect or insecure functioning could result in damage to persons or property, denial of service or loss of privacy.

Copyright © 2009 - 2022 Thales Group. All rights reserved. Thales and the Thales logo are trademarks and service marks of Thales and/or its subsidiaries and affiliates and are registered in certain countries. All other trademarks and service marks, whether registered or not in specific countries, are the properties of their respective owners.

# Table of Contents

<b>Logger CA0: Errors</b> .....	<b>1</b>
<u>Message ID : CA00642E</u> .....	1
<u>Message ID : CA00643E</u> .....	1
<u>Message ID : CA00644E</u> .....	2
<u>Message ID : CA00645E</u> .....	3
<b>Logger CFG: Errors</b> .....	<b>4</b>
<u>Message ID : CFG0026E</u> .....	4
<u>Message ID : CFG0027E</u> .....	4
<u>Message ID : CFG0028E</u> .....	5
<u>Message ID : CFG0029E</u> .....	6
<u>Message ID : CFG0030E</u> .....	6
<u>Message ID : CFG0031E</u> .....	7
<u>Message ID : CFG0032E</u> .....	8
<u>Message ID : CFG0033E</u> .....	8
<u>Message ID : CFG0034E</u> .....	9
<u>Message ID : CFG0264E</u> .....	10
<u>Message ID : CFG0306E</u> .....	10
<u>Message ID : CFG0333E</u> .....	11
<u>Message ID : CFG0334E</u> .....	12
<u>Message ID : CFG0335E</u> .....	12
<u>Message ID : CFG0336E</u> .....	13
<u>Message ID : CFG0339E</u> .....	14
<u>Message ID : CFG0341E</u> .....	14
<u>Message ID : CFG0520E</u> .....	15
<u>Message ID : CFG0521E</u> .....	16
<u>Message ID : CFG0522E</u> .....	16

# Table of Contents

## Logger CFG: Errors

<u>Message ID : CFG0523E</u> .....	17
<u>Message ID : CFG0524E</u> .....	18
<u>Message ID : CFG0527E</u> .....	19
<u>Message ID : CFG0528E</u> .....	19
<u>Message ID : CFG0529E</u> .....	20
<u>Message ID : CFG0530E</u> .....	21
<u>Message ID : CFG0531E</u> .....	21
<u>Message ID : CFG0532E</u> .....	22
<u>Message ID : CFG0636E</u> .....	23
<u>Message ID : CFG1334E</u> .....	23
<u>Message ID : CFG1335E</u> .....	24
<u>Message ID : CFG1352E</u> .....	25
<u>Message ID : CFG1367E</u> .....	25
<u>Message ID : CFG1368E</u> .....	26
<u>Message ID : CFG1400E</u> .....	27
<u>Message ID : CFG1514E</u> .....	28
<u>Message ID : CFG1515E</u> .....	28
<u>Message ID : CFG1517E</u> .....	29
<u>Message ID : CFG1705E</u> .....	30
<u>Message ID : CFG1727E</u> .....	30
<u>Message ID : CFG1734E</u> .....	31
<u>Message ID : CFG1735E</u> .....	32
<u>Message ID : CFG1775E</u> .....	32
<u>Message ID : CFG1776E</u> .....	33
<u>Message ID : CFG1777E</u> .....	34
<u>Message ID : CFG1778E</u> .....	34

# Table of Contents

<b><u>Logger CFG: Errors</u></b>	
<u>Message ID : CFG1827E</u>	35
<b><u>Logger CFG: Fatal errors</u></b>	<b>36</b>
<u>Message ID : CFG1733E</u>	36
<u>Message ID : CFG1842E</u>	36
<b><u>Logger CFG: Information</u></b>	<b>38</b>
<u>Message ID : CFG0633I</u>	38
<u>Message ID : CFG0634I</u>	39
<u>Message ID : CFG1516I</u>	40
<u>Message ID : CFG1736I</u>	40
<u>Message ID : CFG1841I</u>	41
<b><u>Logger CFG: Warnings</u></b>	<b>42</b>
<u>Message ID : CFG1297W</u>	42
<b><u>Logger CGA: Errors</u></b>	<b>43</b>
<u>Message ID : CGA2614E</u>	43
<u>Message ID : CGA2617E</u>	43
<u>Message ID : CGA2618E</u>	44
<u>Message ID : CGA2619E</u>	45
<u>Message ID : CGA2620E</u>	45
<u>Message ID : CGA2621E</u>	46
<u>Message ID : CGA2624E</u>	47
<u>Message ID : CGA2625E</u>	48
<u>Message ID : CGA2626E</u>	48

# Table of Contents

## Logger CGA: Errors

<u>Message ID : CGA2627E</u> .....	49
<u>Message ID : CGA2628E</u> .....	50
<u>Message ID : CGA2629E</u> .....	51
<u>Message ID : CGA2634E</u> .....	52
<u>Message ID : CGA2635E</u> .....	53
<u>Message ID : CGA2636E</u> .....	54
<u>Message ID : CGA2637E</u> .....	55
<u>Message ID : CGA2638E</u> .....	55
<u>Message ID : CGA2639E</u> .....	56
<u>Message ID : CGA2645E</u> .....	57
<u>Message ID : CGA2648E</u> .....	58
<u>Message ID : CGA2649E</u> .....	59
<u>Message ID : CGA2650E</u> .....	60
<u>Message ID : CGA2651E</u> .....	61
<u>Message ID : CGA2652E</u> .....	62
<u>Message ID : CGA2653E</u> .....	63
<u>Message ID : CGA2654E</u> .....	64
<u>Message ID : CGA2655E</u> .....	65
<u>Message ID : CGA2656E</u> .....	66
<u>Message ID : CGA2657E</u> .....	67
<u>Message ID : CGA2658E</u> .....	68
<u>Message ID : CGA2659E</u> .....	69
<u>Message ID : CGA3003E</u> .....	70
<u>Message ID : CGA3004E</u> .....	71
<u>Message ID : CGA3007E</u> .....	71
<u>Message ID : CGA3008E</u> .....	72

# Table of Contents

## Logger CGA: Errors

<u>Message ID : CGA3009E</u> .....	73
<u>Message ID : CGA3010E</u> .....	74
<u>Message ID : CGA3011E</u> .....	75
<u>Message ID : CGA3012E</u> .....	76
<u>Message ID : CGA3013E</u> .....	76
<u>Message ID : CGA3014E</u> .....	77
<u>Message ID : CGA3015E</u> .....	78
<u>Message ID : CGA3016E</u> .....	79
<u>Message ID : CGA3017E</u> .....	79
<u>Message ID : CGA3018E</u> .....	80
<u>Message ID : CGA3021E</u> .....	81
<u>Message ID : CGA3022E</u> .....	82
<u>Message ID : CGA3023E</u> .....	83
<u>Message ID : CGA3024E</u> .....	83
<u>Message ID : CGA3059E</u> .....	84
<u>Message ID : CGA3060E</u> .....	85
<u>Message ID : CGA3061E</u> .....	86
<u>Message ID : CGA3062E</u> .....	87
<u>Message ID : CGA3063E</u> .....	88
<u>Message ID : CGA3064E</u> .....	89
<u>Message ID : CGA3065E</u> .....	90
<u>Message ID : CGA3066E</u> .....	91
<u>Message ID : CGA3067E</u> .....	92
<u>Message ID : CGA3068E</u> .....	92
<u>Message ID : CGA3069E</u> .....	93
<u>Message ID : CGA3070E</u> .....	94



# Table of Contents

## Logger CGA: Errors

<u>Message ID : CGA3071E</u> .....	95
<u>Message ID : CGA3072E</u> .....	96
<u>Message ID : CGA3073E</u> .....	97
<u>Message ID : CGA3074E</u> .....	98
<u>Message ID : CGA3075E</u> .....	99
<u>Message ID : CGA3076E</u> .....	99
<u>Message ID : CGA3077E</u> .....	100
<u>Message ID : CGA3078E</u> .....	101
<u>Message ID : CGA3079E</u> .....	102
<u>Message ID : CGA3080E</u> .....	103
<u>Message ID : CGA3081E</u> .....	104
<u>Message ID : CGA3082E</u> .....	105
<u>Message ID : CGA3083E</u> .....	106
<u>Message ID : CGA3084E</u> .....	106
<u>Message ID : CGA3085E</u> .....	107
<u>Message ID : CGA3086E</u> .....	108
<u>Message ID : CGA3087E</u> .....	109
<u>Message ID : CGA3088E</u> .....	110
<u>Message ID : CGA3089E</u> .....	111
<u>Message ID : CGA3090E</u> .....	112
<u>Message ID : CGA3091E</u> .....	113
<u>Message ID : CGA3092E</u> .....	114
<u>Message ID : CGA3093E</u> .....	115
<u>Message ID : CGA3094E</u> .....	116
<u>Message ID : CGA3095E</u> .....	117
<u>Message ID : CGA3096E</u> .....	117

# Table of Contents

## Logger CGA: Errors

<u>Message ID : CGA3097E</u> .....	118
<u>Message ID : CGA3098E</u> .....	119
<u>Message ID : CGA3099E</u> .....	120
<u>Message ID : CGA3100E</u> .....	121
<u>Message ID : CGA3101E</u> .....	122
<u>Message ID : CGA3102E</u> .....	122
<u>Message ID : CGA3103E</u> .....	123
<u>Message ID : CGA3109E</u> .....	124
<u>Message ID : CGA3110E</u> .....	125
<u>Message ID : CGA3111E</u> .....	126
<u>Message ID : CGA3112E</u> .....	127
<u>Message ID : CGA3113E</u> .....	128
<u>Message ID : CGA3114E</u> .....	129
<u>Message ID : CGA3115E</u> .....	130
<u>Message ID : CGA3116E</u> .....	131
<u>Message ID : CGA3117E</u> .....	131
<u>Message ID : CGA3118E</u> .....	132
<u>Message ID : CGA3119E</u> .....	133
<u>Message ID : CGA3120E</u> .....	134
<u>Message ID : CGA3121E</u> .....	135
<u>Message ID : CGA3122E</u> .....	136
<u>Message ID : CGA3123E</u> .....	137
<u>Message ID : CGA3124E</u> .....	138
<u>Message ID : CGA3125E</u> .....	139
<u>Message ID : CGA3126E</u> .....	140
<u>Message ID : CGA3127E</u> .....	141

# Table of Contents

## Logger CGA: Errors

<u>Message ID : CGA3128E</u> .....	142
<u>Message ID : CGA3129E</u> .....	143
<u>Message ID : CGA3130E</u> .....	144
<u>Message ID : CGA3131E</u> .....	144
<u>Message ID : CGA3132E</u> .....	145
<u>Message ID : CGA3133E</u> .....	146
<u>Message ID : CGA3134E</u> .....	147
<u>Message ID : CGA3135E</u> .....	148
<u>Message ID : CGA3136E</u> .....	149
<u>Message ID : CGA3137E</u> .....	150
<u>Message ID : CGA3138E</u> .....	151
<u>Message ID : CGA3139E</u> .....	152
<u>Message ID : CGA3140E</u> .....	153
<u>Message ID : CGA3141E</u> .....	154
<u>Message ID : CGA3142E</u> .....	155
<u>Message ID : CGA3143E</u> .....	156
<u>Message ID : CGA3144E</u> .....	157
<u>Message ID : CGA3145E</u> .....	157
<u>Message ID : CGA3146E</u> .....	158
<u>Message ID : CGA3147E</u> .....	159
<u>Message ID : CGA3148E</u> .....	160
<u>Message ID : CGA3149E</u> .....	161
<u>Message ID : CGA3150E</u> .....	162
<u>Message ID : CGA3151E</u> .....	163
<u>Message ID : CGA3152E</u> .....	164
<u>Message ID : CGA3153E</u> .....	165

# Table of Contents

## Logger CGA: Errors

<u>Message ID : CGA3154E</u> .....	166
<u>Message ID : CGA3155E</u> .....	167
<u>Message ID : CGA3156E</u> .....	168
<u>Message ID : CGA3157E</u> .....	169
<u>Message ID : CGA3158E</u> .....	170
<u>Message ID : CGA3159E</u> .....	170
<u>Message ID : CGA3160E</u> .....	171
<u>Message ID : CGA3161E</u> .....	172
<u>Message ID : CGA3162E</u> .....	173
<u>Message ID : CGA3163E</u> .....	174
<u>Message ID : CGA3164E</u> .....	175
<u>Message ID : CGA3165E</u> .....	176
<u>Message ID : CGA3166E</u> .....	177
<u>Message ID : CGA3167E</u> .....	178
<u>Message ID : CGA3168E</u> .....	179
<u>Message ID : CGA3169E</u> .....	180
<u>Message ID : CGA3170E</u> .....	181
<u>Message ID : CGA3171E</u> .....	182
<u>Message ID : CGA3172E</u> .....	183
<u>Message ID : CGA3173E</u> .....	183
<u>Message ID : CGA3174E</u> .....	184
<u>Message ID : CGA3175E</u> .....	185
<u>Message ID : CGA3176E</u> .....	186
<u>Message ID : CGA3177E</u> .....	187
<u>Message ID : CGA3178E</u> .....	188
<u>Message ID : CGA3179E</u> .....	189

# Table of Contents

## Logger CGA: Errors

<u>Message ID : CGA3180E</u> .....	190
<u>Message ID : CGA3181E</u> .....	191
<u>Message ID : CGA3182E</u> .....	192
<u>Message ID : CGA3184E</u> .....	193
<u>Message ID : CGA3185E</u> .....	194
<u>Message ID : CGA3187E</u> .....	194
<u>Message ID : CGA3188E</u> .....	195
<u>Message ID : CGA3189E</u> .....	196
<u>Message ID : CGA3190E</u> .....	197
<u>Message ID : CGA3191E</u> .....	198
<u>Message ID : CGA3192E</u> .....	199
<u>Message ID : CGA3206E</u> .....	200
<u>Message ID : CGA3212E</u> .....	201
<u>Message ID : CGA3218E</u> .....	201
<u>Message ID : CGA3220E</u> .....	202
<u>Message ID : CGA3222E</u> .....	203
<u>Message ID : CGA3223E</u> .....	204
<u>Message ID : CGA3227E</u> .....	205
<u>Message ID : CGA3228E</u> .....	206
<u>Message ID : CGA3229E</u> .....	207
<u>Message ID : CGA3230E</u> .....	208
<u>Message ID : CGA3232E</u> .....	209
<u>Message ID : CGA3233E</u> .....	210
<u>Message ID : CGA3235E</u> .....	211
<u>Message ID : CGA3236E</u> .....	212
<u>Message ID : CGA3237E</u> .....	213

# Table of Contents

## Logger CGA: Errors

<u>Message ID : CGA3238E</u> .....	214
<u>Message ID : CGA3239E</u> .....	215
<u>Message ID : CGA3252E</u> .....	216
<u>Message ID : CGA3256E</u> .....	217
<u>Message ID : CGA3272E</u> .....	217
<u>Message ID : CGA3274E</u> .....	218
<u>Message ID : CGA3275E</u> .....	219
<u>Message ID : CGA3278E</u> .....	220
<u>Message ID : CGA3279E</u> .....	221
<u>Message ID : CGA3280E</u> .....	222
<u>Message ID : CGA3282E</u> .....	223
<u>Message ID : CGA3284E</u> .....	224
<u>Message ID : CGA3289E</u> .....	225
<u>Message ID : CGA3292E</u> .....	226
<u>Message ID : CGA3295E</u> .....	226
<u>Message ID : CGA3298E</u> .....	227
<u>Message ID : CGA3301E</u> .....	228
<u>Message ID : CGA3304E</u> .....	229
<u>Message ID : CGA3306E</u> .....	230
<u>Message ID : CGA3307E</u> .....	231
<u>Message ID : CGA3308E</u> .....	232
<u>Message ID : CGA3309E</u> .....	233
<u>Message ID : CGA3310E</u> .....	234

# Table of Contents

<b>Logger CGA: Information</b> .....	<b>235</b>
<u>Message ID : CGA2622I</u> .....	235
<u>Message ID : CGA2630I</u> .....	235
<u>Message ID : CGA2631I</u> .....	236
<u>Message ID : CGA2632I</u> .....	237
<u>Message ID : CGA2633I</u> .....	237
<u>Message ID : CGA2640I</u> .....	238
<u>Message ID : CGA2641I</u> .....	239
<u>Message ID : CGA2642I</u> .....	239
<u>Message ID : CGA2643I</u> .....	240
<u>Message ID : CGA2644I</u> .....	241
<u>Message ID : CGA2646I</u> .....	241
<u>Message ID : CGA2647I</u> .....	242
<u>Message ID : CGA2656I</u> .....	243
<u>Message ID : CGA2657I</u> .....	244
<u>Message ID : CGA3001I</u> .....	245
<u>Message ID : CGA3005I</u> .....	246
<u>Message ID : CGA3006I</u> .....	246
<u>Message ID : CGA3019I</u> .....	247
<u>Message ID : CGA3020I</u> .....	248
<u>Message ID : CGA3058I</u> .....	249
<u>Message ID : CGA3105I</u> .....	250
<u>Message ID : CGA3183I</u> .....	251
<u>Message ID : CGA3186I</u> .....	252
<u>Message ID : CGA3193I</u> .....	253
<u>Message ID : CGA3194I</u> .....	254
<u>Message ID : CGA3195I</u> .....	254

# Table of Contents

## **Logger CGA: Information**

<u>Message ID : CGA3196I</u> .....	255
<u>Message ID : CGA3197I</u> .....	256
<u>Message ID : CGA3198I</u> .....	257
<u>Message ID : CGA3199I</u> .....	258
<u>Message ID : CGA3200I</u> .....	259
<u>Message ID : CGA3201I</u> .....	260
<u>Message ID : CGA3202I</u> .....	261
<u>Message ID : CGA3203I</u> .....	262
<u>Message ID : CGA3204I</u> .....	263
<u>Message ID : CGA3205I</u> .....	264
<u>Message ID : CGA3207I</u> .....	264
<u>Message ID : CGA3208I</u> .....	265
<u>Message ID : CGA3209I</u> .....	266
<u>Message ID : CGA3210I</u> .....	267
<u>Message ID : CGA3211I</u> .....	268
<u>Message ID : CGA3213I</u> .....	269
<u>Message ID : CGA3214I</u> .....	270
<u>Message ID : CGA3215I</u> .....	270
<u>Message ID : CGA3216I</u> .....	271
<u>Message ID : CGA3217I</u> .....	272
<u>Message ID : CGA3219I</u> .....	273
<u>Message ID : CGA3221I</u> .....	274
<u>Message ID : CGA3224I</u> .....	275
<u>Message ID : CGA3225I</u> .....	276
<u>Message ID : CGA3226I</u> .....	277
<u>Message ID : CGA3240I</u> .....	278



# Table of Contents

## **Logger CGA: Information**

<u>Message ID : CGA3241I</u> .....	279
<u>Message ID : CGA3242I</u> .....	280
<u>Message ID : CGA3244I</u> .....	281
<u>Message ID : CGA3245I</u> .....	281
<u>Message ID : CGA3246I</u> .....	282
<u>Message ID : CGA3247I</u> .....	283
<u>Message ID : CGA3248I</u> .....	284
<u>Message ID : CGA3257I</u> .....	285
<u>Message ID : CGA3258I</u> .....	286
<u>Message ID : CGA3269I</u> .....	287
<u>Message ID : CGA3270I</u> .....	288
<u>Message ID : CGA3271I</u> .....	289
<u>Message ID : CGA3273I</u> .....	289
<u>Message ID : CGA3281I</u> .....	290
<u>Message ID : CGA3283I</u> .....	291
<u>Message ID : CGA3287I</u> .....	292
<u>Message ID : CGA3288I</u> .....	293
<u>Message ID : CGA3290I</u> .....	294
<u>Message ID : CGA3291I</u> .....	295
<u>Message ID : CGA3293I</u> .....	296
<u>Message ID : CGA3294I</u> .....	297
<u>Message ID : CGA3296I</u> .....	298
<u>Message ID : CGA3297I</u> .....	299
<u>Message ID : CGA3299I</u> .....	299
<u>Message ID : CGA3300I</u> .....	300
<u>Message ID : CGA3305I</u> .....	301

# Table of Contents

<b><u>Logger CGA: Warnings</u></b> .....	<b>303</b>
<u>Message ID : CGA2615W</u> .....	303
<u>Message ID : CGA2616W</u> .....	303
<u>Message ID : CGA2623W</u> .....	304
<u>Message ID : CGA2901W</u> .....	305
<u>Message ID : CGA3002W</u> .....	306
<u>Message ID : CGA3104W</u> .....	307
<u>Message ID : CGA3106W</u> .....	308
<u>Message ID : CGA3107W</u> .....	309
<u>Message ID : CGA3108W</u> .....	310
<u>Message ID : CGA3231W</u> .....	310
<u>Message ID : CGA3243W</u> .....	311
<u>Message ID : CGA3265W</u> .....	312
<u>Message ID : CGA3276W</u> .....	313
<u>Message ID : CGA3285W</u> .....	314
<u>Message ID : CGA3286W</u> .....	315
<b><u>Logger CGP: Errors</u></b> .....	<b>317</b>
<u>Message ID : CGP2602E</u> .....	317
<u>Message ID : CGP2604E</u> .....	318
<u>Message ID : CGP2606E</u> .....	319
<u>Message ID : CGP2608E</u> .....	321
<u>Message ID : CGP2610E</u> .....	322
<b><u>Logger CGP: Information</u></b> .....	<b>324</b>
<u>Message ID : CGP2601I</u> .....	324
<u>Message ID : CGP2603I</u> .....	325

# Table of Contents

## **Logger CGP: Information**

<u>Message ID : CGP2605I</u> .....	326
<u>Message ID : CGP2607I</u> .....	328
<u>Message ID : CGP2609I</u> .....	329

## **Logger CGS: Errors**.....**331**

<u>Message ID : CGS2613E</u> .....	331
<u>Message ID : CGS3025E</u> .....	331
<u>Message ID : CGS3026E</u> .....	332
<u>Message ID : CGS3027E</u> .....	333
<u>Message ID : CGS3028E</u> .....	334
<u>Message ID : CGS3031E</u> .....	335
<u>Message ID : CGS3032E</u> .....	336
<u>Message ID : CGS3033E</u> .....	337
<u>Message ID : CGS3034E</u> .....	338
<u>Message ID : CGS3035E</u> .....	339
<u>Message ID : CGS3038E</u> .....	340
<u>Message ID : CGS3039E</u> .....	340
<u>Message ID : CGS3042E</u> .....	341
<u>Message ID : CGS3043E</u> .....	342
<u>Message ID : CGS3044E</u> .....	343
<u>Message ID : CGS3045E</u> .....	344
<u>Message ID : CGS3047E</u> .....	345
<u>Message ID : CGS3048E</u> .....	346
<u>Message ID : CGS3049E</u> .....	347
<u>Message ID : CGS3050E</u> .....	347
<u>Message ID : CGS3051E</u> .....	348

# Table of Contents

## Logger CGS: Errors

<u>Message ID : CGS3052E</u> .....	349
<u>Message ID : CGS3053E</u> .....	350
<u>Message ID : CGS3054E</u> .....	351
<u>Message ID : CGS3055E</u> .....	352
<u>Message ID : CGS3057E</u> .....	353
<u>Message ID : CGS3234E</u> .....	354
<u>Message ID : CGS3253E</u> .....	355
<u>Message ID : CGS3259E</u> .....	356
<u>Message ID : CGS3260E</u> .....	357
<u>Message ID : CGS3261E</u> .....	357
<u>Message ID : CGS3262E</u> .....	358
<u>Message ID : CGS3263E</u> .....	359
<u>Message ID : CGS3264E</u> .....	360
<u>Message ID : CGS3266E</u> .....	361
<u>Message ID : CGS3304E</u> .....	362
<u>Message ID : CGS3305E</u> .....	363
<u>Message ID : CGS3306E</u> .....	364
<u>Message ID : CGS3307E</u> .....	365
<u>Message ID : CGS3308E</u> .....	366
<u>Message ID : CGS3309E</u> .....	366
<u>Message ID : CGS3311E</u> .....	367
<u>Message ID : CGS3312E</u> .....	368
<u>Message ID : CGS3313E</u> .....	369
<u>Message ID : CGS3314E</u> .....	370
<u>Message ID : CGS3315E</u> .....	371
<u>Message ID : CGS3316E</u> .....	372

# Table of Contents

## **Logger CGS: Errors**

<u>Message ID : CGS3317E</u> .....	373
------------------------------------	-----

## **Logger CGS: Information**.....**374**

<u>Message ID : CGS3029I</u> .....	374
<u>Message ID : CGS3030I</u> .....	375
<u>Message ID : CGS3036I</u> .....	375
<u>Message ID : CGS3037I</u> .....	376
<u>Message ID : CGS3040I</u> .....	377
<u>Message ID : CGS3041I</u> .....	378
<u>Message ID : CGS3046I</u> .....	379
<u>Message ID : CGS3056I</u> .....	380
<u>Message ID : CGS3249I</u> .....	381
<u>Message ID : CGS3250I</u> .....	381
<u>Message ID : CGS3251I</u> .....	382
<u>Message ID : CGS3254I</u> .....	383
<u>Message ID : CGS3255I</u> .....	384
<u>Message ID : CGS3277I</u> .....	385

## **Logger CGS: Warnings**.....**387**

<u>Message ID : CGS3267W</u> .....	387
<u>Message ID : CGS3268W</u> .....	388
<u>Message ID : CGS3302W</u> .....	389
<u>Message ID : CGS3303W</u> .....	390
<u>Message ID : CGS3310W</u> .....	391

# Table of Contents

<b><u>Logger CMG: Information</u></b> .....	<b>392</b>
<u>Message ID : CMG1150I</u> .....	392
<b><u>Logger CMG: Warnings</u></b> .....	<b>393</b>
<u>Message ID : CMG1100W</u> .....	393
<u>Message ID : CMG1101W</u> .....	394
<u>Message ID : CMG1120W</u> .....	395
<u>Message ID : CMG1121W</u> .....	396
<b><u>Logger COM: Errors</u></b> .....	<b>397</b>
<u>Message ID : COM0002E</u> .....	397
<u>Message ID : COM0003E</u> .....	397
<u>Message ID : COM0005E</u> .....	398
<u>Message ID : COM0174E</u> .....	399
<u>Message ID : COM0175E</u> .....	399
<u>Message ID : COM0271E</u> .....	400
<u>Message ID : COM0272E</u> .....	401
<u>Message ID : COM0275E</u> .....	401
<u>Message ID : COM0300E</u> .....	402
<u>Message ID : COM0303E</u> .....	403
<u>Message ID : COM0312E</u> .....	404
<u>Message ID : COM0313E</u> .....	404
<u>Message ID : COM0429E</u> .....	405
<u>Message ID : COM0430E</u> .....	406
<u>Message ID : COM0431E</u> .....	407
<u>Message ID : COM0432E</u> .....	407
<u>Message ID : COM0433E</u> .....	408

# Table of Contents

## Logger COM: Errors

<u>Message ID : COM0434E</u> .....	409
<u>Message ID : COM0435E</u> .....	409
<u>Message ID : COM0436E</u> .....	410
<u>Message ID : COM0506E</u> .....	411
<u>Message ID : COM0507E</u> .....	412
<u>Message ID : COM0508E</u> .....	412
<u>Message ID : COM0509E</u> .....	413
<u>Message ID : COM0510E</u> .....	414
<u>Message ID : COM0511E</u> .....	414
<u>Message ID : COM0512E</u> .....	415
<u>Message ID : COM0513E</u> .....	416
<u>Message ID : COM0514E</u> .....	416
<u>Message ID : COM0515E</u> .....	417
<u>Message ID : COM0516E</u> .....	418
<u>Message ID : COM0536E</u> .....	418
<u>Message ID : COM0537E</u> .....	419
<u>Message ID : COM0539E</u> .....	420
<u>Message ID : COM0540E</u> .....	421
<u>Message ID : COM0541E</u> .....	421
<u>Message ID : COM0542E</u> .....	422
<u>Message ID : COM0543E</u> .....	423
<u>Message ID : COM0555E</u> .....	423
<u>Message ID : COM0556E</u> .....	424
<u>Message ID : COM0557E</u> .....	425
<u>Message ID : COM0558E</u> .....	425
<u>Message ID : COM0588E</u> .....	426

# Table of Contents

## Logger COM: Errors

<u>Message ID : COM0589E</u> .....	427
<u>Message ID : COM0590E</u> .....	427
<u>Message ID : COM0594E</u> .....	428
<u>Message ID : COM0595E</u> .....	429
<u>Message ID : COM0600E</u> .....	430
<u>Message ID : COM0601E</u> .....	431
<u>Message ID : COM0602E</u> .....	431
<u>Message ID : COM0603E</u> .....	432
<u>Message ID : COM0605E</u> .....	433
<u>Message ID : COM0609E</u> .....	434
<u>Message ID : COM0613E</u> .....	435
<u>Message ID : COM0619E</u> .....	435
<u>Message ID : COM0620E</u> .....	436
<u>Message ID : COM0621E</u> .....	437
<u>Message ID : COM0622E</u> .....	437
<u>Message ID : COM0623E</u> .....	438
<u>Message ID : COM0627E</u> .....	439
<u>Message ID : COM0628E</u> .....	439
<u>Message ID : COM0650E</u> .....	440
<u>Message ID : COM0651E</u> .....	441
<u>Message ID : COM0652E</u> .....	441
<u>Message ID : COM0653E</u> .....	442
<u>Message ID : COM0660E</u> .....	443
<u>Message ID : COM0661E</u> .....	444
<u>Message ID : COM0712E</u> .....	445
<u>Message ID : COM0713E</u> .....	446



# Table of Contents

## Logger COM: Errors

<u>Message ID : COM0759E</u> .....	447
<u>Message ID : COM0772E</u> .....	448
<u>Message ID : COM0805E</u> .....	448
<u>Message ID : COM0900E</u> .....	449
<u>Message ID : COM0901E</u> .....	450
<u>Message ID : COM1257E</u> .....	450
<u>Message ID : COM1263E</u> .....	451
<u>Message ID : COM1264E</u> .....	452
<u>Message ID : COM1285E</u> .....	452
<u>Message ID : COM1306E</u> .....	453
<u>Message ID : COM1307E</u> .....	454
<u>Message ID : COM1308E</u> .....	454
<u>Message ID : COM1310E</u> .....	455
<u>Message ID : COM1315E</u> .....	456
<u>Message ID : COM1321E</u> .....	456
<u>Message ID : COM1322E</u> .....	457
<u>Message ID : COM1349E</u> .....	458
<u>Message ID : COM1350E</u> .....	458
<u>Message ID : COM1367E</u> .....	459
<u>Message ID : COM1400E</u> .....	460
<u>Message ID : COM1401E</u> .....	460
<u>Message ID : COM1402E</u> .....	461
<u>Message ID : COM1403E</u> .....	462
<u>Message ID : COM1410E</u> .....	462
<u>Message ID : COM1669E</u> .....	463
<u>Message ID : COM1692E</u> .....	464

# Table of Contents

## **Logger COM: Errors**

<u>Message ID : COM1740E</u> .....	464
<u>Message ID : COM1741E</u> .....	465
<u>Message ID : COM1744E</u> .....	466
<u>Message ID : COM4547E</u> .....	466
<u>Message ID : COM4631E</u> .....	467
<u>Message ID : COM4638E</u> .....	468
<u>Message ID : COM4644E</u> .....	469

## **Logger COM: Fatal errors.....470**

<u>Message ID : COM0004F</u> .....	470
<u>Message ID : COM4503F</u> .....	470
<u>Message ID : COM4506F</u> .....	471
<u>Message ID : COM4511F</u> .....	472
<u>Message ID : COM4512F</u> .....	473
<u>Message ID : COM4513F</u> .....	474
<u>Message ID : COM4514F</u> .....	475
<u>Message ID : COM4515F</u> .....	475
<u>Message ID : COM4521F</u> .....	476
<u>Message ID : COM4523F</u> .....	477
<u>Message ID : COM4527F</u> .....	478
<u>Message ID : COM4529F</u> .....	479
<u>Message ID : COM4531F</u> .....	480
<u>Message ID : COM4533F</u> .....	480
<u>Message ID : COM4534F</u> .....	481
<u>Message ID : COM4538F</u> .....	482
<u>Message ID : COM4542F</u> .....	483

# Table of Contents

## **Logger COM: Fatal errors**

<u>Message ID : COM4548F</u> .....	484
<u>Message ID : COM4551F</u> .....	485
<u>Message ID : COM4552F</u> .....	485
<u>Message ID : COM4554F</u> .....	486
<u>Message ID : COM4558F</u> .....	487
<u>Message ID : COM4562F</u> .....	488
<u>Message ID : COM4563F</u> .....	489
<u>Message ID : COM4567F</u> .....	490
<u>Message ID : COM4569F</u> .....	491
<u>Message ID : COM4571F</u> .....	492
<u>Message ID : COM4577F</u> .....	493
<u>Message ID : COM4578F</u> .....	493
<u>Message ID : COM4579F</u> .....	494
<u>Message ID : COM4583F</u> .....	495
<u>Message ID : COM4584F</u> .....	496
<u>Message ID : COM4586F</u> .....	497
<u>Message ID : COM4587F</u> .....	497
<u>Message ID : COM4588F</u> .....	498
<u>Message ID : COM4592F</u> .....	499
<u>Message ID : COM4599F</u> .....	500
<u>Message ID : COM4600F</u> .....	501
<u>Message ID : COM4603F</u> .....	502
<u>Message ID : COM4604F</u> .....	503
<u>Message ID : COM4628F</u> .....	504
<u>Message ID : COM4629F</u> .....	505
<u>Message ID : COM4630F</u> .....	506

# Table of Contents

## **Logger COM: Fatal errors**

<u>Message ID : COM4637F</u> .....	507
------------------------------------	-----

## **Logger COM: Information**..... **509**

<u>Message ID : COM0006I</u> .....	509
<u>Message ID : COM0007I</u> .....	510
<u>Message ID : COM0008I</u> .....	511
<u>Message ID : COM0009I</u> .....	512
<u>Message ID : COM0010I</u> .....	513
<u>Message ID : COM0011I</u> .....	514
<u>Message ID : COM0012I</u> .....	515
<u>Message ID : COM0013I</u> .....	516
<u>Message ID : COM0014I</u> .....	517
<u>Message ID : COM0015I</u> .....	518
<u>Message ID : COM0016I</u> .....	519
<u>Message ID : COM0017I</u> .....	519
<u>Message ID : COM0018I</u> .....	520
<u>Message ID : COM0019I</u> .....	521
<u>Message ID : COM0020I</u> .....	522
<u>Message ID : COM0021I</u> .....	522
<u>Message ID : COM0022I</u> .....	523
<u>Message ID : COM0023I</u> .....	524
<u>Message ID : COM0024I</u> .....	524
<u>Message ID : COM0025I</u> .....	525
<u>Message ID : COM0173I</u> .....	526
<u>Message ID : COM0314I</u> .....	527
<u>Message ID : COM0538I</u> .....	527

# Table of Contents

## **Logger COM: Information**

<u>Message ID : COM0559I</u> .....	528
<u>Message ID : COM0572I</u> .....	529
<u>Message ID : COM0574I</u> .....	530
<u>Message ID : COM0649I</u> .....	531
<u>Message ID : COM0666I</u> .....	532
<u>Message ID : COM0707I</u> .....	533
<u>Message ID : COM0710I</u> .....	533
<u>Message ID : COM0711I</u> .....	534
<u>Message ID : COM1311I</u> .....	535
<u>Message ID : COM1312I</u> .....	536
<u>Message ID : COM1519I</u> .....	537
<u>Message ID : COM1521I</u> .....	538
<u>Message ID : COM1784I</u> .....	539
<u>Message ID : COM1813I</u> .....	539
<u>Message ID : COM1835I</u> .....	540
<u>Message ID : COM4601I</u> .....	541
<u>Message ID : COM4602I</u> .....	542
<u>Message ID : COM4626I</u> .....	543
<u>Message ID : COM4627I</u> .....	543

## **Logger COM: Warnings**..... **545**

<u>Message ID : COM0591W</u> .....	545
<u>Message ID : COM0607W</u> .....	546
<u>Message ID : COM0612W</u> .....	546
<u>Message ID : COM0614W</u> .....	547
<u>Message ID : COM0617W</u> .....	548

# Table of Contents

## **Logger COM: Warnings**

<u>Message ID : COM0618W</u> .....	548
<u>Message ID : COM0667W</u> .....	549
<u>Message ID : COM1251W</u> .....	550
<u>Message ID : COM1314W</u> .....	550
<u>Message ID : COM1323W</u> .....	551
<u>Message ID : COM1337W</u> .....	552
<u>Message ID : COM4605W</u> .....	552
<u>Message ID : COM4632W</u> .....	553
<u>Message ID : COM4633W</u> .....	554
<u>Message ID : COM4634W</u> .....	556
<u>Message ID : COM4635W</u> .....	556

## **Logger CXM: Errors**..... **559**

<u>Message ID : CXM0654E</u> .....	559
<u>Message ID : CXM0657E</u> .....	560
<u>Message ID : CXM0658E</u> .....	560
<u>Message ID : CXM0659E</u> .....	561
<u>Message ID : CXM0770E</u> .....	562
<u>Message ID : CXM1354E</u> .....	563
<u>Message ID : CXM1355E</u> .....	564
<u>Message ID : CXM1356E</u> .....	565
<u>Message ID : CXM1357E</u> .....	565
<u>Message ID : CXM1358E</u> .....	566
<u>Message ID : CXM1359E</u> .....	567
<u>Message ID : CXM1360E</u> .....	567
<u>Message ID : CXM1361E</u> .....	568

# Table of Contents

## **Logger CXM: Errors**

<u>Message ID : CXM1391E</u> .....	569
<u>Message ID : CXM1392E</u> .....	569
<u>Message ID : CXM1393E</u> .....	570
<u>Message ID : CXM1693E</u> .....	571

## **Logger CXM: Information**..... **572**

<u>Message ID : CXM0221I</u> .....	572
<u>Message ID : CXM0224I</u> .....	573
<u>Message ID : CXM0225I</u> .....	573
<u>Message ID : CXM0646I</u> .....	574
<u>Message ID : CXM0647I</u> .....	575
<u>Message ID : CXM0648I</u> .....	576
<u>Message ID : CXM0655I</u> .....	577
<u>Message ID : CXM0656I</u> .....	578
<u>Message ID : CXM0659I</u> .....	579
<u>Message ID : CXM0660I</u> .....	580
<u>Message ID : CXM0661I</u> .....	581
<u>Message ID : CXM0662I</u> .....	582
<u>Message ID : CXM0771I</u> .....	583
<u>Message ID : CXM1340I</u> .....	584
<u>Message ID : CXM1341I</u> .....	585
<u>Message ID : CXM1342I</u> .....	586
<u>Message ID : CXM1344I</u> .....	587
<u>Message ID : CXM1345I</u> .....	588
<u>Message ID : CXM1346I</u> .....	589
<u>Message ID : CXM1347I</u> .....	590

# Table of Contents

## **Logger CXM: Information**

<u>Message ID : CXM1624I</u> .....	590
<u>Message ID : CXM1732I</u> .....	591
<u>Message ID : CXM1748I</u> .....	592

## **Logger CXM: Warnings**..... **594**

<u>Message ID : CXM0222W</u> .....	594
<u>Message ID : CXM0223W</u> .....	595
<u>Message ID : CXM0226W</u> .....	595
<u>Message ID : CXM0227W</u> .....	596
<u>Message ID : CXM0289W</u> .....	597
<u>Message ID : CXM0802W</u> .....	598
<u>Message ID : CXM1250W</u> .....	599
<u>Message ID : CXM1294W</u> .....	600
<u>Message ID : CXM1343W</u> .....	601
<u>Message ID : CXM1363W</u> .....	601
<u>Message ID : CXM1423W</u> .....	602
<u>Message ID : CXM1520W</u> .....	603
<u>Message ID : CXM1749W</u> .....	604

## **Logger DA0: Errors**..... **606**

<u>Message ID : DA001322E</u> .....	606
<u>Message ID : DA001323E</u> .....	606

## **Logger DAO: Errors**..... **608**

<u>Message ID : DAO0038E</u> .....	608
<u>Message ID : DAO0039E</u> .....	608



# Table of Contents

## Logger DAO: Errors

<u>Message ID : DAO0040E</u> .....	609
<u>Message ID : DAO0041E</u> .....	610
<u>Message ID : DAO0042E</u> .....	610
<u>Message ID : DAO0043E</u> .....	611
<u>Message ID : DAO0044E</u> .....	612
<u>Message ID : DAO0049E</u> .....	612
<u>Message ID : DAO0050E</u> .....	613
<u>Message ID : DAO0051E</u> .....	614
<u>Message ID : DAO0056E</u> .....	614
<u>Message ID : DAO0057E</u> .....	615
<u>Message ID : DAO0058E</u> .....	616
<u>Message ID : DAO0059E</u> .....	616
<u>Message ID : DAO0060E</u> .....	617
<u>Message ID : DAO0066E</u> .....	618
<u>Message ID : DAO0067E</u> .....	618
<u>Message ID : DAO0069E</u> .....	619
<u>Message ID : DAO0070E</u> .....	620
<u>Message ID : DAO0081E</u> .....	620
<u>Message ID : DAO0087E</u> .....	621
<u>Message ID : DAO0088E</u> .....	622
<u>Message ID : DAO01299E</u> .....	622
<u>Message ID : DAO01320E</u> .....	623
<u>Message ID : DAO01328E</u> .....	624
<u>Message ID : DAO01329E</u> .....	624
<u>Message ID : DAO01335E</u> .....	625
<u>Message ID : DAO01336E</u> .....	626

# Table of Contents

## Logger DAO: Errors

<u>Message ID : DAO01342E</u> .....	626
<u>Message ID : DAO01343E</u> .....	627
<u>Message ID : DAO01344E</u> .....	628
<u>Message ID : DAO01346E</u> .....	628
<u>Message ID : DAO01347E</u> .....	629
<u>Message ID : DAO01348E</u> .....	630
<u>Message ID : DAO01349E</u> .....	630
<u>Message ID : DAO01350E</u> .....	631
<u>Message ID : DAO01351E</u> .....	632
<u>Message ID : DAO01384E</u> .....	632
<u>Message ID : DAO01392E</u> .....	633
<u>Message ID : DAO01400E</u> .....	634
<u>Message ID : DAO01518E</u> .....	634
<u>Message ID : DAO01658E</u> .....	635
<u>Message ID : DAO01659E</u> .....	636
<u>Message ID : DAO0226E</u> .....	636
<u>Message ID : DAO0242E</u> .....	637
<u>Message ID : DAO0246E</u> .....	638
<u>Message ID : DAO0247E</u> .....	638
<u>Message ID : DAO0249E</u> .....	639
<u>Message ID : DAO0250E</u> .....	640
<u>Message ID : DAO0268E</u> .....	640
<u>Message ID : DAO0291E</u> .....	641
<u>Message ID : DAO0297E</u> .....	642
<u>Message ID : DAO0304E</u> .....	643
<u>Message ID : DAO0671E</u> .....	644

# Table of Contents

## **Logger DAO: Errors**

<u>Message ID : DAO0705E</u> .....	644
<u>Message ID : DAO0706E</u> .....	645
<u>Message ID : DAO0807E</u> .....	646
<u>Message ID : DAO0855E</u> .....	646
<u>Message ID : DAO1632E</u> .....	647
<u>Message ID : DAO1633E</u> .....	648
<u>Message ID : DAO1634E</u> .....	648
<u>Message ID : DAO1635E</u> .....	649
<u>Message ID : DAO1636E</u> .....	650
<u>Message ID : DAO1666E</u> .....	650
<u>Message ID : DAO1718E</u> .....	651
<u>Message ID : DAO1727E</u> .....	652
<u>Message ID : DAO1750E</u> .....	652

## **Logger DAO: Information**..... **654**

<u>Message ID : DAO0045I</u> .....	654
<u>Message ID : DAO0046I</u> .....	655
<u>Message ID : DAO0047I</u> .....	656
<u>Message ID : DAO0048I</u> .....	657
<u>Message ID : DAO0049I</u> .....	658
<u>Message ID : DAO0052I</u> .....	659
<u>Message ID : DAO0053I</u> .....	660
<u>Message ID : DAO0055I</u> .....	661
<u>Message ID : DAO0061I</u> .....	662
<u>Message ID : DAO0062I</u> .....	663
<u>Message ID : DAO0063I</u> .....	664

# Table of Contents

## **Logger DAO: Information**

<u>Message ID : DAO0064I</u> .....	665
<u>Message ID : DAO0071I</u> .....	666
<u>Message ID : DAO0072I</u> .....	667
<u>Message ID : DAO0073I</u> .....	668
<u>Message ID : DAO0074I</u> .....	669
<u>Message ID : DAO0075I</u> .....	670
<u>Message ID : DAO0076I</u> .....	670
<u>Message ID : DAO0077I</u> .....	671
<u>Message ID : DAO0078I</u> .....	672
<u>Message ID : DAO0079I</u> .....	673
<u>Message ID : DAO0080I</u> .....	674
<u>Message ID : DAO0082I</u> .....	675
<u>Message ID : DAO0083I</u> .....	676
<u>Message ID : DAO0084I</u> .....	676
<u>Message ID : DAO0085I</u> .....	677
<u>Message ID : DAO0086I</u> .....	678
<u>Message ID : DAO0089I</u> .....	679
<u>Message ID : DAO0090I</u> .....	680
<u>Message ID : DAO0091I</u> .....	681
<u>Message ID : DAO0092I</u> .....	682
<u>Message ID : DAO0093I</u> .....	683
<u>Message ID : DAO01286I</u> .....	683
<u>Message ID : DAO01287I</u> .....	684
<u>Message ID : DAO01332I</u> .....	685
<u>Message ID : DAO01333I</u> .....	686
<u>Message ID : DAO01340I</u> .....	687

# Table of Contents

## **Logger DAO: Information**

<u>Message ID : DAO01341I</u> .....	688
<u>Message ID : DAO01345I</u> .....	689
<u>Message ID : DAO01379I</u> .....	690
<u>Message ID : DAO01380I</u> .....	691
<u>Message ID : DAO01381I</u> .....	691
<u>Message ID : DAO01382I</u> .....	692
<u>Message ID : DAO01383I</u> .....	693
<u>Message ID : DAO01384I</u> .....	693
<u>Message ID : DAO01385I</u> .....	694
<u>Message ID : DAO01386I</u> .....	695
<u>Message ID : DAO01387I</u> .....	696
<u>Message ID : DAO01388I</u> .....	696
<u>Message ID : DAO01389I</u> .....	697
<u>Message ID : DAO01509I</u> .....	698
<u>Message ID : DAO01510I</u> .....	698
<u>Message ID : DAO01519I</u> .....	699
<u>Message ID : DAO01520I</u> .....	700
<u>Message ID : DAO01542I</u> .....	701
<u>Message ID : DAO0227I</u> .....	701
<u>Message ID : DAO0228I</u> .....	702
<u>Message ID : DAO0229I</u> .....	703
<u>Message ID : DAO0230I</u> .....	704
<u>Message ID : DAO0231I</u> .....	705
<u>Message ID : DAO0232I</u> .....	706
<u>Message ID : DAO0233I</u> .....	707
<u>Message ID : DAO0234I</u> .....	708

# Table of Contents

## **Logger DAO: Information**

<u>Message ID : DAO0235I</u> .....	709
<u>Message ID : DAO0236I</u> .....	710
<u>Message ID : DAO0237I</u> .....	711
<u>Message ID : DAO0238I</u> .....	712
<u>Message ID : DAO0239I</u> .....	713
<u>Message ID : DAO0240I</u> .....	714
<u>Message ID : DAO0241I</u> .....	715
<u>Message ID : DAO0243I</u> .....	716
<u>Message ID : DAO0244I</u> .....	717
<u>Message ID : DAO0245I</u> .....	718
<u>Message ID : DAO0248I</u> .....	719
<u>Message ID : DAO0251I</u> .....	720
<u>Message ID : DAO0252I</u> .....	721
<u>Message ID : DAO0253I</u> .....	722
<u>Message ID : DAO0254I</u> .....	723
<u>Message ID : DAO0255I</u> .....	724
<u>Message ID : DAO0256I</u> .....	725
<u>Message ID : DAO0257I</u> .....	725
<u>Message ID : DAO0258I</u> .....	726
<u>Message ID : DAO0259I</u> .....	727
<u>Message ID : DAO0260I</u> .....	727
<u>Message ID : DAO0261I</u> .....	728
<u>Message ID : DAO0263I</u> .....	729
<u>Message ID : DAO0267I</u> .....	729
<u>Message ID : DAO0269I</u> .....	730
<u>Message ID : DAO0280I</u> .....	731

# Table of Contents

## **Logger DAO: Information**

<u>Message ID : DAO0281I</u> .....	732
<u>Message ID : DAO0282I</u> .....	733
<u>Message ID : DAO0305I</u> .....	734
<u>Message ID : DAO0317I</u> .....	735
<u>Message ID : DAO0401I</u> .....	736
<u>Message ID : DAO0402I</u> .....	737
<u>Message ID : DAO0404I</u> .....	738
<u>Message ID : DAO0405I</u> .....	739
<u>Message ID : DAO0406I</u> .....	740
<u>Message ID : DAO0407I</u> .....	741
<u>Message ID : DAO0408I</u> .....	742
<u>Message ID : DAO0412I</u> .....	743
<u>Message ID : DAO0413I</u> .....	744
<u>Message ID : DAO0414I</u> .....	745
<u>Message ID : DAO0415I</u> .....	746
<u>Message ID : DAO0423I</u> .....	747
<u>Message ID : DAO0424I</u> .....	748
<u>Message ID : DAO0425I</u> .....	749
<u>Message ID : DAO0426I</u> .....	750
<u>Message ID : DAO0445I</u> .....	751
<u>Message ID : DAO0446I</u> .....	752
<u>Message ID : DAO0447I</u> .....	753
<u>Message ID : DAO0449I</u> .....	754
<u>Message ID : DAO0460I</u> .....	754
<u>Message ID : DAO0461I</u> .....	755
<u>Message ID : DAO0462I</u> .....	756

# Table of Contents

## **Logger DAO: Information**

<u>Message ID : DAO0501I</u> .....	757
<u>Message ID : DAO0502I</u> .....	758
<u>Message ID : DAO0518I</u> .....	759
<u>Message ID : DAO0519I</u> .....	760
<u>Message ID : DAO0546I</u> .....	761
<u>Message ID : DAO0560I</u> .....	762
<u>Message ID : DAO0561I</u> .....	763
<u>Message ID : DAO0562I</u> .....	764
<u>Message ID : DAO0563I</u> .....	765
<u>Message ID : DAO0564I</u> .....	766
<u>Message ID : DAO0565I</u> .....	767
<u>Message ID : DAO0566I</u> .....	768
<u>Message ID : DAO0567I</u> .....	769
<u>Message ID : DAO0568I</u> .....	770
<u>Message ID : DAO0569I</u> .....	771
<u>Message ID : DAO0570I</u> .....	772
<u>Message ID : DAO0571I</u> .....	773
<u>Message ID : DAO0573I</u> .....	774
<u>Message ID : DAO0576I</u> .....	775
<u>Message ID : DAO0578I</u> .....	776
<u>Message ID : DAO0579I</u> .....	777
<u>Message ID : DAO0606I</u> .....	778
<u>Message ID : DAO0638I</u> .....	778
<u>Message ID : DAO0639I</u> .....	779
<u>Message ID : DAO0640I</u> .....	780
<u>Message ID : DAO0641I</u> .....	781



# Table of Contents

## **Logger DAO: Information**

<u>Message ID : DAO0659I</u> .....	782
<u>Message ID : DAO0672I</u> .....	783
<u>Message ID : DAO0673I</u> .....	784
<u>Message ID : DAO0674I</u> .....	785
<u>Message ID : DAO0675I</u> .....	786
<u>Message ID : DAO0676I</u> .....	787
<u>Message ID : DAO0677I</u> .....	788
<u>Message ID : DAO0678I</u> .....	790
<u>Message ID : DAO0679I</u> .....	791
<u>Message ID : DAO0680I</u> .....	792
<u>Message ID : DAO0681I</u> .....	793
<u>Message ID : DAO0682I</u> .....	794
<u>Message ID : DAO0683I</u> .....	795
<u>Message ID : DAO0684I</u> .....	796
<u>Message ID : DAO0685I</u> .....	797
<u>Message ID : DAO0697I</u> .....	798
<u>Message ID : DAO0699I</u> .....	799
<u>Message ID : DAO0700I</u> .....	800
<u>Message ID : DAO0701I</u> .....	801
<u>Message ID : DAO0715I</u> .....	802
<u>Message ID : DAO0716I</u> .....	802
<u>Message ID : DAO0720I</u> .....	803
<u>Message ID : DAO0721I</u> .....	804
<u>Message ID : DAO0722I</u> .....	805
<u>Message ID : DAO0723I</u> .....	806
<u>Message ID : DAO0724I</u> .....	807

# Table of Contents

## **Logger DAO: Information**

<u>Message ID : DAO0725I</u> .....	808
<u>Message ID : DAO0790I</u> .....	809
<u>Message ID : DAO0791I</u> .....	810
<u>Message ID : DAO0792I</u> .....	811
<u>Message ID : DAO0803I</u> .....	812
<u>Message ID : DAO0804I</u> .....	813
<u>Message ID : DAO0850I</u> .....	813
<u>Message ID : DAO1265I</u> .....	814
<u>Message ID : DAO1266I</u> .....	815
<u>Message ID : DAO1281I</u> .....	816
<u>Message ID : DAO1353I</u> .....	817
<u>Message ID : DAO1364I</u> .....	818
<u>Message ID : DAO1410I</u> .....	819
<u>Message ID : DAO1500I</u> .....	820
<u>Message ID : DAO1524I</u> .....	821
<u>Message ID : DAO1530I</u> .....	822
<u>Message ID : DAO1536I</u> .....	823
<u>Message ID : DAO1537I</u> .....	824
<u>Message ID : DAO1538I</u> .....	825
<u>Message ID : DAO1539I</u> .....	825
<u>Message ID : DAO1541I</u> .....	826
<u>Message ID : DAO1560I</u> .....	827
<u>Message ID : DAO1624I</u> .....	828
<u>Message ID : DAO1625I</u> .....	829
<u>Message ID : DAO1626I</u> .....	829
<u>Message ID : DAO1739I</u> .....	830

# Table of Contents

## **Logger DAO: Information**

<u>Message ID : DAO1774I</u> .....	831
<u>Message ID : DAO1828I</u> .....	832
<u>Message ID : DAO1832I</u> .....	833
<u>Message ID : DAO1834I</u> .....	834
<u>Message ID : DAO1837I</u> .....	835
<u>Message ID : DAO1847I</u> .....	836
<u>Message ID : DAO1848I</u> .....	837
<u>Message ID : DAO1861I</u> .....	838
<u>Message ID : DAO1862I</u> .....	839

## **Logger DAO: Warnings..... 841**

<u>Message ID : DAO01319W</u> .....	841
-------------------------------------	-----

## **Logger DGV: Errors..... 842**

<u>Message ID : DGV6001E</u> .....	842
<u>Message ID : DGV6002E</u> .....	842
<u>Message ID : DGV6003E</u> .....	843
<u>Message ID : DGV6004E</u> .....	844
<u>Message ID : DGV6005E</u> .....	845
<u>Message ID : DGV6006E</u> .....	846
<u>Message ID : DGV6007E</u> .....	847
<u>Message ID : DGV6008E</u> .....	848
<u>Message ID : DGV6009E</u> .....	848
<u>Message ID : DGV6010E</u> .....	849
<u>Message ID : DGV6011E</u> .....	850
<u>Message ID : DGV6012E</u> .....	851

# Table of Contents

<b><u>Logger DGV: Errors</u></b>	
<u>Message ID : DGV6013E</u> .....	852
<u>Message ID : DGV6014E</u> .....	853
<u>Message ID : DGV6015E</u> .....	854
<u>Message ID : DGV6016E</u> .....	854
<u>Message ID : DGV6017E</u> .....	855
<u>Message ID : DGV6018E</u> .....	856
<b><u>Logger DGV: Information</u></b> .....	<b>858</b>
<u>Message ID : DGV6019I</u> .....	858
<u>Message ID : DGV6020I</u> .....	858
<b><u>Logger DMG: Errors</u></b> .....	<b>860</b>
<u>Message ID : DMG0549E</u> .....	860
<u>Message ID : DMG0550E</u> .....	860
<u>Message ID : DMG0551E</u> .....	861
<u>Message ID : DMG0552E</u> .....	862
<u>Message ID : DMG0553E</u> .....	862
<u>Message ID : DMG0554E</u> .....	863
<b><u>Logger DMG: Information</u></b> .....	<b>865</b>
<u>Message ID : DMG0575I</u> .....	865
<b><u>Logger DXF: Debug messages</u></b> .....	<b>866</b>
<u>Message ID : DXF4308D</u> .....	866
<u>Message ID : DXF4310D</u> .....	866
<u>Message ID : DXF4311D</u> .....	867

# Table of Contents

## **Logger DXF: Debug messages**

<u>Message ID : DXF4473D</u> .....	868
<u>Message ID : DXF4475D</u> .....	868

## **Logger DXF: Errors.....870**

<u>Message ID : DXF3205E</u> .....	870
<u>Message ID : DXF3206E</u> .....	871
<u>Message ID : DXF3207E</u> .....	871
<u>Message ID : DXF3208E</u> .....	872
<u>Message ID : DXF3209E</u> .....	873
<u>Message ID : DXF3215E</u> .....	874
<u>Message ID : DXF3216E</u> .....	875
<u>Message ID : DXF3217E</u> .....	876
<u>Message ID : DXF3218E</u> .....	877
<u>Message ID : DXF3219E</u> .....	878
<u>Message ID : DXF3220E</u> .....	878
<u>Message ID : DXF3221E</u> .....	879
<u>Message ID : DXF3222E</u> .....	880
<u>Message ID : DXF3223E</u> .....	881
<u>Message ID : DXF3224E</u> .....	882
<u>Message ID : DXF3225E</u> .....	883
<u>Message ID : DXF3226E</u> .....	884
<u>Message ID : DXF3227E</u> .....	885
<u>Message ID : DXF3228E</u> .....	885
<u>Message ID : DXF3229E</u> .....	886
<u>Message ID : DXF3230E</u> .....	887
<u>Message ID : DXF3231E</u> .....	888

# Table of Contents

## **Logger DXF: Errors**

<u>Message ID : DXF3232E</u> .....	889
<u>Message ID : DXF3233E</u> .....	890
<u>Message ID : DXF3238E</u> .....	891
<u>Message ID : DXF3239E</u> .....	892
<u>Message ID : DXF3240E</u> .....	892
<u>Message ID : DXF3241E</u> .....	893
<u>Message ID : DXF3242E</u> .....	894
<u>Message ID : DXF4100E</u> .....	895
<u>Message ID : DXF4101E</u> .....	896
<u>Message ID : DXF4102E</u> .....	896
<u>Message ID : DXF4105E</u> .....	897
<u>Message ID : DXF4106E</u> .....	898
<u>Message ID : DXF4107E</u> .....	899
<u>Message ID : DXF4108E</u> .....	900
<u>Message ID : DXF4109E</u> .....	901
<u>Message ID : DXF4111E</u> .....	902
<u>Message ID : DXF4112E</u> .....	903
<u>Message ID : DXF4113E</u> .....	904
<u>Message ID : DXF4114E</u> .....	905
<u>Message ID : DXF4115E</u> .....	906
<u>Message ID : DXF4116E</u> .....	907
<u>Message ID : DXF4117E</u> .....	908
<u>Message ID : DXF4119E</u> .....	909
<u>Message ID : DXF4120E</u> .....	910
<u>Message ID : DXF4121E</u> .....	910
<u>Message ID : DXF4124E</u> .....	911

# Table of Contents

## **Logger DXF: Errors**

<u>Message ID : DXF4125E</u> .....	912
<u>Message ID : DXF4133E</u> .....	913
<u>Message ID : DXF4134E</u> .....	913
<u>Message ID : DXF4135E</u> .....	914
<u>Message ID : DXF4136E</u> .....	915
<u>Message ID : DXF4137E</u> .....	916
<u>Message ID : DXF4138E</u> .....	917
<u>Message ID : DXF4139E</u> .....	918
<u>Message ID : DXF4140E</u> .....	919
<u>Message ID : DXF4141E</u> .....	919
<u>Message ID : DXF4142E</u> .....	920
<u>Message ID : DXF4149E</u> .....	921
<u>Message ID : DXF4150E</u> .....	922
<u>Message ID : DXF4151E</u> .....	923
<u>Message ID : DXF4152E</u> .....	923
<u>Message ID : DXF4153E</u> .....	924
<u>Message ID : DXF4155E</u> .....	925
<u>Message ID : DXF4156E</u> .....	925
<u>Message ID : DXF4157E</u> .....	926
<u>Message ID : DXF4158E</u> .....	927
<u>Message ID : DXF4159E</u> .....	928
<u>Message ID : DXF4160E</u> .....	928
<u>Message ID : DXF4162E</u> .....	929
<u>Message ID : DXF4163E</u> .....	930
<u>Message ID : DXF4164E</u> .....	931
<u>Message ID : DXF4165E</u> .....	932

# Table of Contents

## **Logger DXF: Errors**

<u>Message ID : DXF4166E</u> .....	933
<u>Message ID : DXF4167E</u> .....	933
<u>Message ID : DXF4168E</u> .....	934
<u>Message ID : DXF4215E</u> .....	935
<u>Message ID : DXF4227E</u> .....	936
<u>Message ID : DXF4228E</u> .....	936
<u>Message ID : DXF4229E</u> .....	937
<u>Message ID : DXF4230E</u> .....	938
<u>Message ID : DXF4231E</u> .....	938
<u>Message ID : DXF4232E</u> .....	939
<u>Message ID : DXF4233E</u> .....	940
<u>Message ID : DXF4234E</u> .....	940
<u>Message ID : DXF4235E</u> .....	941
<u>Message ID : DXF4236E</u> .....	942
<u>Message ID : DXF4237E</u> .....	942
<u>Message ID : DXF4238E</u> .....	943
<u>Message ID : DXF4239E</u> .....	944
<u>Message ID : DXF4240E</u> .....	944
<u>Message ID : DXF4241E</u> .....	945
<u>Message ID : DXF4243E</u> .....	946
<u>Message ID : DXF4244E</u> .....	946
<u>Message ID : DXF4247E</u> .....	947
<u>Message ID : DXF4248E</u> .....	948
<u>Message ID : DXF4249E</u> .....	949
<u>Message ID : DXF4250E</u> .....	950
<u>Message ID : DXF4251E</u> .....	951



# Table of Contents

## **Logger DXF: Errors**

<u>Message ID : DXF4252E</u> .....	952
<u>Message ID : DXF4255E</u> .....	953
<u>Message ID : DXF4266E</u> .....	954
<u>Message ID : DXF4270E</u> .....	955
<u>Message ID : DXF4271E</u> .....	955
<u>Message ID : DXF4272E</u> .....	956
<u>Message ID : DXF4282E</u> .....	957
<u>Message ID : DXF4286E</u> .....	958
<u>Message ID : DXF4287E</u> .....	959
<u>Message ID : DXF4288E</u> .....	960
<u>Message ID : DXF4289E</u> .....	961
<u>Message ID : DXF4290E</u> .....	962
<u>Message ID : DXF4291E</u> .....	963
<u>Message ID : DXF4292E</u> .....	964
<u>Message ID : DXF4294E</u> .....	964
<u>Message ID : DXF4295E</u> .....	965
<u>Message ID : DXF4296E</u> .....	966
<u>Message ID : DXF4297E</u> .....	967
<u>Message ID : DXF4298E</u> .....	967
<u>Message ID : DXF4299E</u> .....	968
<u>Message ID : DXF4300E</u> .....	969
<u>Message ID : DXF4301E</u> .....	970
<u>Message ID : DXF4302E</u> .....	971
<u>Message ID : DXF4303E</u> .....	972
<u>Message ID : DXF4304E</u> .....	972
<u>Message ID : DXF4306E</u> .....	973

# Table of Contents

## Logger DXF: Errors

<u>Message ID : DXF4312E</u> .....	974
<u>Message ID : DXF4313E</u> .....	975
<u>Message ID : DXF4314E</u> .....	976
<u>Message ID : DXF4315E</u> .....	977
<u>Message ID : DXF4325E</u> .....	978
<u>Message ID : DXF4326E</u> .....	979
<u>Message ID : DXF4328E</u> .....	979
<u>Message ID : DXF4330E</u> .....	980
<u>Message ID : DXF4331E</u> .....	981
<u>Message ID : DXF4334E</u> .....	982
<u>Message ID : DXF4335E</u> .....	983
<u>Message ID : DXF4336E</u> .....	983
<u>Message ID : DXF4340E</u> .....	984
<u>Message ID : DXF4341E</u> .....	985
<u>Message ID : DXF4342E</u> .....	985
<u>Message ID : DXF4343E</u> .....	986
<u>Message ID : DXF4346E</u> .....	987
<u>Message ID : DXF4347E</u> .....	987
<u>Message ID : DXF4349E</u> .....	988
<u>Message ID : DXF4350E</u> .....	989
<u>Message ID : DXF4353E</u> .....	990
<u>Message ID : DXF4354E</u> .....	990
<u>Message ID : DXF4355E</u> .....	991
<u>Message ID : DXF4356E</u> .....	992
<u>Message ID : DXF4357E</u> .....	993
<u>Message ID : DXF4358E</u> .....	993

# Table of Contents

## **Logger DXF: Errors**

<u>Message ID : DXF4360E</u> .....	994
<u>Message ID : DXF4367E</u> .....	995
<u>Message ID : DXF4368E</u> .....	996
<u>Message ID : DXF4376E</u> .....	997
<u>Message ID : DXF4377E</u> .....	998
<u>Message ID : DXF4379E</u> .....	999
<u>Message ID : DXF4381E</u> .....	1000
<u>Message ID : DXF4382E</u> .....	1000
<u>Message ID : DXF4391E</u> .....	1001
<u>Message ID : DXF4392E</u> .....	1002
<u>Message ID : DXF4393E</u> .....	1003
<u>Message ID : DXF4394E</u> .....	1004
<u>Message ID : DXF4395E</u> .....	1005
<u>Message ID : DXF4396E</u> .....	1005
<u>Message ID : DXF4400E</u> .....	1006
<u>Message ID : DXF4401E</u> .....	1007
<u>Message ID : DXF4403E</u> .....	1008
<u>Message ID : DXF4404E</u> .....	1009
<u>Message ID : DXF4405E</u> .....	1009
<u>Message ID : DXF4407E</u> .....	1010
<u>Message ID : DXF4408E</u> .....	1011
<u>Message ID : DXF4409E</u> .....	1012
<u>Message ID : DXF4427E</u> .....	1013
<u>Message ID : DXF4430E</u> .....	1014
<u>Message ID : DXF4432E</u> .....	1014
<u>Message ID : DXF4433E</u> .....	1015

# Table of Contents

## **Logger DXF: Errors**

<u>Message ID : DXF4434E</u> .....	1016
<u>Message ID : DXF4435E</u> .....	1017
<u>Message ID : DXF4436E</u> .....	1017
<u>Message ID : DXF4437E</u> .....	1018
<u>Message ID : DXF4438E</u> .....	1019
<u>Message ID : DXF4439E</u> .....	1019
<u>Message ID : DXF4440E</u> .....	1020
<u>Message ID : DXF4441E</u> .....	1021
<u>Message ID : DXF4442E</u> .....	1021
<u>Message ID : DXF4443E</u> .....	1022
<u>Message ID : DXF4444E</u> .....	1023
<u>Message ID : DXF4445E</u> .....	1023
<u>Message ID : DXF4446E</u> .....	1024
<u>Message ID : DXF4447E</u> .....	1025
<u>Message ID : DXF4448E</u> .....	1025
<u>Message ID : DXF4449E</u> .....	1026
<u>Message ID : DXF4450E</u> .....	1027
<u>Message ID : DXF4451E</u> .....	1027
<u>Message ID : DXF4452E</u> .....	1028
<u>Message ID : DXF4453E</u> .....	1029
<u>Message ID : DXF4454E</u> .....	1029
<u>Message ID : DXF4455E</u> .....	1030
<u>Message ID : DXF4456E</u> .....	1031
<u>Message ID : DXF4457E</u> .....	1031
<u>Message ID : DXF4458E</u> .....	1032
<u>Message ID : DXF4459E</u> .....	1033

# Table of Contents

## Logger DXF: Errors

<u>Message ID : DXF4460E</u> .....	1033
<u>Message ID : DXF4461E</u> .....	1034
<u>Message ID : DXF4462E</u> .....	1035
<u>Message ID : DXF4463E</u> .....	1035
<u>Message ID : DXF4464E</u> .....	1036
<u>Message ID : DXF4465E</u> .....	1037
<u>Message ID : DXF4466E</u> .....	1037
<u>Message ID : DXF4467E</u> .....	1038
<u>Message ID : DXF4468E</u> .....	1039
<u>Message ID : DXF4469E</u> .....	1040
<u>Message ID : DXF4470E</u> .....	1040
<u>Message ID : DXF4471E</u> .....	1041
<u>Message ID : DXF4472E</u> .....	1042
<u>Message ID : DXF4474E</u> .....	1042
<u>Message ID : DXF4476E</u> .....	1043
<u>Message ID : DXF4477E</u> .....	1044
<u>Message ID : DXF4478E</u> .....	1045
<u>Message ID : DXF4479E</u> .....	1045
<u>Message ID : DXF4480E</u> .....	1046
<u>Message ID : DXF4482E</u> .....	1047
<u>Message ID : DXF4483E</u> .....	1048
<u>Message ID : DXF4484E</u> .....	1049
<u>Message ID : DXF4486E</u> .....	1049
<u>Message ID : DXF4494E</u> .....	1050
<u>Message ID : DXF4498E</u> .....	1051
<u>Message ID : DXF4499E</u> .....	1052

# Table of Contents

<b><u>Logger DXF: Fatal errors</u></b> .....	<b>1054</b>
<u>Message ID : DXF4431E</u> .....	1054
<b><u>Logger DXF: Information</u></b> .....	<b>1055</b>
<u>Message ID : DXF3211I</u> .....	1055
<u>Message ID : DXF3235I</u> .....	1056
<u>Message ID : DXF3236I</u> .....	1057
<u>Message ID : DXF3237I</u> .....	1058
<u>Message ID : DXF4122I</u> .....	1059
<u>Message ID : DXF4123I</u> .....	1059
<u>Message ID : DXF4126I</u> .....	1060
<u>Message ID : DXF4127I</u> .....	1061
<u>Message ID : DXF4128I</u> .....	1061
<u>Message ID : DXF4129I</u> .....	1062
<u>Message ID : DXF4130I</u> .....	1063
<u>Message ID : DXF4131I</u> .....	1064
<u>Message ID : DXF4132I</u> .....	1064
<u>Message ID : DXF4143I</u> .....	1065
<u>Message ID : DXF4144I</u> .....	1066
<u>Message ID : DXF4145I</u> .....	1067
<u>Message ID : DXF4146I</u> .....	1068
<u>Message ID : DXF4147I</u> .....	1069
<u>Message ID : DXF4148I</u> .....	1070
<u>Message ID : DXF4154I</u> .....	1071
<u>Message ID : DXF4161I</u> .....	1072
<u>Message ID : DXF4200I</u> .....	1072
<u>Message ID : DXF4201I</u> .....	1073

# Table of Contents

## **Logger DXF: Information**

<u>Message ID : DXF4202I</u> .....	1074
<u>Message ID : DXF4203I</u> .....	1075
<u>Message ID : DXF4204I</u> .....	1076
<u>Message ID : DXF4205I</u> .....	1077
<u>Message ID : DXF4206I</u> .....	1077
<u>Message ID : DXF4207I</u> .....	1078
<u>Message ID : DXF4208I</u> .....	1079
<u>Message ID : DXF4209I</u> .....	1080
<u>Message ID : DXF4210I</u> .....	1081
<u>Message ID : DXF4211I</u> .....	1082
<u>Message ID : DXF4212I</u> .....	1082
<u>Message ID : DXF4213I</u> .....	1083
<u>Message ID : DXF4214I</u> .....	1084
<u>Message ID : DXF4216I</u> .....	1085
<u>Message ID : DXF4217I</u> .....	1086
<u>Message ID : DXF4218I</u> .....	1087
<u>Message ID : DXF4219I</u> .....	1087
<u>Message ID : DXF4220I</u> .....	1088
<u>Message ID : DXF4221I</u> .....	1089
<u>Message ID : DXF4222I</u> .....	1090
<u>Message ID : DXF4223I</u> .....	1091
<u>Message ID : DXF4224I</u> .....	1092
<u>Message ID : DXF4225I</u> .....	1093
<u>Message ID : DXF4226I</u> .....	1093
<u>Message ID : DXF4253I</u> .....	1094
<u>Message ID : DXF4257I</u> .....	1095

# Table of Contents

## **Logger DXF: Information**

<u>Message ID : DXF4258I</u> .....	1096
<u>Message ID : DXF4259I</u> .....	1097
<u>Message ID : DXF4260I</u> .....	1098
<u>Message ID : DXF4261I</u> .....	1098
<u>Message ID : DXF4262I</u> .....	1099
<u>Message ID : DXF4263I</u> .....	1100
<u>Message ID : DXF4264I</u> .....	1101
<u>Message ID : DXF4265I</u> .....	1102
<u>Message ID : DXF4267I</u> .....	1103
<u>Message ID : DXF4268I</u> .....	1104
<u>Message ID : DXF4269I</u> .....	1105
<u>Message ID : DXF4273I</u> .....	1105
<u>Message ID : DXF4274I</u> .....	1106
<u>Message ID : DXF4275I</u> .....	1107
<u>Message ID : DXF4276I</u> .....	1108
<u>Message ID : DXF4277I</u> .....	1109
<u>Message ID : DXF4278I</u> .....	1110
<u>Message ID : DXF4279I</u> .....	1110
<u>Message ID : DXF4280I</u> .....	1111
<u>Message ID : DXF4281I</u> .....	1112
<u>Message ID : DXF4283I</u> .....	1113
<u>Message ID : DXF4284I</u> .....	1114
<u>Message ID : DXF4285I</u> .....	1115
<u>Message ID : DXF4293I</u> .....	1116
<u>Message ID : DXF4309I</u> .....	1117
<u>Message ID : DXF4316I</u> .....	1117



# Table of Contents

## **Logger DXF: Information**

<u>Message ID : DXF4317I</u> .....	1118
<u>Message ID : DXF4318I</u> .....	1119
<u>Message ID : DXF4319I</u> .....	1120
<u>Message ID : DXF4320I</u> .....	1121
<u>Message ID : DXF4321I</u> .....	1122
<u>Message ID : DXF4322I</u> .....	1122
<u>Message ID : DXF4323I</u> .....	1123
<u>Message ID : DXF4329I</u> .....	1124
<u>Message ID : DXF4332I</u> .....	1125
<u>Message ID : DXF4344I</u> .....	1126
<u>Message ID : DXF4345I</u> .....	1127
<u>Message ID : DXF4352I</u> .....	1128
<u>Message ID : DXF4361I</u> .....	1128
<u>Message ID : DXF4362I</u> .....	1129
<u>Message ID : DXF4363I</u> .....	1130
<u>Message ID : DXF4364I</u> .....	1131
<u>Message ID : DXF4365I</u> .....	1132
<u>Message ID : DXF4366I</u> .....	1133
<u>Message ID : DXF4369I</u> .....	1134
<u>Message ID : DXF4370I</u> .....	1135
<u>Message ID : DXF4371I</u> .....	1136
<u>Message ID : DXF4372I</u> .....	1137
<u>Message ID : DXF4375I</u> .....	1138
<u>Message ID : DXF4378I</u> .....	1138
<u>Message ID : DXF4380I</u> .....	1139
<u>Message ID : DXF4383I</u> .....	1140

# Table of Contents

## **Logger DXF: Information**

<u>Message ID : DXF4384I</u> .....	1141
<u>Message ID : DXF4385I</u> .....	1142
<u>Message ID : DXF4386I</u> .....	1143
<u>Message ID : DXF4387I</u> .....	1144
<u>Message ID : DXF4388I</u> .....	1145
<u>Message ID : DXF4389I</u> .....	1146
<u>Message ID : DXF4390I</u> .....	1147
<u>Message ID : DXF4397I</u> .....	1147
<u>Message ID : DXF4399I</u> .....	1148
<u>Message ID : DXF4414I</u> .....	1149
<u>Message ID : DXF4415I</u> .....	1150
<u>Message ID : DXF4416I</u> .....	1151
<u>Message ID : DXF4417I</u> .....	1152
<u>Message ID : DXF4418I</u> .....	1152
<u>Message ID : DXF4419I</u> .....	1153
<u>Message ID : DXF4420I</u> .....	1154
<u>Message ID : DXF4421I</u> .....	1155
<u>Message ID : DXF4422I</u> .....	1156
<u>Message ID : DXF4423I</u> .....	1157
<u>Message ID : DXF4424I</u> .....	1158
<u>Message ID : DXF4425I</u> .....	1159
<u>Message ID : DXF4429I</u> .....	1160
<u>Message ID : DXF4481I</u> .....	1161
<u>Message ID : DXF4485I</u> .....	1162
<u>Message ID : DXF4487I</u> .....	1162
<u>Message ID : DXF4488I</u> .....	1163

# Table of Contents

## **Logger DXF: Information**

<u>Message ID : DXF4489I</u> .....	1164
<u>Message ID : DXF4490I</u> .....	1165
<u>Message ID : DXF4491I</u> .....	1166
<u>Message ID : DXF4492I</u> .....	1167
<u>Message ID : DXF4493I</u> .....	1167
<u>Message ID : DXF4495I</u> .....	1168
<u>Message ID : DXF4496I</u> .....	1169
<u>Message ID : DXF4497I</u> .....	1170

## **Logger DXF: Warnings**.....**1171**

<u>Message ID : DXF3210W</u> .....	1171
<u>Message ID : DXF4103W</u> .....	1172
<u>Message ID : DXF4104W</u> .....	1172
<u>Message ID : DXF4118W</u> .....	1173
<u>Message ID : DXF4242W</u> .....	1174
<u>Message ID : DXF4254W</u> .....	1175
<u>Message ID : DXF4307W</u> .....	1176
<u>Message ID : DXF4324W</u> .....	1177
<u>Message ID : DXF4327W</u> .....	1177
<u>Message ID : DXF4333W</u> .....	1178
<u>Message ID : DXF4337W</u> .....	1179
<u>Message ID : DXF4338W</u> .....	1180
<u>Message ID : DXF4339W</u> .....	1181
<u>Message ID : DXF4351W</u> .....	1181
<u>Message ID : DXF4359W</u> .....	1182
<u>Message ID : DXF4373W</u> .....	1183

# Table of Contents

<b><u>Logger DXF: Warnings</u></b>	
<u>Message ID : DXF4398W</u>	1184
<u>Message ID : DXF4406W</u>	1185
<u>Message ID : DXF4410W</u>	1186
<u>Message ID : DXF4413W</u>	1187
<u>Message ID : DXF4428W</u>	1187
<b><u>Logger FIP: Fatal errors</u></b>	<b>1189</b>
<u>Message ID : FIP0625E</u>	1189
<u>Message ID : FIP0626E</u>	1190
<b><u>Logger FIP: Information</u></b>	<b>1191</b>
<u>Message ID : FIP0624I</u>	1191
<b><u>Logger GEN: Errors</u></b>	<b>1192</b>
<u>Message ID : GEN1253E</u>	1192
<u>Message ID : GEN1280E</u>	1192
<b><u>Logger GEN: Information</u></b>	<b>1194</b>
<u>Message ID : GEN1276I</u>	1194
<u>Message ID : GEN1279I</u>	1195
<b><u>Logger IEP: Errors</u></b>	<b>1196</b>
<u>Message ID : IEP0321E</u>	1196
<u>Message ID : IEP0322E</u>	1196
<u>Message ID : IEP0323E</u>	1197
<u>Message ID : IEP0324E</u>	1198

# Table of Contents

## **Logger IEP: Errors**

<u>Message ID : IEP0325E</u> .....	1198
<u>Message ID : IEP0326E</u> .....	1199
<u>Message ID : IEP0327E</u> .....	1200
<u>Message ID : IEP0328E</u> .....	1200
<u>Message ID : IEP0329E</u> .....	1201
<u>Message ID : IEP0330E</u> .....	1202
<u>Message ID : IEP0331E</u> .....	1202
<u>Message ID : IEP0332E</u> .....	1203

## **Logger IEP: Information**.....1205

<u>Message ID : IEP0577I</u> .....	1205
------------------------------------	------

## **Logger IEP: Warnings**.....1206

<u>Message ID : IEP0338W</u> .....	1206
<u>Message ID : IEP0342W</u> .....	1207
<u>Message ID : IEP0343W</u> .....	1207
<u>Message ID : IEP0344W</u> .....	1208
<u>Message ID : IEP0345W</u> .....	1209

## **Logger KMG: Errors**.....1210

<u>Message ID : KMG0065E</u> .....	1210
<u>Message ID : KMG0068E</u> .....	1210
<u>Message ID : KMG0094E</u> .....	1211
<u>Message ID : KMG0095E</u> .....	1212
<u>Message ID : KMG0096E</u> .....	1212
<u>Message ID : KMG0097E</u> .....	1213

# Table of Contents

## Logger KMG: Errors

<u>Message ID : KMG0098E</u> .....	1214
<u>Message ID : KMG0099E</u> .....	1215
<u>Message ID : KMG0100E</u> .....	1215
<u>Message ID : KMG0101E</u> .....	1216
<u>Message ID : KMG0102E</u> .....	1217
<u>Message ID : KMG0103E</u> .....	1217
<u>Message ID : KMG0104E</u> .....	1218
<u>Message ID : KMG0105E</u> .....	1219
<u>Message ID : KMG0106E</u> .....	1219
<u>Message ID : KMG0107E</u> .....	1220
<u>Message ID : KMG0108E</u> .....	1221
<u>Message ID : KMG0109E</u> .....	1222
<u>Message ID : KMG0110E</u> .....	1222
<u>Message ID : KMG0111E</u> .....	1223
<u>Message ID : KMG0112E</u> .....	1224
<u>Message ID : KMG0113E</u> .....	1225
<u>Message ID : KMG0114E</u> .....	1225
<u>Message ID : KMG0220E</u> .....	1226
<u>Message ID : KMG0221E</u> .....	1227
<u>Message ID : KMG0222E</u> .....	1227
<u>Message ID : KMG0256E</u> .....	1228
<u>Message ID : KMG0257E</u> .....	1229
<u>Message ID : KMG0258E</u> .....	1229
<u>Message ID : KMG0262E</u> .....	1230
<u>Message ID : KMG0265E</u> .....	1231
<u>Message ID : KMG0273E</u> .....	1231

# Table of Contents

## Logger KMG: Errors

<u>Message ID : KMG0274E</u> .....	1232
<u>Message ID : KMG0285E</u> .....	1233
<u>Message ID : KMG0301E</u> .....	1233
<u>Message ID : KMG0307E</u> .....	1234
<u>Message ID : KMG0524E</u> .....	1235
<u>Message ID : KMG0615E</u> .....	1236
<u>Message ID : KMG0616E</u> .....	1236
<u>Message ID : KMG0686E</u> .....	1237
<u>Message ID : KMG0687E</u> .....	1238
<u>Message ID : KMG0688E</u> .....	1238
<u>Message ID : KMG0689E</u> .....	1239
<u>Message ID : KMG0690E</u> .....	1240
<u>Message ID : KMG0691E</u> .....	1240
<u>Message ID : KMG0692E</u> .....	1241
<u>Message ID : KMG0693E</u> .....	1242
<u>Message ID : KMG0694E</u> .....	1242
<u>Message ID : KMG0695E</u> .....	1243
<u>Message ID : KMG0696E</u> .....	1244
<u>Message ID : KMG0698E</u> .....	1244
<u>Message ID : KMG0699E</u> .....	1245
<u>Message ID : KMG0700E</u> .....	1246
<u>Message ID : KMG0708E</u> .....	1246
<u>Message ID : KMG0709E</u> .....	1247
<u>Message ID : KMG0726E</u> .....	1248
<u>Message ID : KMG0727E</u> .....	1248
<u>Message ID : KMG0728E</u> .....	1249

# Table of Contents

## Logger KMG: Errors

<u>Message ID : KMG0729E</u> .....	1250
<u>Message ID : KMG0730E</u> .....	1250
<u>Message ID : KMG0731E</u> .....	1251
<u>Message ID : KMG0732E</u> .....	1252
<u>Message ID : KMG0733E</u> .....	1252
<u>Message ID : KMG0734E</u> .....	1253
<u>Message ID : KMG0735E</u> .....	1254
<u>Message ID : KMG0736E</u> .....	1254
<u>Message ID : KMG0737E</u> .....	1255
<u>Message ID : KMG0738E</u> .....	1256
<u>Message ID : KMG0739E</u> .....	1256
<u>Message ID : KMG0740E</u> .....	1257
<u>Message ID : KMG0741E</u> .....	1258
<u>Message ID : KMG0742E</u> .....	1258
<u>Message ID : KMG0743E</u> .....	1259
<u>Message ID : KMG0744E</u> .....	1260
<u>Message ID : KMG0745E</u> .....	1260
<u>Message ID : KMG0746E</u> .....	1261
<u>Message ID : KMG0747E</u> .....	1262
<u>Message ID : KMG0748E</u> .....	1262
<u>Message ID : KMG0749E</u> .....	1263
<u>Message ID : KMG0750E</u> .....	1264
<u>Message ID : KMG0751E</u> .....	1264
<u>Message ID : KMG0752E</u> .....	1265
<u>Message ID : KMG0753E</u> .....	1266
<u>Message ID : KMG0754E</u> .....	1266



# Table of Contents

## Logger KMG: Errors

<u>Message ID : KMG0755E</u> .....	1267
<u>Message ID : KMG0756E</u> .....	1268
<u>Message ID : KMG0757E</u> .....	1268
<u>Message ID : KMG0758E</u> .....	1269
<u>Message ID : KMG0760E</u> .....	1270
<u>Message ID : KMG0762E</u> .....	1270
<u>Message ID : KMG0765E</u> .....	1271
<u>Message ID : KMG0766E</u> .....	1272
<u>Message ID : KMG0767E</u> .....	1272
<u>Message ID : KMG0768E</u> .....	1273
<u>Message ID : KMG0769E</u> .....	1274
<u>Message ID : KMG0770E</u> .....	1274
<u>Message ID : KMG0773E</u> .....	1275
<u>Message ID : KMG0775E</u> .....	1276
<u>Message ID : KMG1252E</u> .....	1276
<u>Message ID : KMG1255E</u> .....	1277
<u>Message ID : KMG1258E</u> .....	1278
<u>Message ID : KMG1267E</u> .....	1278
<u>Message ID : KMG1268E</u> .....	1279
<u>Message ID : KMG1269E</u> .....	1280
<u>Message ID : KMG1270E</u> .....	1280
<u>Message ID : KMG1271E</u> .....	1281
<u>Message ID : KMG1272E</u> .....	1282
<u>Message ID : KMG1273E</u> .....	1282
<u>Message ID : KMG1274E</u> .....	1283
<u>Message ID : KMG1282E</u> .....	1284

# Table of Contents

## Logger KMG: Errors

<u>Message ID : KMG1283E</u> .....	1284
<u>Message ID : KMG1284E</u> .....	1285
<u>Message ID : KMG1338E</u> .....	1286
<u>Message ID : KMG1339E</u> .....	1286
<u>Message ID : KMG1340E</u> .....	1287
<u>Message ID : KMG1341E</u> .....	1288
<u>Message ID : KMG1380E</u> .....	1288
<u>Message ID : KMG1382E</u> .....	1289
<u>Message ID : KMG1383E</u> .....	1290
<u>Message ID : KMG1384E</u> .....	1290
<u>Message ID : KMG1385E</u> .....	1291
<u>Message ID : KMG1387E</u> .....	1292
<u>Message ID : KMG1388E</u> .....	1292
<u>Message ID : KMG1394E</u> .....	1293
<u>Message ID : KMG1409E</u> .....	1294
<u>Message ID : KMG1410E</u> .....	1294
<u>Message ID : KMG1411E</u> .....	1295
<u>Message ID : KMG1412E</u> .....	1296
<u>Message ID : KMG1413E</u> .....	1296
<u>Message ID : KMG1414E</u> .....	1297
<u>Message ID : KMG1416E</u> .....	1298
<u>Message ID : KMG1417E</u> .....	1298
<u>Message ID : KMG1418E</u> .....	1299
<u>Message ID : KMG1430E</u> .....	1300
<u>Message ID : KMG1512E</u> .....	1300
<u>Message ID : KMG1518E</u> .....	1301

# Table of Contents

## Logger KMG: Errors

<u>Message ID : KMG1521E</u> .....	1302
<u>Message ID : KMG1522E</u> .....	1302
<u>Message ID : KMG1523E</u> .....	1303
<u>Message ID : KMG1525E</u> .....	1304
<u>Message ID : KMG1526E</u> .....	1304
<u>Message ID : KMG1527E</u> .....	1305
<u>Message ID : KMG1528E</u> .....	1306
<u>Message ID : KMG1529E</u> .....	1306
<u>Message ID : KMG1531E</u> .....	1307
<u>Message ID : KMG1532E</u> .....	1308
<u>Message ID : KMG1533E</u> .....	1308
<u>Message ID : KMG1534E</u> .....	1309
<u>Message ID : KMG1535E</u> .....	1310
<u>Message ID : KMG1536E</u> .....	1310
<u>Message ID : KMG1537E</u> .....	1311
<u>Message ID : KMG1538E</u> .....	1312
<u>Message ID : KMG1539E</u> .....	1312
<u>Message ID : KMG1540E</u> .....	1313
<u>Message ID : KMG1541E</u> .....	1314
<u>Message ID : KMG1542E</u> .....	1314
<u>Message ID : KMG1544E</u> .....	1315
<u>Message ID : KMG1545E</u> .....	1316
<u>Message ID : KMG1546E</u> .....	1316
<u>Message ID : KMG1547E</u> .....	1317
<u>Message ID : KMG1566E</u> .....	1318
<u>Message ID : KMG1591E</u> .....	1318

# Table of Contents

## Logger KMG: Errors

<u>Message ID : KMG1592E</u> .....	1319
<u>Message ID : KMG1593E</u> .....	1320
<u>Message ID : KMG1594E</u> .....	1320
<u>Message ID : KMG1595E</u> .....	1321
<u>Message ID : KMG1596E</u> .....	1322
<u>Message ID : KMG1597E</u> .....	1322
<u>Message ID : KMG1598E</u> .....	1323
<u>Message ID : KMG1599E</u> .....	1324
<u>Message ID : KMG1600E</u> .....	1324
<u>Message ID : KMG1610E</u> .....	1325
<u>Message ID : KMG1612E</u> .....	1326
<u>Message ID : KMG1613E</u> .....	1326
<u>Message ID : KMG1618E</u> .....	1327
<u>Message ID : KMG1619E</u> .....	1328
<u>Message ID : KMG1620E</u> .....	1328
<u>Message ID : KMG1621E</u> .....	1329
<u>Message ID : KMG1622E</u> .....	1330
<u>Message ID : KMG1624E</u> .....	1330
<u>Message ID : KMG1625E</u> .....	1331
<u>Message ID : KMG1626E</u> .....	1332
<u>Message ID : KMG1633E</u> .....	1333
<u>Message ID : KMG1635E</u> .....	1333
<u>Message ID : KMG1636E</u> .....	1334
<u>Message ID : KMG1637E</u> .....	1335
<u>Message ID : KMG1638E</u> .....	1335
<u>Message ID : KMG1639E</u> .....	1336

# Table of Contents

## Logger KMG: Errors

<u>Message ID : KMG1640E</u> .....	1337
<u>Message ID : KMG1641E</u> .....	1337
<u>Message ID : KMG1642E</u> .....	1338
<u>Message ID : KMG1643E</u> .....	1339
<u>Message ID : KMG1644E</u> .....	1339
<u>Message ID : KMG1647E</u> .....	1340
<u>Message ID : KMG1648E</u> .....	1341
<u>Message ID : KMG1650E</u> .....	1341
<u>Message ID : KMG1651E</u> .....	1342
<u>Message ID : KMG1653E</u> .....	1343
<u>Message ID : KMG1654E</u> .....	1343
<u>Message ID : KMG1660E</u> .....	1344
<u>Message ID : KMG1661E</u> .....	1345
<u>Message ID : KMG1666E</u> .....	1345
<u>Message ID : KMG1667E</u> .....	1346
<u>Message ID : KMG1670E</u> .....	1347
<u>Message ID : KMG1674E</u> .....	1347
<u>Message ID : KMG1675E</u> .....	1348
<u>Message ID : KMG1676E</u> .....	1349
<u>Message ID : KMG1677E</u> .....	1349
<u>Message ID : KMG1694E</u> .....	1350
<u>Message ID : KMG1695E</u> .....	1351
<u>Message ID : KMG1696E</u> .....	1351
<u>Message ID : KMG1698E</u> .....	1352
<u>Message ID : KMG1699E</u> .....	1353
<u>Message ID : KMG1700E</u> .....	1353

# Table of Contents

## **Logger KMG: Errors**

<u>Message ID : KMG1701E</u> .....	1354
<u>Message ID : KMG1720E</u> .....	1355
<u>Message ID : KMG1728E</u> .....	1355
<u>Message ID : KMG1745E</u> .....	1356
<u>Message ID : KMG1762E</u> .....	1357
<u>Message ID : KMG1763E</u> .....	1357
<u>Message ID : KMG1764E</u> .....	1358
<u>Message ID : KMG1765E</u> .....	1359
<u>Message ID : KMG1766E</u> .....	1359
<u>Message ID : KMG1767E</u> .....	1360
<u>Message ID : KMG1768E</u> .....	1361
<u>Message ID : KMG1771E</u> .....	1361
<u>Message ID : KMG1772E</u> .....	1362
<u>Message ID : KMG1773E</u> .....	1363
<u>Message ID : KMG1782E</u> .....	1363
<u>Message ID : KMG1849E</u> .....	1364
<u>Message ID : KMG1850E</u> .....	1365

## **Logger KMG: Information**.....1366

<u>Message ID : KMG0547I</u> .....	1366
<u>Message ID : KMG0610I</u> .....	1366
<u>Message ID : KMG0611I</u> .....	1367
<u>Message ID : KMG0761I</u> .....	1368
<u>Message ID : KMG1220I</u> .....	1369
<u>Message ID : KMG1221I</u> .....	1370
<u>Message ID : KMG1361I</u> .....	1371

# Table of Contents

<b><u>Logger KMG: Information</u></b>	
<u>Message ID : KMG1362I</u> .....	1371
<u>Message ID : KMG1381I</u> .....	1372
<u>Message ID : KMG1386I</u> .....	1373
<u>Message ID : KMG1543I</u> .....	1373
<u>Message ID : KMG1645I</u> .....	1374
<u>Message ID : KMG1646I</u> .....	1375
<b><u>Logger KMG: Warnings</u></b> .....	<b>1376</b>
<u>Message ID : KMG0596W</u> .....	1376
<u>Message ID : KMG0774W</u> .....	1376
<u>Message ID : KMG1200W</u> .....	1377
<u>Message ID : KMG1201W</u> .....	1378
<u>Message ID : KMG1202W</u> .....	1379
<u>Message ID : KMG1203W</u> .....	1380
<u>Message ID : KMG1210W</u> .....	1380
<u>Message ID : KMG1211W</u> .....	1381
<u>Message ID : KMG1212W</u> .....	1382
<u>Message ID : KMG1213W</u> .....	1383
<u>Message ID : KMG1295W</u> .....	1384
<u>Message ID : KMG1300W</u> .....	1385
<u>Message ID : KMG1512W</u> .....	1385
<b><u>Logger LIC: Errors</u></b> .....	<b>1387</b>
<u>Message ID : LIC0276E</u> .....	1387
<u>Message ID : LIC0277E</u> .....	1387
<u>Message ID : LIC0278E</u> .....	1388

# Table of Contents

## Logger LIC: Errors

<u>Message ID : LIC0279E</u> .....	1389
<u>Message ID : LIC0580E</u> .....	1389
<u>Message ID : LIC0581E</u> .....	1390
<u>Message ID : LIC0582E</u> .....	1391
<u>Message ID : LIC0586E</u> .....	1391
<u>Message ID : LIC1160E</u> .....	1392
<u>Message ID : LIC1161E</u> .....	1393
<u>Message ID : LIC1162E</u> .....	1394
<u>Message ID : LIC1163E</u> .....	1395
<u>Message ID : LIC1164E</u> .....	1395
<u>Message ID : LIC1165E</u> .....	1396
<u>Message ID : LIC1166E</u> .....	1397
<u>Message ID : LIC1167E</u> .....	1397
<u>Message ID : LIC1261E</u> .....	1398
<u>Message ID : LIC1291E</u> .....	1399
<u>Message ID : LIC1292E</u> .....	1399
<u>Message ID : LIC1293E</u> .....	1400
<u>Message ID : LIC1298E</u> .....	1401
<u>Message ID : LIC1324E</u> .....	1401
<u>Message ID : LIC1325E</u> .....	1402
<u>Message ID : LIC1326E</u> .....	1403
<u>Message ID : LIC1327E</u> .....	1403
<u>Message ID : LIC1621E</u> .....	1404
<u>Message ID : LIC1690E</u> .....	1405
<u>Message ID : LIC1691E</u> .....	1405
<u>Message ID : LIC1736E</u> .....	1406



# Table of Contents

<b><u>Logger LIC: Errors</u></b>	
<u>Message ID : LIC1737E</u>	1407
<b><u>Logger LIC: Information</u></b>	<b>1408</b>
<u>Message ID : LIC0587I</u>	1408
<b><u>Logger LIC: Warnings</u></b>	<b>1409</b>
<u>Message ID : LIC1323W</u>	1409
<b><u>Logger LOG: Errors</u></b>	<b>1410</b>
<u>Message ID : LOG0138E</u>	1410
<u>Message ID : LOG0139E</u>	1410
<u>Message ID : LOG0287E</u>	1411
<b><u>Logger LOG: Information</u></b>	<b>1413</b>
<u>Message ID : LOG0140I</u>	1413
<u>Message ID : LOG0141I</u>	1414
<u>Message ID : LOG0541I</u>	1414
<u>Message ID : LOG0669I</u>	1415
<b><u>Logger LOG: Warnings</u></b>	<b>1417</b>
<u>Message ID : LOG0668W</u>	1417
<u>Message ID : LOG1318W</u>	1418
<b><u>Logger LUP: Errors</u></b>	<b>1419</b>
<u>Message ID : LUP0114E</u>	1419
<u>Message ID : LUP0117E</u>	1420

# Table of Contents

## **Logger LUP: Errors**

<u>Message ID : LUP0118E</u> .....	1421
<u>Message ID : LUP0119E</u> .....	1421
<u>Message ID : LUP0120E</u> .....	1422
<u>Message ID : LUP0121E</u> .....	1423
<u>Message ID : LUP0122E</u> .....	1424
<u>Message ID : LUP0123E</u> .....	1425
<u>Message ID : LUP0128E</u> .....	1426
<u>Message ID : LUP0131E</u> .....	1427
<u>Message ID : LUP0132E</u> .....	1428
<u>Message ID : LUP0133E</u> .....	1428
<u>Message ID : LUP0134E</u> .....	1429
<u>Message ID : LUP0135E</u> .....	1430
<u>Message ID : LUP0136E</u> .....	1431
<u>Message ID : LUP0299E</u> .....	1432

## **Logger LUP: Fatal errors**.....1434

<u>Message ID : LUP0124F</u> .....	1434
<u>Message ID : LUP0126F</u> .....	1435
<u>Message ID : LUP0127F</u> .....	1435
<u>Message ID : LUP0129F</u> .....	1436
<u>Message ID : LUP0130F</u> .....	1437
<u>Message ID : LUP0137F</u> .....	1438

## **Logger LUP: Information**.....1440

<u>Message ID : LUP0115I</u> .....	1440
<u>Message ID : LUP0116I</u> .....	1440

# Table of Contents

## **Logger LUP: Information**

<u>Message ID : LUP0125I</u> .....	1441
<u>Message ID : LUP0428I</u> .....	1442

## **Logger PLC: Errors**.....**1444**

<u>Message ID : PLC0179E</u> .....	1444
<u>Message ID : PLC0180E</u> .....	1444
<u>Message ID : PLC0183E</u> .....	1445
<u>Message ID : PLC0184E</u> .....	1446
<u>Message ID : PLC0185E</u> .....	1446
<u>Message ID : PLC0186E</u> .....	1447
<u>Message ID : PLC0187E</u> .....	1448
<u>Message ID : PLC0188E</u> .....	1448
<u>Message ID : PLC0189E</u> .....	1449
<u>Message ID : PLC0190E</u> .....	1450
<u>Message ID : PLC0191E</u> .....	1450
<u>Message ID : PLC0192E</u> .....	1451
<u>Message ID : PLC0193E</u> .....	1452
<u>Message ID : PLC0194E</u> .....	1452
<u>Message ID : PLC0195E</u> .....	1453
<u>Message ID : PLC0196E</u> .....	1454
<u>Message ID : PLC0288E</u> .....	1454
<u>Message ID : PLC0302E</u> .....	1455
<u>Message ID : PLC0548E</u> .....	1456
<u>Message ID : PLC0604E</u> .....	1456
<u>Message ID : PLC0764E</u> .....	1457
<u>Message ID : PLC0806E</u> .....	1458

# Table of Contents

## Logger PLC: Errors

<u>Message ID : PLC1301E</u> .....	1458
<u>Message ID : PLC1302E</u> .....	1459
<u>Message ID : PLC1303E</u> .....	1460
<u>Message ID : PLC1304E</u> .....	1460
<u>Message ID : PLC1305E</u> .....	1461
<u>Message ID : PLC1306E</u> .....	1462
<u>Message ID : PLC1309E</u> .....	1462
<u>Message ID : PLC1313E</u> .....	1463
<u>Message ID : PLC1316E</u> .....	1464
<u>Message ID : PLC1317E</u> .....	1464
<u>Message ID : PLC1320E</u> .....	1465
<u>Message ID : PLC1321E</u> .....	1466
<u>Message ID : PLC1500E</u> .....	1467
<u>Message ID : PLC1501E</u> .....	1467
<u>Message ID : PLC1502E</u> .....	1468
<u>Message ID : PLC1503E</u> .....	1469
<u>Message ID : PLC1505E</u> .....	1469
<u>Message ID : PLC1506E</u> .....	1470
<u>Message ID : PLC1507E</u> .....	1471
<u>Message ID : PLC1508E</u> .....	1471
<u>Message ID : PLC1509E</u> .....	1472
<u>Message ID : PLC1512E</u> .....	1473
<u>Message ID : PLC1515E</u> .....	1473
<u>Message ID : PLC1516E</u> .....	1474
<u>Message ID : PLC1517E</u> .....	1475
<u>Message ID : PLC1518E</u> .....	1475

# Table of Contents

## **Logger PLC: Errors**

<u>Message ID : PLC1623E</u> .....	1476
<u>Message ID : PLC1624E</u> .....	1477
<u>Message ID : PLC1671E</u> .....	1477
<u>Message ID : PLC1672E</u> .....	1478
<u>Message ID : PLC1673E</u> .....	1479
<u>Message ID : PLC1678E</u> .....	1479
<u>Message ID : PLC1679E</u> .....	1480
<u>Message ID : PLC1680E</u> .....	1481
<u>Message ID : PLC1681E</u> .....	1482
<u>Message ID : PLC1682E</u> .....	1482
<u>Message ID : PLC1688E</u> .....	1483
<u>Message ID : PLC1704E</u> .....	1484
<u>Message ID : PLC1719E</u> .....	1484
<u>Message ID : PLC1743E</u> .....	1485
<u>Message ID : PLC1751E</u> .....	1486
<u>Message ID : PLC1752E</u> .....	1487
<u>Message ID : PLC1753E</u> .....	1487
<u>Message ID : PLC1754E</u> .....	1488
<u>Message ID : PLC1755E</u> .....	1489
<u>Message ID : PLC1756E</u> .....	1489
<u>Message ID : PLC1757E</u> .....	1490
<u>Message ID : PLC1779E</u> .....	1491
<u>Message ID : PLC1780E</u> .....	1491
<u>Message ID : PLC1781E</u> .....	1492
<u>Message ID : PLC1783E</u> .....	1493
<u>Message ID : PLC1785E</u> .....	1493

# Table of Contents

## **Logger PLC: Errors**

<u>Message ID : PLC1786E</u> .....	1494
<u>Message ID : PLC1787E</u> .....	1495
<u>Message ID : PLC1788E</u> .....	1495
<u>Message ID : PLC1789E</u> .....	1496
<u>Message ID : PLC1820E</u> .....	1497

## **Logger PLC: Information**.....**1498**

<u>Message ID : PLC1511I</u> .....	1498
<u>Message ID : PLC1513I</u> .....	1499
<u>Message ID : PLC1514I</u> .....	1499

## **Logger PLC: Warnings**.....**1501**

<u>Message ID : PLC0181W</u> .....	1501
<u>Message ID : PLC0182W</u> .....	1501
<u>Message ID : PLC1318W</u> .....	1502
<u>Message ID : PLC1319W</u> .....	1503
<u>Message ID : PLC1369W</u> .....	1503
<u>Message ID : PLC1370W</u> .....	1504
<u>Message ID : PLC1371W</u> .....	1505
<u>Message ID : PLC1372W</u> .....	1506
<u>Message ID : PLC1373W</u> .....	1506
<u>Message ID : PLC1374W</u> .....	1507

## **Logger POL: Errors**.....**1509**

<u>Message ID : POL4556E</u> .....	1509
<u>Message ID : POL4580E</u> .....	1510

# Table of Contents

## **Logger POL: Errors**

<u>Message ID : POL4613E</u> .....	1511
<u>Message ID : POL4701E</u> .....	1512
<u>Message ID : POL4704E</u> .....	1513

## **Logger POL: Fatal errors**.....1514

<u>Message ID : POL4510F</u> .....	1514
<u>Message ID : POL4516F</u> .....	1515
<u>Message ID : POL4528F</u> .....	1516
<u>Message ID : POL4530F</u> .....	1517
<u>Message ID : POL4545F</u> .....	1518
<u>Message ID : POL4564F</u> .....	1518
<u>Message ID : POL4581F</u> .....	1519
<u>Message ID : POL4593F</u> .....	1520
<u>Message ID : POL4614F</u> .....	1521

## **Logger POL: Information**.....1523

<u>Message ID : POL0142I</u> .....	1523
<u>Message ID : POL0143I</u> .....	1523
<u>Message ID : POL0144I</u> .....	1524
<u>Message ID : POL0145I</u> .....	1526
<u>Message ID : POL0146I</u> .....	1527
<u>Message ID : POL0147I</u> .....	1528
<u>Message ID : POL0148I</u> .....	1529
<u>Message ID : POL0149I</u> .....	1531
<u>Message ID : POL0150I</u> .....	1532
<u>Message ID : POL0151I</u> .....	1532

# Table of Contents

## **Logger POL: Information**

<u>Message ID : POL0152I</u> .....	1533
<u>Message ID : POL0153I</u> .....	1534
<u>Message ID : POL0154I</u> .....	1535
<u>Message ID : POL0155I</u> .....	1535
<u>Message ID : POL4537I</u> .....	1536
<u>Message ID : POL4553I</u> .....	1537
<u>Message ID : POL4573I</u> .....	1538
<u>Message ID : POL4574I</u> .....	1539
<u>Message ID : POL4575I</u> .....	1540
<u>Message ID : POL4576I</u> .....	1541
<u>Message ID : POL4582I</u> .....	1542
<u>Message ID : POL4615I</u> .....	1542
<u>Message ID : POL4702I</u> .....	1544

## **Logger POL: Warnings.....1545**

<u>Message ID : POL4703W</u> .....	1545
------------------------------------	------

## **Logger SDK: Errors.....1546**

<u>Message ID : SDK0197E</u> .....	1546
<u>Message ID : SDK0198E</u> .....	1546
<u>Message ID : SDK0199E</u> .....	1547
<u>Message ID : SDK0200E</u> .....	1548
<u>Message ID : SDK0201E</u> .....	1548
<u>Message ID : SDK0202E</u> .....	1549
<u>Message ID : SDK0203E</u> .....	1550
<u>Message ID : SDK0204E</u> .....	1550



# Table of Contents

## Logger SDK: Errors

<u>Message ID : SDK0205E</u> .....	1551
<u>Message ID : SDK0206E</u> .....	1552
<u>Message ID : SDK0207E</u> .....	1552
<u>Message ID : SDK0208E</u> .....	1553
<u>Message ID : SDK0283E</u> .....	1554
<u>Message ID : SDK0284E</u> .....	1554
<u>Message ID : SDK0286E</u> .....	1555
<u>Message ID : SDK0403E</u> .....	1556
<u>Message ID : SDK0407E</u> .....	1556
<u>Message ID : SDK0408E</u> .....	1557
<u>Message ID : SDK0410E</u> .....	1558
<u>Message ID : SDK0411E</u> .....	1558
<u>Message ID : SDK0416E</u> .....	1559
<u>Message ID : SDK0417E</u> .....	1560
<u>Message ID : SDK0418E</u> .....	1560
<u>Message ID : SDK0419E</u> .....	1561
<u>Message ID : SDK0420E</u> .....	1562
<u>Message ID : SDK0421E</u> .....	1562
<u>Message ID : SDK0422E</u> .....	1563
<u>Message ID : SDK0423E</u> .....	1564
<u>Message ID : SDK0427E</u> .....	1564
<u>Message ID : SDK0437E</u> .....	1565
<u>Message ID : SDK0438E</u> .....	1566
<u>Message ID : SDK0439E</u> .....	1566
<u>Message ID : SDK0440E</u> .....	1567
<u>Message ID : SDK0441E</u> .....	1568

# Table of Contents

## **Logger SDK: Errors**

<u>Message ID : SDK0442E</u> .....	1569
<u>Message ID : SDK0443E</u> .....	1569
<u>Message ID : SDK0444E</u> .....	1570
<u>Message ID : SDK0447E</u> .....	1571
<u>Message ID : SDK0450E</u> .....	1571
<u>Message ID : SDK0451E</u> .....	1572
<u>Message ID : SDK0503E</u> .....	1573
<u>Message ID : SDK0504E</u> .....	1573
<u>Message ID : SDK0505E</u> .....	1574
<u>Message ID : SDK0517E</u> .....	1575
<u>Message ID : SDK0525E</u> .....	1575
<u>Message ID : SDK0526E</u> .....	1576
<u>Message ID : SDK0533E</u> .....	1577
<u>Message ID : SDK0534E</u> .....	1577
<u>Message ID : SDK0608E</u> .....	1578
<u>Message ID : SDK0630E</u> .....	1579
<u>Message ID : SDK0637E</u> .....	1580
<u>Message ID : SDK0662E</u> .....	1580
<u>Message ID : SDK0663E</u> .....	1581
<u>Message ID : SDK0664E</u> .....	1582
<u>Message ID : SDK0670E</u> .....	1583
<u>Message ID : SDK0671E</u> .....	1583
<u>Message ID : SDK0716E</u> .....	1584
<u>Message ID : SDK0717E</u> .....	1585
<u>Message ID : SDK0718E</u> .....	1585
<u>Message ID : SDK0719E</u> .....	1586

# Table of Contents

## **Logger SDK: Errors**

<u>Message ID : SDK0776E</u> .....	1587
<u>Message ID : SDK0777E</u> .....	1587
<u>Message ID : SDK0778E</u> .....	1588
<u>Message ID : SDK0780E</u> .....	1589
<u>Message ID : SDK0800E</u> .....	1589
<u>Message ID : SDK0801E</u> .....	1590
<u>Message ID : SDK1237E</u> .....	1591
<u>Message ID : SDK1238E</u> .....	1591
<u>Message ID : SDK1239E</u> .....	1592
<u>Message ID : SDK1240E</u> .....	1593
<u>Message ID : SDK1241E</u> .....	1593
<u>Message ID : SDK1242E</u> .....	1594
<u>Message ID : SDK1243E</u> .....	1595
<u>Message ID : SDK1256E</u> .....	1595
<u>Message ID : SDK1262E</u> .....	1596
<u>Message ID : SDK1296E</u> .....	1597
<u>Message ID : SDK1315E</u> .....	1597
<u>Message ID : SDK1324E</u> .....	1598
<u>Message ID : SDK1340E</u> .....	1599
<u>Message ID : SDK1365E</u> .....	1599
<u>Message ID : SDK1385E</u> .....	1600
<u>Message ID : SDK1386E</u> .....	1601
<u>Message ID : SDK1387E</u> .....	1601
<u>Message ID : SDK1388E</u> .....	1602
<u>Message ID : SDK1389E</u> .....	1603
<u>Message ID : SDK1390E</u> .....	1603

# Table of Contents

## **Logger SDK: Errors**

<u>Message ID : SDK1391E</u> .....	1604
<u>Message ID : SDK1407E</u> .....	1605
<u>Message ID : SDK1426E</u> .....	1605
<u>Message ID : SDK1504E</u> .....	1606
<u>Message ID : SDK1508E</u> .....	1607
<u>Message ID : SDK1513E</u> .....	1607
<u>Message ID : SDK1550E</u> .....	1608
<u>Message ID : SDK1553E</u> .....	1609
<u>Message ID : SDK1554E</u> .....	1609
<u>Message ID : SDK1558E</u> .....	1610
<u>Message ID : SDK1564E</u> .....	1611
<u>Message ID : SDK1565E</u> .....	1611
<u>Message ID : SDK1566E</u> .....	1612
<u>Message ID : SDK1567E</u> .....	1613
<u>Message ID : SDK1568E</u> .....	1613
<u>Message ID : SDK1617E</u> .....	1614
<u>Message ID : SDK1619E</u> .....	1615
<u>Message ID : SDK1620E</u> .....	1615
<u>Message ID : SDK1621E</u> .....	1616
<u>Message ID : SDK1622E</u> .....	1617
<u>Message ID : SDK1623E</u> .....	1617
<u>Message ID : SDK1649E</u> .....	1618
<u>Message ID : SDK1652E</u> .....	1619
<u>Message ID : SDK1654E</u> .....	1619
<u>Message ID : SDK1655E</u> .....	1620
<u>Message ID : SDK1660E</u> .....	1621

# Table of Contents

## **Logger SDK: Errors**

<u>Message ID : SDK1663E</u> .....	1621
<u>Message ID : SDK1668E</u> .....	1622
<u>Message ID : SDK1671E</u> .....	1623
<u>Message ID : SDK1672E</u> .....	1623
<u>Message ID : SDK1683E</u> .....	1624
<u>Message ID : SDK1706E</u> .....	1625
<u>Message ID : SDK1718E</u> .....	1625
<u>Message ID : SDK1731E</u> .....	1626
<u>Message ID : SDK1742E</u> .....	1627
<u>Message ID : SDK1746E</u> .....	1627
<u>Message ID : SDK1747E</u> .....	1628
<u>Message ID : SDK1760E</u> .....	1629
<u>Message ID : SDK1761E</u> .....	1629
<u>Message ID : SDK1769E</u> .....	1630
<u>Message ID : SDK1770E</u> .....	1631
<u>Message ID : SDK1795E</u> .....	1631
<u>Message ID : SDK1796E</u> .....	1632
<u>Message ID : SDK1797E</u> .....	1633
<u>Message ID : SDK1798E</u> .....	1634
<u>Message ID : SDK1801E</u> .....	1634
<u>Message ID : SDK1802E</u> .....	1635
<u>Message ID : SDK1803E</u> .....	1636
<u>Message ID : SDK1807E</u> .....	1636
<u>Message ID : SDK1808E</u> .....	1637
<u>Message ID : SDK1809E</u> .....	1638
<u>Message ID : SDK1811E</u> .....	1638

# Table of Contents

## Logger SDK: Errors

<u>Message ID : SDK1812E</u> .....	1639
<u>Message ID : SDK1814E</u> .....	1640
<u>Message ID : SDK1815E</u> .....	1640
<u>Message ID : SDK1817E</u> .....	1641
<u>Message ID : SDK1818E</u> .....	1642
<u>Message ID : SDK1819E</u> .....	1642
<u>Message ID : SDK1821E</u> .....	1643
<u>Message ID : SDK1822E</u> .....	1644
<u>Message ID : SDK1823E</u> .....	1644
<u>Message ID : SDK1824E</u> .....	1645
<u>Message ID : SDK1829E</u> .....	1646
<u>Message ID : SDK1830E</u> .....	1646
<u>Message ID : SDK1843E</u> .....	1647
<u>Message ID : SDK1851E</u> .....	1648
<u>Message ID : SDK1852E</u> .....	1648
<u>Message ID : SDK1853E</u> .....	1649
<u>Message ID : SDK1854E</u> .....	1650
<u>Message ID : SDK1855E</u> .....	1650
<u>Message ID : SDK1856E</u> .....	1651
<u>Message ID : SDK1857E</u> .....	1652
<u>Message ID : SDK1858E</u> .....	1652
<u>Message ID : SDK1859E</u> .....	1653
<u>Message ID : SDK1860E</u> .....	1654

# Table of Contents

<b>Logger SDK: Information</b> .....	<b>1655</b>
<u>Message ID : SDK0544I</u> .....	1655
<u>Message ID : SDK0545I</u> .....	1656
<u>Message ID : SDK0665I</u> .....	1656
<u>Message ID : SDK1551I</u> .....	1657
<u>Message ID : SDK1552I</u> .....	1658
<u>Message ID : SDK1555I</u> .....	1659
<u>Message ID : SDK1556I</u> .....	1660
<u>Message ID : SDK1557I</u> .....	1660
<u>Message ID : SDK1559I</u> .....	1661
<u>Message ID : SDK1560I</u> .....	1662
<u>Message ID : SDK1561I</u> .....	1662
<u>Message ID : SDK1562I</u> .....	1663
<u>Message ID : SDK1563I</u> .....	1664
<u>Message ID : SDK1670I</u> .....	1664
<u>Message ID : SDK1689I</u> .....	1665
<u>Message ID : SDK1738I</u> .....	1666
<u>Message ID : SDK1799I</u> .....	1666
<u>Message ID : SDK1800I</u> .....	1667
<u>Message ID : SDK1810I</u> .....	1668
<u>Message ID : SDK1825I</u> .....	1669
<u>Message ID : SDK1826I</u> .....	1670
<u>Message ID : SDK1831I</u> .....	1671
<u>Message ID : SDK1833I</u> .....	1672

# Table of Contents

<b><u>Logger SDK: Warnings</u></b> .....	<b>1673</b>
<u>Message ID : SDK0290W</u> .....	1673
<u>Message ID : SDK0583W</u> .....	1673
<u>Message ID : SDK0584W</u> .....	1674
<u>Message ID : SDK0585W</u> .....	1675
<u>Message ID : SDK0597W</u> .....	1676
<u>Message ID : SDK0779W</u> .....	1676
<u>Message ID : SDK1336W</u> .....	1677
<u>Message ID : SDK1338W</u> .....	1678
<u>Message ID : SDK1368W</u> .....	1678
<u>Message ID : SDK1390W</u> .....	1679
<u>Message ID : SDK1616W</u> .....	1680
<u>Message ID : SDK1617W</u> .....	1681
<u>Message ID : SDK1669W</u> .....	1681
<b><u>Logger SIN: Errors</u></b> .....	<b>1683</b>
<u>Message ID : SIN0209E</u> .....	1683
<u>Message ID : SIN0210E</u> .....	1683
<u>Message ID : SIN0211E</u> .....	1684
<u>Message ID : SIN0212E</u> .....	1685
<u>Message ID : SIN0213E</u> .....	1685
<u>Message ID : SIN0214E</u> .....	1686
<b><u>Logger SIN: Fatal errors</u></b> .....	<b>1688</b>
<u>Message ID : SIN0176F</u> .....	1688
<u>Message ID : SIN0177F</u> .....	1689
<u>Message ID : SIN0178F</u> .....	1689



# Table of Contents

<b>Logger USR: Errors</b> .....	<b>1691</b>
<u>Message ID : USR0156E</u> .....	1691
<u>Message ID : USR0157E</u> .....	1691
<u>Message ID : USR0158E</u> .....	1692
<u>Message ID : USR0159E</u> .....	1693
<u>Message ID : USR0160E</u> .....	1693
<u>Message ID : USR0161E</u> .....	1694
<u>Message ID : USR0162E</u> .....	1695
<u>Message ID : USR0163E</u> .....	1695
<u>Message ID : USR0164E</u> .....	1696
<u>Message ID : USR0165E</u> .....	1697
<u>Message ID : USR0166E</u> .....	1697
<u>Message ID : USR0168E</u> .....	1698
<u>Message ID : USR0169E</u> .....	1699
<u>Message ID : USR0170E</u> .....	1699
<u>Message ID : USR0219E</u> .....	1700
<u>Message ID : USR0266E</u> .....	1701
<u>Message ID : USR0270E</u> .....	1701
<u>Message ID : USR0298E</u> .....	1702
<u>Message ID : USR0308E</u> .....	1703
<u>Message ID : USR0309E</u> .....	1704
<u>Message ID : USR0310E</u> .....	1704
<u>Message ID : USR0311E</u> .....	1705
<u>Message ID : USR0315E</u> .....	1706
<u>Message ID : USR0316E</u> .....	1706
<u>Message ID : USR0318E</u> .....	1707
<u>Message ID : USR0319E</u> .....	1708

# Table of Contents

## Logger USR: Errors

<u>Message ID : USR0320E</u> .....	1708
<u>Message ID : USR0337E</u> .....	1709
<u>Message ID : USR0340E</u> .....	1710
<u>Message ID : USR0409E</u> .....	1710
<u>Message ID : USR0535E</u> .....	1711
<u>Message ID : USR0593E</u> .....	1712
<u>Message ID : USR0632E</u> .....	1712
<u>Message ID : USR1230E</u> .....	1713
<u>Message ID : USR1231E</u> .....	1714
<u>Message ID : USR1232E</u> .....	1714
<u>Message ID : USR1233E</u> .....	1715
<u>Message ID : USR1234E</u> .....	1716
<u>Message ID : USR1235E</u> .....	1716
<u>Message ID : USR1236E</u> .....	1717
<u>Message ID : USR1254E</u> .....	1718
<u>Message ID : USR1275E</u> .....	1718
<u>Message ID : USR1288E</u> .....	1719
<u>Message ID : USR1289E</u> .....	1720
<u>Message ID : USR1321E</u> .....	1720
<u>Message ID : USR1325E</u> .....	1721
<u>Message ID : USR1326E</u> .....	1722
<u>Message ID : USR1327E</u> .....	1722
<u>Message ID : USR1328E</u> .....	1723
<u>Message ID : USR1329E</u> .....	1724
<u>Message ID : USR1330E</u> .....	1724
<u>Message ID : USR1332E</u> .....	1725

# Table of Contents

## Logger USR: Errors

<u>Message ID : USR1333E</u> .....	1726
<u>Message ID : USR1351E</u> .....	1726
<u>Message ID : USR1385E</u> .....	1727
<u>Message ID : USR1386E</u> .....	1728
<u>Message ID : USR1387E</u> .....	1729
<u>Message ID : USR1388E</u> .....	1729
<u>Message ID : USR1389E</u> .....	1730
<u>Message ID : USR1393E</u> .....	1731
<u>Message ID : USR1396E</u> .....	1731
<u>Message ID : USR1397E</u> .....	1732
<u>Message ID : USR1398E</u> .....	1733
<u>Message ID : USR1399E</u> .....	1733
<u>Message ID : USR1400E</u> .....	1734
<u>Message ID : USR1401E</u> .....	1735
<u>Message ID : USR1402E</u> .....	1735
<u>Message ID : USR1403E</u> .....	1736
<u>Message ID : USR1404E</u> .....	1737
<u>Message ID : USR1405E</u> .....	1737
<u>Message ID : USR1406E</u> .....	1738
<u>Message ID : USR1408E</u> .....	1739
<u>Message ID : USR1411E</u> .....	1739
<u>Message ID : USR1412E</u> .....	1740
<u>Message ID : USR1413E</u> .....	1741
<u>Message ID : USR1414E</u> .....	1741
<u>Message ID : USR1415E</u> .....	1742
<u>Message ID : USR1416E</u> .....	1743

# Table of Contents

## Logger USR: Errors

<u>Message ID : USR1417E</u> .....	1743
<u>Message ID : USR1418E</u> .....	1744
<u>Message ID : USR1419E</u> .....	1745
<u>Message ID : USR1420E</u> .....	1745
<u>Message ID : USR1421E</u> .....	1746
<u>Message ID : USR1422E</u> .....	1747
<u>Message ID : USR1424E</u> .....	1747
<u>Message ID : USR1425E</u> .....	1748
<u>Message ID : USR1426E</u> .....	1749
<u>Message ID : USR1427E</u> .....	1749
<u>Message ID : USR1428E</u> .....	1750
<u>Message ID : USR1429E</u> .....	1751
<u>Message ID : USR1430E</u> .....	1751
<u>Message ID : USR1431E</u> .....	1752
<u>Message ID : USR1432E</u> .....	1753
<u>Message ID : USR1433E</u> .....	1753
<u>Message ID : USR1622E</u> .....	1754
<u>Message ID : USR1650E</u> .....	1755
<u>Message ID : USR1671E</u> .....	1755
<u>Message ID : USR1672E</u> .....	1756
<u>Message ID : USR1673E</u> .....	1757
<u>Message ID : USR1707E</u> .....	1757
<u>Message ID : USR1708E</u> .....	1758
<u>Message ID : USR1710E</u> .....	1759
<u>Message ID : USR1711E</u> .....	1759
<u>Message ID : USR1712E</u> .....	1760

# Table of Contents

## **Logger USR: Errors**

<u>Message ID : USR1713E</u> .....	1761
<u>Message ID : USR1714E</u> .....	1762
<u>Message ID : USR1715E</u> .....	1762
<u>Message ID : USR1716E</u> .....	1763
<u>Message ID : USR1717E</u> .....	1764
<u>Message ID : USR1719E</u> .....	1764
<u>Message ID : USR1721E</u> .....	1765
<u>Message ID : USR1722E</u> .....	1766
<u>Message ID : USR1729E</u> .....	1766
<u>Message ID : USR1730E</u> .....	1767
<u>Message ID : USR1836E</u> .....	1768
<u>Message ID : USR1838E</u> .....	1768
<u>Message ID : USR1839E</u> .....	1769
<u>Message ID : USR1840E</u> .....	1770
<u>Message ID : USR1843E</u> .....	1770

## **Logger USR: Information**.....1772

<u>Message ID : USR0631I</u> .....	1772
<u>Message ID : USR1277I</u> .....	1773
<u>Message ID : USR1278I</u> .....	1773
<u>Message ID : USR1330I</u> .....	1774
<u>Message ID : USR1331I</u> .....	1775

## **Logger USR: Warnings**.....1777

<u>Message ID : USR1615W</u> .....	1777
<u>Message ID : USR1709W</u> .....	1778

# Table of Contents

<b><u>Logger VAD: Errors</u></b> .....	<b>1779</b>
<u>Message ID : VAD4642E</u> .....	1779
<b><u>Logger VAD: Information</u></b> .....	<b>1781</b>
<u>Message ID : VAD4641I</u> .....	1781
<b><u>Logger VAD: Warnings</u></b> .....	<b>1783</b>
<u>Message ID : VAD4643W</u> .....	1783
<b><u>Logger VMD: Errors</u></b> .....	<b>1784</b>
<u>Message ID : VMD3203E</u> .....	1784
<u>Message ID : VMD3204E</u> .....	1785
<u>Message ID : VMD3503E</u> .....	1785
<u>Message ID : VMD3507E</u> .....	1786
<u>Message ID : VMD3509E</u> .....	1787
<u>Message ID : VMD3510E</u> .....	1788
<u>Message ID : VMD3514E</u> .....	1788
<u>Message ID : VMD3517E</u> .....	1789
<u>Message ID : VMD3520E</u> .....	1790
<u>Message ID : VMD3525E</u> .....	1790
<u>Message ID : VMD3527E</u> .....	1791
<u>Message ID : VMD3533E</u> .....	1792
<u>Message ID : VMD3544E</u> .....	1792
<u>Message ID : VMD3546E</u> .....	1793
<u>Message ID : VMD3550E</u> .....	1794
<u>Message ID : VMD3559E</u> .....	1795
<u>Message ID : VMD3563E</u> .....	1795

# Table of Contents

## Logger VMD: Errors

<u>Message ID : VMD3572E</u> .....	1796
<u>Message ID : VMD3578E</u> .....	1797
<u>Message ID : VMD3581E</u> .....	1798
<u>Message ID : VMD3596E</u> .....	1798
<u>Message ID : VMD3597E</u> .....	1799
<u>Message ID : VMD3605E</u> .....	1800
<u>Message ID : VMD3607E</u> .....	1801
<u>Message ID : VMD3611E</u> .....	1801
<u>Message ID : VMD3612E</u> .....	1802
<u>Message ID : VMD3616E</u> .....	1803
<u>Message ID : VMD3617E</u> .....	1803
<u>Message ID : VMD3628E</u> .....	1804
<u>Message ID : VMD3629E</u> .....	1805
<u>Message ID : VMD3633E</u> .....	1806
<u>Message ID : VMD3644E</u> .....	1806
<u>Message ID : VMD3645E</u> .....	1807
<u>Message ID : VMD3651E</u> .....	1808
<u>Message ID : VMD3655E</u> .....	1809
<u>Message ID : VMD3665E</u> .....	1809
<u>Message ID : VMD3666E</u> .....	1810
<u>Message ID : VMD3667E</u> .....	1811
<u>Message ID : VMD3674E</u> .....	1811
<u>Message ID : VMD3676E</u> .....	1812
<u>Message ID : VMD3681E</u> .....	1813
<u>Message ID : VMD3683E</u> .....	1813
<u>Message ID : VMD3685E</u> .....	1814

# Table of Contents

## Logger VMD: Errors

<u>Message ID : VMD3686E</u> .....	1815
<u>Message ID : VMD3689E</u> .....	1815
<u>Message ID : VMD3697E</u> .....	1816
<u>Message ID : VMD3700E</u> .....	1817
<u>Message ID : VMD3702E</u> .....	1818
<u>Message ID : VMD3707E</u> .....	1818
<u>Message ID : VMD3713E</u> .....	1819
<u>Message ID : VMD3718E</u> .....	1820
<u>Message ID : VMD3723E</u> .....	1820
<u>Message ID : VMD3724E</u> .....	1821
<u>Message ID : VMD3726E</u> .....	1822
<u>Message ID : VMD3730E</u> .....	1822
<u>Message ID : VMD3734E</u> .....	1823
<u>Message ID : VMD3736E</u> .....	1824
<u>Message ID : VMD3747E</u> .....	1824
<u>Message ID : VMD3748E</u> .....	1825
<u>Message ID : VMD3750E</u> .....	1826
<u>Message ID : VMD3758E</u> .....	1826
<u>Message ID : VMD3759E</u> .....	1827
<u>Message ID : VMD3760E</u> .....	1828
<u>Message ID : VMD3779E</u> .....	1828
<u>Message ID : VMD3780E</u> .....	1829
<u>Message ID : VMD3782E</u> .....	1830
<u>Message ID : VMD3784E</u> .....	1831
<u>Message ID : VMD3786E</u> .....	1832
<u>Message ID : VMD3787E</u> .....	1833



# Table of Contents

## Logger VMD: Errors

<u>Message ID : VMD3788E</u> .....	1834
<u>Message ID : VMD3789E</u> .....	1834
<u>Message ID : VMD3790E</u> .....	1835
<u>Message ID : VMD3792E</u> .....	1836
<u>Message ID : VMD3795E</u> .....	1837
<u>Message ID : VMD3796E</u> .....	1838
<u>Message ID : VMD3799E</u> .....	1839
<u>Message ID : VMD3801E</u> .....	1839
<u>Message ID : VMD3802E</u> .....	1840
<u>Message ID : VMD3807E</u> .....	1841
<u>Message ID : VMD3809E</u> .....	1842
<u>Message ID : VMD3811E</u> .....	1843
<u>Message ID : VMD3812E</u> .....	1844
<u>Message ID : VMD3816E</u> .....	1845
<u>Message ID : VMD3819E</u> .....	1846
<u>Message ID : VMD3822E</u> .....	1846
<u>Message ID : VMD3828E</u> .....	1847
<u>Message ID : VMD3830E</u> .....	1848
<u>Message ID : VMD3831E</u> .....	1849
<u>Message ID : VMD3833E</u> .....	1850
<u>Message ID : VMD3834E</u> .....	1851
<u>Message ID : VMD3835E</u> .....	1852
<u>Message ID : VMD3837E</u> .....	1853
<u>Message ID : VMD3838E</u> .....	1854
<u>Message ID : VMD3840E</u> .....	1855
<u>Message ID : VMD3843E</u> .....	1855

# Table of Contents

## Logger VMD: Errors

<u>Message ID : VMD3844E</u> .....	1856
<u>Message ID : VMD3845E</u> .....	1857
<u>Message ID : VMD3846E</u> .....	1858
<u>Message ID : VMD3848E</u> .....	1859
<u>Message ID : VMD3849E</u> .....	1860
<u>Message ID : VMD3855E</u> .....	1861
<u>Message ID : VMD3858E</u> .....	1862
<u>Message ID : VMD3864E</u> .....	1863
<u>Message ID : VMD3865E</u> .....	1864
<u>Message ID : VMD3866E</u> .....	1865
<u>Message ID : VMD3867E</u> .....	1866
<u>Message ID : VMD3872E</u> .....	1866
<u>Message ID : VMD3873E</u> .....	1867
<u>Message ID : VMD3874E</u> .....	1868
<u>Message ID : VMD3875E</u> .....	1869
<u>Message ID : VMD3876E</u> .....	1870
<u>Message ID : VMD3877E</u> .....	1871
<u>Message ID : VMD3878E</u> .....	1871
<u>Message ID : VMD3879E</u> .....	1872
<u>Message ID : VMD3888E</u> .....	1873
<u>Message ID : VMD3890E</u> .....	1874
<u>Message ID : VMD3891E</u> .....	1875
<u>Message ID : VMD3892E</u> .....	1876
<u>Message ID : VMD3901E</u> .....	1876
<u>Message ID : VMD3903E</u> .....	1877
<u>Message ID : VMD3905E</u> .....	1878

# Table of Contents

## **Logger VMD: Errors**

<u>Message ID : VMD3907E</u> .....	1879
<u>Message ID : VMD3909E</u> .....	1880
<u>Message ID : VMD3911E</u> .....	1881
<u>Message ID : VMD3913E</u> .....	1882
<u>Message ID : VMD3915E</u> .....	1883
<u>Message ID : VMD3916E</u> .....	1884
<u>Message ID : VMD3917E</u> .....	1885
<u>Message ID : VMD3918E</u> .....	1885
<u>Message ID : VMD3922E</u> .....	1886
<u>Message ID : VMD3923E</u> .....	1887
<u>Message ID : VMD4245E</u> .....	1888
<u>Message ID : VMD4594E</u> .....	1889
<u>Message ID : VMD4606E</u> .....	1890
<u>Message ID : VMD4607E</u> .....	1891
<u>Message ID : VMD4608E</u> .....	1892
<u>Message ID : VMD4609E</u> .....	1893
<u>Message ID : VMD4610E</u> .....	1893
<u>Message ID : VMD4612E</u> .....	1894
<u>Message ID : VMD4617E</u> .....	1895

## **Logger VMD: Fatal errors.....1897**

<u>Message ID : VMD3767F</u> .....	1897
<u>Message ID : VMD3768F</u> .....	1898
<u>Message ID : VMD3769F</u> .....	1899
<u>Message ID : VMD3770F</u> .....	1899
<u>Message ID : VMD3771F</u> .....	1901

# Table of Contents

## **Logger VMD: Fatal errors**

<u>Message ID : VMD3772F</u> .....	1902
<u>Message ID : VMD3797F</u> .....	1902
<u>Message ID : VMD3894F</u> .....	1903
<u>Message ID : VMD4595F</u> .....	1904
<u>Message ID : VMD4616F</u> .....	1905

## **Logger VMD: Information.....1907**

<u>Message ID : VMD3201I</u> .....	1907
<u>Message ID : VMD3202I</u> .....	1908
<u>Message ID : VMD3548I</u> .....	1908
<u>Message ID : VMD3558I</u> .....	1909
<u>Message ID : VMD3626I</u> .....	1910
<u>Message ID : VMD3640I</u> .....	1911
<u>Message ID : VMD3663I</u> .....	1912
<u>Message ID : VMD3773I</u> .....	1913
<u>Message ID : VMD3778I</u> .....	1914
<u>Message ID : VMD3781I</u> .....	1914
<u>Message ID : VMD3785I</u> .....	1915
<u>Message ID : VMD3794I</u> .....	1916
<u>Message ID : VMD3798I</u> .....	1917
<u>Message ID : VMD3800I</u> .....	1918
<u>Message ID : VMD3803I</u> .....	1919
<u>Message ID : VMD3804I</u> .....	1919
<u>Message ID : VMD3814I</u> .....	1920
<u>Message ID : VMD3815I</u> .....	1921
<u>Message ID : VMD3817I</u> .....	1922

# Table of Contents

## **Logger VMD: Information**

<u>Message ID : VMD3818I</u> .....	1923
<u>Message ID : VMD3820I</u> .....	1924
<u>Message ID : VMD3821I</u> .....	1925
<u>Message ID : VMD3823I</u> .....	1926
<u>Message ID : VMD3825I</u> .....	1927
<u>Message ID : VMD3827I</u> .....	1928
<u>Message ID : VMD3829I</u> .....	1929
<u>Message ID : VMD3832I</u> .....	1929
<u>Message ID : VMD3836I</u> .....	1930
<u>Message ID : VMD3839I</u> .....	1931
<u>Message ID : VMD3841I</u> .....	1932
<u>Message ID : VMD3842I</u> .....	1933
<u>Message ID : VMD3847I</u> .....	1934
<u>Message ID : VMD3851I</u> .....	1935
<u>Message ID : VMD3852I</u> .....	1936
<u>Message ID : VMD3853I</u> .....	1937
<u>Message ID : VMD3854I</u> .....	1938
<u>Message ID : VMD3856I</u> .....	1939
<u>Message ID : VMD3857I</u> .....	1939
<u>Message ID : VMD3859I</u> .....	1940
<u>Message ID : VMD3861I</u> .....	1941
<u>Message ID : VMD3862I</u> .....	1942
<u>Message ID : VMD3863I</u> .....	1943
<u>Message ID : VMD3868I</u> .....	1944
<u>Message ID : VMD3870I</u> .....	1945
<u>Message ID : VMD3880I</u> .....	1946

# Table of Contents

## **Logger VMD: Information**

<u>Message ID : VMD3881I</u> .....	1947
<u>Message ID : VMD3883I</u> .....	1947
<u>Message ID : VMD3885I</u> .....	1948
<u>Message ID : VMD3886I</u> .....	1950
<u>Message ID : VMD3893I</u> .....	1951
<u>Message ID : VMD3895I</u> .....	1952
<u>Message ID : VMD3896I</u> .....	1952
<u>Message ID : VMD3897I</u> .....	1953
<u>Message ID : VMD3898I</u> .....	1954
<u>Message ID : VMD3900I</u> .....	1955
<u>Message ID : VMD3902I</u> .....	1956
<u>Message ID : VMD3904I</u> .....	1957
<u>Message ID : VMD3906I</u> .....	1958
<u>Message ID : VMD3908I</u> .....	1959
<u>Message ID : VMD3910I</u> .....	1960
<u>Message ID : VMD3912I</u> .....	1961
<u>Message ID : VMD3914I</u> .....	1962
<u>Message ID : VMD3919I</u> .....	1963
<u>Message ID : VMD4246I</u> .....	1964
<u>Message ID : VMD4611I</u> .....	1965
<u>Message ID : VMD4619I</u> .....	1965
<u>Message ID : VMD4620I</u> .....	1966

## **Logger VMD: Warnings.....1968**

<u>Message ID : VMD3714W</u> .....	1968
<u>Message ID : VMD3805W</u> .....	1968

# Table of Contents

## Logger VMD: Warnings

<u>Message ID : VMD3806W</u> .....	1969
<u>Message ID : VMD3813W</u> .....	1970
<u>Message ID : VMD3824W</u> .....	1971
<u>Message ID : VMD3826W</u> .....	1972
<u>Message ID : VMD3850W</u> .....	1973
<u>Message ID : VMD3860W</u> .....	1974
<u>Message ID : VMD3869W</u> .....	1975
<u>Message ID : VMD3871W</u> .....	1975
<u>Message ID : VMD3882W</u> .....	1976
<u>Message ID : VMD3887W</u> .....	1977
<u>Message ID : VMD3889W</u> .....	1978
<u>Message ID : VMD3899W</u> .....	1979
<u>Message ID : VMD3920W</u> .....	1980
<u>Message ID : VMD3921W</u> .....	1981
<u>Message ID : VMD3924W</u> .....	1982
<u>Message ID : VMD4618W</u> .....	1983
<u>Message ID : VMD4621W</u> .....	1984
<u>Message ID : VMD4622W</u> .....	1985
<u>Message ID : VMD4623W</u> .....	1986
<u>Message ID : VMD4624W</u> .....	1987
<u>Message ID : VMD4625W</u> .....	1988
<u>Message ID : VMD4636W</u> .....	1989
<u>Message ID : VMD4639W</u> .....	1990
<u>Message ID : VMD4640W</u> .....	1991

# Table of Contents

<b><u>Logger XFM: Errors</u></b> .....	<b>1993</b>
<u>Message ID : XFM4501E</u> .....	1993
<u>Message ID : XFM4502E</u> .....	1994
<u>Message ID : XFM4504E</u> .....	1994
<u>Message ID : XFM4535E</u> .....	1995
<u>Message ID : XFM4568E</u> .....	1996
<u>Message ID : XFM4589E</u> .....	1997
<u>Message ID : XFM4590E</u> .....	1998
<u>Message ID : XFM4591E</u> .....	1999
<b><u>Logger XFM: Fatal errors</u></b> .....	<b>2000</b>
<u>Message ID : XFM4508F</u> .....	2000
<u>Message ID : XFM4509F</u> .....	2000
<u>Message ID : XFM4518F</u> .....	2001
<u>Message ID : XFM4519F</u> .....	2002
<u>Message ID : XFM4525F</u> .....	2003
<u>Message ID : XFM4532F</u> .....	2004
<u>Message ID : XFM4536F</u> .....	2005
<u>Message ID : XFM4539F</u> .....	2006
<u>Message ID : XFM4540F</u> .....	2006
<u>Message ID : XFM4541F</u> .....	2007
<u>Message ID : XFM4544F</u> .....	2008
<u>Message ID : XFM4546F</u> .....	2009
<u>Message ID : XFM4561F</u> .....	2010
<u>Message ID : XFM4565F</u> .....	2011



# Table of Contents

<b><u>Logger XFM: Information</u></b> .....	<b>2012</b>
<u>Message ID : XFM4507I</u> .....	2012
<u>Message ID : XFM4517I</u> .....	2012
<u>Message ID : XFM4522I</u> .....	2013
<u>Message ID : XFM4526I</u> .....	2014
<u>Message ID : XFM4549I</u> .....	2015
<u>Message ID : XFM4557I</u> .....	2016
<u>Message ID : XFM4559I</u> .....	2017
<b><u>Logger XFM: Warnings</u></b> .....	<b>2018</b>
<u>Message ID : XFM4550W</u> .....	2018

# Logger CA0: Errors

**Message ID : CA00642E**

## Severity

Error

## Long Form

Can not create CA.

## Short Form

can not create CA

## Parameters

No parameters are provided for this message type

## Description

None

**Message ID : CA00643E**

## **Severity**

Error

## **Long Form**

Can not update CA.

## **Short Form**

No short form is provided for this message type

## **Description**

None

**Message ID : CA00644E**

## **Severity**

Error

## **Long Form**

Can not delete CA.

Message ID : CA00643E

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : CA00645E**

## **Severity**

Error

## **Long Form**

Can not get CA.

## **Short Form**

No short form is provided for this message type

## **Description**

None

Message ID : CA00644E

## **Logger CFG: Errors**

**Message ID : CFG0026E**

### **Severity**

Error

### **Long Form**

Internal error. Refer to cgss.log for details.

### **Short Form**

No short form is provided for this message type

### **Description**

None

**Message ID : CFG0027E**

### **Severity**

Error

## **Long Form**

Unable to obtain list of configuration names.

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : CFG0028E**

## **Severity**

Error

## **Long Form**

Unable to update configuration information.

## **Short Form**

No short form is provided for this message type

Message ID : CFG0027E

## **Description**

None

**Message ID : CFG0029E**

## **Severity**

Error

## **Long Form**

Unable to obtain the value for key = {0}.

## **Short Form**

No short form is provided for this message type

## **Description**

None

**Message ID : CFG0030E**

## **Severity**

Error

Message ID : CFG0028E

## **Long Form**

Unable to create loggers.

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : CFG0031E**

## **Severity**

Error

## **Long Form**

Unable to update loggers.

## **Short Form**

No short form is provided for this message type

Message ID : CFG0030E



## **Description**

None

**Message ID : CFG0032E**

## **Severity**

Error

## **Long Form**

Unable to obtain list of default loggers.

## **Short Form**

No short form is provided for this message type

## **Description**

None

**Message ID : CFG0033E**

## **Severity**

Error

Message ID : CFG0031E

## **Long Form**

Unable to delete loggers for host with id = {0}.

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : CFG0034E**

## **Severity**

Error

## **Long Form**

Unable to obtain loggers for host with id = {0}.

## **Short Form**

No short form is provided for this message type

Message ID : CFG0033E

## **Description**

None

**Message ID : CFG0264E**

## **Severity**

Error

## **Long Form**

CGSS Server Name "{0}" is unknown to the Security Server.

## **Short Form**

No short form is provided for this message type

## **Description**

None

**Message ID : CFG0306E**

## **Severity**

Error

Message ID : CFG0034E

## **Long Form**

Internal error. No password policy found, there needs to be one password policy defined. Please contact support.

## **Short Form**

No short form is provided for this message type

## **Description**

None

**Message ID : CFG0333E**

## **Severity**

Error

## **Long Form**

Security Server brand must be either vor or eet.

## **Short Form**

No short form is provided for this message type

Message ID : CFG0306E

## **Description**

None

**Message ID : CFG0334E**

## **Severity**

Error

## **Long Form**

Security Server role must be either primary or failover.

## **Short Form**

No short form is provided for this message type

## **Description**

None

**Message ID : CFG0335E**

## **Severity**

Error

Message ID : CFG0333E

## **Long Form**

Provide true or false for the property {0}.

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : CFG0336E**

## **Severity**

Error

## **Long Form**

Security Server version must be defined.

## **Short Form**

No short form is provided for this message type

Message ID : CFG0335E

## **Description**

None

**Message ID : CFG0339E**

## **Severity**

Error

## **Long Form**

Security Server build number must be defined.

## **Short Form**

No short form is provided for this message type

## **Description**

None

**Message ID : CFG0341E**

## **Severity**

Error

Message ID : CFG0336E

## **Long Form**

Platform is not supported.

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : CFG0520E**

## **Severity**

Error

## **Long Form**

The Security Server was unable to find a partition available for software installation. The software cannot be installed. Please un-install old software and try again.

## **Short Form**

No short form is provided for this message type

Message ID : CFG0341E



## **Description**

None

**Message ID : CFG0521E**

## **Severity**

Error

## **Long Form**

The Security Server was unable to to uncompress the backup file. The software upgrade cannot continue. Please check if you have enough disk space.

## **Short Form**

No short form is provided for this message type

## **Description**

None

**Message ID : CFG0522E**

## **Severity**

Error

## **Long Form**

The Security Server was unable to verify the signature. The software upgrade cannot continue. Please check if the uploaded file is valid.

## **Short Form**

No short form is provided for this message type

## **Description**

None

**Message ID : CFG0523E**

## **Severity**

Error

## **Long Form**

The Security Server was unable to retrieve the public key needed to verify the signature for the software to be installed. The software upgrade cannot continue. Please check if the uploaded file is valid.

Message ID : CFG0522E

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : CFG0524E**

## **Severity**

Error

## **Long Form**

The Security Server was unable to verify the signature. The file is not valid. The software upgrade cannot continue. Please make sure that the file you are downloading for installation is a valid file.

## **Short Form**

No short form is provided for this message type

## **Description**

None

Message ID : CFG0523E

## **Message ID : CFG0527E**

### **Severity**

Error

### **Long Form**

Upgrade target not supported. Retry with higher version/build.

### **Short Form**

No short form is provided for this message type

### **Description**

None

## **Message ID : CFG0528E**

### **Severity**

Error

### **Long Form**

The Security Server is unable to find the current version of the software. Please check the logs.

Message ID : CFG0527E

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : CFG0529E**

## **Severity**

Error

## **Long Form**

The Security Server is unable to install software. The directory is not empty. Please ensure that the directory is empty and try the install again.

## **Short Form**

No short form is provided for this message type

## **Description**

None

Message ID : CFG0528E

## **Message ID : CFG0530E**

### **Severity**

Error

### **Long Form**

The Security Server failed to synchronize the failover server {0} replication.

### **Short Form**

No short form is provided for this message type

### **Description**

None

## **Message ID : CFG0531E**

### **Severity**

Error

### **Long Form**

The Security Server failed to configure the failover server {0} replication.

Message ID : CFG0530E

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : CFG0532E**

## **Severity**

Error

## **Long Form**

The Security Server failed to clean up the failover server {0} replication.

## **Short Form**

No short form is provided for this message type

## **Description**

None

Message ID : CFG0531E

## **Message ID : CFG0636E**

### **Severity**

Error

### **Long Form**

Operation failed. The Security Server is busy, please retry later.

### **Short Form**

No short form is provided for this message type

### **Description**

None

## **Message ID : CFG1334E**

### **Severity**

Error

### **Long Form**

DSM Server Name "{0}" unknown; if there has been a restore, either do a "gencert" or change hostname.

Message ID : CFG0636E



## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : CFG1335E**

## **Severity**

Error

## **Long Form**

{0}

## **Short Form**

No short form is provided for this message type

## **Description**

None

Message ID : CFG1334E

## **Message ID : CFG1352E**

### **Severity**

Error

### **Long Form**

Operation not allowed in Common Criteria mode.

### **Short Form**

No short form is provided for this message type

### **Description**

None

## **Message ID : CFG1367E**

### **Severity**

Error

### **Long Form**

Login banner can not be empty.

Message ID : CFG1352E

## Short Form

No short form is provided for this message type

## Description

None

## Message ID : CFG1368E

## Severity

Error

## Long Form

User "{0}" failed to upgrade system. Reason:{1}

## Short Form

Failed to upgrade system

## Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
showStr	reason	Text	Code specifying reason for allowing access, if any

Message ID : CFG1367E

Label	CEF Label	Type	Usage

## Description

None

**Message ID : CFG1400E**

## Severity

Error

## Long Form

Unable to delete docker loggers for host {0}.

## Short Form

No short form is provided for this message type

## Description

None

Message ID : CFG1368E

## **Message ID : CFG1514E**

### **Severity**

Error

### **Long Form**

Upgrade information not available

### **Short Form**

No short form is provided for this message type

### **Description**

None

## **Message ID : CFG1515E**

### **Severity**

Error

### **Long Form**

System upgrade failed. Please see log files.

Message ID : CFG1514E

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : CFG1517E**

## **Severity**

Error

## **Long Form**

There was an error in getting the system upgrade status from the upgrade log file

## **Short Form**

No short form is provided for this message type

## **Description**

None

Message ID : CFG1515E

## **Message ID : CFG1705E**

### **Severity**

Error

### **Long Form**

Unable to update {0} general configuration for domain.

### **Short Form**

No short form is provided for this message type

### **Description**

None

## **Message ID : CFG1727E**

### **Severity**

Error

### **Long Form**

Log message type is not found.

Message ID : CFG1705E

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : CFG1734E**

## **Severity**

Error

## **Long Form**

HSM key not found. Required HSM partition may be inaccessible or missing registration.

## **Short Form**

No short form is provided for this message type

## **Description**

None

Message ID : CFG1727E



## **Message ID : CFG1735E**

### **Severity**

Error

### **Long Form**

HSM failed.

### **Short Form**

No short form is provided for this message type

### **Description**

None

## **Message ID : CFG1775E**

### **Severity**

Error

### **Long Form**

Field {0} must be required for setting {1}.

Message ID : CFG1735E

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : CFG1776E**

## **Severity**

Error

## **Long Form**

Field {0} must be enabled for setting {1}.

## **Short Form**

No short form is provided for this message type

## **Description**

None

Message ID : CFG1775E

## **Message ID : CFG1777E**

### **Severity**

Error

### **Long Form**

DEBUG level not supported for {0} log destination.

### **Short Form**

No short form is provided for this message type

### **Description**

None

## **Message ID : CFG1778E**

### **Severity**

Error

### **Long Form**

Host does not support {0} so it cannot be enabled or disabled.

Message ID : CFG1777E

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : CFG1827E**

## **Severity**

Error

## **Long Form**

Invalid TLS info for secure syslog server {0}

## **Short Form**

No short form is provided for this message type

## **Description**

None

Message ID : CFG1778E

## **Logger CFG: Fatal errors**

**Message ID : CFG1733F**

### **Severity**

Fatal error

### **Long Form**

Lost connection to network HSM.

### **Short Form**

No short form is provided for this message type

### **Description**

None

**Message ID : CFG1842F**

### **Severity**

Fatal error

## **Long Form**

Unable to recover HSM session. Restarting service!

## **Short Form**

No short form is provided for this message type

## **Description**

None

# Logger CFG: Information

**Message ID : CFG0633I**

## Severity

Information

## Long Form

User "{0}" configured replication for failover server {1}.

## Short Form

failover replication configured

### Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
shost	shost	Text	Source host name

## Description

None

## Message ID : CFG0634I

### Severity

Information

### Long Form

User "{0}" cleaned up replication for failover server {1}.

### Short Form

failover replication cleanup

### Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
shost	shost	Text	Source host name

### Description

None



## **Message ID : CFG1516I**

### **Severity**

Information

### **Long Form**

SUCCESS: System upgrade is complete. Please log in and make a system backup.

### **Short Form**

No short form is provided for this message type

### **Description**

None

## **Message ID : CFG1736I**

### **Severity**

Information

### **Long Form**

"{0}" generated a migration backup.

Message ID : CFG1516I

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : CFG1841I**

## **Severity**

Information

## **Long Form**

SUCCESS: User {0} uploaded {1} to DSM server.

## **Short Form**

No short form is provided for this message type

## **Description**

None

Message ID : CFG1736I

# Logger CFG: Warnings

**Message ID : CFG1297W**

## **Severity**

Warning

## **Long Form**

Skipping KMIP operation. KMIP feature is enabled in the license but KMIP is not set up.

## **Short Form**

The KMIP feature is enabled in the license but KMIP is not set up

## **Parameters**

No parameters are provided for this message type

## **Description**

None

## **Logger CGA: Errors**

**Message ID : CGA2614E**

### **Severity**

Error

### **Long Form**

Syntax error: Domain name '\*' is reserved

### **Short Form**

No short form is provided for this message type

### **Description**

None

**Message ID : CGA2617E**

### **Severity**

Error

## Long Form

[[0]] Set [[1]] used but not defined

## Short Form

No short form is provided for this message type

## Description

None

## Message ID : CGA2618E

## Severity

Error

## Long Form

Failed to import password object

## Short Form

No short form is provided for this message type

Message ID : CGA2617E

## **Description**

None

**Message ID : CGA2619E**

## **Severity**

Error

## **Long Form**

Policy [{0}]: Invalid policy

## **Short Form**

No short form is provided for this message type

## **Description**

None

**Message ID : CGA2620E**

## **Severity**

Error

Message ID : CGA2618E

## **Long Form**

Policy [{0}]: Invalid policy length

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : CGA2621E**

## **Severity**

Error

## **Long Form**

Policy [{0}]: Policy import failed

## **Short Form**

No short form is provided for this message type

Message ID : CGA2620E

## Description

None

**Message ID : CGA2624E**

## Severity

Error

## Long Form

Policy [{0}]: Failed to import Name Identifier

## Short Form

Name import failed

## Parameters

Label	CEF Label	Type	Usage
pol	cs1	Text	Policy name

## Description

None

Message ID : CGA2621E



## **Message ID : CGA2625E**

### **Severity**

Error

### **Long Form**

Failed to import keys

### **Short Form**

Keys import failed

### **Parameters**

No parameters are provided for this message type

### **Description**

None

## **Message ID : CGA2626E**

### **Severity**

Error

Message ID : CGA2625E

## Long Form

Policy [{0}]: Invalid root path

## Short Form

Invalid rootpath

### Parameters

Label	CEF Label	Type	Usage
pol	cs1	Text	Policy name

## Description

None

**Message ID : CGA2627E**

## Severity

Error

## Long Form

Policy [{0}]: Failed to import root path

Message ID : CGA2626E

## Short Form

Import rootpath fail

### Parameters

Label	CEF Label	Type	Usage
pol	cs1	Text	Policy name

## Description

None

## Message ID : CGA2628E

## Severity

Error

## Long Form

Policy [{0}]: [{1}] Set [{2}] not defined

## Short Form

Undefined policy type/set

Message ID : CGA2627E

## Parameters

Label	CEF Label	Type	Usage
pol	cs1	Text	Policy name
oType	vds_oType	Text	Object type in policy rule
oName	vds_oName	Text	Object name in policy rule

## Description

None

## Message ID : CGA2629E

## Severity

Error

## Long Form

Policy [{0}]: Key rule not yet built

## Short Form

Invalid key rule

Message ID : CGA2628E

### Parameters

Label	CEF Label	Type	Usage
pol	cs1	Text	Policy name

### Description

None

**Message ID : CGA2634E**

### Severity

Error

### Long Form

Policy [{0}]: Invalid Rule

### Short Form

Invalid rules object

### Parameters

Label	CEF Label	Type	Usage
pol	cs1	Text	Policy name

Message ID : CGA2629E

Label	CEF Label	Type	Usage

## Description

None

## Message ID : CGA2635E

## Severity

Error

## Long Form

Policy [{0}]: Invalid syntax for key effect [{1}]

## Short Form

Invalid key effect

## Parameters

Label	CEF Label	Type	Usage
pol	cs1	Text	Policy name
act	act	Text	Action being requested or performed

Message ID : CGA2634E

## Description

None

**Message ID : CGA2636E**

## Severity

Error

## Long Form

Policy [{0}]: Invalid name and/or access

## Short Form

Invalid name/access

## Parameters

Label	CEF Label	Type	Usage
pol	cs1	Text	Policy name

## Description

None

Message ID : CGA2635E

## Message ID : CGA2637E

### Severity

Error

### Long Form

Policy [{0}]: Invalid rule syntax: Effect not defined

### Short Form

Undefined effect

### Parameters

Label	CEF Label	Type	Usage
pol	cs1	Text	Policy name

### Description

None

## Message ID : CGA2638E



## Severity

Error

## Long Form

Policy [{0}]: Invalid rule syntax: Action [{1}] not defined

## Short Form

Undefined action

### Parameters

Label	CEF Label	Type	Usage
pol	cs1	Text	Policy name
act	act	Text	Action being requested or performed

## Description

None

## Message ID : CGA2639E

Message ID : CGA2638E

## Severity

Error

## Long Form

Policy [{0}]: Invalid rule syntax: GoTo label [{1}] not defined

## Short Form

Undefined label

### Parameters

Label	CEF Label	Type	Usage
pol	cs1	Text	Policy name
label	vds_label	Text	Label in rule sequence

## Description

None

## Message ID : CGA2645E

Message ID : CGA2639E

## Severity

Error

## Long Form

Policy [{0}]: Recursive GoTo detected at rule number [{1}]

## Short Form

Recursive goto

### Parameters

Label	CEF Label	Type	Usage
pol	cs1	Text	Policy name
ruleNo	vds_ruleNo	Numeric	Index into policy rule set

## Description

None

## Message ID : CGA2648E

Message ID : CGA2645E

## Severity

Error

## Long Form

Policy [{0}]: Invalid GoTo - Missing destination label

## Short Form

Invalid goto

### Parameters

Label	CEF Label	Type	Usage
pol	cs1	Text	Policy name

## Description

None

**Message ID : CGA2649E**

## Severity

Error

Message ID : CGA2648E

## Long Form

Policy [{0}]: Invalid effect syntax [{1}]

## Short Form

Invalid syntax

### Parameters

Label	CEF Label	Type	Usage
pol	cs1	Text	Policy name
act	act	Text	Action being requested or performed

## Description

None

**Message ID : CGA2650E**

## Severity

Error

Message ID : CGA2649E

## Long Form

Policy [{0}]: Invalid action syntax [{1}]

## Short Form

Invalid action

### Parameters

Label	CEF Label	Type	Usage
pol	cs1	Text	Policy name
act	act	Text	Action being requested or performed

## Description

None

**Message ID : CGA2651E**

## Severity

Error

Message ID : CGA2650E

## Long Form

No policy defined for [{}0] set [{}1]

## Short Form

Undefined policy set

### Parameters

Label	CEF Label	Type	Usage
oType	vds_oType	Text	Object type in policy rule
oName	vds_oName	Text	Object name in policy rule

## Description

None

**Message ID : CGA2652E**

## Severity

Error

Message ID : CGA2651E

## Long Form

Policy [{0}]: old and new key rule numbers do not match [old {1}, new {2}]

## Short Form

Mismatched rule numbers

### Parameters

Label	CEF Label	Type	Usage
pol	cs1	Text	Policy name
ruleNo	vds_ruleNo	Numeric	Index into policy rule set
altRuleNo	vds_altRuleNo	Numeric	Alternate rule number

## Description

None

## Message ID : CGA2653E

## Severity

Error

Message ID : CGA2652E



## Long Form

Policy [{0}]: old and new key names do not match [key rule {1}, old {2}, new {3}]

## Short Form

Mismatched key names

### Parameters

Label	CEF Label	Type	Usage
pol	cs1	Text	Policy name
ruleNo	vds_ruleNo	Numeric	Index into policy rule set
key	cs3	Text	Name of key or key pair
altKey	vds_altKey	Text	Name of alternate key for multi-key operations

## Description

None

## Message ID : CGA2654E

## Severity

Error

Message ID : CGA2653E

## Long Form

Policy [{0}]: old and new key resources do not match [key rule {1}]

## Short Form

Mismatched key resource

### Parameters

Label	CEF Label	Type	Usage
pol	cs1	Text	Policy name
ruleNo	vds_ruleNo	Numeric	Index into policy rule set

## Description

None

**Message ID : CGA2655E**

## Severity

Error

Message ID : CGA2654E

## Long Form

Failed to import key [{0}]

## Short Form

Key import failed

### Parameters

Label	CEF Label	Type	Usage
key	cs3	Text	Name of key or key pair

## Description

None

**Message ID : CGA2656E**

## Severity

Error

## Long Form

Failed to find encryption key [%lld]

Message ID : CGA2655E

## Short Form

Encryption key not found

### Parameters

No parameters are provided for this message type

## Description

None

**Message ID : CGA2657E**

## Severity

Error

## Long Form

Failed to validate policy on [{0}], rekey in progress

## Short Form

Policy failure, rekey in progress

Message ID : CGA2656E

### Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

### Description

None

### Message ID : CGA2658E

### Severity

Error

### Long Form

Failed to validate policy on [{0}]

### Short Form

Policy validation failure

### Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Message ID : CGA2657E

Label	CEF Label	Type	Usage

## Description

None

## Message ID : CGA2659E

## Severity

Error

## Long Form

Unsupported key type in policy on [{0}]

## Short Form

Unsupported key type in policy

## Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Message ID : CGA2658E

## Description

None

**Message ID : CGA3003E**

## Severity

Error

## Long Form

EVENT: {0}

## Short Form

Event

## Parameters

Label	CEF Label	Type	Usage
showStr	reason	Text	Code specifying reason for allowing access, if any

## Description

None

Message ID : CGA2659E

## **Message ID : CGA3004E**

### **Severity**

Error

### **Long Form**

An invalid host password was entered

### **Short Form**

Invalid host password

### **Parameters**

No parameters are provided for this message type

### **Description**

None

## **Message ID : CGA3007E**

### **Severity**

Error

Message ID : CGA3004E



## Long Form

NOTUSED

## Short Form

No short form is provided for this message type

## Description

None

## Message ID : CGA3008E

## Severity

Error

## Long Form

Pid [{}] has not been initialized properly in [{}]

## Short Form

Bad caller

Message ID : CGA3007E

## Parameters

Label	CEF Label	Type	Usage
pid	dvcpid	Numeric	Numeric process ID
func	vds_func	Text	A function name

## Description

Internal error; try start/stop of agent or reinstallation of agent.

## Message ID : CGA3009E

## Severity

Error

## Long Form

NOTUSED

## Short Form

No short form is provided for this message type

Message ID : CGA3008E

## Description

An internal error occurred. Please contact Vormetric Support.

## Message ID : CGA3010E

## Severity

Error

## Long Form

Failed to write to file [{0}] in [{1}]

## Short Form

Write fail

## Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file
func	vds_func	Text	A function name

## Description

None

## Message ID : CGA3011E

## Severity

Error

## Long Form

Failed to read file [{{0}}] in [{{1}}]

## Short Form

Read fail

## Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file
func	vds_func	Text	A function name

## **Description**

None

**Message ID : CGA3012E**

## **Severity**

Error

## **Long Form**

NOTUSED

## **Short Form**

No short form is provided for this message type

## **Description**

None

**Message ID : CGA3013E**

## **Severity**

Error

Message ID : CGA3011E

## **Long Form**

NOTUSED

## **Short Form**

No short form is provided for this message type

## **Description**

None

**Message ID : CGA3014E**

## **Severity**

Error

## **Long Form**

NOTUSED

## **Short Form**

No short form is provided for this message type

Message ID : CGA3013E

## Description

None

## Message ID : CGA3015E

## Severity

Error

## Long Form

Bad version [{0}] in configuration

## Short Form

Bad config version

## Parameters

Label	CEF Label	Type	Usage
verno	vds_verno	Numeric	A version number

## Description

None

Message ID : CGA3014E

## **Message ID : CGA3016E**

### **Severity**

Error

### **Long Form**

NOTUSED

### **Short Form**

No short form is provided for this message type

### **Description**

None

## **Message ID : CGA3017E**

### **Severity**

Error

### **Long Form**

Failed to apply new security configuration

Message ID : CGA3016E



## **Short Form**

Security config update failed

### **Parameters**

No parameters are provided for this message type

## **Description**

None

## **Message ID : CGA3018E**

## **Severity**

Error

## **Long Form**

Challenge/Response: An invalid challenge/response was entered

## **Short Form**

Invalid challenge/response

### **Parameters**

No parameters are provided for this message type

### **Description**

None

### **Message ID : CGA3021E**

### **Severity**

Error

### **Long Form**

Challenge/Response: Error processing challenge/response

### **Short Form**

Challenge/Response encryption error

### **Parameters**

No parameters are provided for this message type

Message ID : CGA3018E

## Description

None

**Message ID : CGA3022E**

## Severity

Error

## Long Form

Key Protection: Key integrity check failed in [{0}]

## Short Form

Key integrity check failed

## Parameters

Label	CEF Label	Type	Usage
func	vds_func	Text	A function name

## Description

None

Message ID : CGA3021E

## **Message ID : CGA3023E**

### **Severity**

Error

### **Long Form**

NOTUSED

### **Short Form**

No short form is provided for this message type

### **Description**

None

## **Message ID : CGA3024E**

### **Severity**

Error

### **Long Form**

Key Protection: Extract rkey: Hardware signature has changed

Message ID : CGA3023E

## Short Form

Hardware signature changed

### Parameters

No parameters are provided for this message type

## Description

None

## Message ID : CGA3059E

## Severity

Error

## Long Form

[AUDIT] Process[`{0}`] Pid[`{1}`] Uid[`{2}`] Operation[`{3}`] File[`{4}`] Failure[`{5}`] Effect[PERMIT]

## Short Form

Sysfile modified error

## Parameters

Label	CEF Label	Type	Usage
command	command	Text	Task struct comm field
pid	dvcpid	Numeric	Numeric process ID
uid	suid	Numeric	User id
op_name	op_name	Text	Operation name
filePath	filePath	Text	Full path to file
ecode	cnl	Numeric	An error code

## Description

None

**Message ID : CGA3060E**

## Severity

Error

## Long Form

[ALARM] Process[{0}] Pid[{1}] Uid[{2}] Operation[{3}] File[{4}] Effect[DENIED]

Message ID : CGA3059E

## Short Form

Sysfile protected

### Parameters

Label	CEF Label	Type	Usage
command	command	Text	Task struct comm field
pid	dvcpid	Numeric	Numeric process ID
uid	suid	Numeric	User id
op_name	op_name	Text	Operation name
filePath	filePath	Text	Full path to file

## Description

None

**Message ID : CGA3061E**

## Severity

Error

Message ID : CGA3060E

## Long Form

Key Protection: Encryption/Decryption: Bad arguments in function [{}]

## Short Form

En/Decrypt BadArgs

### Parameters

Label	CEF Label	Type	Usage
func	vds_func	Text	A function name

## Description

None

## Message ID : CGA3062E

## Severity

Error

## Long Form

Key Protection: Private key write: Null key in function [{}]

Message ID : CGA3061E



## Short Form

PrivKeyWrite NullKey

### Parameters

Label	CEF Label	Type	Usage
func	vds_func	Text	A function name

## Description

None

## Message ID : CGA3063E

## Severity

Error

## Long Form

Key Protection: Private key write: Invalid key length in function [{0}]

## Short Form

PrivKeyWrite InvalKeylen

Message ID : CGA3062E

### Parameters

Label	CEF Label	Type	Usage
func	vds_func	Text	A function name

### Description

None

### Message ID : CGA3064E

### Severity

Error

### Long Form

Key Protection: Verify sanity: Bad configuration directory and/or session key arguments in function [{0}]

### Short Form

VrfySan BadArgs

### Parameters

Label	CEF Label	Type	Usage
func	vds_func	Text	A function name

Message ID : CGA3063E

Label	CEF Label	Type	Usage

## Description

None

## Message ID : CGA3065E

## Severity

Error

## Long Form

Key Protection: Verify password: Bad configuration directory and/or password arguments in function [{0}]

## Short Form

VrfyPwd BadArgs

## Parameters

Label	CEF Label	Type	Usage
func	vds_func	Text	A function name

Message ID : CGA3064E

## Description

None

**Message ID : CGA3066E**

## Severity

Error

## Long Form

Key Protection: Get salt: Bad configuration directory argument in function [{0}]

## Short Form

GetSalt BadArg

### Parameters

Label	CEF Label	Type	Usage
func	vds_func	Text	A function name

## Description

None

Message ID : CGA3065E

## Message ID : CGA3067E

### Severity

Error

### Long Form

Key Protection: Shared secret: Bad configuration directory argument in function [{}0]

### Short Form

ShrdSecret BadArg

#### Parameters

Label	CEF Label	Type	Usage
func	vds_func	Text	A function name

### Description

None

## Message ID : CGA3068E

## Severity

Error

## Long Form

Key Protection: Key integrity check: Bad arguments in function [{0}]

## Short Form

KeyIntegChk BadArgs

### Parameters

Label	CEF Label	Type	Usage
func	vds_func	Text	A function name

## Description

None

**Message ID : CGA3069E**

## Severity

Error

Message ID : CGA3068E

## Long Form

Key Protection: Key integrity check: Invalid key length in function [{0}]

## Short Form

KeyIntegChk BadLen

### Parameters

Label	CEF Label	Type	Usage
func	vds_func	Text	A function name

## Description

None

## Message ID : CGA3070E

## Severity

Error

## Long Form

Key Protection: Extract rkey: Bad arguments in function [{0}]

Message ID : CGA3069E

## Short Form

ExtrRkey BadArgs

### Parameters

Label	CEF Label	Type	Usage
func	vds_func	Text	A function name

## Description

None

**Message ID : CGA3071E**

## Severity

Error

## Long Form

Key Protection: Extract rkey: Invalid extraction method in function [{}]

## Short Form

ExtrRkey BadMeth

Message ID : CGA3070E



### Parameters

Label	CEF Label	Type	Usage
func	vds_func	Text	A function name

### Description

None

### Message ID : CGA3072E

### Severity

Error

### Long Form

Key Protection: Policy key update: Bad configuration directory argument in function [{}]

### Short Form

PolKeyUpd BadArg

### Parameters

Label	CEF Label	Type	Usage
func	vds_func	Text	A function name

Message ID : CGA3071E

Label	CEF Label	Type	Usage

## Description

None

## Message ID : CGA3073E

## Severity

Error

## Long Form

Key Protection: Signature update: Bad signature update argument in function [{}]

## Short Form

SigUpd BadArg

## Parameters

Label	CEF Label	Type	Usage
func	vds_func	Text	A function name

Message ID : CGA3072E

## Description

None

**Message ID : CGA3074E**

## Severity

Error

## Long Form

Key Protection: Session key decryption: Bad arguments in function [{}]

## Short Form

SessKeyDcrpt BadArgs

### Parameters

Label	CEF Label	Type	Usage
func	vds_func	Text	A function name

## Description

None

Message ID : CGA3073E

## Message ID : CGA3075E

### Severity

Error

### Long Form

Key Protection: Host password: Invalid argument in function [{}]

### Short Form

HostPwd BadArg

### Parameters

Label	CEF Label	Type	Usage
func	vds_func	Text	A function name

### Description

None

## Message ID : CGA3076E

## Severity

Error

## Long Form

Key Protection: Challenge 256: Invalid argument in function [{}0]

## Short Form

Chlnge256 BadArg

### Parameters

Label	CEF Label	Type	Usage
func	vds_func	Text	A function name

## Description

None

## Message ID : CGA3077E

## Severity

Error

Message ID : CGA3076E

## Long Form

Key Protection: Challenge: Invalid argument in function [{0}]

## Short Form

ChlngeBadArg

### Parameters

Label	CEF Label	Type	Usage
func	vds_func	Text	A function name

## Description

None

## Message ID : CGA3078E

## Severity

Error

## Long Form

Key Protection: Failed to write private key in function [{0}]

Message ID : CGA3077E

## Short Form

PrivKeyWr Fail

### Parameters

Label	CEF Label	Type	Usage
func	vds_func	Text	A function name

## Description

None

**Message ID : CGA3079E**

## Severity

Error

## Long Form

Key Protection: Failed to read private key in function [{0}]

## Short Form

PrivkeyRd Fail

Message ID : CGA3078E

### Parameters

Label	CEF Label	Type	Usage
func	vds_func	Text	A function name

### Description

None

### Message ID : CGA3080E

### Severity

Error

### Long Form

Key Protection: Extract password: Private key unavailable in function [{0}]

### Short Form

ExtrPwd PrivKeyUnavail

### Parameters

Label	CEF Label	Type	Usage
func	vds_func	Text	A function name

Message ID : CGA3079E



Label	CEF Label	Type	Usage

## Description

None

## Message ID : CGA3081E

## Severity

Error

## Long Form

Key Protection: Verify configuration sanity: Private key unavailable in function [{0}]

## Short Form

VrfyConfig: PrivKeyUnavail

## Parameters

Label	CEF Label	Type	Usage
func	vds_func	Text	A function name

Message ID : CGA3080E

## Description

None

**Message ID : CGA3082E**

## Severity

Error

## Long Form

Key Protection: Extract rkey: Private key unavailable in function [{0}]

## Short Form

ExtrRkey PrivKeyUnavail

## Parameters

Label	CEF Label	Type	Usage
func	vds_func	Text	A function name

## Description

None

Message ID : CGA3081E

## Message ID : CGA3083E

### Severity

Error

### Long Form

Key Protection: Extract password: Failed to decrypt using private key in function [{0}]

### Short Form

ExtrPwd PrivKeyDcrpt Fail

### Parameters

Label	CEF Label	Type	Usage
func	vds_func	Text	A function name

### Description

None

## Message ID : CGA3084E

## Severity

Error

## Long Form

Key Protection: Verify configuration sanity: Failed to decrypt using private key in function [{0}]

## Short Form

VrfyCfg PrivKeyDcrpt Fail

### Parameters

Label	CEF Label	Type	Usage
func	vds_func	Text	A function name

## Description

None

**Message ID : CGA3085E**

## Severity

Error

Message ID : CGA3084E

## Long Form

Key Protection: Extract rkey CR256: Failed to decrypt using private key in function [{0}]

## Short Form

ExtrRkey256 PrivKeyDcrpt Fail

### Parameters

Label	CEF Label	Type	Usage
func	vds_func	Text	A function name

## Description

None

## Message ID : CGA3086E

## Severity

Error

## Long Form

Key Protection: Extract rkey: Failed to decrypt using private key in function [{0}]

Message ID : CGA3085E

## Short Form

ExtrRkey PrivKeyDecrypt Fail

### Parameters

Label	CEF Label	Type	Usage
func	vds_func	Text	A function name

## Description

None

## Message ID : CGA3087E

## Severity

Error

## Long Form

Key Protection: Verify configuration sanity: Bad session key in file [{0}], function [{1}] line [{2}]

## Short Form

VrfyCfg BadSessKey

Message ID : CGA3086E

## Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file
func	vds_func	Text	A function name

## Description

None

## Message ID : CGA3088E

## Severity

Error

## Long Form

Key Protection: Verify configuration sanity: Failed HMAX verification in file [{0}], function [{1}] line [{2}]

## Short Form

VrfyCfg FailHMAXVrfy Fail

## Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file
func	vds_func	Text	A function name

## Description

None

## Message ID : CGA3089E

## Severity

Error

## Long Form

Key Protection: Verify configuration sanity: Bad rkey in file [{0}], function [{1}] line [{2}]

## Short Form

VrfyCfg BadRkey



## Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file
func	vds_func	Text	A function name

## Description

None

**Message ID : CGA3090E**

## Severity

Error

## Long Form

Key Protection: File session key decrypt: Failed description in file [{0}] in function [{1}]

## Short Form

FileSessKeyDcrpt Fail

Message ID : CGA3089E

## Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file
func	vds_func	Text	A function name

## Description

None

## Message ID : CGA3091E

## Severity

Error

## Long Form

Key Protection: Extract rkey: Bad password in function [{0}]

## Short Form

ExtrRkey BadPwd

### Parameters

Label	CEF Label	Type	Usage
func	vds_func	Text	A function name

### Description

None

### Message ID : CGA3092E

### Severity

Error

### Long Form

Key Protection: Policy key update: Bad password in function [{0}]

### Short Form

PolKeyUpd BadPwd

### Parameters

Label	CEF Label	Type	Usage
func	vds_func	Text	A function name

Message ID : CGA3091E

Label	CEF Label	Type	Usage

## Description

None

## Message ID : CGA3093E

## Severity

Error

## Long Form

Key Protection: Policy key update: Extract rkey failure in function [{0}]

## Short Form

PolKeyUpd ExtrRkey Fail

## Parameters

Label	CEF Label	Type	Usage
func	vds_func	Text	A function name

Message ID : CGA3092E

## **Description**

None

**Message ID : CGA3094E**

## **Severity**

Error

## **Long Form**

Compare dir key: Failed to get dir

## **Short Form**

CmpDirKey FailGetDir

## **Parameters**

No parameters are provided for this message type

## **Description**

None

Message ID : CGA3093E

## **Message ID : CGA3095E**

### **Severity**

Error

### **Long Form**

Compare dir key: Failed to add keyset

### **Short Form**

CmpDirKey FailAddKeyset

### **Parameters**

No parameters are provided for this message type

### **Description**

None

## **Message ID : CGA3096E**

### **Severity**

Error

Message ID : CGA3095E

## Long Form

Get keyid: Invalid key object in [{0}] at [{1}]

## Short Form

GetKeyid InvalKeyObj

### Parameters

Label	CEF Label	Type	Usage
func	vds_func	Text	A function name

## Description

None

## Message ID : CGA3097E

## Severity

Error

## Long Form

Get keyid: Local key get failed in [{0}] at [{1}]

Message ID : CGA3096E

## Short Form

GetKeyid LclKeyGet Fail

### Parameters

Label	CEF Label	Type	Usage
func	vds_func	Text	A function name

## Description

None

**Message ID : CGA3098E**

## Severity

Error

## Long Form

Policy validation failed

## Short Form

PolVald Fail

Message ID : CGA3097E



### **Parameters**

No parameters are provided for this message type

### **Description**

None

### **Message ID : CGA3099E**

### **Severity**

Error

### **Long Form**

LDT: Failed to start

### **Short Form**

LDT: Fail to start

### **Parameters**

No parameters are provided for this message type

## **Description**

None

**Message ID : CGA3100E**

## **Severity**

Error

## **Long Form**

LDT: Failed to stop

## **Short Form**

LDT: Fail to stop

## **Parameters**

No parameters are provided for this message type

## **Description**

None

Message ID : CGA3099E

## **Message ID : CGA3101E**

### **Severity**

Error

### **Long Form**

LDT: Failed to exit

### **Short Form**

LDT: Fail to exit

### **Parameters**

No parameters are provided for this message type

### **Description**

None

## **Message ID : CGA3102E**

### **Severity**

Error

Message ID : CGA3101E

## Long Form

LDT: Cross guard point key compare failed

## Short Form

LDT: Cross guard point key compare failed

### Parameters

No parameters are provided for this message type

## Description

None

## Message ID : CGA3103E

## Severity

Error

## Long Form

LDT: Not enough disk space for file [{0}], aborting transformation

## Short Form

LDT: Out of disk space

### Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

## Description

None

## Message ID : CGA3109E

## Severity

Error

## Long Form

Not guarding path [{0}] from container [{1}] (Reason: Simulation mode)

## Short Form

IgnrCntnrGrd SimMode

Message ID : CGA3103E

## Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory
dockerid	dockerid	Text	Docker image or container id

## Description

None

## Message ID : CGA3110E

## Severity

Error

## Long Form

Not guarding path [{0}] (Reason: Simulation mode)

## Short Form

IgnrGrd SimMode

### Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

### Description

None

### Message ID : CGA3111E

### Severity

Error

### Long Form

Not guarding path [{0}] from container [{1}] (Reason: Contains symlinks or is malformed)

### Short Form

IgnrCntnrGrd HasSymlnks

### Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

Message ID : CGA3110E

Label	CEF Label	Type	Usage
dockerid	dockerid	Text	Docker image or container id

## Description

None

## Message ID : CGA3112E

## Severity

Error

## Long Form

Not guarding path [{0}] (Reason: Contains symlinks or is malformed)

## Short Form

IgnrGrd HasSymlnks

## Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

Message ID : CGA3111E



## Description

None

**Message ID : CGA3113E**

## Severity

Error

## Long Form

Not guarding path [{0}] from container [{1}] (Reason: Can't guard root)

## Short Form

IgnrCntnrGrd NoRoot

## Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory
dockerid	dockerid	Text	Docker image or container id

Message ID : CGA3112E

## Description

None

**Message ID : CGA3114E**

## Severity

Error

## Long Form

Not guarding path [{0}] (Reason: Can't guard root)

## Short Form

IgnrGrd NoRoot

## Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

## Description

None

Message ID : CGA3113E

## Message ID : CGA3115E

### Severity

Error

### Long Form

Not guarding path [{0}] from container [{1}] (Reason: Path too long)

### Short Form

IgnrCntnrGrd PathLong

### Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory
dockerid	dockerid	Text	Docker image or container id

### Description

None

## Message ID : CGA3116E

### Severity

Error

### Long Form

Not guarding path [{0}] (Reason: Path too long)

### Short Form

IgnrGrd PathLong

### Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

### Description

None

## Message ID : CGA3117E

## Severity

Error

## Long Form

Not guarding path [{0}] from container [{1}] (Reason: AUTOFS, but type is not automount)

## Short Form

IgnrCntnrGrd AUTOFS

### Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory
dockerid	dockerid	Text	Docker image or container id

## Description

None

## Message ID : CGA3118E

## Severity

Error

## Long Form

Not guarding path [{0}] (Reason: AUTOFS, but type is not automount)

## Short Form

IgnrGrd AUTOFS

### Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

## Description

None

## Message ID : CGA3119E

## Severity

Error

Message ID : CGA3118E

## Long Form

Not guarding path [{0}] from container [{1}] (Reason: Not allowed)

## Short Form

IgnrCntnrGrd IsInval

### Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory
dockerid	dockerid	Text	Docker image or container id

## Description

None

**Message ID : CGA3120E**

## Severity

Error

Message ID : CGA3119E

## Long Form

Not guarding path [{0}] (Reason: Not allowed)

## Short Form

IgnrGrd IsInval

### Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

## Description

None

## Message ID : CGA3121E

## Severity

Error

## Long Form

Not guarding path [{0}] from container [{1}] (Reason: Raw device not supported)

Message ID : CGA3120E



## Short Form

IgnrCntnrGrd RawDev

### Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory
dockerid	dockerid	Text	Docker image or container id

## Description

None

**Message ID : CGA3122E**

## Severity

Error

## Long Form

Not guarding path [{0}] (Reason: Raw device not supported)

## Short Form

IgnrGrd RawDev

### Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

## Description

None

## Message ID : CGA3123E

## Severity

Error

## Long Form

Not guarding path [{0}] from container [{1}] (Reason: Unknown)

## Short Form

IgnrCntnrGrd BadFlag

Message ID : CGA3122E

## Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory
dockerid	dockerid	Text	Docker image or container id

## Description

None

**Message ID : CGA3124E**

## Severity

Error

## Long Form

Not guarding path [{0}] (Reason: Unknown)

## Short Form

IgnrCntnrGrd BadFlag

Message ID : CGA3123E

### Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

### Description

None

### Message ID : CGA3125E

### Severity

Error

### Long Form

Not unguarding path [{0}] from container [{1}] (Reason: Unknown)

### Short Form

IgnrCntnrUngrd BadFlag

### Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

Message ID : CGA3124E

Label	CEF Label	Type	Usage
dockerid	dockerid	Text	Docker image or container id

## Description

None

## Message ID : CGA3126E

## Severity

Error

## Long Form

Not unguarding path [{}] (Reason: Unknown)

## Short Form

IgnrUngrd BadFlag

## Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

Message ID : CGA3125E

## Description

None

## Message ID : CGA3127E

## Severity

Error

## Long Form

Not guarding path [{0}] from container [{1}] (Reason: Nested paths not allowed)

## Short Form

BadCntnrGrdPath IsNested

## Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory
dockerid	dockerid	Text	Docker image or container id

## Description

None

**Message ID : CGA3128E**

## Severity

Error

## Long Form

Not guarding path [{0}] (Reason: Nested paths not allowed)

## Short Form

BadGrdPath IsNested

## Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

## Description

None

Message ID : CGA3127E

## Message ID : CGA3129E

### Severity

Error

### Long Form

Not guarding path [{0}] from container [{1}] (Reason: Busy, will continue to retry)

### Short Form

BadCntnrGrdPath IsBusy

### Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory
dockerid	dockerid	Text	Docker image or container id

### Description

None



## Message ID : CGA3130E

### Severity

Error

### Long Form

Not guarding path [{0}] (Reason: Busy, will continue to retry)

### Short Form

BadGrdPath IsBusy

### Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

### Description

None

## Message ID : CGA3131E

## Severity

Error

## Long Form

Not unguarding path [{0}] from container [{1}] (Reason: Busy, will continue to retry)

## Short Form

BadCntnrUngrdPath IsBusy

### Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory
dockerid	dockerid	Text	Docker image or container id

## Description

None

## Message ID : CGA3132E

## Severity

Error

## Long Form

Not unguarding path [{0}] (Reason: Busy, will continue to retry)

## Short Form

BadUngrdPath IsBusy

### Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

## Description

None

## Message ID : CGA3133E

## Severity

Error

Message ID : CGA3132E

## Long Form

Not guarding path [{0}] from container [{1}] (Reason: Does not exist)

## Short Form

BadCntnrGrdPath NotExist

### Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory
dockerid	dockerid	Text	Docker image or container id

## Description

None

**Message ID : CGA3134E**

## Severity

Error

Message ID : CGA3133E

## Long Form

Not guarding path [{0}] (Reason: Does not exist)

## Short Form

BadGrdPath NotExist

### Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

## Description

None

## Message ID : CGA3135E

## Severity

Error

## Long Form

Not unguarding path [{0}] from container [{1}] (Reason: Does not exist)

Message ID : CGA3134E

## Short Form

BadCntnrUngrdPath NotExist

### Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory
dockerid	dockerid	Text	Docker image or container id

## Description

None

**Message ID : CGA3136E**

## Severity

Error

## Long Form

Not unguarding path [{0}] (Reason: Does not exist)

Message ID : CGA3135E

## Short Form

BadUngrdPath NotExist

### Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

## Description

None

## Message ID : CGA3137E

## Severity

Error

## Long Form

Not guarding path [{0}] from container [{1}] (Reason: Already mounted)

## Short Form

BadCntnrGrdPath AlreadyMounted

Message ID : CGA3136E

## Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory
dockerid	dockerid	Text	Docker image or container id

## Description

None

## Message ID : CGA3138E

## Severity

Error

## Long Form

Not guarding path [{0}] (Reason: Already mounted)

## Short Form

BadGrdPath AlreadyMounted



### Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

### Description

None

### Message ID : CGA3139E

### Severity

Error

### Long Form

Not guarding path [{0}] from container [{1}] (Reason: Max guard point limit reached)

### Short Form

BadCntnrGrd MaxGrds

### Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

Message ID : CGA3138E

Label	CEF Label	Type	Usage
dockerid	dockerid	Text	Docker image or container id

## Description

None

## Message ID : CGA3140E

## Severity

Error

## Long Form

Not guarding path [{0}] (Reason: Max guard point limit reached)

## Short Form

BadGrd MaxGrds

## Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

Message ID : CGA3139E

## Description

None

**Message ID : CGA3141E**

## Severity

Error

## Long Form

Not guarding path [{0}] from container [{1}] (Reason: Resource not available)

## Short Form

BadCntnrGrd ResrcUnavail

## Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory
dockerid	dockerid	Text	Docker image or container id

Message ID : CGA3140E

## Description

None

**Message ID : CGA3142E**

## Severity

Error

## Long Form

Not guarding path [{0}] (Reason: Resource not available)

## Short Form

BadGrd ResrcUnavail

## Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

## Description

None

Message ID : CGA3141E

## Message ID : CGA3143E

### Severity

Error

### Long Form

Not guarding path [{0}] from container [{1}] (Reason: Operation timed out, retrying)

### Short Form

BadCntnrGrd TimedOut

### Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory
dockerid	dockerid	Text	Docker image or container id

### Description

None

## Message ID : CGA3144E

### Severity

Error

### Long Form

Not guarding path [{0}] (Reason: Operation timed out, retrying)

### Short Form

BadGrd TimedOut

### Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

### Description

None

## Message ID : CGA3145E

## Severity

Error

## Long Form

Not unguarding path [{0}] from container [{1}] (Reason: Operation timed out, retrying)

## Short Form

BadCntnrUngrd TimedOut

### Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory
dockerid	dockerid	Text	Docker image or container id

## Description

None

## Message ID : CGA3146E

## Severity

Error

## Long Form

Not unguarding path [{0}] (Reason: Operation timed out, retrying)

## Short Form

BadUngrd TimedOut

### Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

## Description

None

## Message ID : CGA3147E

## Severity

Error

Message ID : CGA3146E



## Long Form

Not guarding path [{0}] from container [{1}] (Reason: Invalid guard point)

## Short Form

BadCntnrGrdPath InvalGrdPath

### Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory
dockerid	dockerid	Text	Docker image or container id

## Description

None

**Message ID : CGA3148E**

## Severity

Error

Message ID : CGA3147E

## Long Form

Not guarding path [{0}] (Reason: Invalid guard point)

## Short Form

BadGrdPath InvalGrdPath

### Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

## Description

None

## Message ID : CGA3149E

## Severity

Error

## Long Form

Not guarding path [{0}] from container [{1}] (Reason: Invalid, AUTOFS but type is not automount)

Message ID : CGA3148E

## Short Form

BadCntnrGrdPath AUTOFSNoAuto

### Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory
dockerid	dockerid	Text	Docker image or container id

## Description

None

## Message ID : CGA3150E

## Severity

Error

## Long Form

Not guarding path [{0}] (Reason: Invalid, AUTOFS but type is not automount)

## Short Form

BadGrdPath AUTOFSNoAuto

### Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

## Description

None

## Message ID : CGA3151E

## Severity

Error

## Long Form

Not guarding path [{0}] from container [{1}] (Reason: Partially guarded)

## Short Form

BadCntnrGrd PartialGrd

Message ID : CGA3150E

## Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory
dockerid	dockerid	Text	Docker image or container id

## Description

None

## Message ID : CGA3152E

## Severity

Error

## Long Form

Not guarding path [{0}] (Reason: Partially guarded)

## Short Form

BadGrd PartialGrd

### Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

### Description

None

### Message ID : CGA3153E

### Severity

Error

### Long Form

Not guarding path [{0}] from container [{1}] (Reason: Logical drive or path compressed)

### Short Form

BadCntnrGrd IsCompressed

### Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

Message ID : CGA3152E

Label	CEF Label	Type	Usage
dockerid	dockerid	Text	Docker image or container id

## Description

None

## Message ID : CGA3154E

## Severity

Error

## Long Form

Not guarding path [{0}] (Reason: Logical drive or path compressed)

## Short Form

BadGrd IsCompressed

## Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

## Description

None

**Message ID : CGA3155E**

## Severity

Error

## Long Form

Not guarding path [{0}] from container [{1}] (Reason: Logical drive or path encrypted)

## Short Form

BadCntnrGrd IsEncrypt

## Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory
dockerid	dockerid	Text	Docker image or container id

Message ID : CGA3154E



## Description

None

**Message ID : CGA3156E**

## Severity

Error

## Long Form

Not guarding path [{0}] (Reason: Logical drive or path encrypted)

## Short Form

BadGrd IsEncrypt

## Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

## Description

None

Message ID : CGA3155E

## Message ID : CGA3157E

### Severity

Error

### Long Form

Not guarding path [{0}] from container [{1}] (Reason: System Error/Module not present)

### Short Form

BadCntnrGrd SysError

### Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory
dockerid	dockerid	Text	Docker image or container id

### Description

None

## Message ID : CGA3158E

### Severity

Error

### Long Form

Not guarding path [{0}] (Reason: System Error/Module not present)

### Short Form

BadGrd SysError

### Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

### Description

None

## Message ID : CGA3159E

## Severity

Error

## Long Form

Not unguarding path [{0}] from container [{1}] (Reason: System Error/Module not present)

## Short Form

BadCntnrUngrd SysError

### Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory
dockerid	dockerid	Text	Docker image or container id

## Description

None

## Message ID : CGA3160E

Message ID : CGA3159E

## Severity

Error

## Long Form

Not unguarding path [{0}] (Reason: System Error/Module not present)

## Short Form

BadUngrd SysError

### Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

## Description

None

## Message ID : CGA3161E

## Severity

Error

Message ID : CGA3160E

## Long Form

Not guarding path [{0}] from container [{1}] (Reason: Protected file system is stale)

## Short Form

BadCntnrGrdPath StaleFS

### Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory
dockerid	dockerid	Text	Docker image or container id

## Description

None

**Message ID : CGA3162E**

## Severity

Error

Message ID : CGA3161E

## Long Form

Not guarding path [{0}] (Reason: Protected file system is stale)

## Short Form

BadGrdPath StaleFS

### Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

## Description

None

## Message ID : CGA3163E

## Severity

Error

## Long Form

Not guarding path [{0}] from container [{1}] (Reason: Unsupported filesystem type)

Message ID : CGA3162E

## Short Form

BadCntnrGrdPath FSNotSupp

### Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory
dockerid	dockerid	Text	Docker image or container id

## Description

None

## Message ID : CGA3164E

## Severity

Error

## Long Form

Not guarding path [{0}] (Reason: Unsupported filesystem type)



## Short Form

BadGrdPath FSNotSupp

### Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

## Description

None

## Message ID : CGA3165E

## Severity

Error

## Long Form

Not guarding path [{0}] from container [{1}] (Reason: Guard point has metadata, only Live Data Transform policy allowed)

## Short Form

BadCntnrGrd BadPol

Message ID : CGA3164E

## Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory
dockerid	dockerid	Text	Docker image or container id

## Description

None

## Message ID : CGA3166E

## Severity

Error

## Long Form

Not guarding path [{0}] (Reason: Guard point has metadata, only Live Data Transform policy allowed)

## Short Form

BadGrd BadPol

### Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

### Description

None

### Message ID : CGA3167E

### Severity

Error

### Long Form

Not guarding path [{0}] from container [{1}] (Reason: Filesystem type is not supported with Live Data Transform policy)

### Short Form

BadCntnrGrd BadFS

### Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

Message ID : CGA3166E

Label	CEF Label	Type	Usage
dockerid	dockerid	Text	Docker image or container id

## Description

None

## Message ID : CGA3168E

## Severity

Error

## Long Form

Not guarding path [{0}] (Reason: Filesystem type is not supported with Live Data Transform policy)

## Short Form

BadGrd BadFS

## Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

Message ID : CGA3167E

## Description

None

## Message ID : CGA3169E

## Severity

Error

## Long Form

Not guarding path [{0}] from container [{1}] (Reason: File system not mounted with Extended attribute support)

## Short Form

BadCntnrGrd XattrDisabled

## Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory
dockerid	dockerid	Text	Docker image or container id

## Description

None

## Message ID : CGA3170E

## Severity

Error

## Long Form

Not guarding path [{0}] (Reason: File system not mounted with Extended attribute support)

## Short Form

BadGrd XattrDisabled

## Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

## Description

None

Message ID : CGA3169E

## Message ID : CGA3171E

### Severity

Error

### Long Form

Not guarding path [{0}] from container [{1}] (Reason: Nested mount path not allowed for LDT)

### Short Form

BadCntnrGrd NestMount

### Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory
dockerid	dockerid	Text	Docker image or container id

### Description

None

## Message ID : CGA3172E

### Severity

Error

### Long Form

Not guarding path [{0}] (Reason: Nested mount path not allowed for LDT)

### Short Form

BadGrd NestMount

### Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

### Description

None

## Message ID : CGA3173E



## Severity

Error

## Long Form

Not unguarding path [{0}] from container [{1}] (Reason: LDT metadata removal in progress)

## Short Form

BadCntnrGrd LDTMetadata

### Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory
dockerid	dockerid	Text	Docker image or container id

## Description

None

**Message ID : CGA3174E**

Message ID : CGA3173E

## Severity

Error

## Long Form

Not unguarding path [{0}] (Reason: LDT metadata removal in progress)

## Short Form

BadGrd LDTMetadata

### Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

## Description

None

## Message ID : CGA3175E

## Severity

Error

Message ID : CGA3174E

## Long Form

Not guarding path [{0}] from container [{1}] (Reason: Inactive)

## Short Form

BadCntnrGrd Inactive

### Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory
dockerid	dockerid	Text	Docker image or container id

## Description

None

**Message ID : CGA3176E**

## Severity

Error

Message ID : CGA3175E

## Long Form

Not guarding path [{0}] (Reason: Inactive)

## Short Form

BadGrd Inactive

### Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

## Description

None

## Message ID : CGA3177E

## Severity

Error

## Long Form

Not unguarding path [{0}] from container [{1}] (Reason: Inactive)

Message ID : CGA3176E

## Short Form

BadCntnrUngrd Inactive

### Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory
dockerid	dockerid	Text	Docker image or container id

## Description

None

**Message ID : CGA3178E**

## Severity

Error

## Long Form

Not unguarding path [{0}] (Reason: Inactive)

Message ID : CGA3177E

## Short Form

BadUngrd Inactive

### Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

## Description

None

## Message ID : CGA3179E

## Severity

Error

## Long Form

Not guarding path [{0}] from container [{1}] (Reason: Unknown)

## Short Form

BadCntnrGrd BadFlag

Message ID : CGA3178E

## Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory
dockerid	dockerid	Text	Docker image or container id

## Description

None

## Message ID : CGA3180E

## Severity

Error

## Long Form

Not guarding path [{0}] (Reason: Unknown)

## Short Form

BadGrd BadFlag

### Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

### Description

None

### Message ID : CGA3181E

### Severity

Error

### Long Form

Not unguarding path [{0}] from container [{1}] (Reason: Unknown)

### Short Form

BadCntnrUngrd BadFlag

### Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

Message ID : CGA3180E



Label	CEF Label	Type	Usage
dockerid	dockerid	Text	Docker image or container id

## Description

None

## Message ID : CGA3182E

## Severity

Error

## Long Form

Not unguarding path [{0}] (Reason: Unknown)

## Short Form

BadUngrd BadFlag

## Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

Message ID : CGA3181E

## Description

None

**Message ID : CGA3184E**

## Severity

Error

## Long Form

Failed to guard path [{0}] (Reason: [{1}] file system not supported)

## Short Form

FS NotSupp

## Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

## Description

None

Message ID : CGA3182E

## Message ID : CGA3185E

### Severity

Error

### Long Form

Not guarding path [{0}] (Reason: Can't guard root)

### Short Form

GrdPath IsRoot

### Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

### Description

None

## Message ID : CGA3187E

## Severity

Error

## Long Form

An encryption policy was applied to a folder containing NTFS compressed files, [{0}]. NTFS compressed files are not encrypted

## Short Form

Folder IsCompressed

### Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

## Description

None

## Message ID : CGA3188E

## Severity

Error

Message ID : CGA3187E

## Long Form

An encryption policy was applied to a folder containing NTFS encrypted files, [{0}]. NTFS encrypted files are not encrypted

## Short Form

Folder IsCrypt

### Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

## Description

None

## Message ID : CGA3189E

## Severity

Error

## Long Form

Guard path [{0}]: Guard point has metadata, only Live Data Transform policy allowed

Message ID : CGA3188E

## Short Form

Bad GrdPath Pol

### Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

## Description

None

## Message ID : CGA3190E

## Severity

Error

## Long Form

Guard path [{0}]: Wrong fs type for this guard point

## Short Form

Bad GrdPath FS

Message ID : CGA3189E

### Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

### Description

None

### Message ID : CGA3191E

### Severity

Error

### Long Form

Guard path [{}]: Extended attribute not enabled for guard point

### Short Form

GrdPath XattrDisabled

### Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

Message ID : CGA3190E

Label	CEF Label	Type	Usage

## Description

None

## Message ID : CGA3192E

## Severity

Error

## Long Form

Guard path [{0}]: Nested mount not allowed for Live Data Transform

## Short Form

GrdPath NestMount

## Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

Message ID : CGA3191E



## **Description**

None

**Message ID : CGA3206E**

## **Severity**

Error

## **Long Form**

LDT: failed to encrypt data

## **Short Form**

LDT Crypt Fail

## **Parameters**

No parameters are provided for this message type

## **Description**

None

Message ID : CGA3192E

## Message ID : CGA3212E

### Severity

Error

### Long Form

LDT-ALERT: Error in scanning guardpoint [{0}].

### Short Form

LDT-ALERT: Error in scanning guardpoint

### Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

### Description

None

## Message ID : CGA3218E

## Severity

Error

## Long Form

LDT: Skipping transformation of file [{0}], due to pre-check error.

## Short Form

LDT: Skipping transformation of file, due to pre-check error

### Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

## Description

None

## Message ID : CGA3220E

## Severity

Error

Message ID : CGA3218E

## Long Form

LDT: Error recovering ranges from previous transformation for file [{0}].

## Short Form

LDT: Error recovering ranges from previous transformation for file

### Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

## Description

None

## Message ID : CGA3222E

## Severity

Error

## Long Form

[AUDIT] Process[{0}] Pid[{1}] Uid[{2}] Operation[{3}] File[{4}] ContainerID[{5}] Failure[{6}] Effect[PERMIT]

Message ID : CGA3220E

## Short Form

Sysfile modified error

### Parameters

Label	CEF Label	Type	Usage
command	command	Text	Task struct comm field
pid	dvcpid	Numeric	Numeric process ID
uid	suid	Numeric	User id
op_name	op_name	Text	Operation name
filePath	filePath	Text	Full path to file
cid	cid	Text	Container ID
ecode	cn1	Numeric	An error code

### Description

None

**Message ID : CGA3223E**

### Severity

Error

Message ID : CGA3222E

## Long Form

[ALARM] Process[{0}] Pid[{1}] Uid[{2}] Operation[{3}] File[{4}] ContainerID[{5}] Effect[DENIED]

## Short Form

Sysfile protected

### Parameters

Label	CEF Label	Type	Usage
command	command	Text	Task struct comm field
pid	dvcpid	Numeric	Numeric process ID
uid	suid	Numeric	User id
op_name	op_name	Text	Operation name
filePath	filePath	Text	Full path to file
cid	cid	Text	Container ID

## Description

None

## Message ID : CGA3227E

Message ID : CGA3223E

## Severity

Error

## Long Form

LDT: Error while rekeying guardpoint [{0}]

## Short Form

LDT: Error while rekeying guardpoint

### Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

## Description

None

## Message ID : CGA3228E

## Severity

Error

Message ID : CGA3227E

## Long Form

Ptrace denied on authenticator [{0}] pid [{1}]

## Short Form

Ptrace authenticator denied

### Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file
pid	dvcpid	Numeric	Numeric process ID

## Description

None

**Message ID : CGA3229E**

## Severity

Error

Message ID : CGA3228E



## Long Form

Ptrace denied on protected process [{0}] pid [{1}]

## Short Form

Ptrace protected denied

### Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file
pid	dvcpid	Numeric	Numeric process ID

## Description

None

**Message ID : CGA3230E**

## Severity

Error

Message ID : CGA3229E

## Long Form

LDT: Terminating rekey ON [{0}] due to data corruption

## Short Form

LDT: terminated, corruption

### Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

## Description

None

## Message ID : CGA3232E

### Severity

Error

## Long Form

LDT: Data transformation is aborted on file [{0}]. Error : {1}

Message ID : CGA3230E

## Short Form

LDT: Data transformation is aborted on file

### Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file
ecode	cn1	Numeric	An error code

## Description

None

**Message ID : CGA3233E**

## Severity

Error

## Long Form

LDT: Data transformation is aborted on file [{0}]. Error : {1}. Reason : {2}

## Short Form

LDT: Data transformation is aborted on file

### Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file
ecode	cnl	Numeric	An error code
showStr	reason	Text	Code specifying reason for allowing access, if any

## Description

None

## Message ID : CGA3235E

### Severity

Error

## Long Form

Key Protection: Failed to generate derived key in function [{}]

Message ID : CGA3233E

## Short Form

Generate derived key failed

### Parameters

Label	CEF Label	Type	Usage
func	vds_func	Text	A function name

## Description

None

## Message ID : CGA3236E

## Severity

Error

## Long Form

Key Protection: Encryption error in function [{0}]

## Short Form

Encryption error

Message ID : CGA3235E

### Parameters

Label	CEF Label	Type	Usage
func	vds_func	Text	A function name

### Description

None

### Message ID : CGA3237E

### Severity

Error

### Long Form

Key Protection: Invalid access file in [{0}] at [{1}]

### Short Form

Invalid access file

### Parameters

Label	CEF Label	Type	Usage
func	vds_func	Text	A function name

Message ID : CGA3236E

Label	CEF Label	Type	Usage

## Description

None

## Message ID : CGA3238E

## Severity

Error

## Long Form

Not re-guarding path [{0}] from container [{1}] (Reason: Guard point initialization already in progress)

## Short Form

BadCntnrGrd InProgress

## Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory
dockerid	dockerid	Text	Docker image or container id

Message ID : CGA3237E

## Description

None

**Message ID : CGA3239E**

## Severity

Error

## Long Form

Not re-guarding path [{0}] (Reason: Guard point initialization already in progress)

## Short Form

BadGrd InProgress

## Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

## Description

None

Message ID : CGA3238E



## Message ID : CGA3252E

### Severity

Error

### Long Form

LDT-ALERT: Cannot enable guard point [{0}], LDT initialization failed with error [{1}]

### Short Form

LDT: enable failure

### Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory
ecode	cn1	Numeric	An error code

### Description

None

## **Message ID : CGA3256E**

### **Severity**

Error

### **Long Form**

LDT-ALERT: Error initializing resources, LDT will not be operational.

### **Short Form**

LDT init fail

### **Parameters**

No parameters are provided for this message type

### **Description**

None

## **Message ID : CGA3272E**

### **Severity**

Error

Message ID : CGA3256E

## Long Form

{0} does not have UUID

## Short Form

UUID does not exist

### Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

## Description

None

**Message ID : CGA3274E**

## Severity

Error

## Long Form

Failed to write classification {0} to {1}

Message ID : CGA3272E

## Short Form

Failed to write

### Parameters

Label	CEF Label	Type	Usage
tag	tag	Text	Tag
filePath	filePath	Text	Full path to file

## Description

None

**Message ID : CGA3275E**

## Severity

Error

## Long Form

Data classification transaction {0} failed for operation {1} with {2} : {3}

Message ID : CGA3274E

## Short Form

Classification transaction failed

### Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file
filePath	filePath	Text	Full path to file

## Description

None

**Message ID : CGA3278E**

## Severity

Error

## Long Form

Key Conflict for File [{0}]: key information in LDT metadata does not match with the key specified under policy

## Short Form

Mismatch policy

### Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

## Description

None

**Message ID : CGA3279E**

## Severity

Error

## Long Form

ESG/IDT-ALERT: IO error on header for ESG/IDT-Capable device [{0}]

## Short Form

header IO error

Message ID : CGA3278E

### Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

### Description

None

### Message ID : CGA3280E

### Severity

Error

### Long Form

ESG/IDT-ALERT: Data transformation failure on ESG/IDT-Capable device [{}]

### Short Form

IDT fail

### Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

Message ID : CGA3279E

Label	CEF Label	Type	Usage

## Description

None

## Message ID : CGA3282E

## Severity

Error

## Long Form

ESG/IDT-ALERT: Failed to update new device size on ESG/IDT-Capable device [{0}]

## Short Form

resize fail

## Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory



## Description

None

**Message ID : CGA3284E**

## Severity

Error

## Long Form

LDT: Failed to flag GuardPoint [{0}] for deferred key rotation, error [{1}]

## Short Form

Defer rotate fail

## Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory
ecode	cn1	Numeric	An error code

## Description

None

**Message ID : CGA3289E**

## Severity

Error

## Long Form

Failed to have permission to remediate {0}

## Short Form

Failed to have permission to remediate

## Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

## Description

None

Message ID : CGA3284E

## Message ID : CGA3292E

### Severity

Error

### Long Form

Failed to prepare remediation for {0}

### Short Form

Failed to prepare remediation

### Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

### Description

None

## Message ID : CGA3295E

## Severity

Error

## Long Form

Failed to remediate {0} offline

## Short Form

Failed to remediate offline

### Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

## Description

None

**Message ID : CGA3298E**

## Severity

Error

Message ID : CGA3295E

## Long Form

Failed to commit remediation for {0}

## Short Form

Failed to commit remediation

### Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

## Description

None

**Message ID : CGA3301E**

## Severity

Error

## Long Form

Failed to remediate {0} online

Message ID : CGA3298E

## Short Form

Failed to remediate online

### Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

## Description

None

**Message ID : CGA3304E**

## Severity

Error

## Long Form

ESG-ALERT: Process [{0}] disallowed on ESG device [{1}]

## Short Form

Disallow ESG

Message ID : CGA3301E

## Parameters

Label	CEF Label	Type	Usage
sproc	sproc	Text	Source process
gp	fileId	Text	Guardpoint base directory

## Description

None

## Message ID : CGA3306E

## Severity

Error

## Long Form

LDT: Skipping transformation of file [{}], Unable to retrieve the File Information MD.

## Short Form

LDT: Skipped invalid INF

### Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

### Description

None

### Message ID : CGA3307E

### Severity

Error

### Long Form

LDT: Skipping transformation of file [{}], As failed to validate LDT file MetaData. Please contact support for more information.

### Short Form

LDT: Skipped invalid metadata

### Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Message ID : CGA3306E



Label	CEF Label	Type	Usage

## Description

None

## Message ID : CGA3308E

## Severity

Error

## Long Form

LDT: Skipping transformation of file [{}], Key in the policy doesn't match with the key in the MD. Please contact support for more information.

## Short Form

LDT: Skipped key mismatch

## Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Message ID : CGA3307E

## Description

None

**Message ID : CGA3309E**

## Severity

Error

## Long Form

LDT: Skipping transformation of file [{}],file is being restored or exclusively accessed by the application. Please retrigger the rekey again after application finishes the processing on the file.

## Short Form

LDT: Skipped restore

### Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

## Description

None

Message ID : CGA3308E

## Message ID : CGA3310E

### Severity

Error

### Long Form

LDT: Skipping transformation of file [{}],As failed to remove the read-only attribute of the file. Please retrigger the rekey again after checking the file permissions.

### Short Form

LDT: Skipped read only

#### Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

### Description

None

## **Logger CGA: Information**

**Message ID : CGA2622I**

### **Severity**

Information

### **Long Form**

Access Check Tracing: Invalid policy, use default policy object

### **Short Form**

No short form is provided for this message type

### **Description**

None

**Message ID : CGA2630I**

### **Severity**

Information

## Long Form

Policy [{0}]: Key match file is [{1}]

## Short Form

No short form is provided for this message type

## Description

None

## Message ID : CGA2631I

## Severity

Information

## Long Form

Policy [{0}]: Key match resource domain is [{1}]

## Short Form

No short form is provided for this message type

Message ID : CGA2630I

## **Description**

None

**Message ID : CGA2632I**

## **Severity**

Information

## **Long Form**

Policy [{0}]: Using Key [{1}] of rule number [{2}]

## **Short Form**

No short form is provided for this message type

## **Description**

None

**Message ID : CGA2633I**

## **Severity**

Information

Message ID : CGA2631I

## Long Form

Policy [{0}]: No key rule matched: Using clear key

## Short Form

No short form is provided for this message type

## Description

None

## Message ID : CGA2640I

## Severity

Information

## Long Form

Access check tracing: Policy [{0}]: Proc[{{1}}] Gen[{{2}}] User[{{3}} {{4}} {{5}}] Res[{{6}}]

## Short Form

No short form is provided for this message type

Message ID : CGA2633I

## **Description**

None

**Message ID : CGA2641I**

## **Severity**

Information

## **Long Form**

Access check tracing: Policy [{0}]: Empty rules table

## **Short Form**

No short form is provided for this message type

## **Description**

None

**Message ID : CGA2642I**

## **Severity**

Information

Message ID : CGA2640I



## Long Form

Access check tracing: Policy [{0}]: [{1}] Domain [{2}] matched

## Short Form

No short form is provided for this message type

## Description

None

## Message ID : CGA2643I

## Severity

Information

## Long Form

Access check tracing: Policy [{0}]: Rule number [{1}] matched

## Short Form

No short form is provided for this message type

Message ID : CGA2642I

## Description

None

**Message ID : CGA2644I**

## Severity

Information

## Long Form

Access check tracing: Policy [{0}]: GoTo rule number [{1}]

## Short Form

No short form is provided for this message type

## Description

None

**Message ID : CGA2646I**

## Severity

Information

Message ID : CGA2643I

## Long Form

Access check tracing: Policy [{0}]: No rule matched - default action is [Deny]

## Short Form

No short form is provided for this message type

## Description

None

## Message ID : CGA2647I

## Severity

Information

## Long Form

Access check tracing: Policy [{0}]: Using effect of rule number [{1}]: [{2} {3} {4}]

## Short Form

No short form is provided for this message type

## Description

None

## Message ID : CGA2656I

## Severity

Information

## Long Form

Policy [{0}]: Set [{1}] empty with no [{2}]

## Short Form

Empty policy set

## Parameters

Label	CEF Label	Type	Usage
pol	cs1	Text	Policy name
oType	vds_oType	Text	Object type in policy rule
oName	vds_oName	Text	Object name in policy rule

## Description

None

**Message ID : CGA2657I**

## Severity

Information

## Long Form

Policy: Set [{}] empty with no [{}]

## Short Form

Empty policy set

## Parameters

Label	CEF Label	Type	Usage
oType	vds_oType	Text	Object type in policy rule
oName	vds_oName	Text	Object name in policy rule

## Description

None

**Message ID : CGA3001I**

## Severity

Information

## Long Form

EVENT: {0}

## Short Form

Event

## Parameters

Label	CEF Label	Type	Usage
showStr	reason	Text	Code specifying reason for allowing access, if any

## Description

None

Message ID : CGA2657I

## **Message ID : CGA3005I**

### **Severity**

Information

### **Long Form**

Host password successfully supplied

### **Short Form**

Host password accepted.

### **Parameters**

No parameters are provided for this message type

### **Description**

None

## **Message ID : CGA3006I**

### **Severity**

Information

Message ID : CGA3005I

## **Long Form**

A host password was entered, but was not required

## **Short Form**

Host password not required

### **Parameters**

No parameters are provided for this message type

## **Description**

None

## **Message ID : CGA3019I**

## **Severity**

Information

## **Long Form**

Challenge/Response: Successfully unlocked keys



## **Short Form**

Challenge/Response successful

### **Parameters**

No parameters are provided for this message type

## **Description**

None

## **Message ID : CGA3020I**

## **Severity**

Information

## **Long Form**

Challenge/Response: Challenge/response was entered, but was not required

## **Short Form**

Challenge/Response not required

## Parameters

No parameters are provided for this message type

## Description

None

## Message ID : CGA3058I

## Severity

Information

## Long Form

[AUDIT] Process[**{0}**] Pid[**{1}**] Uid[**{2}**] Operation[**{3}**] File[**{4}**] Effect[PERMIT]

## Short Form

Sysfile modified

## Parameters

Label	CEF Label	Type	Usage
command	command	Text	Task struct comm field
pid	dvcpid	Numeric	Numeric process ID

Message ID : CGA3020I

Label	CEF Label	Type	Usage
uid	suid	Numeric	User id
op_name	op_name	Text	Operation name
filePath	filePath	Text	Full path to file

## Description

None

## Message ID : CGA3105I

## Severity

Information

## Long Form

LDT: Error deleting stale metadata for [{0}]. Delete existing metadata before guarding with a production or data transform policy.

## Short Form

LDT: Error deleting stale metadata

### Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

### Description

None

### Message ID : CGA3183I

### Severity

Information

### Long Form

Successfully unguarded path [{0}]

### Short Form

Ungrd Success

### Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Message ID : CGA3105I

Label	CEF Label	Type	Usage

## Description

None

## Message ID : CGA3186I

## Severity

Information

## Long Form

Successfully configured automount for path [{0}]

## Short Form

Automnt Success

## Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

Message ID : CGA3183I

## Description

None

**Message ID : CGA3193I**

## Severity

Information

## Long Form

Successfully guarded [{0}]

## Short Form

Grd Success

## Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

## Description

None

Message ID : CGA3186I

## Message ID : CGA3194I

### Severity

Information

### Long Form

Successfully guarded [{0}] in simulation mode

### Short Form

SimMode Grd Success

### Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

### Description

None

## Message ID : CGA3195I

## Severity

Information

## Long Form

Successfully guarded [{0}] from container [{1}]

## Short Form

Cntnr Grd Success

### Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory
dockerid	dockerid	Text	Docker image or container id

## Description

None

## Message ID : CGA3196I



## Severity

Information

## Long Form

Successfully guarded [{0}] from container [{1}] in simulation mode

## Short Form

SimMode Cntnr Grd Success

### Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory
dockerid	dockerid	Text	Docker image or container id

## Description

None

## Message ID : CGA3197I

## Severity

Information

## Long Form

[[0]] System lock enabled

## Short Form

System lock enabled

### Parameters

Label	CEF Label	Type	Usage
stime	start	Text	A start time stamp

## Description

None

## Message ID : CGA3198I

## Severity

Information

Message ID : CGA3197I

## Long Form

[[0]] System lock disabled

## Short Form

SysLock Disabled

### Parameters

Label	CEF Label	Type	Usage
stime	start	Text	A start time stamp

## Description

None

**Message ID : CGA3199I**

## Severity

Information

## Long Form

[[0]] FS agent lock enabled

Message ID : CGA3198I

## Short Form

FSAgentLock Enabled

### Parameters

Label	CEF Label	Type	Usage
stime	start	Text	A start time stamp

## Description

None

## Message ID : CGA3200I

## Severity

Information

## Long Form

[[0]] FS agent lock disabled

## Short Form

FSAgentLock Disabled

Message ID : CGA3199I

### Parameters

Label	CEF Label	Type	Usage
stime	start	Text	A start time stamp

### Description

None

### Message ID : CGA3201I

### Severity

Information

### Long Form

[[{0}]] Concise logging enabled

### Short Form

ConsLog Enabled

### Parameters

Label	CEF Label	Type	Usage
stime	start	Text	A start time stamp

Message ID : CGA3200I

Label	CEF Label	Type	Usage

## Description

None

## Message ID : CGA3202I

## Severity

Information

## Long Form

[[0]] Concise logging disabled

## Short Form

ConsLog Disabled

## Parameters

Label	CEF Label	Type	Usage
stime	start	Text	A start time stamp

## Description

None

**Message ID : CGA3203I**

## Severity

Information

## Long Form

Policy [{}] took effect or was modified

## Short Form

Pol Modified

## Parameters

Label	CEF Label	Type	Usage
pol	cs1	Text	Policy name

## Description

None

Message ID : CGA3202I

## Message ID : CGA3204I

### Severity

Information

### Long Form

Successfully unguarded [{0}] from container [{1}]

### Short Form

Cntnr Ungrd Success

#### Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory
dockerid	dockerid	Text	Docker image or container id

### Description

None



## Message ID : CGA3205I

### Severity

Information

### Long Form

Successfully unguarded [{0}]

### Short Form

Ungrd Success

#### Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

### Description

None

## Message ID : CGA3207I

## **Severity**

Information

## **Long Form**

FS Agent lock successful

## **Short Form**

FSAgent Lock Success

### **Parameters**

No parameters are provided for this message type

## **Description**

None

## **Message ID : CGA3208I**

## **Severity**

Information

## Long Form

FS Agent unlock successful

## Short Form

FSAgent Unlock Success

### Parameters

No parameters are provided for this message type

## Description

None

## Message ID : CGA3209I

## Severity

Information

## Long Form

System is now locked

## **Short Form**

System Lock Success

### **Parameters**

No parameters are provided for this message type

## **Description**

None

## **Message ID : CGA3210I**

## **Severity**

Information

## **Long Form**

System is now unlocked

## **Short Form**

System Unlock Success

### **Parameters**

No parameters are provided for this message type

### **Description**

None

### **Message ID : CGA3211I**

### **Severity**

Information

### **Long Form**

McAfee Host Intrusion Prevention is disabled while the system is unlocked

### **Short Form**

HIPS Disabled

### **Parameters**

No parameters are provided for this message type

## Description

None

**Message ID : CGA3213I**

## Severity

Information

## Long Form

LDT: Completed scanning guardpoint [{0}].

## Short Form

LDT: Completed scanning guardpoint

## Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

## Description

None

Message ID : CGA3211I

## Message ID : CGA3214I

### Severity

Information

### Long Form

LDT: Starting transformation for guardpoint [{0}].

### Short Form

LDT: Starting transformation for guardpoint

### Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

### Description

None

## Message ID : CGA3215I

## Severity

Information

## Long Form

LDT: Completed transformation for guardpoint [{}].

## Short Form

LDT: Completed transformation for guardpoint

### Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

## Description

None

## Message ID : CGA3216I

## Severity

Information

Message ID : CGA3215I



## Long Form

LDT: Skipping transformation of passthrough file [{0}].

## Short Form

LDT: Skipping transformation of passthrough file

### Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

## Description

None

## Message ID : CGA3217I

## Severity

Information

## Long Form

LDT: Skipping transformation of read-only file [{0}].

Message ID : CGA3216I

## Short Form

LDT: Skipping transformation of read-only file

### Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

## Description

None

## Message ID : CGA3219I

## Severity

Information

## Long Form

LDT: Starting transformation of file [{0}].

## Short Form

LDT: Starting transformation of file

### Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

### Description

None

### Message ID : CGA3221I

### Severity

Information

### Long Form

[AUDIT] Process[{0}] Pid[{1}] Uid[{2}] Operation[{3}] File[{4}] ContainerID[{5}] Effect[PERMIT]

### Short Form

Sysfile modified

### Parameters

Label	CEF Label	Type	Usage
command	command	Text	Task struct comm field

Message ID : CGA3219I

Label	CEF Label	Type	Usage
pid	dvcpid	Numeric	Numeric process ID
uid	suid	Numeric	User id
op_name	op_name	Text	Operation name
filePath	filePath	Text	Full path to file
cid	cid	Text	Container ID

## Description

None

## Message ID : CGA3224I

## Severity

Information

## Long Form

LDT: Completed transformation of guardpoint [{0}] {1}

## Short Form

LDT: Completed transformation of guardpoint

Message ID : CGA3221I

## Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory
ldt_stats	ldt_stats	Text	LDT statistics

## Description

None

## Message ID : CGA3225I

## Severity

Information

## Long Form

LDT: Skipping transformation of reparse point or link [{0}].

## Short Form

LDT: Skipping transformation of reparse point

### Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

### Description

None

### Message ID : CGA3226I

### Severity

Information

### Long Form

LDT: Scan completed for guardpoint [{0}]. Data statistics for guard point: {1}.

### Short Form

LDT: GP stats:

### Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

Message ID : CGA3225I

Label	CEF Label	Type	Usage
ldt_stats	ldt_stats	Text	LDT statistics

## Description

None

## Message ID : CGA3240I

## Severity

Information

## Long Form

LDT: Skipping transformation of passthrough file [{0}]. The file resides in the boot directory. CTE cannot encrypt boot directory files.

## Short Form

LDT: Skipping passthrough bootdir

## Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Message ID : CGA3226I

Label	CEF Label	Type	Usage

## Description

None

## Message ID : CGA3241I

## Severity

Information

## Long Form

LDT: Skipping transformation of passthrough file [{}]. CTE cannot encrypt these files. They are already encrypted using NTFS encryption or compressed.

## Short Form

LDT: Skipping passthrough encrypted

## Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file



## Description

None

## Message ID : CGA3242I

## Severity

Information

## Long Form

LDT: Skipping transformation of passthrough file [{}]. File is not in a GuardPoint directory.

## Short Form

LDT: Skipping passthrough notfiltered

## Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

## Description

None

Message ID : CGA3241I

## Message ID : CGA3244I

### Severity

Information

### Long Form

Volume [{}0] is being mounted. Guard points on this volume will be protected by Thales CTE

### Short Form

Volume is being mounted

#### Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

### Description

None

## Message ID : CGA3245I

## **Severity**

Information

## **Long Form**

CTE upgrade enabled

## **Short Form**

VTE upgrade enabled

## **Parameters**

No parameters are provided for this message type

## **Description**

None

## **Message ID : CGA3246I**

## **Severity**

Information

## **Long Form**

CTE upgrade disabled

## **Short Form**

VTE upgrade disabled

## **Parameters**

No parameters are provided for this message type

## **Description**

None

**Message ID : CGA3247I**

## **Severity**

Information

## **Long Form**

CTE upgrade canceled

## Short Form

VTE upgrade canceled

### Parameters

No parameters are provided for this message type

## Description

None

## Message ID : CGA3248I

## Severity

Information

## Long Form

CTE upgraded on reboot

## Short Form

VTE upgraded on reboot

### Parameters

No parameters are provided for this message type

### Description

None

### Message ID : CGA3257I

### Severity

Information

### Long Form

LDT: Exclusive access for rekey delayed on inode [%lld].

### Short Form

LDT exclusive delayed

### Parameters

Label	CEF Label	Type	Usage
node	vds_node	Numeric	A node identifier

Message ID : CGA3248I

## Description

None

## Message ID : CGA3258I

## Severity

Information

## Long Form

LDT: Exclusive access for rekey granted after delay on inode [%lld].

## Short Form

LDT exclusive granted

## Parameters

Label	CEF Label	Type	Usage
node	vds_node	Numeric	A node identifier

## Description

None

Message ID : CGA3257I

## Message ID : CGA3269I

### Severity

Information

### Long Form

Key change detected on {0} with Operation [{1}] and classification {2}

### Short Form

Classification key change

#### Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file
tag_op	tag_op	Text	Tag operation
tag	tag	Text	Tag

### Description

None



## Message ID : CGA3270I

### Severity

Information

### Long Form

Operation {0} failed because data classification is not enabled on {1}

### Short Form

Classification not enabled

### Parameters

Label	CEF Label	Type	Usage
tag_op	tag_op	Text	Tag operation
filePath	filePath	Text	Full path to file

### Description

None

## Message ID : CGA3271I

### Severity

Information

### Long Form

Data classification initialization has not been finished for guard point {0}

### Short Form

classification not initialized

### Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

### Description

None

## Message ID : CGA3273I

## Severity

Information

## Long Form

Succeeded to write classification {0} to {1}

## Short Form

Succeeded to write

### Parameters

Label	CEF Label	Type	Usage
tag	tag	Text	Tag
filePath	filePath	Text	Full path to file

## Description

None

**Message ID : CGA3281I**

## Severity

Information

## Long Form

ESG/IDT-INFO: Data transformation complete on ESG/IDT-Capable device [{}]

## Short Form

IDT ok

### Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

## Description

None

## Message ID : CGA3283I

## Severity

Information

Message ID : CGA3281I

## Long Form

LDT: Deferred key rotation on GuardPoint [{0}] until after completion of current transformation

## Short Form

Defer rotate ok

### Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

## Description

None

## Message ID : CGA3287I

## Severity

Information

## Long Form

Acquiring permission to remediate {0}

Message ID : CGA3283I

## Short Form

Acquiring permission to remediate

### Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

## Description

None

**Message ID : CGA3288I**

## Severity

Information

## Long Form

Got permission to remediate {0}

## Short Form

Got permission to remediate

Message ID : CGA3287I

### Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

### Description

None

### Message ID : CGA3290I

### Severity

Information

### Long Form

Preparing to remediate {0}

### Short Form

Preparing to remediate

### Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Message ID : CGA3288I

Label	CEF Label	Type	Usage

## Description

None

## Message ID : CGA3291I

## Severity

Information

## Long Form

Ready to remediate {0}

## Short Form

Ready to remediate

## Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file



## Description

None

**Message ID : CGA3293I**

## Severity

Information

## Long Form

Remediating {0} from {1} to {2} offline

## Short Form

Remediating offline

## Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file
key	cs3	Text	Name of key or key pair
key	cs3	Text	Name of key or key pair

Message ID : CGA3291I

## Description

None

**Message ID : CGA3294I**

## Severity

Information

## Long Form

Remediated {0} from {1} to {2} offline

## Short Form

Remediated offline

## Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file
key	cs3	Text	Name of key or key pair
key	cs3	Text	Name of key or key pair

Message ID : CGA3293I

## Description

None

**Message ID : CGA3296I**

## Severity

Information

## Long Form

Committing remediation for {0}

## Short Form

Committing remediation

## Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

## Description

None

Message ID : CGA3294I

## Message ID : CGA3297I

### Severity

Information

### Long Form

Committed remediation for {0}

### Short Form

Committed remediation

### Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

### Description

None

## Message ID : CGA3299I

## Severity

Information

## Long Form

Remediating {0} from {1} to {2} online

## Short Form

Remediating online

### Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file
key	cs3	Text	Name of key or key pair
key	cs3	Text	Name of key or key pair

## Description

None

**Message ID : CGA3300I**

Message ID : CGA3299I

## Severity

Information

## Long Form

Remediated {0} from {1} to {2} online

## Short Form

Remediated online

### Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file
key	cs3	Text	Name of key or key pair
key	cs3	Text	Name of key or key pair

## Description

None

## Message ID : CGA3305I

Message ID : CGA3300I

## Severity

Information

## Long Form

ESG-INFO: Process [{0}] allowed on ESG device [{1}]

## Short Form

Allow ESG

### Parameters

Label	CEF Label	Type	Usage
sproc	sproc	Text	Source process
gp	fileId	Text	Guardpoint base directory

## Description

None

## **Logger CGA: Warnings**

**Message ID : CGA2615W**

### **Severity**

Warning

### **Long Form**

[[0] {1}]: Sub-domain [{2}] not found

### **Short Form**

No short form is provided for this message type

### **Description**

None

**Message ID : CGA2616W**

### **Severity**

Warning



## Long Form

[[0] {1}]: Undefined sub-domain [{2}]

## Short Form

No short form is provided for this message type

## Description

None

## Message ID : CGA2623W

## Severity

Warning

## Long Form

Policy [[0]]: Rename problem: source [{1}] is encrypted by key [{2}] but destination [{3}] by key [{4}]

## Short Form

Policy rename failed

## Parameters

Label	CEF Label	Type	Usage
pol	cs1	Text	Policy name
oldFilePath	oldFilePath	Text	Previous path to file (for rename and link)
key	cs3	Text	Name of key or key pair
filePath	filePath	Text	Full path to file
altKey	vds_altKey	Text	Name of alternate key for multi-key operations

## Description

None

## Message ID : CGA2901W

## Severity

Warning

## Long Form

Challenge/Response: Challenge/response requested to decrypt keys

## **Short Form**

Challenge/Response requested to decrypt keys

### **Parameters**

No parameters are provided for this message type

## **Description**

None

## **Message ID : CGA3002W**

## **Severity**

Warning

## **Long Form**

EVENT: {0}

## **Short Form**

Event

### Parameters

Label	CEF Label	Type	Usage
showStr	reason	Text	Code specifying reason for allowing access, if any

### Description

None

### Message ID : CGA3104W

### Severity

Warning

### Long Form

LDT: Volume dismounted. Aborting transformation at file [{0}]

### Short Form

LDT: Stopping on dismount

### Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Message ID : CGA3002W

Label	CEF Label	Type	Usage

## Description

None

## Message ID : CGA3106W

## Severity

Warning

## Long Form

LDT: The guard point [{"0}"] does not have a valid transformation policy, there is no new key rule

## Short Form

LDT: no new key rule

## Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

## Description

None

**Message ID : CGA3107W**

## Severity

Warning

## Long Form

LDT: The guard point [{}0] does not have a valid transformation policy, there is no key\_op rule

## Short Form

LDT: no key\_op rule

## Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

## Description

None

Message ID : CGA3106W

## Message ID : CGA3108W

### Severity

Warning

### Long Form

LDT: The guard point [{0}] does not support Live Data Transform, only file operations from the Offline Data Transform process will be allowed

### Short Form

LDT: online rekey not supported

### Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

### Description

None

## Message ID : CGA3231W

## Severity

Warning

## Long Form

Failed to get a HDFS file name for {0}. Check the secfsd.log and the vor-hdfs-stderr.log for more details, and make sure the NameNode is running

## Short Form

Failed to get HDFS file name

### Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

## Description

None

**Message ID : CGA3243W**

## Severity

Warning

Message ID : CGA3231W



## Long Form

Volume [{}] is getting dismounted. Guard Points on this volume will not be protected by Thales CTE

## Short Form

Volume is getting dismounted

### Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

## Description

None

## Message ID : CGA3265W

## Severity

Warning

## Long Form

FSADM-ALERT: ESG/IDT required Signature Set for system utilities may have to be resigned {}

Message ID : CGA3243W

## Short Form

FSADM-ALERT: Resigning of file system binaries is required

### Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

## Description

None

## Message ID : CGA3276W

## Severity

Warning

## Long Form

Denied access to {0}{1} during classification initialization

## Short Form

File access denied during initialization

Message ID : CGA3265W

## Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file
filePath	filePath	Text	Full path to file

## Description

None

## Message ID : CGA3285W

## Severity

Warning

## Long Form

Denied access to data classification internal file {0}{1}

## Short Form

Internal file access denied

## Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file
filePath	filePath	Text	Full path to file

## Description

None

## Message ID : CGA3286W

## Severity

Warning

## Long Form

Denied access to {0}{1} during data remediation

## Short Form

File access denied during remediation

## Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file
filePath	filePath	Text	Full path to file

## Description

None

# Logger CGP: Errors

Message ID : CGP2602E

## Severity

Error

## Long Form

{0} Policy[{{1}}] User[{{2}}] Process[{{3}}] Action[{{4}}] Res[{{5}}{6}] Key[{{7}}] Effect[{{8}} {9}]

## Short Form

Reject access

### Parameters

Label	CEF Label	Type	Usage
cat	cat	Text	Event Category (e.g. AUDIT, TRACE)
pol	cs1	Text	Policy name
user	suser	Text	User name
sproc	sproc	Text	Source process
act	act	Text	Action being requested or performed

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory
filePath	filePath	Text	Full path to file
key	cs3	Text	Name of key or key pair
denyStr	msg	Text	Code specifying reason for denying access, if any
showStr	reason	Text	Code specifying reason for allowing access, if any

## Description

A GuardPoint policy has blocked access to encrypted data. The reason for blocking the attempt is provided in the message fields.

## Message ID : CGP2604E

### Severity

Error

### Long Form

{0} Policy[{1}] User[{2}] Process[{3}] Action[{4}] Res[{5}{6}] {7} Effect[{8} {9}]

### Short Form

Reject access

## Parameters

Label	CEF Label	Type	Usage
cat	cat	Text	Event Category (e.g. AUDIT, TRACE)
pol	cs1	Text	Policy name
user	suser	Text	User name
sproc	sproc	Text	Source process
act	act	Text	Action being requested or performed
gp	fileId	Text	Guardpoint base directory
filePath	filePath	Text	Full path to file
denyStr	msg	Text	Code specifying reason for denying access, if any
showStr	reason	Text	Code specifying reason for allowing access, if any

## Description

A GuardPoint policy has blocked access to encrypted data. The reason for blocking the attempt is provided in the message fields.

## Message ID : CGP2606E

## Severity

Error

Message ID : CGP2604E



## Long Form

{0} Policy[{1}] User[{2}] Process[{3}] Action[{4}] Res[{5}{6}] Effect[{7} {8}]

## Short Form

Reject node

### Parameters

Label	CEF Label	Type	Usage
cat	cat	Text	Event Category (e.g. AUDIT, TRACE)
pol	cs1	Text	Policy name
user	suser	Text	User name
sproc	sproc	Text	Source process
act	act	Text	Action being requested or performed
gp	fileId	Text	Guardpoint base directory
filePath	filePath	Text	Full path to file
denyStr	msg	Text	Code specifying reason for denying access, if any
showStr	reason	Text	Code specifying reason for allowing access, if any

## Description

A GuardPoint policy has blocked access to encrypted data. The reason for blocking the attempt is provided in the message fields.

## Message ID : CGP2608E

## Severity

Error

## Long Form

{0} Policy[{{1}}] User[{{2}}] Process[{{3}}] Action[{{4}}] Res[{{5}}]{{6}} [{{7}}]{{8}} Effect[{{9}}] {{10}}

## Short Form

Reject link

## Parameters

Label	CEF Label	Type	Usage
cat	cat	Text	Event Category (e.g. AUDIT, TRACE)
pol	cs1	Text	Policy name
user	suser	Text	User name
sproc	sproc	Text	Source process

Label	CEF Label	Type	Usage
act	act	Text	Action being requested or performed
gp	fileId	Text	Guardpoint base directory
oldFilePath	oldFilePath	Text	Previous path to file (for rename and link)
filePath	filePath	Text	Full path to file
denyStr	msg	Text	Code specifying reason for denying access, if any
showStr	reason	Text	Code specifying reason for allowing access, if any

## Description

None

## Message ID : CGP2610E

## Severity

Error

## Long Form

{0} Policy[{1}] User[{2}] Process[{3}] Action[{4}] Res[{5}{6}] [{7}{8}] Effect[{9} {10}]

## Short Form

Reject rename

### Parameters

Label	CEF Label	Type	Usage
cat	cat	Text	Event Category (e.g. AUDIT, TRACE)
pol	cs1	Text	Policy name
user	suser	Text	User name
sproc	sproc	Text	Source process
act	act	Text	Action being requested or performed
gp	fileId	Text	Guardpoint base directory
oldFilePath	oldFilePath	Text	Previous path to file (for rename and link)
filePath	filePath	Text	Full path to file
denyStr	msg	Text	Code specifying reason for denying access, if any
showStr	reason	Text	Code specifying reason for allowing access, if any

## Description

None

# Logger CGP: Information

Message ID : CGP2601I

## Severity

Information

## Long Form

{0} Policy[{{1}}] User[{{2}}] Process[{{3}}] Action[{{4}}] Res[{{5}}{6}] Key[{{7}}] Effect[{{8}} {9}]

## Short Form

Audit access

### Parameters

Label	CEF Label	Type	Usage
cat	cat	Text	Event Category (e.g. AUDIT, TRACE)
pol	cs1	Text	Policy name
user	suser	Text	User name
sproc	sproc	Text	Source process
act	act	Text	Action being requested or performed

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory
filePath	filePath	Text	Full path to file
key	cs3	Text	Name of key or key pair
denyStr	msg	Text	Code specifying reason for denying access, if any
showStr	reason	Text	Code specifying reason for allowing access, if any

## Description

None

## Message ID : CGP2603I

## Severity

Information

## Long Form

{0} Policy[{1}] User[{2}] Process[{3}] Action[{4}] Res[{5}{6}] {7} Effect[{8} {9}]

## Short Form

Audit access

Message ID : CGP2601I

## Parameters

Label	CEF Label	Type	Usage
cat	cat	Text	Event Category (e.g. AUDIT, TRACE)
pol	cs1	Text	Policy name
user	suser	Text	User name
sproc	sproc	Text	Source process
act	act	Text	Action being requested or performed
gp	fileId	Text	Guardpoint base directory
filePath	filePath	Text	Full path to file
denyStr	msg	Text	Code specifying reason for denying access, if any
showStr	reason	Text	Code specifying reason for allowing access, if any

## Description

None

## Message ID : CGP2605I

## Severity

Information

Message ID : CGP2603I

## Long Form

{0} Policy[{1}] User[{2}] Process[{3}] Action[{4}] Res[{5}{6}] Effect[{7} {8}]

## Short Form

Audit node

### Parameters

Label	CEF Label	Type	Usage
cat	cat	Text	Event Category (e.g. AUDIT, TRACE)
pol	cs1	Text	Policy name
user	suser	Text	User name
sproc	sproc	Text	Source process
act	act	Text	Action being requested or performed
gp	fileId	Text	Guardpoint base directory
filePath	filePath	Text	Full path to file
denyStr	msg	Text	Code specifying reason for denying access, if any
showStr	reason	Text	Code specifying reason for allowing access, if any



## Description

None

## Message ID : CGP2607I

## Severity

Information

## Long Form

{0} Policy[{{1}}] User[{{2}}] Process[{{3}}] Action[{{4}}] Res[{{5}}{6}] [{{7}}{8}] Effect[{{9}} {10}]

## Short Form

Audit link

## Parameters

Label	CEF Label	Type	Usage
cat	cat	Text	Event Category (e.g. AUDIT, TRACE)
pol	cs1	Text	Policy name
user	suser	Text	User name
sproc	sproc	Text	Source process

Label	CEF Label	Type	Usage
act	act	Text	Action being requested or performed
gp	fileId	Text	Guardpoint base directory
oldFilePath	oldFilePath	Text	Previous path to file (for rename and link)
filePath	filePath	Text	Full path to file
denyStr	msg	Text	Code specifying reason for denying access, if any
showStr	reason	Text	Code specifying reason for allowing access, if any

## Description

None

## Message ID : CGP2609I

## Severity

Information

## Long Form

{0} Policy[{1}] User[{2}] Process[{3}] Action[{4}] Res[{5}{6}] [{7}{8}] Effect[{9} {10}]

## Short Form

Audit rename

### Parameters

Label	CEF Label	Type	Usage
cat	cat	Text	Event Category (e.g. AUDIT, TRACE)
pol	cs1	Text	Policy name
user	suser	Text	User name
sproc	sproc	Text	Source process
act	act	Text	Action being requested or performed
gp	fileId	Text	Guardpoint base directory
oldFilePath	oldFilePath	Text	Previous path to file (for rename and link)
filePath	filePath	Text	Full path to file
denyStr	msg	Text	Code specifying reason for denying access, if any
showStr	reason	Text	Code specifying reason for allowing access, if any

## Description

None

# Logger CGS: Errors

**Message ID : CGS2613E**

## Severity

Error

## Long Form

Memory allocation failed in [{}] at line [{}]

## Short Form

Out of memory

## Parameters

No parameters are provided for this message type

## Description

None

**Message ID : CGS3025E**

## Severity

Error

## Long Form

LDT: Unable to remove LDT extended attribute on guard point [{0}]. Error: [{1}]

## Short Form

Extended attr delete

### Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file
showStr	reason	Text	Code specifying reason for allowing access, if any

## Description

None

## Message ID : CGS3026E

## Severity

Error

## Long Form

LDT-ALERT: QoS failed to start

## Short Form

QoS failed to start

## Parameters

No parameters are provided for this message type

## Description

None

**Message ID : CGS3027E**

## Severity

Error

## Long Form

LDT-ALERT: Failed to launch transformation on [{}]

## Short Form

LDT: launch failure

### Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

## Description

None

## Message ID : CGS3028E

## Severity

Error

## Long Form

LDT: Encryption key for file [{}] unavailable for LDT, possibly due to loss of communication to DSM

Message ID : CGS3027E

## Short Form

LDT: Key unavailable

### Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

## Description

None

## Message ID : CGS3031E

### Severity

Error

## Long Form

LDT: Rekey failed for file [{0}] on guard point [{1}]. Error {2}

## Short Form

LDT: failed

Message ID : CGS3028E



## Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file
gp	fileId	Text	Guardpoint base directory
ecode	cn1	Numeric	An error code

## Description

None

## Message ID : CGS3032E

## Severity

Error

## Long Form

LDT-ALERT: Key rotation failed on guard point [{}]

## Short Form

LDT: Key rotation failed

Message ID : CGS3031E

### Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

### Description

None

### Message ID : CGS3033E

### Severity

Error

### Long Form

LDT-ALERT: Failed to update LDT attribute on guard point [{{0}}]. Error: [{{1}}]

### Short Form

LDT: Key rotation failure, EA

### Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Message ID : CGS3032E

Label	CEF Label	Type	Usage
ecode	cn1	Numeric	An error code

## Description

None

## Message ID : CGS3034E

## Severity

Error

## Long Form

LDT-ALERT: Failed to suspend rekey on guard point [{0}]

## Short Form

LDT: suspend failure

## Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

Message ID : CGS3033E

## **Description**

None

**Message ID : CGS3035E**

## **Severity**

Error

## **Long Form**

LDT: Failed to suspend rekey on all guard points

## **Short Form**

LDT: suspend failure: all

## **Parameters**

No parameters are provided for this message type

## **Description**

None

Message ID : CGS3034E

## Message ID : CGS3038E

### Severity

Error

### Long Form

LDT-ALERT: Failed to resume rekey on guard point [{0}]

### Short Form

LDT: resume failure

### Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

### Description

None

## Message ID : CGS3039E

## **Severity**

Error

## **Long Form**

LDT-ALERT: Failed to resume rekey on all guard points

## **Short Form**

LDT: resume failure: all

### **Parameters**

No parameters are provided for this message type

## **Description**

None

**Message ID : CGS3042E**

## **Severity**

Error

## Long Form

LDT: Skipped LDT recovery on read-only file system [{0}]

## Short Form

Skipped LDT recovery: ROFS

### Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

## Description

None

## Message ID : CGS3043E

## Severity

Error

## Long Form

LDT-ALERT: MDS file [{0}] exceeded diskspace quota on gp [{1}]

Message ID : CGS3042E

## Short Form

MDS ENOSPC

### Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file
gp	fileId	Text	Guardpoint base directory

## Description

None

**Message ID : CGS3044E**

## Severity

Error

## Long Form

LDT: Insufficient memory condition encountered during LDT on guard point [{0}]

Message ID : CGS3043E



## Short Form

MDS ENOMEM

### Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

## Description

None

## Message ID : CGS3045E

## Severity

Error

## Long Form

LDT-ALERT: Failed to update LDT attribute

## Short Form

LDT: xattr failure

Message ID : CGS3044E

## Parameters

No parameters are provided for this message type

## Description

None

## Message ID : CGS3047E

## Severity

Error

## Long Form

LDT-ALERT: Aborting rekey of file [{}] due to insufficient disk space

## Short Form

LDT:SFS ENOSPC

## Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Message ID : CGS3045E

## Description

None

**Message ID : CGS3048E**

## Severity

Error

## Long Form

LDT: Aborting rekey of file [{}] due to lack of free memory. Try closing other applications to resolve the issue

## Short Form

LDT:SFS ENOMEM

## Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

## Description

None

Message ID : CGS3047E

## Message ID : CGS3049E

### Severity

Error

### Long Form

LDT-ALERT: Skipped key rotation on guard point [{0}]. It is on a read-only file system

### Short Form

LDT: Skipped ROFS

### Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

### Description

None

## Message ID : CGS3050E

## Severity

Error

## Long Form

LDT-ALERT: Skipped key rotation on guard point [{0}] due to insufficient disk space

## Short Form

LDT: Skipped ENOSPC

### Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

## Description

None

## Message ID : CGS3051E

## Severity

Error

Message ID : CGS3050E

## Long Form

LDT-ALERT: Failed to rotate key on guard point [{0}]. Another rekey operation is already in progress

## Short Form

LDT: Skipped EBUSY

### Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

## Description

None

## Message ID : CGS3052E

## Severity

Error

## Long Form

LDT-ALERT: Skipped key rotation on guard point [{0}]. Error: [{1}]

Message ID : CGS3051E

## Short Form

LDT: Skipped, error

### Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory
ecode	cn1	Numeric	An error code

## Description

None

## Message ID : CGS3053E

### Severity

Error

## Long Form

LDT-ALERT: Failed to rotate key on guard point [{0}] during pre-commit

## Short Form

LDT: pre-commit failed

### Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

## Description

None

## Message ID : CGS3054E

## Severity

Error

## Long Form

LDT-ALERT: Failed to rotate key on guard point [{0}] during commit

## Short Form

LDT: commit failed

Message ID : CGS3053E



### Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

### Description

None

### Message ID : CGS3055E

### Severity

Error

### Long Form

LDT: Failed to abort key rotation on guard point [{0}]

### Short Form

LDT: abort failed

### Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

Message ID : CGS3054E

Label	CEF Label	Type	Usage

## Description

None

## Message ID : CGS3057E

## Severity

Error

## Long Form

LDT: Extended attribute of inode [%lld] is corrupted under guard point [{0}]

## Short Form

LDT: xattr corrupted

## Parameters

Label	CEF Label	Type	Usage
node	vds_node	Numeric	A node identifier
gp	fileId	Text	Guardpoint base directory

Message ID : CGS3055E

## Description

None

**Message ID : CGS3234E**

## Severity

Error

## Long Form

LDT: Rekey failed for file [{0}] on guard point [{1}]. Error {2}. Reason :{3}

## Short Form

LDT: failed

## Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file
gp	fileId	Text	Guardpoint base directory
ecode	cn1	Numeric	An error code
showStr	reason	Text	Code specifying reason for allowing access, if any

Message ID : CGS3057E

## Description

None

## Message ID : CGS3253E

## Severity

Error

## Long Form

LDT: Extended attribute of inode [%lld] is missing under guard point [{0}]

## Short Form

LDT: xattr missing

## Parameters

Label	CEF Label	Type	Usage
node	vds_node	Numeric	A node identifier
gp	fileId	Text	Guardpoint base directory

## Description

None

**Message ID : CGS3259E**

## Severity

Error

## Long Form

IV of file [{0}] is corrupted

## Short Form

file IV corrupted

## Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

## Description

None

Message ID : CGS3253E

## Message ID : CGS3260E

### Severity

Error

### Long Form

IV of file [{0}] is mismatched(file may be restored to wrong fs)

### Short Form

file IV mismatched

### Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

### Description

None

## Message ID : CGS3261E

## Severity

Error

## Long Form

LDT-ALERT: failed to rekey segment [{0}] of [{1}]. Error: [{2}]

## Short Form

LDT: failure to rekey segment

### Parameters

Label	CEF Label	Type	Usage
segID	vds_segID	Numeric	Segment ID
filePath	filePath	Text	Full path to file
ecode	cn1	Numeric	An error code

## Description

None

**Message ID : CGS3262E**

Message ID : CGS3261E

## Severity

Error

## Long Form

LDT-ALERT: Skipped rekeying [{0}] on guard point [{1}]. Error: [{2}]

## Short Form

LDT: skipped rekey on file

### Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file
gp	fileId	Text	Guardpoint base directory
ecode	cn1	Numeric	An error code

## Description

None

## Message ID : CGS3263E

Message ID : CGS3262E



## Severity

Error

## Long Form

LDT-ALERT: LDT recovery failure on guard point [{0}]. Error: [{1}]

## Short Form

LDT-ALERT: LDT recovery failure

### Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory
ecode	cn1	Numeric	An error code

## Description

None

## Message ID : CGS3264E

## Severity

Error

## Long Form

LDT-ALERT: Restore of LDT protected file [{0}] not allowed by policy.

## Short Form

LDT-ALERT: LDT restore denied

### Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

## Description

None

## Message ID : CGS3266E

## Severity

Error

Message ID : CGS3264E

## Long Form

LDT-ALERT: Cannot enable guard point [{0}] due to inconsistencies in underlying file system encountered during LDT recovery.

## Short Form

LDT-ALERT: LDT recovery failure

### Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

## Description

None

## Message ID : CGS3304E

## Severity

Error

## Long Form

IDT-TD-ALERT: Node {0} did not respond to pcl command

Message ID : CGS3266E

## Short Form

IDT-TD-ALERT: Remote node did not respond to pcl

### Parameters

Label	CEF Label	Type	Usage
shost	shost	Text	Source host name

## Description

None

## Message ID : CGS3305E

## Severity

Error

## Long Form

IDT-TD-ALERT: Node {0} failed to perform voradmin task

## Short Form

IDT-TD-ALERT: voradmin failed on remote node

Message ID : CGS3304E

### Parameters

Label	CEF Label	Type	Usage
shost	shost	Text	Source host name

### Description

None

**Message ID : CGS3306E**

### Severity

Error

### Long Form

IDT-TD-ALERT: Failed to find clique for disk {0}

### Short Form

IDT-TD-ALERT: Failed to find clique

### Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

Message ID : CGS3305E

Label	CEF Label	Type	Usage

## Description

None

## Message ID : CGS3307E

## Severity

Error

## Long Form

IDT-TD-ALERT: Failed to distribute IDT-Capable metadata file to remote nodes

## Short Form

IDT-TD-ALERT: Failed to distribute IDT-Capable metadata

## Parameters

No parameters are provided for this message type

## Description

None

Message ID : CGS3306E

## **Message ID : CGS3308E**

### **Severity**

Error

### **Long Form**

IDT-TD-ALERT: Failed to move or rename IDT-Capable metadata file on remote nodes

### **Short Form**

IDT-TD-ALERT: Failed to move or rename IDT-Capable metadata

### **Parameters**

No parameters are provided for this message type

### **Description**

None

## **Message ID : CGS3309E**

### **Severity**

Error

## Long Form

IDT-TD-ALERT: Failed to get GuardPoint status on remote nodes

## Short Form

IDT-TD-ALERT: Failed to get GuardPoint status

### Parameters

No parameters are provided for this message type

## Description

None

## Message ID : CGS3311E

## Severity

Error

## Long Form

IDT-TD-ALERT: Failed to complete rekey on remote nodes



## Short Form

IDT-TD-ALERT: Failed to complete rekey

### Parameters

No parameters are provided for this message type

## Description

None

## Message ID : CGS3312E

## Severity

Error

## Long Form

LDT-NFS-ALERT: Host waiting to take over NFS GuardPoint {0} for LDT

## Short Form

Waiting to take over

### Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

### Description

None

### Message ID : CGS3313E

### Severity

Error

### Long Form

LDT-ALERT: Cannot enable GuardPoint due to wrong policy applied to {{0}}

### Short Form

Incorrect policy

### Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

Message ID : CGS3312E

Label	CEF Label	Type	Usage

## Description

None

## Message ID : CGS3314E

## Severity

Error

## Long Form

LDT: Cannot enable [{0}] due to stale policy

## Short Form

LDT: stale policy

## Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

## Description

None

**Message ID : CGS3315E**

## Severity

Error

## Long Form

LDT-NFS-ALERT: Cannot enable GuardPoint [{0}] on a read-only file system

## Short Form

LDT-NFS: Guarding ROFS

## Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

## Description

None

Message ID : CGS3314E

## Message ID : CGS3316E

### Severity

Error

### Long Form

LDT-ALERT: Failed to process directory rename for {0}, error {1}

### Short Form

LDT: dir rename failed

### Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory
ecode	cn1	Numeric	An error code

### Description

None

## Message ID : CGS3317E

### Severity

Error

### Long Form

LDT-ALERT: Failed to rekey {0} file(s) in directory {1}

### Short Form

LDT: dir rekey errors

### Parameters

Label	CEF Label	Type	Usage
count	vds_count	Numeric	A generic count value
gp	fileId	Text	Guardpoint base directory

### Description

None

# Logger CGS: Information

**Message ID : CGS3029I**

## Severity

Information

## Long Form

LDT: Cannot enable guard point [{}] during LDT clean-up process

## Short Form

LDT: EA removing

### Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

## Description

None

## Message ID : CGS3030I

### Severity

Information

### Long Form

LDT: Successfully rekeyed file [{0}]

### Short Form

Successfully rekeyed

#### Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

### Description

None

## Message ID : CGS3036I



## Severity

Information

## Long Form

LDT: Successfully suspended rekey on guard point [{0}]

## Short Form

LDT: suspend success

### Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

## Description

None

## Message ID : CGS3037I

## Severity

Information

Message ID : CGS3036I

## **Long Form**

LDT: Rekey will be suspended on all applicable guard points

## **Short Form**

LDT: suspend success: all

### **Parameters**

No parameters are provided for this message type

## **Description**

None

## **Message ID : CGS3040I**

## **Severity**

Information

## **Long Form**

LDT: Successfully resumed rekey on guard point [{}]

## Short Form

LDT: resume success

### Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

## Description

None

## Message ID : CGS3041I

## Severity

Information

## Long Form

LDT: Rekey will be resumed on all applicable guard points

## Short Form

LDT: resume success: all

Message ID : CGS3040I

## Parameters

No parameters are provided for this message type

## Description

None

## Message ID : CGS3046I

## Severity

Information

## Long Form

LDT-ALERT: Suspending rekey of binary file [{0}] during its execution

## Short Form

LDT:SFS EXTBUSY

## Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

## Description

None

**Message ID : CGS3056I**

## Severity

Information

## Long Form

LDT: Rekey operation completed on guard point [{}]

## Short Form

LDT: completed

### Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

## Description

None

Message ID : CGS3046I

## Message ID : CGS3249I

### Severity

Information

### Long Form

LDT-ALERT: Skipped key rotation on guard point [{0}] on a read-only file system

### Short Form

LDT: Skipped ROFS

#### Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

### Description

None

## Message ID : CGS3250I

## Severity

Information

## Long Form

LDT-ALERT: Skipped key rotation on guard point [{0}] due to insufficient disk space

## Short Form

LDT: Skipped ENOSPC

### Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

## Description

None

## Message ID : CGS3251I

## Severity

Information

Message ID : CGS3250I

## Long Form

LDT-ALERT: Skipped key rotation on guard point [{0}] while another rekey operation is in progress

## Short Form

LDT: Skipped EBUSY

### Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

## Description

None

## Message ID : CGS3254I

## Severity

Information

## Long Form

LDT: Metadata will start getting removed from all files in guard point [{0}]

Message ID : CGS3251I



## Short Form

Extended attr will be deleted from gp

### Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

## Description

None

## Message ID : CGS3255I

## Severity

Information

## Long Form

LDT: Metadata has been removed from all files in guard point [{}]

## Short Form

Extended attr deleted from gp

Message ID : CGS3254I

### Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

### Description

None

### Message ID : CGS3277I

### Severity

Information

### Long Form

LDT-ALERT: Low space on guard point [{0}], increase free space or LDT will be suspended.

### Short Form

low disk

### Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

Message ID : CGS3255I

Label	CEF Label	Type	Usage

## Description

None

# Logger CGS: Warnings

**Message ID : CGS3267W**

## Severity

Warning

## Long Form

LDT-ALERT: LDT manual recovery on guard point [{0}] completed with [{1}] errors.

## Short Form

LDT-ALERT: LDT manual recovery forced

### Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory
count	vds_count	Numeric	A generic count value

## Description

None

## Message ID : CGS3268W

### Severity

Warning

### Long Form

LDT-ALERT: encrypted data detected in filename [{0}] inode [%lld] in guard point [{1}] under clear exclusion key rule

### Short Form

LDT-ALERT: encrypted data in clear file

### Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file
node	vds_node	Numeric	A node identifier
gp	fileId	Text	Guardpoint base directory

### Description

None

## Message ID : CGS3302W

### Severity

Warning

### Long Form

LDT-ALERT: Rekey is restarting due to previous transient error on guard point [{0}]. Error: [{1}]

### Short Form

Res acc issue

#### Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory
ecode	cn1	Numeric	An error code

### Description

None

## Message ID : CGS3303W

### Severity

Warning

### Long Form

LDT-ALERT: Rekey is restarting due to previous transient error on guard point [{0}]. Error: [{1}] Reason: [{2}]

### Short Form

Res acc issue desc

#### Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory
ecode	cn1	Numeric	An error code
showStr	reason	Text	Code specifying reason for allowing access, if any

### Description

None

## **Message ID : CGS3310W**

### **Severity**

Warning

### **Long Form**

IDT-TD-WARNING: Failed to delete IDT-Capable metadata file on remote nodes

### **Short Form**

IDT-TD-WARNING: Failed to delete IDT-Capable metadata

### **Parameters**

No parameters are provided for this message type

### **Description**

None



# Logger CMG: Information

**Message ID : CMG1150I**

## **Severity**

Information

## **Long Form**

Please [login to DSM server](#) to view the "Certificates" report for detail.

## **Short Form**

No short form is provided for this message type

## **Description**

None

# Logger CMG: Warnings

## Message ID : CMG1100W

### Severity

Warning

### Long Form

{0} certificates will expire {2} {1} days.

### Short Form

cert will expire

#### Parameters

Label	CEF Label	Type	Usage
cert	vds_cert	Text	Certificate type or name

### Description

Vormetric agents use certificates to authenticate them with the Security Server. These certificates are created during the registration process after the agent is installed and are valid for one year. They automatically renew 60 days before expiration. No action is required.

## Message ID : CMG1101W

### Severity

Warning

### Long Form

{0} certificate key will expire {2} {1} days.

### Short Form

cert key will expire

#### Parameters

Label	CEF Label	Type	Usage
cert	vds_cert	Text	Certificate type or name

### Description

Vormetric agents use certificates to authenticate them with the Security Server. These certificates are created during the registration process after the agent is installed and are valid for one year. They automatically renew 60 days before expiration. No action is required.

## Message ID : CMG1120W

### Severity

Warning

### Long Form

{0} certificates have been expired for {1} days.

### Short Form

cert expired

#### Parameters

Label	CEF Label	Type	Usage
cert	vds_cert	Text	Certificate type or name

### Description

Vormetric agents use certificates to authenticate them with the Security Server. These certificates are created during the registration process after the agent is installed and are valid for one year. They automatically renew 60 days before expiration. No action is required.

## Message ID : CMG1121W

### Severity

Warning

### Long Form

{0} certificate has been expired for {1} days.

### Short Form

cert key expired

#### Parameters

Label	CEF Label	Type	Usage
cert	vds_cert	Text	Certificate type or name

### Description

Vormetric agents use certificates to authenticate them with the Security Server. These certificates are created during the registration process after the agent is installed and are valid for one year. They automatically renew 60 days before expiration. No action is required.

## **Logger COM: Errors**

**Message ID : COM0002E**

### **Severity**

Error

### **Long Form**

The Security Server failed to validate the data received from the Agent on host {1} for the policy evaluation request. Reason is {0}.

### **Short Form**

No short form is provided for this message type

### **Description**

None

**Message ID : COM0003E**

### **Severity**

Error

## Long Form

Timestamp is {0}. Timestamp format should be yyyy-mm-dd hh:mm:ss.

## Short Form

No short form is provided for this message type

## Description

None

## Message ID : COM0005E

## Severity

Error

## Long Form

The Security server received a request from agent on host {0} for loggers. The Security Server failed to obtain any loggers. The Agent will be shut down.

## Short Form

No short form is provided for this message type

**Description**

None

**Message ID : COM0174E****Severity**

Error

**Long Form**

The Security Server was unable to contact the agent on host {0}. Directory information will not be displayed.

**Short Form**

No short form is provided for this message type

**Description**

None

**Message ID : COM0175E****Severity**

Error

Message ID : COM0005E



## **Long Form**

The Security Server was unable to obtain directory information from host {0}. Directory information will not be displayed.

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : COM0271E**

## **Severity**

Error

## **Long Form**

The Security Server was unable to contact the agent on host {0}. Host information will not be displayed.

## **Short Form**

No short form is provided for this message type

## **Description**

None

**Message ID : COM0272E**

## **Severity**

Error

## **Long Form**

The Security Server was unable to contact the agent on host {0}. The latest security configuration will not be sent to the host.

## **Short Form**

No short form is provided for this message type

## **Description**

None

**Message ID : COM0275E**

## **Severity**

Error

Message ID : COM0271E

## Long Form

The Security Server was unable to initialize communication with the agent on host {0}. The server and agent will not be able to communicate.

## Short Form

No short form is provided for this message type

## Description

None

## Message ID : COM0300E

## Severity

Error

## Long Form

The Security Server was unable to contact the file system agent on host {0} for deletion. The host record will not be deleted from the server database. De-select the file system agent registration checkbox to delete the host record from the database without contacting the file system agent.

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : COM0303E**

## **Severity**

Error

## **Long Form**

The Security Server failed to contact host {0} after {1} tries. An update will be pushed to the host if the management service (vmd) at the host is re-initialized or with the next policy change affecting the host.

## **Short Form**

No short form is provided for this message type

## **Description**

None

Message ID : COM0300E

## **Message ID : COM0312E**

### **Severity**

Error

### **Long Form**

The Security Server was unable to contact {0}.

### **Short Form**

No short form is provided for this message type

### **Description**

None

## **Message ID : COM0313E**

### **Severity**

Error

### **Long Form**

The Security Server failed to contact host {0}. The Security Server will make another attempt to contact the host at approximately {1}.

Message ID : COM0312E

## Short Form

failed to contact host

### Parameters

Label	CEF Label	Type	Usage
shost	shost	Text	Source host name
nexttime	vds_nexttime	Text	Time of next attempt

## Description

Wait for server to retry. If failure persists check for a network problem or the agent may be shut down.

## Message ID : COM0429E

### Severity

Error

## Long Form

The Security Server was unable to determine the communication version for host {0}. Directory information will not be displayed.

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : COM0430E**

## **Severity**

Error

## **Long Form**

The Security Server was unable to determine the communication version for host {0}. The latest security configuration will not be sent to the host.

## **Short Form**

No short form is provided for this message type

## **Description**

None

Message ID : COM0429E

## **Message ID : COM0431E**

### **Severity**

Error

### **Long Form**

The Security Server is too old for the agent on host {0}. Agent min version supported is {1}. Server max version supported is {2}. The Server and Agent will not be able to communicate. Ensure that server and agent versions are compatible.

### **Short Form**

No short form is provided for this message type

### **Description**

None

## **Message ID : COM0432E**

### **Severity**

Error



## Long Form

The agent on host {0} is too old for the Security Server. Agent max version supported is {1}. Server min version supported is {2}. The Server and Agent will not be able to communicate. Ensure that server and agent versions are compatible.

## Short Form

No short form is provided for this message type

## Description

None

## Message ID : COM0433E

## Severity

Error

## Long Form

The Security Server is unable to obtain the communication version from the database for the agent on host {0}. The server and agent will not be able to communicate. Ensure that the database is functional.

## Short Form

No short form is provided for this message type

Message ID : COM0432E

## **Description**

None

**Message ID : COM0434E**

## **Severity**

Error

## **Long Form**

The Security Server is unable to negotiate a communication version with the agent on host {0} because host information cannot be retrieved from the database. The server and agent will not be able to communicate. Ensure that the database is functional.

## **Short Form**

No short form is provided for this message type

## **Description**

None

**Message ID : COM0435E**

## Severity

Error

## Long Form

A roll back has been detected for the agent on host {0}. Agent min/max: {1}/{2}. Min/max for host in the database: {3}/{4}. The server and agent will not be able to communicate. The agent must be upgraded or the agent must re-register with the Server.

## Short Form

No short form is provided for this message type

## Description

None

## Message ID : COM0436E

## Severity

Error

## Long Form

The negotiated version {0} from the database for the agent on host {1} is not in the min/max range of agent: {2}/{3}. The Server and Agent will not be able to communicate. Ensure that server and agent versions are compatible.

Message ID : COM0435E

## Short Form

No short form is provided for this message type

## Description

None

## Message ID : COM0506E

## Severity

Error

## Long Form

The Security Server received a fault message from the agent at host {0}. The errorcode {1} sent by the agent is not recognized by the server. Please ensure that the agent and server versions are matching.

## Short Form

No short form is provided for this message type

## Description

None

Message ID : COM0436E

## **Message ID : COM0507E**

### **Severity**

Error

### **Long Form**

The Security Server detected an Internal error from the agent at host {0}. Please check the agent logs.

### **Short Form**

No short form is provided for this message type

### **Description**

None

## **Message ID : COM0508E**

### **Severity**

Error

### **Long Form**

The Security Server was unable to browse the directory {0} at host {1}. The directory name is invalid. Browse information will not be displayed.

Message ID : COM0507E

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : COM0509E**

## **Severity**

Error

## **Long Form**

The Security Server detected a "failed to implement security configuration from the agent at host {0}". Please check the agent logs.

## **Short Form**

No short form is provided for this message type

## **Description**

None

Message ID : COM0508E

## **Message ID : COM0510E**

### **Severity**

Error

### **Long Form**

The Security Server detected a "failed to query security configuration" from the agent at host {0}". Please check the agent logs.

### **Short Form**

No short form is provided for this message type

### **Description**

None

## **Message ID : COM0511E**

### **Severity**

Error

### **Long Form**

The Security Server detected a "Failed to delete host" from the agent at host {0}". Please check the agent logs.

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : COM0512E**

## **Severity**

Error

## **Long Form**

The Security Server was unable to browse the directory {0} from host {1}. Network path {2} was either typed incorrectly, does not exist, or the network provider is not currently available. Please ensure that the network path is valid.

## **Short Form**

No short form is provided for this message type

## **Description**

None

Message ID : COM0511E



## **Message ID : COM0513E**

### **Severity**

Error

### **Long Form**

The Security Server was unable to browse the directory {0} from host {1}. Unknown user name {2} under domain {3} or bad password. Please ensure that the user name, domain and password are valid.

### **Short Form**

No short form is provided for this message type

### **Description**

None

## **Message ID : COM0514E**

### **Severity**

Error

## Long Form

The Security Server was unable to browse the directory {0} from host {1}. Network path {2} cannot be found. Please ensure that the network path exists.

## Short Form

No short form is provided for this message type

## Description

None

## Message ID : COM0515E

## Severity

Error

## Long Form

The Security Server was unable to browse the directory {0} from host {1}. Failed to enumerate network resource {2}. Please check the agent logs.

## Short Form

No short form is provided for this message type

Message ID : COM0514E

## **Description**

None

**Message ID : COM0516E**

## **Severity**

Error

## **Long Form**

The Security Server was unable to browse the directory {0} from host {1}. Multiple connections to network resource {2} by user {3} under domain {4} are not allowed. Disconnect all previous connections to the server or shared resource and try again.

## **Short Form**

No short form is provided for this message type

## **Description**

None

**Message ID : COM0536E**

## Severity

Error

## Long Form

The Security Server was unable to contact host {0}. If the hostname has been recently modified, the security server may still be aware of the previous hostname. Restarting the security server may clear up this condition.

## Short Form

No short form is provided for this message type

## Description

None

## Message ID : COM0537E

## Severity

Error

## Long Form

The Security Server was unable to contact the agent on host {0}. The agent is refusing connections. Please ensure that the agent is up and running.

Message ID : COM0536E

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : COM0539E**

## **Severity**

Error

## **Long Form**

The Security Server was unable to retrieve the data for host {0} from the database. Refer to cgss.log and server.log for details. Call support if necessary.

## **Short Form**

No short form is provided for this message type

## **Description**

None

Message ID : COM0537E

## **Message ID : COM0540E**

### **Severity**

Error

### **Long Form**

The Security Server failed to invoke the command line interface with the following error message: {0}.

### **Short Form**

No short form is provided for this message type

### **Description**

None

## **Message ID : COM0541E**

### **Severity**

Error

### **Long Form**

The upgrade package file has been successfully uploaded to the server. Since Thales HSM firmware upgrade is required, you must run "maintenance sysupgrade" from the DSM CLI to continue the upgrade process.

Message ID : COM0540E

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : COM0542E**

## **Severity**

Error

## **Long Form**

The Security Server is unable to send configuration changes to the agent at host {0}. The agent does not support the guarding of raw devices. Please disable or un-guard the raw devices or update the agent software.

## **Short Form**

No short form is provided for this message type

## **Description**

None

Message ID : COM0541E

## **Message ID : COM0543E**

### **Severity**

Error

### **Long Form**

The Security Server was unable to perform {0} operation. Refer to the DSM logs for more information.

### **Short Form**

No short form is provided for this message type

### **Description**

None

## **Message ID : COM0555E**

### **Severity**

Error

### **Long Form**

The Security Server was unable to contact the agent on host {0}. User information will not be displayed.



## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : COM0556E**

## **Severity**

Error

## **Long Form**

The Security Server was unable to obtain user information from host {0}. User information will not be displayed.

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : COM0557E**

### **Severity**

Error

### **Long Form**

The Security Server was unable to browse the domain {0} from host {1}. Invalid user name, domain name or password.

### **Short Form**

No short form is provided for this message type

### **Description**

None

## **Message ID : COM0558E**

### **Severity**

Error

### **Long Form**

The Security Server was unable to browse the domain {0} from host {1}. The directory service is unavailable.

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : COM0588E**

## **Severity**

Error

## **Long Form**

The Security Server is waiting for the signature data from host {0}. Communication between Server and host cannot proceed.

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : COM0589E**

### **Severity**

Error

### **Long Form**

The Security Server is waiting for the signature data from host {0}. The signature request may be rejected due to invalid file or directory name.

### **Short Form**

No short form is provided for this message type

### **Description**

None

## **Message ID : COM0590E**

### **Severity**

Error

## Long Form

The Security Server received a signature message from the agent at host {0}. But the signature message is not in standard format.

## Short Form

received bad signature message from agent

### Parameters

Label	CEF Label	Type	Usage
shost	shost	Text	Source host name

## Description

None

## Message ID : COM0594E

## Severity

Error

## Long Form

The Security Server was unable to contact host {0}. The host name is defined by IP address, please use CLI command "network agentip show" to check if agent ip is enabled.

Message ID : COM0590E

## Short Form

No short form is provided for this message type

## Description

None

## Message ID : COM0595E

## Severity

Error

## Long Form

The Security Server failed to contact host {0}. Please make sure the agent ip is enabled. The Security Server will make another attempt to contact the host at approximately {1}.

## Short Form

server failed to contact host

## Parameters

Label	CEF Label	Type	Usage
shost	shost	Text	Source host name

Message ID : COM0594E

Label	CEF Label	Type	Usage
nexttime	vds_nexttime	Text	Time of next attempt

## Description

Allow host registration using IP address. Use CLI to enable Agentip under the Network menu.

## Message ID : COM0600E

### Severity

Error

### Long Form

The Security Server is unable to contact the host {0}. The host may be down.

### Short Form

No short form is provided for this message type

### Description

None

## Message ID : COM0601E

### Severity

Error

### Long Form

The Security Server received signature value that is more than 64 bytes on the file {0}.

### Short Form

received signature value more than 64 bytes

### Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

### Description

None

## Message ID : COM0602E



## **Severity**

Error

## **Long Form**

The Security Server cannot push the signature(s) to the agent at host {0}. Communication between Server and host cannot proceed.

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : COM0603E**

## **Severity**

Error

## **Long Form**

The Security Server cannot push the signature(s) to the agent at host {0}. The version of the agent does not support this operation.

## Short Form

cannot push the signature(s) to agent

### Parameters

Label	CEF Label	Type	Usage
shost	shost	Text	Source host name

## Description

None

## Message ID : COM0605E

## Severity

Error

## Long Form

The Security Server is sending the message of canceling signing process to the agent at host {0} because the user is deleting the signature set while the signing is in progress.

## Short Form

sending signing cancelation to agent

Message ID : COM0603E

### Parameters

Label	CEF Label	Type	Usage
shost	shost	Text	Source host name

### Description

None

**Message ID : COM0609E**

### Severity

Error

### Long Form

The Security Server is unable to cancel the signing on the host {0} because the operation is timed out after 60000ms. Please try again at a later time.

### Short Form

No short form is provided for this message type

### Description

None

Message ID : COM0605E

## **Message ID : COM0613E**

### **Severity**

Error

### **Long Form**

Invalid operation. The command {0} is not available on a failover server {1}.

### **Short Form**

No short form is provided for this message type

### **Description**

None

## **Message ID : COM0619E**

### **Severity**

Error

### **Long Form**

The domain name is required.

Message ID : COM0613E

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : COM0620E**

## **Severity**

Error

## **Long Form**

Either the domain description or help desk information is required.

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : COM0621E**

### **Severity**

Error

### **Long Form**

The administrator name is required.

### **Short Form**

No short form is provided for this message type

### **Description**

None

## **Message ID : COM0622E**

### **Severity**

Error

### **Long Form**

The domain is already assigned to a domain administrator.

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : COM0623E**

## **Severity**

Error

## **Long Form**

The user type is not in DOMAIN, or DOMAIN\_SECURITY, or ALL administrator.

## **Short Form**

No short form is provided for this message type

## **Description**

None

Message ID : COM0622E

## **Message ID : COM0627E**

### **Severity**

Error

### **Long Form**

The domain {0} is not assigned to the user {1}.

### **Short Form**

No short form is provided for this message type

### **Description**

None

## **Message ID : COM0628E**

### **Severity**

Error

### **Long Form**

Server failed to replicate configuration data to other server "{0}".



## Short Form

failed to replicate configuration data to other server

### Parameters

Label	CEF Label	Type	Usage
shost	shost	Text	Source host name

## Description

None

## Message ID : COM0650E

### Severity

Error

## Long Form

The Security Server was unable to contact server host {0} CA service. The host name is defined by IP address.

## Short Form

No short form is provided for this message type

Message ID : COM0628E

## **Description**

None

**Message ID : COM0651E**

## **Severity**

Error

## **Long Form**

The Security Server was unable to initialize communication with the {0} CA service. The server and CA service will not be able to communicate.

## **Short Form**

No short form is provided for this message type

## **Description**

None

**Message ID : COM0652E**

## Severity

Error

## Long Form

The Vormetric RA Failed to talk to the Certificate Authority service at {0}.

## Short Form

ra failed contact Certificate Authority service

### Parameters

Label	CEF Label	Type	Usage
shost	shost	Text	Source host name

## Description

None

**Message ID : COM0653E**

## Severity

Error

Message ID : COM0652E

## Long Form

The Security Server was unable to contact the CA service on host {0}. The CA service is refusing connections. Please ensure that the CA service is up and running.

## Short Form

No short form is provided for this message type

## Description

None

## Message ID : COM0660E

## Severity

Error

## Long Form

The Security Server could not find the syslog host {0}. All logging to the syslog host will FAIL.

## Short Form

could not find syslog host

### Parameters

Label	CEF Label	Type	Usage
shost	shost	Text	Source host name

### Description

None

### Message ID : COM0661E

### Severity

Error

### Long Form

The Security Server could not instantiate TCP socket to the syslog host {0}. All logging to the syslog host will FAIL.

### Short Form

could not connect syslog host via TCP

### Parameters

Label	CEF Label	Type	Usage
shost	shost	Text	Source host name

Message ID : COM0660E

Label	CEF Label	Type	Usage

## Description

None

## Message ID : COM0712E

## Severity

Error

## Long Form

The security server {0} failed to delete the host {1} upon the deletion request from the {2} agent because the {3}agents are still registered.

## Short Form

failed to delete host

## Parameters

Label	CEF Label	Type	Usage
shost	shost	Text	Source host name
shost	shost	Text	Source host name

Message ID : COM0661E

Label	CEF Label	Type	Usage
agent	deviceProcessName	Text	The short identifier of the agent software
showStr	reason	Text	Code specifying reason for allowing access, if any

## Description

None

## Message ID : COM0713E

## Severity

Error

## Long Form

The Security Server denied an unregister request from unauthorized host "{0}".

## Short Form

denied unregister request from unauthorized host

### Parameters

Label	CEF Label	Type	Usage
-------	-----------	------	-------

Message ID : COM0712E

Label	CEF Label	Type	Usage
shost	shost	Text	Source host name

## Description

If host is authorized, Edit that host and select "Registration Allowed".

## Message ID : COM0759E

## Severity

Error

## Long Form

The security server failed to obtain hardware status. The service call is not compatible with the appliance.

## Short Form

No short form is provided for this message type

## Description

None



## **Message ID : COM0772E**

### **Severity**

Error

### **Long Form**

The communication is not enabled for key agent at host {0} on the security server. The operation will not proceed.

### **Short Form**

No short form is provided for this message type

### **Description**

None

## **Message ID : COM0805E**

### **Severity**

Error

### **Long Form**

The user of the type {0} is not allowed to be assigned to the domain.

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : COM0900E**

## **Severity**

Error

## **Long Form**

The domain quota value is required.

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : COM0901E**

### **Severity**

Error

### **Long Form**

The administrator cannot modify his/her own role.

### **Short Form**

No short form is provided for this message type

### **Description**

None

## **Message ID : COM1257E**

### **Severity**

Error

### **Long Form**

The domain name is too long. Please correct the problem and try again.

## **Short Form**

No short form is provided for this message type

## **Description**

None

**Message ID : COM1263E**

## **Severity**

Error

## **Long Form**

System administrator cannot be added to domain.

## **Short Form**

No short form is provided for this message type

## **Description**

None

Message ID : COM1257E

## **Message ID : COM1264E**

### **Severity**

Error

### **Long Form**

Exceeded maximum batch size {0}.

### **Short Form**

No short form is provided for this message type

### **Description**

None

## **Message ID : COM1285E**

### **Severity**

Error

### **Long Form**

Session not found: {0}

Message ID : COM1264E

## Short Form

No short form is provided for this message type

## Description

None

## Message ID : COM1306E

## Severity

Error

## Long Form

Host {0} does NOT support Suite-B cipher suites.

## Short Form

Host does NOT support Suite-B cipher suites

### Parameters

Label	CEF Label	Type	Usage
shost	shost	Text	Source host name

## **Description**

None

**Message ID : COM1307E**

## **Severity**

Error

## **Long Form**

The batch size is less than 0.

## **Short Form**

No short form is provided for this message type

## **Description**

None

**Message ID : COM1308E**

## **Severity**

Error

Message ID : COM1306E

## **Long Form**

Another push using newer style.

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : COM1310E**

## **Severity**

Error

## **Long Form**

Internal error. Refer to server.log for details.

## **Short Form**

No short form is provided for this message type

Message ID : COM1308E



## **Description**

None

**Message ID : COM1315E**

## **Severity**

Error

## **Long Form**

The administrator cannot modify his/her own read-only attribute.

## **Short Form**

No short form is provided for this message type

## **Description**

None

**Message ID : COM1321E**

## **Severity**

Error

Message ID : COM1310E

## **Long Form**

Error in starting data transform

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : COM1322E**

## **Severity**

Error

## **Long Form**

Error in stopping data transform

## **Short Form**

No short form is provided for this message type

Message ID : COM1321E

**Description**

None

**Message ID : COM1349E****Severity**

Error

**Long Form**

The license type must be one of TERM, PERPETUAL or HOURLY.

**Short Form**

No short form is provided for this message type

**Description**

None

**Message ID : COM1350E****Severity**

Error

Message ID : COM1322E

## **Long Form**

The validity period must be one of ONE\_HOUR, ONE\_DAY, ONE\_WEEK or ONE\_MONTH.

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : COM1367E**

## **Severity**

Error

## **Long Form**

The security server does not have any backup schedules defined

## **Short Form**

No short form is provided for this message type

## **Description**

None

**Message ID : COM1400E**

## **Severity**

Error

## **Long Form**

Host {0} cannot be re-registered with LDT disabled. Delete the host from DSM and re-add it again

## **Short Form**

No short form is provided for this message type

## **Description**

None

**Message ID : COM1401E**

## **Severity**

Error

Message ID : COM1367E

## Long Form

Host {0} cannot be re-registered with Docker disabled. Delete the host from DSM and re-add it again

## Short Form

No short form is provided for this message type

## Description

None

## Message ID : COM1402E

## Severity

Error

## Long Form

Host {0} cannot be registered. It's part of a host group that defines a guardpoint with enabled exclusion key rule in LDT policy. You need to upgrade the agent to version 6.2.0 or higher.

## Short Form

No short form is provided for this message type

## **Description**

None

**Message ID : COM1403E**

## **Severity**

Error

## **Long Form**

Host {0} cannot be re-registered with Cloud Object Storage disabled. Delete the host from DSM and re-add it again

## **Short Form**

No short form is provided for this message type

## **Description**

None

**Message ID : COM1410E**

## **Severity**

Error

Message ID : COM1402E

## Long Form

Host "{0}" does not support the CBC\_CS1 encryption mode, you cannot re-register with a GuardPoint with a Policy that contains a key that uses this encryption mode.

## Short Form

No short form is provided for this message type

## Description

None

## Message ID : COM1669E

## Severity

Error

## Long Form

Host {0} cannot be re-registered with "{1}" feature disabled. Delete the host from DSM and re-add it again

## Short Form

No short form is provided for this message type



## **Description**

None

**Message ID : COM1692E**

## **Severity**

Error

## **Long Form**

Host {0} cannot be re-registered with FF1 disabled. Delete the host from DSM and re-add it again

## **Short Form**

No short form is provided for this message type

## **Description**

None

**Message ID : COM1740E**

## **Severity**

Error

Message ID : COM1669E

## Long Form

Host fingerprint mismatch (fingerprintFromDB={0}, fingerprintFromCert={1}).

## Short Form

No short form is provided for this message type

## Description

None

## Message ID : COM1741E

## Severity

Error

## Long Form

Invalid client certificate from host {0}.

## Short Form

No short form is provided for this message type

Message ID : COM1740E

## **Description**

None

**Message ID : COM1744E**

## **Severity**

Error

## **Long Form**

Agent from host "{0}" is not allowed to perform operation "{1}" on host "{2}".

## **Short Form**

No short form is provided for this message type

## **Description**

None

**Message ID : COM4547E**

## **Severity**

Error

Message ID : COM1741E

## **Long Form**

Internal error: Invalid configuration type given to communications subsystem. Contact support.

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : COM4631E**

## **Severity**

Error

## **Long Form**

OPENSSL ERROR: {0}

## **Short Form**

OpenSSL error

## Parameters

Label	CEF Label	Type	Usage
showStr	reason	Text	Code specifying reason for allowing access, if any

## Description

None

**Message ID : COM4638E**

## Severity

Error

## Long Form

We have detected a change in the system hardware. Communication to the DSM has been disabled. This condition can be fixed by re-registering this agent with the DSM.

## Short Form

Hardware Change

## Parameters

No parameters are provided for this message type

Message ID : COM4631E

## Description

None

**Message ID : COM4644E**

## Severity

Error

## Long Form

An invalid REST object has been received - {0}

## Short Form

Bad REST object

## Parameters

Label	CEF Label	Type	Usage
detail	vds_detail	Text	Fault detail

## Description

None

Message ID : COM4638E

# Logger COM: Fatal errors

## Message ID : COM0004F

### Severity

Fatal error

### Long Form

The Security Server failed to initialize upon startup. The Security Server could not retrieve its configuration parameters. Verify that the Security Server database is functional. If the problem persists, contact support.

### Short Form

No short form is provided for this message type

### Description

None

## Message ID : COM4503F

### Severity

Fatal error

## Long Form

Communications module initialization failure. Contact support.

## Short Form

Comms init fail

### Parameters

No parameters are provided for this message type

## Description

None

## Message ID : COM4506F

## Severity

Fatal error

## Long Form

Failed to set up logger "{0}". Contact support.



## Short Form

Logger setup error

### Parameters

Label	CEF Label	Type	Usage
showStr	reason	Text	Code specifying reason for allowing access, if any

## Description

None

## Message ID : COM4511F

## Severity

Fatal error

## Long Form

The communication request to the Key Manager was garbled or otherwise incorrect: error {0}. Contact support.

## Short Form

Bad policy request

Message ID : COM4506F

### Parameters

Label	CEF Label	Type	Usage
ecode	cn1	Numeric	An error code

### Description

None

### Message ID : COM4512F

### Severity

Fatal error

### Long Form

Policy response garbled: unable to find attribute "{0}".

### Short Form

Resp attr missing

### Parameters

Label	CEF Label	Type	Usage
showStr	reason	Text	Code specifying reason for allowing access, if any

Message ID : COM4511F

Label	CEF Label	Type	Usage

## Description

None

## Message ID : COM4513F

## Severity

Fatal error

## Long Form

Unable to configure secure communication channel. Contact support.

## Short Form

No short form is provided for this message type

## Description

None

## Message ID : COM4514F

### Severity

Fatal error

### Long Form

The communication request to the Key Manager was garbled or otherwise incorrect: error {0}. Contact support.

### Short Form

Server init req error

#### Parameters

Label	CEF Label	Type	Usage
ecode	cn1	Numeric	An error code

### Description

None

## Message ID : COM4515F

## Severity

Fatal error

## Long Form

There was a communication failure with the Key Manager. The server returned a fault: {0}{1}; "{2}"; Subcode: "{3}"; Reason: "{4}"; Detail: "{5}".

## Short Form

No short form is provided for this message type

## Description

None

## Message ID : COM4521F

## Severity

Fatal error

## Long Form

Internal version not supported, version required: {0}.

## Short Form

Bad SDK version

### Parameters

Label	CEF Label	Type	Usage
version	vds_version	Text	Software version string

## Description

None

## Message ID : COM4523F

## Severity

Fatal error

## Long Form

Unable to establish a connection to a Key Manager for the purpose of policy evaluation. Verify that the configuration file has the correct URL(s) to the server.

## Short Form

Policy info missing

Message ID : COM4521F

### **Parameters**

No parameters are provided for this message type

### **Description**

None

### **Message ID : COM4527F**

### **Severity**

Fatal error

### **Long Form**

The Agent could not obtain configuration information. The Agent failed to initialize. Verify connectivity to the Key Manager and retry the operation.

### **Short Form**

Agent config missing

### **Parameters**

No parameters are provided for this message type

## **Description**

None

## **Message ID : COM4529F**

## **Severity**

Fatal error

## **Long Form**

Unable to establish an initial connection to any Key Manager. Verify that the configuration file has the correct URL(s) to the server.

## **Short Form**

No config from server

## **Parameters**

No parameters are provided for this message type

## **Description**

None



## **Message ID : COM4531F**

### **Severity**

Fatal error

### **Long Form**

Unable to configure secure communication channel. Contact support.

### **Short Form**

SSL setup fail

### **Parameters**

No parameters are provided for this message type

### **Description**

None

## **Message ID : COM4533F**

### **Severity**

Fatal error

## Long Form

{0} from file does not match that from backup. File: "{1}". Backup: "{2}".

## Short Form

Backup opaque data mismatch

### Parameters

No parameters are provided for this message type

## Description

None

## Message ID : COM4534F

## Severity

Fatal error

## Long Form

File type mismatch: {0} must be a directory.

## Short Form

Not a dir

### Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

## Description

None

## Message ID : COM4538F

### Severity

Fatal error

## Long Form

The Key Manager URL ({0}) must start with "https:".

## Short Form

Invalid URL

Message ID : COM4534F

## Parameters

Label	CEF Label	Type	Usage
url	request	Text	A uniform resource location

## Description

None

## Message ID : COM4542F

## Severity

Fatal error

## Long Form

The agent could not allocate enough memory. Contact support.

## Short Form

Out of memory

## Parameters

No parameters are provided for this message type

Message ID : COM4538F

## Description

None

**Message ID : COM4548F**

## Severity

Fatal error

## Long Form

Policy request garbled: unable to find attribute "{0}".

## Short Form

Req attr missing

## Parameters

Label	CEF Label	Type	Usage
showStr	reason	Text	Code specifying reason for allowing access, if any

## Description

None

Message ID : COM4542F

## Message ID : COM4551F

### Severity

Fatal error

### Long Form

The Agent failed to initialize, reporting "{0}". Verify the logging configuration on the Key Manager and retry the operation. If the problem persists, contact support.

### Short Form

Agent init error

### Parameters

Label	CEF Label	Type	Usage
showStr	reason	Text	Code specifying reason for allowing access, if any

### Description

None

## Message ID : COM4552F

## Severity

Fatal error

## Long Form

Communication with the Key Manager was established, but an invalid response (error {0}) was received. The requested operation cannot continue. Contact support.

## Short Form

Bad policy response

### Parameters

Label	CEF Label	Type	Usage
ecode	cn1	Numeric	An error code

## Description

None

## Message ID : COM4554F

## Severity

Fatal error

Message ID : COM4552F

## Long Form

Communication with the Key Manager was established, but an invalid response (error {0}) was received. The requested operation cannot continue. Contact support.

## Short Form

Comms response error

### Parameters

Label	CEF Label	Type	Usage
ecode	cn1	Numeric	An error code

## Description

None

**Message ID : COM4558F**

## Severity

Fatal error

## Long Form

Key Manager communications failure. URL: {0}. Check the URL in the agent.conf file. Verify that the server url is correct and retry

Message ID : COM4554F



the operation.

## Short Form

Bad config from server

### Parameters

Label	CEF Label	Type	Usage
url	request	Text	A uniform resource location

## Description

None

## Message ID : COM4562F

## Severity

Fatal error

## Long Form

The communication request to the Key Manager was garbled or otherwise incorrect: error {0}. Contact support.

## Short Form

Comms init error

### Parameters

Label	CEF Label	Type	Usage
ecode	cn1	Numeric	An error code

## Description

None

## Message ID : COM4563F

## Severity

Fatal error

## Long Form

Key Manager connection failure. Check the URL in the agent.conf file. Verify that the server url is correct and retry the operation.

## Short Form

No short form is provided for this message type

Message ID : COM4562F

## Description

None

**Message ID : COM4567F**

## Severity

Fatal error

## Long Form

Communication with the Key Manager was established, but an invalid response (error {0}) was received. The requested operation cannot continue. Contact support.

## Short Form

SDK response error

### Parameters

Label	CEF Label	Type	Usage
ecode	cn1	Numeric	An error code

## Description

None

Message ID : COM4563F

## Message ID : COM4569F

### Severity

Fatal error

### Long Form

The Key Manager URL is too long. It is {0} characters, while the maximum size is {1} characters. The URL is {2}.

### Short Form

URL too long

#### Parameters

Label	CEF Label	Type	Usage
slen	in	Numeric	Input byte count or length
dlen	out	Numeric	Output byte count or length
url	request	Text	A uniform resource location

### Description

None

## Message ID : COM4571F

### Severity

Fatal error

### Long Form

File access failure: Unable to open {0}: {1}.

### Short Form

Open error

### Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file
showStr	reason	Text	Code specifying reason for allowing access, if any

### Description

None

## **Message ID : COM4577F**

### **Severity**

Fatal error

### **Long Form**

Error adding host {0} information to server.

### **Short Form**

No short form is provided for this message type

### **Description**

None

## **Message ID : COM4578F**

### **Severity**

Fatal error

### **Long Form**

Request from {0} to add host is invalid.

Message ID : COM4577F

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : COM4579F**

## **Severity**

Fatal error

## **Long Form**

Response to add host request from {0} is invalid: {1}.

## **Short Form**

No short form is provided for this message type

## **Description**

None

Message ID : COM4578F

## Message ID : COM4583F

### Severity

Fatal error

### Long Form

Error initializing agent.

### Short Form

Agent init fail

### Parameters

No parameters are provided for this message type

### Description

The agent is unable to reach the Security Server. You may see any of the following error messages: COM4583F, COM4633W, VMD3770F, VMD3885I or VMD3886I. You may experience any of the following:

1. Connection to the Security Server is down.
2. The VMD Host has been deleted from the Security Server.
3. The host does not have "Communication Enabled" in the Security Server UI.
4. The VMD's host may be deleted from the Security Server. Run the register\_host utility to re-register the VMD with the Security Server.



## Message ID : COM4584F

### Severity

Fatal error

### Long Form

Initialize Agent request invalid, {0} ({1}).

### Short Form

Invalid config

#### Parameters

Label	CEF Label	Type	Usage
ecode	cn1	Numeric	An error code
showStr	reason	Text	Code specifying reason for allowing access, if any

### Description

None

## **Message ID : COM4586F**

### **Severity**

Fatal error

### **Long Form**

Error evaluating policy.

### **Short Form**

Policy eval fail

### **Parameters**

No parameters are provided for this message type

### **Description**

None

## **Message ID : COM4587F**

### **Severity**

Fatal error

Message ID : COM4586F

## Long Form

Error evaluating policy request, {0}.

## Short Form

Policy eval error

### Parameters

Label	CEF Label	Type	Usage
ecode	cn1	Numeric	An error code

## Description

None

**Message ID : COM4588F**

## Severity

Fatal error

## Long Form

Error evaluating policy response, {0}.

Message ID : COM4587F

## Short Form

Policy response error

### Parameters

Label	CEF Label	Type	Usage
ecode	cn1	Numeric	An error code

## Description

None

## Message ID : COM4592F

### Severity

Fatal error

## Long Form

Error running VMSDK server, {0} (port: {1}).

## Short Form

VMSDK server error

Message ID : COM4588F

## Parameters

Label	CEF Label	Type	Usage
ecode	cn1	Numeric	An error code
port	spt	Numeric	A socket port number

## Description

None

## Message ID : COM4599F

## Severity

Fatal error

## Long Form

An error was encountered when trying to listen to requests from the server. The listening interface is "{0}" and the port is {1}.  
Error: {2}.

## Short Form

No short form is provided for this message type

## Description

None

## Message ID : COM4600F

## Severity

Fatal error

## Long Form

There was a communication failure with the Key Manager ({0}). The server returned a fault: {1}{2}; "{3}"; Subcode: "{4}"; Reason: "{5}"; Detail: "{6}".

## Short Form

SOAP client error

## Parameters

Label	CEF Label	Type	Usage
url	request	Text	A uniform resource location
showStr	reason	Text	Code specifying reason for allowing access, if any
verno	vds_verno	Numeric	A version number
context	vds_context	Text	Fault context

Message ID : COM4599F

Label	CEF Label	Type	Usage
subcode	vds_subcode	Text	Fault subcode
showStr	reason	Text	Code specifying reason for allowing access, if any
detail	vds_detail	Text	Fault detail

## Description

None

## Message ID : COM4603F

## Severity

Fatal error

## Long Form

Unable to parse the URL {0}. This attribute is located in the config file at {1}. Please fix the URL or re-install this product.

## Short Form

Bad URL

## Parameters

Label	CEF Label	Type	Usage
url	request	Text	A uniform resource location
filePath	filePath	Text	Full path to file

## Description

None

**Message ID : COM4604F**

## Severity

Fatal error

## Long Form

Internal error: unable to set attribute {0}.

## Short Form

Cannot set attr

Message ID : COM4603F



### Parameters

Label	CEF Label	Type	Usage
showStr	reason	Text	Code specifying reason for allowing access, if any

### Description

None

### Message ID : COM4628F

### Severity

Fatal error

### Long Form

Unable to connect to a Key Manager. URL: {0}. Please verify that the agent host is registered with a Key Manager.

### Short Form

Server connect fail

### Parameters

Label	CEF Label	Type	Usage
url	request	Text	A uniform resource location

Message ID : COM4604F

Label	CEF Label	Type	Usage

## Description

None

## Message ID : COM4629F

## Severity

Fatal error

## Long Form

The server at {0} attempted to contact this machine, but it was denied access due to an invalid certificate.

## Short Form

Bad cert from server

## Parameters

Label	CEF Label	Type	Usage
url	request	Text	A uniform resource location

## Description

None

## Message ID : COM4630F

## Severity

Fatal error

## Long Form

A machine identifying itself as {0} tried to contact the VMD, but there was an error: {1}{2}; "{3}"; Subcode: "{4}"; Reason: "{5}"; Detail: "{6}".

## Short Form

SOAP server error

## Parameters

Label	CEF Label	Type	Usage
url	request	Text	A uniform resource location
showStr	reason	Text	Code specifying reason for allowing access, if any
verno	vds_verno	Numeric	A version number
context	vds_context	Text	Fault context

Message ID : COM4629F

Label	CEF Label	Type	Usage
subcode	vds_subcode	Text	Fault subcode
showStr	reason	Text	Code specifying reason for allowing access, if any
detail	vds_detail	Text	Fault detail

## Description

None

## Message ID : COM4637F

## Severity

Fatal error

## Long Form

Failed to bind to port {0}. Please ensure that this port is not in use by another program.

## Short Form

SDK bind error

### Parameters

Label	CEF Label	Type	Usage
port	spt	Numeric	A socket port number

### Description

None

# Logger COM: Information

**Message ID : COM0006I**

## Severity

Information

## Long Form

The Security Server permitted a backup request from host {0} for dbinstance({1}), dbalias({2}), dbpartition({3}). The policy used is ({4}), the rule used is ({5}).

## Short Form

permitted backup req from host

### Parameters

Label	CEF Label	Type	Usage
shost	shost	Text	Source host name
dbinstance	vds_dbinstance	Text	Database instance
dbalias	vds_dbalias	Text	Database alias
dbpart	vds_dbpart	Numeric	Database partition
pol	cs1	Text	Policy name

Label	CEF Label	Type	Usage
rule	vds_rule	Text	Name of policy rule set

## Description

None

## Message ID : COM0007I

## Severity

Information

## Long Form

The Security Server denied a backup request from host {0} for dbinstance({1}), dbalias({2}), dbpartition({3}). The policy used is ({4}), the rule used is ({5}).

## Short Form

No short form is provided for this message type

## Description

None

## Message ID : COM0008I

### Severity

Information

### Long Form

The Security Server permitted a restore request from host {0} for dbinstance({1}), dbalias({2}), dbpartition({3}). The policy used is ({4}), the rule used is ({5}).

### Short Form

permitted restore req from host

### Parameters

Label	CEF Label	Type	Usage
shost	shost	Text	Source host name
dbinstance	vds_dbinstance	Text	Database instance
dbalias	vds_dbalias	Text	Database alias
dbpart	vds_dbpart	Numeric	Database partition
pol	cs1	Text	Policy name
rule	vds_rule	Text	Name of policy rule set



## Description

None

## Message ID : COM0009I

## Severity

Information

## Long Form

The Security Server denied a restore request from host {0} for dbinstance({1}), dbalias({2}), dbpartition({3}). The policy used is ({4}), the rule used is ({5}).

## Short Form

denied restore req from host

## Parameters

Label	CEF Label	Type	Usage
shost	shost	Text	Source host name
dbinstance	vds_dbinstance	Text	Database instance
dbalias	vds_dbalias	Text	Database alias
dbpart	vds_dbpart	Numeric	Database partition

Label	CEF Label	Type	Usage
pol	cs1	Text	Policy name
rule	vds_rule	Text	Name of policy rule set

## Description

None

## Message ID : COM0010I

## Severity

Information

## Long Form

The Security Server received a backup request from host {0} for dbinstance({1}), dbalias({2}), dbpartition({3}).

## Short Form

received backup req from host

### Parameters

Label	CEF Label	Type	Usage
-------	-----------	------	-------

Message ID : COM0009I

Label	CEF Label	Type	Usage
shost	shost	Text	Source host name
dbinstance	vds_dbinstance	Text	Database instance
dbalias	vds_dbalias	Text	Database alias
dbpart	vds_dbpart	Numeric	Database partition

## Description

None

## Message ID : COM0011I

## Severity

Information

## Long Form

The Security Server received a restore request from host {0} for dbinstance({1}), dbalias({2}), dbpartition({3}).

## Short Form

received restore req from host

## Parameters

Label	CEF Label	Type	Usage
shost	shost	Text	Source host name
dbinstance	vds_dbinstance	Text	Database instance
dbalias	vds_dbalias	Text	Database alias
dbpart	vds_dbpart	Numeric	Database partition

## Description

None

## Message ID : COM0012I

## Severity

Information

## Long Form

The Security Server is unable to locate a key or header information needed for the backup request from host {0} for dbinstance({1}), dbalias({2}), dbpartition({3}). The backup request will be denied.

## Short Form

unable to locate key for req from host

### Parameters

Label	CEF Label	Type	Usage
shost	shost	Text	Source host name
dbinstance	vds_dbinstance	Text	Database instance
dbalias	vds_dbalias	Text	Database alias
dbpart	vds_dbpart	Numeric	Database partition

## Description

None

## Message ID : COM0013I

## Severity

Information

## Long Form

The Security Server is unable to locate a key needed for the restore request from host {0} for dbinstance({1}), dbalias({2}), dbpartition({3}). The restore request will be denied.

Message ID : COM0012I

## Short Form

No short form is provided for this message type

## Description

None

## Message ID : COM0014I

## Severity

Information

## Long Form

The Security Server denied a backup request from host {0} for dbinstance({1}), dbalias({2}), dbpartition({3}). There were no applicable policy or applicable rule found.

## Short Form

No short form is provided for this message type

## Description

None

Message ID : COM0013I

## Message ID : COM0015I

### Severity

Information

### Long Form

The Security Server denied a restore request from host {0} for dbinstance({1}), dbalias({2}), dbpartition({3}). There were no applicable policy or applicable rule found.

### Short Form

denied restore req from host

### Parameters

Label	CEF Label	Type	Usage
shost	shost	Text	Source host name
dbinstance	vds_dbinstance	Text	Database instance
dbalias	vds_dbalias	Text	Database alias
dbpart	vds_dbpart	Numeric	Database partition

## Description

None

**Message ID : COM0016I**

## Severity

Information

## Long Form

The Security Server permitted a backup request from host {0} for server name({1}), Server Number({3}). The policy used is ({4}), the rule used is ({5}).

## Short Form

No short form is provided for this message type

## Description

None

**Message ID : COM0017I**



## Severity

Information

## Long Form

The Security Server denied a backup request from host {0} for server name({1}), Server Number({3}). The policy used is ({4}), the rule used is ({5}).

## Short Form

No short form is provided for this message type

## Description

None

## Message ID : COM0018I

## Severity

Information

## Long Form

The Security Server permitted a restore request from host {0} for server name({1}), Server Number({3}). The policy used is ({4}), the rule used is ({5}).

Message ID : COM0017I

## Short Form

No short form is provided for this message type

## Description

None

## Message ID : COM0019I

## Severity

Information

## Long Form

The Security Server denied a restore request from host {0} for server name({1}), Server Number({3}). The policy used is ({4}), the rule used is ({5}).

## Short Form

No short form is provided for this message type

## Description

None

Message ID : COM0018I

## **Message ID : COM0020I**

### **Severity**

Information

### **Long Form**

The Security Server received a backup request from host {0} for server name({1}), Server Number({3}).

### **Short Form**

No short form is provided for this message type

### **Description**

None

## **Message ID : COM0021I**

### **Severity**

Information

### **Long Form**

The Security Server received a restore request from host {0} for server name({1}), Server Number({3}).

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : COM0022I**

## **Severity**

Information

## **Long Form**

The Security Server is unable to locate a key or header information needed for the backup request from host {0} for server name({1}), Server Number({3}). The backup request will be denied.

## **Short Form**

No short form is provided for this message type

## **Description**

None

Message ID : COM0021I

## **Message ID : COM0023I**

### **Severity**

Information

### **Long Form**

The Security Server is unable to locate a key needed for the restore request from host {0} for server name({1}), Server Number({3}). The restore request will be denied.

### **Short Form**

No short form is provided for this message type

### **Description**

None

## **Message ID : COM0024I**

### **Severity**

Information

## Long Form

The Security Server denied a backup request from host {0} for server name({1}), Server Number({3}). There were no applicable policy or applicable rule found.

## Short Form

No short form is provided for this message type

## Description

None

## Message ID : COM0025I

## Severity

Information

## Long Form

The Security Server denied a restore request from host {0} for server name({1}), Server Number({3}). There were no applicable policy or applicable rule found.

## Short Form

No short form is provided for this message type

Message ID : COM0024I

## Description

None

**Message ID : COM0173I**

## Severity

Information

## Long Form

The Security Server denied a request from unauthorized host "{0}".

## Short Form

denied req from unauthorized host

## Parameters

Label	CEF Label	Type	Usage
shost	shost	Text	Source host name

## Description

None

Message ID : COM0025I

## Message ID : COM0314I

### Severity

Information

### Long Form

The Security Server was able to successfully send security configuration changes to the agent on host {0}.

### Short Form

security config push ok

#### Parameters

Label	CEF Label	Type	Usage
shost	shost	Text	Source host name

### Description

None

## Message ID : COM0538I



## **Severity**

Information

## **Long Form**

The Security Server is unable to browse the agent at host {0}. The agent is not registered with the server or communication with the agent is not allowed. Please ensure that the agent is registered with the server and communication with the agent is allowed.

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : COM0559I**

## **Severity**

Information

## **Long Form**

The communication version of agent on host {0} is not compatible to support this operation.

## Short Form

No short form is provided for this message type

## Description

None

## Message ID : COM0572I

## Severity

Information

## Long Form

The Security Server is waiting for replication completion before pushing configuration to host {0}. The Security Server will make another attempt to contact the host at approximately {1}.

## Short Form

waiting for replication completion

## Parameters

Label	CEF Label	Type	Usage
shost	shost	Text	Source host name

Label	CEF Label	Type	Usage
nexttime	vds_nexttime	Text	Time of next attempt

## Description

None

## Message ID : COM0574I

## Severity

Information

## Long Form

Primary Server is unable to perform replication synchronization to failover server "{0}" for more than "{1}" minutes.

## Short Form

primary unable to perform replication synchronization to failover

## Parameters

Label	CEF Label	Type	Usage
shost	shost	Text	Source host name

Label	CEF Label	Type	Usage
mins	vds_mins	Numeric	Elaped minutes

## Description

None

## Message ID : COM0649I

## Severity

Information

## Long Form

The communication version of the registration authority on host {0} is not compatible to support this operation.

## Short Form

No short form is provided for this message type

## Description

None

## Message ID : COM0666I

### Severity

Information

### Long Form

There are {0} logs dropped for the past hour during the syslog-ng host {1} downtime.

### Short Form

logs dropped in past hour during syslog downtime

#### Parameters

Label	CEF Label	Type	Usage
scount	vds_scount	Text	A generic count as a string
shost	shost	Text	Source host name

### Description

None

## **Message ID : COM0707I**

### **Severity**

Information

### **Long Form**

The host password of host "{0}" is changed, it needs to communicate to primary server get configuration.

### **Short Form**

No short form is provided for this message type

### **Description**

None

## **Message ID : COM0710I**

### **Severity**

Information

### **Long Form**

The {0} agent at host {1} is unregistered successfully.

## Short Form

agent unregistered ok

### Parameters

Label	CEF Label	Type	Usage
agent	deviceProcessName	Text	The short identifier of the agent software
shost	shost	Text	Source host name

## Description

None

## Message ID : COM0711I

## Severity

Information

## Long Form

The {0} agent at host {1} requested deletion of the host. The host {1} is deleted from the security server {2} successfully.

## Short Form

agent requested host deletion

### Parameters

Label	CEF Label	Type	Usage
agent	deviceProcessName	Text	The short identifier of the agent software
shost	shost	Text	Source host name
shost	shost	Text	Source host name

## Description

None

## Message ID : COM1311I

### Severity

Information

## Long Form

Host {0} enable one-way communication



## Short Form

Host enable one-way communication

### Parameters

Label	CEF Label	Type	Usage
shost	shost	Text	Source host name

## Description

None

## Message ID : COM1312I

## Severity

Information

## Long Form

Host {0} disable one-way communication

## Short Form

Host disable one-way communication

Message ID : COM1311I

### Parameters

Label	CEF Label	Type	Usage
shost	shost	Text	Source host name

### Description

None

### Message ID : COM1519I

### Severity

Information

### Long Form

Generated a key for host "{0}".

### Short Form

Generated a key for host

### Parameters

Label	CEF Label	Type	Usage
shost	shost	Text	Source host name

Message ID : COM1312I

Label	CEF Label	Type	Usage

## Description

None

## Message ID : COM1521I

## Severity

Information

## Long Form

Replication to other server "{0} recovered".

## Short Form

Replication to other server recovered

## Parameters

Label	CEF Label	Type	Usage
shost	shost	Text	Source host name

## **Description**

None

**Message ID : COM1784I**

## **Severity**

Information

## **Long Form**

[[0]] network ping ...

## **Short Form**

No short form is provided for this message type

## **Description**

None

**Message ID : COM1813I**

## **Severity**

Information

Message ID : COM1521I

## Long Form

The host "{0}" reported incompatible agent state. {1}.

## Short Form

No short form is provided for this message type

## Description

None

## Message ID : COM1835I

## Severity

Information

## Long Form

The Security Server pushed following section(s) to the agent {0} :: {1}.#

## Short Form

The Security Server pushed following section(s) to the agent

### Parameters

Label	CEF Label	Type	Usage
shost	shost	Text	Source host name

### Description

None

**Message ID : COM4601I**

### Severity

Information

### Long Form

Successful Agent init with Key Manager ({}).

### Short Form

Comms init OK

### Parameters

Label	CEF Label	Type	Usage
url	request	Text	A uniform resource location

Message ID : COM1835I

Label	CEF Label	Type	Usage

## Description

None

## Message ID : COM4602I

## Severity

Information

## Long Form

Failed Agent init with Key Manager ({0}).

## Short Form

Comms init fail

## Parameters

Label	CEF Label	Type	Usage
url	request	Text	A uniform resource location

## **Description**

None

**Message ID : COM4626I**

## **Severity**

Information

## **Long Form**

The agent failed to initialize with the Key Manager. This may indicate that the connection to the server is down, the agent's host has been deleted from the Key Manager, or "Communication Enabled" for the host has not been enabled in the Key Manager UI.

## **Short Form**

No short form is provided for this message type

## **Description**

None

**Message ID : COM4627I**



## Severity

Information

## Long Form

The agent's host may no longer be registered with a Key Manager. The agent's host may have been deleted from the Key Manager. You may want to run the register\_host utility to re-register the agent with a Key Manager.

## Short Form

*Agent not registered*

### Parameters

No parameters are provided for this message type

## Description

None

# Logger COM: Warnings

**Message ID : COM0591W**

## Severity

Warning

## Long Form

The agent at host {0} failed to generate the signature on this file {1}. Please check the VMD log for the cause.

## Short Form

agent failed to generate signature on file

### Parameters

Label	CEF Label	Type	Usage
shost	shost	Text	Source host name
filePath	filePath	Text	Full path to file

## Description

None

## **Message ID : COM0607W**

### **Severity**

Warning

### **Long Form**

Unable to sign the source on host {0}. Please check if the source exists on the host.

### **Short Form**

No short form is provided for this message type

### **Description**

None

## **Message ID : COM0612W**

### **Severity**

Warning

### **Long Form**

The Security Server will not try to push the security configuration to the host {0} any more because the retry attempts have reached the maximum number.

Message ID : COM0607W

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : COM0614W**

## **Severity**

Warning

## **Long Form**

Warning: Requires atleast one parameter (description/password/readonly). The Administrator info will not be changed.

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : COM0617W**

### **Severity**

Warning

### **Long Form**

The user must have at least one role.

### **Short Form**

No short form is provided for this message type

### **Description**

None

## **Message ID : COM0618W**

### **Severity**

Warning

### **Long Form**

The domain name is needed to delete a domain.

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : COM0667W**

## **Severity**

Warning

## **Long Form**

The agent at host {0} uses challenge response compatible host password.

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : COM1251W**

### **Severity**

Warning

### **Long Form**

The password and description cannot be changed at the same time. Please supply either password info or description info.

### **Short Form**

No short form is provided for this message type

### **Description**

None

## **Message ID : COM1314W**

### **Severity**

Warning

### **Long Form**

This security configuration must be downloaded from primary server.

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : COM1323W**

## **Severity**

Warning

## **Long Form**

Please use the number between 0 and 100.

## **Short Form**

No short form is provided for this message type

## **Description**

None

Message ID : COM1314W



## **Message ID : COM1337W**

### **Severity**

Warning

### **Long Form**

Adding more domain(s) is not allowed because the current domain count has exceeded the maximum number of domains allowed by the license.COM1348E=The agent type must be one of FS, DB2, IDS, KEY or KMIPC.

### **Short Form**

No short form is provided for this message type

### **Description**

None

## **Message ID : COM4605W**

### **Severity**

Warning

## Long Form

Logging destination changed from {0} to {1}

## Short Form

Upload dest change

### Parameters

Label	CEF Label	Type	Usage
shost	shost	Text	Source host name
url	request	Text	A uniform resource location

## Description

None

**Message ID : COM4632W**

## Severity

Warning

Message ID : COM4605W

## Long Form

There was a communication failure with the Key Manager. The server returned a fault: {0}{1}; "{2}"; Subcode: "{3}"; Reason: "{4}"; Detail: "{5}".

## Short Form

No short form is provided for this message type

## Description

None

## Message ID : COM4633W

## Severity

Warning

## Long Form

There was a communication failure with the Key Manager ({0}). The server returned a fault: {1}{2}; "{3}"; Subcode: "{4}"; Reason: "{5}"; Detail: "{6}".

## Short Form

SOAP client error

Message ID : COM4632W

## Parameters

Label	CEF Label	Type	Usage
url	request	Text	A uniform resource location
showStr	reason	Text	Code specifying reason for allowing access, if any
verno	vds_verno	Numeric	A version number
context	vds_context	Text	Fault context
subcode	vds_subcode	Text	Fault subcode
showStr	reason	Text	Code specifying reason for allowing access, if any
detail	vds_detail	Text	Fault detail

## Description

The agent is unable to reach the Security Server. You may see any of the following error messages: COM4583F, COM4633W, VMD3770F, VMD3885I or VMD3886I. You may experience any of the following:

1. Connection to the Security Server is down.
2. The VMD Host has been deleted from the Security Server.
3. The host does not have "Communication Enabled" in the Security Server UI.
4. The VMD's host may be deleted from the Security Server. Run the register\_host utility to re-register the VMD with the Security Server.

## Message ID : COM4634W

### Severity

Warning

### Long Form

The server at {0} attempted to contact this machine, but it was denied access due to an invalid certificate.

### Short Form

Bad cert from server

#### Parameters

Label	CEF Label	Type	Usage
url	request	Text	A uniform resource location

### Description

An attempt to contact the agent was rejected. This may be due to attempting to register an agent with a new Security Server after that agent was registered with a different Security Server. A COM4635W log message may give more details.

## Message ID : COM4635W

## Severity

Warning

## Long Form

A machine identifying itself as {0} tried to contact the VMD, but there was an error: {1}{2}; "{3}"; Subcode: "{4}"; Reason: "{5}"; Detail: "{6}".

## Short Form

SOAP server error

### Parameters

Label	CEF Label	Type	Usage
url	request	Text	A uniform resource location
showStr	reason	Text	Code specifying reason for allowing access, if any
verno	vds_verno	Numeric	A version number
context	vds_context	Text	Fault context
subcode	vds_subcode	Text	Fault subcode
showStr	reason	Text	Code specifying reason for allowing access, if any
detail	vds_detail	Text	Fault detail

## **Description**

The Security Server tried to contact the agent but did not succeed. The "reason" field tells you why the certificate was rejected, and the "detail" field tells you what action was attempted at the time.

# Logger CXM: Errors

**Message ID : CXM0654E**

## Severity

Error

## Long Form

{0}.

## Short Form

err

## Parameters

Label	CEF Label	Type	Usage
showStr	reason	Text	Code specifying reason for allowing access, if any

## Description

None



## Message ID : CXM0657E

### Severity

Error

### Long Form

The user "{0}" failed to generate the certificate signing request files.

### Short Form

failed to generate cert signing req files

### Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name

### Description

None

## Message ID : CXM0658E

## Severity

Error

## Long Form

The user "{0}" failed to import the signed certificates into the security server. Reason: {1}

## Short Form

failed to import signed certs

### Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
showStr	reason	Text	Code specifying reason for allowing access, if any

## Description

None

## Message ID : CXM0659E

## Severity

Error

## Long Form

The user "{0}" failed to import the LDAP certificate. Reason: {1}

## Short Form

failed to import LDAP certificate

### Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
showStr	reason	Text	Code specifying reason for allowing access, if any

## Description

None

**Message ID : CXM0770E**

## Severity

Error

## Long Form

The user "{0}" failed to import the trust certificate(s) into the security server.

## Short Form

failed to import trust certs

### Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name

## Description

None

## Message ID : CXM1354E

## Severity

Error

Message ID : CXM0770E

## **Long Form**

The sha1 signature hash algorithm in certificate "{0}" is not accepted.

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : CXM1355E**

## **Severity**

Error

## **Long Form**

The digital signature cannot be validated on "{0}" by "{1}". This may indicate the man-in-the-middle attack.

## **Short Form**

No short form is provided for this message type

## **Description**

None

**Message ID : CXM1356E**

## **Severity**

Error

## **Long Form**

The intermediate CA certificate is required.

## **Short Form**

No short form is provided for this message type

## **Description**

None

**Message ID : CXM1357E**

## **Severity**

Error

Message ID : CXM1355E

## **Long Form**

The trusted signed certificate issued by the certificate authority is required.

## **Short Form**

No short form is provided for this message type

## **Description**

None

**Message ID : CXM1358E**

## **Severity**

Error

## **Long Form**

Certificate already exists and was not replaced. Please generate a new CSR and choose a new signed certificate if you wish to replace the current one.

## **Short Form**

No short form is provided for this message type

Message ID : CXM1357E

## **Description**

None

**Message ID : CXM1359E**

## **Severity**

Error

## **Long Form**

The public keys or digital signatures mismatch. This may indicate the man-in-the-middle attack.

## **Short Form**

No short form is provided for this message type

## **Description**

None

**Message ID : CXM1360E**

## **Severity**

Error

Message ID : CXM1358E



## Long Form

{0} PEM file(s) do not exist.

## Short Form

No short form is provided for this message type

## Description

None

## Message ID : CXM1361E

## Severity

Error

## Long Form

The message-digest algorithm in certificate "{0}" is not accepted.

## Short Form

No short form is provided for this message type

## **Description**

None

## **Message ID : CXM1391E**

### **Severity**

Error

### **Long Form**

The certificate "{0}" is either expired or not effective yet or an invalid certificate.

### **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : CXM1392E**

### **Severity**

Error

Message ID : CXM1361E

## Long Form

The certificate is not a valid certificate.

## Short Form

No short form is provided for this message type

## Description

None

## Message ID : CXM1393E

## Severity

Error

## Long Form

The user "{0}" failed to import the syslog certificate for the syslog host "{1}". Reason: {2}

## Short Form

No short form is provided for this message type

## **Description**

None

**Message ID : CXM1693E**

## **Severity**

Error

## **Long Form**

The ripemd160 signature hash algorithm in certificate "{0}" is not accepted.

## **Short Form**

No short form is provided for this message type

## **Description**

None

# Logger CXM: Information

**Message ID : CXM0221I**

## Severity

Information

## Long Form

The Security Server received a certificate generation request from host "{0}".

## Short Form

received cert gen request

### Parameters

Label	CEF Label	Type	Usage
shost	shost	Text	Source host name

## Description

None

## Message ID : CXM0224I

### Severity

Information

### Long Form

The Security Server generated a certificate for host "{0}".

### Short Form

generated cert

#### Parameters

Label	CEF Label	Type	Usage
shost	shost	Text	Source host name

### Description

None

## Message ID : CXM0225I

## **Severity**

Information

## **Long Form**

The Certificate manager does not support GETs. Retry with a POST request.

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : CXM0646I**

## **Severity**

Information

## **Long Form**

The agent on host {0} has requested a certificate.

## Short Form

agent cert req

### Parameters

Label	CEF Label	Type	Usage
shost	shost	Text	Source host name

## Description

None

## Message ID : CXM0647I

## Severity

Information

## Long Form

The Vormetric Registration Authority (RA) has forwarded the request to the {0} Certificate Authority (CA).

## Short Form

ra forwarded request to ca



### Parameters

Label	CEF Label	Type	Usage
provider	vds_provider	Text	Certificate authority/provider

### Description

None

### Message ID : CXM0648I

### Severity

Information

### Long Form

The Vormetric Registration Authority (RA) received the certificate from the {0} CA and forwarded the certificate to the host {1}.

### Short Form

ra forwarded cert to agent

### Parameters

Label	CEF Label	Type	Usage
provider	vds_provider	Text	Certificate authority/provider

Message ID : CXM0647I

Label	CEF Label	Type	Usage
shost	shost	Text	Source host name

## Description

None

## Message ID : CXM0655I

## Severity

Information

## Long Form

The user "{0}" successfully generated the certificate signing request files with subject(s): {1}.

## Short Form

user generated cert signing req files

## Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name

Message ID : CXM0648I

Label	CEF Label	Type	Usage

## Description

None

## Message ID : CXM0656I

## Severity

Information

## Long Form

The user "{0}" successfully imported the signed certificates into the security server.

## Short Form

successfully imported signed certs

## Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name

## Description

None

## Message ID : CXM0659I

## Severity

Information

## Long Form

The user "{0}" successfully imported the signed certificates into the security server. DSM CA certificate Subject DN: {1}, Issuer DN: {2} and ExpirationDate: {3}. Agent CA certificate Subject DN: {4}, Issuer DN: {5} and ExpirationDate: {6}.

## Short Form

successfully imported signed certificates

## Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name

## Description

None

## Message ID : CXM0660I

## Severity

Information

## Long Form

The user "{0}" successfully imported the signed certificates into the security server. DSM CA certificate Subject DN: {1}, Issuer DN: {2} and ExpirationDate: {3}.

## Short Form

successfully imported signed certificates

## Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name

## Description

None

**Message ID : CXM0661I**

## Severity

Information

## Long Form

The user "{0}" successfully imported the syslog certificate for the Syslog Host "{1}". Syslog certificate Subject DN: {2}, Issuer DN: {3} and ExpirationDate: {4}.

## Short Form

successfully imported syslog certificate

## Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name

## Description

None

## Message ID : CXM0662I

## Severity

Information

## Long Form

The user "{0}" successfully imported the LDAP certificate. LDAP certificate Subject DN: {1}, Issuer DN: {2} and ExpirationDate: {3}.

## Short Form

successfully imported LDAP certificate

## Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name

## Description

None

## Message ID : CXM0771I

## Severity

Information

## Long Form

The user "{0}" successfully imported the trust certificate(s) into the security server.

## Short Form

successfully imported trust certs

## Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name

## Description

None

Message ID : CXM0662I



## Message ID : CXM1340I

### Severity

Information

### Long Form

Host {0} registered into domain {1}, host group {2} using a shared secret

### Short Form

host registered using a shared secret

### Parameters

Label	CEF Label	Type	Usage
shost	shost	Text	Source host name
domain	domain	Text	A domain name (policy, network, users, etc)
group	group	Text	Group name

### Description

None

## Message ID : CXM1341I

### Severity

Information

### Long Form

Host {0} registered into domain {1} using a shared secret

### Short Form

host registered using a shared secret

### Parameters

Label	CEF Label	Type	Usage
shost	shost	Text	Source host name
domain	domain	Text	A domain name (policy, network, users, etc)

### Description

None

## Message ID : CXM1342I

### Severity

Information

### Long Form

Host {0} registered into domain {1} using fingerprint

### Short Form

host registered using fingerprint

### Parameters

Label	CEF Label	Type	Usage
shost	shost	Text	Source host name
domain	domain	Text	A domain name (policy, network, users, etc)

### Description

None

## Message ID : CXM1344I

### Severity

Information

### Long Form

User "{0}" modified shared secret of domain {1}, host group {2}

### Short Form

user modified shared secret

### Parameters

Label	Type	Usage
user	Text	User name
domain	Text	A domain name (policy, network, users, etc)
group	Text	Group name

### Description

None

## Message ID : CXM1345I

### Severity

Information

### Long Form

User "{0}" modified shared secret of domain {1}

### Short Form

user modified shared secret

### Parameters

Label	Type	Usage
user	Text	User name
domain	Text	A domain name (policy, network, users, etc)

### Description

None

## Message ID : CXM1346I

### Severity

Information

### Long Form

Shared secret of domain {0}, host group {1} expired

### Short Form

shared secret expired

### Parameters

Label	Type	Usage
domain	Text	A domain name (policy, network, users, etc)
group	Text	Group name

### Description

None

## Message ID : CXM1347I

### Severity

Information

### Long Form

Shared secret of domain {0} expired

### Short Form

{0} {1} CEF:0|Vormetric, Inc.|dsm|{3}|CXM1346I|shared secret expired|3|cs4Label=logger cs4=CXM spid={2} rt={4} dvchost={1}

### Parameters

Label	Type	Usage
domain	Text	A domain name (policy, network, users, etc)

### Description

None

## Message ID : CXM1624I

## Severity

Information

## Long Form

Certificate details for host "{0}", {1}.

## Short Form

generated cert

### Parameters

Label	CEF Label	Type	Usage
shost	shost	Text	Source host name
cert	cert	Text	Certificate type or name

## Description

None

## Message ID : CXM1732I



## Severity

Information

## Long Form

The Security Server exported a {2}CA certificate with Subject "{0}" by user "{1}".

## Short Form

No short form is provided for this message type

## Description

None

## Message ID : CXM1748I

## Severity

Information

## Long Form

A registration token that will be expired at "{0}" was generated in domain "{1}" by user "{2}" for host "{3}".

## Short Form

registration token generated in domain

### Parameters

Label	CEF Label	Type	Usage
domain	domain	Text	A domain name (policy, network, users, etc)
user	suser	Text	User name
shost	shost	Text	Source host name

## Description

None

# Logger CXM: Warnings

**Message ID : CXM0222W**

## Severity

Warning

## Long Form

The Security Server denied a certificate generation request from "{0}". The {1} agent is not enabled for the host in server.

## Short Form

denied cert gen request: agent not enabled

## Parameters

Label	CEF Label	Type	Usage
shost	shost	Text	Source host name
agent	deviceProcessName	Text	The short identifier of the agent software

## Description

An agent certificate generation request was rejected as unauthorized. Select the "Registration Allowed" box for the appropriate Agent on the Host page.

## Message ID : CXM0223W

### Severity

Warning

### Long Form

The Security Server denied a certificate generation request from "{0}". An entry already exists for the host.

### Short Form

denied cert gen request: duplicate

#### Parameters

Label	CEF Label	Type	Usage
shost	shost	Text	Source host name

### Description

A duplicate agent with the same name already exists. Please clear the existing agent fingerprint and re-register the agent with the server.

## Message ID : CXM0226W

## Severity

Warning

## Long Form

License has expired, The Security Server is continuing with certificate renewal request from "{0}". Renew expired license.

## Short Form

processing cert gen request:renew expired license

### Parameters

Label	CEF Label	Type	Usage
shost	shost	Text	Source host name

## Description

None

## Message ID : CXM0227W

## Severity

Warning

Message ID : CXM0226W

## Long Form

"{0}" is not defined in the initial DSM server.

## Short Form

cert gen request:failover server not defined

### Parameters

Label	CEF Label	Type	Usage
shost	shost	Text	Source host name

## Description

None

## Message ID : CXM0289W

## Severity

Warning

## Long Form

The Security Server denied a certificate generation request from "{0}". The host is not reachable.

Message ID : CXM0227W

## Short Form

denied cert gen request:host unreachable

### Parameters

Label	CEF Label	Type	Usage
shost	shost	Text	Source host name

## Description

An agent certificate generation request has been denied because the agent is unreachable. Check for the following:

1. Proper name resolution.
2. Confirm host/server connection is established.
3. Check the firewall for proper port configuration.

## Message ID : CXM0802W

### Severity

Warning

## **Long Form**

There is missing server certificate chain...

## **Short Form**

No short form is provided for this message type

## **Description**

None

**Message ID : CXM1250W**

## **Severity**

Warning

## **Long Form**

There is missing APPID certificate chain...

## **Short Form**

No short form is provided for this message type

Message ID : CXM0802W



## Description

None

**Message ID : CXM1294W**

## Severity

Warning

## Long Form

The agent registration on host {0} has been denied due to license validation failed: {1}

## Short Form

agent license validation failed

## Parameters

Label	CEF Label	Type	Usage
shost	shost	Text	Source host name

## Description

None

Message ID : CXM1250W

## Message ID : CXM1343W

### Severity

Warning

### Long Form

Host {0} ({1}) attempted and failed to register using a shared secret

### Short Form

host failed to register using a shared secret

### Parameters

Label	CEF Label	Type	Usage
shost	shost	Text	Source host name

### Description

None

## Message ID : CXM1363W

## Severity

Warning

## Long Form

Domain {0} not found

## Short Form

Domain not found

### Parameters

Label	Type	Usage
domain	Text	A domain name (policy, network, users, etc)

## Description

None

**Message ID : CXM1423W**

## Severity

Warning

Message ID : CXM1363W

## Long Form

Registration is locked from IP address "{0}", because of too many failed attempts. It will be unlocked in "{1}" minutes.

## Short Form

host registration locked due to too many failed attempts

### Parameters

Label	CEF Label	Type	Usage
shost	shost	Text	Source host name

## Description

None

## Message ID : CXM1520W

## Severity

Warning

## Long Form

The Security Server denied a certificate generation request from "{0}". The host already has a {1} agent registered with a different one way communication setting.

Message ID : CXM1423W

## Short Form

denied cert gen request:inconsistent one way comm setting

### Parameters

Label	CEF Label	Type	Usage
shost	shost	Text	Source host name

## Description

None

## Message ID : CXM1749W

## Severity

Warning

## Long Form

The registration token from host "{0}" is invalid. Reason: {1}.

## Short Form

No short form is provided for this message type

Message ID : CXM1520W

## Description

None

# Logger DA0: Errors

**Message ID : DA001322E**

## Severity

Error

## Long Form

"{0}" is not a valid name. The name must consist of alpha-numeric characters; and the only non-alpha-numeric characters allowed are dot (.), and dash (-).

## Short Form

No short form is provided for this message type

## Description

None

**Message ID : DA001323E**

## Severity

Error

## **Long Form**

The length of the host name exceeds the maximum 255 characters

## **Short Form**

No short form is provided for this message type

## **Description**

None



## **Logger DAO: Errors**

**Message ID : DAO0038E**

### **Severity**

Error

### **Long Form**

An internal error occurred on the Security Server. Refer to cgss.log and server.log for details. Call support if necessary.

### **Short Form**

No short form is provided for this message type

### **Description**

None

**Message ID : DAO0039E**

### **Severity**

Error

## Long Form

The Security Server failed to connect to the repository database. Restart the Security Server and retry. If the problem persists, call support.

## Short Form

No short form is provided for this message type

## Description

None

## Message ID : DAO0040E

## Severity

Error

## Long Form

The Security Server failed to persist data into the repository database. Refer to cgss.log and server.log for details. Call support if necessary.

## Short Form

No short form is provided for this message type

Message ID : DAO0039E

## **Description**

None

**Message ID : DAO0041E**

## **Severity**

Error

## **Long Form**

The Security Server failed to connect to the repository database. Ensure that the database is functional and running.

## **Short Form**

No short form is provided for this message type

## **Description**

None

**Message ID : DAO0042E**

## **Severity**

Error

Message ID : DAO0040E

## **Long Form**

Host Name "{0}" is already in use. Specify a different name.

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : DAO0043E**

## **Severity**

Error

## **Long Form**

The selected host no longer exists.

## **Short Form**

No short form is provided for this message type

**Description**

None

**Message ID : DAO0044E****Severity**

Error

**Long Form**

One or more hosts no longer exist.

**Short Form**

No short form is provided for this message type

**Description**

None

**Message ID : DAO0049E****Severity**

Error

Message ID : DAO0043E

## **Long Form**

Host Group Name "{0}" is already in use. Specify a different name.

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : DAO0050E**

## **Severity**

Error

## **Long Form**

The selected host group no longer exists.

## **Short Form**

No short form is provided for this message type

## **Description**

None

**Message ID : DAO0051E**

## **Severity**

Error

## **Long Form**

One or more host groups no longer exist.

## **Short Form**

No short form is provided for this message type

## **Description**

None

**Message ID : DAO0056E**

## **Severity**

Error

Message ID : DAO0050E

## **Long Form**

A policy with name "{0}" already exists in domain "{1}". Please specify a different policy name.

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : DAO0057E**

## **Severity**

Error

## **Long Form**

The selected policy no longer exists.

## **Short Form**

No short form is provided for this message type



## **Description**

None

**Message ID : DAO0058E**

## **Severity**

Error

## **Long Form**

One or more rules in the policy have non-unique rule names. Check the rule names and make sure they are different.

## **Short Form**

No short form is provided for this message type

## **Description**

None

**Message ID : DAO0059E**

## **Severity**

Error

Message ID : DAO0057E

## **Long Form**

One or more conditions in some rule(s) have non-unique names. Check the conditions for each rule and make sure they are different.

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : DAO0060E**

## **Severity**

Error

## **Long Form**

Policy with name "{0}" no longer exists. Refresh the list of Policies before retrying the operation.

## **Short Form**

No short form is provided for this message type

## **Description**

None

**Message ID : DAO0066E**

## **Severity**

Error

## **Long Form**

The selected key pair no longer exists.

## **Short Form**

No short form is provided for this message type

## **Description**

None

**Message ID : DAO0067E**

## **Severity**

Error

Message ID : DAO0060E

## **Long Form**

One or more keys no longer exist.

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : DAO0069E**

## **Severity**

Error

## **Long Form**

Affiliated Key Name "{0}" is already in use. Specify a different name.

## **Short Form**

No short form is provided for this message type

## **Description**

None

**Message ID : DAO0070E**

## **Severity**

Error

## **Long Form**

The selected affiliated keys no longer exist.

## **Short Form**

No short form is provided for this message type

## **Description**

None

**Message ID : DAO0081E**

## **Severity**

Error

Message ID : DAO0069E

## **Long Form**

One of the fields in an audit log entry contains a NULL value. Check the failed audit log file for the potential error. Fields in an audit log entry cannot be NULL.

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : DAO0087E**

## **Severity**

Error

## **Long Form**

User Name "{0}" is already in use. Specify a different name.

## **Short Form**

No short form is provided for this message type

## **Description**

None

**Message ID : DAO0088E**

## **Severity**

Error

## **Long Form**

The selected user no longer exists.

## **Short Form**

No short form is provided for this message type

## **Description**

None

**Message ID : DAO01299E**

## **Severity**

Error

Message ID : DAO0087E

## **Long Form**

Duplicate certificate exists.

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : DAO01320E**

## **Severity**

Error

## **Long Form**

Unable to import policy {0}, the set {1} exceeds 100MB limit

## **Short Form**

No short form is provided for this message type

Message ID : DAO01299E



**Description**

None

**Message ID : DAO01328E****Severity**

Error

**Long Form**

Domain with name "{0}" not found

**Short Form**

No short form is provided for this message type

**Description**

None

**Message ID : DAO01329E****Severity**

Error

Message ID : DAO01320E

## **Long Form**

User with name "{0}" not found

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : DAO01335E**

## **Severity**

Error

## **Long Form**

Host port {0} is not a valid port number. A valid network port should be in the range 1024-65535.

## **Short Form**

No short form is provided for this message type

Message ID : DAO01329E

## **Description**

None

**Message ID : DAO01336E**

## **Severity**

Error

## **Long Form**

QOS rekeyrate {0} is not in valid limit. A valid rekeyrate should be in the range 0-32767.

## **Short Form**

No short form is provided for this message type

## **Description**

None

**Message ID : DAO01342E**

## **Severity**

Error

Message ID : DAO01335E

## **Long Form**

LDT Schedule {0} not found

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : DAO01343E**

## **Severity**

Error

## **Long Form**

LDT Schedule {0} already exists

## **Short Form**

No short form is provided for this message type

Message ID : DAO01342E

**Description**

None

**Message ID : DAO01344E****Severity**

Error

**Long Form**

LDT Schedule {0} is associated with {1}, cannot be deleted

**Short Form**

No short form is provided for this message type

**Description**

None

**Message ID : DAO01346E****Severity**

Error

Message ID : DAO01343E

## **Long Form**

System defined LDT Schedule {0} cannot be modified

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : DAO01347E**

## **Severity**

Error

## **Long Form**

System defined LDT Schedule {0} cannot be deleted

## **Short Form**

No short form is provided for this message type

## **Description**

None

**Message ID : DAO01348E**

## **Severity**

Error

## **Long Form**

LDT is not enabled for host {0}

## **Short Form**

No short form is provided for this message type

## **Description**

None

**Message ID : DAO01349E**

## **Severity**

Error

Message ID : DAO01347E

## Long Form

Audit log configuration exists for Docker Host {0} for imageId {1} containerId {2}

## Short Form

No short form is provided for this message type

## Description

None

## Message ID : DAO01350E

## Severity

Error

## Long Form

Cannot delete non docker audit log configuration for Host {0} with audit log configuration id {1}

## Short Form

No short form is provided for this message type

Message ID : DAO01349E



## **Description**

None

**Message ID : DAO01351E**

## **Severity**

Error

## **Long Form**

User {0} updated docker meta data for host {1}

## **Short Form**

No short form is provided for this message type

## **Description**

None

**Message ID : DAO01384E**

## **Severity**

Error

Message ID : DAO01350E

## **Long Form**

Unauthorized domain

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : DAO01392E**

## **Severity**

Error

## **Long Form**

Non unique key shares found. The key shares should be unique.

## **Short Form**

No short form is provided for this message type

Message ID : DAO01384E

**Description**

None

**Message ID : DAO01400E****Severity**

Error

**Long Form**

Attribute {0} value is not unique

**Short Form**

No short form is provided for this message type

**Description**

None

**Message ID : DAO01518E****Severity**

Error

Message ID : DAO01392E

## **Long Form**

FS Communication Port cannot be the same as VDE Communication Port

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : DAO01658E**

## **Severity**

Error

## **Long Form**

Attribute MUID value is not unique

## **Short Form**

No short form is provided for this message type

## **Description**

None

**Message ID : DAO01659E**

## **Severity**

Error

## **Long Form**

Attribute EXT\_KID value is not unique

## **Short Form**

No short form is provided for this message type

## **Description**

None

**Message ID : DAO0226E**

## **Severity**

Error

Message ID : DAO01658E

## **Long Form**

Hibernate internal error.

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : DAO0242E**

## **Severity**

Error

## **Long Form**

Host or host group "{0}" has already been guarded by policy "{1}".

## **Short Form**

No short form is provided for this message type

## **Description**

None

**Message ID : DAO0246E**

## **Severity**

Error

## **Long Form**

Host or host group "{0}" is not guarded by policy "{1}". Nothing was done with the unguard operation.

## **Short Form**

No short form is provided for this message type

## **Description**

None

**Message ID : DAO0247E**

## **Severity**

Error

Message ID : DAO0242E

## **Long Form**

Host "{0}" is not guarded by policy "{1}". Nothing was done with the update operation.

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : DAO0249E**

## **Severity**

Error

## **Long Form**

Policy "{0}" does not exist.

## **Short Form**

No short form is provided for this message type



**Description**

None

**Message ID : DAO0250E****Severity**

Error

**Long Form**

There is no policy to guard host "{0}".

**Short Form**

No short form is provided for this message type

**Description**

None

**Message ID : DAO0268E****Severity**

Error

Message ID : DAO0249E

## Long Form

Administrator "{0}" account is locked due to multiple failed login attempts.

## Short Form

account locked - multiple failed logins

### Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name

## Description

None

**Message ID : DAO0291E**

## Severity

Error

## Long Form

The host or host group "{0}" has already had an enabled guard with another offline policy.

Message ID : DAO0268E

## Short Form

No short form is provided for this message type

## Description

None

## Message ID : DAO0297E

## Severity

Error

## Long Form

Administrator "{0}" failed to login at {1} from client with IP address {2}.

## Short Form

login failed from client with IP address {5}

## Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name

Message ID : DAO0291E

Label	CEF Label	Type	Usage

## Description

None

**Message ID : DAO0304E**

## Severity

Error

## Long Form

Server node already exists with name "{0}". Server node name is case insensitive.

## Short Form

No short form is provided for this message type

## Description

None

Message ID : DAO0297E

## **Message ID : DAO0671E**

### **Severity**

Error

### **Long Form**

The host with ID {0} agent type "{1}" is already in use. Specify a different host and agent type.

### **Short Form**

No short form is provided for this message type

### **Description**

None

## **Message ID : DAO0705E**

### **Severity**

Error

### **Long Form**

The report template is invalid.

Message ID : DAO0671E

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : DAO0706E**

## **Severity**

Error

## **Long Form**

Failed to retrieve report results.

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : DAO0807E**

### **Severity**

Error

### **Long Form**

The same license has already been imported.

### **Short Form**

No short form is provided for this message type

### **Description**

None

## **Message ID : DAO0855E**

### **Severity**

Error

### **Long Form**

Host license type can not be changed.

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : DAO1632E**

## **Severity**

Error

## **Long Form**

Invalid Input Data.

## **Short Form**

No short form is provided for this message type

## **Description**

None



## **Message ID : DAO1633E**

### **Severity**

Error

### **Long Form**

Registration Shared Secret not found.

### **Short Form**

No short form is provided for this message type

### **Description**

None

## **Message ID : DAO1634E**

### **Severity**

Error

### **Long Form**

Cannot delete Registration Shared Secret, Since its HostGroup is shared from external.

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : DAO1635E**

## **Severity**

Error

## **Long Form**

Registration Shared Secret not created.

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : DAO1636E**

### **Severity**

Error

### **Long Form**

Secret not created.

### **Short Form**

No short form is provided for this message type

### **Description**

None

## **Message ID : DAO1666E**

### **Severity**

Error

### **Long Form**

Failed adding new HA node, check if the node is reachable on port 5432, or an 'ha cleanup' from CLI is required.

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : DAO1718E**

## **Severity**

Error

## **Long Form**

Disable Administrator settings "{0}" by administrator "{1}".

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : DAO1727E**

### **Severity**

Error

### **Long Form**

The host is unreachable, please run network check port for host on port 5432

### **Short Form**

No short form is provided for this message type

### **Description**

None

## **Message ID : DAO1750E**

### **Severity**

Error

### **Long Form**

Failed to generate registration token.

Message ID : DAO1727E

## **Short Form**

No short form is provided for this message type

## **Description**

None

# Logger DAO: Information

**Message ID : DAO0045I**

## Severity

Information

## Long Form

Administrator "{0}" added host "{1}".

## Short Form

add host

### Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
shost	shost	Text	Source host name

## Description

None

## Message ID : DAO0046I

### Severity

Information

### Long Form

Administrator "{0}" deleted host "{1}".

### Short Form

delete host

#### Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
shost	shost	Text	Source host name

### Description

None



## Message ID : DAO0047I

### Severity

Information

### Long Form

Administrator "{0}" renamed host "{1}" to "{2}".

### Short Form

rename host

### Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
shost	shost	Text	Source host name
altHost	vds_altHost	Text	Alternate host name in rename operations

### Description

None

## Message ID : DAO0048I

### Severity

Information

### Long Form

Administrator "{0}" updated host "{1}".

### Short Form

update host

#### Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
shost	shost	Text	Source host name

### Description

None

## Message ID : DAO0049I

### Severity

Information

### Long Form

Administrator "{0}" updated host "{1}" unregistered agent "{2}".

### Short Form

unregister agent

#### Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
shost	shost	Text	Source host name
agent	agent	Text	The short identifier of the agent software

### Description

None

## Message ID : DAO0052I

### Severity

Information

### Long Form

Administrator "{0}" added host group "{1}".

### Short Form

add host group

#### Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
group	vds_group	Text	Group name

### Description

None

## Message ID : DAO0053I

### Severity

Information

### Long Form

Administrator "{0}" deleted host group "{1}".

### Short Form

delete host group

#### Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
group	vds_group	Text	Group name

### Description

None

## Message ID : DAO0055I

### Severity

Information

### Long Form

Administrator "{0}" updated host group "{1}".

### Short Form

update host group

#### Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
group	vds_group	Text	Group name

### Description

None

## Message ID : DAO0061I

### Severity

Information

### Long Form

Administrator "{0}" created offline policy "{1}".

### Short Form

create offline policy

#### Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
pol	cs1	Text	Policy name

### Description

None

## Message ID : DAO0062I

### Severity

Information

### Long Form

Administrator "{0}" deleted offline policy "{1}".

### Short Form

delete offline policy

#### Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
pol	cs1	Text	Policy name

### Description

None



## Message ID : DAO0063I

### Severity

Information

### Long Form

Administrator "{0}" updated offline policy "{1}" and renamed the policy to "{2}".

### Short Form

update/rename offline policy

### Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
pol	cs1	Text	Policy name
altPol	vds_altPol	Text	Alternate policy name in rename operations

### Description

None

## Message ID : DAO0064I

### Severity

Information

### Long Form

Administrator "{0}" updated offline policy "{1}".

### Short Form

update offline policy

#### Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
pol	cs1	Text	Policy name

### Description

None

## Message ID : DAO00711

### Severity

Information

### Long Form

{0} at "{1}" created Key Pair "{2}".

### Short Form

create key pair

### Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
shost	shost	Text	Source host name
key	cs3	Text	Name of key or key pair

### Description

None

## Message ID : DAO0072I

### Severity

Information

### Long Form

{0} at "{1}" deleted Key Pair "{2}".

### Short Form

delete key pair

### Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
shost	shost	Text	Source host name
key	cs3	Text	Name of key or key pair

### Description

None

## Message ID : DAO0073I

### Severity

Information

### Long Form

Administrator "{0}" added Public Key "{1}".

### Short Form

add public key

#### Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
key	cs3	Text	Name of key or key pair

### Description

None

## Message ID : DAO0074I

### Severity

Information

### Long Form

Administrator "{0}" deleted Public Key "{1}".

### Short Form

delete public key

#### Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
key	cs3	Text	Name of key or key pair

### Description

None

## **Message ID : DAO0075I**

### **Severity**

Information

### **Long Form**

Affiliated Key "{0}" is updated. It is renamed to "{1}".

### **Short Form**

No short form is provided for this message type

### **Description**

None

## **Message ID : DAO0076I**

### **Severity**

Information

### **Long Form**

Affiliated Key "{0}" is updated.

## Short Form

No short form is provided for this message type

## Description

None

## Message ID : DAO0077I

## Severity

Information

## Long Form

Administrator "{0}" created Key Group "{1}".

## Short Form

create key group

### Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
group	vds_group	Text	Group name

Message ID : DAO0076I



Label	CEF Label	Type	Usage

## Description

None

## Message ID : DAO0078I

## Severity

Information

## Long Form

Administrator "{0}" deleted Key Group "{1}".

## Short Form

delete key group

## Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
group	vds_group	Text	Group name

Message ID : DAO0077I

## Description

None

## Message ID : DAO0079I

## Severity

Information

## Long Form

Administrator "{0}" updated Key Group "{1}" is updated. It is renamed to "{2}".

## Short Form

rename key group

## Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
group	vds_group	Text	Group name
altGroup	vds_altGroup	Text	Name of alternate group for multi-group operations

## Description

None

**Message ID : DAO0080I**

## Severity

Information

## Long Form

Administrator "{0}" updated Key Group "{1}".

## Short Form

update key group

## Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
group	vds_group	Text	Group name

## Description

None

## Message ID : DAO0082I

## Severity

Information

## Long Form

Administrator "{0}" updated Security Server configuration "{1}" from "{2}" to "{3}".

## Short Form

update config value

## Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name

## Description

None

Message ID : DAO0080I

## **Message ID : DAO0083I**

### **Severity**

Information

### **Long Form**

Administrator "{0}" added agent logging configuration for Host "{1}".

### **Short Form**

No short form is provided for this message type

### **Description**

None

## **Message ID : DAO0084I**

### **Severity**

Information

### **Long Form**

Administrator "{0}" updated agent logging configuration for Host "{1}".

## Short Form

audit config updated

### Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
shost	shost	Text	Source host name

## Description

None

**Message ID : DAO0085I**

## Severity

Information

## Long Form

Administrator "{0}" deleted agent logging configuration for Host "{1}".

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : DAO0086I**

## **Severity**

Information

## **Long Form**

Administrator "{0}" updated logging configuration for the default Agent.

## **Short Form**

No short form is provided for this message type

## **Description**

None

## Message ID : DAO0089I

### Severity

Information

### Long Form

Administrator "{0}" added a new {3}administrator "{1}" of user type "{2}" into the Security Server.

### Short Form

add admin user

#### Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
user	suser	Text	User name

### Description

None



## Message ID : DAO0090I

### Severity

Information

### Long Form

Administrator "{0}" deleted {2} administrator "{1}" of user type "{3}" from the Security Server.

### Short Form

delete admin user

### Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
user	suser	Text	User name

### Description

None

## Message ID : DAO0091I

### Severity

Information

### Long Form

Administrator "{0}" updated administrator "{1}" in the Security Server{2}.

### Short Form

updated admin user

### Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
user	suser	Text	User name

### Description

None

## Message ID : DAO0092I

### Severity

Information

### Long Form

Administrator "{0}" resets the password for administrator "{1}".

### Short Form

reset admin user password

### Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
user	suser	Text	User name

### Description

None

## Message ID : DAO0093I

### Severity

Information

### Long Form

Administrator "{0}" resets his/her own password.

### Short Form

reset own password

### Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name

### Description

None

## Message ID : DAO01286I

## Severity

Information

## Long Form

Status updated for host {0}

## Short Form

```
{0} {1} CEF:0|Vormetric, Inc.|dsm|{3}|DAO13001I|host status updated|3|cs4Label=logger cs4=DAO spid={2} rt={4} dvchost={1}
```

### Parameters

Label	CEF Label	Type	Usage
shost	shost	Text	Source host name

## Description

None

**Message ID : DAO01287I**

## Severity

Information

Message ID : DAO01286I

## Long Form

"{0} certificates with issuer ID {1} were deleted".

## Short Form

delete certificate

### Parameters

No parameters are provided for this message type

## Description

None

## Message ID : DAO01332I

## Severity

Information

## Long Form

User {0} generated a symmetric key {1}.

## Short Form

generated a symmetric key

### Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
key	cs3	Text	Name of key or key pair

## Description

None

**Message ID : DAO01333I**

## Severity

Information

## Long Form

User {0} manually created a symmetric key {1}.

Message ID : DAO01332I

## Short Form

manually created a symmetric key

### Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
key	cs3	Text	Name of key or key pair

## Description

None

**Message ID : DAO01340I**

## Severity

Information

## Long Form

Administrator {0} created LDT Schedule {1}

Message ID : DAO01333I



## Short Form

created LDT Schedule

### Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name

## Description

None

**Message ID : DAO01341I**

## Severity

Information

## Long Form

Administrator {0} updated LDT Schedule {1}

## Short Form

updated LDT Schedule

Message ID : DAO01340I

### Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name

### Description

None

**Message ID : DAO01345I**

### Severity

Information

### Long Form

Administrator {0} deleted LDT Schedule {1}

### Short Form

deleted LDT Schedule

### Parameters

Label	CEF Label	Type	Usage
-------	-----------	------	-------

Message ID : DAO01341I

user	suser	Text	User name
------	-------	------	--------------

### **Description**

None

**Message ID : DAO01379I**

### **Severity**

Information

### **Long Form**

Wrapper Key history created

### **Short Form**

No short form is provided for this message type

### **Description**

None

Message ID : DAO01345I

## **Message ID : DAO01380I**

### **Severity**

Information

### **Long Form**

Wrapper Key history made current

### **Short Form**

No short form is provided for this message type

### **Description**

None

## **Message ID : DAO01381I**

### **Severity**

Information

### **Long Form**

User Key shares for domain "{0}" deleted

Message ID : DAO01380I

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : DAO01382I**

## **Severity**

Information

## **Long Form**

User Key shares for users "{0}" deleted

## **Short Form**

No short form is provided for this message type

## **Description**

None

Message ID : DAO01381I

## **Message ID : DAO01383I**

### **Severity**

Information

### **Long Form**

This wrapper Key already exists for this domain

### **Short Form**

No short form is provided for this message type

### **Description**

None

## **Message ID : DAO01384I**

### **Severity**

Information

### **Long Form**

{0} generated key based on password with "{1}" in DSM

## Short Form

key generated

### Parameters

No parameters are provided for this message type

## Description

None

## Message ID : DAO01385I

## Severity

Information

## Long Form

{0} deleted DSM generated key based on password with "{1}" in DSM

## Short Form

{0} {1} CEF:0|Vormetric, Inc.|dsm|{3}|DAO0700I|delete password-based symmetric key|3|cs4Label=logger cs4=DAO  
spid={2} rt={4} dvchost={1}

## Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
key	cs3	Text	Name of key or key pair

## Description

None

**Message ID : DAO01386I**

## Severity

Information

## Long Form

{0} generated SaaS key "{1}" in DSM

## Short Form

No short form is provided for this message type

Message ID : DAO01385I



## **Description**

None

**Message ID : DAO01387I**

## **Severity**

Information

## **Long Form**

{0} retrieved DSM generated key based on password with "{1}" in DSM

## **Short Form**

No short form is provided for this message type

## **Description**

None

**Message ID : DAO01388I**

## **Severity**

Information

Message ID : DAO01386I

## **Long Form**

{0} retrieved SaaS key "{1}" from DSM

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : DAO01389I**

## **Severity**

Information

## **Long Form**

{0} deleted SaaS key "{1}" from DSM

## **Short Form**

No short form is provided for this message type

## **Description**

None

**Message ID : DAO01509I**

## **Severity**

Information

## **Long Form**

User {0} requested security configuration re-push for host {1}

## **Short Form**

No short form is provided for this message type

## **Description**

None

**Message ID : DAO01510I**

## **Severity**

Information

Message ID : DAO01389I

## Long Form

User "{0}" imported policy "{1}"

## Short Form

imported policy

### Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name

## Description

None

## Message ID : DAO01519I

## Severity

Information

## Long Form

Administrator "{0}" updated host group settings for the host "{1}" with host group "{2}" settings.

Message ID : DAO01510I

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : DAO01520I**

## **Severity**

Information

## **Long Form**

Administrator "{0}" removed the host group host settings inheritance for "{1}".

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : DAO01542I**

### **Severity**

Information

### **Long Form**

Certificate with Id = {0} deleted by {1} of {2}.

### **Short Form**

No short form is provided for this message type

### **Description**

None

## **Message ID : DAO0227I**

### **Severity**

Information

### **Long Form**

User "{0}" deleted the signature for file "{1}".

## Short Form

delete file signature

### Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
filePath	filePath	Text	Full path to file

## Description

None

**Message ID : DAO0228I**

## Severity

Information

## Long Form

Signature added by "{0}" to signature reference "{1}".

## Short Form

add signature to set

### Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
set	vds_set	Text	A set name in a policy for user, resource, process, or time sets

## Description

None

## Message ID : DAO0229I

### Severity

Information

## Long Form

Administrator "{0}" added guardpoint "{1}" with policy "{2}" on host "{3}".



## Short Form

add guardpoint

### Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
gp	fileId	Text	Guardpoint base directory
pol	cs1	Text	Policy name
shost	shost	Text	Source host name

## Description

None

## Message ID : DAO0230I

## Severity

Information

## Long Form

Administrator "{0}" added guardpoint "{1}" with policy "{2}" on host "{3}". The guardpoint is disabled because the same path is already guarded.

Message ID : DAO0229I

## Short Form

add disabled guardpoint

### Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
gp	fileId	Text	Guardpoint base directory
pol	cs1	Text	Policy name
shost	shost	Text	Source host name

## Description

None

**Message ID : DAO0231I**

## Severity

Information

## Long Form

Administrator "{0}" added guardpoint "{1}" with policy "{2}" on host group "{3}".

Message ID : DAO0230I

## Short Form

add group guardpoint

### Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
gp	fileId	Text	Guardpoint base directory
pol	cs1	Text	Policy name
group	vds_group	Text	Group name

## Description

None

## Message ID : DAO0232I

### Severity

Information

## Long Form

Administrator "{0}" added guardpoint "{1}" with policy "{2}" on host group "{3}". The guardpoint is disabled because the same path is already guarded by policy "{2}".

Message ID : DAO0231I

## Short Form

add disabled group guardpoint

### Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
gp	fileId	Text	Guardpoint base directory
pol	cs1	Text	Policy name
group	vds_group	Text	Group name

## Description

None

**Message ID : DAO0233I**

## Severity

Information

## Long Form

Host "{0}" is guarded due to the guardpoint "{1}" with policy "{2}" configured on host group "{3}".

Message ID : DAO0232I

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : DAO0234I**

## **Severity**

Information

## **Long Form**

The inherited host group "{3}" guardpoint "{1}" with policy "{2}" on Host "{0}" is disabled due to conflict.

## **Short Form**

No short form is provided for this message type

## **Description**

None

## Message ID : DAO0235I

### Severity

Information

### Long Form

Administrator "{0}" updated guardpoint "{1}" with policy "{2}" on host "{3}".

### Short Form

update guardpoint

#### Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
gp	fileId	Text	Guardpoint base directory
pol	cs1	Text	Policy name
shost	shost	Text	Source host name

### Description

None

## Message ID : DAO0236I

### Severity

Information

### Long Form

Administrator "{0}" updated guardpoint "{1}" with policy "{2}" on host group "{3}".

### Short Form

update group guardpoint

#### Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
gp	fileId	Text	Guardpoint base directory
pol	cs1	Text	Policy name
group	vds_group	Text	Group name

### Description

None

# Message ID : DAO0237I

## Severity

Information

## Long Form

Administrator "{0}" deleted guardpoint "{1}" with policy "{2}" on host "{3}".

## Short Form

delete guardpoint

### Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
gp	fileId	Text	Guardpoint base directory
pol	cs1	Text	Policy name
shost	shost	Text	Source host name

## Description

None



# Message ID : DAO0238I

## Severity

Information

## Long Form

Administrator "{0}" deleted guardpoint "{1}" with policy "{2}" on host group "{3}".

## Short Form

delete group guardpoint

### Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
gp	fileId	Text	Guardpoint base directory
pol	cs1	Text	Policy name
group	vds_group	Text	Group name

## Description

None

## Message ID : DAO0239I

### Severity

Information

### Long Form

{0} at "{1}" created Symmetric Key "{2}".

### Short Form

create symmetric key

#### Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
shost	shost	Text	Source host name
key	cs3	Text	Name of key or key pair

### Description

None

## Message ID : DAO0240I

### Severity

Information

### Long Form

{0} at "{1}" deleted Symmetric Key "{2}".

### Short Form

delete symmetric key

### Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
shost	shost	Text	Source host name
key	cs3	Text	Name of key or key pair

### Description

None

## Message ID : DAO0241I

### Severity

Information

### Long Form

Administrator "{0}" guarded host "{1}" with policy "{2}".

### Short Form

add host guard

#### Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
shost	shost	Text	Source host name
pol	cs1	Text	Policy name

### Description

None

## Message ID : DAO0243I

### Severity

Information

### Long Form

Administrator "{0}" guarded host group "{1}" with policy "{2}".

### Short Form

add host group guard

#### Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
group	vds_group	Text	Group name
pol	cs1	Text	Policy name

### Description

None

# Message ID : DAO0244I

## Severity

Information

## Long Form

Administrator "{0}" removed the guarding of host "{1}" by policy "{2}".

## Short Form

remove host guard

### Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
shost	shost	Text	Source host name
pol	cs1	Text	Policy name

## Description

None

## Message ID : DAO0245I

### Severity

Information

### Long Form

Administrator "{0}" removed the guarding of host group "{1}" by policy "{2}".

### Short Form

remove host group guard

#### Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
group	vds_group	Text	Group name
pol	cs1	Text	Policy name

### Description

None

## Message ID : DAO0248I

### Severity

Information

### Long Form

Administrator "{0}" enabled the guarding of host "{1}" by policy "{2}".

### Short Form

enable host guard

#### Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
shost	shost	Text	Source host name
pol	cs1	Text	Policy name

### Description

None



## Message ID : DAO0251I

### Severity

Information

### Long Form

Administrator "{0}" enabled the guarding of host group "{1}" by policy "{2}".

### Short Form

enable host group guard

#### Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
group	vds_group	Text	Group name
pol	cs1	Text	Policy name

### Description

None

# Message ID : DAO0252I

## Severity

Information

## Long Form

Administrator "{0}" disabled the guarding of host group "{1}" by policy "{2}".

## Short Form

disable host group guard

### Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
group	vds_group	Text	Group name
pol	cs1	Text	Policy name

## Description

None

# Message ID : DAO0253I

## Severity

Information

## Long Form

Administrator "{0}" disabled the guarding of host "{1}" by policy "{2}".

## Short Form

disable host guard

### Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
shost	shost	Text	Source host name
pol	cs1	Text	Policy name

## Description

None

## Message ID : DAO0254I

### Severity

Information

### Long Form

Administrator "{0}" added host "{1}" into host group "{2}".

### Short Form

add host to group

#### Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
shost	shost	Text	Source host name
group	vds_group	Text	Group name

### Description

None

# Message ID : DAO0255I

## Severity

Information

## Long Form

Administrator "{0}" removed host "{1}" from host group "{2}".

## Short Form

remove host from group

### Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
shost	shost	Text	Source host name
group	vds_group	Text	Group name

## Description

None

## **Message ID : DAO0256I**

### **Severity**

Information

### **Long Form**

Administrator "{0}" added server node "{1}".

### **Short Form**

No short form is provided for this message type

### **Description**

None

## **Message ID : DAO0257I**

### **Severity**

Information

### **Long Form**

Administrator "{0}" deleted server node "{1}".

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : DAO0258I**

## **Severity**

Information

## **Long Form**

The node "{0}" of the Security Server is initialized successfully.

## **Short Form**

No short form is provided for this message type

## **Description**

None

Message ID : DAO0257I

## **Message ID : DAO0259I**

### **Severity**

Information

### **Long Form**

Administrator "{0}" deleted the guarding of host "{1}" inherited from host group "{2}".

### **Short Form**

No short form is provided for this message type

### **Description**

None

## **Message ID : DAO0260I**

### **Severity**

Information

### **Long Form**

Administrator "{0}" added the guarding of host "{1}" inherited from host group "{2}".



## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : DAO0261I**

## **Severity**

Information

## **Long Form**

Host "{0}" was updated due to properties inherited from host group "{1}".

## **Short Form**

No short form is provided for this message type

## **Description**

None

Message ID : DAO0260I

## **Message ID : DAO0263I**

### **Severity**

Information

### **Long Form**

The Primary Node "{0}" of the Security Server is initialized successfully.

### **Short Form**

No short form is provided for this message type

### **Description**

None

## **Message ID : DAO0267I**

### **Severity**

Information

### **Long Form**

{4}User "{0}", a {2} logged in at {1} from client with IP address {3}; trusted channel established.

## Short Form

user logged in

### Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
stime	start	Text	A start time stamp

## Description

None

**Message ID : DAO0269I**

## Severity

Information

## Long Form

Administrator "{0}" account is unlocked.

## Short Form

account unlocked

### Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name

## Description

None

## Message ID : DAO0280I

## Severity

Information

## Long Form

Administrator "{0}" created online policy "{1}".

## Short Form

create online policy

Message ID : DAO0269I

## Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
pol	cs1	Text	Policy name

## Description

None

**Message ID : DAO0281I**

## Severity

Information

## Long Form

Administrator "{0}" deleted online policy "{1}".

## Short Form

delete online policy

## Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
pol	cs1	Text	Policy name

## Description

None

**Message ID : DAO0282I**

## Severity

Information

## Long Form

Administrator "{0}" updated online policy "{1}".

## Short Form

update online policy

## Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
pol	cs1	Text	Policy name

## Description

None

**Message ID : DAO0305I**

## Severity

Information

## Long Form

Administrator "{0}" updated the password policy to "{1}".

## Short Form

update password policy

### Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name

### Description

None

**Message ID : DAO0317I**

### Severity

Information

### Long Form

User "{0}" changed the password.

### Short Form

change password

### Parameters

Label	CEF Label	Type	Usage
-------	-----------	------	-------

Message ID : DAO0305I



user	suser	Text	User name
------	-------	------	-----------

## Description

None

## Message ID : DAO0401I

## Severity

Information

## Long Form

System Administrator {0} created domain {1}.

## Short Form

create domain

## Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
domain	dntdom	Text	A domain name (policy, network, users, etc)

Message ID : DAO0317I

Label	CEF Label	Type	Usage

## Description

None

## Message ID : DAO0402I

## Severity

Information

## Long Form

System Administrator {0} deleted domain {1}.

## Short Form

delete domain

## Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
domain	dntdom	Text	A domain name (policy, network, users, etc)

Message ID : DAO0401I

## Description

None

**Message ID : DAO0404I**

## Severity

Information

## Long Form

System Administrator {0} updated domain {1}.

## Short Form

update domain

## Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
domain	dntdom	Text	A domain name (policy, network, users, etc)

## Description

None

**Message ID : DAO0405I**

## Severity

Information

## Long Form

Administrator {0} added user {1} with roles {3} to the domain {2}.

## Short Form

add user to domain

## Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
user	suser	Text	User name
domain	dntdom	Text	A domain name (policy, network, users, etc)

Message ID : DAO0404I

## Description

None

**Message ID : DAO0406I**

## Severity

Information

## Long Form

Domain Administrator {0} removed user {1} from the domain.

## Short Form

remove user from domain

## Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
user	suser	Text	User name

## Description

None

**Message ID : DAO0407I**

## Severity

Information

## Long Form

Administrator "{0}" updated domain "{1}" {2} default license type for registration shared secret from {3} to {4}.

## Short Form

updated default license type for registration shared secret

## Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
domain	dntdom	Text	A domain name (policy, network, users, etc)

## Description

None

**Message ID : DAO0408I**

## Severity

Information

## Long Form

Administrator "{0}" initialized domain "{1}" {2} default license type for registration shared secret to {3}.

## Short Form

initialized default license type for registration shared secret

## Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
domain	dntdom	Text	A domain name (policy, network, users, etc)

## Description

None

**Message ID : DAO0412I**

## Severity

Information

## Long Form

Security Administrator "{0}" allowed host "{1}" to be shared with domain "{2}".

## Short Form

allow host share with domain

## Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
shost	shost	Text	Source host name
domain	dntdom	Text	A domain name (policy, network, users, etc)

Message ID : DAO0408I



## Description

None

**Message ID : DAO0413I**

## Severity

Information

## Long Form

Security Administrator "{0}" disallowed host "{1}" to be shared with domain "{2}".

## Short Form

disallow host share with domain

## Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
shost	shost	Text	Source host name
domain	dntdom	Text	A domain name (policy, network, users, etc)

Message ID : DAO0412I

## Description

None

**Message ID : DAO0414I**

## Severity

Information

## Long Form

Security Administrator "{0}" allowed host group "{1}" to be shared with domain "{2}".

## Short Form

allow host group share with domain

## Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
group	vds_group	Text	Group name
domain	dntdom	Text	A domain name (policy, network, users, etc)

Message ID : DAO0413I

745

## Description

None

**Message ID : DAO0415I**

## Severity

Information

## Long Form

Security Administrator "{0}" disallowed host group "{1}" to be shared with domain "{2}".

## Short Form

disallow host group share with domain

## Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
group	vds_group	Text	Group name
domain	dntdom	Text	A domain name (policy, network, users, etc)

## Description

None

**Message ID : DAO0423I**

## Severity

Information

## Long Form

Administrator {0} is disabled in domain {1} because of password reset.

## Short Form

admin disabled in domain

## Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
domain	dntdom	Text	A domain name (policy, network, users, etc)

Message ID : DAO0415I

## Description

None

**Message ID : DAO0424I**

## Severity

Information

## Long Form

Administrator {0} disabled user {1} in the domain.

## Short Form

disable user in domain

## Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
user	suser	Text	User name

Message ID : DAO0423I

## Description

None

## Message ID : DAO0425I

## Severity

Information

## Long Form

Administrator {0} enabled user {1} in the domain {2}.

## Short Form

enable user in domain

## Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
user	suser	Text	User name

## Description

None

**Message ID : DAO0426I**

## Severity

Information

## Long Form

The Administrator "{0}" switched to the domain at {1}.

## Short Form

switch domain

## Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name

## Description

None

Message ID : DAO0425I

## Message ID : DAO0445I

### Severity

Information

### Long Form

Administrator {0} added SysLog Host {1}.

### Short Form

add syslog host

#### Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
shost	shost	Text	Source host name

### Description

None



## Message ID : DAO0446I

### Severity

Information

### Long Form

Administrator {0} deleted SysLog Host {1}.

### Short Form

delete syslog host

#### Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
shost	shost	Text	Source host name

### Description

None

## Message ID : DAO0447I

### Severity

Information

### Long Form

OTP token {0} binding updated by user {1}.

### Short Form

OTP binding update

#### Parameters

Label	CEF Label	Type	Usage
token	vds_token	Text	A token name (e.g. for one-time-passwords)
user	suser	Text	User name

### Description

None

## Message ID : DAO0449I

### Severity

Information

### Long Form

OTP configuration updated its property {0}.

### Short Form

OTP configuration update

#### Parameters

Label	CEF Label	Type	Usage
property	vds_property	Text	A property name (e.g. for one-time-passwords)

### Description

None

## Message ID : DAO0460I

## Severity

Information

## Long Form

SNMP MIB entry updated: {0} = {1}.

## Short Form

snmp mib update

### Parameters

Label	CEF Label	Type	Usage
oid	vds_oid	Text	Object ID (e.g. for SNMP MIB)
val	vds_val	Numeric	A value string (e.g. for SNMP MIB)

## Description

None

## Message ID : DAO0461I

## Severity

Information

## Long Form

Allowed SNMP host {0} added.

## Short Form

allowed SNMP host add

### Parameters

Label	CEF Label	Type	Usage
shost	shost	Text	Source host name

## Description

None

**Message ID : DAO0462I**

## Severity

Information

Message ID : DAO0461I

## Long Form

Allowed SNMP host {0} deleted.

## Short Form

allowed SNMP host delete

### Parameters

Label	CEF Label	Type	Usage
shost	shost	Text	Source host name

## Description

None

## Message ID : DAO0501I

## Severity

Information

## Long Form

Administrator "{0}" marked guardpoint "{1}" with policy "{2}" pending delete on host "{3}".

Message ID : DAO0462I

## Short Form

marked guardpoint pending delete

### Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
gp	fileId	Text	Guardpoint base directory
pol	cs1	Text	Policy name
shost	shost	Text	Source host name

## Description

None

**Message ID : DAO0502I**

## Severity

Information

## Long Form

Administrator "{0}" deleted pending guardpoint "{1}" with policy "{2}" on host "{3}".

Message ID : DAO0501I

## Short Form

delete pending guardpoint

### Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
gp	fileId	Text	Guardpoint base directory
pol	cs1	Text	Policy name
shost	shost	Text	Source host name

## Description

None

**Message ID : DAO0518I**

## Severity

Information

## Long Form

Administrator "{0}" exported server backup key.

Message ID : DAO0502I



## Short Form

export server backup key

### Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name

## Description

None

## Message ID : DAO0519I

## Severity

Information

## Long Form

Number of key shares or users is null, empty, or do not equal each other.

## Short Form

No short form is provided for this message type

Message ID : DAO0518I

## Description

None

**Message ID : DAO0546I**

## Severity

Information

## Long Form

Administrator "{0}" submitted a server backup key share.

## Short Form

submit server backup key share

## Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name

## Description

None

Message ID : DAO0519I

## Message ID : DAO0560I

### Severity

Information

### Long Form

Administrator "{0}" created resource set "{1}" with {2}.

### Short Form

create resource set

#### Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
set	vds_set	Text	A set name in a policy for user, resource, process, or time sets

### Description

None

## Message ID : DAO0561I

### Severity

Information

### Long Form

Administrator "{0}" deleted resource set "{1}".

### Short Form

delete resource set

### Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
set	vds_set	Text	A set name in a policy for user, resource, process, or time sets

### Description

None

# Message ID : DAO0562I

## Severity

Information

## Long Form

Administrator "{0}" updated resource set "{1}" with {2}.

## Short Form

update resource set

### Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
set	vds_set	Text	A set name in a policy for user, resource, process, or time sets

## Description

None

# Message ID : DAO0563I

## Severity

Information

## Long Form

Administrator "{0}" created process set "{1}" with {2}.

## Short Form

create process set

### Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
set	vds_set	Text	A set name in a policy for user, resource, process, or time sets

## Description

None

## Message ID : DAO0564I

### Severity

Information

### Long Form

Administrator "{0}" deleted process set "{1}".

### Short Form

delete process set

#### Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
set	vds_set	Text	A set name in a policy for user, resource, process, or time sets

### Description

None

## Message ID : DAO0565I

### Severity

Information

### Long Form

Administrator "{0}" updated process set "{1}" with {2}.

### Short Form

update process set

### Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
set	vds_set	Text	A set name in a policy for user, resource, process, or time sets

### Description

None



## Message ID : DAO0566I

### Severity

Information

### Long Form

Administrator "{0}" created user set "{1}" with {2}.

### Short Form

create user set

#### Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
set	vds_set	Text	A set name in a policy for user, resource, process, or time sets

### Description

None

## Message ID : DAO0567I

### Severity

Information

### Long Form

Administrator "{0}" deleted user set "{1}".

### Short Form

delete user set

#### Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
set	vds_set	Text	A set name in a policy for user, resource, process, or time sets

### Description

None

## Message ID : DAO0568I

### Severity

Information

### Long Form

Administrator "{0}" updated user set "{1}" with {2}.

### Short Form

update user set

#### Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
set	vds_set	Text	A set name in a policy for user, resource, process, or time sets

### Description

None

## Message ID : DAO0569I

### Severity

Information

### Long Form

Administrator "{0}" created time set "{1}" with {2}.

### Short Form

create time set

#### Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
set	vds_set	Text	A set name in a policy for user, resource, process, or time sets

### Description

None

# Message ID : DAO0570I

## Severity

Information

## Long Form

Administrator "{0}" deleted time set "{1}".

## Short Form

delete time set

### Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
set	vds_set	Text	A set name in a policy for user, resource, process, or time sets

## Description

None

# Message ID : DAO05711

## Severity

Information

## Long Form

Administrator "{0}" updated time set "{1}" with {2}.

## Short Form

update time set

### Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
set	vds_set	Text	A set name in a policy for user, resource, process, or time sets

## Description

None

## Message ID : DAO0573I

### Severity

Information

### Long Form

Host "{0}" assigned to Server Node "{1}".

### Short Form

assign host to server

### Parameters

Label	CEF Label	Type	Usage
shost	shost	Text	Source host name
shost	shost	Text	Source host name

### Description

None

## Message ID : DAO0576I

### Severity

Information

### Long Form

Administrator "{0}" updated key "{1}".

### Short Form

update key

#### Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
key	cs3	Text	Name of key or key pair

### Description

None



## Message ID : DAO0578I

### Severity

Information

### Long Form

User "{0}" added the signature reference "{1}".

### Short Form

add signature set

#### Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
set	vds_set	Text	A set name in a policy for user, resource, process, or time sets

### Description

None

## Message ID : DAO0579I

### Severity

Information

### Long Form

User "{0}" deleted the signature reference "{1}".

### Short Form

delete signature set

#### Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
set	vds_set	Text	A set name in a policy for user, resource, process, or time sets

### Description

None

## Message ID : DAO0606I

### Severity

Information

### Long Form

Administrator "{0}" notified all hosts.

### Short Form

notify all hosts

### Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name

### Description

None

## Message ID : DAO0638I

## Severity

Information

## Long Form

Administrator "{0}" created CA with URL "{1}".

## Short Form

create CA

### Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
url	request	Text	A uniform resource location

## Description

None

**Message ID : DAO0639I**

## Severity

Information

## Long Form

Administrator "{0}" deleted CA with URL "{1}".

## Short Form

delete CA

### Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
url	request	Text	A uniform resource location

## Description

None

## Message ID : DAO0640I

## Severity

Information

## Long Form

Administrator "{0}" updated CA with URL "{1}".

## Short Form

update CA

### Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
url	request	Text	A uniform resource location

## Description

None

## Message ID : DAO0641I

## Severity

Information

## Long Form

Administrator "{0}" retrieved CA with URL "{1}".

## Short Form

retrieve CA

### Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
url	request	Text	A uniform resource location

## Description

None

## Message ID : DAO0659I

## Severity

Information

## Long Form

Administrator {0} updated SysLog Host {1}.

## Short Form

update syslog host

### Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
shost	shost	Text	Source host name

## Description

None

## Message ID : DAO0672I



## Severity

Information

## Long Form

Administrator "{0}" registered the agent for the agent type "{1}".

## Short Form

register agent

### Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
agent	deviceProcessName	Text	The short identifier of the agent software

## Description

None

## Message ID : DAO0673I

## Severity

Information

## Long Form

Administrator "{0}" updated agent for the agent type "{1}".

## Short Form

update agent

### Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
agent	deviceProcessName	Text	The short identifier of the agent software

## Description

None

## Message ID : DAO0674I

## Severity

Information

## Long Form

{0} at "{1}" created Key Attribute "{2}".

## Short Form

create key attribute

### Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
shost	shost	Text	Source host name
showStr	reason	Text	Code specifying reason for allowing access, if any

## Description

None

## Message ID : DAO0675I

## Severity

Information

## Long Form

{0} at "{1}" deleted Key Attribute "{2}".

## Short Form

delete key attribute

### Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
shost	shost	Text	Source host name
showStr	reason	Text	Code specifying reason for allowing access, if any

## Description

None

## Message ID : DAO0676I

Message ID : DAO0675I

## Severity

Information

## Long Form

{0} at "{1}" updated Key Attribute "{2}".

## Short Form

update key Attribute

### Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
shost	shost	Text	Source host name
showStr	reason	Text	Code specifying reason for allowing access, if any

## Description

None

**Message ID : DAO0677I**

## Severity

Information

## Long Form

{0} at "{1}" updated Key Attribute "{2}". It is renamed to "{3}".

## Short Form

update key Attribute which is renamed

### Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
shost	shost	Text	Source host name
showStr	reason	Text	Code specifying reason for allowing access, if any
altAttr	vds_altAttr	Text	Name of alternate attribute for multi-attribute operations

## Description

None

## Message ID : DAO0678I

### Severity

Information

### Long Form

Administrator "{0}" created Key Template "{1}".

### Short Form

create key template

#### Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
template	vds_template	Text	Key template name

### Description

None

## Message ID : DAO0679I

### Severity

Information

### Long Form

Administrator "{0}" updated Key Template "{1}".

### Short Form

update key template

#### Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
template	vds_template	Text	Key template name

### Description

None



# Message ID : DAO0680I

## Severity

Information

## Long Form

Administrator "{0}" updated Key Template "{1}" is updated. It is renamed to "{2}".

## Short Form

updated/rename key template

### Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
template	vds_template	Text	Key template name
altTemplate	vds_altTemplate	Text	Alternate template name in rename operations

## Description

None

## Message ID : DAO0681I

### Severity

Information

### Long Form

Administrator "{0}" deleted Key Template "{1}".

### Short Form

delete key template

#### Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
template	vds_template	Text	Key template name

### Description

None

## Message ID : DAO0682I

### Severity

Information

### Long Form

Administrator "{0}" created Key Template Attribute "{1}".

### Short Form

create key template attribute

#### Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
showStr	reason	Text	Code specifying reason for allowing access, if any

### Description

None

## Message ID : DAO0683I

### Severity

Information

### Long Form

Administrator "{0}" updated Key Template Attribute "{1}".

### Short Form

update key template attribute

### Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
showStr	reason	Text	Code specifying reason for allowing access, if any

### Description

None

# Message ID : DAO0684I

## Severity

Information

## Long Form

Administrator "{0}" updated Key Template Attribute "{1}" is updated. It is renamed to "{2}".

## Short Form

update/rename key template attribute

### Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
showStr	reason	Text	Code specifying reason for allowing access, if any
altAttr	vds_altAttr	Text	Name of alternate attribute for multi-attribute operations

## Description

None

## Message ID : DAO0685I

### Severity

Information

### Long Form

Administrator "{0}" deleted Key Template Attribute "{1}".

### Short Form

delete key template attribute

#### Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
showStr	reason	Text	Code specifying reason for allowing access, if any

### Description

None

## Message ID : DAO0697I

### Severity

Information

### Long Form

The user "{0}" created vault Key Pair "{1}".

### Short Form

create vault key pair

#### Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
key	cs3	Text	Name of key or key pair

### Description

None

## Message ID : DAO0699I

### Severity

Information

### Long Form

Administrator "{0}" deleted Vault Key Pair "{1}".

### Short Form

delete vault key pair

#### Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
key	cs3	Text	Name of key or key pair

### Description

None



## Message ID : DAO0700I

### Severity

Information

### Long Form

Administrator "{0}" deleted Vault Symmetric Key "{1}".

### Short Form

delete vault symmetric key

#### Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
key	cs3	Text	Name of key or key pair

### Description

None

## Message ID : DAO0701I

### Severity

Information

### Long Form

Administrator "{0}" deleted opaque-object "{1}".

### Short Form

delete opaque-object

### Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
key	cs3	Text	Name of key or key pair

### Description

None

## **Message ID : DAO0715I**

### **Severity**

Information

### **Long Form**

LDAP configuration updated.

### **Short Form**

update ldap configuration

### **Parameters**

No parameters are provided for this message type

### **Description**

None

## **Message ID : DAO0716I**

### **Severity**

Information

Message ID : DAO0715I

## Long Form

LDAP user "{0}" is mapped to Security Server user "{1}".

## Short Form

LDAP user mapped to Security Server

### Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name

## Description

None

## Message ID : DAO0720I

## Severity

Information

## Long Form

Administrator "{0}" defined the following SMTP server: "{1}".

Message ID : DAO0716I

## Short Form

define SMTP server

### Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
shost	shost	Text	Source host name

## Description

None

**Message ID : DAO0721I**

## Severity

Information

## Long Form

Administrator "{0}" deleted the SMTP server.

## Short Form

delete SMTP server

### Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name

## Description

None

## Message ID : DAO0722I

## Severity

Information

## Long Form

Administrator "{0}" updated the SMTP server from "{2}" to "{1}".

## Short Form

update SMTP server

Message ID : DAO0721I

## Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
shost	shost	Text	Source host name

## Description

None

**Message ID : DAO0723I**

## Severity

Information

## Long Form

Administrator "{0}" added email notification group "{1}".

## Short Form

add email notification group

## Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
group	vds_group	Text	Group name

## Description

None

**Message ID : DAO0724I**

## Severity

Information

## Long Form

Administrator "{0}" deleted email notification group "{1}".

## Short Form

delete email notification group

Message ID : DAO0723I



## Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
group	vds_group	Text	Group name

## Description

None

**Message ID : DAO0725I**

## Severity

Information

## Long Form

Administrator "{0}" updated email notification group "{1}" from old value "{2}" to to new value "{3}".

## Short Form

update email notification group

## Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
group	vds_group	Text	Group name

## Description

None

**Message ID : DAO0790I**

## Severity

Information

## Long Form

"Vaulted certificate {0}".

## Short Form

vaulted certificate

### Parameters

Label	CEF Label	Type	Usage
cert	vds_cert	Text	Certificate type or name

### Description

None

### Message ID : DAO0791I

### Severity

Information

### Long Form

{5}Certificate with Subject {0}, Issuer {1} and Id = {2} was deleted by {3} of {4}.

### Short Form

delete certificate

### Parameters

Label	CEF Label	Type	Usage
-------	-----------	------	-------

Message ID : DAO0790I

cert	vds_cert	Text	Certificate type or name
------	----------	------	--------------------------

## Description

None

## Message ID : DAO0792I

## Severity

Information

## Long Form

"Certificate with ID = {0} was updated".

## Short Form

update certificate

## Parameters

Label	CEF Label	Type	Usage
cert	vds_cert	Text	Certificate type or name

Message ID : DAO0791I

## Description

None

**Message ID : DAO0803I**

## Severity

Information

## Long Form

{0} at "{1}" created Vault Symmetric Key "{2}".

## Short Form

create vault symmetric key

## Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
shost	shost	Text	Source host name
key	cs3	Text	Name of key or key pair

Message ID : DAO0792I

**Description**

None

**Message ID : DAO0804I****Severity**

Information

**Long Form**

Administrator already exists.

**Short Form**

No short form is provided for this message type

**Description**

None

**Message ID : DAO0850I****Severity**

Information

Message ID : DAO0803I

## Long Form

Administrator "{0}" updated host "{1}" license type to {2}.

## Short Form

update host license type

### Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
shost	shost	Text	Source host name
lType	vds_lType	Text	A license type

## Description

None

**Message ID : DAO1265I**

## Severity

Information

Message ID : DAO0850I

## Long Form

The user "{0}" imported {1} vault Key Pairs.

## Short Form

```
import vault key pairs
```

### Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
keys	vds_keys	Text	List of key names

## Description

None

**Message ID : DAO1266I**

## Severity

Information

Message ID : DAO1265I



## Long Form

{0} at "{1}" imported {2} Symmetric Keys.

## Short Form

```
import symmetric keys
```

### Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
shost	shost	Text	Source host name
keys	vds_keys	Text	List of key names

## Description

None

**Message ID : DAO1281I**

## Severity

Information

Message ID : DAO1266I

## Long Form

Administrator "{0}" assigned roles {3} to user "{1}" in the domain "{2}" to replace old roles {4}.

## Short Form

```
{0} {1} CEF:0|Vormetric, Inc.|dsm|{3}|DAO0405I|assigned roles to user in domain|3|cs4Label=logger cs4=DAO spid={2}  
rt={4} dvchost={1}
```

### Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
user	suser	Text	User name
domain	dntdom	Text	A domain name (policy, network, users, etc)

## Description

None

**Message ID : DAO1353I**

## Severity

Information

Message ID : DAO1281I

## Long Form

Administrator "{0}" updated host password for host "{1}".

## Short Form

update host password

### Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
shost	shost	Text	Source host name

## Description

None

**Message ID : DAO1364I**

## Severity

Information

Message ID : DAO1353I

## Long Form

Administrator "{0}" update "{1}" log setting from "{2}" to "{3}".

## Short Form

update log setting

### Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
shost	shost	Text	Source host name

## Description

None

**Message ID : DAO1410I**

## Severity

Information

Message ID : DAO1364I

## Long Form

All Administrators disabled in domain "{0}".

## Short Form

No short form is provided for this message type

## Description

None

## Message ID : DAO1500I

## Severity

Information

## Long Form

{0} at "{1}" updated Key Attributes "{2}" for key "{3}".

## Short Form

update key Attributes

## Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
shost	shost	Text	Source host name
showStr	reason	Text	Code specifying reason for allowing access, if any

## Description

None

## Message ID : DAO1524I

## Severity

Information

## Long Form

{0} at "{1}" updated key-state from "{2}" to "{3}" for key "{4}" with version "{5}" and UUID "{6}".

## Short Form

key-state updated

## Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
shost	shost	Text	Source host name
showStr	reason	Text	Code specifying reason for allowing access, if any
key	key	Text	Name of key or key pair
version	version	Text	Software version string

## Description

None

## Message ID : DAO1530I

## Severity

Information

## Long Form

{0} at "{1}" updated key-state-action from "{2}" to "{3}" for key "{4}" with version "{5}" and UUID "{6}".

## Short Form

key-state-action updated

### Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
shost	shost	Text	Source host name
showStr	reason	Text	Code specifying reason for allowing access, if any
key	key	Text	Name of key or key pair
version	version	Text	Software version string

## Description

None

**Message ID : DAO1536I**

## Severity

Information

Message ID : DAO1530I



## Long Form

{0} retrieved SaaS asymmetric key with "{1}" in DSM

## Short Form

No short form is provided for this message type

## Description

None

## Message ID : DAO1537I

## Severity

Information

## Long Form

{0} generated SaaS asymmetric key with name "{2}" with "{1}" host in DSM

## Short Form

No short form is provided for this message type

Message ID : DAO1536I

## **Description**

None

**Message ID : DAO1538I**

## **Severity**

Information

## **Long Form**

{0} deleted SaaS asymmetric key with name "{2}" with "{1}" domain in DSM

## **Short Form**

No short form is provided for this message type

## **Description**

None

**Message ID : DAO1539I**

## **Severity**

Information

Message ID : DAO1537I

## Long Form

certificates for domain with Id {0} and type {1} are deleted.

## Short Form

No short form is provided for this message type

## Description

None

## Message ID : DAO1541I

## Severity

Information

## Long Form

{0} with Subject {1}, Issuer {2} and Id = {3} was added by {4} of {5}.

## Short Form

No short form is provided for this message type

## Description

None

## Message ID : DAO1560I

## Severity

Information

## Long Form

{0} imported external symmetric key with name "{2}" with "{1}" host in DSM.

## Short Form

imported external symmetric key

## Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
shost	shost	Text	Source host name
key	key	Text	Name of key or key pair

## Description

None

**Message ID : DAO1624I**

## Severity

Information

## Long Form

User "{0}" created identity "{1}".

## Short Form

created identity

## Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name

## Description

None

Message ID : DAO1560I

## Message ID : DAO1625I

### Severity

Information

### Long Form

User "{0}" updated identity "{1}".

### Short Form

updated identity

#### Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name

### Description

None

## Message ID : DAO1626I

## Severity

Information

## Long Form

User "{0}" deleted identity "{1}".

## Short Form

deleted identity

### Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name

## Description

None

## Message ID : DAO1739I

## Severity

Information

Message ID : DAO1626I

## Long Form

Administrator "{0}" updated online policy "{1}" with key rule changes.

## Short Form

update online policy with key rule changes

### Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
pol	cs1	Text	Policy name

## Description

None

**Message ID : DAO1774I**

## Severity

Information

Message ID : DAO1739I



## Long Form

LDAP configuration deleted.

## Short Form

delete ldap configuration

### Parameters

No parameters are provided for this message type

## Description

None

## Message ID : DAO1828I

## Severity

Information

## Long Form

Administrator "{0}" updated host "{1}" and Host settings are updated.

## Short Form

update host and host settings

### Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
shost	shost	Text	Source host name

## Description

None

## Message ID : DAO1832I

## Severity

Information

## Long Form

Administrator "{0}" updated silo with "{1}" for host "{2}".

## Short Form

No short form is provided for this message type

## Description

None

## Message ID : DAO1834I

## Severity

Information

## Long Form

User "{0}" updated the signature reference "{1}".

## Short Form

updated signature set

## Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
set	vds_set	Text	A set name in a policy for user, resource, process, or time sets

Message ID : DAO1832I

Label	CEF Label	Type	Usage

## Description

None

## Message ID : DAO1837I

## Severity

Information

## Long Form

Administrator "{0}" added a new LDAP group "{1}" of user type "{2}" into the Security Server.

## Short Form

add LDAP group

## Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
user	suser	Text	

Message ID : DAO1834I

Label	CEF Label	Type	Usage
			User name

## Description

None

## Message ID : DAO1847I

## Severity

Information

## Long Form

Administrator "{0}" purged all destroyed keys.

## Short Form

purge all destroyed keys

## Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name

Message ID : DAO1837I

Label	CEF Label	Type	Usage

## Description

None

## Message ID : DAO1848I

## Severity

Information

## Long Form

Administrator "{0}" purged destroyed key "{1}".

## Short Form

purge destroyed key

## Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
key	cs3	Text	Name of key or key pair

Message ID : DAO1847I

Label	CEF Label	Type	Usage

## Description

None

## Message ID : DAO1861I

## Severity

Information

## Long Form

Administrator "{0}" removed from the allowed KMIP operations list of host "{1}": {2}

## Short Form

remove from allowed KMIP operations

## Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
shost	shost	Text	Source host name

## Description

None

**Message ID : DAO1862I**

## Severity

Information

## Long Form

Administrator "{0}" added to the allowed KMIP operations list of host "{1}": {2}

## Short Form

add to allowed KMIP operations

## Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
shost	shost	Text	Source host name



## **Description**

None

# Logger DAO: Warnings

**Message ID : DAO01319W**

## **Severity**

Warning

## **Long Form**

Unable to archive previous version of policy {0} because its content exceeds the 1GB limit. However the change to the policy and the meta-data of the previous version have been saved successfully

## **Short Form**

No short form is provided for this message type

## **Description**

None

# Logger DGV: Errors

**Message ID : DGV6001E**

## Severity

Error

## Long Form

Memory allocation failed in [{}] at line [{}]

## Short Form

Out of memory

## Parameters

No parameters are provided for this message type

## Description

None

**Message ID : DGV6002E**

## Severity

Error

## Long Form

Data governance exception with error [{0}] in [{1}] at line [{2}]

## Short Form

Exception

### Parameters

No parameters are provided for this message type

## Description

None

**Message ID : DGV6003E**

## Severity

Error

## **Long Form**

Invalid data governance connector type {0}

## **Short Form**

Invalid connector

### **Parameters**

No parameters are provided for this message type

## **Description**

None

**Message ID : DGV6004E**

## **Severity**

Error

## **Long Form**

Invalid data governance data source type {0}

## Short Form

Invalid data source type

### Parameters

No parameters are provided for this message type

## Description

None

## Message ID : DGV6005E

## Severity

Error

## Long Form

HTTP request {0} failed with the status code {1} and message {2}

## Short Form

HTTP request failed

### **Parameters**

No parameters are provided for this message type

### **Description**

None

**Message ID : DGV6006E**

### **Severity**

Error

### **Long Form**

UUID creation failed with error {0}

### **Short Form**

UUID creation failed

### **Parameters**

No parameters are provided for this message type

Message ID : DGV6005E

## **Description**

None

**Message ID : DGV6007E**

## **Severity**

Error

## **Long Form**

Type {0} is not found

## **Short Form**

Type not found

## **Parameters**

No parameters are provided for this message type

## **Description**

None

Message ID : DGV6006E



## **Message ID : DGV6008E**

### **Severity**

Error

### **Long Form**

Attribute {0} value is not found

### **Short Form**

Attribute value not found

### **Parameters**

No parameters are provided for this message type

### **Description**

None

## **Message ID : DGV6009E**

### **Severity**

Error

## **Long Form**

Failed to get attributes for {0} with error {1}

## **Short Form**

Failed to get file attributes

### **Parameters**

No parameters are provided for this message type

## **Description**

None

## **Message ID : DGV6010E**

## **Severity**

Error

## **Long Form**

Failed to create the tag directory {0} with error {1}

## Short Form

Failed to create tag directory

### Parameters

No parameters are provided for this message type

## Description

None

## Message ID : DGV6011E

### Severity

Error

## Long Form

User {0} in domain {1} failed to connect to network path {2}. Error code {3}

## Short Form

Net connect error

## Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
domain	dntdom	Text	A domain name (policy, network, users, etc)
url	request	Text	A uniform resource location
ecode	cn1	Numeric	An error code

## Description

None

**Message ID : DGV6012E**

## Severity

Error

## Long Form

AWS request exception {0}. Error message {1}

## Short Form

AWS request error

Message ID : DGV6011E

### **Parameters**

No parameters are provided for this message type

### **Description**

None

### **Message ID : DGV6013E**

### **Severity**

Error

### **Long Form**

Failed to add tag {0} to {1}. Error message {2}

### **Short Form**

Failed to add tag

### **Parameters**

No parameters are provided for this message type

## Description

None

**Message ID : DGV6014E**

## Severity

Error

## Long Form

Failed to delete tag {0} from {1}. Error message {2}

## Short Form

Failed to delete tag

## Parameters

No parameters are provided for this message type

## Description

None

Message ID : DGV6013E

## **Message ID : DGV6015E**

### **Severity**

Error

### **Long Form**

Failed to initialize tag for {0}

### **Short Form**

Failed to initialize tag

### **Parameters**

No parameters are provided for this message type

### **Description**

None

## **Message ID : DGV6016E**

### **Severity**

Error

Message ID : DGV6015E

## Long Form

Failed to process tagging event. Error message {0}

## Short Form

Failed to process tagging event

### Parameters

No parameters are provided for this message type

## Description

None

## Message ID : DGV6017E

## Severity

Error

## Long Form

Atlas REST failed with SSL. Error message {0}



## Short Form

Atlas REST failed with SSL

### Parameters

No parameters are provided for this message type

## Description

None

## Message ID : DGV6018E

## Severity

Error

## Long Form

Failed to get uuid for {0}

## Short Form

Failed to get uuid

### **Parameters**

No parameters are provided for this message type

### **Description**

None

# Logger DGV: Information

**Message ID : DGV6019I**

## Severity

Information

## Long Form

Starting scan of {0}

## Short Form

Starting scan

## Parameters

No parameters are provided for this message type

## Description

None

**Message ID : DGV6020I**

## **Severity**

Information

## **Long Form**

Finished scan of {0} in {1} seconds

## **Short Form**

Finished scan

### **Parameters**

No parameters are provided for this message type

## **Description**

None

## **Logger DMG: Errors**

**Message ID : DMG0549E**

### **Severity**

Error

### **Long Form**

Unable to remove directory "{0}".

### **Short Form**

No short form is provided for this message type

### **Description**

None

**Message ID : DMG0550E**

### **Severity**

Error

## **Long Form**

Unable to create directory "{0}".

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : DMG0551E**

## **Severity**

Error

## **Long Form**

Unable to extract from the uploaded file "{0}".

## **Short Form**

No short form is provided for this message type

**Description**

None

**Message ID : DMG0552E****Severity**

Error

**Long Form**

Unable to extract policies from the archive "{0}".

**Short Form**

No short form is provided for this message type

**Description**

None

**Message ID : DMG0553E****Severity**

Error

Message ID : DMG0551E

## **Long Form**

Internal error encountered. Please check the log file for details.

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : DMG0554E**

## **Severity**

Error

## **Long Form**

Data migration needs to be performed on a clean install. The module {0} contains data.

## **Short Form**

No short form is provided for this message type



## **Description**

None

# Logger DMG: Information

**Message ID : DMG0575I**

## **Severity**

Information

## **Long Form**

Successfully imported Server Configuration Data.

## **Short Form**

imported config data

## **Parameters**

No parameters are provided for this message type

## **Description**

None

## **Logger DXF: Debug messages**

**Message ID : DXF4308D**

### **Severity**

Debug

### **Long Form**

No files found in directory {0}

### **Short Form**

No short form is provided for this message type

### **Description**

None

**Message ID : DXF4310D**

### **Severity**

Debug

## **Long Form**

Starting data transform of {0}

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : DXF4311D**

## **Severity**

Debug

## **Long Form**

Finished data transform of {0}

## **Short Form**

No short form is provided for this message type

Message ID : DXF4310D

## **Description**

None

**Message ID : DXF4473D**

## **Severity**

Debug

## **Long Form**

Process {0}: error {1} opening lock file at {2}. This may be due to an already running data transform instance

## **Short Form**

No short form is provided for this message type

## **Description**

None

**Message ID : DXF4475D**

## **Severity**

Debug

Message ID : DXF4311D

## **Long Form**

Starting scan of {0}

## **Short Form**

No short form is provided for this message type

## **Description**

None

# Logger DXF: Errors

**Message ID : DXF3205E**

## Severity

Error

## Long Form

The kernel component doesn't support online data transform on "{0}". Please run the data transform utility without --oxf option to transform the data offline.

## Short Form

No online Xform support.

### Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

## Description

None

## **Message ID : DXF3206E**

### **Severity**

Error

### **Long Form**

Deep Scan operation is not supported with online data transformation. Please run deep scan without --oxf option.

### **Short Form**

No short form is provided for this message type

### **Description**

None

## **Message ID : DXF3207E**

### **Severity**

Error

### **Long Form**

Cannot open or create current status file {0} : {1}



## Short Form

No current status file

### Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file
showStr	reason	Text	Code specifying reason for allowing access, if any

## Description

None

**Message ID : DXF3208E**

## Severity

Error

## Long Form

Cannot write current status file {0} : {1}

Message ID : DXF3207E

## Short Form

current status file write error

### Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file
showStr	reason	Text	Code specifying reason for allowing access, if any

## Description

None

## Message ID : DXF3209E

## Severity

Error

## Long Form

Invalid data in current status file {0}

## Short Form

Bad current status file content

### Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

## Description

None

## Message ID : DXF3215E

## Severity

Error

## Long Form

File "{0}" Invalid xf mode.

## Short Form

Invalid xf mode.

Message ID : DXF3209E

### Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

### Description

None

**Message ID : DXF3216E**

### Severity

Error

### Long Form

File "{0}" vmfs get file system failed.

### Short Form

vmfs get file system failed.

### Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Message ID : DXF3215E

Label	CEF Label	Type	Usage

## Description

None

## Message ID : DXF3217E

## Severity

Error

## Long Form

File "{0}" start self access failed.

## Short Form

start self access failed.

## Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

## Description

None

**Message ID : DXF3218E**

## Severity

Error

## Long Form

File "{0}" File handle is invalid.

## Short Form

File handle is invalid.

## Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

## Description

None

Message ID : DXF3217E

## Message ID : DXF3219E

### Severity

Error

### Long Form

File "{0}" failed to get the inode.

### Short Form

inode failure

### Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

### Description

None

## Message ID : DXF3220E

## Severity

Error

## Long Form

File "{0}" failed to get the GuardPoint MD.

## Short Form

failed to get the GuardPoint MD.

### Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

## Description

None

**Message ID : DXF3221E**

## Severity

Error

Message ID : DXF3220E



## Long Form

File "{0}" failed to get the inode INF information.

## Short Form

inode INF failure

### Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

## Description

None

## Message ID : DXF3222E

## Severity

Error

## Long Form

File "{0}" Inode is null.

Message ID : DXF3221E

## Short Form

Inode is null.

### Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

## Description

None

## Message ID : DXF3223E

### Severity

Error

## Long Form

File "{0}" failed to get the file name.

## Short Form

inode name failure.

Message ID : DXF3222E

### Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

### Description

None

### Message ID : DXF3224E

### Severity

Error

### Long Form

File "{0}" validation of MD failed.

### Short Form

validation of MD failed.

### Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Message ID : DXF3223E

Label	CEF Label	Type	Usage

## Description

None

## Message ID : DXF3225E

## Severity

Error

## Long Form

File "{0}" file MD is null.

## Short Form

file MD is null.

## Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

## Description

None

**Message ID : DXF3226E**

## Severity

Error

## Long Form

File "{0}" File MD is in the error state.

## Short Form

File MD is in the error state.

## Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

## Description

None

Message ID : DXF3225E

## Message ID : DXF3227E

### Severity

Error

### Long Form

File "{0}" Access check failed. Please check your policy.

### Short Form

Access check failed. Please check your policy.

### Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

### Description

None

## Message ID : DXF3228E

## Severity

Error

## Long Form

File "{0}" failed while quering the MD from the stream file.

## Short Form

failed while quering the MD from the stream file.

### Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

## Description

None

**Message ID : DXF3229E**

## Severity

Error

Message ID : DXF3228E

## Long Form

File "{0}" Invalid GP meta data.

## Short Form

Invalid GP meta data.

### Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

## Description

None

**Message ID : DXF3230E**

## Severity

Error

## Long Form

File "{0}" failed to get the GuardPoint file system.

Message ID : DXF3229E



## Short Form

failed to get the GuardPoint file system.

### Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

## Description

None

## Message ID : DXF3231E

### Severity

Error

## Long Form

File "{0}" GuardPoint MD is null.

## Short Form

GuardPoint MD is null.

Message ID : DXF3230E

### Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

### Description

None

### Message ID : DXF3232E

### Severity

Error

### Long Form

File "{0}" Rekey failed.

### Short Form

Rekey failed.

### Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Message ID : DXF3231E

Label	CEF Label	Type	Usage

## Description

None

## Message ID : DXF3233E

## Severity

Error

## Long Form

File "{0}" Opening the file handle failed.

## Short Form

Opening the file handle failed.

## Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

## Description

None

## Message ID : DXF3238E

## Severity

Error

## Long Form

LDT-ALERT: Scan error on [{0}] removing MDS guard for relaunching dataxform.

## Short Form

LDT scan error

## Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

## Description

None

Message ID : DXF3233E

## Message ID : DXF3239E

### Severity

Error

### Long Form

LDT-ALERT: Online Dataxfrom failed during post scan stage on [{0}]

### Short Form

LDT postscan failure

### Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

### Description

None

## Message ID : DXF3240E

## Severity

Error

## Long Form

Failed to initialize the context for container {0}.

## Short Form

failed to initialize container

### Parameters

Label	Type	Usage
dockerid	Text	Docker image or container id

## Description

None

**Message ID : DXF3241E**

## Severity

Error

Message ID : DXF3240E

## Long Form

The container {0} is not running.

## Short Form

container not running

### Parameters

Label	Type	Usage
dockerid	Text	Docker image or container id

## Description

None

## Message ID : DXF3242E

## Severity

Error

## Long Form

Verify this is a guard point with valid data transformation policy, and check the system log files for any other problems. It may be due to one or more of following reasons; 1.policy has no valid key rule(s), and/or 2. policy has no key\_op rule, and/or 3. policy has

Message ID : DXF3241E

valid permit rule(s), and/or 4. policy rule that contains key\_op in the action field also specifies other actions, and/or 5. verify that user has not enabled Header Style guardpoint as Offline transformation does not support header based guardpoints.

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : DXF4100E**

## **Severity**

Error

## **Long Form**

. --deep\_scan Perform scan as above with additional file

## **Short Form**

No short form is provided for this message type



## **Description**

None

**Message ID : DXF4101E**

## **Severity**

Error

## **Long Form**

. access checks, and estimate time required to

## **Short Form**

No short form is provided for this message type

## **Description**

None

**Message ID : DXF4102E**

## **Severity**

Error

Message ID : DXF4100E

## **Long Form**

. complete data transformation of guard point

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : DXF4105E**

## **Severity**

Error

## **Long Form**

Number of files previously in error for an unknown reason: {0}

## **Short Form**

Prev unknown file errors

### Parameters

Label	CEF Label	Type	Usage
count	vds_count	Numeric	A generic count value

### Description

None

### Message ID : DXF4106E

### Severity

Error

### Long Form

Number of files in error for an unknown reason: {0}

### Short Form

Unknown file errors

### Parameters

Label	CEF Label	Type	Usage
count	vds_count	Numeric	A generic count value

Message ID : DXF4105E

Label	CEF Label	Type	Usage

## Description

None

## Message ID : DXF4107E

## Severity

Error

## Long Form

The file {0} was previously in error for an unknown reason

## Short Form

Prev error - unknown

## Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

## Description

None

**Message ID : DXF4108E**

## Severity

Error

## Long Form

The file {0} was in error for an unknown reason

## Short Form

Prev xform file in error

## Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

## Description

None

Message ID : DXF4107E

## Message ID : DXF4109E

### Severity

Error

### Long Form

Error "{0}" opening lock file in {1}

### Short Form

Lock file error

### Parameters

Label	CEF Label	Type	Usage
showStr	reason	Text	Code specifying reason for allowing access, if any
filePath	filePath	Text	Full path to file

### Description

None

# Message ID : DXF4111E

## Severity

Error

## Long Form

Process {0}: error "{1}" opening lock file at {2}. This may be due to an already running data transform instance

## Short Form

Lock file open error

## Parameters

Label	CEF Label	Type	Usage
ecode	cn1	Numeric	An error code
showStr	reason	Text	Code specifying reason for allowing access, if any
filePath	filePath	Text	Full path to file

## Description

None

## Message ID : DXF4112E

### Severity

Error

### Long Form

Error "{0}" creating lock file in {1}

### Short Form

Lock file create fail

### Parameters

Label	CEF Label	Type	Usage
showStr	reason	Text	Code specifying reason for allowing access, if any
filePath	filePath	Text	Full path to file

### Description

None



## Message ID : DXF4113E

### Severity

Error

### Long Form

Cannot create the data transform recovery/status file {0}, {1}

### Short Form

Status file create error

### Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file
showStr	reason	Text	Code specifying reason for allowing access, if any

### Description

None

# Message ID : DXF4114E

## Severity

Error

## Long Form

Error "{0}" getting file info for {1}

## Short Form

Stat fail

## Parameters

Label	CEF Label	Type	Usage
showStr	reason	Text	Code specifying reason for allowing access, if any
filePath	filePath	Text	Full path to file

## Description

None

## Message ID : DXF4115E

### Severity

Error

### Long Form

Error "{0}" getting file attributes for {1}

### Short Form

Attr fail

### Parameters

Label	CEF Label	Type	Usage
showStr	reason	Text	Code specifying reason for allowing access, if any
filePath	filePath	Text	Full path to file

### Description

None

## Message ID : DXF4116E

### Severity

Error

### Long Form

Error "{0}" setting file attributes for {1}

### Short Form

Attr set error

### Parameters

Label	CEF Label	Type	Usage
showStr	reason	Text	Code specifying reason for allowing access, if any
filePath	filePath	Text	Full path to file

### Description

None

## Message ID : DXF4117E

### Severity

Error

### Long Form

Cannot find files in {0}, {1}

### Short Form

File first error

### Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file
showStr	reason	Text	Code specifying reason for allowing access, if any

### Description

None

## Message ID : DXF4119E

### Severity

Error

### Long Form

Error "{0}" setting file time for {1}

### Short Form

Time set error

### Parameters

Label	CEF Label	Type	Usage
showStr	reason	Text	Code specifying reason for allowing access, if any
filePath	filePath	Text	Full path to file

### Description

None

## **Message ID : DXF4120E**

### **Severity**

Error

### **Long Form**

Cannot recover previous session as file list is missing

### **Short Form**

Missing file list

### **Parameters**

No parameters are provided for this message type

### **Description**

None

## **Message ID : DXF4121E**

### **Severity**

Error

## Long Form

Cannot perform data transform for {0}, not a directory

## Short Form

Not a dir

### Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

## Description

None

## Message ID : DXF4124E

## Severity

Error

## Long Form

The file {0} was skipped. There was insufficient memory to process it

Message ID : DXF4121E



## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : DXF4125E**

## **Severity**

Error

## **Long Form**

The file {0} was previously skipped. There was insufficient memory to process it

## **Short Form**

No short form is provided for this message type

## **Description**

None

Message ID : DXF4124E

## Message ID : DXF4133E

### Severity

Error

### Long Form

The file {0} was in error. dataxform had insufficient permission

### Short Form

Bad perms

### Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

### Description

None

## Message ID : DXF4134E

## Severity

Error

## Long Form

The file {0} was previously in error. dataxform had insufficient permission

## Short Form

Prev error bad perms

### Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

## Description

None

**Message ID : DXF4135E**

## Severity

Error

Message ID : DXF4134E

## Long Form

Number of files in error due to insufficient permission: {0}

## Short Form

Perm errors

### Parameters

Label	CEF Label	Type	Usage
count	vds_count	Numeric	A generic count value

## Description

None

## Message ID : DXF4136E

## Severity

Error

## Long Form

Number of files previously in error due to insufficient permission: {0}

Message ID : DXF4135E

## Short Form

Prev perm errors

### Parameters

Label	CEF Label	Type	Usage
count	vds_count	Numeric	A generic count value

## Description

None

## Message ID : DXF4137E

## Severity

Error

## Long Form

The file {0} was in error. There was insufficient memory to process it

## Short Form

Out of memory

Message ID : DXF4136E

## Parameters

No parameters are provided for this message type

## Description

None

## Message ID : DXF4138E

## Severity

Error

## Long Form

The file {0} was previously in error. There was insufficient memory to process it

## Short Form

Prev error - no memory

## Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Message ID : DXF4137E

## Description

None

**Message ID : DXF4139E**

## Severity

Error

## Long Form

Number of files in error due to insufficient memory: {0}

## Short Form

No-memory files skipped

## Parameters

Label	CEF Label	Type	Usage
count	vds_count	Numeric	A generic count value

## Description

None

Message ID : DXF4138E

## Message ID : DXF4140E

### Severity

Error

### Long Form

Number of files previously in error due to insufficient memory: {0}

### Short Form

Prev no-memory files skipped

### Parameters

Label	CEF Label	Type	Usage
count	vds_count	Numeric	A generic count value

### Description

None

## Message ID : DXF4141E



## Severity

Error

## Long Form

Directory path too long: {0}

## Short Form

Dir too long

### Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

## Description

None

## Message ID : DXF4142E

## Severity

Error

Message ID : DXF4141E

## Long Form

Unable to process directory {0}

## Short Form

Dir in error

### Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

## Description

None

**Message ID : DXF4149E**

## Severity

Error

## Long Form

. --preserve\_sparse\_files Don't encrypt file holes. Not the default

Message ID : DXF4142E

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : DXF4150E**

## **Severity**

Error

## **Long Form**

Removal of data transformation status files completed

## **Short Form**

No short form is provided for this message type

## **Description**

None

Message ID : DXF4149E

## **Message ID : DXF4151E**

### **Severity**

Error

### **Long Form**

Removal of data transformation status files abandoned

### **Short Form**

No short form is provided for this message type

### **Description**

None

## **Message ID : DXF4152E**

### **Severity**

Error

### **Long Form**

Cleanup-on-success option is only valid with rekey operations

## Short Form

No short form is provided for this message type

## Description

None

## Message ID : DXF4153E

## Severity

Error

## Long Form

. --cleanup\_on\_success Remove status files upon success

## Short Form

No short form is provided for this message type

## Description

None

Message ID : DXF4152E

## Message ID : DXF4155E

### Severity

Error

### Long Form

The rekey list file provided contains an invalid entry "{0}". Please remove or correct the entry then try again.

### Short Form

Invalid rekey file list entry

#### Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

### Description

None

## Message ID : DXF4156E

## Severity

Error

## Long Form

. --unrecoverable Perform rekey without recording recovery data,

## Short Form

No short form is provided for this message type

## Description

None

## Message ID : DXF4157E

## Severity

Error

## Long Form

. which may run considerably faster than a normal

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : DXF4158E**

## **Severity**

Error

## **Long Form**

. rekey, but if it fails restoration of the guarded

## **Short Form**

No short form is provided for this message type

## **Description**

None

Message ID : DXF4157E



## **Message ID : DXF4159E**

### **Severity**

Error

### **Long Form**

. data from backup will be required.

### **Short Form**

No short form is provided for this message type

### **Description**

None

## **Message ID : DXF4160E**

### **Severity**

Error

### **Long Form**

Cannot continue a previous recoverable run with the "--unrecoverable" option set

## Short Form

Prev op was recoverable rekey

### Parameters

No parameters are provided for this message type

## Description

None

## Message ID : DXF4162E

## Severity

Error

## Long Form

Cannot perform data transform for {0}, failed to get HDFS file name

## Short Form

Failed to get HDFS file name

### Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

### Description

None

### Message ID : DXF4163E

### Severity

Error

### Long Form

The file {0} was previously in error. Failed to get HDFS file name

### Short Form

Prev error - failed to get HDFS file name

### Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Message ID : DXF4162E

Label	CEF Label	Type	Usage

## Description

None

## Message ID : DXF4164E

## Severity

Error

## Long Form

Number of files in error due to failure getting HDFS file name: {0}

## Short Form

HDFS file name errors

## Parameters

Label	CEF Label	Type	Usage
count	vds_count	Numeric	A generic count value

Message ID : DXF4163E

## Description

None

**Message ID : DXF4165E**

## Severity

Error

## Long Form

Number of files previously in error due to failure getting HDFS file name: {0}

## Short Form

Prev HDFS file name errors

### Parameters

Label	CEF Label	Type	Usage
count	vds_count	Numeric	A generic count value

## Description

None

Message ID : DXF4164E

## **Message ID : DXF4166E**

### **Severity**

Error

### **Long Form**

The file {0} was in error. There was insufficient disk space to process it

### **Short Form**

Out of disk space

### **Parameters**

No parameters are provided for this message type

### **Description**

None

## **Message ID : DXF4167E**

### **Severity**

Error

## Long Form

. --cid Specify Docker container id.

## Short Form

No short form is provided for this message type

## Description

None

## Message ID : DXF4168E

## Severity

Error

## Long Form

. --migrate Migrate Data from Protect File Encryption.

## Short Form

No short form is provided for this message type

Message ID : DXF4167E

## Description

None

**Message ID : DXF4215E**

## Severity

Error

## Long Form

The file {0} was in error. It was open and could not be modified safely

## Short Form

Error open file

## Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

## Description

None

Message ID : DXF4168E



## **Message ID : DXF4227E**

### **Severity**

Error

### **Long Form**

The options `--preserve_sparse_files` and `--encrypt_sparse_file_holes` are mutually exclusive

### **Short Form**

No short form is provided for this message type

### **Description**

None

## **Message ID : DXF4228E**

### **Severity**

Error

### **Long Form**

`. --preserve_sparse_files` Don't encrypt file holes. Default behavior

## Short Form

No short form is provided for this message type

## Description

None

## Message ID : DXF4229E

## Severity

Error

## Long Form

. --encrypt\_sparse\_file\_holes The opposite of --preserve\_sparse\_files

## Short Form

No short form is provided for this message type

## Description

None

Message ID : DXF4228E

## **Message ID : DXF4230E**

### **Severity**

Error

### **Long Form**

. This option has the potential to increase

### **Short Form**

No short form is provided for this message type

### **Description**

None

## **Message ID : DXF4231E**

### **Severity**

Error

### **Long Form**

. the amount of space files take up on disk

## Short Form

No short form is provided for this message type

## Description

None

## Message ID : DXF4232E

## Severity

Error

## Long Form

. --buf\_size Performance tuning: The size, in KB, of the

## Short Form

No short form is provided for this message type

## Description

None

Message ID : DXF4231E

## **Message ID : DXF4233E**

### **Severity**

Error

### **Long Form**

. buffer used for transforming data

### **Short Form**

No short form is provided for this message type

### **Description**

None

## **Message ID : DXF4234E**

### **Severity**

Error

### **Long Form**

. Range: [4..128]. Default: 128

Message ID : DXF4233E

## Short Form

No short form is provided for this message type

## Description

None

## Message ID : DXF4235E

## Severity

Error

## Long Form

. --mt Performance tuning: The max. number of

## Short Form

No short form is provided for this message type

## Description

None

Message ID : DXF4234E

## **Message ID : DXF4236E**

### **Severity**

Error

### **Long Form**

. threads that the kernel can use per file

### **Short Form**

No short form is provided for this message type

### **Description**

None

## **Message ID : DXF4237E**

### **Severity**

Error

### **Long Form**

. Range: [1..16]. Default: 16

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : DXF4238E**

## **Severity**

Error

## **Long Form**

. --thd Performance tuning: The max. number of

## **Short Form**

No short form is provided for this message type

## **Description**

None

Message ID : DXF4237E



## **Message ID : DXF4239E**

### **Severity**

Error

### **Long Form**

. files to transform at once

### **Short Form**

No short form is provided for this message type

### **Description**

None

## **Message ID : DXF4240E**

### **Severity**

Error

### **Long Form**

. Range: [1..32]. Defaults: unix:28 win:8

## Short Form

No short form is provided for this message type

## Description

None

## Message ID : DXF4241E

## Severity

Error

## Long Form

More than {0} files were encountered in the directory {1}. This will consume excessive system resources. Aborting. No files have been transformed. To disable this check, rerun with the "--disable\_memory\_checking" flag

## Short Form

No short form is provided for this message type

## Description

None

Message ID : DXF4240E

## **Message ID : DXF4243E**

### **Severity**

Error

### **Long Form**

. --status\_interval The frequency, in seconds, of how often to

### **Short Form**

No short form is provided for this message type

### **Description**

None

## **Message ID : DXF4244E**

### **Severity**

Error

### **Long Form**

. report status to the logs. Default: 300

## Short Form

No short form is provided for this message type

## Description

None

## Message ID : DXF4247E

## Severity

Error

## Long Form

Cannot open or create directory listing file {0} : {1}

## Short Form

No dir file

### Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file
showStr	reason	Text	Code specifying reason for allowing access, if any

Message ID : DXF4244E

Label	CEF Label	Type	Usage

## Description

None

## Message ID : DXF4248E

## Severity

Error

## Long Form

Cannot re-use invalid directory listing file {0}

## Short Form

Bad dir file

## Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Message ID : DXF4247E

## Description

None

**Message ID : DXF4249E**

## Severity

Error

## Long Form

Failed to cleanly close directory listing file {0} : {1}

## Short Form

Close dir file error

## Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file
showStr	reason	Text	Code specifying reason for allowing access, if any

## Description

None

## Message ID : DXF4250E

## Severity

Error

## Long Form

Cannot rename directory listing file from {0} to {1} :{2}

## Short Form

Rename dir file error

## Parameters

Label	CEF Label	Type	Usage
oldFilePath	oldFilePath	Text	Previous path to file (for rename and link)
filePath	filePath	Text	Full path to file
showStr	reason	Text	Code specifying reason for allowing access, if any

## Description

None

**Message ID : DXF4251E**

## Severity

Error

## Long Form

Invalid data in listing file {0}

## Short Form

Bad dir file content

## Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

## Description

None

Message ID : DXF4250E



## Message ID : DXF4252E

### Severity

Error

### Long Form

Cannot write directory listing file {0} : {1}

### Short Form

Dir file write error

### Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file
showStr	reason	Text	Code specifying reason for allowing access, if any

### Description

None

## Message ID : DXF4255E

### Severity

Error

### Long Form

Inconsistent data in recovery files {0} and {1}.

### Short Form

Inconsistent recovery files

### Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file
filePath	filePath	Text	Full path to file

### Description

None

## Message ID : DXF4266E

### Severity

Error

### Long Form

Error "{0}" updating status file {1}

### Short Form

File update error

### Parameters

Label	CEF Label	Type	Usage
showStr	reason	Text	Code specifying reason for allowing access, if any
filePath	filePath	Text	Full path to file

### Description

None

## Message ID : DXF4270E

### Severity

Error

### Long Form

Number of files in error due to kernel component stopping data transform: {0}

### Short Form

Kernel stop files errors

### Parameters

Label	CEF Label	Type	Usage
count	vds_count	Numeric	A generic count value

### Description

None

## Message ID : DXF4271E

## Severity

Error

## Long Form

Number of files in error due to a signal stopping the dataxform: {0}

## Short Form

Signal stop files errors

### Parameters

Label	CEF Label	Type	Usage
count	vds_count	Numeric	A generic count value

## Description

None

**Message ID : DXF4272E**

## Severity

Error

Message ID : DXF4271E

## Long Form

Number of files in error due to being open and could not be modified safely: {0}

## Short Form

Unsafe file errors

### Parameters

Label	CEF Label	Type	Usage
count	vds_count	Numeric	A generic count value

## Description

None

## Message ID : DXF4282E

## Severity

Error

## Long Form

Error "{0}" reading directory entry {1}

Message ID : DXF4272E

## Short Form

Read dir error

### Parameters

Label	CEF Label	Type	Usage
showStr	reason	Text	Code specifying reason for allowing access, if any
filePath	filePath	Text	Full path to file

## Description

None

**Message ID : DXF4286E**

## Severity

Error

## Long Form

Number of files previously in error due to kernel component stopping data transform: {0}

Message ID : DXF4282E

## Short Form

Prev kernel stop files errors

### Parameters

Label	CEF Label	Type	Usage
count	vds_count	Numeric	A generic count value

## Description

None

## Message ID : DXF4287E

## Severity

Error

## Long Form

Number of files previously in error due to a signal stopping the dataxform: {0}

## Short Form

Prev signal stop files errors

Message ID : DXF4286E



### Parameters

Label	CEF Label	Type	Usage
count	vds_count	Numeric	A generic count value

### Description

None

### Message ID : DXF4288E

### Severity

Error

### Long Form

Number of files previously in error due to being open and could not be modified safely: {0}

### Short Form

Prev unsafe file errors

### Parameters

Label	CEF Label	Type	Usage
count	vds_count	Numeric	A generic count value

Message ID : DXF4287E

Label	CEF Label	Type	Usage

## Description

None

## Message ID : DXF4289E

## Severity

Error

## Long Form

Unable to read {0}: {1}

## Short Form

Read info error

## Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file
showStr	reason	Text	Code specifying reason for allowing access, if any

Message ID : DXF4288E

## Description

None

## Message ID : DXF4290E

## Severity

Error

## Long Form

Unable to create simulation file {0}: {1}

## Short Form

Create sim file error

## Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file
showStr	reason	Text	Code specifying reason for allowing access, if any

## Description

None

## Message ID : DXF4291E

## Severity

Error

## Long Form

Error creating directory {0}: {1}

## Short Form

Create sim dir error

## Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file
showStr	reason	Text	Code specifying reason for allowing access, if any

## **Description**

None

**Message ID : DXF4292E**

## **Severity**

Error

## **Long Form**

Error removing directory {0}: {1}

## **Short Form**

No short form is provided for this message type

## **Description**

None

**Message ID : DXF4294E**

## **Severity**

Error

Message ID : DXF4291E

## Long Form

About to perform a deep scan

## Short Form

Deep scan start

### Parameters

No parameters are provided for this message type

## Description

None

**Message ID : DXF4295E**

## Severity

Error

## Long Form

-- To enable consistent results, do not access the directory during the scan

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : DXF4296E**

## **Severity**

Error

## **Long Form**

-- Transformation simulations will be performed, which may take some time

## **Short Form**

No short form is provided for this message type

## **Description**

None

Message ID : DXF4295E

## Message ID : DXF4297E

### Severity

Error

### Long Form

Filesystem containing {0} is too full to perform simulations

### Short Form

FS too full

### Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

### Description

None

## Message ID : DXF4298E



## Severity

Error

## Long Form

Filesystem containing {0} is too full to create file lists

## Short Form

FS too fill

### Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

## Description

None

**Message ID : DXF4299E**

## Severity

Error

Message ID : DXF4298E

## Long Form

Verify this is a guard point with valid data transformation policy, and check the system log files for any other problems. It may be due to one or more of following reasons; 1.policy has no valid key rule(s), and/or 2. policy has no key\_op rule, and/or 3. policy has valid permit rule(s), and/or 4. policy rule that contains key\_op in the action field also specifies other actions.

## Short Form

No short form is provided for this message type

## Description

None

## Message ID : DXF4300E

## Severity

Error

## Long Form

Out of Memory

## Short Form

Out of memory

### Parameters

No parameters are provided for this message type

### Description

None

### Message ID : DXF4301E

### Severity

Error

### Long Form

The kernel component doesn't support data transform on {0}

### Short Form

No xform support

### Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

Message ID : DXF4300E

## Description

None

**Message ID : DXF4302E**

## Severity

Error

## Long Form

Error {0} opening configuration file in {1}

## Short Form

Config file error

## Parameters

Label	CEF Label	Type	Usage
ecode	cn1	Numeric	An error code
filePath	filePath	Text	Full path to file

Message ID : DXF4301E

## **Description**

None

**Message ID : DXF4303E**

## **Severity**

Error

## **Long Form**

Error {0} opening lock file in {1}

## **Short Form**

No short form is provided for this message type

## **Description**

None

**Message ID : DXF4304E**

## **Severity**

Error

Message ID : DXF4302E

## **Long Form**

Error {0} creating lock file in {1}

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : DXF4306E**

## **Severity**

Error

## **Long Form**

Error invalid version {0} for configuration file in {1}

## **Short Form**

Bad config version

## Parameters

Label	CEF Label	Type	Usage
verno	vds_verno	Numeric	A version number
filePath	filePath	Text	Full path to file

## Description

None

## Message ID : DXF4312E

## Severity

Error

## Long Form

A file or directory in {0} may be corrupt or unreachable

## Short Form

File inaccessible

### Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

### Description

None

### Message ID : DXF4313E

### Severity

Error

### Long Form

There was an invalid parameter while processing directory {0}

### Short Form

Invalid dir param

### Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Message ID : DXF4312E



Label	CEF Label	Type	Usage

## Description

None

## Message ID : DXF4314E

## Severity

Error

## Long Form

Out of memory while processing directory {0}

## Short Form

Out of memory processing dir

## Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Message ID : DXF4313E

## Description

None

## Message ID : DXF4315E

## Severity

Error

## Long Form

Error code {0} while processing directory {1}

## Short Form

Dir processing error

## Parameters

Label	CEF Label	Type	Usage
ecode	cn1	Numeric	An error code
filePath	filePath	Text	Full path to file

## Description

None

**Message ID : DXF4325E**

## Severity

Error

## Long Form

Cannot perform data transform for {0}, does not exist

## Short Form

Does not exist

## Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

## Description

None

Message ID : DXF4315E

## Message ID : DXF4326E

### Severity

Error

### Long Form

Cannot perform data transform for {0}, access denied

### Short Form

Access denied

### Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

### Description

None

## Message ID : DXF4328E

## Severity

Error

## Long Form

Kernel component gave unexpected status {0}

## Short Form

Unexpected kernel error

### Parameters

Label	CEF Label	Type	Usage
ecode	cn1	Numeric	An error code

## Description

None

**Message ID : DXF4330E**

## Severity

Error

Message ID : DXF4328E

## **Long Form**

No file name provided to hold recovery file list

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : DXF4331E**

## **Severity**

Error

## **Long Form**

Cannot open {0} to get recovery file list

## **Short Form**

List access fail

## Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

## Description

None

**Message ID : DXF4334E**

## Severity

Error

## Long Form

No value provided for command line parameter {0}

## Short Form

No short form is provided for this message type

## Description

None

Message ID : DXF4331E

## **Message ID : DXF4335E**

### **Severity**

Error

### **Long Form**

Unknown command line option {0}

### **Short Form**

No short form is provided for this message type

### **Description**

None

## **Message ID : DXF4336E**

### **Severity**

Error

### **Long Form**

Command line must specify an operation



## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : DXF4340E**

## **Severity**

Error

## **Long Form**

Command line must specify a guard point

## **Short Form**

No short form is provided for this message type

## **Description**

None

Message ID : DXF4336E

## **Message ID : DXF4341E**

### **Severity**

Error

### **Long Form**

Directory specified on command line does not exist, {0}

### **Short Form**

No short form is provided for this message type

### **Description**

None

## **Message ID : DXF4342E**

### **Severity**

Error

### **Long Form**

Only one command line operation is allowed if scan is selected

## Short Form

No short form is provided for this message type

## Description

None

## Message ID : DXF4343E

## Severity

Error

## Long Form

Attempt to normalize directory {0} got error code {1}

## Short Form

No short form is provided for this message type

## Description

None

Message ID : DXF4342E

## **Message ID : DXF4346E**

### **Severity**

Error

### **Long Form**

The command line is not valid

### **Short Form**

No short form is provided for this message type

### **Description**

None

## **Message ID : DXF4347E**

### **Severity**

Error

### **Long Form**

Unable to create the progress-reporting thread

Message ID : DXF4346E

## Short Form

Thread create fail

### Parameters

No parameters are provided for this message type

## Description

None

**Message ID : DXF4349E**

## Severity

Error

## Long Form

Cannot set up data transform recovery/status files

## Short Form

Status file setup fail

Message ID : DXF4347E

### **Parameters**

No parameters are provided for this message type

### **Description**

None

### **Message ID : DXF4350E**

### **Severity**

Error

### **Long Form**

Cannot delete data transform status and lock files

### **Short Form**

Status/lock file delete fail

### **Parameters**

No parameters are provided for this message type

## **Description**

None

**Message ID : DXF4353E**

## **Severity**

Error

## **Long Form**

Check the recovery files for errors, or run "--cleanup" option to remove them.

## **Short Form**

No short form is provided for this message type

## **Description**

None

**Message ID : DXF4354E**

## **Severity**

Error

Message ID : DXF4350E

## **Long Form**

Make sure any files already transformed are restored before a cleanup is done.

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : DXF4355E**

## **Severity**

Error

## **Long Form**

As the previous dataxform run used the "--unrecoverable" option, you need to restore the GuardPoint from a backup, then use the "--cleanup" option before running the rekey operation again.

## **Short Form**

No short form is provided for this message type



## Description

None

**Message ID : DXF4356E**

## Severity

Error

## Long Form

Could not notify kernel component about data transform on {0}

## Short Form

Kernel notify fail

## Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

## Description

None

Message ID : DXF4355E

## Message ID : DXF4357E

### Severity

Error

### Long Form

Could not restrict access to {0}

### Short Form

Access restrict fail

### Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

### Description

None

## Message ID : DXF4358E

## Severity

Error

## Long Form

Could not allow access to {0}

## Short Form

Access allow fail

### Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

## Description

None

**Message ID : DXF4360E**

## Severity

Error

Message ID : DXF4358E

## Long Form

Could not complete data transform, the policy for guard point {0} changed

## Short Form

Policy changed

### Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

## Description

None

**Message ID : DXF4367E**

## Severity

Error

## Long Form

Data transform got errors on some files

Message ID : DXF4360E

## Short Form

Prev xform fail

### Parameters

No parameters are provided for this message type

## Description

None

## Message ID : DXF4368E

## Severity

Error

## Long Form

The file {0} could not be transformed in the previous data transform, it will not be transformed

## Short Form

Prev file xform fail

### Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

### Description

None

### Message ID : DXF4376E

### Severity

Error

### Long Form

Data transform in guard point {0} failed for {1} files

### Short Form

Prev xform failures

### Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

Message ID : DXF4368E

Label	CEF Label	Type	Usage
nfile	vds_nfile	Numeric	The number of files processed

## Description

None

## Message ID : DXF4377E

## Severity

Error

## Long Form

Error while scanning for hard links in directory {0}

## Short Form

No short form is provided for this message type

## Description

None

## Message ID : DXF4379E

### Severity

Error

### Long Form

Error scanning guard point {0} while processing directory {1}

### Short Form

Scan error

### Parameters

Label	CEF Label	Type	Usage
showStr	reason	Text	Code specifying reason for allowing access, if any
filePath	filePath	Text	Full path to file

### Description

None



## Message ID : DXF4381E

### Severity

Error

### Long Form

Error scanning guard point {0}

### Short Form

Scan fail

### Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

### Description

None

## Message ID : DXF4382E

## Severity

Error

## Long Form

Automatic data transform cannot be performed on {0}

## Short Form

No xform support

### Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

## Description

None

## Message ID : DXF4391E

## Severity

Error

Message ID : DXF4382E

## **Long Form**

Data transform of files listed in {0} for guard point {1} failed

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : DXF4392E**

## **Severity**

Error

## **Long Form**

Error {0} opening configuration file in {1}: does not exist

## **Short Form**

Cfg file error

## Parameters

Label	CEF Label	Type	Usage
ecode	cn1	Numeric	An error code
filePath	filePath	Text	Full path to file

## Description

None

## Message ID : DXF4393E

## Severity

Error

## Long Form

Error {0} opening lock file in {1}: does not exist

## Short Form

Lock file error

## Parameters

Label	CEF Label	Type	Usage
ecode	cn1	Numeric	An error code
filePath	filePath	Text	Full path to file

## Description

None

## Message ID : DXF4394E

## Severity

Error

## Long Form

Error {0} creating lock file in {1}: does not exist

## Short Form

No short form is provided for this message type

## **Description**

None

**Message ID : DXF4395E**

## **Severity**

Error

## **Long Form**

Error {0} getting file info for {1}

## **Short Form**

No short form is provided for this message type

## **Description**

None

**Message ID : DXF4396E**

## **Severity**

Error

Message ID : DXF4394E

## **Long Form**

Error {0} getting file attributes for {1}

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : DXF4400E**

## **Severity**

Error

## **Long Form**

Error trying to create a worker thread

## **Short Form**

Threadcreate fail

## Parameters

No parameters are provided for this message type

## Description

None

## Message ID : DXF4401E

## Severity

Error

## Long Form

Error {0} ({1}) trying to delete file {2}

## Short Form

Delete file error

## Parameters

Label	CEF Label	Type	Usage
ecode	cn1	Numeric	An error code
showStr	reason	Text	Code specifying reason for allowing access, if any

Message ID : DXF4400E



Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

## Description

None

## Message ID : DXF4403E

## Severity

Error

## Long Form

No path provided for recovery information file

## Short Form

Missing recovery info

## Parameters

No parameters are provided for this message type

## **Description**

None

**Message ID : DXF4404E**

## **Severity**

Error

## **Long Form**

Error {0} setting file attributes for {1}

## **Short Form**

No short form is provided for this message type

## **Description**

None

**Message ID : DXF4405E**

## **Severity**

Error

Message ID : DXF4403E

## **Long Form**

Error {0} setting file time for {1}

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : DXF4407E**

## **Severity**

Error

## **Long Form**

Could not determine the Windows installation directory

## **Short Form**

Cannot determine install dir

### **Parameters**

No parameters are provided for this message type

### **Description**

None

**Message ID : DXF4408E**

### **Severity**

Error

### **Long Form**

Internal error: thread index {0} is not valid

### **Short Form**

Bad thread id

### **Parameters**

No parameters are provided for this message type

Message ID : DXF4407E

## Description

None

**Message ID : DXF4409E**

## Severity

Error

## Long Form

Cannot find files in {0}, error {1}

## Short Form

Find first error

## Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file
ecode	cn1	Numeric	An error code

## **Description**

None

**Message ID : DXF4427E**

## **Severity**

Error

## **Long Form**

Failed to authorize this program with the kernel

## **Short Form**

Cannot protect PID

## **Parameters**

No parameters are provided for this message type

## **Description**

None

Message ID : DXF4409E

## Message ID : DXF4430E

### Severity

Error

### Long Form

The data transformation process was denied permission to access the directory {0}

### Short Form

Dir access denied

### Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

### Description

None

## Message ID : DXF4432E

## **Severity**

Error

## **Long Form**

Build version: {0}

## **Short Form**

No short form is provided for this message type

## **Description**

None

**Message ID : DXF4433E**

## **Severity**

Error

## **Long Form**

Build ID: {0}

Message ID : DXF4432E



## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : DXF4434E**

## **Severity**

Error

## **Long Form**

Build Date: {0}

## **Short Form**

No short form is provided for this message type

## **Description**

None

Message ID : DXF4433E

## **Message ID : DXF4435E**

### **Severity**

Error

### **Long Form**

About to perform the requested data transform operation

### **Short Form**

No short form is provided for this message type

### **Description**

None

## **Message ID : DXF4436E**

### **Severity**

Error

### **Long Form**

-- Be sure to back up your data

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : DXF4437E**

## **Severity**

Error

## **Long Form**

-- Please do not access files in the guard point during the transform process

## **Short Form**

No short form is provided for this message type

## **Description**

None

Message ID : DXF4436E

## **Message ID : DXF4438E**

### **Severity**

Error

### **Long Form**

-- Please do not attempt to terminate the application

### **Short Form**

No short form is provided for this message type

### **Description**

None

## **Message ID : DXF4439E**

### **Severity**

Error

### **Long Form**

Do you wish to continue (y/n)?

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : DXF4440E**

## **Severity**

Error

## **Long Form**

.Usage:

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : DXF4441E**

### **Severity**

Error

### **Long Form**

. dataxform {operation} {operation options}

### **Short Form**

No short form is provided for this message type

### **Description**

None

## **Message ID : DXF4442E**

### **Severity**

Error

### **Long Form**

. where {operation} is the desired operation

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : DXF4443E**

## **Severity**

Error

## **Long Form**

. --rekey Rekey the files in guard point

## **Short Form**

No short form is provided for this message type

## **Description**

None

Message ID : DXF4442E

## **Message ID : DXF4444E**

### **Severity**

Error

### **Long Form**

. --rekey\_supported Report if rekey is supported on guard point

### **Short Form**

No short form is provided for this message type

### **Description**

None

## **Message ID : DXF4445E**

### **Severity**

Error

### **Long Form**

. --scan Display number of files and directories in



## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : DXF4446E**

## **Severity**

Error

## **Long Form**

. the guard point

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : DXF4447E**

### **Severity**

Error

### **Long Form**

. --check\_links Scan guard point and report any hard links

### **Short Form**

No short form is provided for this message type

### **Description**

None

## **Message ID : DXF4448E**

### **Severity**

Error

### **Long Form**

. --cleanup Remove existing status files from a previous

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : DXF4449E**

## **Severity**

Error

## **Long Form**

. rekey session

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : DXF4450E**

### **Severity**

Error

### **Long Form**

. --recovery Generate a list of files already rekeyed in

### **Short Form**

No short form is provided for this message type

### **Description**

None

## **Message ID : DXF4451E**

### **Severity**

Error

### **Long Form**

. guard point

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : DXF4452E**

## **Severity**

Error

## **Long Form**

. --rekey\_list Only rekey files listed in directive file

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : DXF4453E**

### **Severity**

Error

### **Long Form**

. --version Display the version number

### **Short Form**

No short form is provided for this message type

### **Description**

None

## **Message ID : DXF4454E**

### **Severity**

Error

### **Long Form**

. where {operation options} are parameters for the operation

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : DXF4455E**

## **Severity**

Error

## **Long Form**

. --gp Specify name of guard point

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : DXF4456E**

### **Severity**

Error

### **Long Form**

. Required for all operations except --version

### **Short Form**

No short form is provided for this message type

### **Description**

None

## **Message ID : DXF4457E**

### **Severity**

Error

### **Long Form**

. --file\_list Specify fully qualified name of directive



## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : DXF4458E**

## **Severity**

Error

## **Long Form**

. file for --rekey\_list and --recovery

## **Short Form**

No short form is provided for this message type

## **Description**

None

Message ID : DXF4457E

## **Message ID : DXF4459E**

### **Severity**

Error

### **Long Form**

. Defaults to dataxform\_files in the guard

### **Short Form**

No short form is provided for this message type

### **Description**

None

## **Message ID : DXF4460E**

### **Severity**

Error

### **Long Form**

. point directory

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : DXF4461E**

## **Severity**

Error

## **Long Form**

. --dir\_recovery Specify location for status file

## **Short Form**

No short form is provided for this message type

## **Description**

None

Message ID : DXF4460E

## **Message ID : DXF4462E**

### **Severity**

Error

### **Long Form**

. Defaults to use log file location if there

### **Short Form**

No short form is provided for this message type

### **Description**

None

## **Message ID : DXF4463E**

### **Severity**

Error

### **Long Form**

. is no --status\_gp option

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : DXF4464E**

## **Severity**

Error

## **Long Form**

About to remove the data transformation status files

## **Short Form**

No short form is provided for this message type

## **Description**

None

Message ID : DXF4463E

## Message ID : DXF4465E

### Severity

Error

### Long Form

Shutting down data transform: received fatal signal {0}

### Short Form

Xform killed by sigal

#### Parameters

Label	CEF Label	Type	Usage
sig	vds_sig	Numeric	A signal value

### Description

None

## Message ID : DXF4466E

## Severity

Error

## Long Form

Could not complete data transform for guard point {0}, data transform was interrupted by a signal

## Short Form

Xform interrupted by signal

### Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

## Description

None

**Message ID : DXF4467E**

## Severity

Error

Message ID : DXF4466E

## Long Form

. --preserve\_access\_time Preserve file access time after rekey

## Short Form

No short form is provided for this message type

## Description

None

## Message ID : DXF4468E

## Severity

Error

## Long Form

. --preserve\_modified\_time Preserve file modified time after rekey

## Short Form

No short form is provided for this message type



## **Description**

None

**Message ID : DXF4469E**

## **Severity**

Error

## **Long Form**

. --nq Suppress prompts

## **Short Form**

No short form is provided for this message type

## **Description**

None

**Message ID : DXF4470E**

## **Severity**

Error

Message ID : DXF4468E

## Long Form

. --print\_stat Display data transform statistics

## Short Form

No short form is provided for this message type

## Description

None

## Message ID : DXF4471E

## Severity

Error

## Long Form

. --status\_gp Write status file to the guard point

## Short Form

No short form is provided for this message type

Message ID : DXF4470E

**Description**

None

**Message ID : DXF4472E****Severity**

Error

**Long Form**

. directory

**Short Form**

No short form is provided for this message type

**Description**

None

**Message ID : DXF4474E****Severity**

Error

Message ID : DXF4471E

## Long Form

Process {0}: error {1} opening lock file at {2}. This may be due to an already running data transform instance

## Short Form

No short form is provided for this message type

## Description

None

## Message ID : DXF4476E

## Severity

Error

## Long Form

The file {0} could not be transformed

## Short Form

Prev xform file fail

## Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

## Description

None

**Message ID : DXF4477E**

## Severity

Error

## Long Form

The file {0} could not be transformed, it had error in the previous data transform

## Short Form

No short form is provided for this message type

## Description

None

Message ID : DXF4476E

## Message ID : DXF4478E

### Severity

Error

### Long Form

The file {0} could not be transformed, it was in progress in the previous data transform

### Short Form

Prev xform file in progress

### Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

### Description

None

## Message ID : DXF4479E

## Severity

Error

## Long Form

The file {0} could not be transformed, the kernel component stopped the data transform

## Short Form

Prev xform file stopped by kernel

### Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

## Description

None

**Message ID : DXF4480E**

## Severity

Error

Message ID : DXF4479E

## Long Form

The file {0} could not be transformed, a signal stopped the data transform

## Short Form

Prev xform file stopped by signal

### Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

## Description

None

## Message ID : DXF4482E

## Severity

Error

## Long Form

Cannot create the data transform recovery/status file {0}, errno {1}

Message ID : DXF4480E



## Short Form

No short form is provided for this message type

## Description

None

## Message ID : DXF4483E

## Severity

Error

## Long Form

Cannot create the data transform recovery/status file {0}, the file name is too long

## Short Form

File too long

## Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

## **Description**

None

**Message ID : DXF4484E**

## **Severity**

Error

## **Long Form**

Verify this is a guard point with a data transformation rule, and check the system log files for any other problems

## **Short Form**

No short form is provided for this message type

## **Description**

None

**Message ID : DXF4486E**

## **Severity**

Error

Message ID : DXF4483E

## Long Form

Invalid format in recovery file {0}

## Short Form

Bad recovery file

### Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

## Description

None

**Message ID : DXF4494E**

## Severity

Error

## Long Form

The file {0} was previously in error. The kernel component stopped the data transform

Message ID : DXF4486E

## Short Form

Prev error - kernel stop

### Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

## Description

None

## Message ID : DXF4498E

## Severity

Error

## Long Form

The file {0} was previously in error. A signal stopped the dataxform

## Short Form

Prev skipped - signal stop

Message ID : DXF4494E

### Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

### Description

None

### Message ID : DXF4499E

### Severity

Error

### Long Form

The file {0} was previously in error. It was open and could not be modified safely

### Short Form

Prev error file open

### Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Message ID : DXF4498E

Label	CEF Label	Type	Usage

## Description

None

# Logger DXF: Fatal errors

**Message ID : DXF4431F**

## **Severity**

Fatal error

## **Long Form**

Unable to determine the fully qualified host name of this machine: {0}. Please examine your machine's configuration.

## **Short Form**

No short form is provided for this message type

## **Description**

None

# Logger DXF: Information

**Message ID : DXF3211I**

## Severity

Information

## Long Form

File {0} is being mapped or no-viewed, so it is skipped temporarily and moving on to next file

## Short Form

File is being mapped or no-viewed

### Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

## Description

None



# Message ID : DXF3235I

## Severity

Information

## Long Form

LDT: Live data transform scan phase ran from {0} until {1}

## Short Form

OXF run

### Parameters

Label	CEF Label	Type	Usage
stime	start	Text	A start time stamp
etime	end	Text	An end time stamp

## Description

None

## Message ID : DXF3236I

### Severity

Information

### Long Form

LDT: Live data transform scan operation took {0} hours, {1} minutes and {2} seconds

### Short Form

OXF duration

#### Parameters

Label	CEF Label	Type	Usage
hours	vds_hours	Numeric	Elapsed hours
mins	vds_mins	Numeric	Elaped minutes
secs	vds_secs	Numeric	Elapsed seconds

### Description

None

# Message ID : DXF3237I

## Severity

Information

## Long Form

LDT: Live data transformation scan operation took {0} hours, {1} minutes and {2} seconds

## Short Form

OXF op duration

### Parameters

Label	CEF Label	Type	Usage
hours	vds_hours	Numeric	Elapsed hours
mins	vds_mins	Numeric	Elaped minutes
secs	vds_secs	Numeric	Elapsed seconds

## Description

None

## **Message ID : DXF4122I**

### **Severity**

Information

### **Long Form**

Number of files skipped due to insufficient memory: {0}

### **Short Form**

No short form is provided for this message type

### **Description**

None

## **Message ID : DXF4123I**

### **Severity**

Information

### **Long Form**

Number of files previously skipped due to insufficient memory: {0}

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : DXF4126I**

## **Severity**

Information

## **Long Form**

-- This is an estimated time using actual data transformations on test files

## **Short Form**

No short form is provided for this message type

## **Description**

None

Message ID : DXF4123I

## **Message ID : DXF4127I**

### **Severity**

Information

### **Long Form**

-- This is an estimated time using simulated data transformations on test files

### **Short Form**

No short form is provided for this message type

### **Description**

None

## **Message ID : DXF4128I**

### **Severity**

Information

### **Long Form**

-- The actual transformation time may be more or less than this estimate

## Short Form

No short form is provided for this message type

## Description

None

## Message ID : DXF4129I

## Severity

Information

## Long Form

The file {0} was skipped. It was excluded by policy

## Short Form

Skipped file by policy

## Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

## Description

None

**Message ID : DXF4130I**

## Severity

Information

## Long Form

The file {0} was previously skipped. It was excluded by policy

## Short Form

Prev skipped file by policy

## Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

## Description

None

Message ID : DXF4129I



## Message ID : DXF4131I

### Severity

Information

### Long Form

Number of files skipped due to policy exclusion: {0}

### Short Form

Skipped files by policy

#### Parameters

Label	CEF Label	Type	Usage
count	vds_count	Numeric	A generic count value

### Description

None

## Message ID : DXF4132I

## Severity

Information

## Long Form

Number of files previously skipped due to policy exclusion: {0}

## Short Form

Prev skipped files by policy

### Parameters

Label	CEF Label	Type	Usage
count	vds_count	Numeric	A generic count value

## Description

None

## Message ID : DXF4143I

## Severity

Information

Message ID : DXF4132I

## Long Form

{0} is not a guard point with a rekey policy applied

## Short Form

Xform not supported

### Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

## Description

None

## Message ID : DXF4144I

## Severity

Information

## Long Form

The deep scan will emulate transformation to derive timing estimates

Message ID : DXF4143I

## Short Form

Emulating xforms

### Parameters

No parameters are provided for this message type

## Description

None

## Message ID : DXF4145I

## Severity

Information

## Long Form

The file {0} was skipped. It does not exist

## Short Form

File missing

### Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

### Description

None

### Message ID : DXF4146I

### Severity

Information

### Long Form

Number of files skipped due to not existing: {0}

### Short Form

Files missing

### Parameters

Label	CEF Label	Type	Usage
count	vds_count	Numeric	A generic count value

Message ID : DXF4145I

Label	CEF Label	Type	Usage

## Description

None

## Message ID : DXF4147I

## Severity

Information

## Long Form

Number of files previously skipped due to not existing: {0}

## Short Form

Prev files missing

### Parameters

Label	CEF Label	Type	Usage
count	vds_count	Numeric	A generic count value

## Description

None

**Message ID : DXF4148I**

## Severity

Information

## Long Form

The file {0} was previously skipped. It does not exist

## Short Form

Prev error - file missing

## Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

## Description

None

Message ID : DXF4147I

## Message ID : DXF4154I

### Severity

Information

### Long Form

The data transform program ran from {0} until {1}

### Short Form

Xform run

#### Parameters

Label	CEF Label	Type	Usage
stime	start	Text	A start time stamp
etime	end	Text	An end time stamp

### Description

None



## Message ID : DXF4161I

### Severity

Information

### Long Form

Skipping junction point {0}

### Short Form

Junction point

#### Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

### Description

None

## Message ID : DXF4200I

## Severity

Information

## Long Form

The file {0} was skipped. It was an additional hard link

## Short Form

Skipped dup hard link

### Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

## Description

None

## Message ID : DXF4201I

## Severity

Information

Message ID : DXF4200I

## Long Form

The file {0} was skipped. It was a soft link

## Short Form

Skipped soft link

### Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

## Description

None

## Message ID : DXF4202I

## Severity

Information

## Long Form

The file {0} was skipped. It was a dataxform internal file

Message ID : DXF4201I

## Short Form

Skipped internal file

### Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

## Description

None

## Message ID : DXF4203I

### Severity

Information

## Long Form

The file {0} was skipped. dataxform had insufficient permission

## Short Form

No short form is provided for this message type

Message ID : DXF4202I

## Description

None

**Message ID : DXF4204I**

## Severity

Information

## Long Form

The file {0} was skipped. It had an ambiguous name

## Short Form

Skipped bad name

## Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

## Description

None

Message ID : DXF4203I

## Message ID : DXF4205I

### Severity

Information

### Long Form

The file {0} was skipped. It was a special file

### Short Form

Skipped special file

### Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

### Description

None

## Message ID : DXF4206I

## Severity

Information

## Long Form

The file {0} was skipped. It was exempt from data transform

## Short Form

Skipped except file

### Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

## Description

None

**Message ID : DXF4207I**

## Severity

Information

Message ID : DXF4206I

## Long Form

The file {0} was skipped. It was a compressed file

## Short Form

Skipped compressed file

### Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

## Description

None

**Message ID : DXF4208I**

## Severity

Information

## Long Form

The file {0} was skipped. It was an encrypted file

Message ID : DXF4207I



## Short Form

Skipped encrypted file

### Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

## Description

None

## Message ID : DXF4209I

## Severity

Information

## Long Form

The file {0} was skipped. It was not a regular file

## Short Form

Skipped non-file

Message ID : DXF4208I

## Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

## Description

None

## Message ID : DXF4210I

## Severity

Information

## Long Form

The file {0} was skipped. There was insufficient memory to process it

## Short Form

No short form is provided for this message type

## Description

None

Message ID : DXF4209I

## **Message ID : DXF4211I**

### **Severity**

Information

### **Long Form**

The file {0} was skipped. It could not be classified

### **Short Form**

No short form is provided for this message type

### **Description**

None

## **Message ID : DXF4212I**

### **Severity**

Information

### **Long Form**

The file {0} was skipped. It was no longer present when a transform was attempted

## Short Form

File gone away

### Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

## Description

None

## Message ID : DXF4213I

## Severity

Information

## Long Form

The file {0} was skipped. A transform would have used the same key

## Short Form

Skipped - same key

Message ID : DXF4212I

### Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

### Description

None

### Message ID : DXF4214I

### Severity

Information

### Long Form

The file {0} was skipped. Rekey was not supported for this file

### Short Form

Skipped unsupported file

### Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Message ID : DXF4213I

Label	CEF Label	Type	Usage

## Description

None

## Message ID : DXF4216I

## Severity

Information

## Long Form

The file {0} was previously skipped. It was an additional hard link

## Short Form

Prev skipped dup link

## Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

## Description

None

**Message ID : DXF4217I**

## Severity

Information

## Long Form

The file {0} was previously skipped. It was a soft link

## Short Form

Prev skipped soft link

## Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

## Description

None

Message ID : DXF4216I

## Message ID : DXF4218I

### Severity

Information

### Long Form

The file {0} was previously skipped. It was a dataxform internal file

### Short Form

Prev skipped internal file

### Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

### Description

None

## Message ID : DXF4219I



## **Severity**

Information

## **Long Form**

The file {0} was previously skipped. dataxform had insufficient permission

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : DXF4220I**

## **Severity**

Information

## **Long Form**

The file {0} was previously skipped. It had an ambiguous name

Message ID : DXF4219I

1088

## Short Form

Prev skipped bad name

### Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

## Description

None

## Message ID : DXF4221I

## Severity

Information

## Long Form

The file {0} was previously skipped. It was a special file

## Short Form

Prev skipped special file

Message ID : DXF4220I

### Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

### Description

None

### Message ID : DXF4222I

### Severity

Information

### Long Form

The file {0} was previously skipped. It was exempt from data transform

### Short Form

Prev skipped exempt file

### Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Message ID : DXF4221I

Label	CEF Label	Type	Usage

## Description

None

## Message ID : DXF4223I

## Severity

Information

## Long Form

The file {0} was previously skipped. It was a compressed file

## Short Form

Prev skipped compressed file

## Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

## Description

None

**Message ID : DXF4224I**

## Severity

Information

## Long Form

The file {0} was previously skipped. It was an encrypted file

## Short Form

Prev skipped encrypted file

## Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

## Description

None

Message ID : DXF4223I

## Message ID : DXF4225I

### Severity

Information

### Long Form

Automatic data transform for guard point {0} deferred, no configuration file

### Short Form

No config file

### Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

### Description

None

## Message ID : DXF4226I

## Severity

Information

## Long Form

The file {0} has the same "to" and "from" keys; skipping

## Short Form

Skipping same keys

### Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

## Description

None

## Message ID : DXF4253I

## Severity

Information

Message ID : DXF4226I

## Long Form

There is no partial data transform for {0} to recover

## Short Form

Nothing to recover

### Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

## Description

None

## Message ID : DXF4257I

## Severity

Information

## Long Form

Number of additional hard links skipped: {0}

Message ID : DXF4253I



## Short Form

Hardlinks skipped

### Parameters

Label	CEF Label	Type	Usage
count	vds_count	Numeric	A generic count value

## Description

None

## Message ID : DXF4258I

### Severity

Information

## Long Form

Number of soft links skipped: {0}

## Short Form

Softlinks skipped

Message ID : DXF4257I

## Parameters

Label	CEF Label	Type	Usage
count	vds_count	Numeric	A generic count value

## Description

None

## Message ID : DXF4259I

## Severity

Information

## Long Form

Number of files skipped due to insufficient permission: {0}

## Short Form

No short form is provided for this message type

## Description

None

Message ID : DXF4258I

## Message ID : DXF4260I

### Severity

Information

### Long Form

Number of files skipped due to an ambiguous name: {0}

### Short Form

Bad name errors

#### Parameters

Label	CEF Label	Type	Usage
count	vds_count	Numeric	A generic count value

### Description

None

## Message ID : DXF4261I

## Severity

Information

## Long Form

Number of special files skipped: {0}

## Short Form

Special files skipped

### Parameters

Label	CEF Label	Type	Usage
count	vds_count	Numeric	A generic count value

## Description

None

## Message ID : DXF4262I

## Severity

Information

Message ID : DXF4261I

## Long Form

Number of files exempt from data transform skipped: {0}

## Short Form

Exempt files skipped

### Parameters

Label	CEF Label	Type	Usage
count	vds_count	Numeric	A generic count value

## Description

None

## Message ID : DXF4263I

## Severity

Information

## Long Form

Number of compressed files skipped: {0}

Message ID : DXF4262I

## Short Form

Compressed files skipped

### Parameters

Label	CEF Label	Type	Usage
count	vds_count	Numeric	A generic count value

## Description

None

## Message ID : DXF4264I

## Severity

Information

## Long Form

Number of encrypted files skipped: {0}

## Short Form

Encrypted files skipped

Message ID : DXF4263I

### Parameters

Label	CEF Label	Type	Usage
count	vds_count	Numeric	A generic count value

### Description

None

### Message ID : DXF4265I

### Severity

Information

### Long Form

Number of non-regular files skipped: {0}

### Short Form

Non-reg files skipped

### Parameters

Label	CEF Label	Type	Usage
count	vds_count	Numeric	A generic count value

Message ID : DXF4264I

Label	CEF Label	Type	Usage

## Description

None

## Message ID : DXF4267I

## Severity

Information

## Long Form

Number of files skipped due to being no longer present when transform attempted: {0}

## Short Form

Files gone away

## Parameters

Label	CEF Label	Type	Usage
count	vds_count	Numeric	A generic count value



## Description

None

**Message ID : DXF4268I**

## Severity

Information

## Long Form

Number of files skipped due to a duplicate key: {0}

## Short Form

Files with dup key

### Parameters

Label	CEF Label	Type	Usage
count	vds_count	Numeric	A generic count value

## Description

None

Message ID : DXF4267I

## Message ID : DXF4269I

### Severity

Information

### Long Form

Number of files skipped due to rekey not supported for this file: {0}

### Short Form

Unsupported files skipped

### Parameters

Label	CEF Label	Type	Usage
count	vds_count	Numeric	A generic count value

### Description

None

## Message ID : DXF4273I

## Severity

Information

## Long Form

Number of additional hard links previously skipped: {0}

## Short Form

Prev hardlinks skipped

### Parameters

Label	CEF Label	Type	Usage
count	vds_count	Numeric	A generic count value

## Description

None

## Message ID : DXF4274I

## Severity

Information

Message ID : DXF4273I

## Long Form

Number of soft links previously skipped: {0}

## Short Form

Prev softlinks skipped

### Parameters

Label	CEF Label	Type	Usage
count	vds_count	Numeric	A generic count value

## Description

None

## Message ID : DXF4275I

## Severity

Information

## Long Form

Number of files previously skipped due to insufficient permission: {0}

Message ID : DXF4274I

## Short Form

No short form is provided for this message type

## Description

None

## Message ID : DXF4276I

## Severity

Information

## Long Form

Number of files previously skipped due to an ambiguous name: {0}

## Short Form

Prev bad name errors

### Parameters

Label	CEF Label	Type	Usage
count	vds_count	Numeric	A generic count value

Message ID : DXF4275I

## Description

None

**Message ID : DXF4277I**

## Severity

Information

## Long Form

Number of special files previously skipped: {0}

## Short Form

Prev special files skipped

## Parameters

Label	CEF Label	Type	Usage
count	vds_count	Numeric	A generic count value

## Description

None

Message ID : DXF4276I

## Message ID : DXF4278I

### Severity

Information

### Long Form

Number of files exempt from data transform previously skipped: {0}

### Short Form

Prev exempt files skipped

#### Parameters

Label	CEF Label	Type	Usage
count	vds_count	Numeric	A generic count value

### Description

None

## Message ID : DXF4279I

## Severity

Information

## Long Form

Number of compressed files previously skipped: {0}

## Short Form

Prev compressed files skipped

### Parameters

Label	CEF Label	Type	Usage
count	vds_count	Numeric	A generic count value

## Description

None

## Message ID : DXF4280I

## Severity

Information

Message ID : DXF4279I



## Long Form

Number of encrypted files previously skipped: {0}

## Short Form

Prev encrypted files skipped

### Parameters

Label	CEF Label	Type	Usage
count	vds_count	Numeric	A generic count value

## Description

None

## Message ID : DXF4281I

## Severity

Information

## Long Form

Number of non-regular files previously skipped: {0}

Message ID : DXF4280I

## Short Form

Prev non-reg files skipped

### Parameters

Label	CEF Label	Type	Usage
count	vds_count	Numeric	A generic count value

## Description

None

## Message ID : DXF4283I

## Severity

Information

## Long Form

Number of files previously skipped due to being no longer present when transform attempted: {0}

## Short Form

Prev files gone away

Message ID : DXF4281I

1113

### Parameters

Label	CEF Label	Type	Usage
count	vds_count	Numeric	A generic count value

### Description

None

### Message ID : DXF4284I

### Severity

Information

### Long Form

Number of files previously skipped due to a duplicate key: {0}

### Short Form

Prev files with dup key

### Parameters

Label	CEF Label	Type	Usage
count	vds_count	Numeric	A generic count value

Message ID : DXF4283I

Label	CEF Label	Type	Usage

## Description

None

## Message ID : DXF4285I

## Severity

Information

## Long Form

Number of files previously skipped due to rekey not supported for this file: {0}

## Short Form

Prev unsupported files skipped

## Parameters

Label	CEF Label	Type	Usage
count	vds_count	Numeric	A generic count value

## Description

None

**Message ID : DXF4293I**

## Severity

Information

## Long Form

Estimated data transformation time for {0} is {1}

## Short Form

Estimate duration

### Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory
rt	rt	Text	Time of event

## **Description**

None

**Message ID : DXF4309I**

## **Severity**

Information

## **Long Form**

Building the list of previously transformed files in {0}

## **Short Form**

No short form is provided for this message type

## **Description**

None

**Message ID : DXF4316I**

## **Severity**

Information

Message ID : DXF4293I

## **Long Form**

Status information for directories in guard point

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : DXF4317I**

## **Severity**

Information

## **Long Form**

Finished processing directory {0}

## **Short Form**

Completed dir

### Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

### Description

None

### Message ID : DXF4318I

### Severity

Information

### Long Form

Partially processed directory {0}

### Short Form

Partially processed dir

### Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Message ID : DXF4317I



Label	CEF Label	Type	Usage

## Description

None

## Message ID : DXF4319I

## Severity

Information

## Long Form

Skipping directory {0}

## Short Form

Skipped dir

## Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Message ID : DXF4318I

## Description

None

**Message ID : DXF4320I**

## Severity

Information

## Long Form

Skipping empty directory {0}

## Short Form

Empty dir

## Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

## Description

None

Message ID : DXF4319I

## Message ID : DXF4321I

### Severity

Information

### Long Form

Skipping exempt directory {0}

### Short Form

Exempt dir

### Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

### Description

None

## Message ID : DXF4322I

## Severity

Information

## Long Form

Unknown status for directory {0}

## Short Form

Dir bad status

### Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

## Description

None

**Message ID : DXF4323I**

## Severity

Information

Message ID : DXF4322I

## Long Form

Directory {0} contains {1} files ({2})

## Short Form

Xform to do

### Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file
nfile	vds_nfile	Numeric	The number of files processed

## Description

None

**Message ID : DXF4329I**

## Severity

Information

Message ID : DXF4323I

## **Long Form**

Finished check for hard links in {0}

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : DXF4332I**

## **Severity**

Information

## **Long Form**

Setting recovery-file-list to {0}

## **Short Form**

No short form is provided for this message type

Message ID : DXF4329I

## Description

None

**Message ID : DXF4344I**

## Severity

Information

## Long Form

Data transform version {0}

## Short Form

Datatform

## Parameters

Label	CEF Label	Type	Usage
version	vds_version	Text	Software version string

## Description

None

Message ID : DXF4332I

## Message ID : DXF4345I

### Severity

Information

### Long Form

Data transform version {0}, using policy {1} on guard point {2}

### Short Form

Auto dataxform

#### Parameters

Label	CEF Label	Type	Usage
version	vds_version	Text	Software version string
pol	cs1	Text	Policy name
gp	fileId	Text	Guardpoint base directory

### Description

None



## Message ID : DXF4352I

### Severity

Information

### Long Form

Data transform for {0} was previously completed

### Short Form

Xform prev complete

#### Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

### Description

None

## Message ID : DXF4361I

## Severity

Information

## Long Form

Data transform for guard point {0} finished

## Short Form

Xform done

### Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

## Description

None

## Message ID : DXF4362I

## Severity

Information

Message ID : DXF4361I

## Long Form

Data transform for guard point {0} finished but {1} files were not processed due to errors

## Short Form

Xform done with errors

### Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory
count	vds_count	Numeric	A generic count value

## Description

None

**Message ID : DXF4363I**

## Severity

Information

Message ID : DXF4362I

1130

## Long Form

Data transform for guard point {0} finished but {1} files were skipped

## Short Form

Xform done with skips

### Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory
count	vds_count	Numeric	A generic count value

## Description

None

**Message ID : DXF4364I**

## Severity

Information

Message ID : DXF4363I

1131

## Long Form

Data transform for guard point {0} finished but {1} files were not processed due to errors and {2} files were skipped

## Short Form

Xform done with errors and skips

### Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory
count	vds_count	Numeric	A generic count value
count	vds_count	Numeric	A generic count value

## Description

None

**Message ID : DXF4365I**

## Severity

Information

Message ID : DXF4364I

1132

## Long Form

The data transform operation took {0} hours, {1} minutes and {2} seconds

## Short Form

Xform duration

### Parameters

Label	CEF Label	Type	Usage
hours	vds_hours	Numeric	Elapsed hours
mins	vds_mins	Numeric	Elaped minutes
secs	vds_secs	Numeric	Elapsed seconds

## Description

None

**Message ID : DXF4366I**

## Severity

Information

Message ID : DXF4365I

## Long Form

The current operation took {0} hours, {1} minutes and {2} seconds

## Short Form

Xform op duration

### Parameters

Label	CEF Label	Type	Usage
hours	vds_hours	Numeric	Elapsed hours
mins	vds_mins	Numeric	Elaped minutes
secs	vds_secs	Numeric	Elapsed seconds

## Description

None

**Message ID : DXF4369I**

## Severity

Information

Message ID : DXF4366I

## **Long Form**

Data transform had some files in progress

## **Short Form**

Prev xform incomplete

### **Parameters**

No parameters are provided for this message type

## **Description**

None

## **Message ID : DXF4370I**

## **Severity**

Information

## **Long Form**

The file {0} was in progress in the previous data transform, it will not be transformed



## Short Form

Prev xform file inprogress

### Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

## Description

None

## Message ID : DXF4371I

## Severity

Information

## Long Form

Data transform skipped some files

## Short Form

No short form is provided for this message type

Message ID : DXF4370I

## Description

None

**Message ID : DXF4372I**

## Severity

Information

## Long Form

The file {0} was skipped in the previous data transform, it will be skipped

## Short Form

Prev xform file skipped

## Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

## Description

None

Message ID : DXF4371I

## **Message ID : DXF4375I**

### **Severity**

Information

### **Long Form**

Data transform last successfully transformed the file {0}

### **Short Form**

No short form is provided for this message type

### **Description**

None

## **Message ID : DXF4378I**

### **Severity**

Information

### **Long Form**

Scan found {0} files ({1}) in {2} directories for guard point {3}

## Short Form

Scan result

### Parameters

Label	CEF Label	Type	Usage
nfile	vds_nfile	Numeric	The number of files processed
ndir	vds_ndir	Numeric	The number of directories processed
gp	fileId	Text	Guardpoint base directory

## Description

None

## Message ID : DXF4380I

### Severity

Information

## Long Form

Transformed {0} files ({1}) of {2} files ({3}) for guard point {4}

Message ID : DXF4378I

## Short Form

Scan stats

### Parameters

Label	CEF Label	Type	Usage
nfile	vds_nfile	Numeric	The number of files processed
space	vds_space	Text	A string representation of file or disk space
nfiles	vds_nfiles	Numeric	The total number of files in an operation
space	vds_space	Text	A string representation of file or disk space
gp	fileId	Text	Guardpoint base directory

## Description

None

**Message ID : DXF4383I**

## Severity

Information

Message ID : DXF4380I

1140

## Long Form

Generating list of files previously transformed on {0}

## Short Form

Recovery gen

### Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

## Description

None

## Message ID : DXF4384I

## Severity

Information

## Long Form

Automatic data transform status for {0}: previous attempt completed

Message ID : DXF4383I

## Short Form

Prev auto xform done

### Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

## Description

None

## Message ID : DXF4385I

## Severity

Information

## Long Form

Automatic data transform status for {0}: previous attempt did not complete

## Short Form

Prev auto xform fail

Message ID : DXF4384I

### Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

### Description

None

### Message ID : DXF4386I

### Severity

Information

### Long Form

Automatic data transform from host {0} for {1}: previous attempt completed

### Short Form

Prev auto xform done

### Parameters

Label	CEF Label	Type	Usage
shost	shost	Text	Source host name

Message ID : DXF4385I



Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

## Description

None

## Message ID : DXF4387I

## Severity

Information

## Long Form

Automatic data transform from host {0} for {1}: previous attempt did not complete

## Short Form

Prev auto xform fail

## Parameters

Label	CEF Label	Type	Usage
shost	shost	Text	Source host name

Message ID : DXF4386I

1144

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

## Description

None

## Message ID : DXF4388I

## Severity

Information

## Long Form

Automatic data transform for {0}: could not get status

## Short Form

Auto xform stat fail

## Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

Message ID : DXF4387I

1145

## Description

None

## Message ID : DXF4389I

## Severity

Information

## Long Form

Starting data transform of {0} for files listed in {1}

## Short Form

Rekey file start

## Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory
filePath	filePath	Text	Full path to file

## **Description**

None

**Message ID : DXF4390I**

## **Severity**

Information

## **Long Form**

Data transform of {0} of {1} files listed in {2} for guard point {3}

## **Short Form**

No short form is provided for this message type

## **Description**

None

**Message ID : DXF4397I**

## **Severity**

Information

Message ID : DXF4389I

## Long Form

Found {0} references to hard link

## Short Form

Hardlink count

### Parameters

Label	CEF Label	Type	Usage
count	vds_count	Numeric	A generic count value

## Description

None

## Message ID : DXF4399I

## Severity

Information

## Long Form

Hardlink reference {0} {1}

Message ID : DXF4397I

## Short Form

Hardlink refs

### Parameters

Label	CEF Label	Type	Usage
count	vds_count	Numeric	A generic count value
filePath	filePath	Text	Full path to file

## Description

None

**Message ID : DXF4414I**

## Severity

Information

## Long Form

Executing script {0}

Message ID : DXF4399I

1149

## Short Form

Exec fail

### Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

## Description

None

**Message ID : DXF4415I**

## Severity

Information

## Long Form

Generating list of files transformed during previous session for guard point {0}

## Short Form

List create

Message ID : DXF4414I

1150

## Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

## Description

None

## Message ID : DXF4416I

## Severity

Information

## Long Form

Writing list of files transformed during previous session for guard point {0}

## Short Form

No short form is provided for this message type

## Description

None

Message ID : DXF4415I



## Message ID : DXF4417I

### Severity

Information

### Long Form

Checking if {0} is a guard point with a rekey policy applied

### Short Form

Checking supported

#### Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

### Description

None

## Message ID : DXF4418I

## **Severity**

Information

## **Long Form**

Preparing data transform

## **Short Form**

Prepare xform

### **Parameters**

No parameters are provided for this message type

## **Description**

None

## **Message ID : DXF4419I**

## **Severity**

Information

## Long Form

Preparing data transform for next phase of execution

## Short Form

xform thread idle

### Parameters

No parameters are provided for this message type

## Description

None

## Message ID : DXF4420I

## Severity

Information

## Long Form

Generating list of files to transform in directory {0}

## Short Form

Generating list

### Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

## Description

None

**Message ID : DXF4421I**

## Severity

Information

## Long Form

Scanning for hard links in directory {0}

## Short Form

Check links

Message ID : DXF4420I

1155

## Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

## Description

None

## Message ID : DXF4422I

## Severity

Information

## Long Form

Processing the list of files specified in {0}

## Short Form

Processing list

## Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Message ID : DXF4421I

Label	CEF Label	Type	Usage

## Description

None

## Message ID : DXF4423I

## Severity

Information

## Long Form

Processed {0} files ({1}) of {2} files ({3}) in {4}

## Short Form

Processed files

## Parameters

Label	CEF Label	Type	Usage
nfile	vds_nfile	Numeric	The number of files processed
nfiles	vds_nfiles	Numeric	The total number of files in an operation

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

## Description

None

## Message ID : DXF4424I

## Severity

Information

## Long Form

Processed {0} files ({1}) of {2} files ({3}) in {4}, in progress {5}, completed {6}

## Short Form

Processing files

## Parameters

Label	CEF Label	Type	Usage
nfile	vds_nfile	Numeric	The number of files processed
nfiles	vds_nfiles	Numeric	The total number of files in an operation

Message ID : DXF4423I

1158

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file
scount	vds_scount	Text	A generic count as a string
scount	vds_scount	Text	A generic count as a string

## Description

None

## Message ID : DXF4425I

## Severity

Information

## Long Form

Processed {0} files of {1} files specified by {2} in guard point {3}

## Short Form

Processed list



## Parameters

Label	CEF Label	Type	Usage
nfile	vds_nfile	Numeric	The number of files processed
nfiles	vds_nfiles	Numeric	The total number of files in an operation
filePath	filePath	Text	Full path to file
gp	fileId	Text	Guardpoint base directory

## Description

None

## Message ID : DXF4429I

## Severity

Information

## Long Form

{0} is a guard point with a rekey policy applied

## Short Form

Xform supported

Message ID : DXF4425I

1160

## Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

## Description

None

## Message ID : DXF4481I

## Severity

Information

## Long Form

The file {0} was skipped

## Short Form

No short form is provided for this message type

## Description

None

Message ID : DXF4429I

## Message ID : DXF4485I

### Severity

Information

### Long Form

Data transform last processing was on the file {0}

### Short Form

Last file xformed

#### Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

### Description

None

## Message ID : DXF4487I

## **Severity**

Information

## **Long Form**

The file {0} could not be transformed, it was skipped in a previous data transform

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : DXF4488I**

## **Severity**

Information

## **Long Form**

Previous status information relates to a --rekey\_file operation.

## Short Form

Prev op was rekey

### Parameters

No parameters are provided for this message type

## Description

None

## Message ID : DXF4489I

## Severity

Information

## Long Form

Previous status information does not relate to a --rekey\_file operation.

## Short Form

Prev op was rekey\_file

### **Parameters**

No parameters are provided for this message type

### **Description**

None

### **Message ID : DXF4490I**

### **Severity**

Information

### **Long Form**

Previous status information will be ignored

### **Short Form**

Prev status ignored

### **Parameters**

No parameters are provided for this message type

## Description

None

**Message ID : DXF4491I**

## Severity

Information

## Long Form

The file {0} was previously skipped. It was not a regular file

## Short Form

Prev skipped non-file

## Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

## Description

None

Message ID : DXF4490I

## **Message ID : DXF4492I**

### **Severity**

Information

### **Long Form**

The file {0} was previously skipped. There was insufficient memory to process it

### **Short Form**

No short form is provided for this message type

### **Description**

None

## **Message ID : DXF4493I**

### **Severity**

Information

### **Long Form**

The file {0} was previously skipped. It could not be classified



## Short Form

No short form is provided for this message type

## Description

None

## Message ID : DXF4495I

## Severity

Information

## Long Form

The file {0} was previously skipped. It was no longer present when a transform was attempted

## Short Form

Prev error - file gone

### Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

## Description

None

**Message ID : DXF4496I**

## Severity

Information

## Long Form

The file {0} was previously skipped. A transform would have used the same key

## Short Form

Prev skipped - same key

## Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

## Description

None

Message ID : DXF4495I

## Message ID : DXF4497I

### Severity

Information

### Long Form

The file {0} was previously skipped. Rekey was not supported for this file

### Short Form

Prev skipped unsupported file

### Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

### Description

None

# Logger DXF: Warnings

**Message ID : DXF3210W**

## Severity

Warning

## Long Form

If Shadow Copy was used on your system, you must back up your data before attempting to run dataxform. Once DataXform has been completed, you may restart Shadow Copy. Note, however, that all Shadow Copy backups made prior to running dataxform will be unusable and should be discarded. Attempting to restore your cleartext Shadow Copy backups made prior to running dataxform into your encrypted data will result in data corruption.

## Short Form

Shadow copy

### Parameters

No parameters are provided for this message type

## Description

None

## **Message ID : DXF4103W**

### **Severity**

Warning

### **Long Form**

Transformation time estimation will be simulated as guard point does not support rekeying

### **Short Form**

No rekey support

### **Parameters**

No parameters are provided for this message type

### **Description**

None

## **Message ID : DXF4104W**

### **Severity**

Warning

## Long Form

Missing {0} references to hard link {1}

## Short Form

Missing hardlink refs

### Parameters

Label	CEF Label	Type	Usage
count	vds_count	Numeric	A generic count value
filePath	filePath	Text	Full path to file

## Description

None

**Message ID : DXF4118W**

## Severity

Warning

Message ID : DXF4104W

## Long Form

Could not return file time for {0} to its original value, got error {1}

## Short Form

Time restore error

### Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file
showStr	reason	Text	Code specifying reason for allowing access, if any

## Description

None

**Message ID : DXF4242W**

## Severity

Warning

Message ID : DXF4118W

1174

## Long Form

More than {0} files were encountered in the directory {1}. Dataxform may consume excessive system resources while operating upon this directory. Proceeding

## Short Form

No short form is provided for this message type

## Description

None

## Message ID : DXF4254W

## Severity

Warning

## Long Form

Note: data from a previous dataxform run is being used

## Short Form

Prev run data in use



### **Parameters**

No parameters are provided for this message type

### **Description**

None

### **Message ID : DXF4307W**

### **Severity**

Warning

### **Long Form**

Skipping previously transformed directory {0}

### **Short Form**

No short form is provided for this message type

### **Description**

None

## **Message ID : DXF4324W**

### **Severity**

Warning

### **Long Form**

Cannot perform data transform for {0} with identical key

### **Short Form**

No short form is provided for this message type

### **Description**

None

## **Message ID : DXF4327W**

### **Severity**

Warning

### **Long Form**

Kernel component returned stop-data-transform status

Message ID : DXF4324W

## Short Form

Stopped by kernel

### Parameters

No parameters are provided for this message type

## Description

None

## Message ID : DXF4333W

## Severity

Warning

## Long Form

Unknown version for recovery file list

## Short Form

Bad version

## Parameters

No parameters are provided for this message type

## Description

None

## Message ID : DXF4337W

## Severity

Warning

## Long Form

Resetting read buffer size to {0}KB

## Short Form

Setting buf size

## Parameters

Label	CEF Label	Type	Usage
slen	in	Numeric	Input byte count or length

Message ID : DXF4333W

## Description

None

**Message ID : DXF4338W**

## Severity

Warning

## Long Form

Resetting the maximum number of kernel threads to {0}

## Short Form

Number kthreads

### Parameters

Label	CEF Label	Type	Usage
count	vds_count	Numeric	A generic count value

## Description

None

Message ID : DXF4337W

## Message ID : DXF4339W

### Severity

Warning

### Long Form

Resetting the maximum number of utility threads to {0}

### Short Form

Max uthreads

#### Parameters

Label	CEF Label	Type	Usage
count	vds_count	Numeric	A generic count value

### Description

None

## Message ID : DXF4351W

## **Severity**

Warning

## **Long Form**

Could not load previous data transform information

## **Short Form**

Recovery file load fail

## **Parameters**

No parameters are provided for this message type

## **Description**

None

**Message ID : DXF4359W**

## **Severity**

Warning

## Long Form

Could not notify kernel component that data transform completed on {0}

## Short Form

Kernel notify complete fail

### Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

## Description

None

## Message ID : DXF4373W

## Severity

Warning

## Long Form

Data transform was previously run on guard point {0}

Message ID : DXF4359W



## Short Form

Xform prev completed

### Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

## Description

None

## Message ID : DXF4398W

## Severity

Warning

## Long Form

Found {0} references to hard link but expected {1}

## Short Form

Hardlink count error

Message ID : DXF4373W

## Parameters

Label	CEF Label	Type	Usage
count	vds_count	Numeric	A generic count value
count	vds_count	Numeric	A generic count value

## Description

None

## Message ID : DXF4406W

## Severity

Warning

## Long Form

Could not return file time for {0} to its original value, got error code {1}

## Short Form

No short form is provided for this message type

## Description

None

**Message ID : DXF4410W**

## Severity

Warning

## Long Form

Could not read the Windows registry, section {0}

## Short Form

Read read fail

## Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

## Description

None

Message ID : DXF4406W

## **Message ID : DXF4413W**

### **Severity**

Warning

### **Long Form**

Attempted to restrict access to unknown object ID {0}

### **Short Form**

No short form is provided for this message type

### **Description**

None

## **Message ID : DXF4428W**

### **Severity**

Warning

### **Long Form**

Unable to contact Key Manager; will perform all logging to the local log file

## **Short Form**

No short form is provided for this message type

## **Description**

None

# Logger FIP: Fatal errors

**Message ID : FIP0625F**

## Severity

Fatal error

## Long Form

FIPS self-test complete. Result: FAIL. Failure in "{0}" test. The Security Server cannot continue and will be shutdown.

## Short Form

FIPS self-test failed

### Parameters

Label	CEF Label	Type	Usage
showStr	reason	Text	Code specifying reason for allowing access, if any

## Description

None

## **Message ID : FIP0626F**

### **Severity**

Fatal error

### **Long Form**

An unexpected error occurred during FIPS self-test. The Security Server cannot continue and will be shutdown.

### **Short Form**

FIPS self-test failed

### **Parameters**

No parameters are provided for this message type

### **Description**

None

# Logger FIP: Information

**Message ID : FIP0624I**

## **Severity**

Information

## **Long Form**

FIPS self-test complete. Result: PASS.

## **Short Form**

FIPS self-test complete ok

## **Parameters**

No parameters are provided for this message type

## **Description**

None



## **Logger GEN: Errors**

**Message ID : GEN1253E**

### **Severity**

Error

### **Long Form**

Invalid date format: {0}

### **Short Form**

No short form is provided for this message type

### **Description**

None

**Message ID : GEN1280E**

### **Severity**

Error

## Long Form

Failed to establish trusted connection to {0}. Reason: {1}

## Short Form

failed to establish trusted connection

### Parameters

Label	CEF Label	Type	Usage
shost	shost	Text	Source host name
showStr	reason	Text	Code specifying reason for allowing access, if any

## Description

None

# Logger GEN: Information

**Message ID : GEN1276I**

## Severity

Information

## Long Form

Data Security Manager was started successfully at {0}.

## Short Form

server started

### Parameters

Label	CEF Label	Type	Usage
stime	start	Text	A start time stamp

## Description

None

## Message ID : GEN1279I

### Severity

Information

### Long Form

Trusted channel established to {0}.

### Short Form

trusted channel established

### Parameters

Label	CEF Label	Type	Usage
shost	shost	Text	Source host name

### Description

None

## **Logger IEP: Errors**

**Message ID : IEP0321E**

### **Severity**

Error

### **Long Form**

The Security Server failed to retrieve the public key from the keystore.

### **Short Form**

No short form is provided for this message type

### **Description**

None

**Message ID : IEP0322E**

### **Severity**

Error

## **Long Form**

The Security Server failed to retrieve the private key from the keystore.

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : IEP0323E**

## **Severity**

Error

## **Long Form**

The Security Server failed to decrypt the symmetric key that was used to protect the imported key data.

## **Short Form**

No short form is provided for this message type

## **Description**

None

**Message ID : IEP0324E**

## **Severity**

Error

## **Long Form**

The Security Server failed to write the imported key data into a temporary file. Check the server file system disk space.

## **Short Form**

No short form is provided for this message type

## **Description**

None

**Message ID : IEP0325E**

## **Severity**

Error

Message ID : IEP0323E

## **Long Form**

The Security Server failed to decrypt the imported keys.

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : IEP0326E**

## **Severity**

Error

## **Long Form**

The Security server failed to open the file "{0}" for writing data.

## **Short Form**

No short form is provided for this message type



**Description**

None

**Message ID : IEP0327E****Severity**

Error

**Long Form**

The Security server failed to read the decrypted key data file.

**Short Form**

No short form is provided for this message type

**Description**

None

**Message ID : IEP0328E****Severity**

Error

Message ID : IEP0326E

## **Long Form**

The Security server will not import the keys into the server because the imported data has been tampered.

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : IEP0329E**

## **Severity**

Error

## **Long Form**

The Security Server failed to connect to database cgssdb.

## **Short Form**

No short form is provided for this message type

## **Description**

None

**Message ID : IEP0330E**

## **Severity**

Error

## **Long Form**

The Security Server failed to obtain server configuration from database.

## **Short Form**

No short form is provided for this message type

## **Description**

None

**Message ID : IEP0331E**

## **Severity**

Error

Message ID : IEP0329E

## **Long Form**

The Security Server failed to export the public key.

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : IEP0332E**

## **Severity**

Error

## **Long Form**

The Security Server failed to read key data.

## **Short Form**

No short form is provided for this message type

## **Description**

None

# Logger IEP: Information

**Message ID : IEP0577I**

## Severity

Information

## Long Form

Configuration summary exported by {0}.

## Short Form

configuration summary exported

### Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name

## Description

None

# Logger IEP: Warnings

**Message ID : IEP0338W**

## Severity

Warning

## Long Form

There was key name conflict while importing keys. The key has been renamed: {0}.

## Short Form

key renamed

### Parameters

Label	CEF Label	Type	Usage
key	cs3	Text	Name of key or key pair

## Description

None

## Message ID : IEP0342W

### Severity

Warning

### Long Form

The unique to host key or clear key importing is not supported. The key {0} has been ignored.

### Short Form

key ignored

#### Parameters

Label	CEF Label	Type	Usage
key	cs3	Text	Name of key or key pair

### Description

None

## Message ID : IEP0343W



## **Severity**

Warning

## **Long Form**

Duplicate key names encountered. Renamed imported keys. Please check the Management Console Log for details.

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : IEP0344W**

## **Severity**

Warning

## **Long Form**

vormetric\_clear key has been encountered but is not imported. Please check the Management Console Log for details.

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : IEP0345W**

## **Severity**

Warning

## **Long Form**

There were key name conflicts and clear key encountered. Please check the Management Console Log for details.

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Logger KMG: Errors**

**Message ID : KMG0065E**

### **Severity**

Error

### **Long Form**

Clear Key "{0}" cannot be deleted from the Security Server.

### **Short Form**

No short form is provided for this message type

### **Description**

None

**Message ID : KMG0068E**

### **Severity**

Error

## **Long Form**

Key Group Name "{0}" is already in use on this server. Specify a different name.

## **Short Form**

No short form is provided for this message type

## **Description**

None

**Message ID : KMG0094E**

## **Severity**

Error

## **Long Form**

The Security Server failed to save the key. Ensure that the Security Server database is functional. Contact support if the problem persists.

## **Short Form**

No short form is provided for this message type

Message ID : KMG0068E

1211

## **Description**

None

**Message ID : KMG0095E**

## **Severity**

Error

## **Long Form**

The Security Server failed to retrieve keys from the database. Previously saved keys are not lost. Ensure the Security Server database is functional. Contact support if the problem persists.

## **Short Form**

No short form is provided for this message type

## **Description**

None

**Message ID : KMG0096E**

## **Severity**

Error

## **Long Form**

The Security Server failed to delete one or more keys. Retry the operation. Ensure the Security Server database is functional. Contact support if the problem persists.

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : KMG0097E**

## **Severity**

Error

## **Long Form**

The specified key(s) was not found in the database. The key(s) may have been deleted by another user.

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : KMG0098E**

## **Severity**

Error

## **Long Form**

The Security Server could not find key "{0}" in the database. The key may have been deleted.

## **Short Form**

No short form is provided for this message type

## **Description**

None

Message ID : KMG0097E

## **Message ID : KMG0099E**

### **Severity**

Error

### **Long Form**

The Security Server failed to create a key for the key name "{0}". Retry the operation. Contact support if the problem persists.

### **Short Form**

No short form is provided for this message type

### **Description**

None

## **Message ID : KMG0100E**

### **Severity**

Error

### **Long Form**

The Security Server failed to retrieve the Backup encryption key from the header. This could be caused by a corrupt backup image. Contact support.



## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : KMG0101E**

## **Severity**

Error

## **Long Form**

The specified key group(s) was not found in the database. The key group(s) may have been deleted by another user. Refresh the page and retry the operation.

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : KMG0102E**

### **Severity**

Error

### **Long Form**

The Security Server could not delete Key Group "{0}". Please remove member keys and/or associated client identities and retry the operation.

### **Short Form**

No short form is provided for this message type

### **Description**

None

## **Message ID : KMG0103E**

### **Severity**

Error

## **Long Form**

The Security Server could not delete Key "{0}". The Key is currently in use by some security policies.

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : KMG0104E**

## **Severity**

Error

## **Long Form**

The Security Server could not create an empty Key Group. The Key Group must have at least one local key or an Affiliate key.

## **Short Form**

No short form is provided for this message type

## **Description**

None

**Message ID : KMG0105E**

## **Severity**

Error

## **Long Form**

The Security Server failed to delete affiliate key. Retry the operation. Ensure the Security Server database is functional. Contact support if the problem persists.

## **Short Form**

No short form is provided for this message type

## **Description**

None

**Message ID : KMG0106E**

## Severity

Error

## Long Form

The Security Server failed to retrieve key groups from the database. Previously saved key groups are not lost. Ensure the Security Server database is functional. Contact support if the problem persists.

## Short Form

No short form is provided for this message type

## Description

None

## Message ID : KMG0107E

## Severity

Error

## Long Form

The Security Server failed to create the key group "{0}". Retry the operation. Ensure the Security Server database is functional. Contact support if the problem persists.

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : KMG0108E**

## **Severity**

Error

## **Long Form**

The Security Server failed to update key group "{0}". Retry the operation. Ensure the Security Server database is functional. Contact support if the problem persists.

## **Short Form**

No short form is provided for this message type

## **Description**

None

Message ID : KMG0107E

1221

## **Message ID : KMG0109E**

### **Severity**

Error

### **Long Form**

The Security Server failed to delete key group(s). Retry the operation. Ensure the key group or key(s) in the group is not used in an existing policy. Ensure the Security Server database is functional. Contact support if the problem persists.

### **Short Form**

No short form is provided for this message type

### **Description**

None

## **Message ID : KMG0110E**

### **Severity**

Error

## Long Form

The Security Server failed to import the public key input. The public key input was invalid. Choose from a different file and retry the operation.

## Short Form

No short form is provided for this message type

## Description

None

**Message ID : KMG0111E**

## Severity

Error

## Long Form

Header information provided by agent indicates a version that can not be handled by this server. Please update the server to a later version.

## Short Form

unsupported version in header info

Message ID : KMG0110E

1223



### **Parameters**

No parameters are provided for this message type

### **Description**

None

**Message ID : KMG0112E**

### **Severity**

Error

### **Long Form**

The Security Server failed to retrieve the header version. Restore operation will be aborted. Contact support.

### **Short Form**

failed to retrieve header version

### **Parameters**

No parameters are provided for this message type

Message ID : KMG0111E

1224

**Description**

None

**Message ID : KMG0113E****Severity**

Error

**Long Form**

The encryption mode for key name "{0}" cannot be updated.

**Short Form**

No short form is provided for this message type

**Description**

None

**Message ID : KMG0114E****Severity**

Error

Message ID : KMG0112E

## **Long Form**

The user does not have permission to delete this key.

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : KMG0220E**

## **Severity**

Error

## **Long Form**

Key Name "{0}" is already in use on this server. Specify a different key name.

## **Short Form**

No short form is provided for this message type

## **Description**

None

**Message ID : KMG0221E**

## **Severity**

Error

## **Long Form**

{0} is not a correct length for an asymmetric key.

## **Short Form**

No short form is provided for this message type

## **Description**

None

**Message ID : KMG0222E**

## **Severity**

Error

Message ID : KMG0220E

## Long Form

Key UUID "{0}" is already in use on this server. Specify a different key UUID.

## Short Form

No short form is provided for this message type

## Description

None

## Message ID : KMG0256E

## Severity

Error

## Long Form

Unsupported symmetric key type for key "{0}"

## Short Form

No short form is provided for this message type

## **Description**

None

**Message ID : KMG0257E**

## **Severity**

Error

## **Long Form**

Unsupported symmetric key type for key "{0}". CBC or CBC\_CS1 encryption modes are used for AES keys only.

## **Short Form**

No short form is provided for this message type

## **Description**

None

**Message ID : KMG0258E**

## **Severity**

Error

Message ID : KMG0256E

## **Long Form**

The key "{0}" that you are trying to add to the vault uses CBC CS1 encryption mode which is not supported.

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : KMG0262E**

## **Severity**

Error

## **Long Form**

The Security Server failed to access the server key store. Refer to cgss.log and server.log for details. Call support if necessary.

## **Short Form**

No short form is provided for this message type

## Description

None

**Message ID : KMG0265E**

## Severity

Error

## Long Form

The Security Server failed to generate symmetric key "{0}".

## Short Form

No short form is provided for this message type

## Description

None

**Message ID : KMG0273E**

## Severity

Error

Message ID : KMG0262E



## **Long Form**

The Security Server failed to perform encryption using a symmetric key.

## **Short Form**

No short form is provided for this message type

## **Description**

None

**Message ID : KMG0274E**

## **Severity**

Error

## **Long Form**

Invalid key type to export. The Security Server only supports export of the public keys.

## **Short Form**

No short form is provided for this message type

Message ID : KMG0273E

## **Description**

None

**Message ID : KMG0285E**

## **Severity**

Error

## **Long Form**

The Security Server failed to create the backup header for offline protection. Refer to cgss.log and server.log for details. Call support if necessary.

## **Short Form**

No short form is provided for this message type

## **Description**

None

**Message ID : KMG0301E**

## **Severity**

Error

## **Long Form**

The Security Server could not delete Key "{0}". The Key is currently in key group(s).

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : KMG0307E**

## **Severity**

Error

## **Long Form**

The Security Server could not get the fingerprint of the CA certificate.

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : KMG0524E**

## **Severity**

Error

## **Long Form**

Invalid Query. Cannot specify multiple KeyIdentifiers for query

## **Short Form**

No short form is provided for this message type

## **Description**

None

Message ID : KMG0307E

1235

## **Message ID : KMG0615E**

### **Severity**

Error

### **Long Form**

File to import has unexpected format.

### **Short Form**

No short form is provided for this message type

### **Description**

None

## **Message ID : KMG0616E**

### **Severity**

Error

### **Long Form**

Format of the file to import is newer than the format this Security Server supports.

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : KMG0686E**

## **Severity**

Error

## **Long Form**

Key Attribute ID "{0}" is already in use on this server. Specify a different key attribute id.

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : KMG0687E**

### **Severity**

Error

### **Long Form**

The specified key attribute(s) was not found in the database. The key attribute(s) may have been deleted by another user.

### **Short Form**

No short form is provided for this message type

### **Description**

None

## **Message ID : KMG0688E**

### **Severity**

Error

### **Long Form**

Key template name "{0}" in the domain is already in use on this server. Please specify a different key template name in the domain.

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : KMG0689E**

## **Severity**

Error

## **Long Form**

The specified key template was not found in the database. The key template(s) may have been deleted by another user.

## **Short Form**

No short form is provided for this message type

## **Description**

None



## **Message ID : KMG0690E**

### **Severity**

Error

### **Long Form**

Key Template Attribute ID "{0}" is already in use on this server. Specify a different key template attribute id.

### **Short Form**

No short form is provided for this message type

### **Description**

None

## **Message ID : KMG0691E**

### **Severity**

Error

### **Long Form**

The specified key template attribute was not found in the database. The key template attribute(s) may have been deleted by another user.

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : KMG0692E**

## **Severity**

Error

## **Long Form**

The specified key ID was not found in the database. The key attribute may have been deleted by another user.

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : KMG0693E**

### **Severity**

Error

### **Long Form**

Key string confirmation failed.

### **Short Form**

No short form is provided for this message type

### **Description**

None

## **Message ID : KMG0694E**

### **Severity**

Error

### **Long Form**

The specified key attribute(s) was found in the database.

## **Short Form**

No short form is provided for this message type

## **Description**

None

**Message ID : KMG0695E**

## **Severity**

Error

## **Long Form**

The Security Server failed to import the private key input. The private key input was invalid. Choose from a different file and retry the operation.

## **Short Form**

No short form is provided for this message type

## **Description**

None

Message ID : KMG0694E

1243

## **Message ID : KMG0696E**

### **Severity**

Error

### **Long Form**

The duplicated attribute name is not allowed.

### **Short Form**

No short form is provided for this message type

### **Description**

None

## **Message ID : KMG0698E**

### **Severity**

Error

### **Long Form**

The Security Server failed to import the public key and private key input. Either the public key or the private key input was invalid. Choose from a different file and retry the operation.

Message ID : KMG0696E

1244

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : KMG0699E**

## **Severity**

Error

## **Long Form**

The Security Server failed to create the key template.

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : KMG0700E**

### **Severity**

Error

### **Long Form**

Key template name needs to be specified.

### **Short Form**

No short form is provided for this message type

### **Description**

None

## **Message ID : KMG0708E**

### **Severity**

Error

### **Long Form**

The Security Server failed to validate public key. Please see cgss.log or server.log for details.

## **Short Form**

No short form is provided for this message type

## **Description**

None

**Message ID : KMG0709E**

## **Severity**

Error

## **Long Form**

The Security Server failed to validate private key. Either private key format is invalid or public key and private key are not a key pair.

## **Short Form**

No short form is provided for this message type

## **Description**

None

Message ID : KMG0708E

1247



## **Message ID : KMG0726E**

### **Severity**

Error

### **Long Form**

The Security Server failed to validate the vault key pair.

### **Short Form**

No short form is provided for this message type

### **Description**

None

## **Message ID : KMG0727E**

### **Severity**

Error

### **Long Form**

The Security Server failed to validate the vault key pair. The specified key type (length) does not match actual key type (length).

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : KMG0728E**

## **Severity**

Error

## **Long Form**

Unique identifier is not specified.

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : KMG0729E**

### **Severity**

Error

### **Long Form**

Invalid unique identifier.

### **Short Form**

No short form is provided for this message type

### **Description**

None

## **Message ID : KMG0730E**

### **Severity**

Error

### **Long Form**

The name and value cannot be null.

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : KMG0731E**

## **Severity**

Error

## **Long Form**

Client is not allowed to perform the specified operation.

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : KMG0732E**

### **Severity**

Error

### **Long Form**

Cannot destroy the managed key object in database.rm -rf /opt

### **Short Form**

No short form is provided for this message type

### **Description**

None

## **Message ID : KMG0733E**

### **Severity**

Error

### **Long Form**

The operation {0} is not available on a failover server.

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : KMG0734E**

## **Severity**

Error

## **Long Form**

Server does not support operation. Operation Not Supported on key length {0}.

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : KMG0735E**

### **Severity**

Error

### **Long Form**

Server does not support operation. Operation Not Supported on the cryptographic algorithm {0}.

### **Short Form**

No short form is provided for this message type

### **Description**

None

## **Message ID : KMG0736E**

### **Severity**

Error

### **Long Form**

Object Type is not recognized. Invalid Field on {0}.

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : KMG0737E**

## **Severity**

Error

## **Long Form**

Cannot store the key data into the database.

## **Short Form**

No short form is provided for this message type

## **Description**

None



## **Message ID : KMG0738E**

### **Severity**

Error

### **Long Form**

Error Creating Cryptographic Object.

### **Short Form**

No short form is provided for this message type

### **Description**

None

## **Message ID : KMG0739E**

### **Severity**

Error

### **Long Form**

Non-existing attributes, attributes that the server does not understand or templates that do not exist are given in the request.

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : KMG0740E**

## **Severity**

Error

## **Long Form**

The Key Management Web Service does not allow duplicate key attributes.

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : KMG0741E**

### **Severity**

Error

### **Long Form**

Cannot locate the key data in the database.

### **Short Form**

No short form is provided for this message type

### **Description**

None

## **Message ID : KMG0742E**

### **Severity**

Error

### **Long Form**

Item Deleted.

## **Short Form**

No short form is provided for this message type

## **Description**

None

**Message ID : KMG0743E**

## **Severity**

Error

## **Long Form**

Item Out Of Range.

## **Short Form**

No short form is provided for this message type

## **Description**

None

Message ID : KMG0742E

## **Message ID : KMG0744E**

### **Severity**

Error

### **Long Form**

Object does not exist.

### **Short Form**

No short form is provided for this message type

### **Description**

None

## **Message ID : KMG0745E**

### **Severity**

Error

### **Long Form**

Cannot find the key data in database.

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : KMG0746E**

## **Severity**

Error

## **Long Form**

No object with the specified Unique Identifier exists.

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : KMG0747E**

### **Severity**

Error

### **Long Form**

Cannot add the key attribute in database.

### **Short Form**

No short form is provided for this message type

### **Description**

None

## **Message ID : KMG0748E**

### **Severity**

Error

### **Long Form**

Cannot modify the key attribute in database.

Message ID : KMG0747E

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : KMG0749E**

## **Severity**

Error

## **Long Form**

Attempt to delete a read-only/REQUIRED attribute.

## **Short Form**

No short form is provided for this message type

## **Description**

None



## **Message ID : KMG0750E**

### **Severity**

Error

### **Long Form**

No attribute with the specified name exists.

### **Short Form**

No short form is provided for this message type

### **Description**

None

## **Message ID : KMG0751E**

### **Severity**

Error

### **Long Form**

Cannot delete the key attribute in database.

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : KMG0752E**

## **Severity**

Error

## **Long Form**

Cannot encrypt the data from the key agent.

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : KMG0753E**

### **Severity**

Error

### **Long Form**

Cannot decrypt the data from the key agent.

### **Short Form**

No short form is provided for this message type

### **Description**

None

## **Message ID : KMG0754E**

### **Severity**

Error

### **Long Form**

Cannot sign the data from the key agent.

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : KMG0755E**

## **Severity**

Error

## **Long Form**

Cannot encrypt the data with rsa key from the key agent.

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : KMG0756E**

### **Severity**

Error

### **Long Form**

Cannot decrypt the data with rsa key from the key agent.

### **Short Form**

No short form is provided for this message type

### **Description**

None

## **Message ID : KMG0757E**

### **Severity**

Error

### **Long Form**

The Expiry Date cannot be the same or earlier than the creation date. Please correct the problem and try again.

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : KMG0758E**

## **Severity**

Error

## **Long Form**

REQUIRED field(s) "{0}" is missing.

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : KMG0760E**

### **Severity**

Error

### **Long Form**

The {0} timestamp is invalid.

### **Short Form**

No short form is provided for this message type

### **Description**

None

## **Message ID : KMG0762E**

### **Severity**

Error

### **Long Form**

The attribute name entry is duplicated with the existing attribute name {0}.

## Short Form

No short form is provided for this message type

## Description

None

## Message ID : KMG0765E

## Severity

Error

## Long Form

The key string with key name {0} must contain 48 hex characters for 3DES; or 32 hex characters for AES128 or ARIA128; or 64 hex characters for AES256 or ARIA256.

## Short Form

No short form is provided for this message type

## Description

None

Message ID : KMG0762E

1271



## **Message ID : KMG0766E**

### **Severity**

Error

### **Long Form**

The key value with key name {0} is not in hex format. Please correct the problem and try again.

### **Short Form**

No short form is provided for this message type

### **Description**

None

## **Message ID : KMG0767E**

### **Severity**

Error

### **Long Form**

The symmetric key entry is too big. The maximum key size is 399 bytes.

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : KMG0768E**

## **Severity**

Error

## **Long Form**

The public key entry is too big. The maximum public key size is 5000 bytes.

## **Short Form**

No short form is provided for this message type

## **Description**

None

Message ID : KMG0767E

## **Message ID : KMG0769E**

### **Severity**

Error

### **Long Form**

The private key entry is too big. The maximum private key size is 7487 bytes.

### **Short Form**

No short form is provided for this message type

### **Description**

None

## **Message ID : KMG0770E**

### **Severity**

Error

### **Long Form**

The key string with key name {0} must contain 48 hex characters for 3DES; or 32 hex characters for AES128 or ARIA128; or 64 hex characters for AES256 or ARIA256. If CBC\_CS1 or XTS encryption mode is used for AES keys, the expected key length is

doubled.

### **Short Form**

No short form is provided for this message type

### **Description**

None

**Message ID : KMG0773E**

### **Severity**

Error

### **Long Form**

Wrapper Key is corrupt. Import or generate a new one.

### **Short Form**

No short form is provided for this message type

### **Description**

None

Message ID : KMG0770E

## **Message ID : KMG0775E**

### **Severity**

Error

### **Long Form**

The Security Server could not delete the vault key "{0}". The vault key is currently in use by a policy.

### **Short Form**

No short form is provided for this message type

### **Description**

None

## **Message ID : KMG1252E**

### **Severity**

Error

### **Long Form**

The creation date for the key cannot be future date and time.

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : KMG1255E**

## **Severity**

Error

## **Long Form**

Cannot import the symmetric agent key "{0}" with unique to host set to true.

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : KMG1258E**

### **Severity**

Error

### **Long Form**

Both public key and private key are null. Please correct the problem and try again.

### **Short Form**

No short form is provided for this message type

### **Description**

None

## **Message ID : KMG1267E**

### **Severity**

Error

### **Long Form**

Unsupported certificate encoding.

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : KMG1268E**

## **Severity**

Error

## **Long Form**

No such algorithm.

## **Short Form**

No short form is provided for this message type

## **Description**

None



## **Message ID : KMG1269E**

### **Severity**

Error

### **Long Form**

No such provider.

### **Short Form**

No short form is provided for this message type

### **Description**

None

## **Message ID : KMG1270E**

### **Severity**

Error

### **Long Form**

The key is invalid.

## **Short Form**

No short form is provided for this message type

## **Description**

None

**Message ID : KMG1271E**

## **Severity**

Error

## **Long Form**

No subject alternative names present.

## **Short Form**

No short form is provided for this message type

## **Description**

None

Message ID : KMG1270E

## **Message ID : KMG1272E**

### **Severity**

Error

### **Long Form**

The signatures are not matching.

### **Short Form**

No short form is provided for this message type

### **Description**

None

## **Message ID : KMG1273E**

### **Severity**

Error

### **Long Form**

General security error.

## **Short Form**

No short form is provided for this message type

## **Description**

None

**Message ID : KMG1274E**

## **Severity**

Error

## **Long Form**

Unable to parse the certificate.

## **Short Form**

No short form is provided for this message type

## **Description**

None

Message ID : KMG1273E

## **Message ID : KMG1282E**

### **Severity**

Error

### **Long Form**

Operation Not Supported on the managed object: the symmetric key is not specified.

### **Short Form**

No short form is provided for this message type

### **Description**

None

## **Message ID : KMG1283E**

### **Severity**

Error

### **Long Form**

Operation Not Supported on the managed object: the public exponent and modulus for the public key are not specified.

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : KMG1284E**

## **Severity**

Error

## **Long Form**

Operation Not Supported on the managed object: the private exponent and modulus for the private key are not specified.

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : KMG1338E**

### **Severity**

Error

### **Long Form**

No such algorithm for message digest (SHA-384).

### **Short Form**

No short form is provided for this message type

### **Description**

None

## **Message ID : KMG1339E**

### **Severity**

Error

### **Long Form**

The expiration date cannot be before today.

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : KMG1340E**

## **Severity**

Error

## **Long Form**

Encryption failed, public key is null.

## **Short Form**

No short form is provided for this message type

## **Description**

None

Message ID : KMG1339E



## **Message ID : KMG1341E**

### **Severity**

Error

### **Long Form**

Encryption failed, empty payload.

### **Short Form**

No short form is provided for this message type

### **Description**

None

## **Message ID : KMG1380E**

### **Severity**

Error

### **Long Form**

The symmetric key {0} does not exist. Please use another symmetric key name for the key rotation.

## Short Form

No short form is provided for this message type

## Description

None

## Message ID : KMG1382E

## Severity

Error

## Long Form

Key [Name: {0}, Description: {1}] versioning failed. Reason: {2}

## Short Form

No short form is provided for this message type

## Description

None

## **Message ID : KMG1383E**

### **Severity**

Error

### **Long Form**

Key "{0}" is not enabled for versioning in domain {1}.

### **Short Form**

No short form is provided for this message type

### **Description**

None

## **Message ID : KMG1384E**

### **Severity**

Error

### **Long Form**

The symmetric key (name:{0}, version :{1}) version does not exist

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : KMG1385E**

## **Severity**

Error

## **Long Form**

Key version life span is between 2 and 99999 inclusively.

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : KMG1387E**

### **Severity**

Error

### **Long Form**

Administrator "{0}" failed to version key [Name: {1}, Description: {2}].

### **Short Form**

No short form is provided for this message type

### **Description**

None

## **Message ID : KMG1388E**

### **Severity**

Error

### **Long Form**

Key Refresh Period value for "{0}" can be between {1} and {2} inclusively.

## **Short Form**

No short form is provided for this message type

## **Description**

None

**Message ID : KMG1394E**

## **Severity**

Error

## **Long Form**

Template enforcement is in effect, cannot modify expiration time

## **Short Form**

No short form is provided for this message type

## **Description**

None

Message ID : KMG1388E

## **Message ID : KMG1409E**

### **Severity**

Error

### **Long Form**

Key(s) import failed. A problem could be that you do not have the right wrapper key installed.

### **Short Form**

No short form is provided for this message type

### **Description**

None

## **Message ID : KMG1410E**

### **Severity**

Error

### **Long Form**

Server does not support the operation "{0}" at this time.

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : KMG1411E**

## **Severity**

Error

## **Long Form**

The key type "{0}" is not supported.

## **Short Form**

No short form is provided for this message type

## **Description**

None



## **Message ID : KMG1412E**

### **Severity**

Error

### **Long Form**

No such key wrapping specification.

### **Short Form**

No short form is provided for this message type

### **Description**

None

## **Message ID : KMG1413E**

### **Severity**

Error

### **Long Form**

The block cipher mode "{0}" is not supported.

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : KMG1414E**

## **Severity**

Error

## **Long Form**

The key identifier "{0}" is not recognized.

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : KMG1416E**

### **Severity**

Error

### **Long Form**

Key Agent at {1} is not authorized to access key "{0}".

### **Short Form**

No short form is provided for this message type

### **Description**

None

## **Message ID : KMG1417E**

### **Severity**

Error

### **Long Form**

Cannot encrypt the password.

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : KMG1418E**

## **Severity**

Error

## **Long Form**

The format of the password does not conform to the password policy.

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : KMG1430E**

### **Severity**

Error

### **Long Form**

Key {0} is not enabled for versioning. Only versioned keys can be rotated

### **Short Form**

No short form is provided for this message type

### **Description**

None

## **Message ID : KMG1512E**

### **Severity**

Error

### **Long Form**

Certificate "{0}" has expired.

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : KMG1518E**

## **Severity**

Error

## **Long Form**

Client must provide a non zero random byte size.

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : KMG1521E**

### **Severity**

Error

### **Long Form**

Attribute "{0}" requires epoch time as long integer attribute value.

### **Short Form**

No short form is provided for this message type

### **Description**

None

## **Message ID : KMG1522E**

### **Severity**

Error

### **Long Form**

Value of "{0}" cannot be null or empty

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : KMG1523E**

## **Severity**

Error

## **Long Form**

Unable to update key-state. Invalid key-state transition from "{0}" to "{1}" was attempted.

## **Short Form**

No short form is provided for this message type

## **Description**

None



## **Message ID : KMG1525E**

### **Severity**

Error

### **Long Form**

Cannot add the key attribute. Key already enabled for versioning

### **Short Form**

No short form is provided for this message type

### **Description**

None

## **Message ID : KMG1526E**

### **Severity**

Error

### **Long Form**

Cannot add/modify the key attribute "{0}" due to potential invalid key-state transition from "{1}" to "{2}".

## **Short Form**

No short form is provided for this message type

## **Description**

None

**Message ID : KMG1527E**

## **Severity**

Error

## **Long Form**

Failed to generate unique external key identifier after retries. Please try again later or contact Support for assistance.

## **Short Form**

No short form is provided for this message type

## **Description**

None

Message ID : KMG1526E

## **Message ID : KMG1528E**

### **Severity**

Error

### **Long Form**

Unable to generate random integer for external key identifier.

### **Short Form**

No short form is provided for this message type

### **Description**

None

## **Message ID : KMG1529E**

### **Severity**

Error

### **Long Form**

Cannot add/modify attribute "{0}" due to potential invalid key-state-action transition from "{1}" to "{2}".

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : KMG1531E**

## **Severity**

Error

## **Long Form**

Unable to update key-state-action. Invalid key-state-action transition from "{0}" to "{1}" was attempted.

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : KMG1532E**

### **Severity**

Error

### **Long Form**

Unsupported key attribute "{0}" was found in create template.

### **Short Form**

No short form is provided for this message type

### **Description**

None

## **Message ID : KMG1533E**

### **Severity**

Error

### **Long Form**

Cannot accept past date for attribute "{0}".

## Short Form

No short form is provided for this message type

## Description

None

## Message ID : KMG1534E

## Severity

Error

## Long Form

Date attribute "{0}" value cannot be greater than or equal to date attribute "{1}" value.

## Short Form

No short form is provided for this message type

## Description

None

## **Message ID : KMG1535E**

### **Severity**

Error

### **Long Form**

Invalid key-state-action transition was attempted. Key is not in 'ACTIVE' state.

### **Short Form**

No short form is provided for this message type

### **Description**

None

## **Message ID : KMG1536E**

### **Severity**

Error

### **Long Form**

Cannot accept destroy date without de-activation date.

## Short Form

No short form is provided for this message type

## Description

None

## Message ID : KMG1537E

## Severity

Error

## Long Form

Invalid date for "{0}". Value must be greater than x-activation-date but lower than x-suspend-date, x-deactivation-date, x-destroy-date.

## Short Form

No short form is provided for this message type

## Description

None

Message ID : KMG1536E



## **Message ID : KMG1538E**

### **Severity**

Error

### **Long Form**

Cannot delete attribute "{0}" that has epoch time in the past. This indicates that associated jobs may already have been executed and therefore attribute must be retained at server for audit log purposes.

### **Short Form**

No short form is provided for this message type

### **Description**

None

## **Message ID : KMG1539E**

### **Severity**

Error

## **Long Form**

Version {0} already exists for key {1}

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : KMG1540E**

## **Severity**

Error

## **Long Form**

Cannot add versions to non-versioned key {0}

## **Short Form**

No short form is provided for this message type

**Description**

None

**Message ID : KMG1541E****Severity**

Error

**Long Form**

Opaque Object not specified

**Short Form**

No short form is provided for this message type

**Description**

None

**Message ID : KMG1542E****Severity**

Error

Message ID : KMG1540E

## **Long Form**

Opaque Object not found for id {0}

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : KMG1544E**

## **Severity**

Error

## **Long Form**

One or more of the specified key attribute(s) is read-only and cannot be deleted.

## **Short Form**

No short form is provided for this message type

## **Description**

None

**Message ID : KMG1545E**

## **Severity**

Error

## **Long Form**

The opaque object size is too big. The maximum opaque object size supported is {0} bytes.

## **Short Form**

No short form is provided for this message type

## **Description**

None

**Message ID : KMG1546E**

## **Severity**

Error

Message ID : KMG1544E

## **Long Form**

Cannot perform encryption in "{0}" key state.

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : KMG1547E**

## **Severity**

Error

## **Long Form**

Cannot clone external key.

## **Short Form**

No short form is provided for this message type

## **Description**

None

**Message ID : KMG1566E**

## **Severity**

Error

## **Long Form**

Unexpected key usage value "{0}". Expected values are:"{1}"

## **Short Form**

No short form is provided for this message type

## **Description**

None

**Message ID : KMG1591E**

## **Severity**

Error

Message ID : KMG1547E

## **Long Form**

unwrapping key is not provided.

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : KMG1592E**

## **Severity**

Error

## **Long Form**

unwrapping payload of type {0} is not supported as of now.

## **Short Form**

No short form is provided for this message type



## **Description**

None

**Message ID : KMG1593E**

## **Severity**

Error

## **Long Form**

unwrapping with keys of format {0} is not supported as of now .

## **Short Form**

No short form is provided for this message type

## **Description**

None

**Message ID : KMG1594E**

## **Severity**

Error

Message ID : KMG1592E

## **Long Form**

The Security Server failed to perform decryption using a symmetric key.

## **Short Form**

No short form is provided for this message type

## **Description**

None

**Message ID : KMG1595E**

## **Severity**

Error

## **Long Form**

The wrapped key bytes are not provided.

## **Short Form**

No short form is provided for this message type

Message ID : KMG1594E

**Description**

None

**Message ID : KMG1596E****Severity**

Error

**Long Form**

The Key format is not provided.

**Short Form**

No short form is provided for this message type

**Description**

None

**Message ID : KMG1597E****Severity**

Error

Message ID : KMG1595E

## **Long Form**

The Host Name and Agent Type are not provided.

## **Short Form**

No short form is provided for this message type

## **Description**

None

**Message ID : KMG1598E**

## **Severity**

Error

## **Long Form**

Host Not Found.

## **Short Form**

No short form is provided for this message type

Message ID : KMG1597E

## **Description**

None

**Message ID : KMG1599E**

## **Severity**

Error

## **Long Form**

Unwrapped Keylength {0} does not match the length {1} provided in template attributes.

## **Short Form**

No short form is provided for this message type

## **Description**

None

**Message ID : KMG1600E**

## **Severity**

Error

Message ID : KMG1598E

## **Long Form**

Unwrapping versioned keys is not supported.

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : KMG1610E**

## **Severity**

Error

## **Long Form**

Cryptographic Mask is not specified for the key you are trying to export.

## **Short Form**

No short form is provided for this message type

**Description**

None

**Message ID : KMG1612E****Severity**

Error

**Long Form**

Unable to parse the public key.

**Short Form**

No short form is provided for this message type

**Description**

None

**Message ID : KMG1613E****Severity**

Error

Message ID : KMG1610E

## **Long Form**

Invalid unwrapping key.

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : KMG1618E**

## **Severity**

Error

## **Long Form**

default key template(s)cannot be deleted.

## **Short Form**

No short form is provided for this message type



## **Description**

None

**Message ID : KMG1619E**

## **Severity**

Error

## **Long Form**

Key attributes "{0}" does not match with key template "{1}" attributes

## **Short Form**

No short form is provided for this message type

## **Description**

None

**Message ID : KMG1620E**

## **Severity**

Error

Message ID : KMG1618E

## **Long Form**

Asymmetric key can not created with template "{0}" algorithm type "{1}"

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : KMG1621E**

## **Severity**

Error

## **Long Form**

SAAS key(s) or clear\_key are not eligible for export

## **Short Form**

No short form is provided for this message type

## **Description**

None

**Message ID : KMG1622E**

## **Severity**

Error

## **Long Form**

Export failed. Possible payload contains SAAS key(s), clear\_key or non-existing keys. SAAS keys, clear\_key are not eligible for export

## **Short Form**

No short form is provided for this message type

## **Description**

None

**Message ID : KMG1624E**

## **Severity**

Error

## **Long Form**

Default key template attribute can not be modified

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : KMG1625E**

## **Severity**

Error

## **Long Form**

Neither keyid or keyname are specified.

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : KMG1626E**

## **Severity**

Error

## **Long Form**

Key state value "{0}" is not valid keystate.

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : KMG1633E**

### **Severity**

Error

### **Long Form**

Key attribute name "{0}" is a system reserved name and read only. Please choose a different name for this new attribute.

### **Short Form**

No short form is provided for this message type

### **Description**

None

## **Message ID : KMG1635E**

### **Severity**

Error

### **Long Form**

Key Name cannot be longer than {0} characters

## Short Form

No short form is provided for this message type

## Description

None

## Message ID : KMG1636E

## Severity

Error

## Long Form

Invalid key name. Only alpha numeric characters, dot("."), underscore("\_"), slash("/"), equal sign("="), plus("+") and ("-") are allowed and key name must start with letter or number

## Short Form

No short form is provided for this message type

## Description

None

Message ID : KMG1635E

1334

## **Message ID : KMG1637E**

### **Severity**

Error

### **Long Form**

Key description cannot be longer than {0} characters

### **Short Form**

No short form is provided for this message type

### **Description**

None

## **Message ID : KMG1638E**

### **Severity**

Error

### **Long Form**

KMIP is not enabled

Message ID : KMG1637E



## **Short Form**

No short form is provided for this message type

## **Description**

None

**Message ID : KMG1639E**

## **Severity**

Error

## **Long Form**

Could not create the KMIP key

## **Short Form**

No short form is provided for this message type

## **Description**

None

Message ID : KMG1638E

## **Message ID : KMG1640E**

### **Severity**

Error

### **Long Form**

Key length mismatch

### **Short Form**

No short form is provided for this message type

### **Description**

None

## **Message ID : KMG1641E**

### **Severity**

Error

### **Long Form**

Activation date cannot be in the past

## **Short Form**

No short form is provided for this message type

## **Description**

None

**Message ID : KMG1642E**

## **Severity**

Error

## **Long Form**

Deactivation date cannot be in the past

## **Short Form**

No short form is provided for this message type

## **Description**

None

Message ID : KMG1641E

## **Message ID : KMG1643E**

### **Severity**

Error

### **Long Form**

Deactivation date cannot be before the activation date

### **Short Form**

No short form is provided for this message type

### **Description**

None

## **Message ID : KMG1644E**

### **Severity**

Error

### **Long Form**

Invalid size of {0} for key

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : KMG1647E**

## **Severity**

Error

## **Long Form**

KMIP key of UUID "{0}" deletion failed. Error: "{1}"

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : KMG1648E**

### **Severity**

Error

### **Long Form**

KMIP object of UUID "{0}" not found

### **Short Form**

No short form is provided for this message type

### **Description**

None

## **Message ID : KMG1650E**

### **Severity**

Error

### **Long Form**

Key template with key usage "CACHE\_ON\_HOST" or "STORED\_ON\_SERVER" eligible for symmetric keys only

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : KMG1651E**

## **Severity**

Error

## **Long Form**

RSA Publickey of size should be 2048 bits or larger.

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : KMG1653E**

### **Severity**

Error

### **Long Form**

Key version number must be numeric.

### **Short Form**

No short form is provided for this message type

### **Description**

None

## **Message ID : KMG1654E**

### **Severity**

Error

### **Long Form**

Key version number must be greater or equal to zero.



## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : KMG1660E**

## **Severity**

Error

## **Long Form**

Cannot add versionLifeSpan to non-versioned key {0}

## **Short Form**

No short form is provided for this message type

## **Description**

None

Message ID : KMG1654E

## **Message ID : KMG1661E**

### **Severity**

Error

### **Long Form**

Cannot add restricted key {0}

### **Short Form**

No short form is provided for this message type

### **Description**

None

## **Message ID : KMG1666E**

### **Severity**

Error

### **Long Form**

Provided key format is unexpected, expected format is "RSA PUBLIC KEY" as "PEM"

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : KMG1667E**

## **Severity**

Error

## **Long Form**

Imported Key Name "{0}" is already in use on this server. Delete the existing key and import again.

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : KMG1670E**

### **Severity**

Error

### **Long Form**

Unsupported symmetric key type for key "{0}". {1} encryption mode is used for AES256 keys only.

### **Short Form**

No short form is provided for this message type

### **Description**

None

## **Message ID : KMG1674E**

### **Severity**

Error

### **Long Form**

Encryption mode must be set for AES keys

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : KMG1675E**

## **Severity**

Error

## **Long Form**

KMIP accessible key "{0}" contains invalid client attribute names. A valid KMIP client attribute name shall have a prefix of "x-".

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : KMG1676E**

### **Severity**

Error

### **Long Form**

Invalid key template "{0}" for key "{1}"

### **Short Form**

No short form is provided for this message type

### **Description**

None

## **Message ID : KMG1677E**

### **Severity**

Error

### **Long Form**

Invalid key type "{0}/{1}" of usage "{2}" for KMIP accessible key "{3}"

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : KMG1694E**

## **Severity**

Error

## **Long Form**

Missing Link attribute for KMIP accessible key {0}

## **Short Form**

No short form is provided for this message type

## **Description**

None

Message ID : KMG1677E

## **Message ID : KMG1695E**

### **Severity**

Error

### **Long Form**

Updating key {0} in KMIP failed: {1}.

### **Short Form**

No short form is provided for this message type

### **Description**

None

## **Message ID : KMG1696E**

### **Severity**

Error

### **Long Form**

Deleting key attribute "{0}" in KMIP is not allowed.



## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : KMG1698E**

## **Severity**

Error

## **Long Form**

Cannot encrypt data using private key.

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : KMG1699E**

### **Severity**

Error

### **Long Form**

Cannot decrypt data using public key.

### **Short Form**

No short form is provided for this message type

### **Description**

None

## **Message ID : KMG1700E**

### **Severity**

Error

### **Long Form**

Cannot sign data using public key.

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : KMG1701E**

## **Severity**

Error

## **Long Form**

Cannot verify the signed data using private key.

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : KMG1720E**

### **Severity**

Error

### **Long Form**

Invalid {0} algorithm.

### **Short Form**

No short form is provided for this message type

### **Description**

None

## **Message ID : KMG1728E**

### **Severity**

Error

### **Long Form**

The Security Server could not allow exporting affiliate key "{0}".

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : KMG1745E**

## **Severity**

Error

## **Long Form**

Key Governance is enabled so key cannot be modified

## **Short Form**

No short form is provided for this message type

## **Description**

None

Message ID : KMG1728E

## **Message ID : KMG1762E**

### **Severity**

Error

### **Long Form**

EXT\_KID key attribute can only consist alphanumeric and dash (-) characters, cannot be empty or longer than {0} characters.

### **Short Form**

No short form is provided for this message type

### **Description**

None

## **Message ID : KMG1763E**

### **Severity**

Error

### **Long Form**

The specified key(s) "{0}" was not found in the DSM.

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : KMG1764E**

## **Severity**

Error

## **Long Form**

The specified key(s) with algorithms "{0}" not supported.

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : KMG1765E**

### **Severity**

Error

### **Long Form**

Wrapping for "clear\_key" not supported.

### **Short Form**

No short form is provided for this message type

### **Description**

None

## **Message ID : KMG1766E**

### **Severity**

Error

### **Long Form**

Duplicate keys present in the request.



## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : KMG1767E**

## **Severity**

Error

## **Long Form**

The specified key(s) "{0}" are not exportable.

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : KMG1768E**

### **Severity**

Error

### **Long Form**

The specified key(s) "{0}" state is DESTROYED.

### **Short Form**

No short form is provided for this message type

### **Description**

None

## **Message ID : KMG1771E**

### **Severity**

Error

### **Long Form**

Size of RSA Public key should be 2048 bits, 3072 bits or 4096 bits.

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : KMG1772E**

## **Severity**

Error

## **Long Form**

Invalid Subject Alternative Type provided in the SAN "{0}". Allowed types can be EMAIL, URI, DNS, IP, or OID.

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : KMG1773E**

### **Severity**

Error

### **Long Form**

Invalid character found in SAN "{0}" or the SAN value is not a valid format. Multiple Subject Alternative Names should be entered in a separate line with a new line as a delimiter. Wildcard characters are not allowed.

### **Short Form**

No short form is provided for this message type

### **Description**

None

## **Message ID : KMG1782E**

### **Severity**

Error

## Long Form

Invalid Subject Alternative format provided in the SAN "{0}". It should be in the format: ":". Allowed types can be EMAIL, URI, DNS, IP, or OID.

## Short Form

No short form is provided for this message type

## Description

None

## Message ID : KMG1849E

## Severity

Error

## Long Form

The key "{0}" cannot be modified as it is in the DESTROYED state.

## Short Form

No short form is provided for this message type

## **Description**

None

**Message ID : KMG1850E**

## **Severity**

Error

## **Long Form**

The key "{0}" cannot be purged as it is not in the DESTROYED state.

## **Short Form**

No short form is provided for this message type

## **Description**

None

# Logger KMG: Information

**Message ID : KMG0547I**

## **Severity**

Information

## **Long Form**

Bad input. Expecting hex string.

## **Short Form**

No short form is provided for this message type

## **Description**

None

**Message ID : KMG0610I**

## **Severity**

Information

## Long Form

Administrator "{0}" exported {1} agent keys to a file with sha256={2} and size={3} bytes, containing the following keys: {4}

## Short Form

exported agent

### Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
dlen	out	Numeric	Output byte count or length
keys	vds_keys	Text	List of key names

## Description

None

**Message ID : KMG0611I**

## Severity

Information

Message ID : KMG0610I

1367



## Long Form

Administrator "{0}" imported the following {1} symmetric key(s): {2} and following {3} asymmetric key(s): {4}

## Short Form

admin imported symmetric keys

### Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
keys	vds_keys	Text	List of key names

## Description

None

**Message ID : KMG0761I**

## Severity

Information

## Long Form

The RSA key pair used for encryption/decryption has been expired on {0}.

## Short Form

rsa key pair expired

### Parameters

Label	CEF Label	Type	Usage
etime	end	Text	An end time stamp

## Description

None

**Message ID : KMG1220I**

## Severity

Information

## Long Form

Please [login to DSM server](#) to view the "Keys" report for detail.

Message ID : KMG0761I

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : KMG1221I**

## **Severity**

Information

## **Long Form**

Please [login to DSM server](#) to view the "Keys" report for detail.

## **Short Form**

No short form is provided for this message type

**Description**

None

**Message ID : KMG1361I****Severity**

Information

**Long Form**

Agent key "{0}" has expired today.

**Short Form**

No short form is provided for this message type

**Description**

None

**Message ID : KMG1362I****Severity**

Information

Message ID : KMG1221I

## Long Form

Vault key "{0}" has expired today.

## Short Form

No short form is provided for this message type

## Description

None

## Message ID : KMG1381I

## Severity

Information

## Long Form

Key [Name: {0}, Description: {1}] versioned successfully.

## Short Form

No short form is provided for this message type

## **Description**

None

**Message ID : KMG1386I**

## **Severity**

Information

## **Long Form**

Administrator "{0}" successfully versioned key [Name: {1}, Description: {2}].

## **Short Form**

No short form is provided for this message type

## **Description**

None

**Message ID : KMG1543I**

## **Severity**

Information

Message ID : KMG1381I

## Long Form

{0} at "{1}" created Opaque Object {2} with uuid {3}.

## Short Form

No short form is provided for this message type

## Description

None

## Message ID : KMG1645I

## Severity

Information

## Long Form

KMIP key with name "{0}" and UUID "{1}" created

## Short Form

No short form is provided for this message type

## **Description**

None

**Message ID : KMG1646I**

## **Severity**

Information

## **Long Form**

KMIP key of UUID "{0}" deleted

## **Short Form**

No short form is provided for this message type

## **Description**

None



## **Logger KMG: Warnings**

**Message ID : KMG0596W**

### **Severity**

Warning

### **Long Form**

Key needed to unwrap package not found. Please import appropriate wrapper key and try again.

### **Short Form**

No short form is provided for this message type

### **Description**

None

**Message ID : KMG0774W**

### **Severity**

Warning

## Long Form

Wrapper Key needed to proceed is not found. Please import wrapper key with identifier {0}.

## Short Form

No short form is provided for this message type

## Description

None

## Message ID : KMG1200W

## Severity

Warning

## Long Form

{0} agent keys will expire {2} {1} days.

## Short Form

agent keys will expire

## Parameters

No parameters are provided for this message type

## Description

Agent keys will expire soon. Rekey using dataxform.

## Message ID : KMG1201W

## Severity

Warning

## Long Form

{0} agent key will expire {2} {1} days.

## Short Form

agent key will expire

## Parameters

Label	CEF Label	Type	Usage
key	cs3	Text	Name of key or key pair

## **Description**

An agent key will expire soon. Rekey using dataxform.

## **Message ID : KMG1202W**

## **Severity**

Warning

## **Long Form**

{0} vault keys will expire {2} {1} days.

## **Short Form**

vault keys will expire

## **Parameters**

No parameters are provided for this message type

## **Description**

Vault keys will expire soon. Renew key soon.

## Message ID : KMG1203W

### Severity

Warning

### Long Form

{0} vault key will expire {2} {1} days.

### Short Form

vault key will expire

#### Parameters

Label	CEF Label	Type	Usage
key	cs3	Text	Name of key or key pair

### Description

A vault key will expire soon. Renew key soon.

## Message ID : KMG1210W

## Severity

Warning

## Long Form

{0} agent keys have been expired for {1} days.

## Short Form

agent keys expired

### Parameters

No parameters are provided for this message type

## Description

Agent keys have expired. Rekey using dataxform.

**Message ID : KMG1211W**

## Severity

Warning

## Long Form

{0} agent key has been expired for {1} days.

## Short Form

agent key expired

### Parameters

Label	CEF Label	Type	Usage
key	cs3	Text	Name of key or key pair

## Description

An agent key has expired. Renew key soon

## Message ID : KMG1212W

## Severity

Warning

## Long Form

{0} vault keys have been expired for {1} days.

Message ID : KMG1211W

## Short Form

vault keys expired

### Parameters

No parameters are provided for this message type

## Description

None

## Message ID : KMG1213W

## Severity

Warning

## Long Form

{0} vault key has been expired for {1} days.

## Short Form

vault key expired



## Parameters

Label	CEF Label	Type	Usage
key	cs3	Text	Name of key or key pair

## Description

A vault key has expired. Renew key soon

**Message ID : KMG1295W**

## Severity

Warning

## Long Form

The key vault feature is disabled in the license.

## Short Form

No short form is provided for this message type

## Description

None

Message ID : KMG1213W

## **Message ID : KMG1300W**

### **Severity**

Warning

### **Long Form**

No such wrapper key.

### **Short Form**

No short form is provided for this message type

### **Description**

None

## **Message ID : KMG1512W**

### **Severity**

Warning

### **Long Form**

Certificate "{0}" will expire on "{1}".

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Logger LIC: Errors**

**Message ID : LIC0276E**

### **Severity**

Error

### **Long Form**

Error while setting client option for Vendor id {0} and Nodelock file {1}.

### **Short Form**

No short form is provided for this message type

### **Description**

None

**Message ID : LIC0277E**

### **Severity**

Error

## Long Form

Error while initializing License Use Management with license transaction status {0}

## Short Form

No short form is provided for this message type

## Description

None

## Message ID : LIC0278E

## Severity

Error

## Long Form

The Security Server was unable to find a proper nodelock license file for this installation. The Security Server will now shutdown. This can occur if the nodelock file has been removed or manually modified. Restore the original nodelock file and restart the Security Server.

## Short Form

No short form is provided for this message type

Message ID : LIC0277E

1388

## **Description**

None

**Message ID : LIC0279E**

## **Severity**

Error

## **Long Form**

An internal error occurred on the Security Server. Refer to cgss.log and server.log for details. Call support if necessary.

## **Short Form**

No short form is provided for this message type

## **Description**

None

**Message ID : LIC0580E**

## **Severity**

Error

Message ID : LIC0278E

## **Long Form**

Invalid license signature. {0}

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : LIC0581E**

## **Severity**

Error

## **Long Form**

License not found.

## **Short Form**

No short form is provided for this message type

**Description**

None

**Message ID : LIC0582E****Severity**

Error

**Long Form**

Operation exceeds limits of current license.

**Short Form**

No short form is provided for this message type

**Description**

None

**Message ID : LIC0586E****Severity**

Error

Message ID : LIC0581E



## Long Form

License has expired.

## Short Form

license expired

### Parameters

No parameters are provided for this message type

## Description

None

## Message ID : LIC1160E

## Severity

Error

## Long Form

The term license for {0} agent in domain {1} has expired

## Short Form

domain license expired

### Parameters

Label	CEF Label	Type	Usage
lType	vds_lType	Text	A license type
agent	deviceProcessName	Text	The short identifier of the agent software

## Description

None

**Message ID : LIC1161E**

## Severity

Error

## Long Form

The number of registered {0} agents with {1} license on this server has reached the license limit {2}.

Message ID : LIC1160E

1393

## **Short Form**

No short form is provided for this message type

## **Description**

License reallocation or upgrade recommended.

## **Message ID : LIC1162E**

## **Severity**

Error

## **Long Form**

The number of registered {0} agents with {1} license in domain {2} on this server has reached the license limit {3}.

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : LIC1163E**

### **Severity**

Error

### **Long Form**

The required {0} license for {1} agent is not installed

### **Short Form**

No short form is provided for this message type

### **Description**

None

## **Message ID : LIC1164E**

### **Severity**

Error

### **Long Form**

The required {0} license for {1} agent is not installed in domain {2}

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : LIC1165E**

## **Severity**

Error

## **Long Form**

The available {0} license quota for the {1} agent is insufficient

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : LIC1166E**

### **Severity**

Error

### **Long Form**

The license expiration date for {0} agent is invalid

### **Short Form**

No short form is provided for this message type

### **Description**

None

## **Message ID : LIC1167E**

### **Severity**

Error

### **Long Form**

The license quota {0} for {1} agent is invalid

## Short Form

No short form is provided for this message type

## Description

None

## Message ID : LIC1261E

## Severity

Error

## Long Form

The number of available CPU cores for the {0} agents with {1} license is {2}, which is NOT enough for the number of registering host's CPU cores {3}.

## Short Form

No short form is provided for this message type

## Description

None

Message ID : LIC1167E

1398

## **Message ID : LIC1291E**

### **Severity**

Error

### **Long Form**

The term license for {0} agent has expired.

### **Short Form**

No short form is provided for this message type

### **Description**

None

## **Message ID : LIC1292E**

### **Severity**

Error

### **Long Form**

The CPU core hour usage of {0} agents with {1} license on this server has reached the license limit {2}.



## **Short Form**

No short form is provided for this message type

## **Description**

None

**Message ID : LIC1293E**

## **Severity**

Error

## **Long Form**

The CPU core hour usage of {0} agents with {1} license in domain {2} on this server has reached the license limit {3}.

## **Short Form**

No short form is provided for this message type

## **Description**

None

Message ID : LIC1292E

## **Message ID : LIC1298E**

### **Severity**

Error

### **Long Form**

A KMIP enabled license cannot be installed while user domains exist.

### **Short Form**

No short form is provided for this message type

### **Description**

None

## **Message ID : LIC1324E**

### **Severity**

Error

### **Long Form**

LDT license not found.

Message ID : LIC1298E

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : LIC1325E**

## **Severity**

Error

## **Long Form**

The number of registered agents {0} with LDT license on this server has reached the license limit {1}.

## **Short Form**

No short form is provided for this message type

## **Description**

None

Message ID : LIC1324E

## **Message ID : LIC1326E**

### **Severity**

Error

### **Long Form**

Docker license not found.

### **Short Form**

No short form is provided for this message type

### **Description**

None

## **Message ID : LIC1327E**

### **Severity**

Error

### **Long Form**

The number of registered agents {0} with Docker license on this server has reached the license limit {1}.

Message ID : LIC1326E

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : LIC1621E**

## **Severity**

Error

## **Long Form**

Key rotation feature is not licensed. DSM requires either VAE or LDT license to allow key rotation operation.

## **Short Form**

No short form is provided for this message type

## **Description**

None

Message ID : LIC1327E

## **Message ID : LIC1690E**

### **Severity**

Error

### **Long Form**

FF1 license not found.

### **Short Form**

No short form is provided for this message type

### **Description**

None

## **Message ID : LIC1691E**

### **Severity**

Error

### **Long Form**

The number of registered agents {0} with FF1 license on this server has reached the license limit {1}.

## **Short Form**

No short form is provided for this message type

## **Description**

None

**Message ID : LIC1736E**

## **Severity**

Error

## **Long Form**

Efficient Storage license not found.

## **Short Form**

No short form is provided for this message type

## **Description**

None

Message ID : LIC1691E

## **Message ID : LIC1737E**

### **Severity**

Error

### **Long Form**

The number of registered agents {0} with Efficient Storage licenses on this server has reached the license limit {1}.LUP0113E=The security server failed to initialize its configuration. The server will not function correctly. Please restart the system. If the problem persists, contact support.

### **Short Form**

No short form is provided for this message type

### **Description**

None



# Logger LIC: Information

**Message ID : LIC0587I**

## Severity

Information

## Long Form

Administrator {0} successfully installed license.

## Short Form

installed license ok

## Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name

## Description

None

# Logger LIC: Warnings

**Message ID : LIC1323W**

## **Severity**

Warning

## **Long Form**

RA license cannot be installed on a DSM in SuiteB mode.

## **Short Form**

No short form is provided for this message type

## **Description**

None

# Logger LOG: Errors

**Message ID : LOG0138E**

## Severity

Error

## Long Form

The Security Server failed to retrieve audit logs from the database. Verify that the database is functional and retry the operation.

## Short Form

failed to retrieve audit logs from database

## Parameters

No parameters are provided for this message type

## Description

None

**Message ID : LOG0139E**

## Severity

Error

## Long Form

The Security Server failed to purge the debug messages from the database. Verify that the database is functional and retry the operation.

## Short Form

failed to purge debug messages from database

### Parameters

No parameters are provided for this message type

## Description

None

## Message ID : LOG0287E

## Severity

Error

## **Long Form**

The Security Server failed to retrieve the number of denied backup and restore operations because of internal error. Please try it again.

## **Short Form**

No short form is provided for this message type

## **Description**

None

# Logger LOG: Information

**Message ID : LOG0140I**

## Severity

Information

## Long Form

Administrator "{0}" has exported {1} log messages.

## Short Form

exported log messages

### Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name

## Description

None

## Message ID : LOG0141I

### Severity

Information

### Long Form

The Security Server has pruned and exported {0} log messages into file "{1}". These log messages have been deleted from the Security Server.

### Short Form

server has pruned and exported log messages into file

### Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

### Description

None

## Message ID : LOG0541I

## Severity

Information

## Long Form

Administrator "{0}" has deleted {1} log messages.

## Short Form

deleted log messages

### Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name

## Description

None

**Message ID : LOG0669I**

## Severity

Information

Message ID : LOG0541I



## Long Form

Route to syslog server UP: {0} ({1})

## Short Form

route to syslog server UP

### Parameters

Label	CEF Label	Type	Usage
port	spt	Numeric	A socket port number

## Description

None

# Logger LOG: Warnings

**Message ID : LOG0668W**

## Severity

Warning

## Long Form

Route to syslog server DOWN: {0} ({1}) ({2})

## Short Form

route to syslog server DOWN

## Parameters

Label	CEF Label	Type	Usage
port	spt	Numeric	A socket port number
showStr	reason	Text	Code specifying reason for allowing access, if any

## Description

None

## Message ID : LOG1318W

### Severity

Warning

### Long Form

Syslog message back logged: {0} ({1}) ({2})

### Short Form

syslog message back logged

#### Parameters

Label	CEF Label	Type	Usage
port	spt	Numeric	A socket port number
showStr	reason	Text	Code specifying reason for allowing access, if any

### Description

None

# Logger LUP: Errors

**Message ID : LUP0114E**

## Severity

Error

## Long Form

The security server failed to initialize the system to process messages from hosts. This is caused by an internal error or an incorrect server configuration. Please restart your system. If the problem persists, contact support.

## Short Form

failed to initialize system

## Parameters

No parameters are provided for this message type

## Description

None

# Message ID : LUP0117E

## Severity

Error

## Long Form

The security server failed to parse the log file from a host. The file had an invalid format and has been moved to the .../auditlog/badlogs directory. The messages in the file will not be saved to database. The server will continue to log files from the host.

## Short Form

failed to parse log file

### Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

## Description

None

## **Message ID : LUP0118E**

### **Severity**

Error

### **Long Form**

The security server received a host log file with an incorrect timestamp format while processing an uploaded log file from a host. The timestamp on the document received was {0}. The log file will not be saved to the database.

### **Short Form**

No short form is provided for this message type

### **Description**

None

## **Message ID : LUP0119E**

### **Severity**

Error

## Long Form

The security server failed to convert the message time stamp or the arguments were incorrect, while processing the message from host. The message: "{0}, {1}, {2}, {3}" will be not be saved.

## Short Form

failed to parse log message

### Parameters

Label	CEF Label	Type	Usage
showStr	reason	Text	Code specifying reason for allowing access, if any

## Description

None

## Message ID : LUP0120E

## Severity

Error

## Long Form

The security server failed to convert the time zone offset while processing the message from host. The message: "{0}, {1}, {2},

Message ID : LUP0119E

1422

{3}" will be not be saved.

## Short Form

bad time zone

### Parameters

Label	CEF Label	Type	Usage
showStr	reason	Text	Code specifying reason for allowing access, if any

## Description

None

## Message ID : LUP0121E

## Severity

Error

## Long Form

The security server could not find the message id in the message resource for the Agent. The message: "{0}, {1}, {2}, {3}" will not be saved. Please update the message resource file for the Agent.



## Short Form

unknown message id

### Parameters

Label	CEF Label	Type	Usage
showStr	reason	Text	Code specifying reason for allowing access, if any

## Description

None

## Message ID : LUP0122E

### Severity

Error

## Long Form

The security server failed to open the message resource file {0} for the Agent. Check if the message resource file is missing. The server will not be able to process logs uploaded from the Agent.

## Short Form

failed to open resource file

Message ID : LUP0121E

1424

### Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

### Description

None

### Message ID : LUP0123E

### Severity

Error

### Long Form

The security server failed to process the message : "{0}, {1}, {2}, {3}" from a host. The format of the message is invalid. The message will not be saved.

### Short Form

invalid message format

### Parameters

Label	CEF Label	Type	Usage
-------	-----------	------	-------

Message ID : LUP0122E

showStr	reason	Text	Code specifying reason for allowing access, if any
---------	--------	------	--

## Description

None

## Message ID : LUP0128E

## Severity

Error

## Long Form

The security server encountered a message with an incorrect timestamp format while processing the message. The timestamp received was {0}. The message will not be saved to the database.

## Short Form

message with incorrect timestamp

## Parameters

Label	CEF Label	Type	Usage
showStr	reason	Text	Code specifying reason for allowing access, if any

## Description

None

**Message ID : LUP0131E**

## Severity

Error

## Long Form

The security server has an internal error. The server will not be able to process uploaded log files. Please restart your server. If the problem persists, contact support.

## Short Form

internal error

## Parameters

No parameters are provided for this message type

## Description

None

Message ID : LUP0128E

1427

## Message ID : LUP0132E

### Severity

Error

### Long Form

The security server cannot find the uploaded log file {0} for processing. Messages in this file will not be saved. If the problem persists, please contact support.

### Short Form

cannot find log file

### Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

### Description

None

## Message ID : LUP0133E

## Severity

Error

## Long Form

The security Server failed to open the uploaded log file {0} for processing. Messages in this file will not be saved. If the problem persists, please contact support.

## Short Form

cannot open log file

### Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

## Description

None

**Message ID : LUP0134E**

## Severity

Error

Message ID : LUP0133E

## Long Form

The security server could not initialize the message queue {0} for handling messages from Agents. This could be caused by an internal error or if the server's configuration was changed manually. The Server will not process log files uploaded from Agents. Please contact support.

## Short Form

cannot initialize message queue

### Parameters

Label	CEF Label	Type	Usage
queue	vds_queue	Text	A message queue identifier

## Description

None

**Message ID : LUP0135E**

## Severity

Error

## Long Form

The security server encountered an error while clearing a message queue. Ignore the messages that complains not found files. The server will continue to process uploaded log files correctly.

## Short Form

cannot clear message queue

### Parameters

No parameters are provided for this message type

## Description

None

## Message ID : LUP0136E

## Severity

Error

## Long Form

The security server failed to queue unprocessed message files for processing. These message files will not be saved to the database. If the problem persists, contact support.



## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : LUP0299E**

## **Severity**

Error

## **Long Form**

The security server failed to save the messages from a host. Please check your database. This message file will be processed when the server is restarted.

## **Short Form**

failed to save host messages

## **Parameters**

No parameters are provided for this message type

Message ID : LUP0136E

1432

## **Description**

None

# Logger LUP: Fatal errors

**Message ID : LUP0124F**

## Severity

Fatal error

## Long Form

The security server's Logging system is unable to connect to the database to save messages. The logging system will sleep {0} seconds and retry the operation.

## Short Form

Logging system unable to connect to database

## Parameters

No parameters are provided for this message type

## Description

None

## **Message ID : LUP0126F**

### **Severity**

Fatal error

### **Long Form**

An internal error occurred while the Security Server reinitialized the message system to process messages from hosts. Please restart the server. If the problem persists, contact support.

### **Short Form**

internal error

### **Parameters**

No parameters are provided for this message type

### **Description**

None

## **Message ID : LUP0127F**

## Severity

Fatal error

## Long Form

The security server failed to queue the message file {0} for processing. Some messages may be lost. If the problem persists, contact support.

## Short Form

failed to queue message file

### Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

## Description

None

**Message ID : LUP0129F**

## Severity

Fatal error

Message ID : LUP0127F

## Long Form

The security server has an internal error. The server will not be able to process uploaded log files. Please restart your server. If the problem persists, contact support.

## Short Form

internal error

### Parameters

No parameters are provided for this message type

## Description

None

## Message ID : LUP0130F

## Severity

Fatal error

## Long Form

The security server has an internal error. The server will not be able to handle uploaded log files. Please restart your server. If the problem persists, contact support.

Message ID : LUP0129F

1437

## Short Form

internal error

### Parameters

No parameters are provided for this message type

## Description

None

## Message ID : LUP0137F

## Severity

Fatal error

## Long Form

The security server received a log file upload request that contain an incorrect header. The server will ignore the upload request. If the problem persists, contact support.

## Short Form

incorrect header in log file upload request

### **Parameters**

No parameters are provided for this message type

### **Description**

None



## **Logger LUP: Information**

**Message ID : LUP0115I**

### **Severity**

Information

### **Long Form**

The uploaded log file has been processed successfully.

### **Short Form**

No short form is provided for this message type

### **Description**

None

**Message ID : LUP0116I**

### **Severity**

Information

## Long Form

The security server has successfully initialized the logging system to log messages from hosts. The server can now log messages from hosts.

## Short Form

initialized logging system

### Parameters

No parameters are provided for this message type

## Description

None

## Message ID : LUP0125I

## Severity

Information

## Long Form

The message file {0} has been sent for processing.

## Short Form

message file submitted

### Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

## Description

None

**Message ID : LUP0428I**

## Severity

Information

## Long Form

The log file received atfter host "{0}" was deleted.

## Short Form

No short form is provided for this message type

Message ID : LUP0125I

## Description

None

## **Logger PLC: Errors**

**Message ID : PLC0179E**

### **Severity**

Error

### **Long Form**

A policy with name "{0}" already exists in domain "{1}". Please specify a different name.

### **Short Form**

No short form is provided for this message type

### **Description**

None

**Message ID : PLC0180E**

### **Severity**

Error

## **Long Form**

Online Policy with name "{0}" does not exist.

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : PLC0183E**

## **Severity**

Error

## **Long Form**

Action Set name "{0}" is already in use in the domain. Please specify a different name.

## **Short Form**

No short form is provided for this message type

## **Description**

None

**Message ID : PLC0184E**

## **Severity**

Error

## **Long Form**

Process Set with name "{0}" already exists in domain "{1}". Please specify a different name.

## **Short Form**

No short form is provided for this message type

## **Description**

None

**Message ID : PLC0185E**

## **Severity**

Error

Message ID : PLC0183E

## Long Form

Resource Set with name "{0}" already exists in domain "{1}". Please specify a different name.

## Short Form

No short form is provided for this message type

## Description

None

## Message ID : PLC0186E

## Severity

Error

## Long Form

Time Set with name "{0}" already exists in domain "{1}". Please specify a different name.

## Short Form

No short form is provided for this message type



## **Description**

None

**Message ID : PLC0187E**

## **Severity**

Error

## **Long Form**

User Set with name "{0}" already exists in domain "{1}". Please specify a different name.

## **Short Form**

No short form is provided for this message type

## **Description**

None

**Message ID : PLC0188E**

## **Severity**

Error

Message ID : PLC0186E

## **Long Form**

Name "{0}" is too long.

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : PLC0189E**

## **Severity**

Error

## **Long Form**

Offline Policy with name "{0}" no longer exists.

## **Short Form**

No short form is provided for this message type

## **Description**

None

**Message ID : PLC0190E**

## **Severity**

Error

## **Long Form**

No applicable policy can be found for the target.

## **Short Form**

No short form is provided for this message type

## **Description**

None

**Message ID : PLC0191E**

## **Severity**

Error

Message ID : PLC0189E

## **Long Form**

Symmetric Key "{0}" does not exist in the database.

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : PLC0192E**

## **Severity**

Error

## **Long Form**

Action Set "{0}" does not exist in the database.

## **Short Form**

No short form is provided for this message type

## **Description**

None

**Message ID : PLC0193E**

## **Severity**

Error

## **Long Form**

Process Set "{0}" does not exist in the database.

## **Short Form**

No short form is provided for this message type

## **Description**

None

**Message ID : PLC0194E**

## **Severity**

Error

Message ID : PLC0192E

## **Long Form**

Resource Set "{0}" does not exist in the database.

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : PLC0195E**

## **Severity**

Error

## **Long Form**

Time Set "{0}" does not exist in the database.

## **Short Form**

No short form is provided for this message type

## **Description**

None

**Message ID : PLC0196E**

## **Severity**

Error

## **Long Form**

User Set "{0}" does not exist in the database.

## **Short Form**

No short form is provided for this message type

## **Description**

None

**Message ID : PLC0288E**

## **Severity**

Error

Message ID : PLC0195E

## **Long Form**

The rule name "{0}" is already in use. Specify a different name.

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : PLC0302E**

## **Severity**

Error

## **Long Form**

The Security Server could not delete policy "{0}". Hosts or host groups are guarded by the policy.

## **Short Form**

No short form is provided for this message type



**Description**

None

**Message ID : PLC0548E****Severity**

Error

**Long Form**

Policy "{0}" cannot be imported. The XML contains a tag which is no longer supported.

**Short Form**

No short form is provided for this message type

**Description**

None

**Message ID : PLC0604E****Severity**

Error

Message ID : PLC0302E

## **Long Form**

Signature Set "{0}" does not exist in the database.

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : PLC0764E**

## **Severity**

Error

## **Long Form**

The policy {0} xml body cannot be empty. Please correct the problem and try again.

## **Short Form**

No short form is provided for this message type

## **Description**

None

**Message ID : PLC0806E**

## **Severity**

Error

## **Long Form**

The key in policy {0} does not exist in domain.

## **Short Form**

No short form is provided for this message type

## **Description**

None

**Message ID : PLC1301E**

## **Severity**

Error

Message ID : PLC0764E

## **Long Form**

Policy name cannot be empty.

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : PLC1302E**

## **Severity**

Error

## **Long Form**

Process Set "{0}" cannot be deleted because it is referenced in at least one policy.

## **Short Form**

No short form is provided for this message type

Message ID : PLC1301E

## **Description**

None

**Message ID : PLC1303E**

## **Severity**

Error

## **Long Form**

Resource Set "{0}" cannot be deleted because it is referenced in at least one policy.

## **Short Form**

No short form is provided for this message type

## **Description**

None

**Message ID : PLC1304E**

## **Severity**

Error

Message ID : PLC1302E

## **Long Form**

Time Set "{0}" cannot be deleted because it is referenced in at least one policy.

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : PLC1305E**

## **Severity**

Error

## **Long Form**

User Set "{0}" cannot be deleted because it is referenced in at least one policy.

## **Short Form**

No short form is provided for this message type

## **Description**

None

**Message ID : PLC1306E**

## **Severity**

Error

## **Long Form**

Invalid Policy Schema Version. Allowed values are 0 or 1.

## **Short Form**

No short form is provided for this message type

## **Description**

None

**Message ID : PLC1309E**

## **Severity**

Error

Message ID : PLC1305E

## **Long Form**

Apply key in security rule has not been covered by any key rule.

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : PLC1313E**

## **Severity**

Error

## **Long Form**

Key Selection Rules #{0} are being applied to the same Resource.

## **Short Form**

No short form is provided for this message type



## **Description**

None

**Message ID : PLC1316E**

## **Severity**

Error

## **Long Form**

You must specify a valid policy name. (It must be in alpha-numeric characters with a maximum length of 64. It cannot begin with a digit or contain spaces, '\*' or '!'.)

## **Short Form**

No short form is provided for this message type

## **Description**

None

**Message ID : PLC1317E**

## **Severity**

Error

## **Long Form**

Data Transformation Rules #{0} are being applied to the same Resource.

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : PLC1320E**

## **Severity**

Error

## **Long Form**

Policy with Id "{0}" does not exist in the database.

Message ID : PLC1317E

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : PLC1321E**

## **Severity**

Error

## **Long Form**

Policy with Id "{0}" and version "{1}" does not exist in the database.

## **Short Form**

No short form is provided for this message type

## **Description**

None

Message ID : PLC1320E

## **Message ID : PLC1500E**

### **Severity**

Error

### **Long Form**

LDT Policy {0} cannot be associated with LDT disabled host {1}

### **Short Form**

No short form is provided for this message type

### **Description**

None

## **Message ID : PLC1501E**

### **Severity**

Error

### **Long Form**

Versioned key {0} cannot be used in a Standard policy {1}.

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : PLC1502E**

## **Severity**

Error

## **Long Form**

Versioned key {0} cannot be used as Current\_Key in a Live Data Transformation policy {1}.

## **Short Form**

No short form is provided for this message type

## **Description**

None

Message ID : PLC1501E

## **Message ID : PLC1503E**

### **Severity**

Error

### **Long Form**

Non-Versioned key {0} cannot be used as Next\_Key in a Live Data Transformation policy {1}.

### **Short Form**

No short form is provided for this message type

### **Description**

None

## **Message ID : PLC1505E**

### **Severity**

Error

### **Long Form**

Required set {0} ({1}) for policy {2} not found.

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : PLC1506E**

## **Severity**

Error

## **Long Form**

Policy {0} cannot be saved, with missing keys: {1}, missing sets: {2}, and or other validation errors: {3}.

## **Short Form**

No short form is provided for this message type

## **Description**

None

Message ID : PLC1505E

## **Message ID : PLC1507E**

### **Severity**

Error

### **Long Form**

Host "{0}" does not support the CBC\_CS1 encryption mode, you cannot create a GuardPoint with a Policy "{1}" that contains a key that uses this encryption mode.

### **Short Form**

No short form is provided for this message type

### **Description**

None

## **Message ID : PLC1508E**

### **Severity**

Error



## Long Form

Not all the registered Hosts in Host Group "{0}" support the CBC\_CS1 encryption mode, you cannot create a GuardPoint with a Policy "{1}" that contains a key that uses this encryption mode.

## Short Form

No short form is provided for this message type

## Description

None

## Message ID : PLC1509E

## Severity

Error

## Long Form

Raw or Block Device (Manual and Auto Guard) guardpoints are incompatible with Policy "{0}" that contains a key that uses the CBC\_CS1 encryption mode.

## Short Form

No short form is provided for this message type

Message ID : PLC1508E

## **Description**

None

## **Message ID : PLC1512E**

### **Severity**

Error

### **Long Form**

LDT Policy {0} cannot contain a security rule that is missing the "Apply key" effect.

### **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : PLC1515E**

### **Severity**

Error

Message ID : PLC1509E

## **Long Form**

LDT Policy {0} must have at least one non-exclusion key rule.

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : PLC1516E**

## **Severity**

Error

## **Long Form**

Cloud Object Storage Policy {0} can only contain one key rule.

## **Short Form**

No short form is provided for this message type

Message ID : PLC1515E

## **Description**

None

## **Message ID : PLC1517E**

### **Severity**

Error

### **Long Form**

Cloud Object Storage Policy {0} must have at least one CBC-CS1 key rule.

### **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : PLC1518E**

### **Severity**

Error

Message ID : PLC1516E

## **Long Form**

Policy type "{0}" is not a valid policy type.

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : PLC1623E**

## **Severity**

Error

## **Long Form**

"Raw or Block Device " not supported for LDT Policy {0}

## **Short Form**

No short form is provided for this message type

Message ID : PLC1518E

## **Description**

None

**Message ID : PLC1624E**

## **Severity**

Error

## **Long Form**

IDT Policy {0} supports only "Raw or Block Device or incorrect IDT setting"

## **Short Form**

No short form is provided for this message type

## **Description**

None

**Message ID : PLC1671E**

## **Severity**

Error

Message ID : PLC1623E

## **Long Form**

Key Selection Rules cannot contain more than two keys in XTS encryption mode.

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : PLC1672E**

## **Severity**

Error

## **Long Form**

Keys in XTS encryption mode in Key Selection Rules cannot apply to non-empty Resource.

## **Short Form**

No short form is provided for this message type

## Description

None

**Message ID : PLC1673E**

## Severity

Error

## Long Form

Efficient Storage GuardPoint must use a Standard/IDT policy that contains one key. That key must use the {0} encryption mode with KMIP Accessible enabled.

## Short Form

No short form is provided for this message type

## Description

None

**Message ID : PLC1678E**



## Severity

Error

## Long Form

Host "{0}" does not support the {2} encryption mode, you cannot create a GuardPoint with a Policy "{1}" that contains a key that uses this encryption mode.

## Short Form

No short form is provided for this message type

## Description

None

## Message ID : PLC1679E

## Severity

Error

## Long Form

Not all the registered Hosts in Host Group "{0}" support the {2} encryption mode, you cannot create a GuardPoint with a Policy "{1}" that contains a key that uses this encryption mode.

Message ID : PLC1678E

1480

## Short Form

No short form is provided for this message type

## Description

None

## Message ID : PLC1680E

## Severity

Error

## Long Form

Raw or Block Device (Manual and Auto Guard) GuardPoints are incompatible with Policy "{0}" that contains a key with {1} encryption mode.

## Short Form

No short form is provided for this message type

## Description

None

Message ID : PLC1679E

## **Message ID : PLC1681E**

### **Severity**

Error

### **Long Form**

A policy that contains a key that uses the XTS encryption mode is applicable only for Efficient Storage and In-place Data Transformation - Device GuardPoints.

### **Short Form**

No short form is provided for this message type

### **Description**

None

## **Message ID : PLC1682E**

### **Severity**

Error

## Long Form

Directory Device (Manual and Auto Guard) guardpoints are incompatible with Policy "{0}" that contains a key with {1} encryption mode.

## Short Form

No short form is provided for this message type

## Description

None

## Message ID : PLC1688E

## Severity

Error

## Long Form

Current key and Transformation key are not identical They must be the same and Resource set is mandatory for an exclusion rule in LDT-enabled policy.

## Short Form

No short form is provided for this message type

Message ID : PLC1682E

1483

## **Description**

None

**Message ID : PLC1704E**

## **Severity**

Error

## **Long Form**

All FS agents in this group must be version 6.2.0 or higher to support selected LDT policy with exclusion key rule. Please perform an upgrade of FS agent to 6.2.0 or later.

## **Short Form**

No short form is provided for this message type

## **Description**

None

**Message ID : PLC1719E**

## Severity

Error

## Long Form

Cannot create a Cloud Object Storage guardpoint because HostGroup "{0}" has incompatible existing host members.

## Short Form

No short form is provided for this message type

## Description

None

## Message ID : PLC1743E

## Severity

Error

## Long Form

FS (VTE) agent must be version 6.2.0 or higher to support selected LDT policy with exclusion key rule. Perform an upgrade of FS (VTE) agent to 6.2.0 or later.

Message ID : PLC1719E

1485

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : PLC1751E**

## **Severity**

Error

## **Long Form**

GuardPoint with both Efficient-Storage and In-place data transformation - Device is not allowed.

## **Short Form**

No short form is provided for this message type

## **Description**

None

Message ID : PLC1743E

## **Message ID : PLC1752E**

### **Severity**

Error

### **Long Form**

Current Key and New Key cannot be identical in Key Selection Rules of IDT policy.

### **Short Form**

No short form is provided for this message type

### **Description**

None

## **Message ID : PLC1753E**

### **Severity**

Error

### **Long Form**

The Current Key after key rule transition should match the New Key before the transition.



## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : PLC1754E**

## **Severity**

Error

## **Long Form**

Current Key should be associated with a resource. The New Key, in an IDT policy, should not be associated with a resource.

## **Short Form**

No short form is provided for this message type

## **Description**

None

Message ID : PLC1753E

## **Message ID : PLC1755E**

### **Severity**

Error

### **Long Form**

IDT policy should have two keys.

### **Short Form**

No short form is provided for this message type

### **Description**

None

## **Message ID : PLC1756E**

### **Severity**

Error

### **Long Form**

IDT policy only allows "read" "write" "all\_ops" actions in security rules.

## **Short Form**

No short form is provided for this message type

## **Description**

None

**Message ID : PLC1757E**

## **Severity**

Error

## **Long Form**

Learn Mode is not allowed for IDT policy.

## **Short Form**

No short form is provided for this message type

## **Description**

None

Message ID : PLC1756E

## **Message ID : PLC1779E**

### **Severity**

Error

### **Long Form**

IDT Policy "{0}" for "{1}" cannot contain a "clear\_key" and can only contain an XTS key.

### **Short Form**

No short form is provided for this message type

### **Description**

None

## **Message ID : PLC1780E**

### **Severity**

Error

### **Long Form**

IDT Policy "{0}" for "{1}" can only contain either a "clear\_key" or an XTS key.

## Short Form

No short form is provided for this message type

## Description

None

## Message ID : PLC1781E

## Severity

Error

## Long Form

Cloud Object Storage Policy "{0}" only allows "READ\_FILE", "WRITE\_FILE", "REMOVE\_FILE", "READ\_DIRECTORY" and "ALL\_OPERATIONS" actions in security rules.

## Short Form

No short form is provided for this message type

## Description

None

Message ID : PLC1780E

## **Message ID : PLC1783E**

### **Severity**

Error

### **Long Form**

Key operations (key\_op) in security rule have not been covered by key selection rule and data transformation rule.

### **Short Form**

No short form is provided for this message type

### **Description**

None

## **Message ID : PLC1785E**

### **Severity**

Error

### **Long Form**

Policy "{0}" must have at least one data transformation key rule when key\_op action is selected in security rule.

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : PLC1786E**

## **Severity**

Error

## **Long Form**

Policy "{0}" must have at least one backup key rule when "Apply Backup Key" effect is selected in security rule.

## **Short Form**

No short form is provided for this message type

## **Description**

None

Message ID : PLC1785E

## **Message ID : PLC1787E**

### **Severity**

Error

### **Long Form**

Efficient Encrypted Backup Capability is not enabled. Policy with "Apply Backup Key" effect in security rule is not supported.

### **Short Form**

No short form is provided for this message type

### **Description**

None

## **Message ID : PLC1788E**

### **Severity**

Error

### **Long Form**

Policy with "Apply Backup Key" effect in security rule is compatible only with Directory Device (Manual and Auto Guard) guardpoints.

Message ID : PLC1787E

1495



## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : PLC1789E**

## **Severity**

Error

## **Long Form**

Policy with "Apply Backup Key" effect in security rule is compatible only with Standard policy type.POL0142I\_CEF=shost={0}

## **Short Form**

No short form is provided for this message type

## **Description**

None

Message ID : PLC1788E

## **Message ID : PLC1820E**

### **Severity**

Error

### **Long Form**

Policy with "Apply Backup Key" effect in security rule is not supported.

### **Short Form**

No short form is provided for this message type

### **Description**

None

# Logger PLC: Information

**Message ID : PLC1511I**

## Severity

Information

## Long Form

User "{0}" exported policy "{1}"

## Short Form

exported policy

### Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name

## Description

None

## **Message ID : PLC1513I**

### **Severity**

Information

### **Long Form**

{0} in the path and in the object(id) do not match

### **Short Form**

No short form is provided for this message type

### **Description**

None

## **Message ID : PLC1514I**

### **Severity**

Information

### **Long Form**

Policy in the path and in the object(id) do not match

## **Short Form**

No short form is provided for this message type

## **Description**

None

# Logger PLC: Warnings

**Message ID : PLC0181W**

## **Severity**

Warning

## **Long Form**

Some Action Sets, Process Sets, Resource Sets, Time Sets and/or User Sets have been updated by other processes.

## **Short Form**

No short form is provided for this message type

## **Description**

None

**Message ID : PLC0182W**

## **Severity**

Warning

## **Long Form**

Policy "{0}" has been updated by other processes.

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : PLC1318W**

## **Severity**

Warning

## **Long Form**

Learn mode is enabled.

## **Short Form**

No short form is provided for this message type

## **Description**

None

**Message ID : PLC1319W**

## **Severity**

Warning

## **Long Form**

A "Permit" effect is not accompanied by an "Apply key" effect in the security rule. Use of that rule will NOT encrypt/decrypt the data.

## **Short Form**

No short form is provided for this message type

## **Description**

None

**Message ID : PLC1369W**



## Severity

Warning

## Long Form

The new security rule #{0} has been added, but the security rule #{1} has same object sets as security rule #{2} with similar effect. The security rule #{3} may not take effect. Please review security rules carefully before proceeding.

## Short Form

No short form is provided for this message type

## Description

None

## Message ID : PLC1370W

## Severity

Warning

## Long Form

The security rule #{0} has been updated, but the security rule #{1} has same object sets as security rule #{2} with similar effect. The security rule #{3} may not take effect. Please review security rules carefully before proceeding.

Message ID : PLC1369W

1504

## Short Form

No short form is provided for this message type

## Description

None

## Message ID : PLC1371W

## Severity

Warning

## Long Form

The new security rule #{0} has been added, but the security rule #{1} has same object sets as security rule #{2} with conflict effect. The security rule #{3} may not take effect. Please review security rules carefully before proceeding.

## Short Form

No short form is provided for this message type

## Description

None

Message ID : PLC1370W

1505

## **Message ID : PLC1372W**

### **Severity**

Warning

### **Long Form**

The security rule #{0} has been updated, but the security rule #{1} has same object sets as security rule #{2} with conflict effect. The security rule #{3} may not take effect. Please review security rules carefully before proceeding.

### **Short Form**

No short form is provided for this message type

### **Description**

None

## **Message ID : PLC1373W**

### **Severity**

Warning

## Long Form

The new security rule #{0} has been added, but the security rule #{1} object sets supersede security rule #{2} object sets. The security rule #{3} may not take effect. Please review security rules carefully before proceeding.

## Short Form

No short form is provided for this message type

## Description

None

## Message ID : PLC1374W

## Severity

Warning

## Long Form

The security rule #{0} has been updated, but the security rule #{1} object sets supersede security rule #{2} object sets. The security rule #{3} may not take effect. Please review security rules carefully before proceeding.

## Short Form

No short form is provided for this message type

Message ID : PLC1373W

1507

## **Description**

None

# Logger POL: Errors

**Message ID : POL4556E**

## Severity

Error

## Long Form

ACCESS DENIED on request to {0} database {1}, on hostname {2}. Instance name is {3}, partition {4}, catnode {5}. The timestamp is {6}, and the DB2 version is {7}. The request protocol version is {8}.

## Short Form

Access denied by policy

## Parameters

Label	CEF Label	Type	Usage
act	act	Text	Action being requested or performed
dbname	vds_dbname	Text	Database name
shost	shost	Text	Source host name
dbinstance	vds_dbinstance	Text	Database instance
dbpart	vds_dbpart	Numeric	Database partition

Label	CEF Label	Type	Usage
node	vds_node	Numeric	A node identifier
rt	rt	Text	Time of event
dbver	vds_dbver	Numeric	Database version
version	vds_version	Text	Software version string

## Description

None

## Message ID : POL4580E

## Severity

Error

## Long Form

ACCESS DENIED on request to perform {0} for hostname {1}. Server name is {2}, server number {3}, object id {4}. The timestamp is {5}. The request protocol version is {6}.

## Short Form

No short form is provided for this message type

## Description

None

## Message ID : POL4613E

## Severity

Error

## Long Form

ACCESS DENIED on request to perform {0} for hostname {1}. Server name is {2}, server number {3}. The timestamp is {4}. The request protocol version is {5}.

## Short Form

Access denied

## Parameters

Label	CEF Label	Type	Usage
act	act	Text	Action being requested or performed
shost	shost	Text	Source host name
dbinstance	vds_dbinstance	Text	Database instance
dbpart	vds_dbpart	Numeric	Database partition



Label	CEF Label	Type	Usage
rt	rt	Text	Time of event
version	vds_version	Text	Software version string

## Description

An online policy blocked access. Details of the attempted access are provided in the message fields.

## Message ID : POL4701E

### Severity

Error

### Long Form

Memory allocation failed in [{0}] at line [{1}]

### Short Form

Out of memory

### Parameters

No parameters are provided for this message type

Message ID : POL4613E

## Description

None

**Message ID : POL4704E**

## Severity

Error

## Long Form

EVENT: {0}

## Short Form

Event

## Parameters

Label	CEF Label	Type	Usage
showStr	reason	Text	Code specifying reason for allowing access, if any

## Description

None

Message ID : POL4701E

# Logger POL: Fatal errors

## Message ID : POL4510F

### Severity

Fatal error

### Long Form

Fatal error while evaluating policy to {0} database {1}, on hostname {2}. Instance name is {3}, partition {4}, catnode {5}. The timestamp is {6}, and the DB2 version is {7}. The request protocol version is {8}.

### Short Form

Policy eval error

### Parameters

Label	CEF Label	Type	Usage
act	act	Text	Action being requested or performed
dbname	vds_dbname	Text	Database name
shost	shost	Text	Source host name
dbinstance	vds_dbinstance	Text	Database instance
dbpart	vds_dbpart	Numeric	Database partition

Label	CEF Label	Type	Usage
node	vds_node	Numeric	A node identifier
rt	rt	Text	Time of event
dbver	vds_dbver	Numeric	Database version
version	vds_version	Text	Software version string

## Description

None

## Message ID : POL4516F

## Severity

Fatal error

## Long Form

Attribute "{0}" parsing error in policy evaluation request.

## Short Form

Req parse error

### Parameters

Label	CEF Label	Type	Usage
showStr	reason	Text	Code specifying reason for allowing access, if any

### Description

None

### Message ID : POL4528F

### Severity

Fatal error

### Long Form

Attribute "{0}" parsing error in policy evaluation response.

### Short Form

Resp parse error

### Parameters

Label	CEF Label	Type	Usage
showStr	reason	Text	Code specifying reason for allowing access, if any

Message ID : POL4516F

Label	CEF Label	Type	Usage

## Description

None

## Message ID : POL4530F

## Severity

Fatal error

## Long Form

Global restore header invalid. Data corruption has possibly occurred. The restore operation will fail.

## Short Form

Global restore header invalid

## Parameters

No parameters are provided for this message type

## Description

None

Message ID : POL4528F

## **Message ID : POL4545F**

### **Severity**

Fatal error

### **Long Form**

Restore failed: Backup image created with future version.

### **Short Form**

Restore fail - future image

### **Parameters**

No parameters are provided for this message type

### **Description**

None

## **Message ID : POL4564F**

### **Severity**

Fatal error

## Long Form

The agent could not allocate enough memory. Contact support.

## Short Form

Out of memory

### Parameters

No parameters are provided for this message type

## Description

None

## Message ID : POL4581F

## Severity

Fatal error

## Long Form

Fatal error while evaluating policy to perform {0} for hostname {1}. Server name is {2}, server number {3}, object id {4}. The timestamp is {5}. The request protocol version is {6}.



## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : POL4593F**

## **Severity**

Fatal error

## **Long Form**

The agent could not evaluate policy. Contact support.

## **Short Form**

Cannot eval policy

## **Parameters**

No parameters are provided for this message type

## Description

None

## Message ID : POL4614F

## Severity

Fatal error

## Long Form

Fatal error while evaluating policy to perform {0} for hostname {1}. Server name is {2}, server number {3}. The timestamp is {4}. The request protocol version is {5}.

## Short Form

Policy eval error

## Parameters

Label	CEF Label	Type	Usage
act	act	Text	Action being requested or performed
shost	shost	Text	Source host name
dbinstance	vds_dbinstance	Text	Database instance
dbpart	vds_dbpart	Numeric	Database partition

<b>Label</b>	<b>CEF Label</b>	<b>Type</b>	<b>Usage</b>
rt	rt	Text	Time of event
version	vds_version	Text	Software version string

## **Description**

None

# Logger POL: Information

**Message ID : POL0142I**

## Severity

Information

## Long Form

The Security Server received a request from an unrecognized host ({}). The request will be denied.

## Short Form

request from unrecognized host

## Parameters

No parameters are provided for this message type

## Description

None

**Message ID : POL0143I**

## Severity

Information

## Long Form

The Security Server could not find any matching policies for the host ({}). The request will be denied.

## Short Form

could not find matching policies for host

### Parameters

Label	CEF Label	Type	Usage
shost	shost	Text	Source host name

## Description

None

**Message ID : POL0144I**

## Severity

Information

Message ID : POL0143I

## Long Form

The Security Server matched policy ({0}) and rule ({1}) for the {2} request from host ({3}), the database instance {4}, alias {5} and partition {6}.

## Short Form

matched policy/rule from host

### Parameters

Label	CEF Label	Type	Usage
pol	cs1	Text	Policy name
rule	vds_rule	Text	Name of policy rule set
act	act	Text	Action being requested or performed
shost	shost	Text	Source host name
dbinstance	vds_dbinstance	Text	Database instance
dbalias	vds_dbalias	Text	Database alias
dbpart	vds_dbpart	Numeric	Database partition

## Description

None

## Message ID : POL0145I

### Severity

Information

### Long Form

The Security Server could not match any policies for the {0} request from host ({1}), the database instance {2}, alias {3} and partition {4}. The request will be denied.

### Short Form

request denied

### Parameters

Label	CEF Label	Type	Usage
act	act	Text	Action being requested or performed
shost	shost	Text	Source host name
dbinstance	vds_dbinstance	Text	Database instance
dbalias	vds_dbalias	Text	Database alias
dbpart	vds_dbpart	Numeric	Database partition

## Description

None

## Message ID : POL0146I

## Severity

Information

## Long Form

The Security Server matched policy ({0}) for the {2} request from host ({3}), database instance {4}, alias {5} and partition {6}. But the policy did not contain any {1} rules. The request will be denied.

## Short Form

policy contains no rules

## Parameters

Label	CEF Label	Type	Usage
pol	cs1	Text	Policy name
act	act	Text	Action being requested or performed
shost	shost	Text	Source host name
dbinstance	vds_dbinstance	Text	Database instance



Label	CEF Label	Type	Usage
dbalias	vds_dbalias	Text	Database alias
dbpart	vds_dbpart	Numeric	Database partition
rt	rt	Text	Time of event
etime	end	Text	An end time stamp

## Description

None

## Message ID : POL0147I

## Severity

Information

## Long Form

The Security Server matched rule ({0}) to the {1} request for host {2}, database instance {3}, alias {4} and partition {5}. But, the request time {6} is after the end time {7} in the Rule. The rule will not be applied.

## Short Form

request time after end time

## Parameters

Label	CEF Label	Type	Usage
rule	vds_rule	Text	Name of policy rule set
act	act	Text	Action being requested or performed
shost	shost	Text	Source host name
dbinstance	vds_dbinstance	Text	Database instance
dbalias	vds_dbalias	Text	Database alias
dbpart	vds_dbpart	Numeric	Database partition
rt	rt	Text	Time of event
etime	end	Text	An end time stamp

## Description

None

**Message ID : POL0148I**

## Severity

Information

Message ID : POL0147I

1529

## Long Form

The Security Server matched rule ({0}) to the {1} request for host {2}, database instance {3}, alias {4} and partition {5}. But, the request time {6} is before the start time {7} in the Rule. The rule will not be applied.

## Short Form

request time before start time

### Parameters

Label	CEF Label	Type	Usage
rule	vds_rule	Text	Name of policy rule set
act	act	Text	Action being requested or performed
shost	shost	Text	Source host name
dbinstance	vds_dbinstance	Text	Database instance
dbalias	vds_dbalias	Text	Database alias
dbpart	vds_dbpart	Numeric	Database partition
rt	rt	Text	Time of event
stime	start	Text	A start time stamp

## Description

None

# Message ID : POL0149I

## Severity

Information

## Long Form

The Security Server matched rule ({0}) to the {1} request for host {2}, database instance {3}, alias {4} and partition {5}. But the conditions do not match. The rule will not be applied.

## Short Form

conditions do not match

## Parameters

Label	CEF Label	Type	Usage
rule	vds_rule	Text	Name of policy rule set
act	act	Text	Action being requested or performed
shost	shost	Text	Source host name
dbinstance	vds_dbinstance	Text	Database instance
dbalias	vds_dbalias	Text	Database alias
dbpart	vds_dbpart	Numeric	Database partition

## Description

None

**Message ID : POL0150I**

## Severity

Information

## Long Form

The Security Server matched policy ({0}) and rule ({1}) for the {2} request from host ({3}), the server name {4} and Server Number {6}.

## Short Form

No short form is provided for this message type

## Description

None

**Message ID : POL0151I**

## Severity

Information

## Long Form

The Security Server could not match any policies for the {0} request from host ({1}), the server name {2} and Server Number {4}. The request will be denied.

## Short Form

No short form is provided for this message type

## Description

None

## Message ID : POL0152I

## Severity

Information

## Long Form

The Security Server matched policy ({0}) for the {2} request from host ({3}), server name {4} and Server Number {6}. But the policy did not contain any {1} rules. The request will be denied.

Message ID : POL0151I

1533

## Short Form

No short form is provided for this message type

## Description

None

## Message ID : POL0153I

## Severity

Information

## Long Form

The Security Server matched rule ({0}) to the {1} request for host {2}, server name {3} and Server Number {5}. But, the request time {6} is after the end time {7} in the Rule. The rule will not be applied.

## Short Form

No short form is provided for this message type

## Description

None

Message ID : POL0152I

1534

## **Message ID : POL0154I**

### **Severity**

Information

### **Long Form**

The Security Server matched rule ({0}) to the {1} request for host {2}, server name {3} and Server Number {5}. But, the request time {6} is before the start time {7} in the Rule. The rule will not be applied.

### **Short Form**

No short form is provided for this message type

### **Description**

None

## **Message ID : POL0155I**

### **Severity**

Information



## Long Form

The Security Server matched rule ({0}) to the {1} request for host {2}, server name {3} and Server Number {5}. But the conditions do not match. The rule will not be applied

## Short Form

No short form is provided for this message type

## Description

None

## Message ID : POL4537I

## Severity

Information

## Long Form

ACCESS GRANTED on request to {0} database {1}, on hostname {2}. Instance name is {3}, partition {4}, catnode {5}. The timestamp is {6}, and the DB2 version is {7}. The request protocol version is {8}.

## Short Form

Access granted

## Parameters

Label	CEF Label	Type	Usage
act	act	Text	Action being requested or performed
dbname	vds_dbname	Text	Database name
shost	shost	Text	Source host name
dbinstance	vds_dbinstance	Text	Database instance
dbpart	vds_dbpart	Numeric	Database partition
node	vds_node	Numeric	A node identifier
rt	rt	Text	Time of event
dbver	vds_dbver	Numeric	Database version
version	vds_version	Text	Software version string

## Description

None

## Message ID : POL4553I

## Severity

Information

Message ID : POL4537I

## **Long Form**

Internal initialization successful.

## **Short Form**

SDK Init OK

### **Parameters**

No parameters are provided for this message type

## **Description**

None

**Message ID : POL4573I**

## **Severity**

Information

## **Long Form**

Backup failed.

## Short Form

Backup fail

### Parameters

No parameters are provided for this message type

## Description

None

**Message ID : POL4574I**

## Severity

Information

## Long Form

Restore failed.

## Short Form

Restore fail

### **Parameters**

No parameters are provided for this message type

### **Description**

None

**Message ID : POL4575I**

### **Severity**

Information

### **Long Form**

Backup completed successfully.

### **Short Form**

Backup complete OK

### **Parameters**

No parameters are provided for this message type

Message ID : POL4574I

1540

## **Description**

None

**Message ID : POL4576I**

## **Severity**

Information

## **Long Form**

Restore completed successfully.

## **Short Form**

Restore complete OK

## **Parameters**

No parameters are provided for this message type

## **Description**

None

Message ID : POL4575I

## **Message ID : POL4582I**

### **Severity**

Information

### **Long Form**

ACCESS GRANTED on request to perform {0} for hostname {1}. Server name is {2}, server number {3}, object id {4}. The timestamp is {5}. The request protocol version is {6}.

### **Short Form**

No short form is provided for this message type

### **Description**

None

## **Message ID : POL4615I**

### **Severity**

Information

## Long Form

ACCESS GRANTED on request to perform {0} for hostname {1}. Server name is {2}, server number {3}. The timestamp is {4}. The request protocol version is {5}.

## Short Form

Access granted

### Parameters

Label	CEF Label	Type	Usage
act	act	Text	Action being requested or performed
shost	shost	Text	Source host name
dbinstance	vds_dbinstance	Text	Database instance
dbpart	vds_dbpart	Numeric	Database partition
rt	rt	Text	Time of event
version	vds_version	Text	Software version string

## Description

None



## Message ID : POL4702I

### Severity

Information

### Long Form

EVENT: {0}

### Short Form

Event

### Parameters

Label	CEF Label	Type	Usage
showStr	reason	Text	Code specifying reason for allowing access, if any

### Description

None

# Logger POL: Warnings

**Message ID : POL4703W**

## Severity

Warning

## Long Form

EVENT: {0}

## Short Form

Event

### Parameters

Label	CEF Label	Type	Usage
showStr	reason	Text	Code specifying reason for allowing access, if any

## Description

None

## **Logger SDK: Errors**

**Message ID : SDK0197E**

### **Severity**

Error

### **Long Form**

Host "{0}" is unknown to the Management Server.

### **Short Form**

No short form is provided for this message type

### **Description**

None

**Message ID : SDK0198E**

### **Severity**

Error

## Long Form

Host Group "{0}" is unknown to the Management Server.

## Short Form

No short form is provided for this message type

## Description

None

## Message ID : SDK0199E

## Severity

Error

## Long Form

Unable to guard "{0}" on host "{1}" because a GuardPoint with a nested guard path exists.

## Short Form

No short form is provided for this message type

## **Description**

None

**Message ID : SDK0200E**

## **Severity**

Error

## **Long Form**

Unable to guard "{0}" on host group "{1}" because a GuardPoint with a nested guard path exists.

## **Short Form**

No short form is provided for this message type

## **Description**

None

**Message ID : SDK0201E**

## **Severity**

Error

Message ID : SDK0199E

## Long Form

GuardPoint "{0}" with policy "{1}" was created on host "{2}". It was disabled because the same path is already guarded.

## Short Form

No short form is provided for this message type

## Description

None

## Message ID : SDK0202E

## Severity

Error

## Long Form

GuardPoint "{0}" with policy "{1}" was created on host group "{2}". It was disabled because the same path is already guarded.

## Short Form

No short form is provided for this message type

## **Description**

None

**Message ID : SDK0203E**

## **Severity**

Error

## **Long Form**

Unable to guard "{0}" on host "{1}" because a GuardPoint with the same guard path and the same policy is already defined.

## **Short Form**

No short form is provided for this message type

## **Description**

None

**Message ID : SDK0204E**

## **Severity**

Error

Message ID : SDK0202E

## Long Form

Unable to guard "{0}" on host group "{1}" because a GuardPoint with the same guard path and the same policy is already defined.

## Short Form

No short form is provided for this message type

## Description

None

## Message ID : SDK0205E

## Severity

Error

## Long Form

GuardPoint "{0}" on host "{1}" is unknown to the Management Server.

## Short Form

No short form is provided for this message type



## **Description**

None

**Message ID : SDK0206E**

## **Severity**

Error

## **Long Form**

GuardPoint "{0}" on host group "{1}" is unknown to the Management Server.

## **Short Form**

No short form is provided for this message type

## **Description**

None

**Message ID : SDK0207E**

## **Severity**

Error

Message ID : SDK0205E

## Long Form

Unable to guard "{0}" on host "{1}" because the same path or a nested path has already been guarded.

## Short Form

No short form is provided for this message type

## Description

None

## Message ID : SDK0208E

## Severity

Error

## Long Form

Unable to guard "{0}" on host group "{1}" because the same path or a nested path has already been guarded.

## Short Form

No short form is provided for this message type

## **Description**

None

**Message ID : SDK0283E**

## **Severity**

Error

## **Long Form**

Unable to process host security update because the update time "{0}" on host "{1}" is less than the latest security update time.

## **Short Form**

No short form is provided for this message type

## **Description**

None

**Message ID : SDK0284E**

## **Severity**

Error

Message ID : SDK0208E

## **Long Form**

Unable to process host security update because host "{0}" is already in PENDING status.

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : SDK0286E**

## **Severity**

Error

## **Long Form**

Unable to process host security update because host "{0}" 's status is already updated.

## **Short Form**

No short form is provided for this message type

**Description**

None

**Message ID : SDK0403E****Severity**

Error

**Long Form**

The domain "{0}" does not exist in the server database.

**Short Form**

No short form is provided for this message type

**Description**

None

**Message ID : SDK0407E****Severity**

Error

Message ID : SDK0286E

## Long Form

The user "{0}" is not in the domain "{1}".

## Short Form

No short form is provided for this message type

## Description

None

## Message ID : SDK0408E

## Severity

Error

## Long Form

There is more than one remaining user assigned to domain "{0}". The domain cannot be deleted. Ensure that there is only one remaining user in the domain before deleting the domain.

## Short Form

No short form is provided for this message type

## **Description**

None

**Message ID : SDK0410E**

## **Severity**

Error

## **Long Form**

Unable to switch domain "{0}". You are either not in the domain or are disabled in the domain.

## **Short Form**

No short form is provided for this message type

## **Description**

None

**Message ID : SDK0411E**

## **Severity**

Error

Message ID : SDK0408E

## Long Form

Host "{0}" is no longer shared with the domain "{1}".

## Short Form

No short form is provided for this message type

## Description

None

## Message ID : SDK0416E

## Severity

Error

## Long Form

Host Group "{0}" is no longer shared with the domain "{1}".

## Short Form

No short form is provided for this message type



## **Description**

None

**Message ID : SDK0417E**

## **Severity**

Error

## **Long Form**

Unable to stop guarding "{0}" on host "{1}" because the path is guarded by another domain.

## **Short Form**

No short form is provided for this message type

## **Description**

None

**Message ID : SDK0418E**

## **Severity**

Error

Message ID : SDK0416E

## Long Form

Unable to stop guarding "{0}" on host group "{1}" because the path is guarded by another domain.

## Short Form

No short form is provided for this message type

## Description

None

## Message ID : SDK0419E

## Severity

Error

## Long Form

Unable to guard "{0}" on host "{1}" because the path is guarded by another domain.

## Short Form

No short form is provided for this message type

## **Description**

None

**Message ID : SDK0420E**

## **Severity**

Error

## **Long Form**

Unable to guard "{0}" on host group "{1}" because the path is guarded by another domain.

## **Short Form**

No short form is provided for this message type

## **Description**

None

**Message ID : SDK0421E**

## **Severity**

Error

Message ID : SDK0419E

## Long Form

Unable to enable/disable GuardPoint "{0}" on host "{1}" because the path is guarded by another domain.

## Short Form

No short form is provided for this message type

## Description

None

## Message ID : SDK0422E

## Severity

Error

## Long Form

Unable to enable/disable GuardPoint "{0}" on host group "{1}" because the path is guarded by another domain.

## Short Form

No short form is provided for this message type

## **Description**

None

**Message ID : SDK0423E**

## **Severity**

Error

## **Long Form**

Host "{0}" cannot join host group "{1}" because the host does not support CBC\_CS1.

## **Short Form**

No short form is provided for this message type

## **Description**

None

**Message ID : SDK0427E**

## **Severity**

Error

Message ID : SDK0422E

## Long Form

Domain name "{0}" is already in use. Specify a different name.

## Short Form

No short form is provided for this message type

## Description

None

## Message ID : SDK0437E

## Severity

Error

## Long Form

Host "{0}" is already shared with domain "{1}".

## Short Form

No short form is provided for this message type

## Description

None

**Message ID : SDK0438E**

## Severity

Error

## Long Form

There are {0} policies remaining in domain {1}, therefore, the domain cannot be deleted. Delete all remaining policies before deleting the domain.

## Short Form

No short form is provided for this message type

## Description

None

**Message ID : SDK0439E**

## Severity

Error

## Long Form

There are {0} hosts remaining in domain {1}, therefore, the domain cannot be deleted. Delete all remaining hosts before deleting the domain.

## Short Form

No short form is provided for this message type

## Description

None

## Message ID : SDK0440E

## Severity

Error

## Long Form

There are {0} agent keys and/or vault keys remaining in domain {1}, therefore, the domain cannot be deleted. Delete all remaining keys before deleting the domain.

Message ID : SDK0439E

1567



## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : SDK0441E**

## **Severity**

Error

## **Long Form**

There are {0} host groups remaining in domain {1}, therefore, the domain cannot be deleted. Delete all remaining host groups before deleting the domain.

## **Short Form**

No short form is provided for this message type

## **Description**

None

Message ID : SDK0440E

1568

## **Message ID : SDK0442E**

### **Severity**

Error

### **Long Form**

There are {0} key groups remaining in domain {1}, therefore, the domain cannot be deleted. Delete all remaining key groups before deleting the domain.

### **Short Form**

No short form is provided for this message type

### **Description**

None

## **Message ID : SDK0443E**

### **Severity**

Error

## Long Form

SysLog Host name "{0}" is already in use. Specify a different name.

## Short Form

No short form is provided for this message type

## Description

None

## Message ID : SDK0444E

## Severity

Error

## Long Form

SysLog Host "{0}" does not exist.

## Short Form

No short form is provided for this message type

## **Description**

None

**Message ID : SDK0447E**

## **Severity**

Error

## **Long Form**

Host Group Id "{0}" does not belong to Domain ID "{1}".

## **Short Form**

No short form is provided for this message type

## **Description**

None

**Message ID : SDK0450E**

## **Severity**

Error

Message ID : SDK0444E

## Long Form

RSA user name is in use "{0}"

## Short Form

No short form is provided for this message type

## Description

None

## Message ID : SDK0451E

## Severity

Error

## Long Form

OTP record not found for OTP device "{0}"

## Short Form

No short form is provided for this message type

Message ID : SDK0450E

**Description**

None

**Message ID : SDK0503E**

**Severity**

Error

**Long Form**

Unable to share host "{0}" with own domain "{1}".

**Short Form**

No short form is provided for this message type

**Description**

None

**Message ID : SDK0504E**

**Severity**

Error

Message ID : SDK0451E

## Long Form

Unable to share host group "{0}" with own domain "{1}".

## Short Form

No short form is provided for this message type

## Description

None

## Message ID : SDK0505E

## Severity

Error

## Long Form

Host group "{0}" is already shared with domain "{1}".

## Short Form

No short form is provided for this message type

## **Description**

None

**Message ID : SDK0517E**

## **Severity**

Error

## **Long Form**

Unable to update domain level. Invalid domain level.

## **Short Form**

No short form is provided for this message type

## **Description**

None

**Message ID : SDK0525E**

## **Severity**

Error

Message ID : SDK0505E



## **Long Form**

The Security Server was unable to backup the configuration. Check the logs.

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : SDK0526E**

## **Severity**

Error

## **Long Form**

The Security Server was unable to restore the configuration. Check the logs.

## **Short Form**

No short form is provided for this message type

## **Description**

None

**Message ID : SDK0533E**

## **Severity**

Error

## **Long Form**

There are {0} syslog servers remaining in domain {1}, therefore, the domain cannot be deleted. Delete all remaining syslog servers before deleting the domain.

## **Short Form**

No short form is provided for this message type

## **Description**

None

**Message ID : SDK0534E**

## Severity

Error

## Long Form

Guard path "{0}" is not allowed on host or host group "{1}".

## Short Form

No short form is provided for this message type

## Description

None

## Message ID : SDK0608E

## Severity

Error

## Long Form

Host "{0}" is already in host group "{1}".

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : SDK0630E**

## **Severity**

Error

## **Long Form**

The Security Server was unable to perform the action. Check the logs.

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : SDK0637E**

### **Severity**

Error

### **Long Form**

Operation failed. The Security Server is busy, retry later.

### **Short Form**

No short form is provided for this message type

### **Description**

None

## **Message ID : SDK0662E**

### **Severity**

Error

### **Long Form**

Invalid host password challenge input.

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : SDK0663E**

## **Severity**

Error

## **Long Form**

Challenge Response is not supported by host "{0}".

## **Short Form**

No short form is provided for this message type

## **Description**

None

## Message ID : SDK0664E

### Severity

Error

### Long Form

Administrator "{0}" failed to generate host password response for host "{1}".

### Short Form

failed to generate host password response

### Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
shost	shost	Text	Source host name

### Description

None

## **Message ID : SDK0670E**

### **Severity**

Error

### **Long Form**

Agent for the host with id {0} and the agent type "{1}" is unknown to the Management Server.

### **Short Form**

No short form is provided for this message type

### **Description**

None

## **Message ID : SDK0671E**

### **Severity**

Error

### **Long Form**

Host IP "{0}" already exists.



## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : SDK0716E**

## **Severity**

Error

## **Long Form**

SMTP server already defined.

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : SDK0717E**

### **Severity**

Error

### **Long Form**

SMTP server not found.

### **Short Form**

No short form is provided for this message type

### **Description**

None

## **Message ID : SDK0718E**

### **Severity**

Error

### **Long Form**

Email notification group with name "{0}" already defined in domain.

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : SDK0719E**

## **Severity**

Error

## **Long Form**

Email notification group with name "{0}" not defined in domain.

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : SDK0776E**

### **Severity**

Error

### **Long Form**

Host "{0}" cannot join this group because membership in a cluster host group is exclusive.

### **Short Form**

No short form is provided for this message type

### **Description**

None

## **Message ID : SDK0777E**

### **Severity**

Error

### **Long Form**

Host "{0}" has conflicting GuardPoint "{1}" and cannot join the cluster host group.

## Short Form

No short form is provided for this message type

## Description

None

## Message ID : SDK0778E

## Severity

Error

## Long Form

The selected guard policy "{0}" is inherited from cluster host group "{1}". It can only be disabled from host group "{2}".

## Short Form

No short form is provided for this message type

## Description

None

## **Message ID : SDK0780E**

### **Severity**

Error

### **Long Form**

The GuardPoint cannot be enabled because member host "{0}" has a conflicting GuardPoint.

### **Short Form**

No short form is provided for this message type

### **Description**

None

## **Message ID : SDK0800E**

### **Severity**

Error

### **Long Form**

Cannot add an SSL syslog server without certificates.

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : SDK0801E**

## **Severity**

Error

## **Long Form**

Invalid format in certificates file. Expecting PEM or DER encoded X.509 certificate(s).

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : SDK1237E**

### **Severity**

Error

### **Long Form**

The length of the domain name "{0}" cannot exceed 64 characters.

### **Short Form**

No short form is provided for this message type

### **Description**

None

## **Message ID : SDK1238E**

### **Severity**

Error

### **Long Form**

Unrecognized certificate format, use only supported formats.



## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : SDK1239E**

## **Severity**

Error

## **Long Form**

Unable to import the certificate.

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : SDK1240E**

### **Severity**

Error

### **Long Form**

Unable to import the private key.

### **Short Form**

No short form is provided for this message type

### **Description**

None

## **Message ID : SDK1241E**

### **Severity**

Error

### **Long Form**

Unable to find the certificate with id"{0}".

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : SDK1242E**

## **Severity**

Error

## **Long Form**

Unable to export certificates.

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : SDK1243E**

### **Severity**

Error

### **Long Form**

Unable to delete certificates.

### **Short Form**

No short form is provided for this message type

### **Description**

None

## **Message ID : SDK1256E**

### **Severity**

Error

### **Long Form**

Invalid Enhanced Usage specified.

## Short Form

No short form is provided for this message type

## Description

None

## Message ID : SDK1262E

## Severity

Error

## Long Form

Dropped {0} syslog message(s) due to connectivity issue of syslog server "{1}" .

## Short Form

No short form is provided for this message type

## Description

None

Message ID : SDK1256E

## **Message ID : SDK1296E**

### **Severity**

Error

### **Long Form**

Unable to import error while reading the certificate: {0}.

### **Short Form**

No short form is provided for this message type

### **Description**

None

## **Message ID : SDK1315E**

### **Severity**

Error

### **Long Form**

Vaulting certificate is not supported for GDE DSM.

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : SDK1324E**

## **Severity**

Error

## **Long Form**

Your current license does not support certificate vaulting.

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : SDK1340E**

### **Severity**

Error

### **Long Form**

GuardPoint policy "{0}" not found on host group "{1}"

### **Short Form**

No short form is provided for this message type

### **Description**

None

## **Message ID : SDK1365E**

### **Severity**

Error

### **Long Form**

GuardPoint "{0}" not found for policy "{1}" on host "{2}"



## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : SDK1385E**

## **Severity**

Error

## **Long Form**

{0} is enabled for host {1}, therefore, it cannot be disabled.

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : SDK1386E**

### **Severity**

Error

### **Long Form**

{0} is not supported for {1} host {2}

### **Short Form**

No short form is provided for this message type

### **Description**

None

## **Message ID : SDK1387E**

### **Severity**

Error

### **Long Form**

{0} not supported for host {1}.

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : SDK1388E**

## **Severity**

Error

## **Long Form**

Cannot set GuardPoint, docker not enabled on host {0}

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : SDK1389E**

### **Severity**

Error

### **Long Form**

Signature {} cannot be associated with docker. It is associated with host.

### **Short Form**

No short form is provided for this message type

### **Description**

None

## **Message ID : SDK1390E**

### **Severity**

Error

### **Long Form**

Cannot modify docker identifier associated with the Signature {}.

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : SDK1391E**

## **Severity**

Error

## **Long Form**

LDT QoS Schedule {0} conflicts with another schedule {1}.

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : SDK1407E**

### **Severity**

Error

### **Long Form**

Deleting host "{0}" with registered VDE agent is not allowed

### **Short Form**

No short form is provided for this message type

### **Description**

None

## **Message ID : SDK1426E**

### **Severity**

Error

### **Long Form**

Unable to delete host in domain "{0}" from domain "{1}".

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : SDK1504E**

## **Severity**

Error

## **Long Form**

Failed to contact agent on Host {0}. Host cannot be deleted

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : SDK1508E**

### **Severity**

Error

### **Long Form**

Cannot delete Host {0}. Stop guarding/disable GuardPoints associated with the LDT policy before deleting the host.

### **Short Form**

No short form is provided for this message type

### **Description**

None

## **Message ID : SDK1513E**

### **Severity**

Error

### **Long Form**

Concise logging feature is not supported for host {0}.



## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : SDK1550E**

## **Severity**

Error

## **Long Form**

Cert-Chain is not valid

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : SDK1553E**

### **Severity**

Error

### **Long Form**

Could not restart the KMIP server

### **Short Form**

No short form is provided for this message type

### **Description**

None

## **Message ID : SDK1554E**

### **Severity**

Error

### **Long Form**

Could not update trusted ca's for the KMIP server.

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : SDK1558E**

## **Severity**

Error

## **Long Form**

Upload a certificate which is issued by trusted CA

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : SDK1564E**

### **Severity**

Error

### **Long Form**

Certificate is not valid

### **Short Form**

No short form is provided for this message type

### **Description**

None

## **Message ID : SDK1565E**

### **Severity**

Error

### **Long Form**

Certificate {0} is a non-ca certificate, it does not have basic constraints

## Short Form

No short form is provided for this message type

## Description

None

## Message ID : SDK1566E

## Severity

Error

## Long Form

Certificate {0} certificate cannot be verified with its issuer {1}

## Short Form

No short form is provided for this message type

## Description

None

## **Message ID : SDK1567E**

### **Severity**

Error

### **Long Form**

Certificate's common name {0} does not match with the hostname {1}

### **Short Form**

No short form is provided for this message type

### **Description**

None

## **Message ID : SDK1568E**

### **Severity**

Error

### **Long Form**

Certificate {0} is not issued by trusted CA

## Short Form

No short form is provided for this message type

## Description

None

## Message ID : SDK1617E

## Severity

Error

## Long Form

Host "{0}" is not in HostGroup "{1}".

## Short Form

No short form is provided for this message type

## Description

None

## **Message ID : SDK1619E**

### **Severity**

Error

### **Long Form**

Cannot enable both LDT and Docker on a host {0}.

### **Short Form**

No short form is provided for this message type

### **Description**

None

## **Message ID : SDK1620E**

### **Severity**

Error

### **Long Form**

Host {0} is not approved for this operation yet.



## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : SDK1621E**

## **Severity**

Error

## **Long Form**

Agent Lock and System Lock settings combination is not valid. Refer to the documentation for details.

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : SDK1622E**

### **Severity**

Error

### **Long Form**

"Communication Enabled" cannot be set to true if "Registration Allowed" is disabled or set to false.

### **Short Form**

No short form is provided for this message type

### **Description**

None

## **Message ID : SDK1623E**

### **Severity**

Error

### **Long Form**

System Lock can not be enabled if the FA Agent Lock is disabled. Refer to the documentation for details.

## Short Form

No short form is provided for this message type

## Description

None

## Message ID : SDK1649E

## Severity

Error

## Long Form

Host "{0}" cannot join host group "{1}" because the host does not support RekeyRate.

## Short Form

No short form is provided for this message type

## Description

None

## **Message ID : SDK1652E**

### **Severity**

Error

### **Long Form**

Certificate is rejected. This certificate has no client authentication issued by trusted CA.

### **Short Form**

No short form is provided for this message type

### **Description**

None

## **Message ID : SDK1654E**

### **Severity**

Error

### **Long Form**

Unable to process GuardPoint "{0}" creation because the same GuardPoint "{0}" still exists with status: PENDING, in host "{1}".  
Try again later.

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : SDK1655E**

## **Severity**

Error

## **Long Form**

Host sharing is not allowed for this host agent.

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : SDK1660E**

### **Severity**

Error

### **Long Form**

The domain {1} still contains {0} user identity object(s), which need to be deleted before the domain can be deleted.

### **Short Form**

No short form is provided for this message type

### **Description**

None

## **Message ID : SDK1663E**

### **Severity**

Error

### **Long Form**

Host group "{0}" cannot change settings because one of the hosts does not support RekeyRate.

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : SDK1668E**

## **Severity**

Error

## **Long Form**

Unable to import some or all keys from an export file. Check logs or contact support.

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : SDK1671E**

### **Severity**

Error

### **Long Form**

There are {0} GuardPoints remaining in host group {1}, therefore, the host group cannot be deleted. Remove all remaining GuardPoints before deleting the host group.

### **Short Form**

No short form is provided for this message type

### **Description**

None

## **Message ID : SDK1672E**

### **Severity**

Error



## Long Form

There are {0} hosts remaining in host group {1}, therefore, the host group cannot be deleted. Remove all remaining hosts before deleting the host group.

## Short Form

No short form is provided for this message type

## Description

None

## Message ID : SDK1683E

## Severity

Error

## Long Form

Host "{0}" cannot join host group "{1}" because the host does not support {2}.

## Short Form

No short form is provided for this message type

## **Description**

None

**Message ID : SDK1706E**

## **Severity**

Error

## **Long Form**

Certificate with subject DN "{0}" is a {1} certificate which is not supported in {2} mode.

## **Short Form**

No short form is provided for this message type

## **Description**

None

**Message ID : SDK1718E**

## **Severity**

Error

Message ID : SDK1683E

## Long Form

Cloud Object Storage is not enabled for Host "{0}". The DSM cannot join the cluster host group "{1}" because it contains existing Cloud Object Storage GuardPoints.

## Short Form

No short form is provided for this message type

## Description

None

## Message ID : SDK1731E

## Severity

Error

## Long Form

Guard path "{0}" can not exceed 64 bytes on host or host group "{1}".

## Short Form

No short form is provided for this message type

**Description**

None

**Message ID : SDK1742E****Severity**

Error

**Long Form**

"{0}" is not a valid Cloud Object Storage type guard path.

**Short Form**

No short form is provided for this message type

**Description**

None

**Message ID : SDK1746E****Severity**

Error

Message ID : SDK1731E

## **Long Form**

Secure Start must be enabled if Raw or Block Device is selected.

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : SDK1747E**

## **Severity**

Error

## **Long Form**

Efficient Storage feature must be enabled if Raw or Block Device is selected.

## **Short Form**

No short form is provided for this message type

**Description**

None

**Message ID : SDK1760E**

**Severity**

Error

**Long Form**

Host Group GuardPoint policy "{0}" not found.

**Short Form**

No short form is provided for this message type

**Description**

None

**Message ID : SDK1761E**

**Severity**

Error

Message ID : SDK1747E

## Long Form

Host "{0}" does not support GuardPoint for LDT Policy "{1}" with Raw Device.

## Short Form

No short form is provided for this message type

## Description

None

## Message ID : SDK1769E

## Severity

Error

## Long Form

Cannot create "{0}" GuardPoint for COS with "{1}" Policy. The same GuardPoint already exists and is enabled with another policy either in the current or in another domain. The DSM allows exactly one COS GuardPoint to be enabled per S3 bucket.

## Short Form

No short form is provided for this message type

## **Description**

None

**Message ID : SDK1770E**

## **Severity**

Error

## **Long Form**

Cannot enable "{0}" GuardPoint for COS with "{1}" Policy. The same GuardPoint is already enabled with another policy either in the current or in another domain. The DSM allows exactly one COS GuardPoint to be enabled per S3 bucket.

## **Short Form**

No short form is provided for this message type

## **Description**

None

**Message ID : SDK1795E**



## **Severity**

Error

## **Long Form**

GuardPath must follow "Windows" format and it is applicable for Windows agent only if embedded header field is enabled.

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : SDK1796E**

## **Severity**

Error

## **Long Form**

GuardPointType must be "AUTO\_GUARD\_DIRECTORY" if embedded header field is enabled.

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : SDK1797E**

## **Severity**

Error

## **Long Form**

Policy must be of "LDT" type if embedded field is enabled.

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : SDK1798E**

### **Severity**

Error

### **Long Form**

CIFS share credential already exist for user name "{0}" and user domain "{1}".

### **Short Form**

No short form is provided for this message type

### **Description**

None

## **Message ID : SDK1801E**

### **Severity**

Error

### **Long Form**

CIFS share credential does not exist for credential "{0}".

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : SDK1802E**

## **Severity**

Error

## **Long Form**

Unable to create or update CIFS share credential. Please try again later.

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : SDK1803E**

### **Severity**

Error

### **Long Form**

CIFS share credential(s) requested for deletion are already in use.

### **Short Form**

No short form is provided for this message type

### **Description**

None

## **Message ID : SDK1807E**

### **Severity**

Error

### **Long Form**

CIFS share credential is mandatory if policy type is LDT, guard type is "AUTO\_GUARD\_DIRECTORY" and guard path is in CIFS share format.

## Short Form

No short form is provided for this message type

## Description

None

## Message ID : SDK1808E

## Severity

Error

## Long Form

If CIFS share credential is provided then policy type must be LDT, guard type must be "AUTO\_GUARD\_DIRECTORY" and guard path must be in CIFS share format.

## Short Form

No short form is provided for this message type

## Description

None

Message ID : SDK1807E

1637

## **Message ID : SDK1809E**

### **Severity**

Error

### **Long Form**

An internal error occurred on the Security Server. Refer to cgss.log and server.log for details. Call support if necessary.

### **Short Form**

No short form is provided for this message type

### **Description**

None

## **Message ID : SDK1811E**

### **Severity**

Error

### **Long Form**

There are {0} incompatible kernel version hosts in the domain. List of hosts and its status:"{1}".

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : SDK1812E**

## **Severity**

Error

## **Long Form**

The json package contains an invalid agent compatibility JSON signature.

## **Short Form**

No short form is provided for this message type

## **Description**

None



## **Message ID : SDK1814E**

### **Severity**

Error

### **Long Form**

RSA User ID [{0}] is in use by another user. Select a different User ID.

### **Short Form**

No short form is provided for this message type

### **Description**

None

## **Message ID : SDK1815E**

### **Severity**

Error

### **Long Form**

Unable to upload the compatibility list because it is the same list or not the current list. {0}.

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : SDK1817E**

## **Severity**

Error

## **Long Form**

Compatibility list upload failed. Unable to extract the files.

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : SDK1818E**

### **Severity**

Error

### **Long Form**

Uploaded compatibility list file has no data.

### **Short Form**

No short form is provided for this message type

### **Description**

None

## **Message ID : SDK1819E**

### **Severity**

Error

### **Long Form**

Unable to upload the compatibility list because the format of the date or time is not supported. {0}.

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : SDK1821E**

## **Severity**

Error

## **Long Form**

A Silo already exists for name "{0}".

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : SDK1822E**

### **Severity**

Error

### **Long Form**

A Silo does not exist with siloID "{0}".

### **Short Form**

No short form is provided for this message type

### **Description**

None

## **Message ID : SDK1823E**

### **Severity**

Error

### **Long Form**

A Silo does not exist with silo name "{0}".

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : SDK1824E**

## **Severity**

Error

## **Long Form**

Silo(s) requested for deletion are already in use.

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : SDK1829E**

### **Severity**

Error

### **Long Form**

You can only register a silo for a VTE agent that is enabled for LDT.

### **Short Form**

No short form is provided for this message type

### **Description**

None

## **Message ID : SDK1830E**

### **Severity**

Error

### **Long Form**

Administrator {0} is unable to upload the malicious compatibility list because it contains an invalid agent compatibility JSON signature.

## Short Form

No short form is provided for this message type

## Description

None

## Message ID : SDK1843E

## Severity

Error

## Long Form

Host "{0}" does not exist in the domain "{1}".

## Short Form

No short form is provided for this message type

## Description

None



## **Message ID : SDK1851E**

### **Severity**

Error

### **Long Form**

You can only enable Preferred LGS Primary for a VTE agent that is enabled for LDT.

### **Short Form**

No short form is provided for this message type

### **Description**

None

## **Message ID : SDK1852E**

### **Severity**

Error

### **Long Form**

Host "{0}" does not belong to any domain where user has access.

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : SDK1853E**

## **Severity**

Error

## **Long Form**

Signature Set with name "{0}" cannot be found in the domain.

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : SDK1854E**

### **Severity**

Error

### **Long Form**

Certificate file is mandatory and upload file key name must be fileCertificate.

### **Short Form**

No short form is provided for this message type

### **Description**

None

## **Message ID : SDK1855E**

### **Severity**

Error

### **Long Form**

Only one entry is allowed for fileCertificate key.

## Short Form

No short form is provided for this message type

## Description

None

## Message ID : SDK1856E

## Severity

Error

## Long Form

Only one entry is allowed for filePrivateKey key.

## Short Form

No short form is provided for this message type

## Description

None

## **Message ID : SDK1857E**

### **Severity**

Error

### **Long Form**

Invalid content of uploaded certificate file.

### **Short Form**

No short form is provided for this message type

### **Description**

None

## **Message ID : SDK1858E**

### **Severity**

Error

### **Long Form**

Invalid content of uploaded private key file.

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : SDK1859E**

## **Severity**

Error

## **Long Form**

Password is mandatory for PKCS12 format certificate.

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : SDK1860E**

### **Severity**

Error

### **Long Form**

Field "{0}" cannot be updated.#

### **Short Form**

No short form is provided for this message type

### **Description**

None

# Logger SDK: Information

**Message ID : SDK0544I**

## Severity

Information

## Long Form

Administrator "{0}" created a server backup key.

## Short Form

created server backup key

## Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name

## Description

None



## Message ID : SDK0545I

### Severity

Information

### Long Form

Administrator "{0}" imported a server backup key.

### Short Form

imported server backup key

### Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name

### Description

None

## Message ID : SDK0665I

## Severity

Information

## Long Form

Administrator "{0}" generated host password response for host "{1}" successfully.

## Short Form

generated host password response

### Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
shost	shost	Text	Source host name

## Description

None

**Message ID : SDK1551I**

## **Severity**

Information

## **Long Form**

Auth is on

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : SDK1552I**

## **Severity**

Information

## **Long Form**

Auth is off

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : SDK1555I**

## **Severity**

Information

## **Long Form**

Some or all of the certificates exist. Do you want to delete the following certificates?

## **Short Form**

No short form is provided for this message type

## **Description**

None

Message ID : SDK1552I

## **Message ID : SDK1556I**

### **Severity**

Information

### **Long Form**

There is no change in certificates

### **Short Form**

No short form is provided for this message type

### **Description**

None

## **Message ID : SDK1557I**

### **Severity**

Information

### **Long Form**

The client certificate is issued by trusted CA

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : SDK1559I**

## **Severity**

Information

## **Long Form**

The client certificate is not validated because there are no trusted ca's. There could be issues when trusted ca's are added in the future.

## **Short Form**

No short form is provided for this message type

## **Description**

None

Message ID : SDK1557I

1661

## **Message ID : SDK1560I**

### **Severity**

Information

### **Long Form**

No certificates are affected due to this operation.

### **Short Form**

No short form is provided for this message type

### **Description**

None

## **Message ID : SDK1561I**

### **Severity**

Information

### **Long Form**

Client certificate is self signed. It is accepted for now, however, it can create problems when trusted ca's are added in the future.

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : SDK1562I**

## **Severity**

Information

## **Long Form**

Certificate and its dependent certificates are deleted

## **Short Form**

No short form is provided for this message type

## **Description**

None



## **Message ID : SDK1563I**

### **Severity**

Information

### **Long Form**

Certificate is deleted

### **Short Form**

No short form is provided for this message type

### **Description**

None

## **Message ID : SDK1670I**

### **Severity**

Information

### **Long Form**

KMIP enabled on domain: {1}, by user {0}.

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : SDK1689I**

## **Severity**

Information

## **Long Form**

Host {0} already has FF1 enabled. Once FF1 is enabled, it cannot be disabled.

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : SDK1738I**

### **Severity**

Information

### **Long Form**

Cannot enable both {0} and {1} for host {2}.

### **Short Form**

No short form is provided for this message type

### **Description**

None

## **Message ID : SDK1799I**

### **Severity**

Information

### **Long Form**

CIFS share credential created for user name "{1}" and user domain "{2}" by administrator "{0}".

## Short Form

CIFS share credential created

### Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name

## Description

None

## Message ID : SDK1800I

## Severity

Information

## Long Form

CIFS share credential updated for user name "{1}" and user domain "{2}" by administrator "{0}".

## Short Form

CIFS share credential updated

Message ID : SDK1799I

1667

## Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name

## Description

None

## Message ID : SDK1810I

## Severity

Information

## Long Form

Administrator {0} successfully uploaded agent compatibility list JSON "{1}".

## Short Form

{0} {1} CEF:0|Vormetric, Inc.|dsm|{3}|SDK1805I|uploaded agent compatibility list ok|3|cs4Label=logger cs4=SDK spid={2} rt={4} dvchost={1}

### Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name

### Description

None

### Message ID : SDK1825I

### Severity

Information

### Long Form

Silo created for name "{0}" by administrator "{1}".

### Short Form

Silo created

### Parameters

Label	CEF Label	Type	Usage
-------	-----------	------	-------

Message ID : SDK1810I

user	suser	Text	User name
------	-------	------	-----------

## Description

None

## Message ID : SDK1826I

## Severity

Information

## Long Form

Silo updated for name "{0}" by administrator "{1}".

## Short Form

Silo updated

## Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name

Message ID : SDK1825I

1670

## Description

None

**Message ID : SDK1831I**

## Severity

Information

## Long Form

Silo deleted for name "{0}" by administrator "{1}".

## Short Form

Silo deleted

## Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name

## Description

None

Message ID : SDK1826I



## Message ID : SDK1833I

### Severity

Information

### Long Form

CIFS share credential deleted for user name "{1}" and user domain "{2}" by administrator "{0}".

### Short Form

CIFS share credential deleted

#### Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name

### Description

None

# Logger SDK: Warnings

**Message ID : SDK0290W**

## Severity

Warning

## Long Form

The following hosts could not be imported: "{0}". Check the import file format. The correct format is: hostname, description, password, allow\_fs\_agent, allow\_db2\_agent, allow\_ids\_agent, allow\_kmip\_agent. Do NOT include a header row. Also, make sure the host(s) do not already exist.

## Short Form

No short form is provided for this message type

## Description

None

**Message ID : SDK0583W**

## **Severity**

Warning

## **Long Form**

Current license has expired.

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : SDK0584W**

## **Severity**

Warning

## **Long Form**

The maximum number of servers allowed by the current license has been exceeded.

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : SDK0585W**

## **Severity**

Warning

## **Long Form**

The maximum number of agents allowed by the current license has been exceeded.

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : SDK0597W**

### **Severity**

Warning

### **Long Form**

Due to name or UUID/Identifier(s) conflicts, one or more of the imported key's names were appended with a number, or the UUIDs/Identifier(s) were regenerated.

### **Short Form**

No short form is provided for this message type

### **Description**

None

## **Message ID : SDK0779W**

### **Severity**

Warning

## Long Form

The new GuardPoint is added into cluster host group and disabled because member host "{0}" has a conflicting GuardPoint.

## Short Form

No short form is provided for this message type

## Description

None

## Message ID : SDK1336W

## Severity

Warning

## Long Form

Failed to create KMIP partition: {0}.

## Short Form

No short form is provided for this message type

## Description

None

**Message ID : SDK1338W**

## Severity

Warning

## Long Form

There are {0} signatures remaining in domain {1}, therefore, the domain cannot be deleted. Delete all remaining signatures before deleting the domain.

## Short Form

No short form is provided for this message type

## Description

None

**Message ID : SDK1368W**

## Severity

Warning

## Long Form

Failed to retrieve partition id for KMIP partition: {0}.

## Short Form

No short form is provided for this message type

## Description

None

## Message ID : SDK1390W

## Severity

Warning

## Long Form

There are {0} certificates remaining for the domain {1}, therefore, the domain cannot be deleted. Delete all remaining certificates for the domain before deleting the domain.



## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : SDK1616W**

## **Severity**

Warning

## **Long Form**

Only the current version of the key has been imported. Due to either a name or UUID/Identifier(s) conflict, the name of the key has been appended with a number, or the UUID/Identifier(s) has been regenerated.

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : SDK1617W**

### **Severity**

Warning

### **Long Form**

Only the current version of the key has been imported.

### **Short Form**

No short form is provided for this message type

### **Description**

None

## **Message ID : SDK1669W**

### **Severity**

Warning

### **Long Form**

Unable to enable KMIP: {0}.

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Logger SIN: Errors**

**Message ID : SIN0209E**

### **Severity**

Error

### **Long Form**

Error while signing the configuration file. The error may be due to invalid private key (or) error while updating data to be signed. Please check the log for more details.

### **Short Form**

No short form is provided for this message type

### **Description**

None

**Message ID : SIN0210E**

### **Severity**

Error

## **Long Form**

Internal Error. File creation failed. The error may be due to insufficient permissions for creating the file

## **Short Form**

No short form is provided for this message type

## **Description**

None

**Message ID : SIN0211E**

## **Severity**

Error

## **Long Form**

Unable to get Keypair

## **Short Form**

No short form is provided for this message type

Message ID : SIN0210E

## **Description**

None

**Message ID : SIN0212E**

## **Severity**

Error

## **Long Form**

Argument or must be supplied

## **Short Form**

No short form is provided for this message type

## **Description**

None

**Message ID : SIN0213E**

## **Severity**

Error

Message ID : SIN0211E

## **Long Form**

Argument need to specify atleast one file

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : SIN0214E**

## **Severity**

Error

## **Long Form**

Internal Error.

## **Short Form**

No short form is provided for this message type

## Description

None



# Logger SIN: Fatal errors

**Message ID : SIN0176F**

## Severity

Fatal error

## Long Form

The Security Server failed to start up due to a failed integrity check. One of the components "{0}" of the Security Server may have been manually altered. Please ensure that original software components of the Security Server are in place.

## Short Form

failed integrity check

### Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

## Description

None

## Message ID : SIN0177F

### Severity

Fatal error

### Long Form

The Security Server failed to start up due to a missing configuration file. The file "{0}" could not be found. Please ensure that original software components of the Security Server are in place.

### Short Form

missing configuration file

### Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

### Description

None

## Message ID : SIN0178F

## **Severity**

Fatal error

## **Long Form**

The Security Server failed to start up due to missing required steps needed for signing configuration files. Please ensure that all the required steps are completed.

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Logger USR: Errors**

**Message ID : USR0156E**

### **Severity**

Error

### **Long Form**

Invalid Username. A valid username should have at least 5 characters and at most 36 characters.

### **Short Form**

No short form is provided for this message type

### **Description**

None

**Message ID : USR0157E**

### **Severity**

Error

## **Long Form**

Invalid Password. A valid password should have at least 8 characters.

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : USR0158E**

## **Severity**

Error

## **Long Form**

User "{0}" cannot be deleted.

## **Short Form**

No short form is provided for this message type

## **Description**

None

**Message ID : USR0159E**

## **Severity**

Error

## **Long Form**

The password has expired or has been reset. The password needs to be changed.

## **Short Form**

No short form is provided for this message type

## **Description**

None

**Message ID : USR0160E**

## **Severity**

Error

Message ID : USR0158E

## **Long Form**

User name "{0}" does not exist.

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : USR0161E**

## **Severity**

Error

## **Long Form**

User Id "{0}" does not exist.

## **Short Form**

No short form is provided for this message type

## **Description**

None

**Message ID : USR0162E**

## **Severity**

Error

## **Long Form**

Password should contain at least one digit.

## **Short Form**

No short form is provided for this message type

## **Description**

None

**Message ID : USR0163E**

## **Severity**

Error

Message ID : USR0161E



## **Long Form**

Password should contain at least one alphabet.

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : USR0164E**

## **Severity**

Error

## **Long Form**

Invalid username/password.

## **Short Form**

No short form is provided for this message type

## **Description**

None

**Message ID : USR0165E**

## **Severity**

Error

## **Long Form**

User "{0}" does not have sufficient privileges for this operation.

## **Short Form**

No short form is provided for this message type

## **Description**

None

**Message ID : USR0166E**

## **Severity**

Error

Message ID : USR0164E

## **Long Form**

Roles for user "{0}" cannot be modified.

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : USR0168E**

## **Severity**

Error

## **Long Form**

Invalid one-time passcode.

## **Short Form**

No short form is provided for this message type

## **Description**

None

**Message ID : USR0169E**

## **Severity**

Error

## **Long Form**

Setup error in one-time passcode authentication server.

## **Short Form**

No short form is provided for this message type

## **Description**

None

**Message ID : USR0170E**

## **Severity**

Error

Message ID : USR0168E

## **Long Form**

Invalid configuration file.

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : USR0219E**

## **Severity**

Error

## **Long Form**

The session might have timed out. Login again to proceed.

## **Short Form**

No short form is provided for this message type

## **Description**

None

**Message ID : USR0266E**

## **Severity**

Error

## **Long Form**

The system has locked your account because of too many failed attempts. Your account will be unlocked in {0} minutes.

## **Short Form**

No short form is provided for this message type

## **Description**

None

**Message ID : USR0270E**

## **Severity**

Error

Message ID : USR0219E

## Long Form

An error occurred while getting administrator login information.

## Short Form

No short form is provided for this message type

## Description

None

## Message ID : USR0298E

## Severity

Error

## Long Form

Invalid administrator "{0}" failed to login at {1} from client with IP address {2}.

## Short Form

admin login failed from client with IP address {5}

### Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name

### Description

None

**Message ID : USR0308E**

### Severity

Error

### Long Form

{0} must include at least one uppercase character.

### Short Form

No short form is provided for this message type

### Description

None

Message ID : USR0298E



## **Message ID : USR0309E**

### **Severity**

Error

### **Long Form**

{0} must include at least one number.

### **Short Form**

No short form is provided for this message type

### **Description**

None

## **Message ID : USR0310E**

### **Severity**

Error

### **Long Form**

{0} must include at least one of the following {1} special characters.

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : USR0311E**

## **Severity**

Error

## **Long Form**

{0} should not have consecutive repeat characters or numbers.

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : USR0315E**

### **Severity**

Error

### **Long Form**

Internal error occurred during password expiry check.

### **Short Form**

No short form is provided for this message type

### **Description**

None

## **Message ID : USR0316E**

### **Severity**

Error

### **Long Form**

Password is going to expire in {0} days.

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : USR0318E**

## **Severity**

Error

## **Long Form**

Internal error occurred during password history retrieval.

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : USR0319E**

### **Severity**

Error

### **Long Form**

Password cannot be the same as one of your previous {0} passwords.

### **Short Form**

No short form is provided for this message type

### **Description**

None

## **Message ID : USR0320E**

### **Severity**

Error

### **Long Form**

Please specify the correct current password.

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : USR0337E**

## **Severity**

Error

## **Long Form**

{0} must include at least one lowercase character.

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : USR0340E**

### **Severity**

Error

### **Long Form**

{0} length must be at least {1} characters.

### **Short Form**

No short form is provided for this message type

### **Description**

None

## **Message ID : USR0409E**

### **Severity**

Error

### **Long Form**

User "{0}" cannot be deleted because they are in domains.

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : USR0535E**

## **Severity**

Error

## **Long Form**

Invalid User description. A valid description should have at most 128 characters.

## **Short Form**

No short form is provided for this message type

## **Description**

None



## **Message ID : USR0593E**

### **Severity**

Error

### **Long Form**

{0} special characters must be the following {1} special characters.

### **Short Form**

No short form is provided for this message type

### **Description**

None

## **Message ID : USR0632E**

### **Severity**

Error

### **Long Form**

User "{0}" failed to login from client with IP address {1}.

## Short Form

user login failed from client with IP address {5}

### Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name

## Description

None

## Message ID : USR1230E

## Severity

Error

## Long Form

Can't find all admin user type

## Short Form

No short form is provided for this message type

Message ID : USR0632E

## **Description**

None

**Message ID : USR1231E**

## **Severity**

Error

## **Long Form**

Can't find default admin user type

## **Short Form**

No short form is provided for this message type

## **Description**

None

**Message ID : USR1232E**

## **Severity**

Error

Message ID : USR1230E

## **Long Form**

Can't find domain admin user type

## **Short Form**

No short form is provided for this message type

## **Description**

None

**Message ID : USR1233E**

## **Severity**

Error

## **Long Form**

Can't find domain\_security admin user type

## **Short Form**

No short form is provided for this message type

Message ID : USR1232E

1715

**Description**

None

**Message ID : USR1234E****Severity**

Error

**Long Form**

Can't find security admin user type

**Short Form**

No short form is provided for this message type

**Description**

None

**Message ID : USR1235E****Severity**

Error

Message ID : USR1233E

## **Long Form**

Can't find system admin user type

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : USR1236E**

## **Severity**

Error

## **Long Form**

Can't create default admin in domain mode

## **Short Form**

No short form is provided for this message type

Message ID : USR1235E

1717

**Description**

None

**Message ID : USR1254E****Severity**

Error

**Long Form**

LDAP Login failed...

**Short Form**

No short form is provided for this message type

**Description**

None

**Message ID : USR1275E****Severity**

Error

Message ID : USR1236E

## **Long Form**

The new password must be different from the current password by at least {0} characters.

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : USR1288E**

## **Severity**

Error

## **Long Form**

Internal error occurred during password configuration retrieval.

## **Short Form**

No short form is provided for this message type



## **Description**

None

**Message ID : USR1289E**

## **Severity**

Error

## **Long Form**

Your password was last changed on {0}. Password is not allowed to be changed more than once within {1} day(s).

## **Short Form**

No short form is provided for this message type

## **Description**

None

**Message ID : USR1321E**

## **Severity**

Error

Message ID : USR1288E

## **Long Form**

Please cleanup the replication before delete...

## **Short Form**

No short form is provided for this message type

## **Description**

None

**Message ID : USR1325E**

## **Severity**

Error

## **Long Form**

There are multiple colons...

## **Short Form**

No short form is provided for this message type

Message ID : USR1321E

1721

**Description**

None

**Message ID : USR1326E****Severity**

Error

**Long Form**

Cannot validate the host name and the port...

**Short Form**

No short form is provided for this message type

**Description**

None

**Message ID : USR1327E****Severity**

Error

Message ID : USR1325E

## **Long Form**

The port number is invalid.

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : USR1328E**

## **Severity**

Error

## **Long Form**

A system admin cannot be assigned to a domain.

## **Short Form**

No short form is provided for this message type

## **Description**

None

**Message ID : USR1329E**

## **Severity**

Error

## **Long Form**

The operation cannot be performed out side of the user's domain.

## **Short Form**

No short form is provided for this message type

## **Description**

None

**Message ID : USR1330E**

## **Severity**

Error

Message ID : USR1328E

## **Long Form**

Read-Only user cannot be {0} for user type {1}

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : USR1332E**

## **Severity**

Error

## **Long Form**

Read-Only user {0} cannot be the first administrator on domain {1}

## **Short Form**

No short form is provided for this message type

## **Description**

None

**Message ID : USR1333E**

## **Severity**

Error

## **Long Form**

A security administrator cannot be assigned to an unassigned domain.

## **Short Form**

No short form is provided for this message type

## **Description**

None

**Message ID : USR1351E**

## **Severity**

Error

Message ID : USR1332E

## Long Form

LDAP User "{0}" failed to login from client with IP address {1}. Reason: {2}

## Short Form

LDAP user login failed from client with IP address {5}

### Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
showStr	reason	Text	Code specifying reason for allowing access, if any

## Description

None

**Message ID : USR1385E**

## Severity

Error

Message ID : USR1351E

1727



## **Long Form**

The item is in a domain that the current user does not have access to.

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : USR1386E**

## **Severity**

Error

## **Long Form**

Run Cleanup Replication for each configured failover server and try Restore again

## **Short Form**

No short form is provided for this message type

**Description**

None

**Message ID : USR1387E****Severity**

Error

**Long Form**

No attached file found

**Short Form**

No short form is provided for this message type

**Description**

None

**Message ID : USR1388E****Severity**

Error

Message ID : USR1386E

## Long Form

Invalid user ID(s) for the domain: [{0}]

## Short Form

No short form is provided for this message type

## Description

None

## Message ID : USR1389E

## Severity

Error

## Long Form

User with property "{0}" equal "{1}" not found in the domain

## Short Form

No short form is provided for this message type

## **Description**

None

**Message ID : USR1393E**

## **Severity**

Error

## **Long Form**

This key share already exists for the domain

## **Short Form**

No short form is provided for this message type

## **Description**

None

**Message ID : USR1396E**

## **Severity**

Error

Message ID : USR1389E

## **Long Form**

Backup request for {0} is already in process.

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : USR1397E**

## **Severity**

Error

## **Long Form**

Domain {0} is being restored at this time.

## **Short Form**

No short form is provided for this message type

**Description**

None

**Message ID : USR1398E****Severity**

Error

**Long Form**

System restore is in progress.

**Short Form**

No short form is provided for this message type

**Description**

None

**Message ID : USR1399E****Severity**

Error

Message ID : USR1397E

## **Long Form**

Wrapper key does not exist. Please create or import a wrapper key first.

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : USR1400E**

## **Severity**

Error

## **Long Form**

Minimum shares can not exceed total number of shares

## **Short Form**

No short form is provided for this message type

## **Description**

None

**Message ID : USR1401E**

## **Severity**

Error

## **Long Form**

Minimum number of shares must be greater than 0

## **Short Form**

No short form is provided for this message type

## **Description**

None

**Message ID : USR1402E**

## **Severity**

Error

Message ID : USR1400E



## **Long Form**

Total number of shares must be greater than 0

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : USR1403E**

## **Severity**

Error

## **Long Form**

Total number of shares cannot be greater than 10

## **Short Form**

No short form is provided for this message type

**Description**

None

**Message ID : USR1404E****Severity**

Error

**Long Form**

No users specified

**Short Form**

No short form is provided for this message type

**Description**

None

**Message ID : USR1405E****Severity**

Error

Message ID : USR1403E

## **Long Form**

Number of custodians does not match number of users

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : USR1406E**

## **Severity**

Error

## **Long Form**

Size of wrapper key description is greater than 256 chars

## **Short Form**

No short form is provided for this message type

**Description**

None

**Message ID : USR1408E****Severity**

Error

**Long Form**

Decryption failed while restoring. Please check if the correct wrapper key is being used.

**Short Form**

No short form is provided for this message type

**Description**

None

**Message ID : USR1411E****Severity**

Error

Message ID : USR1406E

## **Long Form**

IP address is invalid

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : USR1412E**

## **Severity**

Error

## **Long Form**

IP4 address is invalid

## **Short Form**

No short form is provided for this message type

Message ID : USR1411E

1740

## **Description**

None

**Message ID : USR1413E**

## **Severity**

Error

## **Long Form**

IP6 address is invalid

## **Short Form**

No short form is provided for this message type

## **Description**

None

**Message ID : USR1414E**

## **Severity**

Error

Message ID : USR1412E

## **Long Form**

Problem in converting key share(s) to key. Key share(s) number or value(s) may not be correct.

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : USR1415E**

## **Severity**

Error

## **Long Form**

Problem in converting key share(s) to key. A key share value is not correct.

## **Short Form**

No short form is provided for this message type

**Description**

None

**Message ID : USR1416E****Severity**

Error

**Long Form**

Registration Shared Secret length must be at least {0} characters.

**Short Form**

No short form is provided for this message type

**Description**

None

**Message ID : USR1417E****Severity**

Error

Message ID : USR1415E



## **Long Form**

Invalid system backup file

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : USR1418E**

## **Severity**

Error

## **Long Form**

Invalid domain backup file

## **Short Form**

No short form is provided for this message type

Message ID : USR1417E

## **Description**

None

**Message ID : USR1419E**

## **Severity**

Error

## **Long Form**

Invalid key share input

## **Short Form**

No short form is provided for this message type

## **Description**

None

**Message ID : USR1420E**

## **Severity**

Error

Message ID : USR1418E

## **Long Form**

Invalid hostname, or ip address, or port

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : USR1421E**

## **Severity**

Error

## **Long Form**

Auto backup is not set up

## **Short Form**

No short form is provided for this message type

**Description**

None

**Message ID : USR1422E****Severity**

Error

**Long Form**

Invalid certificate in file

**Short Form**

No short form is provided for this message type

**Description**

None

**Message ID : USR1424E****Severity**

Error

Message ID : USR1421E

## **Long Form**

Unable to connect to {0}

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : USR1425E**

## **Severity**

Error

## **Long Form**

SSH connection not set up properly

## **Short Form**

No short form is provided for this message type

## **Description**

None

**Message ID : USR1426E**

## **Severity**

Error

## **Long Form**

The identity does not have access to the key.

## **Short Form**

No short form is provided for this message type

## **Description**

None

**Message ID : USR1427E**

## **Severity**

Error

Message ID : USR1425E

## **Long Form**

Domain role is required for selected administrator.

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : USR1428E**

## **Severity**

Error

## **Long Form**

Domain role is not compatible for selected administrator.

## **Short Form**

No short form is provided for this message type

## **Description**

None

**Message ID : USR1429E**

## **Severity**

Error

## **Long Form**

Host role also requires selection of Challenge and Response role.

## **Short Form**

No short form is provided for this message type

## **Description**

None

**Message ID : USR1430E**

## **Severity**

Error

Message ID : USR1428E



## **Long Form**

Domain administrator cannot have any other roles than domain.

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : USR1431E**

## **Severity**

Error

## **Long Form**

Cannot assign role for selected administrator.

## **Short Form**

No short form is provided for this message type

**Description**

None

**Message ID : USR1432E****Severity**

Error

**Long Form**

The selected administrator must have at least one role.

**Short Form**

No short form is provided for this message type

**Description**

None

**Message ID : USR1433E****Severity**

Error

Message ID : USR1431E

## **Long Form**

The administrator description cannot be updated.

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : USR1622E**

## **Severity**

Error

## **Long Form**

{0} length cannot exceed {1} characters.

## **Short Form**

No short form is provided for this message type

## **Description**

None

**Message ID : USR1650E**

## **Severity**

Error

## **Long Form**

"{0}" is an invalid host name or ip address. FQDN size cannot be greater than {1} and local host names cannot be greater than {2}

## **Short Form**

No short form is provided for this message type

## **Description**

None

**Message ID : USR1671E**

## **Severity**

Error

Message ID : USR1622E

## **Long Form**

"Restore file has no data."

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : USR1672E**

## **Severity**

Error

## **Long Form**

"Restore process for the system or the specific domain is already in progress."

## **Short Form**

No short form is provided for this message type

## **Description**

None

**Message ID : USR1673E**

## **Severity**

Error

## **Long Form**

"Restore process with id {0} not found"

## **Short Form**

No short form is provided for this message type

## **Description**

None

**Message ID : USR1707E**

## **Severity**

Error

Message ID : USR1672E

## **Long Form**

Smart card login is not globally enabled, so individual smart card user cannot be created.

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : USR1708E**

## **Severity**

Error

## **Long Form**

At least one smart card user mapping criteria must be selected.

## **Short Form**

No short form is provided for this message type

## Description

None

**Message ID : USR1710E**

## Severity

Error

## Long Form

Smart card login is enabled for user "{0}", so username/password login is not allowed. Disable smart card login for this user if username/password login is needed.

## Short Form

No short form is provided for this message type

## Description

None

**Message ID : USR1711E**



## Severity

Error

## Long Form

Client certificate with subject DN "{0}" cannot be mapped to any user.

## Short Form

No short form is provided for this message type

## Description

None

## Message ID : USR1712E

## Severity

Error

## Long Form

Client certificate with subject DN "{0}" is mapped to more than one user: {1}.

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : USR1713E**

## **Severity**

Error

## **Long Form**

Smart card login is not enabled for user "{0}". Remove the smart card from the reader to login.

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : USR1714E**

### **Severity**

Error

### **Long Form**

User "{0}" provided an invalid client certificate for LDAP authentication.

### **Short Form**

No short form is provided for this message type

### **Description**

None

## **Message ID : USR1715E**

### **Severity**

Error

### **Long Form**

User "{0}" provided an invalid client certificate.

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : USR1716E**

## **Severity**

Error

## **Long Form**

Remove the invalid smart card from the reader, restart the web browser and login again.

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : USR1717E**

### **Severity**

Error

### **Long Form**

The user logged in using a username and password that is different from the owner of the smart card certificate.

### **Short Form**

No short form is provided for this message type

### **Description**

None

## **Message ID : USR1719E**

### **Severity**

Error

### **Long Form**

Smart card login configuration is not enabled

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : USR1721E**

## **Severity**

Error

## **Long Form**

To load KMIP certificate for a host the host needs to have "Registration Allowed" & "Communication Enabled".

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : USR1722E**

### **Severity**

Error

### **Long Form**

downloaded file has zero size.

### **Short Form**

No short form is provided for this message type

### **Description**

None

## **Message ID : USR1729E**

### **Severity**

Error

### **Long Form**

Use a number between {0} and 10 for "Minimum Custodians Needed"

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : USR1730E**

## **Severity**

Error

## **Long Form**

Use a number between {0} and 10 for "Total number of Custodians"

## **Short Form**

No short form is provided for this message type

## **Description**

None

Message ID : USR1729E

1767



## **Message ID : USR1836E**

### **Severity**

Error

### **Long Form**

Error while updating "Syslog Queue Size" configuration.

### **Short Form**

No short form is provided for this message type

### **Description**

None

## **Message ID : USR1838E**

### **Severity**

Error

### **Long Form**

User "{0}" is found in {1} different LDAP servers.

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : USR1839E**

## **Severity**

Error

## **Long Form**

User "{0}" belongs to {1} different LDAP groups that have been imported into DSM.

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : USR1840E**

### **Severity**

Error

### **Long Form**

User "{0}" is not a member of the given LDAP group "{1}" or the group has not been imported into DSM.

### **Short Form**

No short form is provided for this message type

### **Description**

None

## **Message ID : USR1843E**

### **Severity**

Error

### **Long Form**

A smart card enabled administrator cannot be created for a restricted domain.

## **Short Form**

No short form is provided for this message type

## **Description**

None

# Logger USR: Information

**Message ID : USR0631I**

## Severity

Information

## Long Form

User "{0}" logged in from client with IP address {1}.

## Short Form

user logged in

### Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name

## Description

None

## Message ID : USR1277I

### Severity

Information

### Long Form

User {0} logged out from client with IP address {1}.

### Short Form

user logged out

### Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name

### Description

None

## Message ID : USR1278I

## Severity

Information

## Long Form

User {0} logged out from client with IP address {1} due to inactivity.

## Short Form

user logged out due to inactivity

### Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name

## Description

None

## Message ID : USR1330I

## Severity

Information

Message ID : USR1278I

## **Long Form**

This version of the product only allows you to create one domain. Please contact Vormetric for licensing information.

## **Short Form**

No short form is provided for this message type

## **Description**

None

**Message ID : USR1331I**

## **Severity**

Information

## **Long Form**

Maximum number of domains allowed by the license have been created. No more domains can be created.

## **Short Form**

No short form is provided for this message type

Message ID : USR1330I

1775



## Description

None

# Logger USR: Warnings

**Message ID : USR1615W**

## Severity

Warning

## Long Form

User {0} already logged in from client with IP address {1}.

## Short Form

User already logged in

## Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name

## Description

None

## **Message ID : USR1709W**

### **Severity**

Warning

### **Long Form**

Smart card login is enabled for user "{0}", but there is no user certificate on file.

### **Short Form**

No short form is provided for this message type

### **Description**

None

# Logger VAD: Errors

**Message ID : VAD4642E**

## Severity

Error

## Long Form

{0}: {1} Failed to establish communication to Key Manager; return code={2}.

## Short Form

Failed to establish communication to key manager

## Parameters

Label	CEF Label	Type	Usage
func	vds_func	Text	A function name
act	act	Text	Action being requested or performed
ecode	cn1	Numeric	An error code

## Description

None

# Logger VAD: Information

**Message ID : VAD4641I**

## Severity

Information

## Long Form

{0}: {1} Successful communication to Key Manager; time= {2}.

## Short Form

Successful communication to key manager

### Parameters

Label	CEF Label	Type	Usage
func	vds_func	Text	A function name
act	act	Text	Action being requested or performed
etime	end	Text	An end time stamp

## Description

None

# Logger VAD: Warnings

**Message ID : VAD4643W**

## Severity

Warning

## Long Form

{0}: {1}.

## Short Form

Tag: Fault

## Parameters

Label	CEF Label	Type	Usage
showStr	reason	Text	Code specifying reason for allowing access, if any
detail	vds_detail	Text	Fault detail

## Description

None



# Logger VMD: Errors

**Message ID : VMD3203E**

## Severity

Error

## Long Form

LDT: Live data transformation pause request from "{0}" failed

## Short Form

LDT pause failed

## Parameters

Label	CEF Label	Type	Usage
shost	shost	Text	Source host name

## Description

None

## Message ID : VMD3204E

### Severity

Error

### Long Form

LDT: Live data transformation resume request from "{0}" failed

### Short Form

LDT resume failed

### Parameters

Label	CEF Label	Type	Usage
shost	shost	Text	Source host name

### Description

None

## Message ID : VMD3503E

## **Severity**

Error

## **Long Form**

ReadBioPublicKey Bio\_new failed {0}

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : VMD3507E**

## **Severity**

Error

## **Long Form**

PEM\_read\_X509 failed

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : VMD3509E**

## **Severity**

Error

## **Long Form**

X509\_extract\_key failed

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : VMD3510E**

### **Severity**

Error

### **Long Form**

vm\_generate\_certificate: mkcert RSA\_generate\_key failed

### **Short Form**

No short form is provided for this message type

### **Description**

None

## **Message ID : VMD3514E**

### **Severity**

Error

### **Long Form**

uname: bad machine name len {0}

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : VMD3517E**

## **Severity**

Error

## **Long Form**

ReadBioPublicKey X509\_extract\_key failed {0}

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : VMD3520E**

### **Severity**

Error

### **Long Form**

set process sid failed

### **Short Form**

Set SID fail

### **Parameters**

No parameters are provided for this message type

### **Description**

None

## **Message ID : VMD3525E**

### **Severity**

Error

## Long Form

ReadBioX509cert Bio\_read\_filename failed {0}

## Short Form

No short form is provided for this message type

## Description

None

## Message ID : VMD3527E

## Severity

Error

## Long Form

PEM\_read\_PrivateKey {0} read

## Short Form

No short form is provided for this message type

Message ID : VMD3525E



**Description**

None

**Message ID : VMD3533E****Severity**

Error

**Long Form**

ReadBioPublicKey failed

**Short Form**

No short form is provided for this message type

**Description**

None

**Message ID : VMD3544E****Severity**

Error

Message ID : VMD3527E

## Long Form

The VMD failed to become a daemon.

## Short Form

VMD daemonize fail

### Parameters

No parameters are provided for this message type

## Description

None

## Message ID : VMD3546E

## Severity

Error

## Long Form

Can't get NIS domain: {0}

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : VMD3550E**

## **Severity**

Error

## **Long Form**

ReadBioPrivateKey BIO\_new failed {0}

## **Short Form**

No short form is provided for this message type

## **Description**

None

Message ID : VMD3546E

## **Message ID : VMD3559E**

### **Severity**

Error

### **Long Form**

ReadBioPublicKey PEM\_read\_bio\_X509 failed {0}

### **Short Form**

No short form is provided for this message type

### **Description**

None

## **Message ID : VMD3563E**

### **Severity**

Error

### **Long Form**

File {0} open failed ({1})

## Short Form

File open error

### Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file
ecode	cn1	Numeric	An error code

## Description

None

**Message ID : VMD3572E**

## Severity

Error

## Long Form

ReadBioPrivateKey PEM\_read\_bio\_RSAPrivateKey failed {0}

Message ID : VMD3563E

1796

## Short Form

No short form is provided for this message type

## Description

None

## Message ID : VMD3578E

## Severity

Error

## Long Form

WriteBioPublicKey PEM\_write\_bio\_X509 failed {0}

## Short Form

No short form is provided for this message type

## Description

None

## **Message ID : VMD3581E**

### **Severity**

Error

### **Long Form**

WriteBioPrivateKey PEM\_write\_bio\_RSAPrivateKey failed {0}

### **Short Form**

No short form is provided for this message type

### **Description**

None

## **Message ID : VMD3596E**

### **Severity**

Error

### **Long Form**

vm\_generate\_certificate: Error initializing openssl random number generator

## Short Form

No short form is provided for this message type

## Description

None

## Message ID : VMD3597E

## Severity

Error

## Long Form

setmntent({0}, r) failed {1}({2})

## Short Form

setmntent error

## Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file
showStr	reason	Text	Code specifying reason for allowing access, if any

Message ID : VMD3596E

1799



Label	CEF Label	Type	Usage
ecode	cn1	Numeric	An error code

## Description

None

## Message ID : VMD3605E

## Severity

Error

## Long Form

sysinfo failed for uname errno {0} : {1}

## Short Form

No short form is provided for this message type

## Description

None

## **Message ID : VMD3607E**

### **Severity**

Error

### **Long Form**

WriteBioPublicKey Bio\_new failed {0}

### **Short Form**

No short form is provided for this message type

### **Description**

None

## **Message ID : VMD3611E**

### **Severity**

Error

### **Long Form**

ReadBioPrivateKey BIO\_read\_filename failed {0}

Message ID : VMD3607E

## Short Form

No short form is provided for this message type

## Description

None

## Message ID : VMD3612E

## Severity

Error

## Long Form

{0}: check\_mount({1}, {2}) malloc({3}) failed {4}

## Short Form

No memory

## Parameters

No parameters are provided for this message type

## Description

None

**Message ID : VMD3616E**

## Severity

Error

## Long Form

sysinfo failed for SI\_HW\_SERIAL errno[{}][{}]

## Short Form

No short form is provided for this message type

## Description

None

**Message ID : VMD3617E**

## Severity

Error

Message ID : VMD3612E

## Long Form

Failed to protect process {0}.

## Short Form

Cannot protect process

### Parameters

Label	CEF Label	Type	Usage
pid	dvcpid	Numeric	Numeric process ID

## Description

None

**Message ID : VMD3628E**

## Severity

Error

## Long Form

WriteBioPrivateKey BIO\_write\_filename failed {0}

Message ID : VMD3617E

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : VMD3629E**

## **Severity**

Error

## **Long Form**

WriteBioPublicKey BIO\_write\_filename failed {0}

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : VMD3633E**

### **Severity**

Error

### **Long Form**

ReadBioX509cert PEM\_read\_bio\_X509 failed {0}

### **Short Form**

No short form is provided for this message type

### **Description**

None

## **Message ID : VMD3644E**

### **Severity**

Error

### **Long Form**

NIS get group error: {0}

## Short Form

No short form is provided for this message type

## Description

None

## Message ID : VMD3645E

## Severity

Error

## Long Form

{0}: check\_mount({1}, {2}) realloc({3}) failed {4}

## Short Form

No memory

## Parameters

No parameters are provided for this message type



## Description

None

**Message ID : VMD3651E**

## Severity

Error

## Long Form

check\_mount: mnttab open failed {0}

## Short Form

Mnttab open error

## Parameters

Label	CEF Label	Type	Usage
ecode	cn1	Numeric	An error code

## Description

None

Message ID : VMD3645E

## **Message ID : VMD3655E**

### **Severity**

Error

### **Long Form**

vm\_generate\_certificate: mkcert EVP\_PKEY\_new failed

### **Short Form**

No short form is provided for this message type

### **Description**

None

## **Message ID : VMD3665E**

### **Severity**

Error

### **Long Form**

WriteBioPrivateKey BIO\_new failed {0}

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : VMD3666E**

## **Severity**

Error

## **Long Form**

ReadBioPrivateKey failed

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : VMD3667E**

### **Severity**

Error

### **Long Form**

Error: can't load public key

### **Short Form**

No short form is provided for this message type

### **Description**

None

## **Message ID : VMD3674E**

### **Severity**

Error

### **Long Form**

Failed to alloc mem for Host Key

Message ID : VMD3667E

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : VMD3676E**

## **Severity**

Error

## **Long Form**

ReadBioX509cert Bio\_new failed {0}

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : VMD3681E**

### **Severity**

Error

### **Long Form**

Failed to open {0}

### **Short Form**

No short form is provided for this message type

### **Description**

None

## **Message ID : VMD3683E**

### **Severity**

Error

### **Long Form**

TEST HOST key failed {0}

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : VMD3685E**

## **Severity**

Error

## **Long Form**

ReadPrivateKey failed

## **Short Form**

No short form is provided for this message type

## **Description**

None

Message ID : VMD3683E

## **Message ID : VMD3686E**

### **Severity**

Error

### **Long Form**

SET machine id failed {0}

### **Short Form**

No short form is provided for this message type

### **Description**

None

## **Message ID : VMD3689E**

### **Severity**

Error

### **Long Form**

X509 certificate file {0} open failed



## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : VMD3697E**

## **Severity**

Error

## **Long Form**

vm\_generate\_certificate: mkcert failed

## **Short Form**

No short form is provided for this message type

## **Description**

None

# Message ID : VMD3700E

## Severity

Error

## Long Form

Unable to create or write to file {0} as part of a policy update. Error code {1}.

## Short Form

Policy update error

### Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file
ecode	cn1	Numeric	An error code

## Description

Verify that the secfsd process is running; if not, restart it. If sesfsd is running, please call Vormetric support for assistance.

## **Message ID : VMD3702E**

### **Severity**

Error

### **Long Form**

NIS get passwd error: {0}

### **Short Form**

No short form is provided for this message type

### **Description**

None

## **Message ID : VMD3707E**

### **Severity**

Error

### **Long Form**

vm\_generate\_certificate: mkcert EVP\_PKEY\_assign\_RSA failed

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : VMD3713E**

## **Severity**

Error

## **Long Form**

vm\_get\_pubkey\_from\_file: Read key file {0} failed

## **Short Form**

No short form is provided for this message type

## **Description**

None

Message ID : VMD3707E

## **Message ID : VMD3718E**

### **Severity**

Error

### **Long Form**

vm\_get\_privkey\_from\_file: Read key file {0} failed

### **Short Form**

No short form is provided for this message type

### **Description**

None

## **Message ID : VMD3723E**

### **Severity**

Error

### **Long Form**

ReadBioPublicKey Bio\_read\_filename failed {0}

## **Short Form**

No short form is provided for this message type

## **Description**

None

**Message ID : VMD3724E**

## **Severity**

Error

## **Long Form**

Private Key file {0} open failed

## **Short Form**

No short form is provided for this message type

## **Description**

None

Message ID : VMD3723E

## **Message ID : VMD3726E**

### **Severity**

Error

### **Long Form**

mount\_sec: {0} mount failed {1}

### **Short Form**

No short form is provided for this message type

### **Description**

None

## **Message ID : VMD3730E**

### **Severity**

Error

### **Long Form**

sysinfo: failed for SI\_HW\_SERIAL.

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : VMD3734E**

## **Severity**

Error

## **Long Form**

sysinfo failed for SI\_SYSNAME errno {0}

## **Short Form**

No short form is provided for this message type

## **Description**

None



## **Message ID : VMD3736E**

### **Severity**

Error

### **Long Form**

hpux\_sysinfo: invalid buffer length

### **Short Form**

No short form is provided for this message type

### **Description**

None

## **Message ID : VMD3747E**

### **Severity**

Error

### **Long Form**

can not write to file={0}

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : VMD3748E**

## **Severity**

Error

## **Long Form**

Failed to read Host Private Key from file {0}

## **Short Form**

No short form is provided for this message type

## **Description**

None

Message ID : VMD3747E

## **Message ID : VMD3750E**

### **Severity**

Error

### **Long Form**

uname failed! errno[{}][{}]

### **Short Form**

No short form is provided for this message type

### **Description**

None

## **Message ID : VMD3758E**

### **Severity**

Error

### **Long Form**

{0}: {1}

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : VMD3759E**

## **Severity**

Error

## **Long Form**

write() ssl error {0}

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : VMD3760E**

### **Severity**

Error

### **Long Form**

Server does not support required soap operation: {0}

### **Short Form**

No short form is provided for this message type

### **Description**

None

## **Message ID : VMD3779E**

### **Severity**

Error

### **Long Form**

Unable to create a signature for file {0}; error code {1}.

## Short Form

Sig creation error

### Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file
ecode	cn1	Numeric	An error code

## Description

None

**Message ID : VMD3780E**

## Severity

Error

## Long Form

Unable to encrypt file {0} with the session key; error code {1}.

## Short Form

File encrypt error

### Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file
ecode	cn1	Numeric	An error code

## Description

None

**Message ID : VMD3782E**

## Severity

Error

## Long Form

A new security configuration was received, but we failed to implement it. The current security configuration will continue to be used.

## Short Form

Config update fail

### Parameters

No parameters are provided for this message type

## Description

An error occurred while attempting to process a policy push from a Security Server. Details of the failure were logged in the preceding message.

## Message ID : VMD3784E

## Severity

Error

## Long Form

Kernel component failed to provide initialization information to VMD.

## Short Form

No config from kernel



## Parameters

No parameters are provided for this message type

## Description

None

## Message ID : VMD3786E

## Severity

Error

## Long Form

Host file browsing for {0} failed.

## Short Form

Host browse fail

## Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Message ID : VMD3784E

## Description

None

**Message ID : VMD3787E**

## Severity

Error

## Long Form

Unable to get status from kernel component. Error code {0}.

## Short Form

Kernel config fetch error

## Parameters

Label	CEF Label	Type	Usage
ecode	cn1	Numeric	An error code

## Description

None

Message ID : VMD3786E

## Message ID : VMD3788E

### Severity

Error

### Long Form

Unable to send data to kernel component. Error code {0}.

### Short Form

Kernel config send error

### Parameters

Label	CEF Label	Type	Usage
ecode	cn1	Numeric	An error code

### Description

None

## Message ID : VMD3789E

## **Severity**

Error

## **Long Form**

Unable to receive data from kernel component. Error code {0}.

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : VMD3790E**

## **Severity**

Error

## **Long Form**

Kernel component did not confirm host-delete operation.

## Short Form

No host-delete ACK

### Parameters

No parameters are provided for this message type

## Description

None

## Message ID : VMD3792E

### Severity

Error

## Long Form

Unable to write authorized file information to disk. Error code {0}.

## Short Form

Write auth file error

## Parameters

Label	CEF Label	Type	Usage
ecode	cn1	Numeric	An error code

## Description

None

**Message ID : VMD3795E**

## Severity

Error

## Long Form

Query security config failed.

## Short Form

Query config fail

## Parameters

No parameters are provided for this message type

Message ID : VMD3792E

## **Description**

None

**Message ID : VMD3796E**

## **Severity**

Error

## **Long Form**

Kernel component reports failure on host-delete operation.

## **Short Form**

Host delete fail

## **Parameters**

No parameters are provided for this message type

## **Description**

None

## **Message ID : VMD3799E**

### **Severity**

Error

### **Long Form**

Delete host operation failed.

### **Short Form**

No short form is provided for this message type

### **Description**

None

## **Message ID : VMD3801E**

### **Severity**

Error

### **Long Form**

Cannot update service status. Error = {0}



## Short Form

Service update error

### Parameters

Label	CEF Label	Type	Usage
ecode	cn1	Numeric	An error code

## Description

None

## Message ID : VMD3802E

## Severity

Error

## Long Form

Cannot set service status to stopped. Error = {0}

## Short Form

Service stop error

Message ID : VMD3801E

### Parameters

Label	CEF Label	Type	Usage
ecode	cn1	Numeric	An error code

### Description

None

### Message ID : VMD3807E

### Severity

Error

### Long Form

Cannot register service handler. Error = {0}

### Short Form

Register server error

### Parameters

Label	CEF Label	Type	Usage
ecode	cn1	Numeric	An error code

Message ID : VMD3802E

Label	CEF Label	Type	Usage

## Description

None

## Message ID : VMD3809E

## Severity

Error

## Long Form

Cannot start service dispatcher. Error = {0}

## Short Form

Start service error

## Parameters

Label	CEF Label	Type	Usage
ecode	cn1	Numeric	An error code

## Description

None

## Message ID : VMD3811E

## Severity

Error

## Long Form

User {0} in domain {1} failed to connect to network path {2}. Error code {3}.

## Short Form

Net connect error

## Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
domain	dntdom	Text	A domain name (policy, network, users, etc)
url	request	Text	A uniform resource location
ecode	cn1	Numeric	An error code

## Description

None

**Message ID : VMD3812E**

## Severity

Error

## Long Form

Failed to enumerate network path {0}. Error code {1}.

## Short Form

Net enumeration error

## Parameters

Label	CEF Label	Type	Usage
url	request	Text	A uniform resource location
ecode	cn1	Numeric	An error code

## Description

None

**Message ID : VMD3816E**

## Severity

Error

## Long Form

Failed to initialize the signature request {0}

## Short Form

Init sig req fail

## Parameters

Label	CEF Label	Type	Usage
showStr	reason	Text	Code specifying reason for allowing access, if any

## Description

None

Message ID : VMD3812E

## Message ID : VMD3819E

### Severity

Error

### Long Form

Failed to generate the file list for the signature request {0}

### Short Form

Sig file list fail

### Parameters

Label	CEF Label	Type	Usage
showStr	reason	Text	Code specifying reason for allowing access, if any

### Description

None

## Message ID : VMD3822E

## Severity

Error

## Long Form

Failed to generate the signatures for the signature request {0}

## Short Form

Sig gen fail

### Parameters

Label	CEF Label	Type	Usage
showStr	reason	Text	Code specifying reason for allowing access, if any

## Description

None

**Message ID : VMD3828E**

## Severity

Error

Message ID : VMD3822E



## Long Form

Failed the signature request {0}

## Short Form

Sig req fail

### Parameters

Label	CEF Label	Type	Usage
showStr	reason	Text	Code specifying reason for allowing access, if any

## Description

None

**Message ID : VMD3830E**

## Severity

Error

## Long Form

Failed to read the file list for the signature request {0}, error code {1}

Message ID : VMD3828E

## Short Form

Sig file list read error

### Parameters

Label	CEF Label	Type	Usage
showStr	reason	Text	Code specifying reason for allowing access, if any
ecode	cnl	Numeric	An error code

## Description

None

## Message ID : VMD3831E

## Severity

Error

## Long Form

Failed to write the file list for the signature request {0}, error code {1}

## Short Form

Sig file list write error

### Parameters

Label	CEF Label	Type	Usage
showStr	reason	Text	Code specifying reason for allowing access, if any
ecode	cnl	Numeric	An error code

## Description

None

**Message ID : VMD3833E**

## Severity

Error

## Long Form

Failed to create the signature disk object

Message ID : VMD3831E

1850

## Short Form

Create sig disk object fail

### Parameters

No parameters are provided for this message type

## Description

None

## Message ID : VMD3834E

## Severity

Error

## Long Form

Failed to add the signature {0} and name {1} into the signature disk object

## Short Form

Add sig object error

## Parameters

Label	CEF Label	Type	Usage
hex	vds_hex	Text	A hex string (e.g. a signature)
filePath	filePath	Text	Full path to file

## Description

None

**Message ID : VMD3835E**

## Severity

Error

## Long Form

Failed to write the signature disk file

## Short Form

Write sig object fail

Message ID : VMD3834E

1852

### **Parameters**

No parameters are provided for this message type

### **Description**

None

**Message ID : VMD3837E**

### **Severity**

Error

### **Long Form**

Failed to write the signature disk file header

### **Short Form**

Sig write header fail

### **Parameters**

No parameters are provided for this message type

Message ID : VMD3835E

## **Description**

None

**Message ID : VMD3838E**

## **Severity**

Error

## **Long Form**

Failed to read the signature disk file header

## **Short Form**

Sig read hreader fail

## **Parameters**

No parameters are provided for this message type

## **Description**

None

Message ID : VMD3837E

1854

## **Message ID : VMD3840E**

### **Severity**

Error

### **Long Form**

Failed to push a new signature database to the kernel

### **Short Form**

Sig push to kernel fail

### **Parameters**

No parameters are provided for this message type

### **Description**

None

## **Message ID : VMD3843E**

### **Severity**

Error



## Long Form

User browsing for {0} failed.

## Short Form

User browse fail

### Parameters

Label	CEF Label	Type	Usage
domain	dntdom	Text	A domain name (policy, network, users, etc)

## Description

None

## Message ID : VMD3844E

## Severity

Error

## Long Form

Failed to bind to {0}. Error code {1}.

Message ID : VMD3843E

## Short Form

Domain bind error

### Parameters

Label	CEF Label	Type	Usage
domain	dntdom	Text	A domain name (policy, network, users, etc)
ecode	cn1	Numeric	An error code

## Description

None

**Message ID : VMD3845E**

## Severity

Error

## Long Form

Failed to query the domain {0} by {1}. Error {2}: {3}.

## Short Form

NIS query error

### Parameters

Label	CEF Label	Type	Usage
domain	dntdom	Text	A domain name (policy, network, users, etc)
effect	vds_effect	Text	Policy effect
ecode	cnl	Numeric	An error code
showStr	reason	Text	Code specifying reason for allowing access, if any

## Description

None

**Message ID : VMD3846E**

## Severity

Error

## Long Form

Failed to query the group {0} in the domain {1} by {2}. Error {3}: {4}.

Message ID : VMD3845E

1858

## Short Form

NIS group query error

### Parameters

Label	CEF Label	Type	Usage
group	vds_group	Text	Group name
domain	dntdom	Text	A domain name (policy, network, users, etc)
effect	vds_effect	Text	Policy effect
ecode	cn1	Numeric	An error code
showStr	reason	Text	Code specifying reason for allowing access, if any

## Description

None

**Message ID : VMD3848E**

## Severity

Error

Message ID : VMD3846E

1859

## Long Form

Domain browsing failed.

## Short Form

Domain browse fail

### Parameters

No parameters are provided for this message type

## Description

None

## Message ID : VMD3849E

## Severity

Error

## Long Form

Error getting common name: {0}

## Short Form

Cannot determine common name

### Parameters

Label	CEF Label	Type	Usage
showStr	reason	Text	Code specifying reason for allowing access, if any

## Description

None

## Message ID : VMD3855E

### Severity

Error

## Long Form

Failed to send {0} signatures for the signature request {1} to the Key Manager

## Short Form

Send sigs error

Message ID : VMD3849E

1861

## Parameters

Label	CEF Label	Type	Usage
nsig	vds_nsig	Numeric	The number of signatures generated
showStr	reason	Text	Code specifying reason for allowing access, if any

## Description

None

**Message ID : VMD3858E**

## Severity

Error

## Long Form

The kernel component was unable to implement the new security configuration

## Short Form

New config to kernel fail

## Parameters

No parameters are provided for this message type

## Description

An error occurred while attempting to apply a policy push from a Security Server.

## Message ID : VMD3864E

## Severity

Error

## Long Form

Unable to parse LDAP URL {0} - error "{1}"

## Short Form

Bad LDAP url

## Parameters

Label	CEF Label	Type	Usage
url	request	Text	A uniform resource location
showStr	reason	Text	Code specifying reason for allowing access, if any

Message ID : VMD3858E



Label	CEF Label	Type	Usage

## Description

None

## Message ID : VMD3865E

## Severity

Error

## Long Form

Unable to query LDAP server {0} - error "{1}"

## Short Form

Bad LADP server

## Parameters

Label	CEF Label	Type	Usage
url	request	Text	A uniform resource location
showStr	reason	Text	Code specifying reason for allowing access, if any

Message ID : VMD3864E

1864

## **Description**

None

**Message ID : VMD3866E**

## **Severity**

Error

## **Long Form**

Invalid LDAP posixAccount data returned

## **Short Form**

Invalid LDAP account

## **Parameters**

No parameters are provided for this message type

## **Description**

None

Message ID : VMD3865E

1865

## **Message ID : VMD3867E**

### **Severity**

Error

### **Long Form**

Invalid LDAP posixGroup data returned

### **Short Form**

Invalid LDAP group

### **Parameters**

No parameters are provided for this message type

### **Description**

None

## **Message ID : VMD3872E**

### **Severity**

Error

Message ID : VMD3867E

## **Long Form**

Internal error: bad arguments to kernel component

## **Short Form**

Bad args to kernel

### **Parameters**

No parameters are provided for this message type

## **Description**

An internal error occurred. Please contact Vormetric Support

## **Message ID : VMD3873E**

## **Severity**

Error

## **Long Form**

Internal error: the kernel component does not believe it's talking to the correct VMD

## Short Form

Kernel rejecting VMD

### Parameters

No parameters are provided for this message type

## Description

None

## Message ID : VMD3874E

## Severity

Error

## Long Form

The kernel component is unable to read its private key

## Short Form

Kernel priv key fail

### **Parameters**

No parameters are provided for this message type

### **Description**

None

### **Message ID : VMD3875E**

### **Severity**

Error

### **Long Form**

The kernel component unable to obtain its PWD

### **Short Form**

Kernel passwd fail

### **Parameters**

No parameters are provided for this message type

## **Description**

None

**Message ID : VMD3876E**

## **Severity**

Error

## **Long Form**

The kernel component contains an invalid PWD

## **Short Form**

Kernel passwd bad

## **Parameters**

No parameters are provided for this message type

## **Description**

None

Message ID : VMD3875E

1870

## **Message ID : VMD3877E**

### **Severity**

Error

### **Long Form**

The kernel component was unable to extract the key-encrypting-key

### **Short Form**

Kernel key extract fail

### **Parameters**

No parameters are provided for this message type

### **Description**

None

## **Message ID : VMD3878E**

### **Severity**

Error

Message ID : VMD3877E



## Long Form

The kernel component failed to pass internal sanity checks around the key-encrypting-key

## Short Form

Kernel key sanity fail

### Parameters

No parameters are provided for this message type

## Description

None

## Message ID : VMD3879E

## Severity

Error

## Long Form

The kernel component was able to perform all of the crypto operations around the policy push, but was unable to actually apply the new policy configuration

## Short Form

Kernel policy apply fail

### Parameters

No parameters are provided for this message type

## Description

None

## Message ID : VMD3888E

## Severity

Error

## Long Form

Unable to replicate coherent guardpoint info - {0}

## Short Form

Unable to replicate coherent GuardPoint info -

### Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

### Description

None

### Message ID : VMD3890E

### Severity

Error

### Long Form

Unable to commit configuration to GPFS cluster

### Short Form

Unable to commit configuration to GPFS cluster

### Parameters

No parameters are provided for this message type

Message ID : VMD3888E

## Description

None

**Message ID : VMD3891E**

## Severity

Error

## Long Form

Non-clustered GP {0} not allowed on clustered filesystem

## Short Form

Non-clustered GP not allowed on clustered filesystem

## Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

## Description

None

Message ID : VMD3890E

## Message ID : VMD3892E

### Severity

Error

### Long Form

Clustered GP {0} not allowed on non-clustered filesystem

### Short Form

Clustered GP not allowed on non-clustered filesystem

### Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

### Description

None

## Message ID : VMD3901E

## **Severity**

Error

## **Long Form**

Docker host browsing failed.

## **Short Form**

Docker host browse fail

## **Parameters**

No parameters are provided for this message type

## **Description**

None

**Message ID : VMD3903E**

## **Severity**

Error

## Long Form

Docker host browsing for image {0} failed.

## Short Form

Docker host browse fail

### Parameters

Label	Type	Usage
dockerid	Text	Docker image or container id

## Description

None

**Message ID : VMD3905E**

## Severity

Error

## Long Form

Docker image {0} file browsing for {1} failed.

Message ID : VMD3903E

## Short Form

Docker image file browse fail

### Parameters

Label	CEF Label	Type	Usage
dockerid	dockerid	Text	Docker image or container id
filePath	filePath	Text	Full path to file

## Description

None

**Message ID : VMD3907E**

## Severity

Error

## Long Form

Docker container {0} file browsing for {1} succeeded.



## Short Form

Docker container file browse fail

### Parameters

Label	CEF Label	Type	Usage
dockerid	dockerid	Text	Docker image or container id
filePath	filePath	Text	Full path to file

## Description

None

**Message ID : VMD3909E**

## Severity

Error

## Long Form

User browsing for image {0} with {1} failed.

## Short Form

Docker image user browse fail

### Parameters

Label	CEF Label	Type	Usage
dockerid	dockerid	Text	Docker image or container id
domain	dntdom	Text	A domain name (policy, network, users, etc)

## Description

None

**Message ID : VMD3911E**

## Severity

Error

## Long Form

User browsing for container {0} with {1} failed.

## Short Form

Docker container user browse fail

### Parameters

Label	CEF Label	Type	Usage
dockerid	dockerid	Text	Docker image or container id
domain	dntdom	Text	A domain name (policy, network, users, etc)

## Description

None

**Message ID : VMD3913E**

## Severity

Error

## Long Form

Domain browsing for image {0} failed.

Message ID : VMD3911E

1882

## Short Form

Docker image domain browse fail

### Parameters

Label	Type	Usage
dockerid	Text	Docker image or container id

## Description

None

**Message ID : VMD3915E**

## Severity

Error

## Long Form

Domain browsing for container {0} failed.

## Short Form

Docker container domain browse fail

Message ID : VMD3913E

1883

## Parameters

Label	Type	Usage
dockerid	Text	Docker image or container id

## Description

None

**Message ID : VMD3916E**

## Severity

Error

## Long Form

The current docker version "{0} {1}" is not supported.

## Short Form

No short form is provided for this message type

## Description

None

Message ID : VMD3915E

## Message ID : VMD3917E

### Severity

Error

### Long Form

Failed to connect to the Docker service at {0}. Please make sure the Docker service is up.

### Short Form

Failed to connect to Docker

### Parameters

Label	CEF Label	Type	Usage
url	request	Text	A uniform resource location

### Description

None

## Message ID : VMD3918E

## Severity

Error

## Long Form

An unauthorized attempt to update the authentication signature for file {0} has been prevented

## Short Form

Unauthorized signature change

### Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

## Description

None

**Message ID : VMD3922E**

## Severity

Error

Message ID : VMD3918E

## Long Form

Internal error: unable to determine {0}.

## Short Form

Unable to determine

### Parameters

Label	CEF Label	Type	Usage
showStr	reason	Text	Code specifying reason for allowing access, if any

## Description

None

**Message ID : VMD3923E**

## Severity

Error

## Long Form

Error from data governance module: {0}

Message ID : VMD3922E



## Short Form

DG error

### Parameters

No parameters are provided for this message type

## Description

None

## Message ID : VMD4245E

## Severity

Error

## Long Form

Key conversion failure when attempting to upgrade to fips-approved private key file format.

## Short Form

Key conv fail

### **Parameters**

No parameters are provided for this message type

### **Description**

None

### **Message ID : VMD4594E**

### **Severity**

Error

### **Long Form**

Failed to strengthen priority of the vmd, may face scheduling problems

### **Short Form**

Cannot raise priority

### **Parameters**

No parameters are provided for this message type

## Description

None

**Message ID : VMD4606E**

## Severity

Error

## Long Form

vm\_read\_file: fstat failed {0}

## Short Form

Stat error

## Parameters

Label	CEF Label	Type	Usage
ecode	cn1	Numeric	An error code

## Description

None

Message ID : VMD4594E

## Message ID : VMD4607E

### Severity

Error

### Long Form

vm\_read\_file: fopen failed for {0} errno {1}

### Short Form

Open error

### Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file
ecode	cn1	Numeric	An error code

### Description

None

## Message ID : VMD4608E

### Severity

Error

### Long Form

vm\_read\_file: malloc for size {0} failed {1}

### Short Form

Out of memory

### Parameters

Label	CEF Label	Type	Usage
slen	in	Numeric	Input byte count or length
ecode	cn1	Numeric	An error code

### Description

None

## Message ID : VMD4609E

### Severity

Error

### Long Form

vm\_read\_file: read() failed for {0}

### Short Form

Read error

### Parameters

Label	CEF Label	Type	Usage
ecode	cn1	Numeric	An error code

### Description

None

## Message ID : VMD4610E

## Severity

Error

## Long Form

vm\_write\_file: fopen failed for {0} mode {1} errno {2}

## Short Form

File open error

### Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file
mode	vds_mode	Text	File open mode
ecode	cn1	Numeric	An error code

## Description

None

**Message ID : VMD4612E**

Message ID : VMD4610E

1894

## Severity

Error

## Long Form

vm\_write\_file: fwrite() failed error {0}

## Short Form

Write error

### Parameters

Label	CEF Label	Type	Usage
ecode	cn1	Numeric	An error code

## Description

None

**Message ID : VMD4617E**

## Severity

Error

Message ID : VMD4612E



## Long Form

The previous message {0} was repeated {1} times

## Short Form

Repeat message

### Parameters

Label	CEF Label	Type	Usage
msgid	vds_msgid	Text	A unique log message identifier
count	vds_count	Numeric	A generic count value

## Description

None

# Logger VMD: Fatal errors

**Message ID : VMD3767F**

## Severity

Fatal error

## Long Form

No attribute {0} was found in the configuration file located at {1}. Please supply this attribute or re-install the product and try again.

## Short Form

Attribute missing

### Parameters

Label	CEF Label	Type	Usage
showStr	reason	Text	Code specifying reason for allowing access, if any
filePath	filePath	Text	Full path to file

## Description

None

## Message ID : VMD3768F

### Severity

Fatal error

### Long Form

Unable to parse the URL {0}. This attribute is located in the config file at {1}. Please fix the URL or re-install this product.

### Short Form

Bad URL in config file

#### Parameters

Label	CEF Label	Type	Usage
url	request	Text	A uniform resource location
filePath	filePath	Text	Full path to file

### Description

None

## Message ID : VMD3769F

### Severity

Fatal error

### Long Form

Internal error: unable to set attribute {0}.

### Short Form

Bad attribute

#### Parameters

Label	CEF Label	Type	Usage
showStr	reason	Text	Code specifying reason for allowing access, if any

### Description

None

## Message ID : VMD3770F

## Severity

Fatal error

## Long Form

The VMD failed to establish a communication channel to the Key Manager.

## Short Form

Cannot contact server

## Parameters

No parameters are provided for this message type

## Description

The agent is unable to reach the Security Server. You may see any of the following error messages: COM4583F, COM4633W, VMD3770F, VMD3885I or VMD3886I. You may experience any of the following:

1. Connection to the Security Server is down.
2. The VMD Host has been deleted from the Security Server.
3. The host does not have "Communication Enabled" in the Security Server UI.
4. The VMD's host may be deleted from the Security Server. Run the register\_host utility to re-register the VMD with the Security Server.

## Message ID : VMD3771F

### Severity

Fatal error

### Long Form

Logging setup failure. Error code {0}; "{1}"

### Short Form

Log setup error

### Parameters

Label	CEF Label	Type	Usage
ecode	cn1	Numeric	An error code
showStr	reason	Text	Code specifying reason for allowing access, if any

### Description

None

## **Message ID : VMD3772F**

### **Severity**

Fatal error

### **Long Form**

Logging setup failure: VMD logger information not found in Key Manager response.

### **Short Form**

Missing logger info

### **Parameters**

No parameters are provided for this message type

### **Description**

None

## **Message ID : VMD3797F**

### **Severity**

Fatal error

## **Long Form**

The VMD is unable to listen for requests from the Key Manager. Shutting down.

## **Short Form**

Cannot list for server req.

### **Parameters**

No parameters are provided for this message type

## **Description**

None

## **Message ID : VMD3894F**

## **Severity**

Fatal error

## **Long Form**

The server does not support required oneway communications.



## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : VMD4595F**

## **Severity**

Fatal error

## **Long Form**

The agent could not allocate enough memory. Contact support.

## **Short Form**

Out of memory

## **Parameters**

No parameters are provided for this message type

## Description

None

## Message ID : VMD4616F

## Severity

Fatal error

## Long Form

The previous message {0} was repeated {1} times

## Short Form

Repeat message

## Parameters

Label	CEF Label	Type	Usage
msgid	vds_msgid	Text	A unique log message identifier
count	vds_count	Numeric	A generic count value

## **Description**

None

# Logger VMD: Information

**Message ID : VMD3201I**

## Severity

Information

## Long Form

LDT: Live data transformation has been paused by "{0}"

## Short Form

LDT paused

### Parameters

Label	CEF Label	Type	Usage
shost	shost	Text	Source host name

## Description

None

## Message ID : VMD3202I

### Severity

Information

### Long Form

LDT: Live data transformation has been resumed by "{0}"

### Short Form

LDT resumed

#### Parameters

Label	CEF Label	Type	Usage
shost	shost	Text	Source host name

### Description

None

## Message ID : VMD3548I

## **Severity**

Information

## **Long Form**

RSA key verification Failed

## **Short Form**

No short form is provided for this message type

## **Description**

None

## **Message ID : VMD3558I**

## **Severity**

Information

## **Long Form**

RSA key verified

## Short Form

No short form is provided for this message type

## Description

None

## Message ID : VMD3626I

## Severity

Information

## Long Form

{0} is MOUNTED

## Short Form

Mount success

## Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

## Description

None

## Message ID : VMD3640I

## Severity

Information

## Long Form

STARTED on {0} PORT {1} VERSION: {2}

## Short Form

VMD Startup

## Parameters

Label	CEF Label	Type	Usage
osname	cs2	Text	A name identifying the agent operating system
port	spt	Numeric	A socket port number
version	vds_version	Text	Software version string



## Description

None

**Message ID : VMD3663I**

## Severity

Information

## Long Form

{0} is not mounted

## Short Form

Mount fail

## Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

## Description

None

Message ID : VMD3640I

# Message ID : VMD3773I

## Severity

Information

## Long Form

The {0} is starting. It was invoked at the command line like this: "{1}"

## Short Form

VMD startup

### Parameters

Label	CEF Label	Type	Usage
agent	deviceProcessName	Text	The short identifier of the agent software
showStr	reason	Text	Code specifying reason for allowing access, if any

## Description

None

## **Message ID : VMD3778I**

### **Severity**

Information

### **Long Form**

The VMD is shutting down.

### **Short Form**

VMD shutdown

### **Parameters**

No parameters are provided for this message type

### **Description**

None

## **Message ID : VMD3781I**

### **Severity**

Information

## **Long Form**

Successfully received and implemented a new security configuration.

## **Short Form**

New Config OK

### **Parameters**

No parameters are provided for this message type

## **Description**

None

## **Message ID : VMD3785I**

## **Severity**

Information

## **Long Form**

Host file browsing for {0} succeeded.

## Short Form

Host browse OK

### Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

## Description

None

**Message ID : VMD3794I**

## Severity

Information

## Long Form

Query security config succeeded.

## Short Form

Query config OK

Message ID : VMD3785I

1916

### **Parameters**

No parameters are provided for this message type

### **Description**

None

**Message ID : VMD3798I**

### **Severity**

Information

### **Long Form**

Delete host operation succeeded.

### **Short Form**

Host delete OK

### **Parameters**

No parameters are provided for this message type

Message ID : VMD3794I

1917

## Description

None

**Message ID : VMD3800I**

## Severity

Information

## Long Form

RESTARTED SDK Server at PORT {0}.

## Short Form

SDK server restart

## Parameters

Label	CEF Label	Type	Usage
port	spt	Numeric	A socket port number

## Description

None

Message ID : VMD3798I

## **Message ID : VMD3803I**

### **Severity**

Information

### **Long Form**

Shutting down file system service.

### **Short Form**

Service stop

### **Parameters**

No parameters are provided for this message type

### **Description**

None

## **Message ID : VMD3804I**

### **Severity**

Information



## Long Form

Stopping file system service...

## Short Form

Service shutdown

### Parameters

No parameters are provided for this message type

## Description

None

## Message ID : VMD3814I

## Severity

Information

## Long Form

Initializing the signature request {0}

## Short Form

Init sig req start

### Parameters

Label	CEF Label	Type	Usage
showStr	reason	Text	Code specifying reason for allowing access, if any

## Description

None

## Message ID : VMD3815I

## Severity

Information

## Long Form

Finished initializing the signature request {0}

## Short Form

Init sig req end

Message ID : VMD3814I

### Parameters

Label	CEF Label	Type	Usage
showStr	reason	Text	Code specifying reason for allowing access, if any

### Description

None

### Message ID : VMD3817I

### Severity

Information

### Long Form

Generating the file list for the signature request {0}

### Short Form

Gen sig file list

### Parameters

Label	CEF Label	Type	Usage
showStr	reason	Text	Code specifying reason for allowing access, if any

Message ID : VMD3815I

Label	CEF Label	Type	Usage

## Description

None

## Message ID : VMD3818I

## Severity

Information

## Long Form

Finished generating the file list for the signature request {0}. Number of files in the list: {1}

## Short Form

Sig file list complete

## Parameters

Label	CEF Label	Type	Usage
showStr	reason	Text	Code specifying reason for allowing access, if any
nfile	vds_nfile	Numeric	The number of files processed

## Description

None

## Message ID : VMD3820I

## Severity

Information

## Long Form

Generating the signatures for the signature request {0}

## Short Form

Generating sigs

## Parameters

Label	CEF Label	Type	Usage
showStr	reason	Text	Code specifying reason for allowing access, if any

## Description

None

Message ID : VMD3818I

# Message ID : VMD3821I

## Severity

Information

## Long Form

Finished generating the signatures for the signature request {0}. Number of processed files: {1}. Number of generated signatures: {2}. Number of failed files: {3}

## Short Form

Generated sigs

### Parameters

Label	CEF Label	Type	Usage
showStr	reason	Text	Code specifying reason for allowing access, if any
nfile	vds_nfile	Numeric	The number of files processed
nsig	vds_nsig	Numeric	The number of signatures generated
nerror	vds_nerror	Numeric	The number of errors encountered

## Description

None

## Message ID : VMD3823I

## Severity

Information

## Long Form

Failed to get the file attributes for {0}, error code {1}, error message: {2}

## Short Form

Sig file attr error

## Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file
ecode	cn1	Numeric	An error code
showStr	reason	Text	Code specifying reason for allowing access, if any

## Description

None

## Message ID : VMD3825I

## Severity

Information

## Long Form

Generating the signatures for the signature request {0}, {1} out of {2} files have been processed

## Short Form

Sig progress

### Parameters

Label	CEF Label	Type	Usage
showStr	reason	Text	Code specifying reason for allowing access, if any
nsig	vds_nsig	Numeric	The number of signatures generated
nfile	vds_nfile	Numeric	The number of files processed



## Description

None

## Message ID : VMD3827I

## Severity

Information

## Long Form

Completed the signature request {0} successfully

## Short Form

Sig sig req done

## Parameters

Label	CEF Label	Type	Usage
showStr	reason	Text	Code specifying reason for allowing access, if any

## Description

None

Message ID : VMD3825I

## Message ID : VMD3829I

### Severity

Information

### Long Form

Canceled the signature request {0}

### Short Form

Sig req cancelled

### Parameters

Label	CEF Label	Type	Usage
showStr	reason	Text	Code specifying reason for allowing access, if any

### Description

None

## Message ID : VMD3832I

## Severity

Information

## Long Form

Generating the file list for the signature request {0}, {1} files have been written to the list

## Short Form

Sig file generation in progress

### Parameters

Label	CEF Label	Type	Usage
showStr	reason	Text	Code specifying reason for allowing access, if any
nfile	vds_nfile	Numeric	The number of files processed

## Description

None

## Message ID : VMD3836I

## **Severity**

Information

## **Long Form**

Finished writing the signature disk file

## **Short Form**

Sig write complete

## **Parameters**

No parameters are provided for this message type

## **Description**

None

**Message ID : VMD3839I**

## **Severity**

Information

## Long Form

Finished pushing a new signature database to the kernel

## Short Form

Sig push to kernel OK

### Parameters

No parameters are provided for this message type

## Description

None

## Message ID : VMD3841I

## Severity

Information

## Long Form

opendir failed for {0} for the signature request {1}, error code {2}

## Short Form

Sig opendir error

### Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file
showStr	reason	Text	Code specifying reason for allowing access, if any
ecode	cnl	Numeric	An error code

## Description

None

## Message ID : VMD3842I

### Severity

Information

## Long Form

User browsing for {0} succeeded.

## Short Form

User browse OK

### Parameters

Label	CEF Label	Type	Usage
domain	dntdom	Text	A domain name (policy, network, users, etc)

## Description

None

## Message ID : VMD3847I

## Severity

Information

## Long Form

Domain browsing succeeded.

## Short Form

Domain browse OK

Message ID : VMD3842I

### Parameters

No parameters are provided for this message type

### Description

None

### Message ID : VMD3851I

### Severity

Information

### Long Form

Canceling the signature request {0}

### Short Form

Sig req cancelled

### Parameters

Label	CEF Label	Type	Usage
showStr	reason	Text	Code specifying reason for allowing access, if any



## Description

None

## Message ID : VMD3852I

## Severity

Information

## Long Form

Querying the status of the signature request {0}

## Short Form

Sig req status query

## Parameters

Label	CEF Label	Type	Usage
showStr	reason	Text	Code specifying reason for allowing access, if any

## Description

None

Message ID : VMD3851I

## Message ID : VMD3853I

### Severity

Information

### Long Form

Sending {0} signatures for the signature request {1} to the Key Manager

### Short Form

Sending sigs

#### Parameters

Label	CEF Label	Type	Usage
nsig	vds_nsig	Numeric	The number of signatures generated
showStr	reason	Text	Code specifying reason for allowing access, if any

### Description

None

## Message ID : VMD3854I

### Severity

Information

### Long Form

{0} signatures of the signature request {1} have been sent to the Key Manager

### Short Form

Sent sigs

#### Parameters

Label	CEF Label	Type	Usage
nsig	vds_nsig	Numeric	The number of signatures generated
showStr	reason	Text	Code specifying reason for allowing access, if any

### Description

None

## **Message ID : VMD3856I**

### **Severity**

Information

### **Long Form**

The Key Manager canceled the signature data push

### **Short Form**

Send sigs cancelled

### **Parameters**

No parameters are provided for this message type

### **Description**

None

## **Message ID : VMD3857I**

### **Severity**

Information

## Long Form

Got the signature data push from the Key Manager. Number of signatures in the push: {0}. Total number of signatures from the Key Manager: {1}

## Short Form

Sig push from server

### Parameters

Label	CEF Label	Type	Usage
nsig	vds_nsig	Numeric	The number of signatures generated
nfile	vds_nfile	Numeric	The number of files processed

## Description

None

**Message ID : VMD3859I**

## Severity

Information

Message ID : VMD3857I

1940

## Long Form

Completed the signature request {0} with some failed files

## Short Form

Sig reg partially done

### Parameters

Label	CEF Label	Type	Usage
showStr	reason	Text	Code specifying reason for allowing access, if any

## Description

None

## Message ID : VMD3861I

## Severity

Information

## Long Form

The Key Manager canceled the signature sending for the signature request {0}

Message ID : VMD3859I

## Short Form

Sig req cancelled

### Parameters

Label	CEF Label	Type	Usage
showStr	reason	Text	Code specifying reason for allowing access, if any

## Description

None

## Message ID : VMD3862I

## Severity

Information

## Long Form

Running in FIPS 140-2 mode, using {0}

## Short Form

FIPS 140-2 mode

Message ID : VMD3861I

### Parameters

Label	CEF Label	Type	Usage
version	vds_version	Text	Software version string

### Description

None

### Message ID : VMD3863I

### Severity

Information

### Long Form

Generating the file list for the signature request {0}, {1} files and directories have been scanned

### Short Form

Sig scan in progress

### Parameters

Label	CEF Label	Type	Usage
showStr	reason	Text	Code specifying reason for allowing access, if any

Message ID : VMD3862I



Label	CEF Label	Type	Usage
nfile	vds_nfile	Numeric	The number of files processed

## Description

None

## Message ID : VMD3868I

## Severity

Information

## Long Form

LDAP search of {0}/{1} for {2} returned "{3}"

## Short Form

LDAP search error

## Parameters

Label	CEF Label	Type	Usage
url	request	Text	A uniform resource location

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file
effect	vds_effect	Text	Policy effect
showStr	reason	Text	Code specifying reason for allowing access, if any

## Description

None

## Message ID : VMD3870I

## Severity

Information

## Long Form

Configuration data was supplied by "{0}".

## Short Form

Config source

### Parameters

Label	CEF Label	Type	Usage
-------	-----------	------	-------

Message ID : VMD3868I

1945

url	request	Text	A uniform resource location
-----	---------	------	-----------------------------

## Description

None

## Message ID : VMD3880I

## Severity

Information

## Long Form

The Key Manager was upgraded recently; informing it that this agent is challenge-response aware

## Short Form

Try new host password req

## Parameters

No parameters are provided for this message type

## Description

None

Message ID : VMD3870I

## **Message ID : VMD3881I**

### **Severity**

Information

### **Long Form**

The new certificate set has been activated

### **Short Form**

New certs activated

### **Parameters**

No parameters are provided for this message type

### **Description**

None

## **Message ID : VMD3883I**

### **Severity**

Information

## Long Form

Certificates for the {0} agent expire in {1} days

## Short Form

Certificate lifetime

### Parameters

Label	CEF Label	Type	Usage
agent	deviceProcessName	Text	The short identifier of the agent software
daysleft	vds_daysleft	Numeric	Days until certificate expiry

## Description

None

**Message ID : VMD3885I**

## Severity

Information

Message ID : VMD3883I

## Long Form

The VMD failed to initialize with the Key Manager. This may indicate that the connection to the server is down, the VMD's host has been deleted from the Key Manager, or "Communication Enabled" for the host has not been enabled in the Key Manager UI.

## Short Form

VMD/Server init fail

### Parameters

No parameters are provided for this message type

## Description

The agent is unable to reach the Security Server. You may see any of the following error messages: COM4583F, COM4633W, VMD3770F, VMD3885I or VMD3886I. You may experience any of the following:

1. Connection to the Security Server is down.
2. The VMD Host has been deleted from the Security Server.
3. The host does not have "Communication Enabled" in the Security Server UI.
4. The VMD's host may be deleted from the Security Server. Run the register\_host utility to re-register the VMD with the Security Server.

# Message ID : VMD3886I

## Severity

Information

## Long Form

The VMD's host may no longer be registered with a Key Manager. The VMD's host may have been deleted from the Key Manager. You may want to run the register\_host utility to re-register the VMD with a Key Manager.

## Short Form

VMD poss unregistered

## Parameters

No parameters are provided for this message type

## Description

The agent is unable to reach the Security Server. You may see any of the following error messages: COM4583F, COM4633W, VMD3770F, VMD3885I or VMD3886I. You may experience any of the following:

1. Connection to the Security Server is down.
2. The VMD Host has been deleted from the Security Server.
3. The host does not have "Communication Enabled" in the Security Server UI.
4. The VMD's host may be deleted from the Security Server. Run the register\_host utility to re-register the VMD with the Security Server.

## Message ID : VMD3893I

### Severity

Information

### Long Form

Clustered property of GP {0} is honored per Key Manager

### Short Form

Clustered property of GP is honored per Key Manager

### Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

### Description

None



## Message ID : VMD3895I

### Severity

Information

### Long Form

RSA certificates detected for the {0} agent, will renew with EC certificates

### Short Form

Switching to EC certs

#### Parameters

Label	CEF Label	Type	Usage
agent	deviceProcessName	Text	The short identifier of the agent software

### Description

None

## Message ID : VMD3896I

## Severity

Information

## Long Form

RSA certificates detected for the {0} agent, will not renew with EC certificates as ports 8446/7 not open to Key Manager

## Short Form

No Switch to EC certs due to missing 8446/7 ports

### Parameters

Label	CEF Label	Type	Usage
agent	deviceProcessName	Text	The short identifier of the agent software

## Description

None

## Message ID : VMD3897I

## Severity

Information

Message ID : VMD3896I

## Long Form

New comms session with {0} using token {1}

## Short Form

Comms session

### Parameters

Label	CEF Label	Type	Usage
shost	shost	Text	Source host name
token	vds_token	Text	A token name (e.g. for one-time-passwords)

## Description

None

**Message ID : VMD3898I**

## Severity

Information

Message ID : VMD3897I

1954

## Long Form

STARTED on {0} VERSION: {1}

## Short Form

VMD Startup

### Parameters

Label	CEF Label	Type	Usage
osname	cs2	Text	A name identifying the agent operating system
version	vds_version	Text	Software version string

## Description

None

**Message ID : VMD3900I**

## Severity

Information

Message ID : VMD3898I

1955

## Long Form

Docker host browsing succeeded.

## Short Form

Docker host browse OK

### Parameters

No parameters are provided for this message type

## Description

None

## Message ID : VMD3902I

## Severity

Information

## Long Form

Docker host browsing for image {0} succeeded.

## Short Form

Docker host browse OK

### Parameters

Label	Type	Usage
dockerid	Text	Docker image or container id

## Description

None

## Message ID : VMD3904I

## Severity

Information

## Long Form

Docker image {0} file browsing for {1} succeeded.

## Short Form

Docker image file browse OK

Message ID : VMD3902I

1957

## Parameters

Label	CEF Label	Type	Usage
dockerid	dockerid	Text	Docker image or container id
filePath	filePath	Text	Full path to file

## Description

None

## Message ID : VMD3906I

## Severity

Information

## Long Form

Docker container {0} file browsing for {1} succeeded.

## Short Form

Docker container file browse OK

## Parameters

Label	CEF Label	Type	Usage
dockerid	dockerid	Text	Docker image or container id
filePath	filePath	Text	Full path to file

## Description

None

## Message ID : VMD3908I

## Severity

Information

## Long Form

User browsing for image {0} with {1} succeeded.

## Short Form

Docker image user browse OK



## Parameters

Label	CEF Label	Type	Usage
dockerid	dockerid	Text	Docker image or container id
domain	dntdom	Text	A domain name (policy, network, users, etc)

## Description

None

**Message ID : VMD3910I**

## Severity

Information

## Long Form

User browsing for container {0} with {1} succeeded.

## Short Form

Docker container user browse OK

## Parameters

Label	CEF Label	Type	Usage
dockerid	dockerid	Text	Docker image or container id
domain	dntdom	Text	A domain name (policy, network, users, etc)

## Description

None

**Message ID : VMD3912I**

## Severity

Information

## Long Form

Domain browsing for image {0} succeeded.

## Short Form

Docker image domain browse OK

### Parameters

Label	Type	Usage
dockerid	Text	Docker image or container id

### Description

None

**Message ID : VMD3914I**

### Severity

Information

### Long Form

Domain browsing for container {0} succeeded.

### Short Form

Docker container domain browse OK

### Parameters

Label	Type	Usage
dockerid	Text	Docker image or container id

Message ID : VMD3912I

Label	Type	Usage

## Description

None

## Message ID : VMD3919I

## Severity

Information

## Long Form

Policy "{0}" version {1} received from Key Manager

## Short Form

Policy update

## Parameters

Label	CEF Label	Type	Usage
pol	cs1	Text	Policy name
verno	vds_verno	Numeric	A version number

## **Description**

None

## **Message ID : VMD4246I**

## **Severity**

Information

## **Long Form**

Detected upgrade situation from pre-FIPS (4.4.0) to post-FIPS (4.4.1). Converting the private key format now.

## **Short Form**

Key converted

## **Parameters**

No parameters are provided for this message type

## **Description**

None

## **Message ID : VMD4611I**

### **Severity**

Information

### **Long Form**

vm\_write\_file: Empty write buffer

### **Short Form**

Empty write buf

### **Parameters**

No parameters are provided for this message type

### **Description**

None

## **Message ID : VMD4619I**

### **Severity**

Information

## Long Form

The previous message {0} was repeated {1} times

## Short Form

Repeat message

### Parameters

Label	CEF Label	Type	Usage
msgid	vds_msgid	Text	A unique log message identifier
count	vds_count	Numeric	A generic count value

## Description

None

## Message ID : VMD4620I

## Severity

Information

## Long Form

The space available for log files in {0} is low ({1} MB)

## Short Form

Log space low

### Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file
count	vds_count	Numeric	A generic count value

## Description

None



# Logger VMD: Warnings

**Message ID : VMD3714W**

## Severity

Warning

## Long Form

check\_mount: {0} {1}{2} match failed({3})

## Short Form

No short form is provided for this message type

## Description

None

**Message ID : VMD3805W**

## Severity

Warning

## Long Form

Unhandled service opcode seen. Opcode = {0}

## Short Form

Unhandled opcode

### Parameters

Label	CEF Label	Type	Usage
ecode	cn1	Numeric	An error code

## Description

None

**Message ID : VMD3806W**

## Severity

Warning

## Long Form

Unrecognized service opcode seen. Opcode = {0}

Message ID : VMD3805W

## Short Form

Unknown opcode

### Parameters

Label	CEF Label	Type	Usage
ecode	cn1	Numeric	An error code

## Description

None

## Message ID : VMD3813W

### Severity

Warning

## Long Form

The VMD is shutting down.

## Short Form

VMD Shutdown

Message ID : VMD3806W

## Parameters

No parameters are provided for this message type

## Description

System shutdown, reboot or system re-registration will cause this message to display because the Vormetric daemon process was terminated.

## Message ID : VMD3824W

## Severity

Warning

## Long Form

Failed to create the signature for {0} for the signature request {1}, error code {2}

## Short Form

Sig creation error

## Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Message ID : VMD3813W

1971

Label	CEF Label	Type	Usage
showStr	reason	Text	Code specifying reason for allowing access, if any
ecode	cn1	Numeric	An error code

## Description

None

## Message ID : VMD3826W

## Severity

Warning

## Long Form

{0} is invalid for the signature request {1}

## Short Form

Bad sig file

## Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Message ID : VMD3824W

1972

Label	CEF Label	Type	Usage
showStr	reason	Text	Code specifying reason for allowing access, if any

## Description

None

## Message ID : VMD3850W

## Severity

Warning

## Long Form

Could not find the signature request {0}

## Short Form

Sig req mismatch

## Parameters

Label	CEF Label	Type	Usage
showStr	reason	Text	Code specifying reason for allowing access, if any

Message ID : VMD3826W

1973

## Description

None

**Message ID : VMD3860W**

## Severity

Warning

## Long Form

The signature request {0} is already initialized

## Short Form

Sig req duplicated

## Parameters

Label	CEF Label	Type	Usage
showStr	reason	Text	Code specifying reason for allowing access, if any

## Description

None

Message ID : VMD3850W

## **Message ID : VMD3869W**

### **Severity**

Warning

### **Long Form**

No LDAP server details were found (missing or incomplete ldap.conf)

### **Short Form**

No LDAP server

#### **Parameters**

No parameters are provided for this message type

### **Description**

No LDAP configuration data was found on the host system. This usually occurs because LDAP services have not been installed or configured properly.

## **Message ID : VMD3871W**



## Severity

Warning

## Long Form

Unauthorized communication attempt from "{0}" rejected

## Short Form

Unauth comms rejected

### Parameters

Label	CEF Label	Type	Usage
url	request	Text	A uniform resource location

## Description

None

**Message ID : VMD3882W**

## Severity

Warning

Message ID : VMD3871W

## **Long Form**

An error occurred with a new certificate set so the previous set has been restored

## **Short Form**

Backup certs restored

### **Parameters**

No parameters are provided for this message type

## **Description**

None

## **Message ID : VMD3887W**

## **Severity**

Warning

## **Long Form**

Unable to initialize/join Vormetric Cluster Group - proceeding unclustered

## Short Form

initialize/join CipherTrust Cluster Group - proceeding unclustered

### Parameters

No parameters are provided for this message type

## Description

None

## Message ID : VMD3889W

## Severity

Warning

## Long Form

Cluster coherent GP {0} not allowed on unclustered node

## Short Form

Cluster coherent GP not allowed on unclustered node

### Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

### Description

None

### Message ID : VMD3899W

### Severity

Warning

### Long Form

The authentication signature for file {0} has changed

### Short Form

Signature changed

### Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Message ID : VMD3889W

Label	CEF Label	Type	Usage

## Description

None

## Message ID : VMD3920W

## Severity

Warning

## Long Form

Agent failing over to server "{0}"

## Short Form

Failover

## Parameters

Label	CEF Label	Type	Usage
shost	shost	Text	Source host name

## Description

None

**Message ID : VMD3921W**

## Severity

Warning

## Long Form

Agent reverting to assigned server "{0}"

## Short Form

Failover end

## Parameters

Label	CEF Label	Type	Usage
shost	shost	Text	Source host name

## Description

None

Message ID : VMD3920W

## Message ID : VMD3924W

### Severity

Warning

### Long Form

Unknown key manager in URL {0} will be ignored. This attribute is located in the config file at {1}.

### Short Form

Unknown URL in config file

#### Parameters

Label	CEF Label	Type	Usage
url	request	Text	A uniform resource location
filePath	filePath	Text	Full path to file

### Description

None

## Message ID : VMD4618W

### Severity

Warning

### Long Form

The previous message {0} was repeated {1} times

### Short Form

Repeat message

#### Parameters

Label	CEF Label	Type	Usage
msgid	vds_msgid	Text	A unique log message identifier
count	vds_count	Numeric	A generic count value

### Description

None



# Message ID : VMD4621W

## Severity

Warning

## Long Form

The space available for log files in {0} is dangerously low ({1} MB)

## Short Form

Log space low

### Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file
count	vds_count	Numeric	A generic count value

## Description

The directory used to process log files is low on space. The "filePath" field gives the path and directory. The "count" field gives the remaining space (in MB).

**When space is low audit trails may become compromised, and error conditions may be unreported. This should be resolved immediately.**

# Message ID : VMD4622W

## Severity

Warning

## Long Form

Raising drop log message level to {0} because space consumed is now greater than {1}% and less than or equal to {2}%.

## Short Form

Raise drop space level

### Parameters

Label	CEF Label	Type	Usage
showStr	reason	Text	Code specifying reason for allowing access, if any
count	vds_count	Numeric	A generic count value
count	vds_count	Numeric	A generic count value

## Description

The space that holds log files uploaded to the Security Server is increasing. Logging levels are automatically modified to accommodate the load. The "reason" field details the change being imposed, and the two "count" fields depict the lower and upper "percentage full" values that caused this condition. The following strings may occur on the "reason" field:

<b>Reason</b>	<b>Meaning</b>
Drop None	No adjustments currently in force
Speed Up	The agent will try to upload logs to the Security Server in larger batches
Drop Info	No INFO level logs will be uploaded
Drop Warn	No WARN level logs will be uploaded
Drop Error	No ERROR level logs will be uploaded

## Message ID : VMD4623W

### Severity

Warning

### Long Form

Raising drop log message level to {0} because number of files is now greater than {1}% and less than or equal to {2}%.

### Short Form

Raise drop file level

### Parameters

<b>Label</b>	<b>CEF Label</b>	<b>Type</b>	<b>Usage</b>
showStr	reason	Text	Code specifying reason for allowing access, if any

Label	CEF Label	Type	Usage
count	vds_count	Numeric	A generic count value
count	vds_count	Numeric	A generic count value

## Description

Files pending upload to the Security Server are increasing, so the agent has temporarily adjusted the logging parameters to handle the situation. The "reason" field details the change imposed, and the two "count" fields indicate the lower and upper percentages of the maximum permitted number of files. See VMD4622W for usage of the "reason" field.

## Message ID : VMD4624W

### Severity

Warning

### Long Form

Lowering drop log message level to {0} because space consumed is now greater than {1}% and less than or equal to {2}%.

### Short Form

Lower drop space level

## Parameters

Label	CEF Label	Type	Usage
showStr	reason	Text	Code specifying reason for allowing access, if any
count	vds_count	Numeric	A generic count value
count	vds_count	Numeric	A generic count value

## Description

The space used to hold log files for uploading to the Security Server is decreasing, so the agent has temporarily adjusted the logging parameters to handle the situation. See VMD4622W for details about the fields used.

## Message ID : VMD4625W

### Severity

Warning

### Long Form

Lowering drop log message level to {0} because number of files is now greater than {1}% and less than or equal to {2}%.

### Short Form

Lower drop file level

## Parameters

Label	CEF Label	Type	Usage
showStr	reason	Text	Code specifying reason for allowing access, if any
count	vds_count	Numeric	A generic count value
count	vds_count	Numeric	A generic count value

## Description

The number of files pending upload to the Security Server is decreasing, so the agent has temporarily adjusted the logging parameters to handle the situation. See VMD4623W for details about the fields used.

## Message ID : VMD4636W

### Severity

Warning

### Long Form

Unable to determine expiry date from certificate {0}

### Short Form

Cannot get expiry date

### Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

### Description

None

### Message ID : VMD4639W

### Severity

Warning

### Long Form

Corrupt log data from kernel in file {0} - some records lost

### Short Form

Corrupt log file

### Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Message ID : VMD4636W

Label	CEF Label	Type	Usage

## Description

None

## Message ID : VMD4640W

## Severity

Warning

## Long Form

Invalid directory in log directory. {0} Please remove.

## Short Form

Invalid directory in log directory.

## Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file



## Description

None

# Logger XFM: Errors

**Message ID : XFM4501E**

## Severity

Error

## Long Form

Decompression failure: the size of the data resulting from decompression is not the same size as before compression. Possible data corruption.

## Short Form

Size mismatch

### Parameters

No parameters are provided for this message type

## Description

None

## **Message ID : XFM4502E**

### **Severity**

Error

### **Long Form**

Compression setup failure: module not initialized.

### **Short Form**

Compression init fail

### **Parameters**

No parameters are provided for this message type

### **Description**

None

## **Message ID : XFM4504E**

### **Severity**

Error

## **Long Form**

Compression setup failure: no applicable module initialized.

## **Short Form**

Compression setup fail

### **Parameters**

No parameters are provided for this message type

## **Description**

None

**Message ID : XFM4535E**

## **Severity**

Error

## **Long Form**

Decompression got corrupted buffer (invalid size of encrypted data).

## Short Form

Encryption buffer corrupt

### Parameters

No parameters are provided for this message type

## Description

None

## Message ID : XFM4568E

## Severity

Error

## Long Form

Compression failure: destination buffer too small: {0} < {1}.

## Short Form

Buffer too small

## Parameters

Label	CEF Label	Type	Usage
slen	in	Numeric	Input byte count or length
dlen	out	Numeric	Output byte count or length

## Description

None

## Message ID : XFM4589E

## Severity

Error

## Long Form

Unable to initialize the message digest subsystem. The operation will fail.

## Short Form

Digest setup fail

### **Parameters**

No parameters are provided for this message type

### **Description**

None

**Message ID : XFM4590E**

### **Severity**

Error

### **Long Form**

Unable to compute the message digest value.

### **Short Form**

Cannot compute digest

### **Parameters**

No parameters are provided for this message type

## **Description**

None

**Message ID : XFM4591E**

## **Severity**

Error

## **Long Form**

Unable to the retrieve the message digest value.

## **Short Form**

Cannot extract digest

## **Parameters**

No parameters are provided for this message type

## **Description**

None

Message ID : XFM4590E



# Logger XFM: Fatal errors

**Message ID : XFM4508F**

## Severity

Fatal error

## Long Form

Unable to find chunk headers; possible data corruption.

## Short Form

Missing chunk hdr

## Parameters

No parameters are provided for this message type

## Description

None

**Message ID : XFM4509F**

## Severity

Fatal error

## Long Form

Decompression/decryption failure: output buffer size ({0} bytes) is too small.

## Short Form

Decomp/decrypt buffer too small

### Parameters

Label	CEF Label	Type	Usage
dlen	out	Numeric	Output byte count or length

## Description

None

## Message ID : XFM4518F

## Severity

Fatal error

Message ID : XFM4509F

## **Long Form**

Invalid encryption key size received from Key Manager. The operation will fail.

## **Short Form**

Invalid encr. key size

### **Parameters**

No parameters are provided for this message type

## **Description**

None

## **Message ID : XFM4519F**

## **Severity**

Fatal error

## **Long Form**

The agent could not allocate enough memory. Contact support.

## Short Form

Out of memory

### Parameters

No parameters are provided for this message type

## Description

None

## Message ID : XFM4525F

## Severity

Fatal error

## Long Form

Decryption fatal error: {0}. The restore operation will fail.

## Short Form

Decryption error

### Parameters

Label	CEF Label	Type	Usage
ecode	cn1	Numeric	An error code

### Description

None

### Message ID : XFM4532F

### Severity

Fatal error

### Long Form

Decryption information mismatch; possible data corruption.

### Short Form

Decryption info mismatch

### Parameters

No parameters are provided for this message type

Message ID : XFM4525F

## Description

None

**Message ID : XFM4536F**

## Severity

Fatal error

## Long Form

Compression module returned fatal error: {0}. The operation will fail.

## Short Form

Compression error

## Parameters

Label	CEF Label	Type	Usage
ecode	cn1	Numeric	An error code

## Description

None

Message ID : XFM4532F

## **Message ID : XFM4539F**

### **Severity**

Fatal error

### **Long Form**

Unable to set up encryption subsystem. The operation will fail.

### **Short Form**

Encryption setup fail

### **Parameters**

No parameters are provided for this message type

### **Description**

None

## **Message ID : XFM4540F**

### **Severity**

Fatal error

## **Long Form**

Decompression information mismatch; possible data corruption.

## **Short Form**

Decompression info mismatch

### **Parameters**

No parameters are provided for this message type

## **Description**

None

## **Message ID : XFM4541F**

## **Severity**

Fatal error

## **Long Form**

Data read problem: corrupted buffer header. Data corruption has possibly occurred. The restore operation will fail.



## Short Form

Corrupt buffer header

### Parameters

No parameters are provided for this message type

## Description

None

## Message ID : XFM4544F

## Severity

Fatal error

## Long Form

Unable to set up compression subsystem. The operation will fail.

## Short Form

Compression setup fail

### **Parameters**

No parameters are provided for this message type

### **Description**

None

**Message ID : XFM4546F**

### **Severity**

Fatal error

### **Long Form**

Compression module initialization failure. The backup operation will fail.

### **Short Form**

Compression init fail

### **Parameters**

No parameters are provided for this message type

Message ID : XFM4544F

## Description

None

**Message ID : XFM4561F**

## Severity

Fatal error

## Long Form

Decompression fatal error: {0}. The restore operation will fail.

## Short Form

Decompression error

## Parameters

Label	CEF Label	Type	Usage
ecode	cn1	Numeric	An error code

## Description

None

Message ID : XFM4546F

## Message ID : XFM4565F

### Severity

Fatal error

### Long Form

Input data length does not match buffer length: {0} != {1}. Data corruption has possible occurred. The restore operation will fail.

### Short Form

Data lenght mismatch

#### Parameters

Label	CEF Label	Type	Usage
slen	in	Numeric	Input byte count or length
dlen	out	Numeric	Output byte count or length

### Description

None

# Logger XFM: Information

**Message ID : XFM4507I**

## **Severity**

Information

## **Long Form**

Using no encryption.

## **Short Form**

Using no encryption

## **Parameters**

No parameters are provided for this message type

## **Description**

None

**Message ID : XFM4517I**

## **Severity**

Information

## **Long Form**

Shutting down compression/decompression subsystem.

## **Short Form**

Comp/decomp shutdown

### **Parameters**

No parameters are provided for this message type

## **Description**

None

## **Message ID : XFM4522I**

## **Severity**

Information

## **Long Form**

Data transformation code now using single-threaded algorithm.

## **Short Form**

Single-thread transform

### **Parameters**

No parameters are provided for this message type

## **Description**

None

## **Message ID : XFM4526I**

## **Severity**

Information

## **Long Form**

Using no compression.

## **Short Form**

Using no compression

### **Parameters**

No parameters are provided for this message type

## **Description**

None

## **Message ID : XFM4549I**

## **Severity**

Information

## **Long Form**

Using compression.

## **Short Form**

Using compression



## Parameters

No parameters are provided for this message type

## Description

None

## Message ID : XFM4557I

## Severity

Information

## Long Form

Using {0} encryption algorithm.

## Short Form

Using enc algorithm

## Parameters

Label	CEF Label	Type	Usage
key	cs3	Text	Name of key or key pair

Message ID : XFM4549I

## **Description**

None

**Message ID : XFM4559I**

## **Severity**

Information

## **Long Form**

Shutting down encryption/decryption subsystem.

## **Short Form**

Encrypt/decrypt shutdown

## **Parameters**

No parameters are provided for this message type

## **Description**

None

Message ID : XFM4557I

2017

# Logger XFM: Warnings

**Message ID : XFM4550W**

## **Severity**

Warning

## **Long Form**

Compression initialization failure: failed to initialize algorithm {0} upon startup.

## **Short Form**

Compression init fail

## **Parameters**

No parameters are provided for this message type

## **Description**

None