



CipherTrust Data Security Platform

CipherTrust Data Security Event and Log Messages Guide

Release 7.3.0

Document Version 1

November 22, 2022

*CipherTrust Data Security CipherTrust Transparent Encryption
CipherTrust Data Security CipherTrust Data Security Event and Log Messages Guide*

Release 7.3.0

November 9, 2022

Document Version 1

All information herein is either public information or is the property of and owned solely by Thales DIS France S.A. and/or its subsidiaries or affiliates who shall have and keep the sole right to file patent applications or any other kind of intellectual property protection in connection with such information.

Nothing herein shall be construed as implying or granting to you any rights, by license, grant or otherwise, under any intellectual and/or industrial property rights of or concerning any of Thales DIS France S.A. and any of its subsidiaries and affiliates (collectively referred to herein after as "Thales") information.

This document can be used for informational, non-commercial, internal and personal use only provided that:

- The copyright notice below, the confidentiality and proprietary legend and this full warning notice appear in all copies.
- This document shall not be posted on any network computer or broadcast in any media and no modification of any part of this document shall be made.

Use for any other purpose is expressly prohibited and may result in severe civil and criminal liabilities.

The information contained in this document is provided "AS IS" without any warranty of any kind. Unless otherwise expressly agreed in writing, Thales makes no warranty as to the value or accuracy of information contained herein.

The document could include technical inaccuracies or typographical errors. Changes are periodically added to the information herein. Furthermore, Thales reserves the right to make any change or improvement in the specifications data, information, and the like described herein, at any time.

Thales hereby disclaims all warranties and conditions with regard to the information contained herein, including all implied warranties of merchantability, fitness for a particular purpose, title and non-infringement. In no event shall Thales be liable, whether in contract, tort or otherwise, for any indirect, special or consequential damages or any damages whatsoever including but not limited to damages resulting from loss of use, data, profits, revenues, or customers, arising out of or in connection with the use or performance of information contained in this document.

Thales does not and shall not warrant that this product will be resistant to all possible attacks and shall not incur, and disclaims, any liability in this respect. Even if each product is compliant with current security standards in force on the date of their design, security mechanisms' resistance necessarily evolves according to the state of the art in security and notably under the emergence of new attacks. Under no circumstances, shall Thales be held liable for any third party actions and in particular in case of any successful attack against systems or equipment incorporating Thales products. Thales disclaims any liability with respect to security for direct, indirect, incidental or consequential damages that result from any use of its products. It is further stressed that independent testing and verification by the person using the product is particularly encouraged, especially in any application in which defective, incorrect or insecure functioning could result in damage to persons or property, denial of service or loss of privacy.

Copyright © 2009 - 2022 Thales Group. All rights reserved. Thales and the Thales logo are trademarks and service marks of Thales and/or its subsidiaries and affiliates and are registered in certain countries. All other trademarks and service marks, whether registered or not in specific countries, are the properties of their respective owners.

Table of Contents

Logger CA0: Errors	1
<u>Message ID : CA00642E</u>	1
<u>Message ID : CA00643E</u>	1
<u>Message ID : CA00644E</u>	2
<u>Message ID : CA00645E</u>	3
Logger CFG: Errors	4
<u>Message ID : CFG0026E</u>	4
<u>Message ID : CFG0027E</u>	4
<u>Message ID : CFG0028E</u>	5
<u>Message ID : CFG0029E</u>	6
<u>Message ID : CFG0030E</u>	6
<u>Message ID : CFG0031E</u>	7
<u>Message ID : CFG0032E</u>	8
<u>Message ID : CFG0033E</u>	8
<u>Message ID : CFG0034E</u>	9
<u>Message ID : CFG0264E</u>	10
<u>Message ID : CFG0306E</u>	10
<u>Message ID : CFG0333E</u>	11
<u>Message ID : CFG0334E</u>	12
<u>Message ID : CFG0335E</u>	12
<u>Message ID : CFG0336E</u>	13
<u>Message ID : CFG0339E</u>	14
<u>Message ID : CFG0341E</u>	14
<u>Message ID : CFG0520E</u>	15
<u>Message ID : CFG0521E</u>	16
<u>Message ID : CFG0522E</u>	16

Table of Contents

Logger CFG: Errors

<u>Message ID : CFG0523E</u>	17
<u>Message ID : CFG0524E</u>	18
<u>Message ID : CFG0527E</u>	19
<u>Message ID : CFG0528E</u>	19
<u>Message ID : CFG0529E</u>	20
<u>Message ID : CFG0530E</u>	21
<u>Message ID : CFG0531E</u>	21
<u>Message ID : CFG0532E</u>	22
<u>Message ID : CFG0636E</u>	23
<u>Message ID : CFG1334E</u>	23
<u>Message ID : CFG1335E</u>	24
<u>Message ID : CFG1352E</u>	25
<u>Message ID : CFG1367E</u>	25
<u>Message ID : CFG1368E</u>	26
<u>Message ID : CFG1400E</u>	27
<u>Message ID : CFG1514E</u>	28
<u>Message ID : CFG1515E</u>	28
<u>Message ID : CFG1517E</u>	29
<u>Message ID : CFG1705E</u>	30
<u>Message ID : CFG1727E</u>	30
<u>Message ID : CFG1734E</u>	31
<u>Message ID : CFG1735E</u>	32
<u>Message ID : CFG1775E</u>	32
<u>Message ID : CFG1776E</u>	33
<u>Message ID : CFG1777E</u>	34
<u>Message ID : CFG1778E</u>	34

Table of Contents

<u>Logger CFG: Errors</u>	
<u>Message ID : CFG1827E</u>	35
<u>Logger CFG: Fatal errors</u>	36
<u>Message ID : CFG1733E</u>	36
<u>Message ID : CFG1842E</u>	36
<u>Logger CFG: Information</u>	38
<u>Message ID : CFG0633I</u>	38
<u>Message ID : CFG0634I</u>	39
<u>Message ID : CFG1516I</u>	40
<u>Message ID : CFG1736I</u>	40
<u>Message ID : CFG1841I</u>	41
<u>Logger CFG: Warnings</u>	42
<u>Message ID : CFG1297W</u>	42
<u>Logger CGA: Errors</u>	43
<u>Message ID : CGA2614E</u>	43
<u>Message ID : CGA2617E</u>	43
<u>Message ID : CGA2618E</u>	44
<u>Message ID : CGA2619E</u>	45
<u>Message ID : CGA2620E</u>	45
<u>Message ID : CGA2621E</u>	46
<u>Message ID : CGA2624E</u>	47
<u>Message ID : CGA2625E</u>	48
<u>Message ID : CGA2626E</u>	48

Table of Contents

Logger CGA: Errors

<u>Message ID : CGA2627E</u>	49
<u>Message ID : CGA2628E</u>	50
<u>Message ID : CGA2629E</u>	51
<u>Message ID : CGA2634E</u>	52
<u>Message ID : CGA2635E</u>	53
<u>Message ID : CGA2636E</u>	54
<u>Message ID : CGA2637E</u>	55
<u>Message ID : CGA2638E</u>	55
<u>Message ID : CGA2639E</u>	56
<u>Message ID : CGA2645E</u>	57
<u>Message ID : CGA2648E</u>	58
<u>Message ID : CGA2649E</u>	59
<u>Message ID : CGA2650E</u>	60
<u>Message ID : CGA2651E</u>	61
<u>Message ID : CGA2652E</u>	62
<u>Message ID : CGA2653E</u>	63
<u>Message ID : CGA2654E</u>	64
<u>Message ID : CGA2655E</u>	65
<u>Message ID : CGA2656E</u>	66
<u>Message ID : CGA2657E</u>	67
<u>Message ID : CGA2658E</u>	68
<u>Message ID : CGA2659E</u>	69
<u>Message ID : CGA3003E</u>	70
<u>Message ID : CGA3004E</u>	71
<u>Message ID : CGA3007E</u>	71
<u>Message ID : CGA3008E</u>	72

Table of Contents

Logger CGA: Errors

<u>Message ID : CGA3009E</u>	73
<u>Message ID : CGA3010E</u>	74
<u>Message ID : CGA3011E</u>	75
<u>Message ID : CGA3012E</u>	76
<u>Message ID : CGA3013E</u>	76
<u>Message ID : CGA3014E</u>	77
<u>Message ID : CGA3015E</u>	78
<u>Message ID : CGA3016E</u>	79
<u>Message ID : CGA3017E</u>	79
<u>Message ID : CGA3018E</u>	80
<u>Message ID : CGA3021E</u>	81
<u>Message ID : CGA3022E</u>	82
<u>Message ID : CGA3023E</u>	83
<u>Message ID : CGA3024E</u>	83
<u>Message ID : CGA3059E</u>	84
<u>Message ID : CGA3060E</u>	85
<u>Message ID : CGA3061E</u>	86
<u>Message ID : CGA3062E</u>	87
<u>Message ID : CGA3063E</u>	88
<u>Message ID : CGA3064E</u>	89
<u>Message ID : CGA3065E</u>	90
<u>Message ID : CGA3066E</u>	91
<u>Message ID : CGA3067E</u>	92
<u>Message ID : CGA3068E</u>	92
<u>Message ID : CGA3069E</u>	93
<u>Message ID : CGA3070E</u>	94

Table of Contents

Logger CGA: Errors

<u>Message ID : CGA3071E</u>	95
<u>Message ID : CGA3072E</u>	96
<u>Message ID : CGA3073E</u>	97
<u>Message ID : CGA3074E</u>	98
<u>Message ID : CGA3075E</u>	99
<u>Message ID : CGA3076E</u>	99
<u>Message ID : CGA3077E</u>	100
<u>Message ID : CGA3078E</u>	101
<u>Message ID : CGA3079E</u>	102
<u>Message ID : CGA3080E</u>	103
<u>Message ID : CGA3081E</u>	104
<u>Message ID : CGA3082E</u>	105
<u>Message ID : CGA3083E</u>	106
<u>Message ID : CGA3084E</u>	106
<u>Message ID : CGA3085E</u>	107
<u>Message ID : CGA3086E</u>	108
<u>Message ID : CGA3087E</u>	109
<u>Message ID : CGA3088E</u>	110
<u>Message ID : CGA3089E</u>	111
<u>Message ID : CGA3090E</u>	112
<u>Message ID : CGA3091E</u>	113
<u>Message ID : CGA3092E</u>	114
<u>Message ID : CGA3093E</u>	115
<u>Message ID : CGA3094E</u>	116
<u>Message ID : CGA3095E</u>	117
<u>Message ID : CGA3096E</u>	117

Table of Contents

Logger CGA: Errors

<u>Message ID : CGA3097E</u>	118
<u>Message ID : CGA3098E</u>	119
<u>Message ID : CGA3099E</u>	120
<u>Message ID : CGA3100E</u>	121
<u>Message ID : CGA3101E</u>	122
<u>Message ID : CGA3102E</u>	122
<u>Message ID : CGA3103E</u>	123
<u>Message ID : CGA3109E</u>	124
<u>Message ID : CGA3110E</u>	125
<u>Message ID : CGA3111E</u>	126
<u>Message ID : CGA3112E</u>	127
<u>Message ID : CGA3113E</u>	128
<u>Message ID : CGA3114E</u>	129
<u>Message ID : CGA3115E</u>	130
<u>Message ID : CGA3116E</u>	131
<u>Message ID : CGA3117E</u>	131
<u>Message ID : CGA3118E</u>	132
<u>Message ID : CGA3119E</u>	133
<u>Message ID : CGA3120E</u>	134
<u>Message ID : CGA3121E</u>	135
<u>Message ID : CGA3122E</u>	136
<u>Message ID : CGA3123E</u>	137
<u>Message ID : CGA3124E</u>	138
<u>Message ID : CGA3125E</u>	139
<u>Message ID : CGA3126E</u>	140
<u>Message ID : CGA3127E</u>	141

Table of Contents

Logger CGA: Errors

<u>Message ID : CGA3128E</u>	142
<u>Message ID : CGA3129E</u>	143
<u>Message ID : CGA3130E</u>	144
<u>Message ID : CGA3131E</u>	144
<u>Message ID : CGA3132E</u>	145
<u>Message ID : CGA3133E</u>	146
<u>Message ID : CGA3134E</u>	147
<u>Message ID : CGA3135E</u>	148
<u>Message ID : CGA3136E</u>	149
<u>Message ID : CGA3137E</u>	150
<u>Message ID : CGA3138E</u>	151
<u>Message ID : CGA3139E</u>	152
<u>Message ID : CGA3140E</u>	153
<u>Message ID : CGA3141E</u>	154
<u>Message ID : CGA3142E</u>	155
<u>Message ID : CGA3143E</u>	156
<u>Message ID : CGA3144E</u>	157
<u>Message ID : CGA3145E</u>	157
<u>Message ID : CGA3146E</u>	158
<u>Message ID : CGA3147E</u>	159
<u>Message ID : CGA3148E</u>	160
<u>Message ID : CGA3149E</u>	161
<u>Message ID : CGA3150E</u>	162
<u>Message ID : CGA3151E</u>	163
<u>Message ID : CGA3152E</u>	164
<u>Message ID : CGA3153E</u>	165

Table of Contents

Logger CGA: Errors

<u>Message ID : CGA3154E</u>	166
<u>Message ID : CGA3155E</u>	167
<u>Message ID : CGA3156E</u>	168
<u>Message ID : CGA3157E</u>	169
<u>Message ID : CGA3158E</u>	170
<u>Message ID : CGA3159E</u>	170
<u>Message ID : CGA3160E</u>	171
<u>Message ID : CGA3161E</u>	172
<u>Message ID : CGA3162E</u>	173
<u>Message ID : CGA3163E</u>	174
<u>Message ID : CGA3164E</u>	175
<u>Message ID : CGA3165E</u>	176
<u>Message ID : CGA3166E</u>	177
<u>Message ID : CGA3167E</u>	178
<u>Message ID : CGA3168E</u>	179
<u>Message ID : CGA3169E</u>	180
<u>Message ID : CGA3170E</u>	181
<u>Message ID : CGA3171E</u>	182
<u>Message ID : CGA3172E</u>	183
<u>Message ID : CGA3173E</u>	183
<u>Message ID : CGA3174E</u>	184
<u>Message ID : CGA3175E</u>	185
<u>Message ID : CGA3176E</u>	186
<u>Message ID : CGA3177E</u>	187
<u>Message ID : CGA3178E</u>	188
<u>Message ID : CGA3179E</u>	189

Table of Contents

Logger CGA: Errors

<u>Message ID : CGA3180E</u>	190
<u>Message ID : CGA3181E</u>	191
<u>Message ID : CGA3182E</u>	192
<u>Message ID : CGA3184E</u>	193
<u>Message ID : CGA3185E</u>	194
<u>Message ID : CGA3187E</u>	194
<u>Message ID : CGA3188E</u>	195
<u>Message ID : CGA3189E</u>	196
<u>Message ID : CGA3190E</u>	197
<u>Message ID : CGA3191E</u>	198
<u>Message ID : CGA3192E</u>	199
<u>Message ID : CGA3206E</u>	200
<u>Message ID : CGA3212E</u>	201
<u>Message ID : CGA3218E</u>	201
<u>Message ID : CGA3220E</u>	202
<u>Message ID : CGA3222E</u>	203
<u>Message ID : CGA3223E</u>	204
<u>Message ID : CGA3227E</u>	205
<u>Message ID : CGA3228E</u>	206
<u>Message ID : CGA3229E</u>	207
<u>Message ID : CGA3230E</u>	208
<u>Message ID : CGA3232E</u>	209
<u>Message ID : CGA3233E</u>	210
<u>Message ID : CGA3235E</u>	211
<u>Message ID : CGA3236E</u>	212
<u>Message ID : CGA3237E</u>	213

Table of Contents

Logger CGA: Errors

<u>Message ID : CGA3238E</u>	214
<u>Message ID : CGA3239E</u>	215
<u>Message ID : CGA3252E</u>	216
<u>Message ID : CGA3256E</u>	217
<u>Message ID : CGA3272E</u>	217
<u>Message ID : CGA3274E</u>	218
<u>Message ID : CGA3275E</u>	219
<u>Message ID : CGA3278E</u>	220
<u>Message ID : CGA3279E</u>	221
<u>Message ID : CGA3280E</u>	222
<u>Message ID : CGA3282E</u>	223
<u>Message ID : CGA3284E</u>	224
<u>Message ID : CGA3289E</u>	225
<u>Message ID : CGA3292E</u>	226
<u>Message ID : CGA3295E</u>	226
<u>Message ID : CGA3298E</u>	227
<u>Message ID : CGA3301E</u>	228
<u>Message ID : CGA3304E</u>	229
<u>Message ID : CGA3306E</u>	230
<u>Message ID : CGA3307E</u>	231
<u>Message ID : CGA3308E</u>	232
<u>Message ID : CGA3309E</u>	233
<u>Message ID : CGA3310E</u>	234

Table of Contents

Logger CGA: Information	235
<u>Message ID : CGA2622I</u>	235
<u>Message ID : CGA2630I</u>	235
<u>Message ID : CGA2631I</u>	236
<u>Message ID : CGA2632I</u>	237
<u>Message ID : CGA2633I</u>	237
<u>Message ID : CGA2640I</u>	238
<u>Message ID : CGA2641I</u>	239
<u>Message ID : CGA2642I</u>	239
<u>Message ID : CGA2643I</u>	240
<u>Message ID : CGA2644I</u>	241
<u>Message ID : CGA2646I</u>	241
<u>Message ID : CGA2647I</u>	242
<u>Message ID : CGA2656I</u>	243
<u>Message ID : CGA2657I</u>	244
<u>Message ID : CGA3001I</u>	245
<u>Message ID : CGA3005I</u>	246
<u>Message ID : CGA3006I</u>	246
<u>Message ID : CGA3019I</u>	247
<u>Message ID : CGA3020I</u>	248
<u>Message ID : CGA3058I</u>	249
<u>Message ID : CGA3105I</u>	250
<u>Message ID : CGA3183I</u>	251
<u>Message ID : CGA3186I</u>	252
<u>Message ID : CGA3193I</u>	253
<u>Message ID : CGA3194I</u>	254
<u>Message ID : CGA3195I</u>	254

Table of Contents

Logger CGA: Information

<u>Message ID : CGA3196I</u>	255
<u>Message ID : CGA3197I</u>	256
<u>Message ID : CGA3198I</u>	257
<u>Message ID : CGA3199I</u>	258
<u>Message ID : CGA3200I</u>	259
<u>Message ID : CGA3201I</u>	260
<u>Message ID : CGA3202I</u>	261
<u>Message ID : CGA3203I</u>	262
<u>Message ID : CGA3204I</u>	263
<u>Message ID : CGA3205I</u>	264
<u>Message ID : CGA3207I</u>	264
<u>Message ID : CGA3208I</u>	265
<u>Message ID : CGA3209I</u>	266
<u>Message ID : CGA3210I</u>	267
<u>Message ID : CGA3211I</u>	268
<u>Message ID : CGA3213I</u>	269
<u>Message ID : CGA3214I</u>	270
<u>Message ID : CGA3215I</u>	270
<u>Message ID : CGA3216I</u>	271
<u>Message ID : CGA3217I</u>	272
<u>Message ID : CGA3219I</u>	273
<u>Message ID : CGA3221I</u>	274
<u>Message ID : CGA3224I</u>	275
<u>Message ID : CGA3225I</u>	276
<u>Message ID : CGA3226I</u>	277
<u>Message ID : CGA3240I</u>	278

Table of Contents

Logger CGA: Information

<u>Message ID : CGA3241I</u>	279
<u>Message ID : CGA3242I</u>	280
<u>Message ID : CGA3244I</u>	281
<u>Message ID : CGA3245I</u>	281
<u>Message ID : CGA3246I</u>	282
<u>Message ID : CGA3247I</u>	283
<u>Message ID : CGA3248I</u>	284
<u>Message ID : CGA3257I</u>	285
<u>Message ID : CGA3258I</u>	286
<u>Message ID : CGA3269I</u>	287
<u>Message ID : CGA3270I</u>	288
<u>Message ID : CGA3271I</u>	289
<u>Message ID : CGA3273I</u>	289
<u>Message ID : CGA3281I</u>	290
<u>Message ID : CGA3283I</u>	291
<u>Message ID : CGA3287I</u>	292
<u>Message ID : CGA3288I</u>	293
<u>Message ID : CGA3290I</u>	294
<u>Message ID : CGA3291I</u>	295
<u>Message ID : CGA3293I</u>	296
<u>Message ID : CGA3294I</u>	297
<u>Message ID : CGA3296I</u>	298
<u>Message ID : CGA3297I</u>	299
<u>Message ID : CGA3299I</u>	299
<u>Message ID : CGA3300I</u>	300
<u>Message ID : CGA3305I</u>	301

Table of Contents

Logger CGA: Information

<u>Message ID : CGA3343I</u>	302
------------------------------------	-----

Logger CGA: Warnings..... **304**

<u>Message ID : CGA2615W</u>	304
<u>Message ID : CGA2616W</u>	304
<u>Message ID : CGA2623W</u>	305
<u>Message ID : CGA2901W</u>	306
<u>Message ID : CGA3002W</u>	307
<u>Message ID : CGA3104W</u>	308
<u>Message ID : CGA3106W</u>	309
<u>Message ID : CGA3107W</u>	310
<u>Message ID : CGA3108W</u>	311
<u>Message ID : CGA3231W</u>	311
<u>Message ID : CGA3243W</u>	312
<u>Message ID : CGA3265W</u>	313
<u>Message ID : CGA3276W</u>	314
<u>Message ID : CGA3285W</u>	315
<u>Message ID : CGA3286W</u>	316

Logger CGP: Errors..... **318**

<u>Message ID : CGP2602E</u>	318
<u>Message ID : CGP2604E</u>	319
<u>Message ID : CGP2606E</u>	320
<u>Message ID : CGP2608E</u>	322
<u>Message ID : CGP2610E</u>	323

Table of Contents

<u>Logger CGP: Information</u>	325
<u>Message ID : CGP2601I</u>	325
<u>Message ID : CGP2603I</u>	326
<u>Message ID : CGP2605I</u>	327
<u>Message ID : CGP2607I</u>	329
<u>Message ID : CGP2609I</u>	330
<u>Logger CGS: Errors</u>	332
<u>Message ID : CGS2613E</u>	332
<u>Message ID : CGS3025E</u>	332
<u>Message ID : CGS3026E</u>	333
<u>Message ID : CGS3027E</u>	334
<u>Message ID : CGS3028E</u>	335
<u>Message ID : CGS3031E</u>	336
<u>Message ID : CGS3032E</u>	337
<u>Message ID : CGS3033E</u>	338
<u>Message ID : CGS3034E</u>	339
<u>Message ID : CGS3035E</u>	340
<u>Message ID : CGS3038E</u>	341
<u>Message ID : CGS3039E</u>	341
<u>Message ID : CGS3042E</u>	342
<u>Message ID : CGS3043E</u>	343
<u>Message ID : CGS3044E</u>	344
<u>Message ID : CGS3045E</u>	345
<u>Message ID : CGS3047E</u>	346
<u>Message ID : CGS3048E</u>	347
<u>Message ID : CGS3049E</u>	348

Table of Contents

Logger CGS: Errors

<u>Message ID : CGS3050E</u>	348
<u>Message ID : CGS3051E</u>	349
<u>Message ID : CGS3052E</u>	350
<u>Message ID : CGS3053E</u>	351
<u>Message ID : CGS3054E</u>	352
<u>Message ID : CGS3055E</u>	353
<u>Message ID : CGS3057E</u>	354
<u>Message ID : CGS3234E</u>	355
<u>Message ID : CGS3253E</u>	356
<u>Message ID : CGS3259E</u>	357
<u>Message ID : CGS3260E</u>	358
<u>Message ID : CGS3261E</u>	358
<u>Message ID : CGS3262E</u>	359
<u>Message ID : CGS3263E</u>	360
<u>Message ID : CGS3264E</u>	361
<u>Message ID : CGS3266E</u>	362
<u>Message ID : CGS3304E</u>	363
<u>Message ID : CGS3305E</u>	364
<u>Message ID : CGS3306E</u>	365
<u>Message ID : CGS3307E</u>	366
<u>Message ID : CGS3308E</u>	367
<u>Message ID : CGS3309E</u>	367
<u>Message ID : CGS3311E</u>	368
<u>Message ID : CGS3312E</u>	369
<u>Message ID : CGS3313E</u>	370
<u>Message ID : CGS3314E</u>	371

Table of Contents

Logger CGS: Errors

<u>Message ID : CGS3315E</u>	372
<u>Message ID : CGS3316E</u>	373
<u>Message ID : CGS3317E</u>	374
<u>Message ID : CGS3319E</u>	375
<u>Message ID : CGS3327E</u>	376
<u>Message ID : CGS3328E</u>	376
<u>Message ID : CGS3329E</u>	378
<u>Message ID : CGS3331E</u>	379
<u>Message ID : CGS3335E</u>	380
<u>Message ID : CGS3336E</u>	381
<u>Message ID : CGS3337E</u>	381
<u>Message ID : CGS3338E</u>	382
<u>Message ID : CGS3339E</u>	383
<u>Message ID : CGS3340E</u>	384
<u>Message ID : CGS3341E</u>	385
<u>Message ID : CGS3342E</u>	386
<u>Message ID : CGS3344E</u>	387

Logger CGS: Information..... **388**

<u>Message ID : CGS3029I</u>	388
<u>Message ID : CGS3030I</u>	389
<u>Message ID : CGS3036I</u>	389
<u>Message ID : CGS3037I</u>	390
<u>Message ID : CGS3040I</u>	391
<u>Message ID : CGS3041I</u>	392
<u>Message ID : CGS3046I</u>	393

Table of Contents

Logger CGS: Information

<u>Message ID : CGS3056I</u>	394
<u>Message ID : CGS3249I</u>	395
<u>Message ID : CGS3250I</u>	395
<u>Message ID : CGS3251I</u>	396
<u>Message ID : CGS3254I</u>	397
<u>Message ID : CGS3255I</u>	398
<u>Message ID : CGS3277I</u>	399
<u>Message ID : CGS3318I</u>	400
<u>Message ID : CGS3320I</u>	401
<u>Message ID : CGS3322I</u>	402
<u>Message ID : CGS3324I</u>	403
<u>Message ID : CGS3325I</u>	403

Logger CGS: Warnings.....**405**

<u>Message ID : CGS3267W</u>	405
<u>Message ID : CGS3268W</u>	406
<u>Message ID : CGS3302W</u>	407
<u>Message ID : CGS3303W</u>	408
<u>Message ID : CGS3310W</u>	409
<u>Message ID : CGS3321W</u>	409
<u>Message ID : CGS3323W</u>	410
<u>Message ID : CGS3326W</u>	411
<u>Message ID : CGS3330W</u>	412
<u>Message ID : CGS3332W</u>	413
<u>Message ID : CGS3333W</u>	414
<u>Message ID : CGS3334W</u>	415

Table of Contents

<u>Logger CMG: Information</u>	417
<u>Message ID : CMG1150I</u>	417
<u>Logger CMG: Warnings</u>	418
<u>Message ID : CMG1100W</u>	418
<u>Message ID : CMG1101W</u>	419
<u>Message ID : CMG1120W</u>	420
<u>Message ID : CMG1121W</u>	421
<u>Logger COM: Errors</u>	422
<u>Message ID : COM0002E</u>	422
<u>Message ID : COM0003E</u>	422
<u>Message ID : COM0005E</u>	423
<u>Message ID : COM0174E</u>	424
<u>Message ID : COM0175E</u>	424
<u>Message ID : COM0271E</u>	425
<u>Message ID : COM0272E</u>	426
<u>Message ID : COM0275E</u>	426
<u>Message ID : COM0300E</u>	427
<u>Message ID : COM0303E</u>	428
<u>Message ID : COM0312E</u>	429
<u>Message ID : COM0313E</u>	429
<u>Message ID : COM0429E</u>	430
<u>Message ID : COM0430E</u>	431
<u>Message ID : COM0431E</u>	432
<u>Message ID : COM0432E</u>	432
<u>Message ID : COM0433E</u>	433

Table of Contents

Logger COM: Errors

<u>Message ID : COM0434E</u>	434
<u>Message ID : COM0435E</u>	434
<u>Message ID : COM0436E</u>	435
<u>Message ID : COM0506E</u>	436
<u>Message ID : COM0507E</u>	437
<u>Message ID : COM0508E</u>	437
<u>Message ID : COM0509E</u>	438
<u>Message ID : COM0510E</u>	439
<u>Message ID : COM0511E</u>	439
<u>Message ID : COM0512E</u>	440
<u>Message ID : COM0513E</u>	441
<u>Message ID : COM0514E</u>	441
<u>Message ID : COM0515E</u>	442
<u>Message ID : COM0516E</u>	443
<u>Message ID : COM0536E</u>	443
<u>Message ID : COM0537E</u>	444
<u>Message ID : COM0539E</u>	445
<u>Message ID : COM0540E</u>	446
<u>Message ID : COM0541E</u>	446
<u>Message ID : COM0542E</u>	447
<u>Message ID : COM0543E</u>	448
<u>Message ID : COM0555E</u>	448
<u>Message ID : COM0556E</u>	449
<u>Message ID : COM0557E</u>	450
<u>Message ID : COM0558E</u>	450
<u>Message ID : COM0588E</u>	451

Table of Contents

Logger COM: Errors

<u>Message ID : COM0589E</u>	452
<u>Message ID : COM0590E</u>	452
<u>Message ID : COM0594E</u>	453
<u>Message ID : COM0595E</u>	454
<u>Message ID : COM0600E</u>	455
<u>Message ID : COM0601E</u>	456
<u>Message ID : COM0602E</u>	456
<u>Message ID : COM0603E</u>	457
<u>Message ID : COM0605E</u>	458
<u>Message ID : COM0609E</u>	459
<u>Message ID : COM0613E</u>	460
<u>Message ID : COM0619E</u>	460
<u>Message ID : COM0620E</u>	461
<u>Message ID : COM0621E</u>	462
<u>Message ID : COM0622E</u>	462
<u>Message ID : COM0623E</u>	463
<u>Message ID : COM0627E</u>	464
<u>Message ID : COM0628E</u>	464
<u>Message ID : COM0650E</u>	465
<u>Message ID : COM0651E</u>	466
<u>Message ID : COM0652E</u>	466
<u>Message ID : COM0653E</u>	467
<u>Message ID : COM0660E</u>	468
<u>Message ID : COM0661E</u>	469
<u>Message ID : COM0712E</u>	470
<u>Message ID : COM0713E</u>	471

Table of Contents

Logger COM: Errors

<u>Message ID : COM0759E</u>	472
<u>Message ID : COM0772E</u>	473
<u>Message ID : COM0805E</u>	473
<u>Message ID : COM0900E</u>	474
<u>Message ID : COM0901E</u>	475
<u>Message ID : COM1257E</u>	475
<u>Message ID : COM1263E</u>	476
<u>Message ID : COM1264E</u>	477
<u>Message ID : COM1285E</u>	477
<u>Message ID : COM1306E</u>	478
<u>Message ID : COM1307E</u>	479
<u>Message ID : COM1308E</u>	479
<u>Message ID : COM1310E</u>	480
<u>Message ID : COM1315E</u>	481
<u>Message ID : COM1321E</u>	481
<u>Message ID : COM1322E</u>	482
<u>Message ID : COM1349E</u>	483
<u>Message ID : COM1350E</u>	483
<u>Message ID : COM1367E</u>	484
<u>Message ID : COM1400E</u>	485
<u>Message ID : COM1401E</u>	485
<u>Message ID : COM1402E</u>	486
<u>Message ID : COM1403E</u>	487
<u>Message ID : COM1410E</u>	487
<u>Message ID : COM1669E</u>	488
<u>Message ID : COM1692E</u>	489

Table of Contents

Logger COM: Errors

<u>Message ID : COM1740E</u>	489
<u>Message ID : COM1741E</u>	490
<u>Message ID : COM1744E</u>	491
<u>Message ID : COM4547E</u>	491
<u>Message ID : COM4631E</u>	492
<u>Message ID : COM4638E</u>	493
<u>Message ID : COM4644E</u>	494

Logger COM: Fatal errors.....495

<u>Message ID : COM0004F</u>	495
<u>Message ID : COM4503F</u>	495
<u>Message ID : COM4506F</u>	496
<u>Message ID : COM4511F</u>	497
<u>Message ID : COM4512F</u>	498
<u>Message ID : COM4513F</u>	499
<u>Message ID : COM4514F</u>	500
<u>Message ID : COM4515F</u>	500
<u>Message ID : COM4521F</u>	501
<u>Message ID : COM4523F</u>	502
<u>Message ID : COM4527F</u>	503
<u>Message ID : COM4529F</u>	504
<u>Message ID : COM4531F</u>	505
<u>Message ID : COM4533F</u>	505
<u>Message ID : COM4534F</u>	506
<u>Message ID : COM4538F</u>	507
<u>Message ID : COM4542F</u>	508

Table of Contents

Logger COM: Fatal errors

<u>Message ID : COM4548F</u>	509
<u>Message ID : COM4551F</u>	510
<u>Message ID : COM4552F</u>	510
<u>Message ID : COM4554F</u>	511
<u>Message ID : COM4558F</u>	512
<u>Message ID : COM4562F</u>	513
<u>Message ID : COM4563F</u>	514
<u>Message ID : COM4567F</u>	515
<u>Message ID : COM4569F</u>	516
<u>Message ID : COM4571F</u>	517
<u>Message ID : COM4577F</u>	518
<u>Message ID : COM4578F</u>	518
<u>Message ID : COM4579F</u>	519
<u>Message ID : COM4583F</u>	520
<u>Message ID : COM4584F</u>	521
<u>Message ID : COM4586F</u>	522
<u>Message ID : COM4587F</u>	522
<u>Message ID : COM4588F</u>	523
<u>Message ID : COM4592F</u>	524
<u>Message ID : COM4599F</u>	525
<u>Message ID : COM4600F</u>	526
<u>Message ID : COM4603F</u>	527
<u>Message ID : COM4604F</u>	528
<u>Message ID : COM4628F</u>	529
<u>Message ID : COM4629F</u>	530
<u>Message ID : COM4630F</u>	531

Table of Contents

Logger COM: Fatal errors

<u>Message ID : COM4637F</u>	532
------------------------------------	-----

Logger COM: Information..... **534**

<u>Message ID : COM0006I</u>	534
<u>Message ID : COM0007I</u>	535
<u>Message ID : COM0008I</u>	536
<u>Message ID : COM0009I</u>	537
<u>Message ID : COM0010I</u>	538
<u>Message ID : COM0011I</u>	539
<u>Message ID : COM0012I</u>	540
<u>Message ID : COM0013I</u>	541
<u>Message ID : COM0014I</u>	542
<u>Message ID : COM0015I</u>	543
<u>Message ID : COM0016I</u>	544
<u>Message ID : COM0017I</u>	544
<u>Message ID : COM0018I</u>	545
<u>Message ID : COM0019I</u>	546
<u>Message ID : COM0020I</u>	547
<u>Message ID : COM0021I</u>	547
<u>Message ID : COM0022I</u>	548
<u>Message ID : COM0023I</u>	549
<u>Message ID : COM0024I</u>	549
<u>Message ID : COM0025I</u>	550
<u>Message ID : COM0173I</u>	551
<u>Message ID : COM0314I</u>	552
<u>Message ID : COM0538I</u>	552

Table of Contents

Logger COM: Information

<u>Message ID : COM0559I</u>	553
<u>Message ID : COM0572I</u>	554
<u>Message ID : COM0574I</u>	555
<u>Message ID : COM0649I</u>	556
<u>Message ID : COM0666I</u>	557
<u>Message ID : COM0707I</u>	558
<u>Message ID : COM0710I</u>	558
<u>Message ID : COM0711I</u>	559
<u>Message ID : COM1311I</u>	560
<u>Message ID : COM1312I</u>	561
<u>Message ID : COM1519I</u>	562
<u>Message ID : COM1521I</u>	563
<u>Message ID : COM1784I</u>	564
<u>Message ID : COM1813I</u>	564
<u>Message ID : COM1835I</u>	565
<u>Message ID : COM4601I</u>	566
<u>Message ID : COM4602I</u>	567
<u>Message ID : COM4626I</u>	568
<u>Message ID : COM4627I</u>	568

Logger COM: Warnings..... **570**

<u>Message ID : COM0591W</u>	570
<u>Message ID : COM0607W</u>	571
<u>Message ID : COM0612W</u>	571
<u>Message ID : COM0614W</u>	572
<u>Message ID : COM0617W</u>	573

Table of Contents

Logger COM: Warnings

<u>Message ID : COM0618W</u>	573
<u>Message ID : COM0667W</u>	574
<u>Message ID : COM1251W</u>	575
<u>Message ID : COM1314W</u>	575
<u>Message ID : COM1323W</u>	576
<u>Message ID : COM1337W</u>	577
<u>Message ID : COM4605W</u>	577
<u>Message ID : COM4632W</u>	578
<u>Message ID : COM4633W</u>	579
<u>Message ID : COM4634W</u>	581
<u>Message ID : COM4635W</u>	581

Logger CXM: Errors..... **584**

<u>Message ID : CXM0654E</u>	584
<u>Message ID : CXM0657E</u>	585
<u>Message ID : CXM0658E</u>	585
<u>Message ID : CXM0659E</u>	586
<u>Message ID : CXM0770E</u>	587
<u>Message ID : CXM1354E</u>	588
<u>Message ID : CXM1355E</u>	589
<u>Message ID : CXM1356E</u>	590
<u>Message ID : CXM1357E</u>	590
<u>Message ID : CXM1358E</u>	591
<u>Message ID : CXM1359E</u>	592
<u>Message ID : CXM1360E</u>	592
<u>Message ID : CXM1361E</u>	593

Table of Contents

Logger CXM: Errors

<u>Message ID : CXM1391E</u>	594
<u>Message ID : CXM1392E</u>	594
<u>Message ID : CXM1393E</u>	595
<u>Message ID : CXM1693E</u>	596

Logger CXM: Information..... **597**

<u>Message ID : CXM022II</u>	597
<u>Message ID : CXM0224I</u>	598
<u>Message ID : CXM0225I</u>	598
<u>Message ID : CXM0646I</u>	599
<u>Message ID : CXM0647I</u>	600
<u>Message ID : CXM0648I</u>	601
<u>Message ID : CXM0655I</u>	602
<u>Message ID : CXM0656I</u>	603
<u>Message ID : CXM0659I</u>	604
<u>Message ID : CXM0660I</u>	605
<u>Message ID : CXM0661I</u>	606
<u>Message ID : CXM0662I</u>	607
<u>Message ID : CXM077II</u>	608
<u>Message ID : CXM1340I</u>	609
<u>Message ID : CXM1341I</u>	610
<u>Message ID : CXM1342I</u>	611
<u>Message ID : CXM1344I</u>	612
<u>Message ID : CXM1345I</u>	613
<u>Message ID : CXM1346I</u>	614
<u>Message ID : CXM1347I</u>	615

Table of Contents

<u>Logger CXM: Information</u>	
<u>Message ID : CXM1624I</u>	615
<u>Message ID : CXM1732I</u>	616
<u>Message ID : CXM1748I</u>	617
<u>Logger CXM: Warnings</u>	619
<u>Message ID : CXM0222W</u>	619
<u>Message ID : CXM0223W</u>	620
<u>Message ID : CXM0226W</u>	620
<u>Message ID : CXM0227W</u>	621
<u>Message ID : CXM0289W</u>	622
<u>Message ID : CXM0802W</u>	623
<u>Message ID : CXM1250W</u>	624
<u>Message ID : CXM1294W</u>	625
<u>Message ID : CXM1343W</u>	626
<u>Message ID : CXM1363W</u>	626
<u>Message ID : CXM1423W</u>	627
<u>Message ID : CXM1520W</u>	628
<u>Message ID : CXM1749W</u>	629
<u>Logger DA0: Errors</u>	631
<u>Message ID : DA001322E</u>	631
<u>Message ID : DA001323E</u>	631
<u>Logger DAO: Errors</u>	633
<u>Message ID : DAO0038E</u>	633
<u>Message ID : DAO0039E</u>	633

Table of Contents

Logger DAO: Errors

<u>Message ID : DAO0040E</u>	634
<u>Message ID : DAO0041E</u>	635
<u>Message ID : DAO0042E</u>	635
<u>Message ID : DAO0043E</u>	636
<u>Message ID : DAO0044E</u>	637
<u>Message ID : DAO0049E</u>	637
<u>Message ID : DAO0050E</u>	638
<u>Message ID : DAO0051E</u>	639
<u>Message ID : DAO0056E</u>	639
<u>Message ID : DAO0057E</u>	640
<u>Message ID : DAO0058E</u>	641
<u>Message ID : DAO0059E</u>	641
<u>Message ID : DAO0060E</u>	642
<u>Message ID : DAO0066E</u>	643
<u>Message ID : DAO0067E</u>	643
<u>Message ID : DAO0069E</u>	644
<u>Message ID : DAO0070E</u>	645
<u>Message ID : DAO0081E</u>	645
<u>Message ID : DAO0087E</u>	646
<u>Message ID : DAO0088E</u>	647
<u>Message ID : DAO01299E</u>	647
<u>Message ID : DAO01320E</u>	648
<u>Message ID : DAO01328E</u>	649
<u>Message ID : DAO01329E</u>	649
<u>Message ID : DAO01335E</u>	650
<u>Message ID : DAO01336E</u>	651

Table of Contents

Logger DAO: Errors

<u>Message ID : DAO01342E</u>	651
<u>Message ID : DAO01343E</u>	652
<u>Message ID : DAO01344E</u>	653
<u>Message ID : DAO01346E</u>	653
<u>Message ID : DAO01347E</u>	654
<u>Message ID : DAO01348E</u>	655
<u>Message ID : DAO01349E</u>	655
<u>Message ID : DAO01350E</u>	656
<u>Message ID : DAO01351E</u>	657
<u>Message ID : DAO01384E</u>	657
<u>Message ID : DAO01392E</u>	658
<u>Message ID : DAO01400E</u>	659
<u>Message ID : DAO01518E</u>	659
<u>Message ID : DAO01658E</u>	660
<u>Message ID : DAO01659E</u>	661
<u>Message ID : DAO0226E</u>	661
<u>Message ID : DAO0242E</u>	662
<u>Message ID : DAO0246E</u>	663
<u>Message ID : DAO0247E</u>	663
<u>Message ID : DAO0249E</u>	664
<u>Message ID : DAO0250E</u>	665
<u>Message ID : DAO0268E</u>	665
<u>Message ID : DAO0291E</u>	666
<u>Message ID : DAO0297E</u>	667
<u>Message ID : DAO0304E</u>	668
<u>Message ID : DAO0671E</u>	669

Table of Contents

Logger DAO: Errors

<u>Message ID : DAO0705E</u>	669
<u>Message ID : DAO0706E</u>	670
<u>Message ID : DAO0807E</u>	671
<u>Message ID : DAO0855E</u>	671
<u>Message ID : DAO1632E</u>	672
<u>Message ID : DAO1633E</u>	673
<u>Message ID : DAO1634E</u>	673
<u>Message ID : DAO1635E</u>	674
<u>Message ID : DAO1636E</u>	675
<u>Message ID : DAO1666E</u>	675
<u>Message ID : DAO1718E</u>	676
<u>Message ID : DAO1727E</u>	677
<u>Message ID : DAO1750E</u>	677
<u>Message ID : DAO1867E</u>	678

Logger DAO: Information..... **679**

<u>Message ID : DAO0045I</u>	679
<u>Message ID : DAO0046I</u>	680
<u>Message ID : DAO0047I</u>	681
<u>Message ID : DAO0048I</u>	682
<u>Message ID : DAO0049I</u>	683
<u>Message ID : DAO0052I</u>	684
<u>Message ID : DAO0053I</u>	685
<u>Message ID : DAO0055I</u>	686
<u>Message ID : DAO0061I</u>	687
<u>Message ID : DAO0062I</u>	688

Table of Contents

Logger DAO: Information

<u>Message ID : DAO0063I</u>	689
<u>Message ID : DAO0064I</u>	690
<u>Message ID : DAO0071I</u>	691
<u>Message ID : DAO0072I</u>	692
<u>Message ID : DAO0073I</u>	693
<u>Message ID : DAO0074I</u>	694
<u>Message ID : DAO0075I</u>	695
<u>Message ID : DAO0076I</u>	695
<u>Message ID : DAO0077I</u>	696
<u>Message ID : DAO0078I</u>	697
<u>Message ID : DAO0079I</u>	698
<u>Message ID : DAO0080I</u>	699
<u>Message ID : DAO0082I</u>	700
<u>Message ID : DAO0083I</u>	701
<u>Message ID : DAO0084I</u>	701
<u>Message ID : DAO0085I</u>	702
<u>Message ID : DAO0086I</u>	703
<u>Message ID : DAO0089I</u>	704
<u>Message ID : DAO0090I</u>	705
<u>Message ID : DAO0091I</u>	706
<u>Message ID : DAO0092I</u>	707
<u>Message ID : DAO0093I</u>	708
<u>Message ID : DAO01286I</u>	708
<u>Message ID : DAO01287I</u>	709
<u>Message ID : DAO01332I</u>	710
<u>Message ID : DAO01333I</u>	711

Table of Contents

Logger DAO: Information

<u>Message ID : DAO01340I</u>	712
<u>Message ID : DAO01341I</u>	713
<u>Message ID : DAO01345I</u>	714
<u>Message ID : DAO01379I</u>	715
<u>Message ID : DAO01380I</u>	716
<u>Message ID : DAO01381I</u>	716
<u>Message ID : DAO01382I</u>	717
<u>Message ID : DAO01383I</u>	718
<u>Message ID : DAO01384I</u>	718
<u>Message ID : DAO01385I</u>	719
<u>Message ID : DAO01386I</u>	720
<u>Message ID : DAO01387I</u>	721
<u>Message ID : DAO01388I</u>	721
<u>Message ID : DAO01389I</u>	722
<u>Message ID : DAO01509I</u>	723
<u>Message ID : DAO01510I</u>	723
<u>Message ID : DAO01519I</u>	724
<u>Message ID : DAO01520I</u>	725
<u>Message ID : DAO01542I</u>	726
<u>Message ID : DAO0227I</u>	726
<u>Message ID : DAO0228I</u>	727
<u>Message ID : DAO0229I</u>	728
<u>Message ID : DAO0230I</u>	729
<u>Message ID : DAO0231I</u>	730
<u>Message ID : DAO0232I</u>	731
<u>Message ID : DAO0233I</u>	732

Table of Contents

Logger DAO: Information

<u>Message ID : DAO0234I</u>	733
<u>Message ID : DAO0235I</u>	734
<u>Message ID : DAO0236I</u>	735
<u>Message ID : DAO0237I</u>	736
<u>Message ID : DAO0238I</u>	737
<u>Message ID : DAO0239I</u>	738
<u>Message ID : DAO0240I</u>	739
<u>Message ID : DAO0241I</u>	740
<u>Message ID : DAO0243I</u>	741
<u>Message ID : DAO0244I</u>	742
<u>Message ID : DAO0245I</u>	743
<u>Message ID : DAO0248I</u>	744
<u>Message ID : DAO0251I</u>	745
<u>Message ID : DAO0252I</u>	746
<u>Message ID : DAO0253I</u>	747
<u>Message ID : DAO0254I</u>	748
<u>Message ID : DAO0255I</u>	749
<u>Message ID : DAO0256I</u>	750
<u>Message ID : DAO0257I</u>	750
<u>Message ID : DAO0258I</u>	751
<u>Message ID : DAO0259I</u>	752
<u>Message ID : DAO0260I</u>	752
<u>Message ID : DAO0261I</u>	753
<u>Message ID : DAO0263I</u>	754
<u>Message ID : DAO0267I</u>	754
<u>Message ID : DAO0269I</u>	755

Table of Contents

Logger DAO: Information

<u>Message ID : DAO0280I</u>	756
<u>Message ID : DAO0281I</u>	757
<u>Message ID : DAO0282I</u>	758
<u>Message ID : DAO0305I</u>	759
<u>Message ID : DAO0317I</u>	760
<u>Message ID : DAO0401I</u>	761
<u>Message ID : DAO0402I</u>	762
<u>Message ID : DAO0404I</u>	763
<u>Message ID : DAO0405I</u>	764
<u>Message ID : DAO0406I</u>	765
<u>Message ID : DAO0407I</u>	766
<u>Message ID : DAO0408I</u>	767
<u>Message ID : DAO0412I</u>	768
<u>Message ID : DAO0413I</u>	769
<u>Message ID : DAO0414I</u>	770
<u>Message ID : DAO0415I</u>	771
<u>Message ID : DAO0423I</u>	772
<u>Message ID : DAO0424I</u>	773
<u>Message ID : DAO0425I</u>	774
<u>Message ID : DAO0426I</u>	775
<u>Message ID : DAO0445I</u>	776
<u>Message ID : DAO0446I</u>	777
<u>Message ID : DAO0447I</u>	778
<u>Message ID : DAO0449I</u>	779
<u>Message ID : DAO0460I</u>	779
<u>Message ID : DAO0461I</u>	780

Table of Contents

Logger DAO: Information

<u>Message ID : DAO0462I</u>	781
<u>Message ID : DAO0501I</u>	782
<u>Message ID : DAO0502I</u>	783
<u>Message ID : DAO0518I</u>	784
<u>Message ID : DAO0519I</u>	785
<u>Message ID : DAO0546I</u>	786
<u>Message ID : DAO0560I</u>	787
<u>Message ID : DAO0561I</u>	788
<u>Message ID : DAO0562I</u>	789
<u>Message ID : DAO0563I</u>	790
<u>Message ID : DAO0564I</u>	791
<u>Message ID : DAO0565I</u>	792
<u>Message ID : DAO0566I</u>	793
<u>Message ID : DAO0567I</u>	794
<u>Message ID : DAO0568I</u>	795
<u>Message ID : DAO0569I</u>	796
<u>Message ID : DAO0570I</u>	797
<u>Message ID : DAO0571I</u>	798
<u>Message ID : DAO0573I</u>	799
<u>Message ID : DAO0576I</u>	800
<u>Message ID : DAO0578I</u>	801
<u>Message ID : DAO0579I</u>	802
<u>Message ID : DAO0606I</u>	803
<u>Message ID : DAO0638I</u>	803
<u>Message ID : DAO0639I</u>	804
<u>Message ID : DAO0640I</u>	805

Table of Contents

Logger DAO: Information

<u>Message ID : DAO0641I</u>	806
<u>Message ID : DAO0659I</u>	807
<u>Message ID : DAO0672I</u>	808
<u>Message ID : DAO0673I</u>	809
<u>Message ID : DAO0674I</u>	810
<u>Message ID : DAO0675I</u>	811
<u>Message ID : DAO0676I</u>	812
<u>Message ID : DAO0677I</u>	813
<u>Message ID : DAO0678I</u>	815
<u>Message ID : DAO0679I</u>	816
<u>Message ID : DAO0680I</u>	817
<u>Message ID : DAO0681I</u>	818
<u>Message ID : DAO0682I</u>	819
<u>Message ID : DAO0683I</u>	820
<u>Message ID : DAO0684I</u>	821
<u>Message ID : DAO0685I</u>	822
<u>Message ID : DAO0697I</u>	823
<u>Message ID : DAO0699I</u>	824
<u>Message ID : DAO0700I</u>	825
<u>Message ID : DAO0701I</u>	826
<u>Message ID : DAO0715I</u>	827
<u>Message ID : DAO0716I</u>	827
<u>Message ID : DAO0720I</u>	828
<u>Message ID : DAO0721I</u>	829
<u>Message ID : DAO0722I</u>	830
<u>Message ID : DAO0723I</u>	831

Table of Contents

Logger DAO: Information

<u>Message ID : DAO0724I</u>	832
<u>Message ID : DAO0725I</u>	833
<u>Message ID : DAO0790I</u>	834
<u>Message ID : DAO0791I</u>	835
<u>Message ID : DAO0792I</u>	836
<u>Message ID : DAO0803I</u>	837
<u>Message ID : DAO0804I</u>	838
<u>Message ID : DAO0850I</u>	838
<u>Message ID : DAO1265I</u>	839
<u>Message ID : DAO1266I</u>	840
<u>Message ID : DAO1281I</u>	841
<u>Message ID : DAO1353I</u>	842
<u>Message ID : DAO1364I</u>	843
<u>Message ID : DAO1410I</u>	844
<u>Message ID : DAO1500I</u>	845
<u>Message ID : DAO1524I</u>	846
<u>Message ID : DAO1530I</u>	847
<u>Message ID : DAO1536I</u>	848
<u>Message ID : DAO1537I</u>	849
<u>Message ID : DAO1538I</u>	850
<u>Message ID : DAO1539I</u>	850
<u>Message ID : DAO1541I</u>	851
<u>Message ID : DAO1560I</u>	852
<u>Message ID : DAO1624I</u>	853
<u>Message ID : DAO1625I</u>	854
<u>Message ID : DAO1626I</u>	854

Table of Contents

Logger DAO: Information

<u>Message ID : DAO1739I</u>	855
<u>Message ID : DAO1774I</u>	856
<u>Message ID : DAO1828I</u>	857
<u>Message ID : DAO1832I</u>	858
<u>Message ID : DAO1834I</u>	859
<u>Message ID : DAO1837I</u>	860
<u>Message ID : DAO1847I</u>	861
<u>Message ID : DAO1848I</u>	862
<u>Message ID : DAO1861I</u>	863
<u>Message ID : DAO1862I</u>	864

Logger DAO: Warnings..... **866**

<u>Message ID : DAO01319W</u>	866
<u>Message ID : DAO1869W</u>	866

Logger DGV: Errors..... **868**

<u>Message ID : DGV6001E</u>	868
<u>Message ID : DGV6002E</u>	868
<u>Message ID : DGV6003E</u>	869
<u>Message ID : DGV6004E</u>	870
<u>Message ID : DGV6005E</u>	871
<u>Message ID : DGV6006E</u>	872
<u>Message ID : DGV6007E</u>	873
<u>Message ID : DGV6008E</u>	874
<u>Message ID : DGV6009E</u>	874
<u>Message ID : DGV6010E</u>	875

Table of Contents

Logger DGV: Errors

<u>Message ID : DGV6011E</u>	876
<u>Message ID : DGV6012E</u>	877
<u>Message ID : DGV6013E</u>	878
<u>Message ID : DGV6014E</u>	879
<u>Message ID : DGV6015E</u>	880
<u>Message ID : DGV6016E</u>	880
<u>Message ID : DGV6017E</u>	881
<u>Message ID : DGV6018E</u>	882

Logger DGV: Information..... **884**

<u>Message ID : DGV6019I</u>	884
<u>Message ID : DGV6020I</u>	884

Logger DMG: Errors..... **886**

<u>Message ID : DMG0549E</u>	886
<u>Message ID : DMG0550E</u>	886
<u>Message ID : DMG0551E</u>	887
<u>Message ID : DMG0552E</u>	888
<u>Message ID : DMG0553E</u>	888
<u>Message ID : DMG0554E</u>	889

Logger DMG: Information..... **891**

<u>Message ID : DMG0575I</u>	891
------------------------------------	-----

Table of Contents

Logger DXF: Debug messages	892
<u>Message ID : DXF4308D</u>	892
<u>Message ID : DXF4310D</u>	892
<u>Message ID : DXF4311D</u>	893
<u>Message ID : DXF4473D</u>	894
<u>Message ID : DXF4475D</u>	894
Logger DXF: Errors	896
<u>Message ID : DXF3205E</u>	896
<u>Message ID : DXF3206E</u>	897
<u>Message ID : DXF3207E</u>	897
<u>Message ID : DXF3208E</u>	898
<u>Message ID : DXF3209E</u>	899
<u>Message ID : DXF3215E</u>	900
<u>Message ID : DXF3216E</u>	901
<u>Message ID : DXF3217E</u>	902
<u>Message ID : DXF3218E</u>	903
<u>Message ID : DXF3219E</u>	904
<u>Message ID : DXF3220E</u>	904
<u>Message ID : DXF3221E</u>	905
<u>Message ID : DXF3222E</u>	906
<u>Message ID : DXF3223E</u>	907
<u>Message ID : DXF3224E</u>	908
<u>Message ID : DXF3225E</u>	909
<u>Message ID : DXF3226E</u>	910
<u>Message ID : DXF3227E</u>	911
<u>Message ID : DXF3228E</u>	911

Table of Contents

Logger DXF: Errors

<u>Message ID : DXF3229E</u>	912
<u>Message ID : DXF3230E</u>	913
<u>Message ID : DXF3231E</u>	914
<u>Message ID : DXF3232E</u>	915
<u>Message ID : DXF3233E</u>	916
<u>Message ID : DXF3238E</u>	917
<u>Message ID : DXF3239E</u>	918
<u>Message ID : DXF3240E</u>	918
<u>Message ID : DXF3241E</u>	919
<u>Message ID : DXF3242E</u>	920
<u>Message ID : DXF4100E</u>	921
<u>Message ID : DXF4101E</u>	922
<u>Message ID : DXF4102E</u>	922
<u>Message ID : DXF4105E</u>	923
<u>Message ID : DXF4106E</u>	924
<u>Message ID : DXF4107E</u>	925
<u>Message ID : DXF4108E</u>	926
<u>Message ID : DXF4109E</u>	927
<u>Message ID : DXF4111E</u>	928
<u>Message ID : DXF4112E</u>	929
<u>Message ID : DXF4113E</u>	930
<u>Message ID : DXF4114E</u>	931
<u>Message ID : DXF4115E</u>	932
<u>Message ID : DXF4116E</u>	933
<u>Message ID : DXF4117E</u>	934
<u>Message ID : DXF4119E</u>	935

Table of Contents

Logger DXF: Errors

<u>Message ID : DXF4120E</u>	936
<u>Message ID : DXF4121E</u>	936
<u>Message ID : DXF4124E</u>	937
<u>Message ID : DXF4125E</u>	938
<u>Message ID : DXF4133E</u>	939
<u>Message ID : DXF4134E</u>	939
<u>Message ID : DXF4135E</u>	940
<u>Message ID : DXF4136E</u>	941
<u>Message ID : DXF4137E</u>	942
<u>Message ID : DXF4138E</u>	943
<u>Message ID : DXF4139E</u>	944
<u>Message ID : DXF4140E</u>	945
<u>Message ID : DXF4141E</u>	945
<u>Message ID : DXF4142E</u>	946
<u>Message ID : DXF4149E</u>	947
<u>Message ID : DXF4150E</u>	948
<u>Message ID : DXF4151E</u>	949
<u>Message ID : DXF4152E</u>	949
<u>Message ID : DXF4153E</u>	950
<u>Message ID : DXF4155E</u>	951
<u>Message ID : DXF4156E</u>	951
<u>Message ID : DXF4157E</u>	952
<u>Message ID : DXF4158E</u>	953
<u>Message ID : DXF4159E</u>	954
<u>Message ID : DXF4160E</u>	954
<u>Message ID : DXF4162E</u>	955

Table of Contents

Logger DXF: Errors

<u>Message ID : DXF4163E</u>	956
<u>Message ID : DXF4164E</u>	957
<u>Message ID : DXF4165E</u>	958
<u>Message ID : DXF4166E</u>	959
<u>Message ID : DXF4167E</u>	959
<u>Message ID : DXF4168E</u>	960
<u>Message ID : DXF4215E</u>	961
<u>Message ID : DXF4227E</u>	962
<u>Message ID : DXF4228E</u>	962
<u>Message ID : DXF4229E</u>	963
<u>Message ID : DXF4230E</u>	964
<u>Message ID : DXF4231E</u>	964
<u>Message ID : DXF4232E</u>	965
<u>Message ID : DXF4233E</u>	966
<u>Message ID : DXF4234E</u>	966
<u>Message ID : DXF4235E</u>	967
<u>Message ID : DXF4236E</u>	968
<u>Message ID : DXF4237E</u>	968
<u>Message ID : DXF4238E</u>	969
<u>Message ID : DXF4239E</u>	970
<u>Message ID : DXF4240E</u>	970
<u>Message ID : DXF4241E</u>	971
<u>Message ID : DXF4243E</u>	972
<u>Message ID : DXF4244E</u>	972
<u>Message ID : DXF4247E</u>	973
<u>Message ID : DXF4248E</u>	974

Table of Contents

Logger DXF: Errors

<u>Message ID : DXF4249E</u>	975
<u>Message ID : DXF4250E</u>	976
<u>Message ID : DXF4251E</u>	977
<u>Message ID : DXF4252E</u>	978
<u>Message ID : DXF4255E</u>	979
<u>Message ID : DXF4266E</u>	980
<u>Message ID : DXF4270E</u>	981
<u>Message ID : DXF4271E</u>	981
<u>Message ID : DXF4272E</u>	982
<u>Message ID : DXF4282E</u>	983
<u>Message ID : DXF4286E</u>	984
<u>Message ID : DXF4287E</u>	985
<u>Message ID : DXF4288E</u>	986
<u>Message ID : DXF4289E</u>	987
<u>Message ID : DXF4290E</u>	988
<u>Message ID : DXF4291E</u>	989
<u>Message ID : DXF4292E</u>	990
<u>Message ID : DXF4294E</u>	990
<u>Message ID : DXF4295E</u>	991
<u>Message ID : DXF4296E</u>	992
<u>Message ID : DXF4297E</u>	993
<u>Message ID : DXF4298E</u>	993
<u>Message ID : DXF4299E</u>	994
<u>Message ID : DXF4300E</u>	995
<u>Message ID : DXF4301E</u>	996
<u>Message ID : DXF4302E</u>	997

Table of Contents

Logger DXF: Errors

<u>Message ID : DXF4303E</u>	998
<u>Message ID : DXF4304E</u>	998
<u>Message ID : DXF4306E</u>	999
<u>Message ID : DXF4312E</u>	1000
<u>Message ID : DXF4313E</u>	1001
<u>Message ID : DXF4314E</u>	1002
<u>Message ID : DXF4315E</u>	1003
<u>Message ID : DXF4325E</u>	1004
<u>Message ID : DXF4326E</u>	1005
<u>Message ID : DXF4328E</u>	1005
<u>Message ID : DXF4330E</u>	1006
<u>Message ID : DXF4331E</u>	1007
<u>Message ID : DXF4334E</u>	1008
<u>Message ID : DXF4335E</u>	1009
<u>Message ID : DXF4336E</u>	1009
<u>Message ID : DXF4340E</u>	1010
<u>Message ID : DXF4341E</u>	1011
<u>Message ID : DXF4342E</u>	1011
<u>Message ID : DXF4343E</u>	1012
<u>Message ID : DXF4346E</u>	1013
<u>Message ID : DXF4347E</u>	1013
<u>Message ID : DXF4349E</u>	1014
<u>Message ID : DXF4350E</u>	1015
<u>Message ID : DXF4353E</u>	1016
<u>Message ID : DXF4354E</u>	1016
<u>Message ID : DXF4355E</u>	1017

Table of Contents

Logger DXF: Errors

<u>Message ID : DXF4356E</u>	1018
<u>Message ID : DXF4357E</u>	1019
<u>Message ID : DXF4358E</u>	1019
<u>Message ID : DXF4360E</u>	1020
<u>Message ID : DXF4367E</u>	1021
<u>Message ID : DXF4368E</u>	1022
<u>Message ID : DXF4376E</u>	1023
<u>Message ID : DXF4377E</u>	1024
<u>Message ID : DXF4379E</u>	1025
<u>Message ID : DXF4381E</u>	1026
<u>Message ID : DXF4382E</u>	1026
<u>Message ID : DXF4391E</u>	1027
<u>Message ID : DXF4392E</u>	1028
<u>Message ID : DXF4393E</u>	1029
<u>Message ID : DXF4394E</u>	1030
<u>Message ID : DXF4395E</u>	1031
<u>Message ID : DXF4396E</u>	1031
<u>Message ID : DXF4400E</u>	1032
<u>Message ID : DXF4401E</u>	1033
<u>Message ID : DXF4403E</u>	1034
<u>Message ID : DXF4404E</u>	1035
<u>Message ID : DXF4405E</u>	1035
<u>Message ID : DXF4407E</u>	1036
<u>Message ID : DXF4408E</u>	1037
<u>Message ID : DXF4409E</u>	1038
<u>Message ID : DXF4427E</u>	1039

Table of Contents

Logger DXF: Errors

<u>Message ID : DXF4430E</u>	1040
<u>Message ID : DXF4432E</u>	1040
<u>Message ID : DXF4433E</u>	1041
<u>Message ID : DXF4434E</u>	1042
<u>Message ID : DXF4435E</u>	1043
<u>Message ID : DXF4436E</u>	1043
<u>Message ID : DXF4437E</u>	1044
<u>Message ID : DXF4438E</u>	1045
<u>Message ID : DXF4439E</u>	1045
<u>Message ID : DXF4440E</u>	1046
<u>Message ID : DXF4441E</u>	1047
<u>Message ID : DXF4442E</u>	1047
<u>Message ID : DXF4443E</u>	1048
<u>Message ID : DXF4444E</u>	1049
<u>Message ID : DXF4445E</u>	1049
<u>Message ID : DXF4446E</u>	1050
<u>Message ID : DXF4447E</u>	1051
<u>Message ID : DXF4448E</u>	1051
<u>Message ID : DXF4449E</u>	1052
<u>Message ID : DXF4450E</u>	1053
<u>Message ID : DXF4451E</u>	1053
<u>Message ID : DXF4452E</u>	1054
<u>Message ID : DXF4453E</u>	1055
<u>Message ID : DXF4454E</u>	1055
<u>Message ID : DXF4455E</u>	1056
<u>Message ID : DXF4456E</u>	1057

Table of Contents

Logger DXF: Errors

<u>Message ID : DXF4457E</u>	1057
<u>Message ID : DXF4458E</u>	1058
<u>Message ID : DXF4459E</u>	1059
<u>Message ID : DXF4460E</u>	1059
<u>Message ID : DXF4461E</u>	1060
<u>Message ID : DXF4462E</u>	1061
<u>Message ID : DXF4463E</u>	1061
<u>Message ID : DXF4464E</u>	1062
<u>Message ID : DXF4465E</u>	1063
<u>Message ID : DXF4466E</u>	1063
<u>Message ID : DXF4467E</u>	1064
<u>Message ID : DXF4468E</u>	1065
<u>Message ID : DXF4469E</u>	1066
<u>Message ID : DXF4470E</u>	1066
<u>Message ID : DXF4471E</u>	1067
<u>Message ID : DXF4472E</u>	1068
<u>Message ID : DXF4474E</u>	1068
<u>Message ID : DXF4476E</u>	1069
<u>Message ID : DXF4477E</u>	1070
<u>Message ID : DXF4478E</u>	1071
<u>Message ID : DXF4479E</u>	1071
<u>Message ID : DXF4480E</u>	1072
<u>Message ID : DXF4482E</u>	1073
<u>Message ID : DXF4483E</u>	1074
<u>Message ID : DXF4484E</u>	1075
<u>Message ID : DXF4486E</u>	1075

Table of Contents

Logger DXF: Errors

<u>Message ID : DXF4494E</u>	1076
<u>Message ID : DXF4498E</u>	1077
<u>Message ID : DXF4499E</u>	1078

Logger DXF: Fatal errors.....1080

<u>Message ID : DXF4431E</u>	1080
------------------------------------	------

Logger DXF: Information.....1081

<u>Message ID : DXF3211I</u>	1081
<u>Message ID : DXF3235I</u>	1082
<u>Message ID : DXF3236I</u>	1083
<u>Message ID : DXF3237I</u>	1084
<u>Message ID : DXF4122I</u>	1085
<u>Message ID : DXF4123I</u>	1085
<u>Message ID : DXF4126I</u>	1086
<u>Message ID : DXF4127I</u>	1087
<u>Message ID : DXF4128I</u>	1087
<u>Message ID : DXF4129I</u>	1088
<u>Message ID : DXF4130I</u>	1089
<u>Message ID : DXF4131I</u>	1090
<u>Message ID : DXF4132I</u>	1090
<u>Message ID : DXF4143I</u>	1091
<u>Message ID : DXF4144I</u>	1092
<u>Message ID : DXF4145I</u>	1093
<u>Message ID : DXF4146I</u>	1094
<u>Message ID : DXF4147I</u>	1095

Table of Contents

Logger DXF: Information

<u>Message ID : DXF4148I</u>	1096
<u>Message ID : DXF4154I</u>	1097
<u>Message ID : DXF4161I</u>	1098
<u>Message ID : DXF4200I</u>	1098
<u>Message ID : DXF4201I</u>	1099
<u>Message ID : DXF4202I</u>	1100
<u>Message ID : DXF4203I</u>	1101
<u>Message ID : DXF4204I</u>	1102
<u>Message ID : DXF4205I</u>	1103
<u>Message ID : DXF4206I</u>	1103
<u>Message ID : DXF4207I</u>	1104
<u>Message ID : DXF4208I</u>	1105
<u>Message ID : DXF4209I</u>	1106
<u>Message ID : DXF4210I</u>	1107
<u>Message ID : DXF4211I</u>	1108
<u>Message ID : DXF4212I</u>	1108
<u>Message ID : DXF4213I</u>	1109
<u>Message ID : DXF4214I</u>	1110
<u>Message ID : DXF4216I</u>	1111
<u>Message ID : DXF4217I</u>	1112
<u>Message ID : DXF4218I</u>	1113
<u>Message ID : DXF4219I</u>	1113
<u>Message ID : DXF4220I</u>	1114
<u>Message ID : DXF4221I</u>	1115
<u>Message ID : DXF4222I</u>	1116
<u>Message ID : DXF4223I</u>	1117

Table of Contents

Logger DXF: Information

<u>Message ID : DXF4224I</u>	1118
<u>Message ID : DXF4225I</u>	1119
<u>Message ID : DXF4226I</u>	1119
<u>Message ID : DXF4253I</u>	1120
<u>Message ID : DXF4257I</u>	1121
<u>Message ID : DXF4258I</u>	1122
<u>Message ID : DXF4259I</u>	1123
<u>Message ID : DXF4260I</u>	1124
<u>Message ID : DXF4261I</u>	1124
<u>Message ID : DXF4262I</u>	1125
<u>Message ID : DXF4263I</u>	1126
<u>Message ID : DXF4264I</u>	1127
<u>Message ID : DXF4265I</u>	1128
<u>Message ID : DXF4267I</u>	1129
<u>Message ID : DXF4268I</u>	1130
<u>Message ID : DXF4269I</u>	1131
<u>Message ID : DXF4273I</u>	1131
<u>Message ID : DXF4274I</u>	1132
<u>Message ID : DXF4275I</u>	1133
<u>Message ID : DXF4276I</u>	1134
<u>Message ID : DXF4277I</u>	1135
<u>Message ID : DXF4278I</u>	1136
<u>Message ID : DXF4279I</u>	1136
<u>Message ID : DXF4280I</u>	1137
<u>Message ID : DXF4281I</u>	1138
<u>Message ID : DXF4283I</u>	1139

Table of Contents

Logger DXF: Information

<u>Message ID : DXF4284I</u>	1140
<u>Message ID : DXF4285I</u>	1141
<u>Message ID : DXF4293I</u>	1142
<u>Message ID : DXF4309I</u>	1143
<u>Message ID : DXF4316I</u>	1143
<u>Message ID : DXF4317I</u>	1144
<u>Message ID : DXF4318I</u>	1145
<u>Message ID : DXF4319I</u>	1146
<u>Message ID : DXF4320I</u>	1147
<u>Message ID : DXF4321I</u>	1148
<u>Message ID : DXF4322I</u>	1148
<u>Message ID : DXF4323I</u>	1149
<u>Message ID : DXF4329I</u>	1150
<u>Message ID : DXF4332I</u>	1151
<u>Message ID : DXF4344I</u>	1152
<u>Message ID : DXF4345I</u>	1153
<u>Message ID : DXF4352I</u>	1154
<u>Message ID : DXF4361I</u>	1154
<u>Message ID : DXF4362I</u>	1155
<u>Message ID : DXF4363I</u>	1156
<u>Message ID : DXF4364I</u>	1157
<u>Message ID : DXF4365I</u>	1158
<u>Message ID : DXF4366I</u>	1159
<u>Message ID : DXF4369I</u>	1160
<u>Message ID : DXF4370I</u>	1161
<u>Message ID : DXF4371I</u>	1162

Table of Contents

Logger DXF: Information

<u>Message ID : DXF4372I</u>	1163
<u>Message ID : DXF4375I</u>	1164
<u>Message ID : DXF4378I</u>	1164
<u>Message ID : DXF4380I</u>	1165
<u>Message ID : DXF4383I</u>	1166
<u>Message ID : DXF4384I</u>	1167
<u>Message ID : DXF4385I</u>	1168
<u>Message ID : DXF4386I</u>	1169
<u>Message ID : DXF4387I</u>	1170
<u>Message ID : DXF4388I</u>	1171
<u>Message ID : DXF4389I</u>	1172
<u>Message ID : DXF4390I</u>	1173
<u>Message ID : DXF4397I</u>	1173
<u>Message ID : DXF4399I</u>	1174
<u>Message ID : DXF4414I</u>	1175
<u>Message ID : DXF4415I</u>	1176
<u>Message ID : DXF4416I</u>	1177
<u>Message ID : DXF4417I</u>	1178
<u>Message ID : DXF4418I</u>	1178
<u>Message ID : DXF4419I</u>	1179
<u>Message ID : DXF4420I</u>	1180
<u>Message ID : DXF4421I</u>	1181
<u>Message ID : DXF4422I</u>	1182
<u>Message ID : DXF4423I</u>	1183
<u>Message ID : DXF4424I</u>	1184
<u>Message ID : DXF4425I</u>	1185

Table of Contents

Logger DXF: Information

<u>Message ID : DXF4429I</u>	1186
<u>Message ID : DXF4481I</u>	1187
<u>Message ID : DXF4485I</u>	1188
<u>Message ID : DXF4487I</u>	1188
<u>Message ID : DXF4488I</u>	1189
<u>Message ID : DXF4489I</u>	1190
<u>Message ID : DXF4490I</u>	1191
<u>Message ID : DXF4491I</u>	1192
<u>Message ID : DXF4492I</u>	1193
<u>Message ID : DXF4493I</u>	1193
<u>Message ID : DXF4495I</u>	1194
<u>Message ID : DXF4496I</u>	1195
<u>Message ID : DXF4497I</u>	1196

Logger DXF: Warnings.....**1197**

<u>Message ID : DXF3210W</u>	1197
<u>Message ID : DXF4103W</u>	1198
<u>Message ID : DXF4104W</u>	1198
<u>Message ID : DXF4118W</u>	1199
<u>Message ID : DXF4242W</u>	1200
<u>Message ID : DXF4254W</u>	1201
<u>Message ID : DXF4307W</u>	1202
<u>Message ID : DXF4324W</u>	1203
<u>Message ID : DXF4327W</u>	1203
<u>Message ID : DXF4333W</u>	1204
<u>Message ID : DXF4337W</u>	1205

Table of Contents

<u>Logger DXF: Warnings</u>	
<u>Message ID : DXF4338W</u>	1206
<u>Message ID : DXF4339W</u>	1207
<u>Message ID : DXF4351W</u>	1207
<u>Message ID : DXF4359W</u>	1208
<u>Message ID : DXF4373W</u>	1209
<u>Message ID : DXF4398W</u>	1210
<u>Message ID : DXF4406W</u>	1211
<u>Message ID : DXF4410W</u>	1212
<u>Message ID : DXF4413W</u>	1213
<u>Message ID : DXF4428W</u>	1213
<u>Logger FIP: Fatal errors</u>	1215
<u>Message ID : FIP0625E</u>	1215
<u>Message ID : FIP0626E</u>	1216
<u>Logger FIP: Information</u>	1217
<u>Message ID : FIP0624I</u>	1217
<u>Logger GEN: Errors</u>	1218
<u>Message ID : GEN1253E</u>	1218
<u>Message ID : GEN1280E</u>	1218
<u>Logger GEN: Information</u>	1220
<u>Message ID : GEN1276I</u>	1220
<u>Message ID : GEN1279I</u>	1221

Table of Contents

<u>Logger IEP: Errors</u>	1222
<u>Message ID : IEP0321E</u>	1222
<u>Message ID : IEP0322E</u>	1222
<u>Message ID : IEP0323E</u>	1223
<u>Message ID : IEP0324E</u>	1224
<u>Message ID : IEP0325E</u>	1224
<u>Message ID : IEP0326E</u>	1225
<u>Message ID : IEP0327E</u>	1226
<u>Message ID : IEP0328E</u>	1226
<u>Message ID : IEP0329E</u>	1227
<u>Message ID : IEP0330E</u>	1228
<u>Message ID : IEP0331E</u>	1228
<u>Message ID : IEP0332E</u>	1229
<u>Logger IEP: Information</u>	1231
<u>Message ID : IEP0577I</u>	1231
<u>Logger IEP: Warnings</u>	1232
<u>Message ID : IEP0338W</u>	1232
<u>Message ID : IEP0342W</u>	1233
<u>Message ID : IEP0343W</u>	1233
<u>Message ID : IEP0344W</u>	1234
<u>Message ID : IEP0345W</u>	1235
<u>Logger KMG: Errors</u>	1236
<u>Message ID : KMG0065E</u>	1236
<u>Message ID : KMG0068E</u>	1236

Table of Contents

Logger KMG: Errors

<u>Message ID : KMG0094E</u>	1237
<u>Message ID : KMG0095E</u>	1238
<u>Message ID : KMG0096E</u>	1238
<u>Message ID : KMG0097E</u>	1239
<u>Message ID : KMG0098E</u>	1240
<u>Message ID : KMG0099E</u>	1241
<u>Message ID : KMG0100E</u>	1241
<u>Message ID : KMG0101E</u>	1242
<u>Message ID : KMG0102E</u>	1243
<u>Message ID : KMG0103E</u>	1243
<u>Message ID : KMG0104E</u>	1244
<u>Message ID : KMG0105E</u>	1245
<u>Message ID : KMG0106E</u>	1245
<u>Message ID : KMG0107E</u>	1246
<u>Message ID : KMG0108E</u>	1247
<u>Message ID : KMG0109E</u>	1248
<u>Message ID : KMG0110E</u>	1248
<u>Message ID : KMG0111E</u>	1249
<u>Message ID : KMG0112E</u>	1250
<u>Message ID : KMG0113E</u>	1251
<u>Message ID : KMG0114E</u>	1251
<u>Message ID : KMG0220E</u>	1252
<u>Message ID : KMG0221E</u>	1253
<u>Message ID : KMG0222E</u>	1253
<u>Message ID : KMG0256E</u>	1254
<u>Message ID : KMG0257E</u>	1255

Table of Contents

Logger KMG: Errors

<u>Message ID : KMG0258E</u>	1255
<u>Message ID : KMG0262E</u>	1256
<u>Message ID : KMG0265E</u>	1257
<u>Message ID : KMG0273E</u>	1257
<u>Message ID : KMG0274E</u>	1258
<u>Message ID : KMG0285E</u>	1259
<u>Message ID : KMG0301E</u>	1259
<u>Message ID : KMG0307E</u>	1260
<u>Message ID : KMG0524E</u>	1261
<u>Message ID : KMG0615E</u>	1262
<u>Message ID : KMG0616E</u>	1262
<u>Message ID : KMG0686E</u>	1263
<u>Message ID : KMG0687E</u>	1264
<u>Message ID : KMG0688E</u>	1264
<u>Message ID : KMG0689E</u>	1265
<u>Message ID : KMG0690E</u>	1266
<u>Message ID : KMG0691E</u>	1266
<u>Message ID : KMG0692E</u>	1267
<u>Message ID : KMG0693E</u>	1268
<u>Message ID : KMG0694E</u>	1268
<u>Message ID : KMG0695E</u>	1269
<u>Message ID : KMG0696E</u>	1270
<u>Message ID : KMG0698E</u>	1270
<u>Message ID : KMG0699E</u>	1271
<u>Message ID : KMG0700E</u>	1272
<u>Message ID : KMG0708E</u>	1272

Table of Contents

Logger KMG: Errors

<u>Message ID : KMG0709E</u>	1273
<u>Message ID : KMG0726E</u>	1274
<u>Message ID : KMG0727E</u>	1274
<u>Message ID : KMG0728E</u>	1275
<u>Message ID : KMG0729E</u>	1276
<u>Message ID : KMG0730E</u>	1276
<u>Message ID : KMG0731E</u>	1277
<u>Message ID : KMG0732E</u>	1278
<u>Message ID : KMG0733E</u>	1278
<u>Message ID : KMG0734E</u>	1279
<u>Message ID : KMG0735E</u>	1280
<u>Message ID : KMG0736E</u>	1280
<u>Message ID : KMG0737E</u>	1281
<u>Message ID : KMG0738E</u>	1282
<u>Message ID : KMG0739E</u>	1282
<u>Message ID : KMG0740E</u>	1283
<u>Message ID : KMG0741E</u>	1284
<u>Message ID : KMG0742E</u>	1284
<u>Message ID : KMG0743E</u>	1285
<u>Message ID : KMG0744E</u>	1286
<u>Message ID : KMG0745E</u>	1286
<u>Message ID : KMG0746E</u>	1287
<u>Message ID : KMG0747E</u>	1288
<u>Message ID : KMG0748E</u>	1288
<u>Message ID : KMG0749E</u>	1289
<u>Message ID : KMG0750E</u>	1290

Table of Contents

Logger KMG: Errors

<u>Message ID : KMG0751E</u>	1290
<u>Message ID : KMG0752E</u>	1291
<u>Message ID : KMG0753E</u>	1292
<u>Message ID : KMG0754E</u>	1292
<u>Message ID : KMG0755E</u>	1293
<u>Message ID : KMG0756E</u>	1294
<u>Message ID : KMG0757E</u>	1294
<u>Message ID : KMG0758E</u>	1295
<u>Message ID : KMG0760E</u>	1296
<u>Message ID : KMG0762E</u>	1296
<u>Message ID : KMG0765E</u>	1297
<u>Message ID : KMG0766E</u>	1298
<u>Message ID : KMG0767E</u>	1298
<u>Message ID : KMG0768E</u>	1299
<u>Message ID : KMG0769E</u>	1300
<u>Message ID : KMG0770E</u>	1300
<u>Message ID : KMG0773E</u>	1301
<u>Message ID : KMG0775E</u>	1302
<u>Message ID : KMG1252E</u>	1302
<u>Message ID : KMG1255E</u>	1303
<u>Message ID : KMG1258E</u>	1304
<u>Message ID : KMG1267E</u>	1304
<u>Message ID : KMG1268E</u>	1305
<u>Message ID : KMG1269E</u>	1306
<u>Message ID : KMG1270E</u>	1306
<u>Message ID : KMG1271E</u>	1307

Table of Contents

Logger KMG: Errors

<u>Message ID : KMG1272E</u>	1308
<u>Message ID : KMG1273E</u>	1308
<u>Message ID : KMG1274E</u>	1309
<u>Message ID : KMG1282E</u>	1310
<u>Message ID : KMG1283E</u>	1310
<u>Message ID : KMG1284E</u>	1311
<u>Message ID : KMG1338E</u>	1312
<u>Message ID : KMG1339E</u>	1312
<u>Message ID : KMG1340E</u>	1313
<u>Message ID : KMG1341E</u>	1314
<u>Message ID : KMG1380E</u>	1314
<u>Message ID : KMG1382E</u>	1315
<u>Message ID : KMG1383E</u>	1316
<u>Message ID : KMG1384E</u>	1316
<u>Message ID : KMG1385E</u>	1317
<u>Message ID : KMG1387E</u>	1318
<u>Message ID : KMG1388E</u>	1318
<u>Message ID : KMG1394E</u>	1319
<u>Message ID : KMG1409E</u>	1320
<u>Message ID : KMG1410E</u>	1320
<u>Message ID : KMG1411E</u>	1321
<u>Message ID : KMG1412E</u>	1322
<u>Message ID : KMG1413E</u>	1322
<u>Message ID : KMG1414E</u>	1323
<u>Message ID : KMG1416E</u>	1324
<u>Message ID : KMG1417E</u>	1324

Table of Contents

Logger KMG: Errors

<u>Message ID : KMG1418E</u>	1325
<u>Message ID : KMG1430E</u>	1326
<u>Message ID : KMG1512E</u>	1326
<u>Message ID : KMG1518E</u>	1327
<u>Message ID : KMG1521E</u>	1328
<u>Message ID : KMG1522E</u>	1328
<u>Message ID : KMG1523E</u>	1329
<u>Message ID : KMG1525E</u>	1330
<u>Message ID : KMG1526E</u>	1330
<u>Message ID : KMG1527E</u>	1331
<u>Message ID : KMG1528E</u>	1332
<u>Message ID : KMG1529E</u>	1332
<u>Message ID : KMG1531E</u>	1333
<u>Message ID : KMG1532E</u>	1334
<u>Message ID : KMG1533E</u>	1334
<u>Message ID : KMG1534E</u>	1335
<u>Message ID : KMG1535E</u>	1336
<u>Message ID : KMG1536E</u>	1336
<u>Message ID : KMG1537E</u>	1337
<u>Message ID : KMG1538E</u>	1338
<u>Message ID : KMG1539E</u>	1338
<u>Message ID : KMG1540E</u>	1339
<u>Message ID : KMG1541E</u>	1340
<u>Message ID : KMG1542E</u>	1340
<u>Message ID : KMG1544E</u>	1341
<u>Message ID : KMG1545E</u>	1342

Table of Contents

Logger KMG: Errors

<u>Message ID : KMG1546E</u>	1342
<u>Message ID : KMG1547E</u>	1343
<u>Message ID : KMG1566E</u>	1344
<u>Message ID : KMG1591E</u>	1344
<u>Message ID : KMG1592E</u>	1345
<u>Message ID : KMG1593E</u>	1346
<u>Message ID : KMG1594E</u>	1346
<u>Message ID : KMG1595E</u>	1347
<u>Message ID : KMG1596E</u>	1348
<u>Message ID : KMG1597E</u>	1348
<u>Message ID : KMG1598E</u>	1349
<u>Message ID : KMG1599E</u>	1350
<u>Message ID : KMG1600E</u>	1350
<u>Message ID : KMG1610E</u>	1351
<u>Message ID : KMG1612E</u>	1352
<u>Message ID : KMG1613E</u>	1352
<u>Message ID : KMG1618E</u>	1353
<u>Message ID : KMG1619E</u>	1354
<u>Message ID : KMG1620E</u>	1354
<u>Message ID : KMG1621E</u>	1355
<u>Message ID : KMG1622E</u>	1356
<u>Message ID : KMG1624E</u>	1356
<u>Message ID : KMG1625E</u>	1357
<u>Message ID : KMG1626E</u>	1358
<u>Message ID : KMG1633E</u>	1359
<u>Message ID : KMG1635E</u>	1359

Table of Contents

Logger KMG: Errors

<u>Message ID : KMG1636E</u>	1360
<u>Message ID : KMG1637E</u>	1361
<u>Message ID : KMG1638E</u>	1361
<u>Message ID : KMG1639E</u>	1362
<u>Message ID : KMG1640E</u>	1363
<u>Message ID : KMG1641E</u>	1363
<u>Message ID : KMG1642E</u>	1364
<u>Message ID : KMG1643E</u>	1365
<u>Message ID : KMG1644E</u>	1365
<u>Message ID : KMG1647E</u>	1366
<u>Message ID : KMG1648E</u>	1367
<u>Message ID : KMG1650E</u>	1367
<u>Message ID : KMG1651E</u>	1368
<u>Message ID : KMG1653E</u>	1369
<u>Message ID : KMG1654E</u>	1369
<u>Message ID : KMG1660E</u>	1370
<u>Message ID : KMG1661E</u>	1371
<u>Message ID : KMG1666E</u>	1371
<u>Message ID : KMG1667E</u>	1372
<u>Message ID : KMG1670E</u>	1373
<u>Message ID : KMG1674E</u>	1373
<u>Message ID : KMG1675E</u>	1374
<u>Message ID : KMG1676E</u>	1375
<u>Message ID : KMG1677E</u>	1375
<u>Message ID : KMG1694E</u>	1376
<u>Message ID : KMG1695E</u>	1377

Table of Contents

Logger KMG: Errors

<u>Message ID : KMG1696E</u>	1377
<u>Message ID : KMG1698E</u>	1378
<u>Message ID : KMG1699E</u>	1379
<u>Message ID : KMG1700E</u>	1379
<u>Message ID : KMG1701E</u>	1380
<u>Message ID : KMG1720E</u>	1381
<u>Message ID : KMG1728E</u>	1381
<u>Message ID : KMG1745E</u>	1382
<u>Message ID : KMG1762E</u>	1383
<u>Message ID : KMG1763E</u>	1383
<u>Message ID : KMG1764E</u>	1384
<u>Message ID : KMG1765E</u>	1385
<u>Message ID : KMG1766E</u>	1385
<u>Message ID : KMG1767E</u>	1386
<u>Message ID : KMG1768E</u>	1387
<u>Message ID : KMG1771E</u>	1387
<u>Message ID : KMG1772E</u>	1388
<u>Message ID : KMG1773E</u>	1389
<u>Message ID : KMG1782E</u>	1389
<u>Message ID : KMG1849E</u>	1390
<u>Message ID : KMG1850E</u>	1391
<u>Message ID : KMG1868E</u>	1391

Logger KMG: Information.....1393

<u>Message ID : KMG0547I</u>	1393
<u>Message ID : KMG0610I</u>	1393

Table of Contents

Logger KMG: Information

<u>Message ID : KMG0611I</u>	1394
<u>Message ID : KMG0761I</u>	1395
<u>Message ID : KMG1220I</u>	1396
<u>Message ID : KMG1221I</u>	1397
<u>Message ID : KMG1361I</u>	1398
<u>Message ID : KMG1362I</u>	1398
<u>Message ID : KMG1381I</u>	1399
<u>Message ID : KMG1386I</u>	1400
<u>Message ID : KMG1543I</u>	1400
<u>Message ID : KMG1645I</u>	1401
<u>Message ID : KMG1646I</u>	1402

Logger KMG: Warnings.....**1403**

<u>Message ID : KMG0596W</u>	1403
<u>Message ID : KMG0774W</u>	1403
<u>Message ID : KMG1200W</u>	1404
<u>Message ID : KMG1201W</u>	1405
<u>Message ID : KMG1202W</u>	1406
<u>Message ID : KMG1203W</u>	1407
<u>Message ID : KMG1210W</u>	1407
<u>Message ID : KMG1211W</u>	1408
<u>Message ID : KMG1212W</u>	1409
<u>Message ID : KMG1213W</u>	1410
<u>Message ID : KMG1295W</u>	1411
<u>Message ID : KMG1300W</u>	1412
<u>Message ID : KMG1512W</u>	1412

Table of Contents

Logger LIC: Errors	1414
<u>Message ID : LIC0276E</u>	1414
<u>Message ID : LIC0277E</u>	1414
<u>Message ID : LIC0278E</u>	1415
<u>Message ID : LIC0279E</u>	1416
<u>Message ID : LIC0580E</u>	1416
<u>Message ID : LIC0581E</u>	1417
<u>Message ID : LIC0582E</u>	1418
<u>Message ID : LIC0586E</u>	1418
<u>Message ID : LIC1160E</u>	1419
<u>Message ID : LIC1161E</u>	1420
<u>Message ID : LIC1162E</u>	1421
<u>Message ID : LIC1163E</u>	1422
<u>Message ID : LIC1164E</u>	1422
<u>Message ID : LIC1165E</u>	1423
<u>Message ID : LIC1166E</u>	1424
<u>Message ID : LIC1167E</u>	1424
<u>Message ID : LIC1261E</u>	1425
<u>Message ID : LIC1291E</u>	1426
<u>Message ID : LIC1292E</u>	1426
<u>Message ID : LIC1293E</u>	1427
<u>Message ID : LIC1298E</u>	1428
<u>Message ID : LIC1324E</u>	1428
<u>Message ID : LIC1325E</u>	1429
<u>Message ID : LIC1326E</u>	1430
<u>Message ID : LIC1327E</u>	1430
<u>Message ID : LIC1621E</u>	1431

Table of Contents

<u>Logger LIC: Errors</u>	
<u>Message ID : LIC1690E</u>	1432
<u>Message ID : LIC1691E</u>	1432
<u>Message ID : LIC1736E</u>	1433
<u>Message ID : LIC1737E</u>	1434
<u>Logger LIC: Information</u>	1435
<u>Message ID : LIC0587I</u>	1435
<u>Logger LIC: Warnings</u>	1436
<u>Message ID : LIC1323W</u>	1436
<u>Logger LOG: Errors</u>	1437
<u>Message ID : LOG0138E</u>	1437
<u>Message ID : LOG0139E</u>	1437
<u>Message ID : LOG0287E</u>	1438
<u>Logger LOG: Information</u>	1440
<u>Message ID : LOG0140I</u>	1440
<u>Message ID : LOG0141I</u>	1441
<u>Message ID : LOG0541I</u>	1441
<u>Message ID : LOG0669I</u>	1442
<u>Logger LOG: Warnings</u>	1444
<u>Message ID : LOG0668W</u>	1444
<u>Message ID : LOG1318W</u>	1445

Table of Contents

<u>Logger LUP: Errors</u>	1446
<u>Message ID : LUP0114E</u>	1446
<u>Message ID : LUP0117E</u>	1447
<u>Message ID : LUP0118E</u>	1448
<u>Message ID : LUP0119E</u>	1448
<u>Message ID : LUP0120E</u>	1449
<u>Message ID : LUP0121E</u>	1450
<u>Message ID : LUP0122E</u>	1451
<u>Message ID : LUP0123E</u>	1452
<u>Message ID : LUP0128E</u>	1453
<u>Message ID : LUP0131E</u>	1454
<u>Message ID : LUP0132E</u>	1455
<u>Message ID : LUP0133E</u>	1455
<u>Message ID : LUP0134E</u>	1456
<u>Message ID : LUP0135E</u>	1457
<u>Message ID : LUP0136E</u>	1458
<u>Message ID : LUP0299E</u>	1459
<u>Logger LUP: Fatal errors</u>	1461
<u>Message ID : LUP0124F</u>	1461
<u>Message ID : LUP0126F</u>	1462
<u>Message ID : LUP0127F</u>	1462
<u>Message ID : LUP0129F</u>	1463
<u>Message ID : LUP0130F</u>	1464
<u>Message ID : LUP0137F</u>	1465

Table of Contents

<u>Logger LUP: Information</u>	1467
<u>Message ID : LUP0115I</u>	1467
<u>Message ID : LUP0116I</u>	1467
<u>Message ID : LUP0125I</u>	1468
<u>Message ID : LUP0428I</u>	1469
<u>Logger PLC: Errors</u>	1471
<u>Message ID : PLC0179E</u>	1471
<u>Message ID : PLC0180E</u>	1471
<u>Message ID : PLC0183E</u>	1472
<u>Message ID : PLC0184E</u>	1473
<u>Message ID : PLC0185E</u>	1473
<u>Message ID : PLC0186E</u>	1474
<u>Message ID : PLC0187E</u>	1475
<u>Message ID : PLC0188E</u>	1475
<u>Message ID : PLC0189E</u>	1476
<u>Message ID : PLC0190E</u>	1477
<u>Message ID : PLC0191E</u>	1477
<u>Message ID : PLC0192E</u>	1478
<u>Message ID : PLC0193E</u>	1479
<u>Message ID : PLC0194E</u>	1479
<u>Message ID : PLC0195E</u>	1480
<u>Message ID : PLC0196E</u>	1481
<u>Message ID : PLC0288E</u>	1481
<u>Message ID : PLC0302E</u>	1482
<u>Message ID : PLC0548E</u>	1483
<u>Message ID : PLC0604E</u>	1483

Table of Contents

Logger PLC: Errors

<u>Message ID : PLC0764E</u>	1484
<u>Message ID : PLC0806E</u>	1485
<u>Message ID : PLC1301E</u>	1485
<u>Message ID : PLC1302E</u>	1486
<u>Message ID : PLC1303E</u>	1487
<u>Message ID : PLC1304E</u>	1487
<u>Message ID : PLC1305E</u>	1488
<u>Message ID : PLC1306E</u>	1489
<u>Message ID : PLC1309E</u>	1489
<u>Message ID : PLC1313E</u>	1490
<u>Message ID : PLC1316E</u>	1491
<u>Message ID : PLC1317E</u>	1491
<u>Message ID : PLC1320E</u>	1492
<u>Message ID : PLC1321E</u>	1493
<u>Message ID : PLC1500E</u>	1494
<u>Message ID : PLC1501E</u>	1494
<u>Message ID : PLC1502E</u>	1495
<u>Message ID : PLC1503E</u>	1496
<u>Message ID : PLC1505E</u>	1496
<u>Message ID : PLC1506E</u>	1497
<u>Message ID : PLC1507E</u>	1498
<u>Message ID : PLC1508E</u>	1498
<u>Message ID : PLC1509E</u>	1499
<u>Message ID : PLC1512E</u>	1500
<u>Message ID : PLC1515E</u>	1500
<u>Message ID : PLC1516E</u>	1501

Table of Contents

Logger PLC: Errors

<u>Message ID : PLC1517E</u>	1502
<u>Message ID : PLC1518E</u>	1502
<u>Message ID : PLC1623E</u>	1503
<u>Message ID : PLC1624E</u>	1504
<u>Message ID : PLC1671E</u>	1504
<u>Message ID : PLC1672E</u>	1505
<u>Message ID : PLC1673E</u>	1506
<u>Message ID : PLC1678E</u>	1506
<u>Message ID : PLC1679E</u>	1507
<u>Message ID : PLC1680E</u>	1508
<u>Message ID : PLC1681E</u>	1509
<u>Message ID : PLC1682E</u>	1509
<u>Message ID : PLC1688E</u>	1510
<u>Message ID : PLC1704E</u>	1511
<u>Message ID : PLC1719E</u>	1511
<u>Message ID : PLC1743E</u>	1512
<u>Message ID : PLC1751E</u>	1513
<u>Message ID : PLC1752E</u>	1514
<u>Message ID : PLC1753E</u>	1514
<u>Message ID : PLC1754E</u>	1515
<u>Message ID : PLC1755E</u>	1516
<u>Message ID : PLC1756E</u>	1516
<u>Message ID : PLC1757E</u>	1517
<u>Message ID : PLC1779E</u>	1518
<u>Message ID : PLC1780E</u>	1518
<u>Message ID : PLC1781E</u>	1519

Table of Contents

Logger PLC: Errors

<u>Message ID : PLC1783E</u>	1520
<u>Message ID : PLC1785E</u>	1520
<u>Message ID : PLC1786E</u>	1521
<u>Message ID : PLC1787E</u>	1522
<u>Message ID : PLC1788E</u>	1522
<u>Message ID : PLC1789E</u>	1523
<u>Message ID : PLC1820E</u>	1524

Logger PLC: Information.....1525

<u>Message ID : PLC1511I</u>	1525
<u>Message ID : PLC1513I</u>	1526
<u>Message ID : PLC1514I</u>	1526

Logger PLC: Warnings.....1528

<u>Message ID : PLC0181W</u>	1528
<u>Message ID : PLC0182W</u>	1528
<u>Message ID : PLC1318W</u>	1529
<u>Message ID : PLC1319W</u>	1530
<u>Message ID : PLC1369W</u>	1530
<u>Message ID : PLC1370W</u>	1531
<u>Message ID : PLC1371W</u>	1532
<u>Message ID : PLC1372W</u>	1533
<u>Message ID : PLC1373W</u>	1533
<u>Message ID : PLC1374W</u>	1534

Table of Contents

<u>Logger POL: Errors</u>	1536
<u>Message ID : POL4556E</u>	1536
<u>Message ID : POL4580E</u>	1537
<u>Message ID : POL4613E</u>	1538
<u>Message ID : POL4701E</u>	1539
<u>Message ID : POL4704E</u>	1540
<u>Logger POL: Fatal errors</u>	1541
<u>Message ID : POL4510F</u>	1541
<u>Message ID : POL4516F</u>	1542
<u>Message ID : POL4528F</u>	1543
<u>Message ID : POL4530F</u>	1544
<u>Message ID : POL4545F</u>	1545
<u>Message ID : POL4564F</u>	1545
<u>Message ID : POL4581F</u>	1546
<u>Message ID : POL4593F</u>	1547
<u>Message ID : POL4614F</u>	1548
<u>Logger POL: Information</u>	1550
<u>Message ID : POL0142I</u>	1550
<u>Message ID : POL0143I</u>	1550
<u>Message ID : POL0144I</u>	1551
<u>Message ID : POL0145I</u>	1553
<u>Message ID : POL0146I</u>	1554
<u>Message ID : POL0147I</u>	1555
<u>Message ID : POL0148I</u>	1556
<u>Message ID : POL0149I</u>	1558

Table of Contents

Logger POL: Information

<u>Message ID : POL0150I</u>	1559
<u>Message ID : POL0151I</u>	1559
<u>Message ID : POL0152I</u>	1560
<u>Message ID : POL0153I</u>	1561
<u>Message ID : POL0154I</u>	1562
<u>Message ID : POL0155I</u>	1562
<u>Message ID : POL4537I</u>	1563
<u>Message ID : POL4553I</u>	1564
<u>Message ID : POL4573I</u>	1565
<u>Message ID : POL4574I</u>	1566
<u>Message ID : POL4575I</u>	1567
<u>Message ID : POL4576I</u>	1568
<u>Message ID : POL4582I</u>	1569
<u>Message ID : POL4615I</u>	1569
<u>Message ID : POL4702I</u>	1571

Logger POL: Warnings.....1572

<u>Message ID : POL4703W</u>	1572
------------------------------------	------

Logger SDK: Errors.....1573

<u>Message ID : SDK0197E</u>	1573
<u>Message ID : SDK0198E</u>	1573
<u>Message ID : SDK0199E</u>	1574
<u>Message ID : SDK0200E</u>	1575
<u>Message ID : SDK0201E</u>	1575
<u>Message ID : SDK0202E</u>	1576

Table of Contents

Logger SDK: Errors

<u>Message ID : SDK0203E</u>	1577
<u>Message ID : SDK0204E</u>	1577
<u>Message ID : SDK0205E</u>	1578
<u>Message ID : SDK0206E</u>	1579
<u>Message ID : SDK0207E</u>	1579
<u>Message ID : SDK0208E</u>	1580
<u>Message ID : SDK0283E</u>	1581
<u>Message ID : SDK0284E</u>	1581
<u>Message ID : SDK0286E</u>	1582
<u>Message ID : SDK0403E</u>	1583
<u>Message ID : SDK0407E</u>	1583
<u>Message ID : SDK0408E</u>	1584
<u>Message ID : SDK0410E</u>	1585
<u>Message ID : SDK0411E</u>	1585
<u>Message ID : SDK0416E</u>	1586
<u>Message ID : SDK0417E</u>	1587
<u>Message ID : SDK0418E</u>	1587
<u>Message ID : SDK0419E</u>	1588
<u>Message ID : SDK0420E</u>	1589
<u>Message ID : SDK0421E</u>	1589
<u>Message ID : SDK0422E</u>	1590
<u>Message ID : SDK0423E</u>	1591
<u>Message ID : SDK0427E</u>	1591
<u>Message ID : SDK0437E</u>	1592
<u>Message ID : SDK0438E</u>	1593
<u>Message ID : SDK0439E</u>	1593

Table of Contents

Logger SDK: Errors

<u>Message ID : SDK0440E</u>	1594
<u>Message ID : SDK0441E</u>	1595
<u>Message ID : SDK0442E</u>	1596
<u>Message ID : SDK0443E</u>	1596
<u>Message ID : SDK0444E</u>	1597
<u>Message ID : SDK0447E</u>	1598
<u>Message ID : SDK0450E</u>	1598
<u>Message ID : SDK0451E</u>	1599
<u>Message ID : SDK0503E</u>	1600
<u>Message ID : SDK0504E</u>	1600
<u>Message ID : SDK0505E</u>	1601
<u>Message ID : SDK0517E</u>	1602
<u>Message ID : SDK0525E</u>	1602
<u>Message ID : SDK0526E</u>	1603
<u>Message ID : SDK0533E</u>	1604
<u>Message ID : SDK0534E</u>	1604
<u>Message ID : SDK0608E</u>	1605
<u>Message ID : SDK0630E</u>	1606
<u>Message ID : SDK0637E</u>	1607
<u>Message ID : SDK0662E</u>	1607
<u>Message ID : SDK0663E</u>	1608
<u>Message ID : SDK0664E</u>	1609
<u>Message ID : SDK0670E</u>	1610
<u>Message ID : SDK0671E</u>	1610
<u>Message ID : SDK0716E</u>	1611
<u>Message ID : SDK0717E</u>	1612

Table of Contents

Logger SDK: Errors

<u>Message ID : SDK0718E</u>	1612
<u>Message ID : SDK0719E</u>	1613
<u>Message ID : SDK0776E</u>	1614
<u>Message ID : SDK0777E</u>	1614
<u>Message ID : SDK0778E</u>	1615
<u>Message ID : SDK0780E</u>	1616
<u>Message ID : SDK0800E</u>	1616
<u>Message ID : SDK0801E</u>	1617
<u>Message ID : SDK1237E</u>	1618
<u>Message ID : SDK1238E</u>	1618
<u>Message ID : SDK1239E</u>	1619
<u>Message ID : SDK1240E</u>	1620
<u>Message ID : SDK1241E</u>	1620
<u>Message ID : SDK1242E</u>	1621
<u>Message ID : SDK1243E</u>	1622
<u>Message ID : SDK1256E</u>	1622
<u>Message ID : SDK1262E</u>	1623
<u>Message ID : SDK1296E</u>	1624
<u>Message ID : SDK1315E</u>	1624
<u>Message ID : SDK1324E</u>	1625
<u>Message ID : SDK1340E</u>	1626
<u>Message ID : SDK1365E</u>	1626
<u>Message ID : SDK1385E</u>	1627
<u>Message ID : SDK1386E</u>	1628
<u>Message ID : SDK1387E</u>	1628
<u>Message ID : SDK1388E</u>	1629

Table of Contents

Logger SDK: Errors

<u>Message ID : SDK1389E</u>	1630
<u>Message ID : SDK1390E</u>	1630
<u>Message ID : SDK1391E</u>	1631
<u>Message ID : SDK1407E</u>	1632
<u>Message ID : SDK1426E</u>	1632
<u>Message ID : SDK1504E</u>	1633
<u>Message ID : SDK1508E</u>	1634
<u>Message ID : SDK1513E</u>	1634
<u>Message ID : SDK1550E</u>	1635
<u>Message ID : SDK1553E</u>	1636
<u>Message ID : SDK1554E</u>	1636
<u>Message ID : SDK1558E</u>	1637
<u>Message ID : SDK1564E</u>	1638
<u>Message ID : SDK1565E</u>	1638
<u>Message ID : SDK1566E</u>	1639
<u>Message ID : SDK1567E</u>	1640
<u>Message ID : SDK1568E</u>	1640
<u>Message ID : SDK1617E</u>	1641
<u>Message ID : SDK1619E</u>	1642
<u>Message ID : SDK1620E</u>	1642
<u>Message ID : SDK1621E</u>	1643
<u>Message ID : SDK1622E</u>	1644
<u>Message ID : SDK1623E</u>	1644
<u>Message ID : SDK1649E</u>	1645
<u>Message ID : SDK1652E</u>	1646
<u>Message ID : SDK1654E</u>	1646

Table of Contents

Logger SDK: Errors

<u>Message ID : SDK1655E</u>	1647
<u>Message ID : SDK1660E</u>	1648
<u>Message ID : SDK1663E</u>	1648
<u>Message ID : SDK1668E</u>	1649
<u>Message ID : SDK1671E</u>	1650
<u>Message ID : SDK1672E</u>	1650
<u>Message ID : SDK1683E</u>	1651
<u>Message ID : SDK1706E</u>	1652
<u>Message ID : SDK1718E</u>	1652
<u>Message ID : SDK1731E</u>	1653
<u>Message ID : SDK1742E</u>	1654
<u>Message ID : SDK1746E</u>	1654
<u>Message ID : SDK1747E</u>	1655
<u>Message ID : SDK1760E</u>	1656
<u>Message ID : SDK1761E</u>	1656
<u>Message ID : SDK1769E</u>	1657
<u>Message ID : SDK1770E</u>	1658
<u>Message ID : SDK1795E</u>	1658
<u>Message ID : SDK1796E</u>	1659
<u>Message ID : SDK1797E</u>	1660
<u>Message ID : SDK1798E</u>	1661
<u>Message ID : SDK1801E</u>	1661
<u>Message ID : SDK1802E</u>	1662
<u>Message ID : SDK1803E</u>	1663
<u>Message ID : SDK1807E</u>	1663
<u>Message ID : SDK1808E</u>	1664

Table of Contents

Logger SDK: Errors

<u>Message ID : SDK1809E</u>	1665
<u>Message ID : SDK1811E</u>	1665
<u>Message ID : SDK1812E</u>	1666
<u>Message ID : SDK1814E</u>	1667
<u>Message ID : SDK1815E</u>	1667
<u>Message ID : SDK1817E</u>	1668
<u>Message ID : SDK1818E</u>	1669
<u>Message ID : SDK1819E</u>	1669
<u>Message ID : SDK1821E</u>	1670
<u>Message ID : SDK1822E</u>	1671
<u>Message ID : SDK1823E</u>	1671
<u>Message ID : SDK1824E</u>	1672
<u>Message ID : SDK1829E</u>	1673
<u>Message ID : SDK1830E</u>	1673
<u>Message ID : SDK1843E</u>	1674
<u>Message ID : SDK1851E</u>	1675
<u>Message ID : SDK1852E</u>	1675
<u>Message ID : SDK1853E</u>	1676
<u>Message ID : SDK1854E</u>	1677
<u>Message ID : SDK1855E</u>	1677
<u>Message ID : SDK1856E</u>	1678
<u>Message ID : SDK1857E</u>	1679
<u>Message ID : SDK1858E</u>	1679
<u>Message ID : SDK1859E</u>	1680
<u>Message ID : SDK1860E</u>	1681
<u>Message ID : SDK1870E</u>	1681

Table of Contents

Logger SDK: Errors

<u>Message ID : SDK1871E</u>	1682
------------------------------------	------

Logger SDK: Information.....**1683**

<u>Message ID : SDK0544I</u>	1683
<u>Message ID : SDK0545I</u>	1684
<u>Message ID : SDK0665I</u>	1684
<u>Message ID : SDK1551I</u>	1685
<u>Message ID : SDK1552I</u>	1686
<u>Message ID : SDK1555I</u>	1687
<u>Message ID : SDK1556I</u>	1688
<u>Message ID : SDK1557I</u>	1688
<u>Message ID : SDK1559I</u>	1689
<u>Message ID : SDK1560I</u>	1690
<u>Message ID : SDK1561I</u>	1690
<u>Message ID : SDK1562I</u>	1691
<u>Message ID : SDK1563I</u>	1692
<u>Message ID : SDK1670I</u>	1692
<u>Message ID : SDK1689I</u>	1693
<u>Message ID : SDK1738I</u>	1694
<u>Message ID : SDK1799I</u>	1694
<u>Message ID : SDK1800I</u>	1695
<u>Message ID : SDK1810I</u>	1696
<u>Message ID : SDK1825I</u>	1697
<u>Message ID : SDK1826I</u>	1698
<u>Message ID : SDK1831I</u>	1699
<u>Message ID : SDK1833I</u>	1700

Table of Contents

<u>Logger SDK: Warnings</u>	1701
<u>Message ID : SDK0290W</u>	1701
<u>Message ID : SDK0583W</u>	1701
<u>Message ID : SDK0584W</u>	1702
<u>Message ID : SDK0585W</u>	1703
<u>Message ID : SDK0597W</u>	1704
<u>Message ID : SDK0779W</u>	1704
<u>Message ID : SDK1336W</u>	1705
<u>Message ID : SDK1338W</u>	1706
<u>Message ID : SDK1368W</u>	1706
<u>Message ID : SDK1390W</u>	1707
<u>Message ID : SDK1616W</u>	1708
<u>Message ID : SDK1617W</u>	1709
<u>Message ID : SDK1669W</u>	1709
<u>Logger SIN: Errors</u>	1711
<u>Message ID : SIN0209E</u>	1711
<u>Message ID : SIN0210E</u>	1711
<u>Message ID : SIN0211E</u>	1712
<u>Message ID : SIN0212E</u>	1713
<u>Message ID : SIN0213E</u>	1713
<u>Message ID : SIN0214E</u>	1714
<u>Logger SIN: Fatal errors</u>	1716
<u>Message ID : SIN0176F</u>	1716
<u>Message ID : SIN0177F</u>	1717
<u>Message ID : SIN0178F</u>	1717

Table of Contents

Logger USR: Errors	1719
<u>Message ID : USR0156E</u>	1719
<u>Message ID : USR0157E</u>	1719
<u>Message ID : USR0158E</u>	1720
<u>Message ID : USR0159E</u>	1721
<u>Message ID : USR0160E</u>	1721
<u>Message ID : USR0161E</u>	1722
<u>Message ID : USR0162E</u>	1723
<u>Message ID : USR0163E</u>	1723
<u>Message ID : USR0164E</u>	1724
<u>Message ID : USR0165E</u>	1725
<u>Message ID : USR0166E</u>	1725
<u>Message ID : USR0168E</u>	1726
<u>Message ID : USR0169E</u>	1727
<u>Message ID : USR0170E</u>	1727
<u>Message ID : USR0219E</u>	1728
<u>Message ID : USR0266E</u>	1729
<u>Message ID : USR0270E</u>	1729
<u>Message ID : USR0298E</u>	1730
<u>Message ID : USR0308E</u>	1731
<u>Message ID : USR0309E</u>	1732
<u>Message ID : USR0310E</u>	1732
<u>Message ID : USR0311E</u>	1733
<u>Message ID : USR0315E</u>	1734
<u>Message ID : USR0316E</u>	1734
<u>Message ID : USR0318E</u>	1735
<u>Message ID : USR0319E</u>	1736

Table of Contents

Logger USR: Errors

<u>Message ID : USR0320E</u>	1736
<u>Message ID : USR0337E</u>	1737
<u>Message ID : USR0340E</u>	1738
<u>Message ID : USR0409E</u>	1738
<u>Message ID : USR0535E</u>	1739
<u>Message ID : USR0593E</u>	1740
<u>Message ID : USR0632E</u>	1740
<u>Message ID : USR1230E</u>	1741
<u>Message ID : USR1231E</u>	1742
<u>Message ID : USR1232E</u>	1742
<u>Message ID : USR1233E</u>	1743
<u>Message ID : USR1234E</u>	1744
<u>Message ID : USR1235E</u>	1744
<u>Message ID : USR1236E</u>	1745
<u>Message ID : USR1254E</u>	1746
<u>Message ID : USR1275E</u>	1746
<u>Message ID : USR1288E</u>	1747
<u>Message ID : USR1289E</u>	1748
<u>Message ID : USR1321E</u>	1748
<u>Message ID : USR1325E</u>	1749
<u>Message ID : USR1326E</u>	1750
<u>Message ID : USR1327E</u>	1750
<u>Message ID : USR1328E</u>	1751
<u>Message ID : USR1329E</u>	1752
<u>Message ID : USR1330E</u>	1752
<u>Message ID : USR1332E</u>	1753

Table of Contents

Logger USR: Errors

<u>Message ID : USR1333E</u>	1754
<u>Message ID : USR1351E</u>	1754
<u>Message ID : USR1385E</u>	1755
<u>Message ID : USR1386E</u>	1756
<u>Message ID : USR1387E</u>	1757
<u>Message ID : USR1388E</u>	1757
<u>Message ID : USR1389E</u>	1758
<u>Message ID : USR1393E</u>	1759
<u>Message ID : USR1396E</u>	1759
<u>Message ID : USR1397E</u>	1760
<u>Message ID : USR1398E</u>	1761
<u>Message ID : USR1399E</u>	1761
<u>Message ID : USR1400E</u>	1762
<u>Message ID : USR1401E</u>	1763
<u>Message ID : USR1402E</u>	1763
<u>Message ID : USR1403E</u>	1764
<u>Message ID : USR1404E</u>	1765
<u>Message ID : USR1405E</u>	1765
<u>Message ID : USR1406E</u>	1766
<u>Message ID : USR1408E</u>	1767
<u>Message ID : USR1411E</u>	1767
<u>Message ID : USR1412E</u>	1768
<u>Message ID : USR1413E</u>	1769
<u>Message ID : USR1414E</u>	1769
<u>Message ID : USR1415E</u>	1770
<u>Message ID : USR1416E</u>	1771

Table of Contents

Logger USR: Errors

<u>Message ID : USR1417E</u>	1771
<u>Message ID : USR1418E</u>	1772
<u>Message ID : USR1419E</u>	1773
<u>Message ID : USR1420E</u>	1773
<u>Message ID : USR1421E</u>	1774
<u>Message ID : USR1422E</u>	1775
<u>Message ID : USR1424E</u>	1775
<u>Message ID : USR1425E</u>	1776
<u>Message ID : USR1426E</u>	1777
<u>Message ID : USR1427E</u>	1777
<u>Message ID : USR1428E</u>	1778
<u>Message ID : USR1429E</u>	1779
<u>Message ID : USR1430E</u>	1779
<u>Message ID : USR1431E</u>	1780
<u>Message ID : USR1432E</u>	1781
<u>Message ID : USR1433E</u>	1781
<u>Message ID : USR1622E</u>	1782
<u>Message ID : USR1650E</u>	1783
<u>Message ID : USR1671E</u>	1783
<u>Message ID : USR1672E</u>	1784
<u>Message ID : USR1673E</u>	1785
<u>Message ID : USR1707E</u>	1785
<u>Message ID : USR1708E</u>	1786
<u>Message ID : USR1710E</u>	1787
<u>Message ID : USR1711E</u>	1787
<u>Message ID : USR1712E</u>	1788

Table of Contents

Logger USR: Errors

<u>Message ID : USR1713E</u>	1789
<u>Message ID : USR1714E</u>	1790
<u>Message ID : USR1715E</u>	1790
<u>Message ID : USR1716E</u>	1791
<u>Message ID : USR1717E</u>	1792
<u>Message ID : USR1719E</u>	1792
<u>Message ID : USR1721E</u>	1793
<u>Message ID : USR1722E</u>	1794
<u>Message ID : USR1729E</u>	1794
<u>Message ID : USR1730E</u>	1795
<u>Message ID : USR1836E</u>	1796
<u>Message ID : USR1838E</u>	1796
<u>Message ID : USR1839E</u>	1797
<u>Message ID : USR1840E</u>	1798
<u>Message ID : USR1843E</u>	1798

Logger USR: Information.....**1800**

<u>Message ID : USR0631I</u>	1800
<u>Message ID : USR1277I</u>	1801
<u>Message ID : USR1278I</u>	1801
<u>Message ID : USR1330I</u>	1802
<u>Message ID : USR1331I</u>	1803

Logger USR: Warnings.....**1805**

<u>Message ID : USR1615W</u>	1805
<u>Message ID : USR1709W</u>	1806

Table of Contents

<u>Logger VAD: Errors</u>	1807
<u>Message ID : VAD4642E</u>	1807
<u>Logger VAD: Information</u>	1809
<u>Message ID : VAD4641I</u>	1809
<u>Logger VAD: Warnings</u>	1811
<u>Message ID : VAD4643W</u>	1811
<u>Logger VMD: Errors</u>	1812
<u>Message ID : VMD3203E</u>	1812
<u>Message ID : VMD3204E</u>	1813
<u>Message ID : VMD3503E</u>	1813
<u>Message ID : VMD3507E</u>	1814
<u>Message ID : VMD3509E</u>	1815
<u>Message ID : VMD3510E</u>	1816
<u>Message ID : VMD3514E</u>	1816
<u>Message ID : VMD3517E</u>	1817
<u>Message ID : VMD3520E</u>	1818
<u>Message ID : VMD3525E</u>	1818
<u>Message ID : VMD3527E</u>	1819
<u>Message ID : VMD3533E</u>	1820
<u>Message ID : VMD3544E</u>	1820
<u>Message ID : VMD3546E</u>	1821
<u>Message ID : VMD3550E</u>	1822
<u>Message ID : VMD3559E</u>	1823
<u>Message ID : VMD3563E</u>	1823

Table of Contents

Logger VMD: Errors

<u>Message ID : VMD3572E</u>	1824
<u>Message ID : VMD3578E</u>	1825
<u>Message ID : VMD3581E</u>	1826
<u>Message ID : VMD3596E</u>	1826
<u>Message ID : VMD3597E</u>	1827
<u>Message ID : VMD3605E</u>	1828
<u>Message ID : VMD3607E</u>	1829
<u>Message ID : VMD3611E</u>	1829
<u>Message ID : VMD3612E</u>	1830
<u>Message ID : VMD3616E</u>	1831
<u>Message ID : VMD3617E</u>	1831
<u>Message ID : VMD3628E</u>	1832
<u>Message ID : VMD3629E</u>	1833
<u>Message ID : VMD3633E</u>	1834
<u>Message ID : VMD3644E</u>	1834
<u>Message ID : VMD3645E</u>	1835
<u>Message ID : VMD3651E</u>	1836
<u>Message ID : VMD3655E</u>	1837
<u>Message ID : VMD3665E</u>	1837
<u>Message ID : VMD3666E</u>	1838
<u>Message ID : VMD3667E</u>	1839
<u>Message ID : VMD3674E</u>	1839
<u>Message ID : VMD3676E</u>	1840
<u>Message ID : VMD3681E</u>	1841
<u>Message ID : VMD3683E</u>	1841
<u>Message ID : VMD3685E</u>	1842

Table of Contents

Logger VMD: Errors

<u>Message ID : VMD3686E</u>	1843
<u>Message ID : VMD3689E</u>	1843
<u>Message ID : VMD3697E</u>	1844
<u>Message ID : VMD3700E</u>	1845
<u>Message ID : VMD3702E</u>	1846
<u>Message ID : VMD3707E</u>	1846
<u>Message ID : VMD3713E</u>	1847
<u>Message ID : VMD3718E</u>	1848
<u>Message ID : VMD3723E</u>	1848
<u>Message ID : VMD3724E</u>	1849
<u>Message ID : VMD3726E</u>	1850
<u>Message ID : VMD3730E</u>	1850
<u>Message ID : VMD3734E</u>	1851
<u>Message ID : VMD3736E</u>	1852
<u>Message ID : VMD3747E</u>	1852
<u>Message ID : VMD3748E</u>	1853
<u>Message ID : VMD3750E</u>	1854
<u>Message ID : VMD3758E</u>	1854
<u>Message ID : VMD3759E</u>	1855
<u>Message ID : VMD3760E</u>	1856
<u>Message ID : VMD3779E</u>	1856
<u>Message ID : VMD3780E</u>	1857
<u>Message ID : VMD3782E</u>	1858
<u>Message ID : VMD3784E</u>	1859
<u>Message ID : VMD3786E</u>	1860
<u>Message ID : VMD3787E</u>	1861

Table of Contents

Logger VMD: Errors

<u>Message ID : VMD3788E</u>	1862
<u>Message ID : VMD3789E</u>	1862
<u>Message ID : VMD3790E</u>	1863
<u>Message ID : VMD3792E</u>	1864
<u>Message ID : VMD3795E</u>	1865
<u>Message ID : VMD3796E</u>	1866
<u>Message ID : VMD3799E</u>	1867
<u>Message ID : VMD3801E</u>	1867
<u>Message ID : VMD3802E</u>	1868
<u>Message ID : VMD3807E</u>	1869
<u>Message ID : VMD3809E</u>	1870
<u>Message ID : VMD3811E</u>	1871
<u>Message ID : VMD3812E</u>	1872
<u>Message ID : VMD3816E</u>	1873
<u>Message ID : VMD3819E</u>	1874
<u>Message ID : VMD3822E</u>	1874
<u>Message ID : VMD3828E</u>	1875
<u>Message ID : VMD3830E</u>	1876
<u>Message ID : VMD3831E</u>	1877
<u>Message ID : VMD3833E</u>	1878
<u>Message ID : VMD3834E</u>	1879
<u>Message ID : VMD3835E</u>	1880
<u>Message ID : VMD3837E</u>	1881
<u>Message ID : VMD3838E</u>	1882
<u>Message ID : VMD3840E</u>	1883
<u>Message ID : VMD3843E</u>	1883

Table of Contents

Logger VMD: Errors

<u>Message ID : VMD3844E</u>	1884
<u>Message ID : VMD3845E</u>	1885
<u>Message ID : VMD3846E</u>	1886
<u>Message ID : VMD3848E</u>	1887
<u>Message ID : VMD3849E</u>	1888
<u>Message ID : VMD3855E</u>	1889
<u>Message ID : VMD3858E</u>	1890
<u>Message ID : VMD3864E</u>	1891
<u>Message ID : VMD3865E</u>	1892
<u>Message ID : VMD3866E</u>	1893
<u>Message ID : VMD3867E</u>	1894
<u>Message ID : VMD3872E</u>	1894
<u>Message ID : VMD3873E</u>	1895
<u>Message ID : VMD3874E</u>	1896
<u>Message ID : VMD3875E</u>	1897
<u>Message ID : VMD3876E</u>	1898
<u>Message ID : VMD3877E</u>	1899
<u>Message ID : VMD3878E</u>	1899
<u>Message ID : VMD3879E</u>	1900
<u>Message ID : VMD3888E</u>	1901
<u>Message ID : VMD3890E</u>	1902
<u>Message ID : VMD3891E</u>	1903
<u>Message ID : VMD3892E</u>	1904
<u>Message ID : VMD3901E</u>	1904
<u>Message ID : VMD3903E</u>	1905
<u>Message ID : VMD3905E</u>	1906

Table of Contents

Logger VMD: Errors

<u>Message ID : VMD3907E</u>	1907
<u>Message ID : VMD3909E</u>	1908
<u>Message ID : VMD3911E</u>	1909
<u>Message ID : VMD3913E</u>	1910
<u>Message ID : VMD3915E</u>	1911
<u>Message ID : VMD3916E</u>	1912
<u>Message ID : VMD3917E</u>	1913
<u>Message ID : VMD3918E</u>	1913
<u>Message ID : VMD3922E</u>	1914
<u>Message ID : VMD3923E</u>	1915
<u>Message ID : VMD4245E</u>	1916
<u>Message ID : VMD4594E</u>	1917
<u>Message ID : VMD4606E</u>	1918
<u>Message ID : VMD4607E</u>	1919
<u>Message ID : VMD4608E</u>	1920
<u>Message ID : VMD4609E</u>	1921
<u>Message ID : VMD4610E</u>	1921
<u>Message ID : VMD4612E</u>	1922
<u>Message ID : VMD4617E</u>	1923

Logger VMD: Fatal errors.....1925

<u>Message ID : VMD3767F</u>	1925
<u>Message ID : VMD3768F</u>	1926
<u>Message ID : VMD3769F</u>	1927
<u>Message ID : VMD3770F</u>	1927
<u>Message ID : VMD3771F</u>	1929

Table of Contents

Logger VMD: Fatal errors

<u>Message ID : VMD3772F</u>	1930
<u>Message ID : VMD3797F</u>	1930
<u>Message ID : VMD3894F</u>	1931
<u>Message ID : VMD4595F</u>	1932
<u>Message ID : VMD4616F</u>	1933

Logger VMD: Information.....1935

<u>Message ID : VMD3201I</u>	1935
<u>Message ID : VMD3202I</u>	1936
<u>Message ID : VMD3548I</u>	1936
<u>Message ID : VMD3558I</u>	1937
<u>Message ID : VMD3626I</u>	1938
<u>Message ID : VMD3640I</u>	1939
<u>Message ID : VMD3663I</u>	1940
<u>Message ID : VMD3773I</u>	1941
<u>Message ID : VMD3778I</u>	1942
<u>Message ID : VMD3781I</u>	1942
<u>Message ID : VMD3785I</u>	1943
<u>Message ID : VMD3794I</u>	1944
<u>Message ID : VMD3798I</u>	1945
<u>Message ID : VMD3800I</u>	1946
<u>Message ID : VMD3803I</u>	1947
<u>Message ID : VMD3804I</u>	1947
<u>Message ID : VMD3814I</u>	1948
<u>Message ID : VMD3815I</u>	1949
<u>Message ID : VMD3817I</u>	1950

Table of Contents

Logger VMD: Information

<u>Message ID : VMD3818I</u>	1951
<u>Message ID : VMD3820I</u>	1952
<u>Message ID : VMD3821I</u>	1953
<u>Message ID : VMD3823I</u>	1954
<u>Message ID : VMD3825I</u>	1955
<u>Message ID : VMD3827I</u>	1956
<u>Message ID : VMD3829I</u>	1957
<u>Message ID : VMD3832I</u>	1957
<u>Message ID : VMD3836I</u>	1958
<u>Message ID : VMD3839I</u>	1959
<u>Message ID : VMD3841I</u>	1960
<u>Message ID : VMD3842I</u>	1961
<u>Message ID : VMD3847I</u>	1962
<u>Message ID : VMD3851I</u>	1963
<u>Message ID : VMD3852I</u>	1964
<u>Message ID : VMD3853I</u>	1965
<u>Message ID : VMD3854I</u>	1966
<u>Message ID : VMD3856I</u>	1967
<u>Message ID : VMD3857I</u>	1967
<u>Message ID : VMD3859I</u>	1968
<u>Message ID : VMD3861I</u>	1969
<u>Message ID : VMD3862I</u>	1970
<u>Message ID : VMD3863I</u>	1971
<u>Message ID : VMD3868I</u>	1972
<u>Message ID : VMD3870I</u>	1973
<u>Message ID : VMD3880I</u>	1974

Table of Contents

Logger VMD: Information

<u>Message ID : VMD3881I</u>	1975
<u>Message ID : VMD3883I</u>	1975
<u>Message ID : VMD3885I</u>	1976
<u>Message ID : VMD3886I</u>	1978
<u>Message ID : VMD3893I</u>	1979
<u>Message ID : VMD3895I</u>	1980
<u>Message ID : VMD3896I</u>	1980
<u>Message ID : VMD3897I</u>	1981
<u>Message ID : VMD3898I</u>	1982
<u>Message ID : VMD3900I</u>	1983
<u>Message ID : VMD3902I</u>	1984
<u>Message ID : VMD3904I</u>	1985
<u>Message ID : VMD3906I</u>	1986
<u>Message ID : VMD3908I</u>	1987
<u>Message ID : VMD3910I</u>	1988
<u>Message ID : VMD3912I</u>	1989
<u>Message ID : VMD3914I</u>	1990
<u>Message ID : VMD3919I</u>	1991
<u>Message ID : VMD4246I</u>	1992
<u>Message ID : VMD4611I</u>	1993
<u>Message ID : VMD4619I</u>	1993
<u>Message ID : VMD4620I</u>	1994

Logger VMD: Warnings.....1996

<u>Message ID : VMD3714W</u>	1996
<u>Message ID : VMD3805W</u>	1996

Table of Contents

Logger VMD: Warnings

<u>Message ID : VMD3806W</u>	1997
<u>Message ID : VMD3813W</u>	1998
<u>Message ID : VMD3824W</u>	1999
<u>Message ID : VMD3826W</u>	2000
<u>Message ID : VMD3850W</u>	2001
<u>Message ID : VMD3860W</u>	2002
<u>Message ID : VMD3869W</u>	2003
<u>Message ID : VMD3871W</u>	2003
<u>Message ID : VMD3882W</u>	2004
<u>Message ID : VMD3887W</u>	2005
<u>Message ID : VMD3889W</u>	2006
<u>Message ID : VMD3899W</u>	2007
<u>Message ID : VMD3920W</u>	2008
<u>Message ID : VMD3921W</u>	2009
<u>Message ID : VMD3924W</u>	2010
<u>Message ID : VMD3925W</u>	2011
<u>Message ID : VMD4618W</u>	2011
<u>Message ID : VMD4621W</u>	2012
<u>Message ID : VMD4622W</u>	2013
<u>Message ID : VMD4623W</u>	2015
<u>Message ID : VMD4624W</u>	2016
<u>Message ID : VMD4625W</u>	2017
<u>Message ID : VMD4636W</u>	2018
<u>Message ID : VMD4639W</u>	2019
<u>Message ID : VMD4640W</u>	2020

Table of Contents

Logger XFM: Errors	2022
<u>Message ID : XFM4501E</u>	2022
<u>Message ID : XFM4502E</u>	2023
<u>Message ID : XFM4504E</u>	2023
<u>Message ID : XFM4535E</u>	2024
<u>Message ID : XFM4568E</u>	2025
<u>Message ID : XFM4589E</u>	2026
<u>Message ID : XFM4590E</u>	2027
<u>Message ID : XFM4591E</u>	2028
Logger XFM: Fatal errors	2029
<u>Message ID : XFM4508F</u>	2029
<u>Message ID : XFM4509F</u>	2029
<u>Message ID : XFM4518F</u>	2030
<u>Message ID : XFM4519F</u>	2031
<u>Message ID : XFM4525F</u>	2032
<u>Message ID : XFM4532F</u>	2033
<u>Message ID : XFM4536F</u>	2034
<u>Message ID : XFM4539F</u>	2035
<u>Message ID : XFM4540F</u>	2035
<u>Message ID : XFM4541F</u>	2036
<u>Message ID : XFM4544F</u>	2037
<u>Message ID : XFM4546F</u>	2038
<u>Message ID : XFM4561F</u>	2039
<u>Message ID : XFM4565F</u>	2040

Table of Contents

<u>Logger XFM: Information</u>	2041
<u>Message ID : XFM4507I</u>	2041
<u>Message ID : XFM4517I</u>	2041
<u>Message ID : XFM4522I</u>	2042
<u>Message ID : XFM4526I</u>	2043
<u>Message ID : XFM4549I</u>	2044
<u>Message ID : XFM4557I</u>	2045
<u>Message ID : XFM4559I</u>	2046
<u>Logger XFM: Warnings</u>	2047
<u>Message ID : XFM4550W</u>	2047

Logger CA0: Errors

Message ID : CA00642E

Severity

Error

Long Form

Can not create CA.

Short Form

can not create CA

Parameters

No parameters are provided for this message type

Description

None

Message ID : CA00643E

Severity

Error

Long Form

Can not update CA.

Short Form

No short form is provided for this message type

Description

None

Message ID : CA00644E

Severity

Error

Long Form

Can not delete CA.

Message ID : CA00643E

Short Form

No short form is provided for this message type

Description

None

Message ID : CA00645E

Severity

Error

Long Form

Can not get CA.

Short Form

No short form is provided for this message type

Description

None

Message ID : CA00644E

Logger CFG: Errors

Message ID : CFG0026E

Severity

Error

Long Form

Internal error. Refer to cgss.log for details.

Short Form

No short form is provided for this message type

Description

None

Message ID : CFG0027E

Severity

Error

Long Form

Unable to obtain list of configuration names.

Short Form

No short form is provided for this message type

Description

None

Message ID : CFG0028E

Severity

Error

Long Form

Unable to update configuration information.

Short Form

No short form is provided for this message type

Message ID : CFG0027E

Description

None

Message ID : CFG0029E

Severity

Error

Long Form

Unable to obtain the value for key = {0}.

Short Form

No short form is provided for this message type

Description

None

Message ID : CFG0030E

Severity

Error

Message ID : CFG0028E

Long Form

Unable to create loggers.

Short Form

No short form is provided for this message type

Description

None

Message ID : CFG0031E

Severity

Error

Long Form

Unable to update loggers.

Short Form

No short form is provided for this message type

Message ID : CFG0030E

Description

None

Message ID : CFG0032E

Severity

Error

Long Form

Unable to obtain list of default loggers.

Short Form

No short form is provided for this message type

Description

None

Message ID : CFG0033E

Severity

Error

Message ID : CFG0031E

Long Form

Unable to delete loggers for host with id = {0}.

Short Form

No short form is provided for this message type

Description

None

Message ID : CFG0034E

Severity

Error

Long Form

Unable to obtain loggers for host with id = {0}.

Short Form

No short form is provided for this message type

Message ID : CFG0033E

Description

None

Message ID : CFG0264E

Severity

Error

Long Form

CGSS Server Name "{0}" is unknown to the Security Server.

Short Form

No short form is provided for this message type

Description

None

Message ID : CFG0306E

Severity

Error

Message ID : CFG0034E

Long Form

Internal error. No password policy found, there needs to be one password policy defined. Please contact support.

Short Form

No short form is provided for this message type

Description

None

Message ID : CFG0333E

Severity

Error

Long Form

Security Server brand must be either vor or eet.

Short Form

No short form is provided for this message type

Message ID : CFG0306E

Description

None

Message ID : CFG0334E

Severity

Error

Long Form

Security Server role must be either primary or failover.

Short Form

No short form is provided for this message type

Description

None

Message ID : CFG0335E

Severity

Error

Message ID : CFG0333E

Long Form

Provide true or false for the property {0}.

Short Form

No short form is provided for this message type

Description

None

Message ID : CFG0336E

Severity

Error

Long Form

Security Server version must be defined.

Short Form

No short form is provided for this message type

Message ID : CFG0335E

Description

None

Message ID : CFG0339E

Severity

Error

Long Form

Security Server build number must be defined.

Short Form

No short form is provided for this message type

Description

None

Message ID : CFG0341E

Severity

Error

Message ID : CFG0336E

Long Form

Platform is not supported.

Short Form

No short form is provided for this message type

Description

None

Message ID : CFG0520E

Severity

Error

Long Form

The Security Server was unable to find a partition available for software installation. The software cannot be installed. Please un-install old software and try again.

Short Form

No short form is provided for this message type

Message ID : CFG0341E

Description

None

Message ID : CFG0521E

Severity

Error

Long Form

The Security Server was unable to to uncompress the backup file. The software upgrade cannot continue. Please check if you have enough disk space.

Short Form

No short form is provided for this message type

Description

None

Message ID : CFG0522E

Severity

Error

Long Form

The Security Server was unable to verify the signature. The software upgrade cannot continue. Please check if the uploaded file is valid.

Short Form

No short form is provided for this message type

Description

None

Message ID : CFG0523E

Severity

Error

Long Form

The Security Server was unable to retrieve the public key needed to verify the signature for the software to be installed. The software upgrade cannot continue. Please check if the uploaded file is valid.

Message ID : CFG0522E

Short Form

No short form is provided for this message type

Description

None

Message ID : CFG0524E

Severity

Error

Long Form

The Security Server was unable to verify the signature. The file is not valid. The software upgrade cannot continue. Please make sure that the file you are downloading for installation is a valid file.

Short Form

No short form is provided for this message type

Description

None

Message ID : CFG0523E

Message ID : CFG0527E

Severity

Error

Long Form

Upgrade target not supported. Retry with higher version/build.

Short Form

No short form is provided for this message type

Description

None

Message ID : CFG0528E

Severity

Error

Long Form

The Security Server is unable to find the current version of the software. Please check the logs.

Message ID : CFG0527E

Short Form

No short form is provided for this message type

Description

None

Message ID : CFG0529E

Severity

Error

Long Form

The Security Server is unable to install software. The directory is not empty. Please ensure that the directory is empty and try the install again.

Short Form

No short form is provided for this message type

Description

None

Message ID : CFG0528E

Message ID : CFG0530E

Severity

Error

Long Form

The Security Server failed to synchronize the failover server {0} replication.

Short Form

No short form is provided for this message type

Description

None

Message ID : CFG0531E

Severity

Error

Long Form

The Security Server failed to configure the failover server {0} replication.

Message ID : CFG0530E

Short Form

No short form is provided for this message type

Description

None

Message ID : CFG0532E

Severity

Error

Long Form

The Security Server failed to clean up the failover server {0} replication.

Short Form

No short form is provided for this message type

Description

None

Message ID : CFG0531E

Message ID : CFG0636E

Severity

Error

Long Form

Operation failed. The Security Server is busy, please retry later.

Short Form

No short form is provided for this message type

Description

None

Message ID : CFG1334E

Severity

Error

Long Form

DSM Server Name "{0}" unknown; if there has been a restore, either do a "gencert" or change hostname.

Message ID : CFG0636E

Short Form

No short form is provided for this message type

Description

None

Message ID : CFG1335E

Severity

Error

Long Form

{0}

Short Form

No short form is provided for this message type

Description

None

Message ID : CFG1334E

Message ID : CFG1352E

Severity

Error

Long Form

Operation not allowed in Common Criteria mode.

Short Form

No short form is provided for this message type

Description

None

Message ID : CFG1367E

Severity

Error

Long Form

Login banner can not be empty.

Message ID : CFG1352E

Short Form

No short form is provided for this message type

Description

None

Message ID : CFG1368E

Severity

Error

Long Form

User "{0}" failed to upgrade system. Reason:{1}

Short Form

Failed to upgrade system

Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
showStr	reason	Text	Code specifying reason for allowing access, if any

Message ID : CFG1367E

Label	CEF Label	Type	Usage

Description

None

Message ID : CFG1400E

Severity

Error

Long Form

Unable to delete docker loggers for host {0}.

Short Form

No short form is provided for this message type

Description

None

Message ID : CFG1368E

Message ID : CFG1514E

Severity

Error

Long Form

Upgrade information not available

Short Form

No short form is provided for this message type

Description

None

Message ID : CFG1515E

Severity

Error

Long Form

System upgrade failed. Please see log files.

Message ID : CFG1514E

Short Form

No short form is provided for this message type

Description

None

Message ID : CFG1517E

Severity

Error

Long Form

There was an error in getting the system upgrade status from the upgrade log file

Short Form

No short form is provided for this message type

Description

None

Message ID : CFG1515E

Message ID : CFG1705E

Severity

Error

Long Form

Unable to update {0} general configuration for domain.

Short Form

No short form is provided for this message type

Description

None

Message ID : CFG1727E

Severity

Error

Long Form

Log message type is not found.

Message ID : CFG1705E

Short Form

No short form is provided for this message type

Description

None

Message ID : CFG1734E

Severity

Error

Long Form

HSM key not found. Required HSM partition may be inaccessible or missing registration.

Short Form

No short form is provided for this message type

Description

None

Message ID : CFG1727E

Message ID : CFG1735E

Severity

Error

Long Form

HSM failed.

Short Form

No short form is provided for this message type

Description

None

Message ID : CFG1775E

Severity

Error

Long Form

Field {0} must be required for setting {1}.

Message ID : CFG1735E

Short Form

No short form is provided for this message type

Description

None

Message ID : CFG1776E

Severity

Error

Long Form

Field {0} must be enabled for setting {1}.

Short Form

No short form is provided for this message type

Description

None

Message ID : CFG1775E

Message ID : CFG1777E

Severity

Error

Long Form

DEBUG level not supported for {0} log destination.

Short Form

No short form is provided for this message type

Description

None

Message ID : CFG1778E

Severity

Error

Long Form

Host does not support {0} so it cannot be enabled or disabled.

Message ID : CFG1777E

Short Form

No short form is provided for this message type

Description

None

Message ID : CFG1827E

Severity

Error

Long Form

Invalid TLS info for secure syslog server {0}

Short Form

No short form is provided for this message type

Description

None

Message ID : CFG1778E

Logger CFG: Fatal errors

Message ID : CFG1733F

Severity

Fatal error

Long Form

Lost connection to network HSM.

Short Form

No short form is provided for this message type

Description

None

Message ID : CFG1842F

Severity

Fatal error

Long Form

Unable to recover HSM session. Restarting service!

Short Form

No short form is provided for this message type

Description

None

Logger CFG: Information

Message ID : CFG0633I

Severity

Information

Long Form

User "{0}" configured replication for failover server {1}.

Short Form

failover replication configured

Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
shost	shost	Text	Source host name

Description

None

Message ID : CFG0634I

Severity

Information

Long Form

User "{0}" cleaned up replication for failover server {1}.

Short Form

failover replication cleanup

Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
shost	shost	Text	Source host name

Description

None

Message ID : CFG1516I

Severity

Information

Long Form

SUCCESS: System upgrade is complete. Please log in and make a system backup.

Short Form

No short form is provided for this message type

Description

None

Message ID : CFG1736I

Severity

Information

Long Form

"{0}" generated a migration backup.

Message ID : CFG1516I

Short Form

No short form is provided for this message type

Description

None

Message ID : CFG1841I

Severity

Information

Long Form

SUCCESS: User {0} uploaded {1} to DSM server.

Short Form

No short form is provided for this message type

Description

None

Message ID : CFG1736I

Logger CFG: Warnings

Message ID : CFG1297W

Severity

Warning

Long Form

Skipping KMIP operation. KMIP feature is enabled in the license but KMIP is not set up.

Short Form

The KMIP feature is enabled in the license but KMIP is not set up

Parameters

No parameters are provided for this message type

Description

None

Logger CGA: Errors

Message ID : CGA2614E

Severity

Error

Long Form

Syntax error: Domain name '*' is reserved

Short Form

No short form is provided for this message type

Description

None

Message ID : CGA2617E

Severity

Error

Long Form

[[0]] Set [[1]] used but not defined

Short Form

No short form is provided for this message type

Description

None

Message ID : CGA2618E

Severity

Error

Long Form

Failed to import password object

Short Form

No short form is provided for this message type

Message ID : CGA2617E

Description

None

Message ID : CGA2619E

Severity

Error

Long Form

Policy [{0}]: Invalid policy

Short Form

No short form is provided for this message type

Description

None

Message ID : CGA2620E

Severity

Error

Message ID : CGA2618E

Long Form

Policy [{0}]: Invalid policy length

Short Form

No short form is provided for this message type

Description

None

Message ID : CGA2621E

Severity

Error

Long Form

Policy [{0}]: Policy import failed

Short Form

No short form is provided for this message type

Message ID : CGA2620E

Description

None

Message ID : CGA2624E

Severity

Error

Long Form

Policy [{0}]: Failed to import Name Identifier

Short Form

Name import failed

Parameters

Label	CEF Label	Type	Usage
pol	cs1	Text	Policy name

Description

None

Message ID : CGA2621E

Message ID : CGA2625E

Severity

Error

Long Form

Failed to import keys

Short Form

Keys import failed

Parameters

No parameters are provided for this message type

Description

None

Message ID : CGA2626E

Severity

Error

Message ID : CGA2625E

Long Form

Policy [{0}]: Invalid root path

Short Form

Invalid rootpath

Parameters

Label	CEF Label	Type	Usage
pol	cs1	Text	Policy name

Description

None

Message ID : CGA2627E

Severity

Error

Long Form

Policy [{0}]: Failed to import root path

Message ID : CGA2626E

Short Form

Import rootpath fail

Parameters

Label	CEF Label	Type	Usage
pol	cs1	Text	Policy name

Description

None

Message ID : CGA2628E

Severity

Error

Long Form

Policy [{0}]: [{1}] Set [{2}] not defined

Short Form

Undefined policy type/set

Message ID : CGA2627E

Parameters

Label	CEF Label	Type	Usage
pol	cs1	Text	Policy name
oType	vds_oType	Text	Object type in policy rule
oName	vds_oName	Text	Object name in policy rule

Description

None

Message ID : CGA2629E

Severity

Error

Long Form

Policy [{}]: Key rule not yet built

Short Form

Invalid key rule

Message ID : CGA2628E

Parameters

Label	CEF Label	Type	Usage
pol	cs1	Text	Policy name

Description

None

Message ID : CGA2634E

Severity

Error

Long Form

Policy [{0}]: Invalid Rule

Short Form

Invalid rules object

Parameters

Label	CEF Label	Type	Usage
pol	cs1	Text	Policy name

Message ID : CGA2629E

Label	CEF Label	Type	Usage

Description

None

Message ID : CGA2635E

Severity

Error

Long Form

Policy [{0}]: Invalid syntax for key effect [{1}]

Short Form

Invalid key effect

Parameters

Label	CEF Label	Type	Usage
pol	cs1	Text	Policy name
act	act	Text	Action being requested or performed

Message ID : CGA2634E

Description

None

Message ID : CGA2636E

Severity

Error

Long Form

Policy [{0}]: Invalid name and/or access

Short Form

Invalid name/access

Parameters

Label	CEF Label	Type	Usage
pol	cs1	Text	Policy name

Description

None

Message ID : CGA2635E

Message ID : CGA2637E

Severity

Error

Long Form

Policy [{0}]: Invalid rule syntax: Effect not defined

Short Form

Undefined effect

Parameters

Label	CEF Label	Type	Usage
pol	cs1	Text	Policy name

Description

None

Message ID : CGA2638E

Severity

Error

Long Form

Policy [{0}]: Invalid rule syntax: Action [{1}] not defined

Short Form

Undefined action

Parameters

Label	CEF Label	Type	Usage
pol	cs1	Text	Policy name
act	act	Text	Action being requested or performed

Description

None

Message ID : CGA2639E

Message ID : CGA2638E

Severity

Error

Long Form

Policy [{0}]: Invalid rule syntax: GoTo label [{1}] not defined

Short Form

Undefined label

Parameters

Label	CEF Label	Type	Usage
pol	cs1	Text	Policy name
label	vds_label	Text	Label in rule sequence

Description

None

Message ID : CGA2645E

Message ID : CGA2639E

Severity

Error

Long Form

Policy [{0}]: Recursive GoTo detected at rule number [{1}]

Short Form

Recursive goto

Parameters

Label	CEF Label	Type	Usage
pol	cs1	Text	Policy name
ruleNo	vds_ruleNo	Numeric	Index into policy rule set

Description

None

Message ID : CGA2648E

Severity

Error

Long Form

Policy [{0}]: Invalid GoTo - Missing destination label

Short Form

Invalid goto

Parameters

Label	CEF Label	Type	Usage
pol	cs1	Text	Policy name

Description

None

Message ID : CGA2649E

Severity

Error

Message ID : CGA2648E

Long Form

Policy [{0}]: Invalid effect syntax [{1}]

Short Form

Invalid syntax

Parameters

Label	CEF Label	Type	Usage
pol	cs1	Text	Policy name
act	act	Text	Action being requested or performed

Description

None

Message ID : CGA2650E

Severity

Error

Message ID : CGA2649E

Long Form

Policy [{0}]: Invalid action syntax [{1}]

Short Form

Invalid action

Parameters

Label	CEF Label	Type	Usage
pol	cs1	Text	Policy name
act	act	Text	Action being requested or performed

Description

None

Message ID : CGA2651E

Severity

Error

Message ID : CGA2650E

Long Form

No policy defined for [{}0] set [{}1]

Short Form

Undefined policy set

Parameters

Label	CEF Label	Type	Usage
oType	vds_oType	Text	Object type in policy rule
oName	vds_oName	Text	Object name in policy rule

Description

None

Message ID : CGA2652E

Severity

Error

Message ID : CGA2651E

Long Form

Policy [{0}]: old and new key rule numbers do not match [old {1}, new {2}]

Short Form

Mismatched rule numbers

Parameters

Label	CEF Label	Type	Usage
pol	cs1	Text	Policy name
ruleNo	vds_ruleNo	Numeric	Index into policy rule set
altRuleNo	vds_altRuleNo	Numeric	Alternate rule number

Description

None

Message ID : CGA2653E

Severity

Error

Message ID : CGA2652E

Long Form

Policy [{0}]: old and new key names do not match [key rule {1}, old {2}, new {3}]

Short Form

Mismatched key names

Parameters

Label	CEF Label	Type	Usage
pol	cs1	Text	Policy name
ruleNo	vds_ruleNo	Numeric	Index into policy rule set
key	cs3	Text	Name of key or key pair
altKey	vds_altKey	Text	Name of alternate key for multi-key operations

Description

None

Message ID : CGA2654E

Severity

Error

Message ID : CGA2653E

Long Form

Policy [{0}]: old and new key resources do not match [key rule {1}]

Short Form

Mismatched key resource

Parameters

Label	CEF Label	Type	Usage
pol	cs1	Text	Policy name
ruleNo	vds_ruleNo	Numeric	Index into policy rule set

Description

None

Message ID : CGA2655E

Severity

Error

Message ID : CGA2654E

Long Form

Failed to import key [{0}]

Short Form

Key import failed

Parameters

Label	CEF Label	Type	Usage
key	cs3	Text	Name of key or key pair

Description

None

Message ID : CGA2656E

Severity

Error

Long Form

Failed to find encryption key [%lld]

Message ID : CGA2655E

Short Form

Encryption key not found

Parameters

No parameters are provided for this message type

Description

None

Message ID : CGA2657E

Severity

Error

Long Form

Failed to validate policy on [{0}], rekey in progress

Short Form

Policy failure, rekey in progress

Message ID : CGA2656E

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : CGA2658E

Severity

Error

Long Form

Failed to validate policy on [{0}]

Short Form

Policy validation failure

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Message ID : CGA2657E

Label	CEF Label	Type	Usage

Description

None

Message ID : CGA2659E

Severity

Error

Long Form

Unsupported key type in policy on [{0}]

Short Form

Unsupported key type in policy

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Message ID : CGA2658E

Description

None

Message ID : CGA3003E

Severity

Error

Long Form

EVENT: {0}

Short Form

Event

Parameters

Label	CEF Label	Type	Usage
showStr	reason	Text	Code specifying reason for allowing access, if any

Description

None

Message ID : CGA2659E

Message ID : CGA3004E

Severity

Error

Long Form

An invalid host password was entered

Short Form

Invalid host password

Parameters

No parameters are provided for this message type

Description

None

Message ID : CGA3007E

Severity

Error

Message ID : CGA3004E

Long Form

NOTUSED

Short Form

No short form is provided for this message type

Description

None

Message ID : CGA3008E

Severity

Error

Long Form

Pid [{}0] has not been initialized properly in [{}1]

Short Form

Bad caller

Message ID : CGA3007E

Parameters

Label	CEF Label	Type	Usage
pid	dvcpid	Numeric	Numeric process ID
func	vds_func	Text	A function name

Description

Internal error; try start/stop of agent or reinstallation of agent.

Message ID : CGA3009E

Severity

Error

Long Form

NOTUSED

Short Form

No short form is provided for this message type

Message ID : CGA3008E

Description

An internal error occurred. Please contact Vormetric Support.

Message ID : CGA3010E

Severity

Error

Long Form

Failed to write to file [{0}] in [{1}]

Short Form

Write fail

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file
func	vds_func	Text	A function name

Description

None

Message ID : CGA3011E

Severity

Error

Long Form

Failed to read file [{0}] in [{1}]

Short Form

Read fail

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file
func	vds_func	Text	A function name

Description

None

Message ID : CGA3012E

Severity

Error

Long Form

NOTUSED

Short Form

No short form is provided for this message type

Description

None

Message ID : CGA3013E

Severity

Error

Message ID : CGA3011E

Long Form

NOTUSED

Short Form

No short form is provided for this message type

Description

None

Message ID : CGA3014E

Severity

Error

Long Form

NOTUSED

Short Form

No short form is provided for this message type

Message ID : CGA3013E

Description

None

Message ID : CGA3015E

Severity

Error

Long Form

Bad version [{0}] in configuration

Short Form

Bad config version

Parameters

Label	CEF Label	Type	Usage
verno	vds_verno	Numeric	A version number

Description

None

Message ID : CGA3014E

Message ID : CGA3016E

Severity

Error

Long Form

NOTUSED

Short Form

No short form is provided for this message type

Description

None

Message ID : CGA3017E

Severity

Error

Long Form

Failed to apply new security configuration

Message ID : CGA3016E

Short Form

Security config update failed

Parameters

No parameters are provided for this message type

Description

None

Message ID : CGA3018E

Severity

Error

Long Form

Challenge/Response: An invalid challenge/response was entered

Short Form

Invalid challenge/response

Parameters

No parameters are provided for this message type

Description

None

Message ID : CGA3021E

Severity

Error

Long Form

Challenge/Response: Error processing challenge/response

Short Form

Challenge/Response encryption error

Parameters

No parameters are provided for this message type

Message ID : CGA3018E

Description

None

Message ID : CGA3022E

Severity

Error

Long Form

Key Protection: Key integrity check failed in [{0}]

Short Form

Key integrity check failed

Parameters

Label	CEF Label	Type	Usage
func	vds_func	Text	A function name

Description

None

Message ID : CGA3021E

Message ID : CGA3023E

Severity

Error

Long Form

NOTUSED

Short Form

No short form is provided for this message type

Description

None

Message ID : CGA3024E

Severity

Error

Long Form

Key Protection: Extract rkey: Hardware signature has changed

Message ID : CGA3023E

Short Form

Hardware signature changed

Parameters

No parameters are provided for this message type

Description

None

Message ID : CGA3059E

Severity

Error

Long Form

[AUDIT] Process[`{0}`] Pid[`{1}`] Uid[`{2}`] Operation[`{3}`] File[`{4}`] Failure[`{5}`] Effect[PERMIT]

Short Form

Sysfile modified error

Parameters

Label	CEF Label	Type	Usage
command	command	Text	Task struct comm field
pid	dvcpid	Numeric	Numeric process ID
uid	suid	Numeric	User id
op_name	op_name	Text	Operation name
filePath	filePath	Text	Full path to file
ecode	cnl	Numeric	An error code

Description

None

Message ID : CGA3060E

Severity

Error

Long Form

[ALARM] Process[{0}] Pid[{1}] Uid[{2}] Operation[{3}] File[{4}] Effect[DENIED]

Message ID : CGA3059E

Short Form

Sysfile protected

Parameters

Label	CEF Label	Type	Usage
command	command	Text	Task struct comm field
pid	dvcpid	Numeric	Numeric process ID
uid	suid	Numeric	User id
op_name	op_name	Text	Operation name
filePath	filePath	Text	Full path to file

Description

None

Message ID : CGA3061E

Severity

Error

Message ID : CGA3060E

Long Form

Key Protection: Encryption/Decryption: Bad arguments in function [{}]

Short Form

En/Decrypt BadArgs

Parameters

Label	CEF Label	Type	Usage
func	vds_func	Text	A function name

Description

None

Message ID : CGA3062E

Severity

Error

Long Form

Key Protection: Private key write: Null key in function [{}]

Message ID : CGA3061E

Short Form

PrivKeyWrite NullKey

Parameters

Label	CEF Label	Type	Usage
func	vds_func	Text	A function name

Description

None

Message ID : CGA3063E

Severity

Error

Long Form

Key Protection: Private key write: Invalid key length in function [{0}]

Short Form

PrivKeyWrite InvalKeylen

Message ID : CGA3062E

Parameters

Label	CEF Label	Type	Usage
func	vds_func	Text	A function name

Description

None

Message ID : CGA3064E

Severity

Error

Long Form

Key Protection: Verify sanity: Bad configuration directory and/or session key arguments in function [{0}]

Short Form

VrfySan BadArgs

Parameters

Label	CEF Label	Type	Usage
func	vds_func	Text	A function name

Message ID : CGA3063E

Label	CEF Label	Type	Usage

Description

None

Message ID : CGA3065E

Severity

Error

Long Form

Key Protection: Verify password: Bad configuration directory and/or password arguments in function [{0}]

Short Form

VrfyPwd BadArgs

Parameters

Label	CEF Label	Type	Usage
func	vds_func	Text	A function name

Message ID : CGA3064E

Description

None

Message ID : CGA3066E

Severity

Error

Long Form

Key Protection: Get salt: Bad configuration directory argument in function [{0}]

Short Form

GetSalt BadArg

Parameters

Label	CEF Label	Type	Usage
func	vds_func	Text	A function name

Description

None

Message ID : CGA3065E

Message ID : CGA3067E

Severity

Error

Long Form

Key Protection: Shared secret: Bad configuration directory argument in function [{}]

Short Form

ShrdSecret BadArg

Parameters

Label	CEF Label	Type	Usage
func	vds_func	Text	A function name

Description

None

Message ID : CGA3068E

Severity

Error

Long Form

Key Protection: Key integrity check: Bad arguments in function [{0}]

Short Form

KeyIntegChk BadArgs

Parameters

Label	CEF Label	Type	Usage
func	vds_func	Text	A function name

Description

None

Message ID : CGA3069E

Severity

Error

Message ID : CGA3068E

Long Form

Key Protection: Key integrity check: Invalid key length in function [{0}]

Short Form

KeyIntegChk BadLen

Parameters

Label	CEF Label	Type	Usage
func	vds_func	Text	A function name

Description

None

Message ID : CGA3070E

Severity

Error

Long Form

Key Protection: Extract rkey: Bad arguments in function [{0}]

Message ID : CGA3069E

Short Form

ExtrRkey BadArgs

Parameters

Label	CEF Label	Type	Usage
func	vds_func	Text	A function name

Description

None

Message ID : CGA3071E

Severity

Error

Long Form

Key Protection: Extract rkey: Invalid extraction method in function [{}]

Short Form

ExtrRkey BadMeth

Message ID : CGA3070E

Parameters

Label	CEF Label	Type	Usage
func	vds_func	Text	A function name

Description

None

Message ID : CGA3072E

Severity

Error

Long Form

Key Protection: Policy key update: Bad configuration directory argument in function [{}]

Short Form

PolKeyUpd BadArg

Parameters

Label	CEF Label	Type	Usage
func	vds_func	Text	A function name

Message ID : CGA3071E

Label	CEF Label	Type	Usage

Description

None

Message ID : CGA3073E

Severity

Error

Long Form

Key Protection: Signature update: Bad signature update argument in function [{}]

Short Form

SigUpd BadArg

Parameters

Label	CEF Label	Type	Usage
func	vds_func	Text	A function name

Message ID : CGA3072E

Description

None

Message ID : CGA3074E

Severity

Error

Long Form

Key Protection: Session key decryption: Bad arguments in function [{}]

Short Form

SessKeyDcrpt BadArgs

Parameters

Label	CEF Label	Type	Usage
func	vds_func	Text	A function name

Description

None

Message ID : CGA3073E

Message ID : CGA3075E

Severity

Error

Long Form

Key Protection: Host password: Invalid argument in function [{}]

Short Form

HostPwd BadArg

Parameters

Label	CEF Label	Type	Usage
func	vds_func	Text	A function name

Description

None

Message ID : CGA3076E

Severity

Error

Long Form

Key Protection: Challenge 256: Invalid argument in function [{}0]

Short Form

Chlnge256 BadArg

Parameters

Label	CEF Label	Type	Usage
func	vds_func	Text	A function name

Description

None

Message ID : CGA3077E

Severity

Error

Message ID : CGA3076E

Long Form

Key Protection: Challenge: Invalid argument in function [{0}]

Short Form

ChlngeBadArg

Parameters

Label	CEF Label	Type	Usage
func	vds_func	Text	A function name

Description

None

Message ID : CGA3078E

Severity

Error

Long Form

Key Protection: Failed to write private key in function [{0}]

Message ID : CGA3077E

Short Form

PrivKeyWr Fail

Parameters

Label	CEF Label	Type	Usage
func	vds_func	Text	A function name

Description

None

Message ID : CGA3079E

Severity

Error

Long Form

Key Protection: Failed to read private key in function [{0}]

Short Form

PrivkeyRd Fail

Message ID : CGA3078E

Parameters

Label	CEF Label	Type	Usage
func	vds_func	Text	A function name

Description

None

Message ID : CGA3080E

Severity

Error

Long Form

Key Protection: Extract password: Private key unavailable in function [{0}]

Short Form

ExtrPwd PrivKeyUnavail

Parameters

Label	CEF Label	Type	Usage
func	vds_func	Text	A function name

Message ID : CGA3079E

Label	CEF Label	Type	Usage

Description

None

Message ID : CGA3081E

Severity

Error

Long Form

Key Protection: Verify configuration sanity: Private key unavailable in function [{0}]

Short Form

VrfyConfig: PrivKeyUnavail

Parameters

Label	CEF Label	Type	Usage
func	vds_func	Text	A function name

Message ID : CGA3080E

Description

None

Message ID : CGA3082E

Severity

Error

Long Form

Key Protection: Extract rkey: Private key unavailable in function [{0}]

Short Form

ExtrRkey PrivKeyUnavail

Parameters

Label	CEF Label	Type	Usage
func	vds_func	Text	A function name

Description

None

Message ID : CGA3081E

Message ID : CGA3083E

Severity

Error

Long Form

Key Protection: Extract password: Failed to decrypt using private key in function [{0}]

Short Form

ExtrPwd PrivKeyDcrpt Fail

Parameters

Label	CEF Label	Type	Usage
func	vds_func	Text	A function name

Description

None

Message ID : CGA3084E

Severity

Error

Long Form

Key Protection: Verify configuration sanity: Failed to decrypt using private key in function [{0}]

Short Form

VrfyCfg PrivKeyDcrpt Fail

Parameters

Label	CEF Label	Type	Usage
func	vds_func	Text	A function name

Description

None

Message ID : CGA3085E

Severity

Error

Message ID : CGA3084E

Long Form

Key Protection: Extract rkey CR256: Failed to decrypt using private key in function [{0}]

Short Form

ExtrRkey256 PrivKeyDcrpt Fail

Parameters

Label	CEF Label	Type	Usage
func	vds_func	Text	A function name

Description

None

Message ID : CGA3086E

Severity

Error

Long Form

Key Protection: Extract rkey: Failed to decrypt using private key in function [{0}]

Message ID : CGA3085E

Short Form

ExtrRkey PrivKeyDecrypt Fail

Parameters

Label	CEF Label	Type	Usage
func	vds_func	Text	A function name

Description

None

Message ID : CGA3087E

Severity

Error

Long Form

Key Protection: Verify configuration sanity: Bad session key in file [{0}], function [{1}] line [{2}]

Short Form

VrfyCfg BadSessKey

Message ID : CGA3086E

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file
func	vds_func	Text	A function name

Description

None

Message ID : CGA3088E

Severity

Error

Long Form

Key Protection: Verify configuration sanity: Failed HMAX verification in file [{0}], function [{1}] line [{2}]

Short Form

VrfyCfg FailHMAXVrfy Fail

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file
func	vds_func	Text	A function name

Description

None

Message ID : CGA3089E

Severity

Error

Long Form

Key Protection: Verify configuration sanity: Bad rkey in file [{0}], function [{1}] line [{2}]

Short Form

VrfyCfg BadRkey

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file
func	vds_func	Text	A function name

Description

None

Message ID : CGA3090E

Severity

Error

Long Form

Key Protection: File session key decrypt: Failed description in file [{0}] in function [{1}]

Short Form

FileSessKeyDcrpt Fail

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file
func	vds_func	Text	A function name

Description

None

Message ID : CGA3091E

Severity

Error

Long Form

Key Protection: Extract rkey: Bad password in function [{0}]

Short Form

ExtrRkey BadPwd

Parameters

Label	CEF Label	Type	Usage
func	vds_func	Text	A function name

Description

None

Message ID : CGA3092E

Severity

Error

Long Form

Key Protection: Policy key update: Bad password in function [{0}]

Short Form

PolKeyUpd BadPwd

Parameters

Label	CEF Label	Type	Usage
func	vds_func	Text	A function name

Message ID : CGA3091E

Label	CEF Label	Type	Usage

Description

None

Message ID : CGA3093E

Severity

Error

Long Form

Key Protection: Policy key update: Extract rkey failure in function [{0}]

Short Form

PolKeyUpd ExtrRkey Fail

Parameters

Label	CEF Label	Type	Usage
func	vds_func	Text	A function name

Message ID : CGA3092E

Description

None

Message ID : CGA3094E

Severity

Error

Long Form

Compare dir key: Failed to get dir

Short Form

CmpDirKey FailGetDir

Parameters

No parameters are provided for this message type

Description

None

Message ID : CGA3093E

Message ID : CGA3095E

Severity

Error

Long Form

Compare dir key: Failed to add keyset

Short Form

CmpDirKey FailAddKeyset

Parameters

No parameters are provided for this message type

Description

None

Message ID : CGA3096E

Severity

Error

Message ID : CGA3095E

Long Form

Get keyid: Invalid key object in [{0}] at [{1}]

Short Form

GetKeyid InvalKeyObj

Parameters

Label	CEF Label	Type	Usage
func	vds_func	Text	A function name

Description

None

Message ID : CGA3097E

Severity

Error

Long Form

Get keyid: Local key get failed in [{0}] at [{1}]

Message ID : CGA3096E

Short Form

GetKeyid LclKeyGet Fail

Parameters

Label	CEF Label	Type	Usage
func	vds_func	Text	A function name

Description

None

Message ID : CGA3098E

Severity

Error

Long Form

Policy validation failed

Short Form

PolVald Fail

Message ID : CGA3097E

Parameters

No parameters are provided for this message type

Description

None

Message ID : CGA3099E

Severity

Error

Long Form

LDT: Failed to start

Short Form

LDT: Fail to start

Parameters

No parameters are provided for this message type

Description

None

Message ID : CGA3100E

Severity

Error

Long Form

LDT: Failed to stop

Short Form

LDT: Fail to stop

Parameters

No parameters are provided for this message type

Description

None

Message ID : CGA3099E

Message ID : CGA3101E

Severity

Error

Long Form

LDT: Failed to exit

Short Form

LDT: Fail to exit

Parameters

No parameters are provided for this message type

Description

None

Message ID : CGA3102E

Severity

Error

Message ID : CGA3101E

Long Form

LDT: Cross guard point key compare failed

Short Form

LDT: Cross guard point key compare failed

Parameters

No parameters are provided for this message type

Description

None

Message ID : CGA3103E

Severity

Error

Long Form

LDT: Not enough disk space for file [{0}], aborting transformation

Short Form

LDT: Out of disk space

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : CGA3109E

Severity

Error

Long Form

Not guarding path [{0}] from container [{1}] (Reason: Simulation mode)

Short Form

IgnrCntnrGrd SimMode

Message ID : CGA3103E

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory
dockerid	dockerid	Text	Docker image or container id

Description

None

Message ID : CGA3110E

Severity

Error

Long Form

Not guarding path [{0}] (Reason: Simulation mode)

Short Form

IgnrGrd SimMode

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

Description

None

Message ID : CGA3111E

Severity

Error

Long Form

Not guarding path [{0}] from container [{1}] (Reason: Contains symlinks or is malformed)

Short Form

IgnrCntnrGrd HasSymlnks

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

Message ID : CGA3110E

Label	CEF Label	Type	Usage
dockerid	dockerid	Text	Docker image or container id

Description

None

Message ID : CGA3112E

Severity

Error

Long Form

Not guarding path [{0}] (Reason: Contains symlinks or is malformed)

Short Form

IgnrGrd HasSymlnks

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

Message ID : CGA3111E

Description

None

Message ID : CGA3113E

Severity

Error

Long Form

Not guarding path [{0}] from container [{1}] (Reason: Can't guard root)

Short Form

IgnrCntnrGrd NoRoot

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory
dockerid	dockerid	Text	Docker image or container id

Message ID : CGA3112E

Description

None

Message ID : CGA3114E

Severity

Error

Long Form

Not guarding path [{0}] (Reason: Can't guard root)

Short Form

IgnrGrd NoRoot

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

Description

None

Message ID : CGA3113E

Message ID : CGA3115E

Severity

Error

Long Form

Not guarding path [{0}] from container [{1}] (Reason: Path too long)

Short Form

IgnrCntnrGrd PathLong

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory
dockerid	dockerid	Text	Docker image or container id

Description

None

Message ID : CGA3116E

Severity

Error

Long Form

Not guarding path [{0}] (Reason: Path too long)

Short Form

IgnrGrd PathLong

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

Description

None

Message ID : CGA3117E

Severity

Error

Long Form

Not guarding path [{0}] from container [{1}] (Reason: AUTOFS, but type is not automount)

Short Form

IgnrCntnrGrd AUTOFS

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory
dockerid	dockerid	Text	Docker image or container id

Description

None

Message ID : CGA3118E

Severity

Error

Long Form

Not guarding path [{0}] (Reason: AUTOFS, but type is not automount)

Short Form

IgnrGrd AUTOFS

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

Description

None

Message ID : CGA3119E

Severity

Error

Message ID : CGA3118E

Long Form

Not guarding path [{0}] from container [{1}] (Reason: Not allowed)

Short Form

IgnrCntnrGrd IsInval

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory
dockerid	dockerid	Text	Docker image or container id

Description

None

Message ID : CGA3120E

Severity

Error

Message ID : CGA3119E

Long Form

Not guarding path [{0}] (Reason: Not allowed)

Short Form

IgnrGrd IsInval

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

Description

None

Message ID : CGA3121E

Severity

Error

Long Form

Not guarding path [{0}] from container [{1}] (Reason: Raw device not supported)

Message ID : CGA3120E

Short Form

IgnrCntnrGrd RawDev

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory
dockerid	dockerid	Text	Docker image or container id

Description

None

Message ID : CGA3122E

Severity

Error

Long Form

Not guarding path [{0}] (Reason: Raw device not supported)

Short Form

IgnrGrd RawDev

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

Description

None

Message ID : CGA3123E

Severity

Error

Long Form

Not guarding path [{0}] from container [{1}] (Reason: Unknown)

Short Form

IgnrCntnrGrd BadFlag

Message ID : CGA3122E

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory
dockerid	dockerid	Text	Docker image or container id

Description

None

Message ID : CGA3124E

Severity

Error

Long Form

Not guarding path [{0}] (Reason: Unknown)

Short Form

IgnrCntnrGrd BadFlag

Message ID : CGA3123E

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

Description

None

Message ID : CGA3125E

Severity

Error

Long Form

Not unguarding path [{0}] from container [{1}] (Reason: Unknown)

Short Form

IgnrCntnrUngrd BadFlag

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

Message ID : CGA3124E

Label	CEF Label	Type	Usage
dockerid	dockerid	Text	Docker image or container id

Description

None

Message ID : CGA3126E

Severity

Error

Long Form

Not unguarding path [{}] (Reason: Unknown)

Short Form

IgnrUngrd BadFlag

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

Message ID : CGA3125E

Description

None

Message ID : CGA3127E

Severity

Error

Long Form

Not guarding path [{0}] from container [{1}] (Reason: Nested paths not allowed)

Short Form

BadCntnrGrdPath IsNested

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory
dockerid	dockerid	Text	Docker image or container id

Description

None

Message ID : CGA3128E

Severity

Error

Long Form

Not guarding path [{0}] (Reason: Nested paths not allowed)

Short Form

BadGrdPath IsNested

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

Description

None

Message ID : CGA3127E

Message ID : CGA3129E

Severity

Error

Long Form

Not guarding path [{0}] from container [{1}] (Reason: Busy, will continue to retry)

Short Form

BadCntnrGrdPath IsBusy

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory
dockerid	dockerid	Text	Docker image or container id

Description

None

Message ID : CGA3130E

Severity

Error

Long Form

Not guarding path [{0}] (Reason: Busy, will continue to retry)

Short Form

BadGrdPath IsBusy

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

Description

None

Message ID : CGA3131E

Severity

Error

Long Form

Not unguarding path [{0}] from container [{1}] (Reason: Busy, will continue to retry)

Short Form

BadCntnrUngrdPath IsBusy

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory
dockerid	dockerid	Text	Docker image or container id

Description

None

Message ID : CGA3132E

Severity

Error

Long Form

Not unguarding path [{0}] (Reason: Busy, will continue to retry)

Short Form

BadUngrdPath IsBusy

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

Description

None

Message ID : CGA3133E

Severity

Error

Message ID : CGA3132E

Long Form

Not guarding path [{0}] from container [{1}] (Reason: Does not exist)

Short Form

BadCntnrGrdPath NotExist

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory
dockerid	dockerid	Text	Docker image or container id

Description

None

Message ID : CGA3134E

Severity

Error

Message ID : CGA3133E

Long Form

Not guarding path [{0}] (Reason: Does not exist)

Short Form

BadGrdPath NotExist

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

Description

None

Message ID : CGA3135E

Severity

Error

Long Form

Not unguarding path [{0}] from container [{1}] (Reason: Does not exist)

Message ID : CGA3134E

Short Form

BadCntnrUngrdPath NotExist

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory
dockerid	dockerid	Text	Docker image or container id

Description

None

Message ID : CGA3136E

Severity

Error

Long Form

Not unguarding path [{0}] (Reason: Does not exist)

Message ID : CGA3135E

Short Form

BadUngrdPath NotExist

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

Description

None

Message ID : CGA3137E

Severity

Error

Long Form

Not guarding path [{0}] from container [{1}] (Reason: Already mounted)

Short Form

BadCntnrGrdPath AlreadyMounted

Message ID : CGA3136E

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory
dockerid	dockerid	Text	Docker image or container id

Description

None

Message ID : CGA3138E

Severity

Error

Long Form

Not guarding path [{0}] (Reason: Already mounted)

Short Form

BadGrdPath AlreadyMounted

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

Description

None

Message ID : CGA3139E

Severity

Error

Long Form

Not guarding path [{0}] from container [{1}] (Reason: Max guard point limit reached)

Short Form

BadCntnrGrd MaxGrds

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

Message ID : CGA3138E

Label	CEF Label	Type	Usage
dockerid	dockerid	Text	Docker image or container id

Description

None

Message ID : CGA3140E

Severity

Error

Long Form

Not guarding path [{0}] (Reason: Max guard point limit reached)

Short Form

BadGrd MaxGrds

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

Message ID : CGA3139E

Description

None

Message ID : CGA3141E

Severity

Error

Long Form

Not guarding path [{0}] from container [{1}] (Reason: Resource not available)

Short Form

BadCntnrGrd ResrcUnavail

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory
dockerid	dockerid	Text	Docker image or container id

Message ID : CGA3140E

Description

None

Message ID : CGA3142E

Severity

Error

Long Form

Not guarding path [{0}] (Reason: Resource not available)

Short Form

BadGrd ResrcUnavail

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

Description

None

Message ID : CGA3141E

Message ID : CGA3143E

Severity

Error

Long Form

Not guarding path [{0}] from container [{1}] (Reason: Operation timed out, retrying)

Short Form

BadCntnrGrd TimedOut

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory
dockerid	dockerid	Text	Docker image or container id

Description

None

Message ID : CGA3144E

Severity

Error

Long Form

Not guarding path [{0}] (Reason: Operation timed out, retrying)

Short Form

BadGrd TimedOut

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

Description

None

Message ID : CGA3145E

Severity

Error

Long Form

Not unguarding path [{0}] from container [{1}] (Reason: Operation timed out, retrying)

Short Form

BadCntnrUngrd TimedOut

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory
dockerid	dockerid	Text	Docker image or container id

Description

None

Message ID : CGA3146E

Severity

Error

Long Form

Not unguarding path [{0}] (Reason: Operation timed out, retrying)

Short Form

BadUngrd TimedOut

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

Description

None

Message ID : CGA3147E

Severity

Error

Message ID : CGA3146E

Long Form

Not guarding path [{0}] from container [{1}] (Reason: Invalid guard point)

Short Form

BadCntnrGrdPath InvalGrdPath

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory
dockerid	dockerid	Text	Docker image or container id

Description

None

Message ID : CGA3148E

Severity

Error

Message ID : CGA3147E

Long Form

Not guarding path [{0}] (Reason: Invalid guard point)

Short Form

BadGrdPath InvalGrdPath

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

Description

None

Message ID : CGA3149E

Severity

Error

Long Form

Not guarding path [{0}] from container [{1}] (Reason: Invalid, AUTOFS but type is not automount)

Message ID : CGA3148E

Short Form

BadCntnrGrdPath AUTOFSNoAuto

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory
dockerid	dockerid	Text	Docker image or container id

Description

None

Message ID : CGA3150E

Severity

Error

Long Form

Not guarding path [{0}] (Reason: Invalid, AUTOFS but type is not automount)

Short Form

BadGrdPath AUTOFSNoAuto

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

Description

None

Message ID : CGA3151E

Severity

Error

Long Form

Not guarding path [{0}] from container [{1}] (Reason: Partially guarded)

Short Form

BadCntnrGrd PartialGrd

Message ID : CGA3150E

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory
dockerid	dockerid	Text	Docker image or container id

Description

None

Message ID : CGA3152E

Severity

Error

Long Form

Not guarding path [{0}] (Reason: Partially guarded)

Short Form

BadGrd PartialGrd

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

Description

None

Message ID : CGA3153E

Severity

Error

Long Form

Not guarding path [{0}] from container [{1}] (Reason: Logical drive or path compressed)

Short Form

BadCntnrGrd IsCompressed

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

Message ID : CGA3152E

Label	CEF Label	Type	Usage
dockerid	dockerid	Text	Docker image or container id

Description

None

Message ID : CGA3154E

Severity

Error

Long Form

Not guarding path [{0}] (Reason: Logical drive or path compressed)

Short Form

BadGrd IsCompressed

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

Message ID : CGA3153E

Description

None

Message ID : CGA3155E

Severity

Error

Long Form

Not guarding path [{0}] from container [{1}] (Reason: Logical drive or path encrypted)

Short Form

BadCntnrGrd IsEncrypt

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory
dockerid	dockerid	Text	Docker image or container id

Message ID : CGA3154E

Description

None

Message ID : CGA3156E

Severity

Error

Long Form

Not guarding path [{0}] (Reason: Logical drive or path encrypted)

Short Form

BadGrd IsEncrypt

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

Description

None

Message ID : CGA3155E

Message ID : CGA3157E

Severity

Error

Long Form

Not guarding path [{0}] from container [{1}] (Reason: System Error/Module not present)

Short Form

BadCntnrGrd SysError

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory
dockerid	dockerid	Text	Docker image or container id

Description

None

Message ID : CGA3158E

Severity

Error

Long Form

Not guarding path [{0}] (Reason: System Error/Module not present)

Short Form

BadGrd SysError

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

Description

None

Message ID : CGA3159E

Severity

Error

Long Form

Not unguarding path [{0}] from container [{1}] (Reason: System Error/Module not present)

Short Form

BadCntnrUngrd SysError

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory
dockerid	dockerid	Text	Docker image or container id

Description

None

Message ID : CGA3160E

Message ID : CGA3159E

Severity

Error

Long Form

Not unguarding path [{0}] (Reason: System Error/Module not present)

Short Form

BadUngrd SysError

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

Description

None

Message ID : CGA3161E

Severity

Error

Message ID : CGA3160E

Long Form

Not guarding path [{0}] from container [{1}] (Reason: Protected file system is stale)

Short Form

BadCntnrGrdPath StaleFS

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory
dockerid	dockerid	Text	Docker image or container id

Description

None

Message ID : CGA3162E

Severity

Error

Message ID : CGA3161E

Long Form

Not guarding path [{0}] (Reason: Protected file system is stale)

Short Form

BadGrdPath StaleFS

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

Description

None

Message ID : CGA3163E

Severity

Error

Long Form

Not guarding path [{0}] from container [{1}] (Reason: Unsupported filesystem type)

Message ID : CGA3162E

Short Form

BadCntnrGrdPath FSNotSupp

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory
dockerid	dockerid	Text	Docker image or container id

Description

None

Message ID : CGA3164E

Severity

Error

Long Form

Not guarding path [{0}] (Reason: Unsupported filesystem type)

Short Form

BadGrdPath FSNotSupp

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

Description

None

Message ID : CGA3165E

Severity

Error

Long Form

Not guarding path [{0}] from container [{1}] (Reason: Guard point has metadata, only Live Data Transform policy allowed)

Short Form

BadCntnrGrd BadPol

Message ID : CGA3164E

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory
dockerid	dockerid	Text	Docker image or container id

Description

None

Message ID : CGA3166E

Severity

Error

Long Form

Not guarding path [{0}] (Reason: Guard point has metadata, only Live Data Transform policy allowed)

Short Form

BadGrd BadPol

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

Description

None

Message ID : CGA3167E

Severity

Error

Long Form

Not guarding path [{0}] from container [{1}] (Reason: Filesystem type is not supported with Live Data Transform policy)

Short Form

BadCntnrGrd BadFS

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

Message ID : CGA3166E

Label	CEF Label	Type	Usage
dockerid	dockerid	Text	Docker image or container id

Description

None

Message ID : CGA3168E

Severity

Error

Long Form

Not guarding path [{0}] (Reason: Filesystem type is not supported with Live Data Transform policy)

Short Form

BadGrd BadFS

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

Message ID : CGA3167E

Description

None

Message ID : CGA3169E

Severity

Error

Long Form

Not guarding path [{0}] from container [{1}] (Reason: File system not mounted with Extended attribute support)

Short Form

BadCntnrGrd XattrDisabled

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory
dockerid	dockerid	Text	Docker image or container id

Description

None

Message ID : CGA3170E

Severity

Error

Long Form

Not guarding path [{0}] (Reason: File system not mounted with Extended attribute support)

Short Form

BadGrd XattrDisabled

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

Description

None

Message ID : CGA3169E

Message ID : CGA3171E

Severity

Error

Long Form

Not guarding path [{0}] from container [{1}] (Reason: Nested mount path not allowed for LDT)

Short Form

BadCntnrGrd NestMount

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory
dockerid	dockerid	Text	Docker image or container id

Description

None

Message ID : CGA3172E

Severity

Error

Long Form

Not guarding path [{0}] (Reason: Nested mount path not allowed for LDT)

Short Form

BadGrd NestMount

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

Description

None

Message ID : CGA3173E

Severity

Error

Long Form

Not unguarding path [{0}] from container [{1}] (Reason: LDT metadata removal in progress)

Short Form

BadCntnrGrd LDTMetadata

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory
dockerid	dockerid	Text	Docker image or container id

Description

None

Message ID : CGA3174E

Severity

Error

Long Form

Not unguarding path [{0}] (Reason: LDT metadata removal in progress)

Short Form

BadGrd LDTMetadata

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

Description

None

Message ID : CGA3175E

Severity

Error

Message ID : CGA3174E

Long Form

Not guarding path [{0}] from container [{1}] (Reason: Inactive)

Short Form

BadCntnrGrd Inactive

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory
dockerid	dockerid	Text	Docker image or container id

Description

None

Message ID : CGA3176E

Severity

Error

Message ID : CGA3175E

Long Form

Not guarding path [{0}] (Reason: Inactive)

Short Form

BadGrd Inactive

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

Description

None

Message ID : CGA3177E

Severity

Error

Long Form

Not unguarding path [{0}] from container [{1}] (Reason: Inactive)

Message ID : CGA3176E

Short Form

BadCntnrUngrd Inactive

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory
dockerid	dockerid	Text	Docker image or container id

Description

None

Message ID : CGA3178E

Severity

Error

Long Form

Not unguarding path [{0}] (Reason: Inactive)

Message ID : CGA3177E

Short Form

BadUngrd Inactive

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

Description

None

Message ID : CGA3179E

Severity

Error

Long Form

Not guarding path [{0}] from container [{1}] (Reason: Unknown)

Short Form

BadCntnrGrd BadFlag

Message ID : CGA3178E

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory
dockerid	dockerid	Text	Docker image or container id

Description

None

Message ID : CGA3180E

Severity

Error

Long Form

Not guarding path [{0}] (Reason: Unknown)

Short Form

BadGrd BadFlag

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

Description

None

Message ID : CGA3181E

Severity

Error

Long Form

Not unguarding path [{0}] from container [{1}] (Reason: Unknown)

Short Form

BadCntnrUngrd BadFlag

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

Message ID : CGA3180E

Label	CEF Label	Type	Usage
dockerid	dockerid	Text	Docker image or container id

Description

None

Message ID : CGA3182E

Severity

Error

Long Form

Not unguarding path [{}] (Reason: Unknown)

Short Form

BadUngrd BadFlag

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

Message ID : CGA3181E

Description

None

Message ID : CGA3184E

Severity

Error

Long Form

Failed to guard path [{0}] (Reason: [{1}] file system not supported)

Short Form

FS NotSupp

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

Description

None

Message ID : CGA3182E

Message ID : CGA3185E

Severity

Error

Long Form

Not guarding path [{0}] (Reason: Can't guard root)

Short Form

GrdPath IsRoot

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

Description

None

Message ID : CGA3187E

Severity

Error

Long Form

An encryption policy was applied to a folder containing NTFS compressed files, [{0}]. NTFS compressed files are not encrypted

Short Form

Folder IsCompressed

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

Description

None

Message ID : CGA3188E

Severity

Error

Message ID : CGA3187E

Long Form

An encryption policy was applied to a folder containing NTFS encrypted files, [{0}]. NTFS encrypted files are not encrypted

Short Form

Folder IsCrypt

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

Description

None

Message ID : CGA3189E

Severity

Error

Long Form

Guard path [{0}]: Guard point has metadata, only Live Data Transform policy allowed

Message ID : CGA3188E

Short Form

Bad GrdPath Pol

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

Description

None

Message ID : CGA3190E

Severity

Error

Long Form

Guard path [{0}]: Wrong fs type for this guard point

Short Form

Bad GrdPath FS

Message ID : CGA3189E

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

Description

None

Message ID : CGA3191E

Severity

Error

Long Form

Guard path [{}]: Extended attribute not enabled for guard point

Short Form

GrdPath XattrDisabled

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

Message ID : CGA3190E

Label	CEF Label	Type	Usage

Description

None

Message ID : CGA3192E

Severity

Error

Long Form

Guard path [{0}]: Nested mount not allowed for Live Data Transform

Short Form

GrdPath NestMount

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

Message ID : CGA3191E

Description

None

Message ID : CGA3206E

Severity

Error

Long Form

LDT: failed to encrypt data

Short Form

LDT Crypt Fail

Parameters

No parameters are provided for this message type

Description

None

Message ID : CGA3192E

Message ID : CGA3212E

Severity

Error

Long Form

LDT-ALERT: Error in scanning guardpoint [{0}].

Short Form

LDT-ALERT: Error in scanning guardpoint

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

Description

None

Message ID : CGA3218E

Severity

Error

Long Form

LDT: Skipping transformation of file [{0}], due to pre-check error.

Short Form

LDT: Skipping transformation of file, due to pre-check error

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : CGA3220E

Severity

Error

Message ID : CGA3218E

Long Form

LDT: Error recovering ranges from previous transformation for file [{0}].

Short Form

LDT: Error recovering ranges from previous transformation for file

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : CGA3222E

Severity

Error

Long Form

[AUDIT] Process[{0}] Pid[{1}] Uid[{2}] Operation[{3}] File[{4}] ContainerID[{5}] Failure[{6}] Effect[PERMIT]

Message ID : CGA3220E

Short Form

Sysfile modified error

Parameters

Label	CEF Label	Type	Usage
command	command	Text	Task struct comm field
pid	dvcpid	Numeric	Numeric process ID
uid	suid	Numeric	User id
op_name	op_name	Text	Operation name
filePath	filePath	Text	Full path to file
cid	cid	Text	Container ID
ecode	cn1	Numeric	An error code

Description

None

Message ID : CGA3223E

Severity

Error

Message ID : CGA3222E

Long Form

[ALARM] Process[{0}] Pid[{1}] Uid[{2}] Operation[{3}] File[{4}] ContainerID[{5}] Effect[DENIED]

Short Form

Sysfile protected

Parameters

Label	CEF Label	Type	Usage
command	command	Text	Task struct comm field
pid	dvcpid	Numeric	Numeric process ID
uid	suid	Numeric	User id
op_name	op_name	Text	Operation name
filePath	filePath	Text	Full path to file
cid	cid	Text	Container ID

Description

None

Message ID : CGA3227E

Message ID : CGA3223E

Severity

Error

Long Form

LDT: Error while rekeying guardpoint [{0}]

Short Form

LDT: Error while rekeying guardpoint

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

Description

None

Message ID : CGA3228E

Severity

Error

Message ID : CGA3227E

Long Form

Ptrace denied on authenticator [{0}] pid [{1}]

Short Form

Ptrace authenticator denied

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file
pid	dvcpid	Numeric	Numeric process ID

Description

None

Message ID : CGA3229E

Severity

Error

Message ID : CGA3228E

Long Form

Ptrace denied on protected process [{0}] pid [{1}]

Short Form

Ptrace protected denied

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file
pid	dvcpid	Numeric	Numeric process ID

Description

None

Message ID : CGA3230E

Severity

Error

Message ID : CGA3229E

Long Form

LDT: Terminating rekey ON [{0}] due to data corruption

Short Form

LDT: terminated, corruption

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

Description

None

Message ID : CGA3232E

Severity

Error

Long Form

LDT: Data transformation is aborted on file [{0}]. Error : {1}

Message ID : CGA3230E

Short Form

LDT: Data transformation is aborted on file

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file
ecode	cn1	Numeric	An error code

Description

None

Message ID : CGA3233E

Severity

Error

Long Form

LDT: Data transformation is aborted on file [{0}]. Error : {1}. Reason : {2}

Short Form

LDT: Data transformation is aborted on file

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file
ecode	cnl	Numeric	An error code
showStr	reason	Text	Code specifying reason for allowing access, if any

Description

None

Message ID : CGA3235E

Severity

Error

Long Form

Key Protection: Failed to generate derived key in function [{0}]

Message ID : CGA3233E

Short Form

Generate derived key failed

Parameters

Label	CEF Label	Type	Usage
func	vds_func	Text	A function name

Description

None

Message ID : CGA3236E

Severity

Error

Long Form

Key Protection: Encryption error in function [{0}]

Short Form

Encryption error

Message ID : CGA3235E

Parameters

Label	CEF Label	Type	Usage
func	vds_func	Text	A function name

Description

None

Message ID : CGA3237E

Severity

Error

Long Form

Key Protection: Invalid access file in [{0}] at [{1}]

Short Form

Invalid access file

Parameters

Label	CEF Label	Type	Usage
func	vds_func	Text	A function name

Message ID : CGA3236E

Label	CEF Label	Type	Usage

Description

None

Message ID : CGA3238E

Severity

Error

Long Form

Not re-guarding path [{0}] from container [{1}] (Reason: Guard point initialization already in progress)

Short Form

BadCntnrGrd InProgress

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory
dockerid	dockerid	Text	Docker image or container id

Message ID : CGA3237E

Description

None

Message ID : CGA3239E

Severity

Error

Long Form

Not re-guarding path [{0}] (Reason: Guard point initialization already in progress)

Short Form

BadGrd InProgress

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

Description

None

Message ID : CGA3238E

Message ID : CGA3252E

Severity

Error

Long Form

LDT-ALERT: Cannot enable guard point [{0}], LDT initialization failed with error [{1}]

Short Form

LDT: enable failure

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory
ecode	cn1	Numeric	An error code

Description

None

Message ID : CGA3256E

Severity

Error

Long Form

LDT-ALERT: Error initializing resources, LDT will not be operational.

Short Form

LDT init fail

Parameters

No parameters are provided for this message type

Description

None

Message ID : CGA3272E

Severity

Error

Message ID : CGA3256E

Long Form

{0} does not have UUID

Short Form

UUID does not exist

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : CGA3274E

Severity

Error

Long Form

Failed to write classification {0} to {1}

Message ID : CGA3272E

Short Form

Failed to write

Parameters

Label	CEF Label	Type	Usage
tag	tag	Text	Tag
filePath	filePath	Text	Full path to file

Description

None

Message ID : CGA3275E

Severity

Error

Long Form

Data classification transaction {0} failed for operation {1} with {2} : {3}

Message ID : CGA3274E

Short Form

Classification transaction failed

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file
filePath	filePath	Text	Full path to file

Description

None

Message ID : CGA3278E

Severity

Error

Long Form

Key Conflict for File [{}]: key information in LDT metadata does not match with the key specified under policy

Short Form

Mismatch policy

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : CGA3279E

Severity

Error

Long Form

ESG/IDT-ALERT: IO error on header for ESG/IDT-Capable device [{0}]

Short Form

header IO error

Message ID : CGA3278E

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

Description

None

Message ID : CGA3280E

Severity

Error

Long Form

ESG/IDT-ALERT: Data transformation failure on ESG/IDT-Capable device [{}]

Short Form

IDT fail

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

Message ID : CGA3279E

Label	CEF Label	Type	Usage

Description

None

Message ID : CGA3282E

Severity

Error

Long Form

ESG/IDT-ALERT: Failed to update new device size on ESG/IDT-Capable device [{0}]

Short Form

resize fail

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

Description

None

Message ID : CGA3284E

Severity

Error

Long Form

LDT: Failed to flag GuardPoint [{0}] for deferred key rotation, error [{1}]

Short Form

Defer rotate fail

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory
ecode	cn1	Numeric	An error code

Description

None

Message ID : CGA3289E

Severity

Error

Long Form

Failed to have permission to remediate {0}

Short Form

Failed to have permission to remediate

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : CGA3284E

Message ID : CGA3292E

Severity

Error

Long Form

Failed to prepare remediation for {0}

Short Form

Failed to prepare remediation

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : CGA3295E

Severity

Error

Long Form

Failed to remediate {0} offline

Short Form

Failed to remediate offline

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : CGA3298E

Severity

Error

Message ID : CGA3295E

Long Form

Failed to commit remediation for {0}

Short Form

Failed to commit remediation

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : CGA3301E

Severity

Error

Long Form

Failed to remediate {0} online

Message ID : CGA3298E

Short Form

Failed to remediate online

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : CGA3304E

Severity

Error

Long Form

ESG-ALERT: Process [{0}] disallowed on ESG device [{1}]

Short Form

Disallow ESG

Message ID : CGA3301E

Parameters

Label	CEF Label	Type	Usage
sproc	sproc	Text	Source process
gp	fileId	Text	Guardpoint base directory

Description

None

Message ID : CGA3306E

Severity

Error

Long Form

LDT: Skipping transformation of file [{}], Unable to retrieve the File Information MD.

Short Form

LDT: Skipped invalid INF

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : CGA3307E

Severity

Error

Long Form

LDT: Skipping transformation of file [{}], As failed to validate LDT file MetaData. Please contact support for more information.

Short Form

LDT: Skipped invalid metadata

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Message ID : CGA3306E

Label	CEF Label	Type	Usage

Description

None

Message ID : CGA3308E

Severity

Error

Long Form

LDT: Skipping transformation of file [{}], Key in the policy doesn't match with the key in the MD. Please contact support for more information.

Short Form

LDT: Skipped key mismatch

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Message ID : CGA3307E

Description

None

Message ID : CGA3309E

Severity

Error

Long Form

LDT: Skipping transformation of file [{}],file is being restored or exclusively accessed by the application. Please retrigger the rekey again after application finishes the processing on the file.

Short Form

LDT: Skipped restore

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : CGA3308E

Message ID : CGA3310E

Severity

Error

Long Form

LDT: Skipping transformation of file [{}],As failed to remove the read-only attribute of the file. Please retrigger the rekey again after checking the file permissions.

Short Form

LDT: Skipped read only

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Logger CGA: Information

Message ID : CGA2622I

Severity

Information

Long Form

Access Check Tracing: Invalid policy, use default policy object

Short Form

No short form is provided for this message type

Description

None

Message ID : CGA2630I

Severity

Information

Long Form

Policy [{0}]: Key match file is [{1}]

Short Form

No short form is provided for this message type

Description

None

Message ID : CGA2631I

Severity

Information

Long Form

Policy [{0}]: Key match resource domain is [{1}]

Short Form

No short form is provided for this message type

Message ID : CGA2630I

Description

None

Message ID : CGA2632I

Severity

Information

Long Form

Policy [{0}]: Using Key [{1}] of rule number [{2}]

Short Form

No short form is provided for this message type

Description

None

Message ID : CGA2633I

Severity

Information

Message ID : CGA2631I

Long Form

Policy [{0}]: No key rule matched: Using clear key

Short Form

No short form is provided for this message type

Description

None

Message ID : CGA2640I

Severity

Information

Long Form

Access check tracing: Policy [{0}]: Proc[{{1}}] Gen[{{2}}] User[{{3}} {{4}} {{5}}] Res[{{6}}]

Short Form

No short form is provided for this message type

Message ID : CGA2633I

Description

None

Message ID : CGA2641I

Severity

Information

Long Form

Access check tracing: Policy [{0}]: Empty rules table

Short Form

No short form is provided for this message type

Description

None

Message ID : CGA2642I

Severity

Information

Message ID : CGA2640I

Long Form

Access check tracing: Policy [{0}]: [{1}] Domain [{2}] matched

Short Form

No short form is provided for this message type

Description

None

Message ID : CGA2643I

Severity

Information

Long Form

Access check tracing: Policy [{0}]: Rule number [{1}] matched

Short Form

No short form is provided for this message type

Message ID : CGA2642I

Description

None

Message ID : CGA2644I

Severity

Information

Long Form

Access check tracing: Policy [{0}]: GoTo rule number [{1}]

Short Form

No short form is provided for this message type

Description

None

Message ID : CGA2646I

Severity

Information

Message ID : CGA2643I

Long Form

Access check tracing: Policy [{0}]: No rule matched - default action is [Deny]

Short Form

No short form is provided for this message type

Description

None

Message ID : CGA2647I

Severity

Information

Long Form

Access check tracing: Policy [{0}]: Using effect of rule number [{1}]: [{2} {3} {4}]

Short Form

No short form is provided for this message type

Description

None

Message ID : CGA2656I

Severity

Information

Long Form

Policy [{0}]: Set [{1}] empty with no [{2}]

Short Form

Empty policy set

Parameters

Label	CEF Label	Type	Usage
pol	cs1	Text	Policy name
oType	vds_oType	Text	Object type in policy rule
oName	vds_oName	Text	Object name in policy rule

Description

None

Message ID : CGA2657I

Severity

Information

Long Form

Policy: Set [{}] empty with no [{}]

Short Form

Empty policy set

Parameters

Label	CEF Label	Type	Usage
oType	vds_oType	Text	Object type in policy rule
oName	vds_oName	Text	Object name in policy rule

Description

None

Message ID : CGA3001I

Severity

Information

Long Form

EVENT: {0}

Short Form

Event

Parameters

Label	CEF Label	Type	Usage
showStr	reason	Text	Code specifying reason for allowing access, if any

Description

None

Message ID : CGA2657I

Message ID : CGA3005I

Severity

Information

Long Form

Host password successfully supplied

Short Form

Host password accepted.

Parameters

No parameters are provided for this message type

Description

None

Message ID : CGA3006I

Severity

Information

Message ID : CGA3005I

Long Form

A host password was entered, but was not required

Short Form

Host password not required

Parameters

No parameters are provided for this message type

Description

None

Message ID : CGA3019I

Severity

Information

Long Form

Challenge/Response: Successfully unlocked keys

Short Form

Challenge/Response successful

Parameters

No parameters are provided for this message type

Description

None

Message ID : CGA3020I

Severity

Information

Long Form

Challenge/Response: Challenge/response was entered, but was not required

Short Form

Challenge/Response not required

Parameters

No parameters are provided for this message type

Description

None

Message ID : CGA3058I

Severity

Information

Long Form

[AUDIT] Process[{0}] Pid[{1}] Uid[{2}] Operation[{3}] File[{4}] Effect[PERMIT]

Short Form

Sysfile modified

Parameters

Label	CEF Label	Type	Usage
command	command	Text	Task struct comm field
pid	dvcpid	Numeric	Numeric process ID

Message ID : CGA3020I

Label	CEF Label	Type	Usage
uid	suid	Numeric	User id
op_name	op_name	Text	Operation name
filePath	filePath	Text	Full path to file

Description

None

Message ID : CGA3105I

Severity

Information

Long Form

LDT: Error deleting stale metadata for [{0}]. Delete existing metadata before guarding with a production or data transform policy.

Short Form

LDT: Error deleting stale metadata

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : CGA3183I

Severity

Information

Long Form

Successfully unguarded path [{0}]

Short Form

Ungrd Success

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Message ID : CGA3105I

Label	CEF Label	Type	Usage

Description

None

Message ID : CGA3186I

Severity

Information

Long Form

Successfully configured automount for path [{0}]

Short Form

Automnt Success

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

Message ID : CGA3183I

Description

None

Message ID : CGA3193I

Severity

Information

Long Form

Successfully guarded [{0}]

Short Form

Grd Success

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

Description

None

Message ID : CGA3186I

Message ID : CGA3194I

Severity

Information

Long Form

Successfully guarded [{0}] in simulation mode

Short Form

SimMode Grd Success

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

Description

None

Message ID : CGA3195I

Severity

Information

Long Form

Successfully guarded [{0}] from container [{1}]

Short Form

Cntnr Grd Success

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory
dockerid	dockerid	Text	Docker image or container id

Description

None

Message ID : CGA3196I

Severity

Information

Long Form

Successfully guarded [{0}] from container [{1}] in simulation mode

Short Form

SimMode Cntnr Grd Success

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory
dockerid	dockerid	Text	Docker image or container id

Description

None

Message ID : CGA3197I

Severity

Information

Long Form

[[0]] System lock enabled

Short Form

System lock enabled

Parameters

Label	CEF Label	Type	Usage
stime	start	Text	A start time stamp

Description

None

Message ID : CGA3198I

Severity

Information

Message ID : CGA3197I

Long Form

[[0]] System lock disabled

Short Form

SysLock Disabled

Parameters

Label	CEF Label	Type	Usage
stime	start	Text	A start time stamp

Description

None

Message ID : CGA3199I

Severity

Information

Long Form

[[0]] FS agent lock enabled

Message ID : CGA3198I

Short Form

FSAgentLock Enabled

Parameters

Label	CEF Label	Type	Usage
stime	start	Text	A start time stamp

Description

None

Message ID : CGA3200I

Severity

Information

Long Form

[[0]] FS agent lock disabled

Short Form

FSAgentLock Disabled

Message ID : CGA3199I

Parameters

Label	CEF Label	Type	Usage
stime	start	Text	A start time stamp

Description

None

Message ID : CGA3201I

Severity

Information

Long Form

[[{0}]] Concise logging enabled

Short Form

ConsLog Enabled

Parameters

Label	CEF Label	Type	Usage
stime	start	Text	A start time stamp

Message ID : CGA3200I

Label	CEF Label	Type	Usage

Description

None

Message ID : CGA3202I

Severity

Information

Long Form

[[0]] Concise logging disabled

Short Form

ConsLog Disabled

Parameters

Label	CEF Label	Type	Usage
stime	start	Text	A start time stamp

Description

None

Message ID : CGA3203I

Severity

Information

Long Form

Policy [{0}] took effect or was modified

Short Form

Pol Modified

Parameters

Label	CEF Label	Type	Usage
pol	cs1	Text	Policy name

Description

None

Message ID : CGA3202I

Message ID : CGA3204I

Severity

Information

Long Form

Successfully unguarded [{0}] from container [{1}]

Short Form

Cntnr Ungrd Success

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory
dockerid	dockerid	Text	Docker image or container id

Description

None

Message ID : CGA3205I

Severity

Information

Long Form

Successfully unguarded [{0}]

Short Form

Ungrd Success

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

Description

None

Message ID : CGA3207I

Severity

Information

Long Form

FS Agent lock successful

Short Form

FSAgent Lock Success

Parameters

No parameters are provided for this message type

Description

None

Message ID : CGA3208I

Severity

Information

Long Form

FS Agent unlock successful

Short Form

FSAgent Unlock Success

Parameters

No parameters are provided for this message type

Description

None

Message ID : CGA3209I

Severity

Information

Long Form

System is now locked

Short Form

System Lock Success

Parameters

No parameters are provided for this message type

Description

None

Message ID : CGA3210I

Severity

Information

Long Form

System is now unlocked

Short Form

System Unlock Success

Parameters

No parameters are provided for this message type

Description

None

Message ID : CGA3211I

Severity

Information

Long Form

McAfee Host Intrusion Prevention is disabled while the system is unlocked

Short Form

HIPS Disabled

Parameters

No parameters are provided for this message type

Description

None

Message ID : CGA3213I

Severity

Information

Long Form

LDT: Completed scanning guardpoint [{0}].

Short Form

LDT: Completed scanning guardpoint

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

Description

None

Message ID : CGA3211I

Message ID : CGA3214I

Severity

Information

Long Form

LDT: Starting transformation for guardpoint [{0}].

Short Form

LDT: Starting transformation for guardpoint

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

Description

None

Message ID : CGA3215I

Severity

Information

Long Form

LDT: Completed transformation for guardpoint [{}].

Short Form

LDT: Completed transformation for guardpoint

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

Description

None

Message ID : CGA3216I

Severity

Information

Message ID : CGA3215I

Long Form

LDT: Skipping transformation of passthrough file [{0}].

Short Form

LDT: Skipping transformation of passthrough file

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : CGA3217I

Severity

Information

Long Form

LDT: Skipping transformation of read-only file [{0}].

Message ID : CGA3216I

Short Form

LDT: Skipping transformation of read-only file

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : CGA3219I

Severity

Information

Long Form

LDT: Starting transformation of file [{0}].

Short Form

LDT: Starting transformation of file

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : CGA3221I

Severity

Information

Long Form

[AUDIT] Process[{0}] Pid[{1}] Uid[{2}] Operation[{3}] File[{4}] ContainerID[{5}] Effect[PERMIT]

Short Form

Sysfile modified

Parameters

Label	CEF Label	Type	Usage
command	command	Text	Task struct comm field

Message ID : CGA3219I

Label	CEF Label	Type	Usage
pid	dvcpid	Numeric	Numeric process ID
uid	suid	Numeric	User id
op_name	op_name	Text	Operation name
filePath	filePath	Text	Full path to file
cid	cid	Text	Container ID

Description

None

Message ID : CGA3224I

Severity

Information

Long Form

LDT: Completed transformation of guardpoint [{0}] {1}

Short Form

LDT: Completed transformation of guardpoint

Message ID : CGA3221I

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory
ldt_stats	ldt_stats	Text	LDT statistics

Description

None

Message ID : CGA3225I

Severity

Information

Long Form

LDT: Skipping transformation of reparse point or link [{0}].

Short Form

LDT: Skipping transformation of reparse point

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : CGA3226I

Severity

Information

Long Form

LDT: Scan completed for guardpoint [{0}]. Data statistics for guard point: {1}.

Short Form

LDT: GP stats:

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

Message ID : CGA3225I

Label	CEF Label	Type	Usage
ldt_stats	ldt_stats	Text	LDT statistics

Description

None

Message ID : CGA3240I

Severity

Information

Long Form

LDT: Skipping transformation of passthrough file [{0}]. The file resides in the boot directory. CTE cannot encrypt boot directory files.

Short Form

LDT: Skipping passthrough bootdir

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Message ID : CGA3226I

Label	CEF Label	Type	Usage

Description

None

Message ID : CGA3241I

Severity

Information

Long Form

LDT: Skipping transformation of passthrough file [{}]. CTE cannot encrypt these files. They are already encrypted using NTFS encryption or compressed.

Short Form

LDT: Skipping passthrough encrypted

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : CGA3242I

Severity

Information

Long Form

LDT: Skipping transformation of passthrough file [{}]. File is not in a GuardPoint directory.

Short Form

LDT: Skipping passthrough notfiltered

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : CGA3241I

Message ID : CGA3244I

Severity

Information

Long Form

Volume [{}] is being mounted. Guard points on this volume will be protected by Thales CTE

Short Form

Volume is being mounted

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : CGA3245I

Severity

Information

Long Form

CTE upgrade enabled

Short Form

VTE upgrade enabled

Parameters

No parameters are provided for this message type

Description

None

Message ID : CGA3246I

Severity

Information

Long Form

CTE upgrade disabled

Short Form

VTE upgrade disabled

Parameters

No parameters are provided for this message type

Description

None

Message ID : CGA3247I

Severity

Information

Long Form

CTE upgrade canceled

Short Form

VTE upgrade canceled

Parameters

No parameters are provided for this message type

Description

None

Message ID : CGA3248I

Severity

Information

Long Form

CTE upgraded on reboot

Short Form

VTE upgraded on reboot

Parameters

No parameters are provided for this message type

Description

None

Message ID : CGA3257I

Severity

Information

Long Form

LDT: Exclusive access for rekey delayed on inode [%lld].

Short Form

LDT exclusive delayed

Parameters

Label	CEF Label	Type	Usage
node	vds_node	Numeric	A node identifier

Message ID : CGA3248I

Description

None

Message ID : CGA3258I

Severity

Information

Long Form

LDT: Exclusive access for rekey granted after delay on inode [%lld].

Short Form

LDT exclusive granted

Parameters

Label	CEF Label	Type	Usage
node	vds_node	Numeric	A node identifier

Description

None

Message ID : CGA3257I

Message ID : CGA3269I

Severity

Information

Long Form

Key change detected on {0} with Operation [{1}] and classification {2}

Short Form

Classification key change

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file
tag_op	tag_op	Text	Tag operation
tag	tag	Text	Tag

Description

None

Message ID : CGA3270I

Severity

Information

Long Form

Operation {0} failed because data classification is not enabled on {1}

Short Form

Classification not enabled

Parameters

Label	CEF Label	Type	Usage
tag_op	tag_op	Text	Tag operation
filePath	filePath	Text	Full path to file

Description

None

Message ID : CGA3271I

Severity

Information

Long Form

Data classification initialization has not been finished for guard point {0}

Short Form

classification not initialized

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

Description

None

Message ID : CGA3273I

Severity

Information

Long Form

Succeeded to write classification {0} to {1}

Short Form

Succeeded to write

Parameters

Label	CEF Label	Type	Usage
tag	tag	Text	Tag
filePath	filePath	Text	Full path to file

Description

None

Message ID : CGA3281I

Severity

Information

Long Form

ESG/IDT-INFO: Data transformation complete on ESG/IDT-Capable device [{}]

Short Form

IDT ok

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

Description

None

Message ID : CGA3283I

Severity

Information

Message ID : CGA3281I

Long Form

LDT: Deferred key rotation on GuardPoint [{0}] until after completion of current transformation

Short Form

Defer rotate ok

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

Description

None

Message ID : CGA3287I

Severity

Information

Long Form

Acquiring permission to remediate {0}

Message ID : CGA3283I

Short Form

Acquiring permission to remediate

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : CGA3288I

Severity

Information

Long Form

Got permission to remediate {0}

Short Form

Got permission to remediate

Message ID : CGA3287I

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : CGA3290I

Severity

Information

Long Form

Preparing to remediate {0}

Short Form

Preparing to remediate

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Message ID : CGA3288I

Label	CEF Label	Type	Usage

Description

None

Message ID : CGA3291I

Severity

Information

Long Form

Ready to remediate {0}

Short Form

Ready to remediate

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : CGA3293I

Severity

Information

Long Form

Remediating {0} from {1} to {2} offline

Short Form

Remediating offline

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file
key	cs3	Text	Name of key or key pair
key	cs3	Text	Name of key or key pair

Message ID : CGA3291I

Description

None

Message ID : CGA3294I

Severity

Information

Long Form

Remediated {0} from {1} to {2} offline

Short Form

Remediated offline

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file
key	cs3	Text	Name of key or key pair
key	cs3	Text	Name of key or key pair

Message ID : CGA3293I

Description

None

Message ID : CGA3296I

Severity

Information

Long Form

Committing remediation for {0}

Short Form

Committing remediation

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : CGA3294I

Message ID : CGA3297I

Severity

Information

Long Form

Committed remediation for {0}

Short Form

Committed remediation

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : CGA3299I

Severity

Information

Long Form

Remediating {0} from {1} to {2} online

Short Form

Remediating online

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file
key	cs3	Text	Name of key or key pair
key	cs3	Text	Name of key or key pair

Description

None

Message ID : CGA3300I

Message ID : CGA3299I

Severity

Information

Long Form

Remediated {0} from {1} to {2} online

Short Form

Remediated online

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file
key	cs3	Text	Name of key or key pair
key	cs3	Text	Name of key or key pair

Description

None

Message ID : CGA3305I

Message ID : CGA3300I

Severity

Information

Long Form

ESG-INFO: Process [{0}] allowed on ESG device [{1}]

Short Form

Allow ESG

Parameters

Label	CEF Label	Type	Usage
sproc	sproc	Text	Source process
gp	fileId	Text	Guardpoint base directory

Description

None

Message ID : CGA3343I

Severity

Information

Long Form

Remediation is being done on other cte client for {0}

Short Form

Remediation on nfs

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Logger CGA: Warnings

Message ID : CGA2615W

Severity

Warning

Long Form

[[0] {1}]: Sub-domain [{2}] not found

Short Form

No short form is provided for this message type

Description

None

Message ID : CGA2616W

Severity

Warning

Long Form

[[0] {1}]: Undefined sub-domain [{2}]

Short Form

No short form is provided for this message type

Description

None

Message ID : CGA2623W

Severity

Warning

Long Form

Policy [[0]]: Rename problem: source [{1}] is encrypted by key [{2}] but destination [{3}] by key [{4}]

Short Form

Policy rename failed

Parameters

Label	CEF Label	Type	Usage
pol	cs1	Text	Policy name
oldFilePath	oldFilePath	Text	Previous path to file (for rename and link)
key	cs3	Text	Name of key or key pair
filePath	filePath	Text	Full path to file
altKey	vds_altKey	Text	Name of alternate key for multi-key operations

Description

None

Message ID : CGA2901W

Severity

Warning

Long Form

Challenge/Response: Challenge/response requested to decrypt keys

Short Form

Challenge/Response requested to decrypt keys

Parameters

No parameters are provided for this message type

Description

None

Message ID : CGA3002W

Severity

Warning

Long Form

EVENT: {0}

Short Form

Event

Parameters

Label	CEF Label	Type	Usage
showStr	reason	Text	Code specifying reason for allowing access, if any

Description

None

Message ID : CGA3104W

Severity

Warning

Long Form

LDT: Volume dismounted. Aborting transformation at file [{0}]

Short Form

LDT: Stopping on dismount

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Message ID : CGA3002W

Label	CEF Label	Type	Usage

Description

None

Message ID : CGA3106W

Severity

Warning

Long Form

LDT: The guard point [{"0}"] does not have a valid transformation policy, there is no new key rule

Short Form

LDT: no new key rule

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

Description

None

Message ID : CGA3107W

Severity

Warning

Long Form

LDT: The guard point [{}0] does not have a valid transformation policy, there is no key_op rule

Short Form

LDT: no key_op rule

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

Description

None

Message ID : CGA3106W

Message ID : CGA3108W

Severity

Warning

Long Form

LDT: The guard point [{0}] does not support Live Data Transform, only file operations from the Offline Data Transform process will be allowed

Short Form

LDT: online rekey not supported

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

Description

None

Message ID : CGA3231W

Severity

Warning

Long Form

Failed to get a HDFS file name for {0}. Check the secfsd.log and the vor-hdfs-stderr.log for more details, and make sure the NameNode is running

Short Form

Failed to get HDFS file name

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : CGA3243W

Severity

Warning

Message ID : CGA3231W

Long Form

Volume [{}] is getting dismounted. Guard Points on this volume will not be protected by Thales CTE

Short Form

Volume is getting dismounted

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : CGA3265W

Severity

Warning

Long Form

FSADM-ALERT: ESG/IDT required Signature Set for system utilities may have to be resigned {}

Message ID : CGA3243W

Short Form

FSADM-ALERT: Resigning of file system binaries is required

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : CGA3276W

Severity

Warning

Long Form

Denied access to {0}{1} during classification initialization

Short Form

File access denied during initialization

Message ID : CGA3265W

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file
filePath	filePath	Text	Full path to file

Description

None

Message ID : CGA3285W

Severity

Warning

Long Form

Denied access to data classification internal file {0}{1}

Short Form

Internal file access denied

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file
filePath	filePath	Text	Full path to file

Description

None

Message ID : CGA3286W

Severity

Warning

Long Form

Denied access to {0}{1} during data remediation

Short Form

File access denied during remediation

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file
filePath	filePath	Text	Full path to file

Description

None

Logger CGP: Errors

Message ID : CGP2602E

Severity

Error

Long Form

{0} Policy[{{1}}] User[{{2}}] Process[{{3}}] Action[{{4}}] Res[{{5}}{6}] Key[{{7}}] Effect[{{8}} {9}]

Short Form

Reject access

Parameters

Label	CEF Label	Type	Usage
cat	cat	Text	Event Category (e.g. AUDIT, TRACE)
pol	cs1	Text	Policy name
user	suser	Text	User name
sproc	sproc	Text	Source process
act	act	Text	Action being requested or performed

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory
filePath	filePath	Text	Full path to file
key	cs3	Text	Name of key or key pair
denyStr	msg	Text	Code specifying reason for denying access, if any
showStr	reason	Text	Code specifying reason for allowing access, if any

Description

A GuardPoint policy has blocked access to encrypted data. The reason for blocking the attempt is provided in the message fields.

Message ID : CGP2604E

Severity

Error

Long Form

{0} Policy[{1}] User[{2}] Process[{3}] Action[{4}] Res[{5}{6}] {7} Effect[{8} {9}]

Short Form

Reject access

Parameters

Label	CEF Label	Type	Usage
cat	cat	Text	Event Category (e.g. AUDIT, TRACE)
pol	cs1	Text	Policy name
user	suser	Text	User name
sproc	sproc	Text	Source process
act	act	Text	Action being requested or performed
gp	fileId	Text	Guardpoint base directory
filePath	filePath	Text	Full path to file
denyStr	msg	Text	Code specifying reason for denying access, if any
showStr	reason	Text	Code specifying reason for allowing access, if any

Description

A GuardPoint policy has blocked access to encrypted data. The reason for blocking the attempt is provided in the message fields.

Message ID : CGP2606E

Severity

Error

Message ID : CGP2604E

Long Form

{0} Policy[{1}] User[{2}] Process[{3}] Action[{4}] Res[{5}{6}] Effect[{7} {8}]

Short Form

Reject node

Parameters

Label	CEF Label	Type	Usage
cat	cat	Text	Event Category (e.g. AUDIT, TRACE)
pol	cs1	Text	Policy name
user	suser	Text	User name
sproc	sproc	Text	Source process
act	act	Text	Action being requested or performed
gp	fileId	Text	Guardpoint base directory
filePath	filePath	Text	Full path to file
denyStr	msg	Text	Code specifying reason for denying access, if any
showStr	reason	Text	Code specifying reason for allowing access, if any

Description

A GuardPoint policy has blocked access to encrypted data. The reason for blocking the attempt is provided in the message fields.

Message ID : CGP2608E

Severity

Error

Long Form

{0} Policy[{{1}}] User[{{2}}] Process[{{3}}] Action[{{4}}] Res[{{5}}]{{6}} [{{7}}]{{8}} Effect[{{9}}] {{10}}

Short Form

Reject link

Parameters

Label	CEF Label	Type	Usage
cat	cat	Text	Event Category (e.g. AUDIT, TRACE)
pol	cs1	Text	Policy name
user	suser	Text	User name
sproc	sproc	Text	Source process

Label	CEF Label	Type	Usage
act	act	Text	Action being requested or performed
gp	fileId	Text	Guardpoint base directory
oldFilePath	oldFilePath	Text	Previous path to file (for rename and link)
filePath	filePath	Text	Full path to file
denyStr	msg	Text	Code specifying reason for denying access, if any
showStr	reason	Text	Code specifying reason for allowing access, if any

Description

None

Message ID : CGP2610E

Severity

Error

Long Form

{0} Policy[{1}] User[{2}] Process[{3}] Action[{4}] Res[{5}{6}] [{7}{8}] Effect[{9} {10}]

Short Form

Reject rename

Parameters

Label	CEF Label	Type	Usage
cat	cat	Text	Event Category (e.g. AUDIT, TRACE)
pol	cs1	Text	Policy name
user	suser	Text	User name
sproc	sproc	Text	Source process
act	act	Text	Action being requested or performed
gp	fileId	Text	Guardpoint base directory
oldFilePath	oldFilePath	Text	Previous path to file (for rename and link)
filePath	filePath	Text	Full path to file
denyStr	msg	Text	Code specifying reason for denying access, if any
showStr	reason	Text	Code specifying reason for allowing access, if any

Description

None

Logger CGP: Information

Message ID : CGP2601I

Severity

Information

Long Form

{0} Policy[{{1}}] User[{{2}}] Process[{{3}}] Action[{{4}}] Res[{{5}}{6}] Key[{{7}}] Effect[{{8}} {9}]

Short Form

Audit access

Parameters

Label	CEF Label	Type	Usage
cat	cat	Text	Event Category (e.g. AUDIT, TRACE)
pol	cs1	Text	Policy name
user	suser	Text	User name
sproc	sproc	Text	Source process
act	act	Text	Action being requested or performed

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory
filePath	filePath	Text	Full path to file
key	cs3	Text	Name of key or key pair
denyStr	msg	Text	Code specifying reason for denying access, if any
showStr	reason	Text	Code specifying reason for allowing access, if any

Description

None

Message ID : CGP2603I

Severity

Information

Long Form

{0} Policy[{1}] User[{2}] Process[{3}] Action[{4}] Res[{5}{6}] {7} Effect[{8} {9}]

Short Form

Audit access

Message ID : CGP2601I

Parameters

Label	CEF Label	Type	Usage
cat	cat	Text	Event Category (e.g. AUDIT, TRACE)
pol	cs1	Text	Policy name
user	suser	Text	User name
sproc	sproc	Text	Source process
act	act	Text	Action being requested or performed
gp	fileId	Text	Guardpoint base directory
filePath	filePath	Text	Full path to file
denyStr	msg	Text	Code specifying reason for denying access, if any
showStr	reason	Text	Code specifying reason for allowing access, if any

Description

None

Message ID : CGP2605I

Severity

Information

Message ID : CGP2603I

Long Form

{0} Policy[{1}] User[{2}] Process[{3}] Action[{4}] Res[{5}{6}] Effect[{7} {8}]

Short Form

Audit node

Parameters

Label	CEF Label	Type	Usage
cat	cat	Text	Event Category (e.g. AUDIT, TRACE)
pol	cs1	Text	Policy name
user	suser	Text	User name
sproc	sproc	Text	Source process
act	act	Text	Action being requested or performed
gp	fileId	Text	Guardpoint base directory
filePath	filePath	Text	Full path to file
denyStr	msg	Text	Code specifying reason for denying access, if any
showStr	reason	Text	Code specifying reason for allowing access, if any

Description

None

Message ID : CGP2607I

Severity

Information

Long Form

{0} Policy[{{1}}] User[{{2}}] Process[{{3}}] Action[{{4}}] Res[{{5}}{6}] [{{7}}{8}] Effect[{{9}} {10}]

Short Form

Audit link

Parameters

Label	CEF Label	Type	Usage
cat	cat	Text	Event Category (e.g. AUDIT, TRACE)
pol	cs1	Text	Policy name
user	suser	Text	User name
sproc	sproc	Text	Source process

Label	CEF Label	Type	Usage
act	act	Text	Action being requested or performed
gp	fileId	Text	Guardpoint base directory
oldFilePath	oldFilePath	Text	Previous path to file (for rename and link)
filePath	filePath	Text	Full path to file
denyStr	msg	Text	Code specifying reason for denying access, if any
showStr	reason	Text	Code specifying reason for allowing access, if any

Description

None

Message ID : CGP2609I

Severity

Information

Long Form

{0} Policy[{1}] User[{2}] Process[{3}] Action[{4}] Res[{5}{6}] [{7}{8}] Effect[{9} {10}]

Short Form

Audit rename

Parameters

Label	CEF Label	Type	Usage
cat	cat	Text	Event Category (e.g. AUDIT, TRACE)
pol	cs1	Text	Policy name
user	suser	Text	User name
sproc	sproc	Text	Source process
act	act	Text	Action being requested or performed
gp	fileId	Text	Guardpoint base directory
oldFilePath	oldFilePath	Text	Previous path to file (for rename and link)
filePath	filePath	Text	Full path to file
denyStr	msg	Text	Code specifying reason for denying access, if any
showStr	reason	Text	Code specifying reason for allowing access, if any

Description

None

Logger CGS: Errors

Message ID : CGS2613E

Severity

Error

Long Form

Memory allocation failed in [{}] at line [{}]

Short Form

Out of memory

Parameters

No parameters are provided for this message type

Description

None

Message ID : CGS3025E

Severity

Error

Long Form

LDT: Unable to remove LDT extended attribute on guard point [{0}]. Error: [{1}]

Short Form

Extended attr delete

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file
showStr	reason	Text	Code specifying reason for allowing access, if any

Description

None

Message ID : CGS3026E

Severity

Error

Long Form

LDT-ALERT: QoS failed to start

Short Form

QoS failed to start

Parameters

No parameters are provided for this message type

Description

None

Message ID : CGS3027E

Severity

Error

Long Form

LDT-ALERT: Failed to launch transformation on [{}]

Short Form

LDT: launch failure

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

Description

None

Message ID : CGS3028E

Severity

Error

Long Form

LDT: Encryption key for file [{}] unavailable for LDT, possibly due to loss of communication to DSM

Message ID : CGS3027E

Short Form

LDT: Key unavailable

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : CGS3031E

Severity

Error

Long Form

LDT: Rekey failed for file [{0}] on guard point [{1}]. Error {2}

Short Form

LDT: failed

Message ID : CGS3028E

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file
gp	fileId	Text	Guardpoint base directory
ecode	cn1	Numeric	An error code

Description

None

Message ID : CGS3032E

Severity

Error

Long Form

LDT-ALERT: Key rotation failed on guard point [{0}]

Short Form

LDT: Key rotation failed

Message ID : CGS3031E

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

Description

None

Message ID : CGS3033E

Severity

Error

Long Form

LDT-ALERT: Failed to update LDT attribute on guard point [{{0}}]. Error: [{{1}}]

Short Form

LDT: Key rotation failure, EA

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Message ID : CGS3032E

Label	CEF Label	Type	Usage
ecode	cn1	Numeric	An error code

Description

None

Message ID : CGS3034E

Severity

Error

Long Form

LDT-ALERT: Failed to suspend rekey on guard point [{0}]

Short Form

LDT: suspend failure

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

Message ID : CGS3033E

Description

None

Message ID : CGS3035E

Severity

Error

Long Form

LDT: Failed to suspend rekey on all guard points

Short Form

LDT: suspend failure: all

Parameters

No parameters are provided for this message type

Description

None

Message ID : CGS3034E

Message ID : CGS3038E

Severity

Error

Long Form

LDT-ALERT: Failed to resume rekey on guard point [{0}]

Short Form

LDT: resume failure

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

Description

None

Message ID : CGS3039E

Severity

Error

Long Form

LDT-ALERT: Failed to resume rekey on all guard points

Short Form

LDT: resume failure: all

Parameters

No parameters are provided for this message type

Description

None

Message ID : CGS3042E

Severity

Error

Long Form

LDT: Skipped LDT recovery on read-only file system [{0}]

Short Form

Skipped LDT recovery: ROFS

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

Description

None

Message ID : CGS3043E

Severity

Error

Long Form

LDT-ALERT: MDS file [{0}] exceeded diskspace quota on gp [{1}]

Message ID : CGS3042E

Short Form

MDS ENOSPC

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file
gp	fileId	Text	Guardpoint base directory

Description

None

Message ID : CGS3044E

Severity

Error

Long Form

LDT: Insufficient memory condition encountered during LDT on guard point [{}]

Short Form

MDS ENOMEM

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

Description

None

Message ID : CGS3045E

Severity

Error

Long Form

LDT-ALERT: Failed to update LDT attribute

Short Form

LDT: xattr failure

Message ID : CGS3044E

Parameters

No parameters are provided for this message type

Description

None

Message ID : CGS3047E

Severity

Error

Long Form

LDT-ALERT: Aborting rekey of file [{}] due to insufficient disk space

Short Form

LDT:SFS ENOSPC

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Message ID : CGS3045E

Description

None

Message ID : CGS3048E

Severity

Error

Long Form

LDT: Aborting rekey of file [{}] due to lack of free memory. Try closing other applications to resolve the issue

Short Form

LDT:SFS ENOMEM

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : CGS3047E

Message ID : CGS3049E

Severity

Error

Long Form

LDT-ALERT: Skipped key rotation on guard point [{0}]. It is on a read-only file system

Short Form

LDT: Skipped ROFS

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

Description

None

Message ID : CGS3050E

Severity

Error

Long Form

LDT-ALERT: Skipped key rotation on guard point [{0}] due to insufficient disk space

Short Form

LDT: Skipped ENOSPC

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

Description

None

Message ID : CGS3051E

Severity

Error

Message ID : CGS3050E

Long Form

LDT-ALERT: Failed to rotate key on guard point [{0}]. Another rekey operation is already in progress

Short Form

LDT: Skipped EBUSY

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

Description

None

Message ID : CGS3052E

Severity

Error

Long Form

LDT-ALERT: Skipped key rotation on guard point [{0}]. Error: [{1}]

Message ID : CGS3051E

Short Form

LDT: Skipped, error

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory
ecode	cn1	Numeric	An error code

Description

None

Message ID : CGS3053E

Severity

Error

Long Form

LDT-ALERT: Failed to rotate key on guard point [{0}] during pre-commit

Short Form

LDT: pre-commit failed

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

Description

None

Message ID : CGS3054E

Severity

Error

Long Form

LDT-ALERT: Failed to rotate key on guard point [{0}] during commit

Short Form

LDT: commit failed

Message ID : CGS3053E

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

Description

None

Message ID : CGS3055E

Severity

Error

Long Form

LDT: Failed to abort key rotation on guard point [{0}]

Short Form

LDT: abort failed

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

Message ID : CGS3054E

Label	CEF Label	Type	Usage

Description

None

Message ID : CGS3057E

Severity

Error

Long Form

LDT: Extended attribute of inode [%lld] is corrupted under guard point [{0}]

Short Form

LDT: xattr corrupted

Parameters

Label	CEF Label	Type	Usage
node	vds_node	Numeric	A node identifier
gp	fileId	Text	Guardpoint base directory

Message ID : CGS3055E

Description

None

Message ID : CGS3234E

Severity

Error

Long Form

LDT: Rekey failed for file [{0}] on guard point [{1}]. Error {2}. Reason :{3}

Short Form

LDT: failed

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file
gp	fileId	Text	Guardpoint base directory
ecode	cn1	Numeric	An error code
showStr	reason	Text	Code specifying reason for allowing access, if any

Message ID : CGS3057E

Description

None

Message ID : CGS3253E

Severity

Error

Long Form

LDT: Extended attribute of inode [%lld] is missing under guard point [{0}]

Short Form

LDT: xattr missing

Parameters

Label	CEF Label	Type	Usage
node	vds_node	Numeric	A node identifier
gp	fileId	Text	Guardpoint base directory

Description

None

Message ID : CGS3259E

Severity

Error

Long Form

IV of file [{0}] is corrupted

Short Form

file IV corrupted

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : CGS3253E

Message ID : CGS3260E

Severity

Error

Long Form

IV of file [{0}] is mismatched(file may be restored to wrong fs)

Short Form

file IV mismatched

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : CGS3261E

Severity

Error

Long Form

LDT-ALERT: failed to rekey segment [{0}] of [{1}]. Error: [{2}]

Short Form

LDT: failure to rekey segment

Parameters

Label	CEF Label	Type	Usage
segID	vds_segID	Numeric	Segment ID
filePath	filePath	Text	Full path to file
ecode	cn1	Numeric	An error code

Description

None

Message ID : CGS3262E

Message ID : CGS3261E

Severity

Error

Long Form

LDT-ALERT: Skipped rekeying [{0}] on guard point [{1}]. Error: [{2}]

Short Form

LDT: skipped rekey on file

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file
gp	fileId	Text	Guardpoint base directory
ecode	cn1	Numeric	An error code

Description

None

Message ID : CGS3263E

Message ID : CGS3262E

Severity

Error

Long Form

LDT-ALERT: LDT recovery failure on guard point [{0}]. Error: [{1}]

Short Form

LDT-ALERT: LDT recovery failure

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory
ecode	cn1	Numeric	An error code

Description

None

Message ID : CGS3264E

Message ID : CGS3263E

Severity

Error

Long Form

LDT-ALERT: Restore of LDT protected file [{0}] not allowed by policy.

Short Form

LDT-ALERT: LDT restore denied

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : CGS3266E

Severity

Error

Message ID : CGS3264E

Long Form

LDT-ALERT: Cannot enable guard point [{0}] due to inconsistencies in underlying file system encountered during LDT recovery.

Short Form

LDT-ALERT: LDT recovery failure

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

Description

None

Message ID : CGS3304E

Severity

Error

Long Form

IDT-TD-ALERT: Node {0} did not respond to pcl command

Message ID : CGS3266E

Short Form

IDT-TD-ALERT: Remote node did not respond to pcl

Parameters

Label	CEF Label	Type	Usage
shost	shost	Text	Source host name

Description

None

Message ID : CGS3305E

Severity

Error

Long Form

IDT-TD-ALERT: Node {0} failed to perform voradmin task

Short Form

IDT-TD-ALERT: voradmin failed on remote node

Message ID : CGS3304E

Parameters

Label	CEF Label	Type	Usage
shost	shost	Text	Source host name

Description

None

Message ID : CGS3306E

Severity

Error

Long Form

IDT-TD-ALERT: Failed to find clique for disk {0}

Short Form

IDT-TD-ALERT: Failed to find clique

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

Message ID : CGS3305E

Label	CEF Label	Type	Usage

Description

None

Message ID : CGS3307E

Severity

Error

Long Form

IDT-TD-ALERT: Failed to distribute IDT-Capable metadata file to remote nodes

Short Form

IDT-TD-ALERT: Failed to distribute IDT-Capable metadata

Parameters

No parameters are provided for this message type

Description

None

Message ID : CGS3306E

Message ID : CGS3308E

Severity

Error

Long Form

IDT-TD-ALERT: Failed to move or rename IDT-Capable metadata file on remote nodes

Short Form

IDT-TD-ALERT: Failed to move or rename IDT-Capable metadata

Parameters

No parameters are provided for this message type

Description

None

Message ID : CGS3309E

Severity

Error

Long Form

IDT-TD-ALERT: Failed to get GuardPoint status on remote nodes

Short Form

IDT-TD-ALERT: Failed to get GuardPoint status

Parameters

No parameters are provided for this message type

Description

None

Message ID : CGS3311E

Severity

Error

Long Form

IDT-TD-ALERT: Failed to complete rekey on remote nodes

Short Form

IDT-TD-ALERT: Failed to complete rekey

Parameters

No parameters are provided for this message type

Description

None

Message ID : CGS3312E

Severity

Error

Long Form

LDT-NFS-ALERT: Host waiting to take over NFS GuardPoint {0} for LDT

Short Form

Waiting to take over

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

Description

None

Message ID : CGS3313E

Severity

Error

Long Form

LDT-ALERT: Cannot enable GuardPoint due to wrong policy applied to {{0}}

Short Form

Incorrect policy

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

Message ID : CGS3312E

Label	CEF Label	Type	Usage

Description

None

Message ID : CGS3314E

Severity

Error

Long Form

LDT: Cannot enable [{0}] due to stale policy

Short Form

LDT: stale policy

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

Description

None

Message ID : CGS3315E

Severity

Error

Long Form

LDT-NFS-ALERT: Cannot enable GuardPoint [{0}] on a read-only file system

Short Form

LDT-NFS: Guarding ROFS

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

Description

None

Message ID : CGS3314E

Message ID : CGS3316E

Severity

Error

Long Form

LDT-ALERT: Failed to process directory rename for {0}, error {1}

Short Form

LDT: dir rename failed

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory
ecode	cn1	Numeric	An error code

Description

None

Message ID : CGS3317E

Severity

Error

Long Form

LDT-ALERT: Failed to rekey {0} file(s) in directory {1}

Short Form

LDT: dir rekey errors

Parameters

Label	CEF Label	Type	Usage
count	vds_count	Numeric	A generic count value
gp	fileId	Text	Guardpoint base directory

Description

None

Message ID : CGS3319E

Severity

Error

Long Form

LDT-NFS-ALERT: Failed to start or stop rekey on GuardPoint [{0}] over NAS, error [{1}]

Short Form

LDT-NFS-ALERT: start or stop failed

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory
ecode	cn1	Numeric	An error code

Description

None

Message ID : CGS3327E

Severity

Error

Long Form

LDT-ALERT: Election of this host for LDT Group Primary role has failed for GuardPoint [{0}]

Short Form

LDT-NFS-ALERT: primary election failed

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

Description

None

Message ID : CGS3328E

Severity

Error

Long Form

LDT-NFS-ALERT: File operation recovery failed on new primary host after primary election, GuardPoint [{{0}}] objID [%llu] error [{{1}}] source [{{2}}]

Short Form

LDT-NFS-ALERT: fop recovery failed

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory
node	vds_node	Numeric	A node identifier
ecode	cn1	Numeric	An error code
count	vds_count	Numeric	A generic count value

Description

None

Message ID : CGS3329E

Severity

Error

Long Form

LDT-NFS-ALERT: LDT recovery failed on new primary host after primary election, GuardPoint [{0}] objID [%llu] error [{1}]

Short Form

LDT-NFS-ALERT: LDT recovery failed

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory
node	vds_node	Numeric	A node identifier
ecode	cn1	Numeric	An error code

Description

None

Message ID : CGS3331E

Severity

Error

Long Form

LDT-NFS-ALERT: File operation failed on secondary host, GuardPoint [{0}] objID [%llu] error [{1}] source [{2}]

Short Form

LDT-NFS-ALERT: fop failed on secondary

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory
node	vds_node	Numeric	A node identifier
ecode	cn1	Numeric	An error code
count	vds_count	Numeric	A generic count value

Description

None

Message ID : CGS3335E

Severity

Error

Long Form

LDT-ALERT: Failed to check rekey status on file {0}, error {1}

Short Form

LDT: monitor failed

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file
ecode	cn1	Numeric	An error code

Description

None

Message ID : CGS3336E

Severity

Error

Long Form

LDT-ALERT: Failed to enable/apply GuardPoint [{0}]

Short Form

Guard failed

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

Description

None

Message ID : CGS3337E

Severity

Error

Long Form

LDT-ALERT: Failed to disable/delete GuardPoint [{0}]

Short Form

Unguard failed

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

Description

None

Message ID : CGS3338E

Severity

Error

Message ID : CGS3337E

Long Form

LDT-ALERT: Failed to join GuardPoint group [{0}]

Short Form

LGS join failed

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

Description

None

Message ID : CGS3339E

Severity

Error

Long Form

LDT-ALERT: Failed to leave GuardPoint group [{0}]

Message ID : CGS3338E

Short Form

LGS leave failed

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

Description

None

Message ID : CGS3340E

Severity

Error

Long Form

LDT-ALERT: Failed to enumerate GuardPoint [{0}], please verify the provided CIFS credentials. CIFS credentials may be expired or may not have permission to access.

Short Form

Invalid creds

Message ID : CGS3339E

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

Description

None

Message ID : CGS3341E

Severity

Error

Long Form

LDT-ALERT: Failed to authenticate a user.

Short Form

CIFS Login error

Parameters

No parameters are provided for this message type

Message ID : CGS3340E

Description

None

Message ID : CGS3342E

Severity

Error

Long Form

LDT-NFS-ALERT: Error processing LDTTC message for GuardPoint [{0}], error [{1}], source [{2}]

Short Form

LDT-NFS-ALERT: bad msg

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory
ecode	cn1	Numeric	An error code
count	vds_count	Numeric	A generic count value

Description

None

Message ID : CGS3344E

Severity

Error

Long Form

LDT-NFS-ALERT: Not guarding path [{}] (Reason: LDT version installed on host is incompatible with version on primary host)

Short Form

LDT-NFS-ALERT: msg ver mismatch

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

Description

None

Message ID : CGS3342E

Logger CGS: Information

Message ID : CGS3029I

Severity

Information

Long Form

LDT: Cannot enable guard point [{}] during LDT clean-up process

Short Form

LDT: EA removing

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

Description

None

Message ID : CGS3030I

Severity

Information

Long Form

LDT: Successfully rekeyed file [{}]

Short Form

Successfully rekeyed

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : CGS3036I

Severity

Information

Long Form

LDT: Successfully suspended rekey on guard point [{0}]

Short Form

LDT: suspend success

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

Description

None

Message ID : CGS3037I

Severity

Information

Message ID : CGS3036I

Long Form

LDT: Rekey will be suspended on all applicable guard points

Short Form

LDT: suspend success: all

Parameters

No parameters are provided for this message type

Description

None

Message ID : CGS3040I

Severity

Information

Long Form

LDT: Successfully resumed rekey on guard point [{}]

Short Form

LDT: resume success

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

Description

None

Message ID : CGS3041I

Severity

Information

Long Form

LDT: Rekey will be resumed on all applicable guard points

Short Form

LDT: resume success: all

Message ID : CGS3040I

Parameters

No parameters are provided for this message type

Description

None

Message ID : CGS3046I

Severity

Information

Long Form

LDT-ALERT: Suspending rekey of binary file [{0}] during its execution

Short Form

LDT:SFS EXTBUSY

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : CGS3056I

Severity

Information

Long Form

LDT: Rekey operation completed on guard point [{}]

Short Form

LDT: completed

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

Description

None

Message ID : CGS3046I

Message ID : CGS3249I

Severity

Information

Long Form

LDT-ALERT: Skipped key rotation on guard point [{0}] on a read-only file system

Short Form

LDT: Skipped ROFS

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

Description

None

Message ID : CGS3250I

Severity

Information

Long Form

LDT-ALERT: Skipped key rotation on guard point [{0}] due to insufficient disk space

Short Form

LDT: Skipped ENOSPC

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

Description

None

Message ID : CGS3251I

Severity

Information

Message ID : CGS3250I

Long Form

LDT-ALERT: Skipped key rotation on guard point [{0}] while another rekey operation is in progress

Short Form

LDT: Skipped EBUSY

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

Description

None

Message ID : CGS3254I

Severity

Information

Long Form

LDT: Metadata will start getting removed from all files in guard point [{0}]

Message ID : CGS3251I

Short Form

Extended attr will be deleted from gp

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

Description

None

Message ID : CGS3255I

Severity

Information

Long Form

LDT: Metadata has been removed from all files in guard point [{}]

Short Form

Extended attr deleted from gp

Message ID : CGS3254I

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

Description

None

Message ID : CGS3277I

Severity

Information

Long Form

LDT-ALERT: Low space on guard point [{0}], increase free space or LDT will be suspended.

Short Form

low disk

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

Message ID : CGS3255I

Label	CEF Label	Type	Usage

Description

None

Message ID : CGS3318I

Severity

Information

Long Form

LDT-NFS-ALERT: Failed to preserve time stamps: GuardPoint [{0}] objID [{1}] error [{2}]

Short Form

LDT-NFS-ALERT: PTS Access

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory
node	vds_node	Numeric	A node identifier

Message ID : CGS3277I

Label	CEF Label	Type	Usage
ecode	cn1	Numeric	An error code

Description

None

Message ID : CGS3320I

Severity

Information

Long Form

LDT: Skipping transformation of NOVIEW file [{0}]. File was opened with NOVIEW access.

Short Form

LDT: Skipping NOVIEW

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Message ID : CGS3318I

Description

None

Message ID : CGS3322I

Severity

Information

Long Form

LDT-NFS-ALERT: LDT Communication Master is up

Short Form

LDT-NFS-ALERT: comm group master up

Parameters

No parameters are provided for this message type

Description

None

Message ID : CGS3320I

Message ID : CGS3324I

Severity

Information

Long Form

LDT-NFS-ALERT: LDT Group Primary host has been elected for GuardPoint [{0}]

Short Form

LDT-NFS-ALERT: group primary elected

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

Description

None

Message ID : CGS3325I

Severity

Information

Long Form

LDT-NFS-ALERT: This host has been promoted to LDT Group Primary role for GuardPoint [{0}]

Short Form

LDT-NFS-ALERT: group primary promoted

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

Description

None

Logger CGS: Warnings

Message ID : CGS3267W

Severity

Warning

Long Form

LDT-ALERT: LDT manual recovery on guard point [{0}] completed with [{1}] errors.

Short Form

LDT-ALERT: LDT manual recovery forced

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory
count	vds_count	Numeric	A generic count value

Description

None

Message ID : CGS3268W

Severity

Warning

Long Form

LDT-ALERT: encrypted data detected in filename [{0}] inode [%lld] in guard point [{1}] under clear exclusion key rule

Short Form

LDT-ALERT: encrypted data in clear file

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file
node	vds_node	Numeric	A node identifier
gp	fileId	Text	Guardpoint base directory

Description

None

Message ID : CGS3302W

Severity

Warning

Long Form

LDT-ALERT: Rekey is restarting due to previous transient error on guard point [{0}]. Error: [{1}]

Short Form

Res acc issue

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory
ecode	cn1	Numeric	An error code

Description

None

Message ID : CGS3303W

Severity

Warning

Long Form

LDT-ALERT: Rekey is restarting due to previous transient error on guard point [{0}]. Error: [{1}] Reason: [{2}]

Short Form

Res acc issue desc

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory
ecode	cn1	Numeric	An error code
showStr	reason	Text	Code specifying reason for allowing access, if any

Description

None

Message ID : CGS3310W

Severity

Warning

Long Form

IDT-TD-WARNING: Failed to delete IDT-Capable metadata file on remote nodes

Short Form

IDT-TD-WARNING: Failed to delete IDT-Capable metadata

Parameters

No parameters are provided for this message type

Description

None

Message ID : CGS3321W

Severity

Warning

Long Form

LDT-NFS-ALERT: LDT Communication Master is down

Short Form

LDT-NFS-ALERT: Comm group master down

Parameters

No parameters are provided for this message type

Description

None

Message ID : CGS3323W

Severity

Warning

Long Form

LDT-NFS-ALERT: LDT Group Primary host left the group for GuardPoint [{}]

Short Form

LDT-NFS-ALERT: group primary left

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

Description

None

Message ID : CGS3326W

Severity

Warning

Long Form

LDT-NFS-ALERT: This host cannot be promoted to LDT Group Primary role for GuardPoint [{0}]

Short Form

LDT-NFS-ALERT: refused primary role

Message ID : CGS3323W

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

Description

None

Message ID : CGS3330W

Severity

Warning

Long Form

LDT-NFS-ALERT: Promotion process taking too long causing delay in file operation, GuardPoint [{0}] objID [%llu]

Short Form

LDT-NFS-ALERT: Promotion taking too long

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

Message ID : CGS3326W

Label	CEF Label	Type	Usage
node	vds_node	Numeric	A node identifier

Description

None

Message ID : CGS3332W

Severity

Warning

Long Form

LDT-NFS-ALERT: Some members of LDT GuardPoint Group for [{0}] have not received latest key version

Short Form

LDT-NFS-ALERT: group doesn't have the same key

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

Message ID : CGS3330W

Description

None

Message ID : CGS3333W

Severity

Warning

Long Form

LDT-NFS-ALERT: Lazy rekey operation failed to rekey file [{0}], error [{1}]

Short Form

LDT-NFS-ALERT: lazy rekey failed

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file
ecode	cn1	Numeric	An error code

Message ID : CGS3332W

Description

None

Message ID : CGS3334W

Severity

Warning

Long Form

LDT-NFS-ALERT: LDT remote operation failed across LDT GuardPoint Group for GuardPoint [{0}], ino [%lld], filename [{1}], error [{2}], remote op [{3}]

Short Form

LDT-NFS-ALERT: remote op failed

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory
node	vds_node	Numeric	A node identifier
filePath	filePath	Text	Full path to file
ecode	cn1	Numeric	An error code

Message ID : CGS3333W

Label	CEF Label	Type	Usage
count	vds_count	Numeric	A generic count value

Description

None

Logger CMG: Information

Message ID : CMG1150I

Severity

Information

Long Form

Please [login to DSM server](#) to view the "Certificates" report for detail.

Short Form

No short form is provided for this message type

Description

None

Logger CMG: Warnings

Message ID : CMG1100W

Severity

Warning

Long Form

{0} certificates will expire {2} {1} days.

Short Form

cert will expire

Parameters

Label	CEF Label	Type	Usage
cert	vds_cert	Text	Certificate type or name

Description

Vormetric agents use certificates to authenticate them with the Security Server. These certificates are created during the registration process after the agent is installed and are valid for one year. They automatically renew 60 days before expiration. No action is required.

Message ID : CMG1101W

Severity

Warning

Long Form

{0} certificate key will expire {2} {1} days.

Short Form

cert key will expire

Parameters

Label	CEF Label	Type	Usage
cert	vds_cert	Text	Certificate type or name

Description

Vormetric agents use certificates to authenticate them with the Security Server. These certificates are created during the registration process after the agent is installed and are valid for one year. They automatically renew 60 days before expiration. No action is required.

Message ID : CMG1120W

Severity

Warning

Long Form

{0} certificates have been expired for {1} days.

Short Form

cert expired

Parameters

Label	CEF Label	Type	Usage
cert	vds_cert	Text	Certificate type or name

Description

Vormetric agents use certificates to authenticate them with the Security Server. These certificates are created during the registration process after the agent is installed and are valid for one year. They automatically renew 60 days before expiration. No action is required.

Message ID : CMG1121W

Severity

Warning

Long Form

{0} certificate has been expired for {1} days.

Short Form

cert key expired

Parameters

Label	CEF Label	Type	Usage
cert	vds_cert	Text	Certificate type or name

Description

Vormetric agents use certificates to authenticate them with the Security Server. These certificates are created during the registration process after the agent is installed and are valid for one year. They automatically renew 60 days before expiration. No action is required.

Logger COM: Errors

Message ID : COM0002E

Severity

Error

Long Form

The Security Server failed to validate the data received from the Agent on host {1} for the policy evaluation request. Reason is {0}.

Short Form

No short form is provided for this message type

Description

None

Message ID : COM0003E

Severity

Error

Long Form

Timestamp is {0}. Timestamp format should be yyyy-mm-dd hh:mm:ss.

Short Form

No short form is provided for this message type

Description

None

Message ID : COM0005E

Severity

Error

Long Form

The Security server received a request from agent on host {0} for loggers. The Security Server failed to obtain any loggers. The Agent will be shut down.

Short Form

No short form is provided for this message type

Message ID : COM0003E

Description

None

Message ID : COM0174E**Severity**

Error

Long Form

The Security Server was unable to contact the agent on host {0}. Directory information will not be displayed.

Short Form

No short form is provided for this message type

Description

None

Message ID : COM0175E**Severity**

Error

Message ID : COM0005E

Long Form

The Security Server was unable to obtain directory information from host {0}. Directory information will not be displayed.

Short Form

No short form is provided for this message type

Description

None

Message ID : COM0271E

Severity

Error

Long Form

The Security Server was unable to contact the agent on host {0}. Host information will not be displayed.

Short Form

No short form is provided for this message type

Description

None

Message ID : COM0272E

Severity

Error

Long Form

The Security Server was unable to contact the agent on host {0}. The latest security configuration will not be sent to the host.

Short Form

No short form is provided for this message type

Description

None

Message ID : COM0275E

Severity

Error

Message ID : COM0271E

Long Form

The Security Server was unable to initialize communication with the agent on host {0}. The server and agent will not be able to communicate.

Short Form

No short form is provided for this message type

Description

None

Message ID : COM0300E

Severity

Error

Long Form

The Security Server was unable to contact the file system agent on host {0} for deletion. The host record will not be deleted from the server database. De-select the file system agent registration checkbox to delete the host record from the database without contacting the file system agent.

Short Form

No short form is provided for this message type

Description

None

Message ID : COM0303E

Severity

Error

Long Form

The Security Server failed to contact host {0} after {1} tries. An update will be pushed to the host if the management service (vmd) at the host is re-initialized or with the next policy change affecting the host.

Short Form

No short form is provided for this message type

Description

None

Message ID : COM0300E

Message ID : COM0312E

Severity

Error

Long Form

The Security Server was unable to contact {0}.

Short Form

No short form is provided for this message type

Description

None

Message ID : COM0313E

Severity

Error

Long Form

The Security Server failed to contact host {0}. The Security Server will make another attempt to contact the host at approximately {1}.

Message ID : COM0312E

Short Form

failed to contact host

Parameters

Label	CEF Label	Type	Usage
shost	shost	Text	Source host name
nexttime	vds_nexttime	Text	Time of next attempt

Description

Wait for server to retry. If failure persists check for a network problem or the agent may be shut down.

Message ID : COM0429E

Severity

Error

Long Form

The Security Server was unable to determine the communication version for host {0}. Directory information will not be displayed.

Short Form

No short form is provided for this message type

Description

None

Message ID : COM0430E

Severity

Error

Long Form

The Security Server was unable to determine the communication version for host {0}. The latest security configuration will not be sent to the host.

Short Form

No short form is provided for this message type

Description

None

Message ID : COM0429E

Message ID : COM0431E

Severity

Error

Long Form

The Security Server is too old for the agent on host {0}. Agent min version supported is {1}. Server max version supported is {2}. The Server and Agent will not be able to communicate. Ensure that server and agent versions are compatible.

Short Form

No short form is provided for this message type

Description

None

Message ID : COM0432E

Severity

Error

Long Form

The agent on host {0} is too old for the Security Server. Agent max version supported is {1}. Server min version supported is {2}. The Server and Agent will not be able to communicate. Ensure that server and agent versions are compatible.

Short Form

No short form is provided for this message type

Description

None

Message ID : COM0433E

Severity

Error

Long Form

The Security Server is unable to obtain the communication version from the database for the agent on host {0}. The server and agent will not be able to communicate. Ensure that the database is functional.

Short Form

No short form is provided for this message type

Message ID : COM0432E

Description

None

Message ID : COM0434E

Severity

Error

Long Form

The Security Server is unable to negotiate a communication version with the agent on host {0} because host information cannot be retrieved from the database. The server and agent will not be able to communicate. Ensure that the database is functional.

Short Form

No short form is provided for this message type

Description

None

Message ID : COM0435E

Severity

Error

Long Form

A roll back has been detected for the agent on host {0}. Agent min/max: {1}/{2}. Min/max for host in the database: {3}/{4}. The server and agent will not be able to communicate. The agent must be upgraded or the agent must re-register with the Server.

Short Form

No short form is provided for this message type

Description

None

Message ID : COM0436E

Severity

Error

Long Form

The negotiated version {0} from the database for the agent on host {1} is not in the min/max range of agent: {2}/{3}. The Server and Agent will not be able to communicate. Ensure that server and agent versions are compatible.

Message ID : COM0435E

Short Form

No short form is provided for this message type

Description

None

Message ID : COM0506E

Severity

Error

Long Form

The Security Server received a fault message from the agent at host {0}. The errorcode {1} sent by the agent is not recognized by the server. Please ensure that the agent and server versions are matching.

Short Form

No short form is provided for this message type

Description

None

Message ID : COM0436E

Message ID : COM0507E

Severity

Error

Long Form

The Security Server detected an Internal error from the agent at host {0}. Please check the agent logs.

Short Form

No short form is provided for this message type

Description

None

Message ID : COM0508E

Severity

Error

Long Form

The Security Server was unable to browse the directory {0} at host {1}. The directory name is invalid. Browse information will not be displayed.

Message ID : COM0507E

Short Form

No short form is provided for this message type

Description

None

Message ID : COM0509E

Severity

Error

Long Form

The Security Server detected a "failed to implement security configuration from the agent at host {0}". Please check the agent logs.

Short Form

No short form is provided for this message type

Description

None

Message ID : COM0510E

Severity

Error

Long Form

The Security Server detected a "failed to query security configuration" from the agent at host {0}". Please check the agent logs.

Short Form

No short form is provided for this message type

Description

None

Message ID : COM0511E

Severity

Error

Long Form

The Security Server detected a "Failed to delete host" from the agent at host {0}". Please check the agent logs.

Short Form

No short form is provided for this message type

Description

None

Message ID : COM0512E

Severity

Error

Long Form

The Security Server was unable to browse the directory {0} from host {1}. Network path {2} was either typed incorrectly, does not exist, or the network provider is not currently available. Please ensure that the network path is valid.

Short Form

No short form is provided for this message type

Description

None

Message ID : COM0511E

Message ID : COM0513E

Severity

Error

Long Form

The Security Server was unable to browse the directory {0} from host {1}. Unknown user name {2} under domain {3} or bad password. Please ensure that the user name, domain and password are valid.

Short Form

No short form is provided for this message type

Description

None

Message ID : COM0514E

Severity

Error

Long Form

The Security Server was unable to browse the directory {0} from host {1}. Network path {2} cannot be found. Please ensure that the network path exists.

Short Form

No short form is provided for this message type

Description

None

Message ID : COM0515E

Severity

Error

Long Form

The Security Server was unable to browse the directory {0} from host {1}. Failed to enumerate network resource {2}. Please check the agent logs.

Short Form

No short form is provided for this message type

Message ID : COM0514E

Description

None

Message ID : COM0516E

Severity

Error

Long Form

The Security Server was unable to browse the directory {0} from host {1}. Multiple connections to network resource {2} by user {3} under domain {4} are not allowed. Disconnect all previous connections to the server or shared resource and try again.

Short Form

No short form is provided for this message type

Description

None

Message ID : COM0536E

Severity

Error

Long Form

The Security Server was unable to contact host {0}. If the hostname has been recently modified, the security server may still be aware of the previous hostname. Restarting the security server may clear up this condition.

Short Form

No short form is provided for this message type

Description

None

Message ID : COM0537E

Severity

Error

Long Form

The Security Server was unable to contact the agent on host {0}. The agent is refusing connections. Please ensure that the agent is up and running.

Message ID : COM0536E

Short Form

No short form is provided for this message type

Description

None

Message ID : COM0539E

Severity

Error

Long Form

The Security Server was unable to retrieve the data for host {0} from the database. Refer to cgss.log and server.log for details. Call support if necessary.

Short Form

No short form is provided for this message type

Description

None

Message ID : COM0537E

Message ID : COM0540E

Severity

Error

Long Form

The Security Server failed to invoke the command line interface with the following error message: {0}.

Short Form

No short form is provided for this message type

Description

None

Message ID : COM0541E

Severity

Error

Long Form

The upgrade package file has been successfully uploaded to the server. Since Thales HSM firmware upgrade is required, you must run "maintenance sysupgrade" from the DSM CLI to continue the upgrade process.

Message ID : COM0540E

Short Form

No short form is provided for this message type

Description

None

Message ID : COM0542E

Severity

Error

Long Form

The Security Server is unable to send configuration changes to the agent at host {0}. The agent does not support the guarding of raw devices. Please disable or un-guard the raw devices or update the agent software.

Short Form

No short form is provided for this message type

Description

None

Message ID : COM0541E

Message ID : COM0543E

Severity

Error

Long Form

The Security Server was unable to perform {0} operation. Refer to the DSM logs for more information.

Short Form

No short form is provided for this message type

Description

None

Message ID : COM0555E

Severity

Error

Long Form

The Security Server was unable to contact the agent on host {0}. User information will not be displayed.

Short Form

No short form is provided for this message type

Description

None

Message ID : COM0556E

Severity

Error

Long Form

The Security Server was unable to obtain user information from host {0}. User information will not be displayed.

Short Form

No short form is provided for this message type

Description

None

Message ID : COM0557E

Severity

Error

Long Form

The Security Server was unable to browse the domain {0} from host {1}. Invalid user name, domain name or password.

Short Form

No short form is provided for this message type

Description

None

Message ID : COM0558E

Severity

Error

Long Form

The Security Server was unable to browse the domain {0} from host {1}. The directory service is unavailable.

Short Form

No short form is provided for this message type

Description

None

Message ID : COM0588E

Severity

Error

Long Form

The Security Server is waiting for the signature data from host {0}. Communication between Server and host cannot proceed.

Short Form

No short form is provided for this message type

Description

None

Message ID : COM0558E

Message ID : COM0589E

Severity

Error

Long Form

The Security Server is waiting for the signature data from host {0}. The signature request may be rejected due to invalid file or directory name.

Short Form

No short form is provided for this message type

Description

None

Message ID : COM0590E

Severity

Error

Long Form

The Security Server received a signature message from the agent at host {0}. But the signature message is not in standard format.

Short Form

received bad signature message from agent

Parameters

Label	CEF Label	Type	Usage
shost	shost	Text	Source host name

Description

None

Message ID : COM0594E

Severity

Error

Long Form

The Security Server was unable to contact host {0}. The host name is defined by IP address, please use CLI command "network agentip show" to check if agent ip is enabled.

Message ID : COM0590E

Short Form

No short form is provided for this message type

Description

None

Message ID : COM0595E

Severity

Error

Long Form

The Security Server failed to contact host {0}. Please make sure the agent ip is enabled. The Security Server will make another attempt to contact the host at approximately {1}.

Short Form

server failed to contact host

Parameters

Label	CEF Label	Type	Usage
shost	shost	Text	Source host name

Message ID : COM0594E

Label	CEF Label	Type	Usage
nexttime	vds_nexttime	Text	Time of next attempt

Description

Allow host registration using IP address. Use CLI to enable Agentip under the Network menu.

Message ID : COM0600E

Severity

Error

Long Form

The Security Server is unable to contact the host {0}. The host may be down.

Short Form

No short form is provided for this message type

Description

None

Message ID : COM0601E

Severity

Error

Long Form

The Security Server received signature value that is more than 64 bytes on the file {0}.

Short Form

received signature value more than 64 bytes

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : COM0602E

Severity

Error

Long Form

The Security Server cannot push the signature(s) to the agent at host {0}. Communication between Server and host cannot proceed.

Short Form

No short form is provided for this message type

Description

None

Message ID : COM0603E

Severity

Error

Long Form

The Security Server cannot push the signature(s) to the agent at host {0}. The version of the agent does not support this operation.

Short Form

cannot push the signature(s) to agent

Parameters

Label	CEF Label	Type	Usage
shost	shost	Text	Source host name

Description

None

Message ID : COM0605E

Severity

Error

Long Form

The Security Server is sending the message of canceling signing process to the agent at host {0} because the user is deleting the signature set while the signing is in progress.

Short Form

sending signing cancelation to agent

Message ID : COM0603E

Parameters

Label	CEF Label	Type	Usage
shost	shost	Text	Source host name

Description

None

Message ID : COM0609E

Severity

Error

Long Form

The Security Server is unable to cancel the signing on the host {0} because the operation is timed out after 60000ms. Please try again at a later time.

Short Form

No short form is provided for this message type

Description

None

Message ID : COM0605E

Message ID : COM0613E

Severity

Error

Long Form

Invalid operation. The command {0} is not available on a failover server {1}.

Short Form

No short form is provided for this message type

Description

None

Message ID : COM0619E

Severity

Error

Long Form

The domain name is required.

Message ID : COM0613E

Short Form

No short form is provided for this message type

Description

None

Message ID : COM0620E

Severity

Error

Long Form

Either the domain description or help desk information is required.

Short Form

No short form is provided for this message type

Description

None

Message ID : COM0621E

Severity

Error

Long Form

The administrator name is required.

Short Form

No short form is provided for this message type

Description

None

Message ID : COM0622E

Severity

Error

Long Form

The domain is already assigned to a domain administrator.

Short Form

No short form is provided for this message type

Description

None

Message ID : COM0623E

Severity

Error

Long Form

The user type is not in DOMAIN, or DOMAIN_SECURITY, or ALL administrator.

Short Form

No short form is provided for this message type

Description

None

Message ID : COM0622E

Message ID : COM0627E

Severity

Error

Long Form

The domain {0} is not assigned to the user {1}.

Short Form

No short form is provided for this message type

Description

None

Message ID : COM0628E

Severity

Error

Long Form

Server failed to replicate configuration data to other server "{0}".

Short Form

failed to replicate configuration data to other server

Parameters

Label	CEF Label	Type	Usage
shost	shost	Text	Source host name

Description

None

Message ID : COM0650E

Severity

Error

Long Form

The Security Server was unable to contact server host {0} CA service. The host name is defined by IP address.

Short Form

No short form is provided for this message type

Message ID : COM0628E

Description

None

Message ID : COM0651E

Severity

Error

Long Form

The Security Server was unable to initialize communication with the {0} CA service. The server and CA service will not be able to communicate.

Short Form

No short form is provided for this message type

Description

None

Message ID : COM0652E

Severity

Error

Long Form

The Vormetric RA Failed to talk to the Certificate Authority service at {0}.

Short Form

ra failed contact Certificate Authority service

Parameters

Label	CEF Label	Type	Usage
shost	shost	Text	Source host name

Description

None

Message ID : COM0653E

Severity

Error

Message ID : COM0652E

Long Form

The Security Server was unable to contact the CA service on host {0}. The CA service is refusing connections. Please ensure that the CA service is up and running.

Short Form

No short form is provided for this message type

Description

None

Message ID : COM0660E

Severity

Error

Long Form

The Security Server could not find the syslog host {0}. All logging to the syslog host will FAIL.

Short Form

could not find syslog host

Parameters

Label	CEF Label	Type	Usage
shost	shost	Text	Source host name

Description

None

Message ID : COM0661E

Severity

Error

Long Form

The Security Server could not instantiate TCP socket to the syslog host {0}. All logging to the syslog host will FAIL.

Short Form

could not connect syslog host via TCP

Parameters

Label	CEF Label	Type	Usage
shost	shost	Text	Source host name

Message ID : COM0660E

Label	CEF Label	Type	Usage

Description

None

Message ID : COM0712E

Severity

Error

Long Form

The security server {0} failed to delete the host {1} upon the deletion request from the {2} agent because the {3}agents are still registered.

Short Form

failed to delete host

Parameters

Label	CEF Label	Type	Usage
shost	shost	Text	Source host name
shost	shost	Text	Source host name

Message ID : COM0661E

Label	CEF Label	Type	Usage
agent	deviceProcessName	Text	The short identifier of the agent software
showStr	reason	Text	Code specifying reason for allowing access, if any

Description

None

Message ID : COM0713E

Severity

Error

Long Form

The Security Server denied an unregister request from unauthorized host "{0}".

Short Form

denied unregister request from unauthorized host

Parameters

Label	CEF Label	Type	Usage
-------	-----------	------	-------

Message ID : COM0712E

Label	CEF Label	Type	Usage
shost	shost	Text	Source host name

Description

If host is authorized, Edit that host and select "Registration Allowed".

Message ID : COM0759E

Severity

Error

Long Form

The security server failed to obtain hardware status. The service call is not compatible with the appliance.

Short Form

No short form is provided for this message type

Description

None

Message ID : COM0772E

Severity

Error

Long Form

The communication is not enabled for key agent at host {0} on the security server. The operation will not proceed.

Short Form

No short form is provided for this message type

Description

None

Message ID : COM0805E

Severity

Error

Long Form

The user of the type {0} is not allowed to be assigned to the domain.

Short Form

No short form is provided for this message type

Description

None

Message ID : COM0900E

Severity

Error

Long Form

The domain quota value is required.

Short Form

No short form is provided for this message type

Description

None

Message ID : COM0901E

Severity

Error

Long Form

The administrator cannot modify his/her own role.

Short Form

No short form is provided for this message type

Description

None

Message ID : COM1257E

Severity

Error

Long Form

The domain name is too long. Please correct the problem and try again.

Short Form

No short form is provided for this message type

Description

None

Message ID : COM1263E

Severity

Error

Long Form

System administrator cannot be added to domain.

Short Form

No short form is provided for this message type

Description

None

Message ID : COM1257E

Message ID : COM1264E

Severity

Error

Long Form

Exceeded maximum batch size {0}.

Short Form

No short form is provided for this message type

Description

None

Message ID : COM1285E

Severity

Error

Long Form

Session not found: {0}

Message ID : COM1264E

Short Form

No short form is provided for this message type

Description

None

Message ID : COM1306E

Severity

Error

Long Form

Host {0} does NOT support Suite-B cipher suites.

Short Form

Host does NOT support Suite-B cipher suites

Parameters

Label	CEF Label	Type	Usage
shost	shost	Text	Source host name

Message ID : COM1285E

Description

None

Message ID : COM1307E

Severity

Error

Long Form

The batch size is less than 0.

Short Form

No short form is provided for this message type

Description

None

Message ID : COM1308E

Severity

Error

Message ID : COM1306E

Long Form

Another push using newer style.

Short Form

No short form is provided for this message type

Description

None

Message ID : COM1310E

Severity

Error

Long Form

Internal error. Refer to server.log for details.

Short Form

No short form is provided for this message type

Description

None

Message ID : COM1315E

Severity

Error

Long Form

The administrator cannot modify his/her own read-only attribute.

Short Form

No short form is provided for this message type

Description

None

Message ID : COM1321E

Severity

Error

Message ID : COM1310E

Long Form

Error in starting data transform

Short Form

No short form is provided for this message type

Description

None

Message ID : COM1322E

Severity

Error

Long Form

Error in stopping data transform

Short Form

No short form is provided for this message type

Message ID : COM1321E

Description

None

Message ID : COM1349E

Severity

Error

Long Form

The license type must be one of TERM, PERPETUAL or HOURLY.

Short Form

No short form is provided for this message type

Description

None

Message ID : COM1350E

Severity

Error

Message ID : COM1322E

Long Form

The validity period must be one of ONE_HOUR, ONE_DAY, ONE_WEEK or ONE_MONTH.

Short Form

No short form is provided for this message type

Description

None

Message ID : COM1367E

Severity

Error

Long Form

The security server does not have any backup schedules defined

Short Form

No short form is provided for this message type

Description

None

Message ID : COM1400E

Severity

Error

Long Form

Host {0} cannot be re-registered with LDT disabled. Delete the host from DSM and re-add it again

Short Form

No short form is provided for this message type

Description

None

Message ID : COM1401E

Severity

Error

Message ID : COM1367E

Long Form

Host {0} cannot be re-registered with Docker disabled. Delete the host from DSM and re-add it again

Short Form

No short form is provided for this message type

Description

None

Message ID : COM1402E

Severity

Error

Long Form

Host {0} cannot be registered. It's part of a host group that defines a guardpoint with enabled exclusion key rule in LDT policy. You need to upgrade the agent to version 6.2.0 or higher.

Short Form

No short form is provided for this message type

Description

None

Message ID : COM1403E

Severity

Error

Long Form

Host {0} cannot be re-registered with Cloud Object Storage disabled. Delete the host from DSM and re-add it again

Short Form

No short form is provided for this message type

Description

None

Message ID : COM1410E

Severity

Error

Message ID : COM1402E

Long Form

Host "{0}" does not support the CBC_CS1 encryption mode, you cannot re-register with a GuardPoint with a Policy that contains a key that uses this encryption mode.

Short Form

No short form is provided for this message type

Description

None

Message ID : COM1669E

Severity

Error

Long Form

Host {0} cannot be re-registered with "{1}" feature disabled. Delete the host from DSM and re-add it again

Short Form

No short form is provided for this message type

Description

None

Message ID : COM1692E

Severity

Error

Long Form

Host {0} cannot be re-registered with FF1 disabled. Delete the host from DSM and re-add it again

Short Form

No short form is provided for this message type

Description

None

Message ID : COM1740E

Severity

Error

Message ID : COM1669E

Long Form

Host fingerprint mismatch (fingerprintFromDB={0}, fingerprintFromCert={1}).

Short Form

No short form is provided for this message type

Description

None

Message ID : COM1741E

Severity

Error

Long Form

Invalid client certificate from host {0}.

Short Form

No short form is provided for this message type

Message ID : COM1740E

Description

None

Message ID : COM1744E

Severity

Error

Long Form

Agent from host "{0}" is not allowed to perform operation "{1}" on host "{2}".

Short Form

No short form is provided for this message type

Description

None

Message ID : COM4547E

Severity

Error

Message ID : COM1741E

Long Form

Internal error: Invalid configuration type given to communications subsystem. Contact support.

Short Form

No short form is provided for this message type

Description

None

Message ID : COM4631E

Severity

Error

Long Form

OPENSSL ERROR: {0}

Short Form

OpenSSL error

Parameters

Label	CEF Label	Type	Usage
showStr	reason	Text	Code specifying reason for allowing access, if any

Description

None

Message ID : COM4638E

Severity

Error

Long Form

We have detected a change in the system hardware. Communication to the DSM has been disabled. This condition can be fixed by re-registering this agent with the DSM.

Short Form

Hardware Change

Parameters

No parameters are provided for this message type

Message ID : COM4631E

Description

None

Message ID : COM4644E

Severity

Error

Long Form

An invalid REST object has been received - {0}

Short Form

Bad REST object

Parameters

Label	CEF Label	Type	Usage
detail	vds_detail	Text	Fault detail

Description

None

Message ID : COM4638E

Logger COM: Fatal errors

Message ID : COM0004F

Severity

Fatal error

Long Form

The Security Server failed to initialize upon startup. The Security Server could not retrieve its configuration parameters. Verify that the Security Server database is functional. If the problem persists, contact support.

Short Form

No short form is provided for this message type

Description

None

Message ID : COM4503F

Severity

Fatal error

Long Form

Communications module initialization failure. Contact support.

Short Form

Comms init fail

Parameters

No parameters are provided for this message type

Description

None

Message ID : COM4506F

Severity

Fatal error

Long Form

Failed to set up logger "{0}". Contact support.

Short Form

Logger setup error

Parameters

Label	CEF Label	Type	Usage
showStr	reason	Text	Code specifying reason for allowing access, if any

Description

None

Message ID : COM4511F

Severity

Fatal error

Long Form

The communication request to the Key Manager was garbled or otherwise incorrect: error {0}. Contact support.

Short Form

Bad policy request

Message ID : COM4506F

Parameters

Label	CEF Label	Type	Usage
ecode	cn1	Numeric	An error code

Description

None

Message ID : COM4512F

Severity

Fatal error

Long Form

Policy response garbled: unable to find attribute "{0}".

Short Form

Resp attr missing

Parameters

Label	CEF Label	Type	Usage
showStr	reason	Text	Code specifying reason for allowing access, if any

Message ID : COM4511F

Label	CEF Label	Type	Usage

Description

None

Message ID : COM4513F

Severity

Fatal error

Long Form

Unable to configure secure communication channel. Contact support.

Short Form

No short form is provided for this message type

Description

None

Message ID : COM4512F

Message ID : COM4514F

Severity

Fatal error

Long Form

The communication request to the Key Manager was garbled or otherwise incorrect: error {0}. Contact support.

Short Form

Server init req error

Parameters

Label	CEF Label	Type	Usage
ecode	cn1	Numeric	An error code

Description

None

Message ID : COM4515F

Severity

Fatal error

Long Form

There was a communication failure with the Key Manager. The server returned a fault: {0}{1}; "{2}"; Subcode: "{3}"; Reason: "{4}"; Detail: "{5}".

Short Form

No short form is provided for this message type

Description

None

Message ID : COM4521F

Severity

Fatal error

Long Form

Internal version not supported, version required: {0}.

Short Form

Bad SDK version

Parameters

Label	CEF Label	Type	Usage
version	vds_version	Text	Software version string

Description

None

Message ID : COM4523F

Severity

Fatal error

Long Form

Unable to establish a connection to a Key Manager for the purpose of policy evaluation. Verify that the configuration file has the correct URL(s) to the server.

Short Form

Policy info missing

Message ID : COM4521F

Parameters

No parameters are provided for this message type

Description

None

Message ID : COM4527F

Severity

Fatal error

Long Form

The Agent could not obtain configuration information. The Agent failed to initialize. Verify connectivity to the Key Manager and retry the operation.

Short Form

Agent config missing

Parameters

No parameters are provided for this message type

Description

None

Message ID : COM4529F

Severity

Fatal error

Long Form

Unable to establish an initial connection to any Key Manager. Verify that the configuration file has the correct URL(s) to the server.

Short Form

No config from server

Parameters

No parameters are provided for this message type

Description

None

Message ID : COM4531F

Severity

Fatal error

Long Form

Unable to configure secure communication channel. Contact support.

Short Form

SSL setup fail

Parameters

No parameters are provided for this message type

Description

None

Message ID : COM4533F

Severity

Fatal error

Long Form

{0} from file does not match that from backup. File: "{1}". Backup: "{2}".

Short Form

Backup opaque data mismatch

Parameters

No parameters are provided for this message type

Description

None

Message ID : COM4534F

Severity

Fatal error

Long Form

File type mismatch: {0} must be a directory.

Short Form

Not a dir

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : COM4538F

Severity

Fatal error

Long Form

The Key Manager URL ({0}) must start with "https:".

Short Form

Invalid URL

Message ID : COM4534F

Parameters

Label	CEF Label	Type	Usage
url	request	Text	A uniform resource location

Description

None

Message ID : COM4542F

Severity

Fatal error

Long Form

The agent could not allocate enough memory. Contact support.

Short Form

Out of memory

Parameters

No parameters are provided for this message type

Message ID : COM4538F

Description

None

Message ID : COM4548F

Severity

Fatal error

Long Form

Policy request garbled: unable to find attribute "{0}".

Short Form

Req attr missing

Parameters

Label	CEF Label	Type	Usage
showStr	reason	Text	Code specifying reason for allowing access, if any

Description

None

Message ID : COM4542F

Message ID : COM4551F

Severity

Fatal error

Long Form

The Agent failed to initialize, reporting "{0}". Verify the logging configuration on the Key Manager and retry the operation. If the problem persists, contact support.

Short Form

Agent init error

Parameters

Label	CEF Label	Type	Usage
showStr	reason	Text	Code specifying reason for allowing access, if any

Description

None

Message ID : COM4552F

Severity

Fatal error

Long Form

Communication with the Key Manager was established, but an invalid response (error {0}) was received. The requested operation cannot continue. Contact support.

Short Form

Bad policy response

Parameters

Label	CEF Label	Type	Usage
ecode	cn1	Numeric	An error code

Description

None

Message ID : COM4554F

Severity

Fatal error

Message ID : COM4552F

Long Form

Communication with the Key Manager was established, but an invalid response (error {0}) was received. The requested operation cannot continue. Contact support.

Short Form

Comms response error

Parameters

Label	CEF Label	Type	Usage
ecode	cn1	Numeric	An error code

Description

None

Message ID : COM4558F

Severity

Fatal error

Long Form

Key Manager communications failure. URL: {0}. Check the URL in the agent.conf file. Verify that the server url is correct and retry

Message ID : COM4554F

the operation.

Short Form

Bad config from server

Parameters

Label	CEF Label	Type	Usage
url	request	Text	A uniform resource location

Description

None

Message ID : COM4562F

Severity

Fatal error

Long Form

The communication request to the Key Manager was garbled or otherwise incorrect: error {0}. Contact support.

Short Form

Comms init error

Parameters

Label	CEF Label	Type	Usage
ecode	cn1	Numeric	An error code

Description

None

Message ID : COM4563F

Severity

Fatal error

Long Form

Key Manager connection failure. Check the URL in the agent.conf file. Verify that the server url is correct and retry the operation.

Short Form

No short form is provided for this message type

Message ID : COM4562F

Description

None

Message ID : COM4567F

Severity

Fatal error

Long Form

Communication with the Key Manager was established, but an invalid response (error {0}) was received. The requested operation cannot continue. Contact support.

Short Form

SDK response error

Parameters

Label	CEF Label	Type	Usage
ecode	cn1	Numeric	An error code

Description

None

Message ID : COM4563F

Message ID : COM4569F

Severity

Fatal error

Long Form

The Key Manager URL is too long. It is {0} characters, while the maximum size is {1} characters. The URL is {2}.

Short Form

URL too long

Parameters

Label	CEF Label	Type	Usage
slen	in	Numeric	Input byte count or length
dlen	out	Numeric	Output byte count or length
url	request	Text	A uniform resource location

Description

None

Message ID : COM4571F

Severity

Fatal error

Long Form

File access failure: Unable to open {0}: {1}.

Short Form

Open error

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file
showStr	reason	Text	Code specifying reason for allowing access, if any

Description

None

Message ID : COM4577F

Severity

Fatal error

Long Form

Error adding host {0} information to server.

Short Form

No short form is provided for this message type

Description

None

Message ID : COM4578F

Severity

Fatal error

Long Form

Request from {0} to add host is invalid.

Short Form

No short form is provided for this message type

Description

None

Message ID : COM4579F

Severity

Fatal error

Long Form

Response to add host request from {0} is invalid: {1}.

Short Form

No short form is provided for this message type

Description

None

Message ID : COM4578F

Message ID : COM4583F

Severity

Fatal error

Long Form

Error initializing agent.

Short Form

Agent init fail

Parameters

No parameters are provided for this message type

Description

The agent is unable to reach the Security Server. You may see any of the following error messages: COM4583F, COM4633W, VMD3770F, VMD3885I or VMD3886I. You may experience any of the following:

1. Connection to the Security Server is down.
2. The VMD Host has been deleted from the Security Server.
3. The host does not have "Communication Enabled" in the Security Server UI.
4. The VMD's host may be deleted from the Security Server. Run the register_host utility to re-register the VMD with the Security Server.

Message ID : COM4584F

Severity

Fatal error

Long Form

Initialize Agent request invalid, {0} ({1}).

Short Form

Invalid config

Parameters

Label	CEF Label	Type	Usage
ecode	cn1	Numeric	An error code
showStr	reason	Text	Code specifying reason for allowing access, if any

Description

None

Message ID : COM4586F

Severity

Fatal error

Long Form

Error evaluating policy.

Short Form

Policy eval fail

Parameters

No parameters are provided for this message type

Description

None

Message ID : COM4587F

Severity

Fatal error

Long Form

Error evaluating policy request, {0}.

Short Form

Policy eval error

Parameters

Label	CEF Label	Type	Usage
ecode	cn1	Numeric	An error code

Description

None

Message ID : COM4588F

Severity

Fatal error

Long Form

Error evaluating policy response, {0}.

Message ID : COM4587F

Short Form

Policy response error

Parameters

Label	CEF Label	Type	Usage
ecode	cn1	Numeric	An error code

Description

None

Message ID : COM4592F

Severity

Fatal error

Long Form

Error running VMSDK server, {0} (port: {1}).

Short Form

VMSDK server error

Message ID : COM4588F

Parameters

Label	CEF Label	Type	Usage
ecode	cn1	Numeric	An error code
port	spt	Numeric	A socket port number

Description

None

Message ID : COM4599F

Severity

Fatal error

Long Form

An error was encountered when trying to listen to requests from the server. The listening interface is "{0}" and the port is {1}.
Error: {2}.

Short Form

No short form is provided for this message type

Description

None

Message ID : COM4600F

Severity

Fatal error

Long Form

There was a communication failure with the Key Manager ({0}). The server returned a fault: {1}{2}; "{3}"; Subcode: "{4}"; Reason: "{5}"; Detail: "{6}".

Short Form

SOAP client error

Parameters

Label	CEF Label	Type	Usage
url	request	Text	A uniform resource location
showStr	reason	Text	Code specifying reason for allowing access, if any
verno	vds_verno	Numeric	A version number
context	vds_context	Text	Fault context

Message ID : COM4599F

Label	CEF Label	Type	Usage
subcode	vds_subcode	Text	Fault subcode
showStr	reason	Text	Code specifying reason for allowing access, if any
detail	vds_detail	Text	Fault detail

Description

None

Message ID : COM4603F

Severity

Fatal error

Long Form

Unable to parse the URL {0}. This attribute is located in the config file at {1}. Please fix the URL or re-install this product.

Short Form

Bad URL

Parameters

Label	CEF Label	Type	Usage
url	request	Text	A uniform resource location
filePath	filePath	Text	Full path to file

Description

None

Message ID : COM4604F

Severity

Fatal error

Long Form

Internal error: unable to set attribute {0}.

Short Form

Cannot set attr

Message ID : COM4603F

Parameters

Label	CEF Label	Type	Usage
showStr	reason	Text	Code specifying reason for allowing access, if any

Description

None

Message ID : COM4628F

Severity

Fatal error

Long Form

Unable to connect to a Key Manager. URL: {0}. Please verify that the agent host is registered with a Key Manager.

Short Form

Server connect fail

Parameters

Label	CEF Label	Type	Usage
url	request	Text	A uniform resource location

Message ID : COM4604F

Label	CEF Label	Type	Usage

Description

None

Message ID : COM4629F

Severity

Fatal error

Long Form

The server at {0} attempted to contact this machine, but it was denied access due to an invalid certificate.

Short Form

Bad cert from server

Parameters

Label	CEF Label	Type	Usage
url	request	Text	A uniform resource location

Description

None

Message ID : COM4630F

Severity

Fatal error

Long Form

A machine identifying itself as {0} tried to contact the VMD, but there was an error: {1}{2}; "{3}"; Subcode: "{4}"; Reason: "{5}"; Detail: "{6}".

Short Form

SOAP server error

Parameters

Label	CEF Label	Type	Usage
url	request	Text	A uniform resource location
showStr	reason	Text	Code specifying reason for allowing access, if any
verno	vds_verno	Numeric	A version number
context	vds_context	Text	Fault context

Message ID : COM4629F

Label	CEF Label	Type	Usage
subcode	vds_subcode	Text	Fault subcode
showStr	reason	Text	Code specifying reason for allowing access, if any
detail	vds_detail	Text	Fault detail

Description

None

Message ID : COM4637F

Severity

Fatal error

Long Form

Failed to bind to port {0}. Please ensure that this port is not in use by another program.

Short Form

SDK bind error

Parameters

Label	CEF Label	Type	Usage
port	spt	Numeric	A socket port number

Description

None

Logger COM: Information

Message ID : COM0006I

Severity

Information

Long Form

The Security Server permitted a backup request from host {0} for dbinstance({1}), dbalias({2}), dbpartition({3}). The policy used is ({4}), the rule used is ({5}).

Short Form

permitted backup req from host

Parameters

Label	CEF Label	Type	Usage
shost	shost	Text	Source host name
dbinstance	vds_dbinstance	Text	Database instance
dbalias	vds_dbalias	Text	Database alias
dbpart	vds_dbpart	Numeric	Database partition
pol	cs1	Text	Policy name

Label	CEF Label	Type	Usage
rule	vds_rule	Text	Name of policy rule set

Description

None

Message ID : COM0007I

Severity

Information

Long Form

The Security Server denied a backup request from host {0} for dbinstance({1}), dbalias({2}), dbpartition({3}). The policy used is ({4}), the rule used is ({5}).

Short Form

No short form is provided for this message type

Description

None

Message ID : COM0008I

Severity

Information

Long Form

The Security Server permitted a restore request from host {0} for dbinstance({1}), dbalias({2}), dbpartition({3}). The policy used is ({4}), the rule used is ({5}).

Short Form

permitted restore req from host

Parameters

Label	CEF Label	Type	Usage
shost	shost	Text	Source host name
dbinstance	vds_dbinstance	Text	Database instance
dbalias	vds_dbalias	Text	Database alias
dbpart	vds_dbpart	Numeric	Database partition
pol	cs1	Text	Policy name
rule	vds_rule	Text	Name of policy rule set

Description

None

Message ID : COM0009I

Severity

Information

Long Form

The Security Server denied a restore request from host {0} for dbinstance({1}), dbalias({2}), dbpartition({3}). The policy used is ({4}), the rule used is ({5}).

Short Form

denied restore req from host

Parameters

Label	CEF Label	Type	Usage
shost	shost	Text	Source host name
dbinstance	vds_dbinstance	Text	Database instance
dbalias	vds_dbalias	Text	Database alias
dbpart	vds_dbpart	Numeric	Database partition

Label	CEF Label	Type	Usage
pol	cs1	Text	Policy name
rule	vds_rule	Text	Name of policy rule set

Description

None

Message ID : COM0010I

Severity

Information

Long Form

The Security Server received a backup request from host {0} for dbinstance({1}), dbalias({2}), dbpartition({3}).

Short Form

received backup req from host

Parameters

Label	CEF Label	Type	Usage
-------	-----------	------	-------

Message ID : COM0009I

Label	CEF Label	Type	Usage
shost	shost	Text	Source host name
dbinstance	vds_dbinstance	Text	Database instance
dbalias	vds_dbalias	Text	Database alias
dbpart	vds_dbpart	Numeric	Database partition

Description

None

Message ID : COM0011I

Severity

Information

Long Form

The Security Server received a restore request from host {0} for dbinstance({1}), dbalias({2}), dbpartition({3}).

Short Form

received restore req from host

Parameters

Label	CEF Label	Type	Usage
shost	shost	Text	Source host name
dbinstance	vds_dbinstance	Text	Database instance
dbalias	vds_dbalias	Text	Database alias
dbpart	vds_dbpart	Numeric	Database partition

Description

None

Message ID : COM0012I

Severity

Information

Long Form

The Security Server is unable to locate a key or header information needed for the backup request from host {0} for dbinstance({1}), dbalias({2}), dbpartition({3}). The backup request will be denied.

Short Form

unable to locate key for req from host

Parameters

Label	CEF Label	Type	Usage
shost	shost	Text	Source host name
dbinstance	vds_dbinstance	Text	Database instance
dbalias	vds_dbalias	Text	Database alias
dbpart	vds_dbpart	Numeric	Database partition

Description

None

Message ID : COM0013I

Severity

Information

Long Form

The Security Server is unable to locate a key needed for the restore request from host {0} for dbinstance({1}), dbalias({2}), dbpartition({3}). The restore request will be denied.

Message ID : COM0012I

Short Form

No short form is provided for this message type

Description

None

Message ID : COM0014I

Severity

Information

Long Form

The Security Server denied a backup request from host {0} for dbinstance({1}), dbalias({2}), dbpartition({3}). There were no applicable policy or applicable rule found.

Short Form

No short form is provided for this message type

Description

None

Message ID : COM0013I

Message ID : COM0015I

Severity

Information

Long Form

The Security Server denied a restore request from host {0} for dbinstance({1}), dbalias({2}), dbpartition({3}). There were no applicable policy or applicable rule found.

Short Form

denied restore req from host

Parameters

Label	CEF Label	Type	Usage
shost	shost	Text	Source host name
dbinstance	vds_dbinstance	Text	Database instance
dbalias	vds_dbalias	Text	Database alias
dbpart	vds_dbpart	Numeric	Database partition

Description

None

Message ID : COM0016I

Severity

Information

Long Form

The Security Server permitted a backup request from host {0} for server name({1}), Server Number({3}). The policy used is ({4}), the rule used is ({5}).

Short Form

No short form is provided for this message type

Description

None

Message ID : COM0017I

Severity

Information

Long Form

The Security Server denied a backup request from host {0} for server name({1}), Server Number({3}). The policy used is ({4}), the rule used is ({5}).

Short Form

No short form is provided for this message type

Description

None

Message ID : COM0018I

Severity

Information

Long Form

The Security Server permitted a restore request from host {0} for server name({1}), Server Number({3}). The policy used is ({4}), the rule used is ({5}).

Message ID : COM0017I

545

Short Form

No short form is provided for this message type

Description

None

Message ID : COM0019I

Severity

Information

Long Form

The Security Server denied a restore request from host {0} for server name({1}), Server Number({3}). The policy used is ({4}), the rule used is ({5}).

Short Form

No short form is provided for this message type

Description

None

Message ID : COM0020I

Severity

Information

Long Form

The Security Server received a backup request from host {0} for server name({1}), Server Number({3}).

Short Form

No short form is provided for this message type

Description

None

Message ID : COM0021I

Severity

Information

Long Form

The Security Server received a restore request from host {0} for server name({1}), Server Number({3}).

Short Form

No short form is provided for this message type

Description

None

Message ID : COM0022I

Severity

Information

Long Form

The Security Server is unable to locate a key or header information needed for the backup request from host {0} for server name({1}), Server Number({3}). The backup request will be denied.

Short Form

No short form is provided for this message type

Description

None

Message ID : COM0021I

Message ID : COM0023I

Severity

Information

Long Form

The Security Server is unable to locate a key needed for the restore request from host {0} for server name({1}), Server Number({3}). The restore request will be denied.

Short Form

No short form is provided for this message type

Description

None

Message ID : COM0024I

Severity

Information

Long Form

The Security Server denied a backup request from host {0} for server name({1}), Server Number({3}). There were no applicable policy or applicable rule found.

Short Form

No short form is provided for this message type

Description

None

Message ID : COM0025I

Severity

Information

Long Form

The Security Server denied a restore request from host {0} for server name({1}), Server Number({3}). There were no applicable policy or applicable rule found.

Short Form

No short form is provided for this message type

Message ID : COM0024I

Description

None

Message ID : COM0173I

Severity

Information

Long Form

The Security Server denied a request from unauthorized host "{0}".

Short Form

denied req from unauthorized host

Parameters

Label	CEF Label	Type	Usage
shost	shost	Text	Source host name

Description

None

Message ID : COM0025I

Message ID : COM0314I

Severity

Information

Long Form

The Security Server was able to successfully send security configuration changes to the agent on host {0}.

Short Form

security config push ok

Parameters

Label	CEF Label	Type	Usage
shost	shost	Text	Source host name

Description

None

Message ID : COM0538I

Severity

Information

Long Form

The Security Server is unable to browse the agent at host {0}. The agent is not registered with the server or communication with the agent is not allowed. Please ensure that the agent is registered with the server and communication with the agent is allowed.

Short Form

No short form is provided for this message type

Description

None

Message ID : COM0559I

Severity

Information

Long Form

The communication version of agent on host {0} is not compatible to support this operation.

Short Form

No short form is provided for this message type

Description

None

Message ID : COM0572I

Severity

Information

Long Form

The Security Server is waiting for replication completion before pushing configuration to host {0}. The Security Server will make another attempt to contact the host at approximately {1}.

Short Form

waiting for replication completion

Parameters

Label	CEF Label	Type	Usage
shost	shost	Text	Source host name

Label	CEF Label	Type	Usage
nexttime	vds_nexttime	Text	Time of next attempt

Description

None

Message ID : COM0574I

Severity

Information

Long Form

Primary Server is unable to perform replication synchronization to failover server "{0}" for more than "{1}" minutes.

Short Form

primary unable to perform replication synchronization to failover

Parameters

Label	CEF Label	Type	Usage
shost	shost	Text	Source host name

Label	CEF Label	Type	Usage
mins	vds_mins	Numeric	Elaped minutes

Description

None

Message ID : COM0649I

Severity

Information

Long Form

The communication version of the registration authority on host {0} is not compatible to support this operation.

Short Form

No short form is provided for this message type

Description

None

Message ID : COM0666I

Severity

Information

Long Form

There are {0} logs dropped for the past hour during the syslog-ng host {1} downtime.

Short Form

logs dropped in past hour during syslog downtime

Parameters

Label	CEF Label	Type	Usage
scount	vds_scount	Text	A generic count as a string
shost	shost	Text	Source host name

Description

None

Message ID : COM0707I

Severity

Information

Long Form

The host password of host "{0}" is changed, it needs to communicate to primary server get configuration.

Short Form

No short form is provided for this message type

Description

None

Message ID : COM0710I

Severity

Information

Long Form

The {0} agent at host {1} is unregistered successfully.

Short Form

agent unregistered ok

Parameters

Label	CEF Label	Type	Usage
agent	deviceProcessName	Text	The short identifier of the agent software
shost	shost	Text	Source host name

Description

None

Message ID : COM0711I

Severity

Information

Long Form

The {0} agent at host {1} requested deletion of the host. The host {1} is deleted from the security server {2} successfully.

Short Form

agent requested host deletion

Parameters

Label	CEF Label	Type	Usage
agent	deviceProcessName	Text	The short identifier of the agent software
shost	shost	Text	Source host name
shost	shost	Text	Source host name

Description

None

Message ID : COM1311I

Severity

Information

Long Form

Host {0} enable one-way communication

Message ID : COM0711I

Short Form

Host enable one-way communication

Parameters

Label	CEF Label	Type	Usage
shost	shost	Text	Source host name

Description

None

Message ID : COM1312I

Severity

Information

Long Form

Host {0} disable one-way communication

Short Form

Host disable one-way communication

Message ID : COM1311I

Parameters

Label	CEF Label	Type	Usage
shost	shost	Text	Source host name

Description

None

Message ID : COM1519I

Severity

Information

Long Form

Generated a key for host "{0}".

Short Form

Generated a key for host

Parameters

Label	CEF Label	Type	Usage
shost	shost	Text	Source host name

Message ID : COM1312I

Label	CEF Label	Type	Usage

Description

None

Message ID : COM1521I

Severity

Information

Long Form

Replication to other server "{0} recovered".

Short Form

Replication to other server recovered

Parameters

Label	CEF Label	Type	Usage
shost	shost	Text	Source host name

Description

None

Message ID : COM1784I

Severity

Information

Long Form

[[0]] network ping ...

Short Form

No short form is provided for this message type

Description

None

Message ID : COM1813I

Severity

Information

Message ID : COM1521I

Long Form

The host "{0}" reported incompatible agent state. {1}.

Short Form

No short form is provided for this message type

Description

None

Message ID : COM1835I

Severity

Information

Long Form

The Security Server pushed following section(s) to the agent {0} :: {1}.#

Short Form

The Security Server pushed following section(s) to the agent

Parameters

Label	CEF Label	Type	Usage
shost	shost	Text	Source host name

Description

None

Message ID : COM4601I

Severity

Information

Long Form

Successful Agent init with Key Manager ({}).

Short Form

Comms init OK

Parameters

Label	CEF Label	Type	Usage
url	request	Text	A uniform resource location

Message ID : COM1835I

Label	CEF Label	Type	Usage

Description

None

Message ID : COM4602I

Severity

Information

Long Form

Failed Agent init with Key Manager ({0}).

Short Form

Comms init fail

Parameters

Label	CEF Label	Type	Usage
url	request	Text	A uniform resource location

Description

None

Message ID : COM4626I

Severity

Information

Long Form

The agent failed to initialize with the Key Manager. This may indicate that the connection to the server is down, the agent's host has been deleted from the Key Manager, or "Communication Enabled" for the host has not been enabled in the Key Manager UI.

Short Form

No short form is provided for this message type

Description

None

Message ID : COM4627I

Severity

Information

Long Form

The agent's host may no longer be registered with a Key Manager. The agent's host may have been deleted from the Key Manager. You may want to run the register_host utility to re-register the agent with a Key Manager.

Short Form

Agent not registered

Parameters

No parameters are provided for this message type

Description

None

Logger COM: Warnings

Message ID : COM0591W

Severity

Warning

Long Form

The agent at host {0} failed to generate the signature on this file {1}. Please check the VMD log for the cause.

Short Form

agent failed to generate signature on file

Parameters

Label	CEF Label	Type	Usage
shost	shost	Text	Source host name
filePath	filePath	Text	Full path to file

Description

None

Message ID : COM0607W

Severity

Warning

Long Form

Unable to sign the source on host {0}. Please check if the source exists on the host.

Short Form

No short form is provided for this message type

Description

None

Message ID : COM0612W

Severity

Warning

Long Form

The Security Server will not try to push the security configuration to the host {0} any more because the retry attempts have reached the maximum number.

Message ID : COM0607W

Short Form

No short form is provided for this message type

Description

None

Message ID : COM0614W

Severity

Warning

Long Form

Warning: Requires atleast one parameter (description/password/readonly). The Administrator info will not be changed.

Short Form

No short form is provided for this message type

Description

None

Message ID : COM0617W

Severity

Warning

Long Form

The user must have at least one role.

Short Form

No short form is provided for this message type

Description

None

Message ID : COM0618W

Severity

Warning

Long Form

The domain name is needed to delete a domain.

Short Form

No short form is provided for this message type

Description

None

Message ID : COM0667W

Severity

Warning

Long Form

The agent at host {0} uses challenge response compatible host password.

Short Form

No short form is provided for this message type

Description

None

Message ID : COM1251W

Severity

Warning

Long Form

The password and description cannot be changed at the same time. Please supply either password info or description info.

Short Form

No short form is provided for this message type

Description

None

Message ID : COM1314W

Severity

Warning

Long Form

This security configuration must be downloaded from primary server.

Short Form

No short form is provided for this message type

Description

None

Message ID : COM1323W

Severity

Warning

Long Form

Please use the number between 0 and 100.

Short Form

No short form is provided for this message type

Description

None

Message ID : COM1314W

Message ID : COM1337W

Severity

Warning

Long Form

Adding more domain(s) is not allowed because the current domain count has exceeded the maximum number of domains allowed by the license.COM1348E=The agent type must be one of FS, DB2, IDS, KEY or KMIPC.

Short Form

No short form is provided for this message type

Description

None

Message ID : COM4605W

Severity

Warning

Long Form

Logging destination changed from {0} to {1}

Short Form

Upload dest change

Parameters

Label	CEF Label	Type	Usage
shost	shost	Text	Source host name
url	request	Text	A uniform resource location

Description

None

Message ID : COM4632W

Severity

Warning

Message ID : COM4605W

Long Form

There was a communication failure with the Key Manager. The server returned a fault: {0}{1}; "{2}"; Subcode: "{3}"; Reason: "{4}"; Detail: "{5}".

Short Form

No short form is provided for this message type

Description

None

Message ID : COM4633W

Severity

Warning

Long Form

There was a communication failure with the Key Manager ({0}). The server returned a fault: {1}{2}; "{3}"; Subcode: "{4}"; Reason: "{5}"; Detail: "{6}".

Short Form

SOAP client error

Message ID : COM4632W

Parameters

Label	CEF Label	Type	Usage
url	request	Text	A uniform resource location
showStr	reason	Text	Code specifying reason for allowing access, if any
verno	vds_verno	Numeric	A version number
context	vds_context	Text	Fault context
subcode	vds_subcode	Text	Fault subcode
showStr	reason	Text	Code specifying reason for allowing access, if any
detail	vds_detail	Text	Fault detail

Description

The agent is unable to reach the Security Server. You may see any of the following error messages: COM4583F, COM4633W, VMD3770F, VMD3885I or VMD3886I. You may experience any of the following:

1. Connection to the Security Server is down.
2. The VMD Host has been deleted from the Security Server.
3. The host does not have "Communication Enabled" in the Security Server UI.
4. The VMD's host may be deleted from the Security Server. Run the register_host utility to re-register the VMD with the Security Server.

Message ID : COM4634W

Severity

Warning

Long Form

The server at {0} attempted to contact this machine, but it was denied access due to an invalid certificate.

Short Form

Bad cert from server

Parameters

Label	CEF Label	Type	Usage
url	request	Text	A uniform resource location

Description

An attempt to contact the agent was rejected. This may be due to attempting to register an agent with a new Security Server after that agent was registered with a different Security Server. A COM4635W log message may give more details.

Message ID : COM4635W

Severity

Warning

Long Form

A machine identifying itself as {0} tried to contact the VMD, but there was an error: {1}{2}; "{3}"; Subcode: "{4}"; Reason: "{5}"; Detail: "{6}".

Short Form

SOAP server error

Parameters

Label	CEF Label	Type	Usage
url	request	Text	A uniform resource location
showStr	reason	Text	Code specifying reason for allowing access, if any
verno	vds_verno	Numeric	A version number
context	vds_context	Text	Fault context
subcode	vds_subcode	Text	Fault subcode
showStr	reason	Text	Code specifying reason for allowing access, if any
detail	vds_detail	Text	Fault detail

Description

The Security Server tried to contact the agent but did not succeed. The "reason" field tells you why the certificate was rejected, and the "detail" field tells you what action was attempted at the time.

Logger CXM: Errors

Message ID : CXM0654E

Severity

Error

Long Form

{0}.

Short Form

err

Parameters

Label	CEF Label	Type	Usage
showStr	reason	Text	Code specifying reason for allowing access, if any

Description

None

Message ID : CXM0657E

Severity

Error

Long Form

The user "{0}" failed to generate the certificate signing request files.

Short Form

failed to generate cert signing req files

Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name

Description

None

Message ID : CXM0658E

Severity

Error

Long Form

The user "{0}" failed to import the signed certificates into the security server. Reason: {1}

Short Form

failed to import signed certs

Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
showStr	reason	Text	Code specifying reason for allowing access, if any

Description

None

Message ID : CXM0659E

Severity

Error

Long Form

The user "{0}" failed to import the LDAP certificate. Reason: {1}

Short Form

failed to import LDAP certificate

Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
showStr	reason	Text	Code specifying reason for allowing access, if any

Description

None

Message ID : CXM0770E

Severity

Error

Long Form

The user "{0}" failed to import the trust certificate(s) into the security server.

Short Form

failed to import trust certs

Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name

Description

None

Message ID : CXM1354E

Severity

Error

Message ID : CXM0770E

Long Form

The sha1 signature hash algorithm in certificate "{0}" is not accepted.

Short Form

No short form is provided for this message type

Description

None

Message ID : CXM1355E

Severity

Error

Long Form

The digital signature cannot be validated on "{0}" by "{1}". This may indicate the man-in-the-middle attack.

Short Form

No short form is provided for this message type

Description

None

Message ID : CXM1356E

Severity

Error

Long Form

The intermediate CA certificate is required.

Short Form

No short form is provided for this message type

Description

None

Message ID : CXM1357E

Severity

Error

Message ID : CXM1355E

Long Form

The trusted signed certificate issued by the certificate authority is required.

Short Form

No short form is provided for this message type

Description

None

Message ID : CXM1358E

Severity

Error

Long Form

Certificate already exists and was not replaced. Please generate a new CSR and choose a new signed certificate if you wish to replace the current one.

Short Form

No short form is provided for this message type

Message ID : CXM1357E

Description

None

Message ID : CXM1359E

Severity

Error

Long Form

The public keys or digital signatures mismatch. This may indicate the man-in-the-middle attack.

Short Form

No short form is provided for this message type

Description

None

Message ID : CXM1360E

Severity

Error

Message ID : CXM1358E

Long Form

{0} PEM file(s) do not exist.

Short Form

No short form is provided for this message type

Description

None

Message ID : CXM1361E

Severity

Error

Long Form

The message-digest algorithm in certificate "{0}" is not accepted.

Short Form

No short form is provided for this message type

Description

None

Message ID : CXM1391E

Severity

Error

Long Form

The certificate "{0}" is either expired or not effective yet or an invalid certificate.

Short Form

No short form is provided for this message type

Description

None

Message ID : CXM1392E

Severity

Error

Message ID : CXM1361E

Long Form

The certificate is not a valid certificate.

Short Form

No short form is provided for this message type

Description

None

Message ID : CXM1393E

Severity

Error

Long Form

The user "{0}" failed to import the syslog certificate for the syslog host "{1}". Reason: {2}

Short Form

No short form is provided for this message type

Description

None

Message ID : CXM1693E

Severity

Error

Long Form

The ripemd160 signature hash algorithm in certificate "{0}" is not accepted.

Short Form

No short form is provided for this message type

Description

None

Logger CXM: Information

Message ID : CXM0221I

Severity

Information

Long Form

The Security Server received a certificate generation request from host "{0}".

Short Form

received cert gen request

Parameters

Label	CEF Label	Type	Usage
shost	shost	Text	Source host name

Description

None

Message ID : CXM0224I

Severity

Information

Long Form

The Security Server generated a certificate for host "{0}".

Short Form

generated cert

Parameters

Label	CEF Label	Type	Usage
shost	shost	Text	Source host name

Description

None

Message ID : CXM0225I

Severity

Information

Long Form

The Certificate manager does not support GETs. Retry with a POST request.

Short Form

No short form is provided for this message type

Description

None

Message ID : CXM0646I

Severity

Information

Long Form

The agent on host {0} has requested a certificate.

Short Form

agent cert req

Parameters

Label	CEF Label	Type	Usage
shost	shost	Text	Source host name

Description

None

Message ID : CXM0647I

Severity

Information

Long Form

The Vormetric Registration Authority (RA) has forwarded the request to the {0} Certificate Authority (CA).

Short Form

ra forwarded request to ca

Message ID : CXM0646I

Parameters

Label	CEF Label	Type	Usage
provider	vds_provider	Text	Certificate authority/provider

Description

None

Message ID : CXM0648I

Severity

Information

Long Form

The Vormetric Registration Authority (RA) received the certificate from the {0} CA and forwarded the certificate to the host {1}.

Short Form

ra forwarded cert to agent

Parameters

Label	CEF Label	Type	Usage
provider	vds_provider	Text	Certificate authority/provider

Message ID : CXM0647I

Label	CEF Label	Type	Usage
shost	shost	Text	Source host name

Description

None

Message ID : CXM0655I

Severity

Information

Long Form

The user "{0}" successfully generated the certificate signing request files with subject(s): {1}.

Short Form

user generated cert signing req files

Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name

Message ID : CXM0648I

Label	CEF Label	Type	Usage

Description

None

Message ID : CXM0656I

Severity

Information

Long Form

The user "{0}" successfully imported the signed certificates into the security server.

Short Form

successfully imported signed certs

Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name

Description

None

Message ID : CXM0659I

Severity

Information

Long Form

The user "{0}" successfully imported the signed certificates into the security server. DSM CA certificate Subject DN: {1}, Issuer DN: {2} and ExpirationDate: {3}. Agent CA certificate Subject DN: {4}, Issuer DN: {5} and ExpirationDate: {6}.

Short Form

successfully imported signed certificates

Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name

Description

None

Message ID : CXM0660I

Severity

Information

Long Form

The user "{0}" successfully imported the signed certificates into the security server. DSM CA certificate Subject DN: {1}, Issuer DN: {2} and ExpirationDate: {3}.

Short Form

successfully imported signed certificates

Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name

Description

None

Message ID : CXM0661I

Severity

Information

Long Form

The user "{0}" successfully imported the syslog certificate for the Syslog Host "{1}". Syslog certificate Subject DN: {2}, Issuer DN: {3} and ExpirationDate: {4}.

Short Form

successfully imported syslog certificate

Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name

Description

None

Message ID : CXM0662I

Severity

Information

Long Form

The user "{0}" successfully imported the LDAP certificate. LDAP certificate Subject DN: {1}, Issuer DN: {2} and ExpirationDate: {3}.

Short Form

successfully imported LDAP certificate

Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name

Description

None

Message ID : CXM0771I

Severity

Information

Long Form

The user "{0}" successfully imported the trust certificate(s) into the security server.

Short Form

successfully imported trust certs

Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name

Description

None

Message ID : CXM0662I

Message ID : CXM1340I

Severity

Information

Long Form

Host {0} registered into domain {1}, host group {2} using a shared secret

Short Form

host registered using a shared secret

Parameters

Label	CEF Label	Type	Usage
shost	shost	Text	Source host name
domain	domain	Text	A domain name (policy, network, users, etc)
group	group	Text	Group name

Description

None

Message ID : CXM1341I

Severity

Information

Long Form

Host {0} registered into domain {1} using a shared secret

Short Form

host registered using a shared secret

Parameters

Label	CEF Label	Type	Usage
shost	shost	Text	Source host name
domain	domain	Text	A domain name (policy, network, users, etc)

Description

None

Message ID : CXM1342I

Severity

Information

Long Form

Host {0} registered into domain {1} using fingerprint

Short Form

host registered using fingerprint

Parameters

Label	CEF Label	Type	Usage
shost	shost	Text	Source host name
domain	domain	Text	A domain name (policy, network, users, etc)

Description

None

Message ID : CXM1344I

Severity

Information

Long Form

User "{0}" modified shared secret of domain {1}, host group {2}

Short Form

user modified shared secret

Parameters

Label	Type	Usage
user	Text	User name
domain	Text	A domain name (policy, network, users, etc)
group	Text	Group name

Description

None

Message ID : CXM1345I

Severity

Information

Long Form

User "{0}" modified shared secret of domain {1}

Short Form

user modified shared secret

Parameters

Label	Type	Usage
user	Text	User name
domain	Text	A domain name (policy, network, users, etc)

Description

None

Message ID : CXM1346I

Severity

Information

Long Form

Shared secret of domain {0}, host group {1} expired

Short Form

shared secret expired

Parameters

Label	Type	Usage
domain	Text	A domain name (policy, network, users, etc)
group	Text	Group name

Description

None

Message ID : CXM1347I

Severity

Information

Long Form

Shared secret of domain {0} expired

Short Form

{0} {1} CEF:0|Vormetric, Inc.|dsm|{3}|CXM1346I|shared secret expired|3|cs4Label=logger cs4=CXM spid={2} rt={4} dvchost={1}

Parameters

Label	Type	Usage
domain	Text	A domain name (policy, network, users, etc)

Description

None

Message ID : CXM1624I

Severity

Information

Long Form

Certificate details for host "{0}", {1}.

Short Form

generated cert

Parameters

Label	CEF Label	Type	Usage
shost	shost	Text	Source host name
cert	cert	Text	Certificate type or name

Description

None

Message ID : CXM1732I

Severity

Information

Long Form

The Security Server exported a {2}CA certificate with Subject "{0}" by user "{1}".

Short Form

No short form is provided for this message type

Description

None

Message ID : CXM1748I

Severity

Information

Long Form

A registration token that will be expired at "{0}" was generated in domain "{1}" by user "{2}" for host "{3}".

Message ID : CXM1732I

Short Form

registration token generated in domain

Parameters

Label	CEF Label	Type	Usage
domain	domain	Text	A domain name (policy, network, users, etc)
user	suser	Text	User name
shost	shost	Text	Source host name

Description

None

Logger CXM: Warnings

Message ID : CXM0222W

Severity

Warning

Long Form

The Security Server denied a certificate generation request from "{0}". The {1} agent is not enabled for the host in server.

Short Form

denied cert gen request: agent not enabled

Parameters

Label	CEF Label	Type	Usage
shost	shost	Text	Source host name
agent	deviceProcessName	Text	The short identifier of the agent software

Description

An agent certificate generation request was rejected as unauthorized. Select the "Registration Allowed" box for the appropriate Agent on the Host page.

Message ID : CXM0223W

Severity

Warning

Long Form

The Security Server denied a certificate generation request from "{0}". An entry already exists for the host.

Short Form

denied cert gen request: duplicate

Parameters

Label	CEF Label	Type	Usage
shost	shost	Text	Source host name

Description

A duplicate agent with the same name already exists. Please clear the existing agent fingerprint and re-register the agent with the server.

Message ID : CXM0226W

Severity

Warning

Long Form

License has expired, The Security Server is continuing with certificate renewal request from "{0}". Renew expired license.

Short Form

processing cert gen request:renew expired license

Parameters

Label	CEF Label	Type	Usage
shost	shost	Text	Source host name

Description

None

Message ID : CXM0227W

Severity

Warning

Message ID : CXM0226W

Long Form

"{0}" is not defined in the initial DSM server.

Short Form

cert gen request:failover server not defined

Parameters

Label	CEF Label	Type	Usage
shost	shost	Text	Source host name

Description

None

Message ID : CXM0289W

Severity

Warning

Long Form

The Security Server denied a certificate generation request from "{0}". The host is not reachable.

Message ID : CXM0227W

Short Form

denied cert gen request:host unreachable

Parameters

Label	CEF Label	Type	Usage
shost	shost	Text	Source host name

Description

An agent certificate generation request has been denied because the agent is unreachable. Check for the following:

1. Proper name resolution.
2. Confirm host/server connection is established.
3. Check the firewall for proper port configuration.

Message ID : CXM0802W

Severity

Warning

Long Form

There is missing server certificate chain...

Short Form

No short form is provided for this message type

Description

None

Message ID : CXM1250W

Severity

Warning

Long Form

There is missing APPID certificate chain...

Short Form

No short form is provided for this message type

Message ID : CXM0802W

Description

None

Message ID : CXM1294W

Severity

Warning

Long Form

The agent registration on host {0} has been denied due to license validation failed: {1}

Short Form

agent license validation failed

Parameters

Label	CEF Label	Type	Usage
shost	shost	Text	Source host name

Description

None

Message ID : CXM1250W

Message ID : CXM1343W

Severity

Warning

Long Form

Host {0} ({1}) attempted and failed to register using a shared secret

Short Form

host failed to register using a shared secret

Parameters

Label	CEF Label	Type	Usage
shost	shost	Text	Source host name

Description

None

Message ID : CXM1363W

Severity

Warning

Long Form

Domain {0} not found

Short Form

Domain not found

Parameters

Label	Type	Usage
domain	Text	A domain name (policy, network, users, etc)

Description

None

Message ID : CXM1423W

Severity

Warning

Message ID : CXM1363W

Long Form

Registration is locked from IP address "{0}", because of too many failed attempts. It will be unlocked in "{1}" minutes.

Short Form

host registration locked due to too many failed attempts

Parameters

Label	CEF Label	Type	Usage
shost	shost	Text	Source host name

Description

None

Message ID : CXM1520W

Severity

Warning

Long Form

The Security Server denied a certificate generation request from "{0}". The host already has a {1} agent registered with a different one way communication setting.

Message ID : CXM1423W

Short Form

denied cert gen request:inconsistent one way comm setting

Parameters

Label	CEF Label	Type	Usage
shost	shost	Text	Source host name

Description

None

Message ID : CXM1749W

Severity

Warning

Long Form

The registration token from host "{0}" is invalid. Reason: {1}.

Short Form

No short form is provided for this message type

Message ID : CXM1520W

Description

None

Logger DA0: Errors

Message ID : DA001322E

Severity

Error

Long Form

"{0}" is not a valid name. The name must consist of alpha-numeric characters; and the only non-alpha-numeric characters allowed are dot (.), and dash (-).

Short Form

No short form is provided for this message type

Description

None

Message ID : DA001323E

Severity

Error

Long Form

The length of the host name exceeds the maximum 255 characters

Short Form

No short form is provided for this message type

Description

None

Logger DAO: Errors

Message ID : DAO0038E

Severity

Error

Long Form

An internal error occurred on the Security Server. Refer to cgss.log and server.log for details. Call support if necessary.

Short Form

No short form is provided for this message type

Description

None

Message ID : DAO0039E

Severity

Error

Long Form

The Security Server failed to connect to the repository database. Restart the Security Server and retry. If the problem persists, call support.

Short Form

No short form is provided for this message type

Description

None

Message ID : DAO0040E

Severity

Error

Long Form

The Security Server failed to persist data into the repository database. Refer to cgss.log and server.log for details. Call support if necessary.

Short Form

No short form is provided for this message type

Message ID : DAO0039E

Description

None

Message ID : DAO0041E

Severity

Error

Long Form

The Security Server failed to connect to the repository database. Ensure that the database is functional and running.

Short Form

No short form is provided for this message type

Description

None

Message ID : DAO0042E

Severity

Error

Message ID : DAO0040E

Long Form

Host Name "{0}" is already in use. Specify a different name.

Short Form

No short form is provided for this message type

Description

None

Message ID : DAO0043E

Severity

Error

Long Form

The selected host no longer exists.

Short Form

No short form is provided for this message type

Description

None

Message ID : DAO0044E**Severity**

Error

Long Form

One or more hosts no longer exist.

Short Form

No short form is provided for this message type

Description

None

Message ID : DAO0049E**Severity**

Error

Message ID : DAO0043E

Long Form

Host Group Name "{0}" is already in use. Specify a different name.

Short Form

No short form is provided for this message type

Description

None

Message ID : DAO0050E

Severity

Error

Long Form

The selected host group no longer exists.

Short Form

No short form is provided for this message type

Description

None

Message ID : DAO0051E

Severity

Error

Long Form

One or more host groups no longer exist.

Short Form

No short form is provided for this message type

Description

None

Message ID : DAO0056E

Severity

Error

Message ID : DAO0050E

Long Form

A policy with name "{0}" already exists in domain "{1}". Please specify a different policy name.

Short Form

No short form is provided for this message type

Description

None

Message ID : DAO0057E

Severity

Error

Long Form

The selected policy no longer exists.

Short Form

No short form is provided for this message type

Description

None

Message ID : DAO0058E**Severity**

Error

Long Form

One or more rules in the policy have non-unique rule names. Check the rule names and make sure they are different.

Short Form

No short form is provided for this message type

Description

None

Message ID : DAO0059E**Severity**

Error

Message ID : DAO0057E

Long Form

One or more conditions in some rule(s) have non-unique names. Check the conditions for each rule and make sure they are different.

Short Form

No short form is provided for this message type

Description

None

Message ID : DAO0060E

Severity

Error

Long Form

Policy with name "{0}" no longer exists. Refresh the list of Policies before retrying the operation.

Short Form

No short form is provided for this message type

Description

None

Message ID : DAO0066E**Severity**

Error

Long Form

The selected key pair no longer exists.

Short Form

No short form is provided for this message type

Description

None

Message ID : DAO0067E**Severity**

Error

Message ID : DAO0060E

Long Form

One or more keys no longer exist.

Short Form

No short form is provided for this message type

Description

None

Message ID : DAO0069E

Severity

Error

Long Form

Affiliated Key Name "{0}" is already in use. Specify a different name.

Short Form

No short form is provided for this message type

Message ID : DAO0067E

Description

None

Message ID : DAO0070E**Severity**

Error

Long Form

The selected affiliated keys no longer exist.

Short Form

No short form is provided for this message type

Description

None

Message ID : DAO0081E**Severity**

Error

Message ID : DAO0069E

Long Form

One of the fields in an audit log entry contains a NULL value. Check the failed audit log file for the potential error. Fields in an audit log entry cannot be NULL.

Short Form

No short form is provided for this message type

Description

None

Message ID : DAO0087E

Severity

Error

Long Form

User Name "{0}" is already in use. Specify a different name.

Short Form

No short form is provided for this message type

Description

None

Message ID : DAO0088E**Severity**

Error

Long Form

The selected user no longer exists.

Short Form

No short form is provided for this message type

Description

None

Message ID : DAO01299E**Severity**

Error

Message ID : DAO0087E

Long Form

Duplicate certificate exists.

Short Form

No short form is provided for this message type

Description

None

Message ID : DAO01320E

Severity

Error

Long Form

Unable to import policy {0}, the set {1} exceeds 100MB limit

Short Form

No short form is provided for this message type

Message ID : DAO01299E

Description

None

Message ID : DAO01328E**Severity**

Error

Long Form

Domain with name "{0}" not found

Short Form

No short form is provided for this message type

Description

None

Message ID : DAO01329E**Severity**

Error

Message ID : DAO01320E

Long Form

User with name "{0}" not found

Short Form

No short form is provided for this message type

Description

None

Message ID : DAO01335E

Severity

Error

Long Form

Host port {0} is not a valid port number. A valid network port should be in the range 1024-65535.

Short Form

No short form is provided for this message type

Message ID : DAO01329E

Description

None

Message ID : DAO01336E

Severity

Error

Long Form

QOS rekeyrate {0} is not in valid limit. A valid rekeyrate should be in the range 0-32767.

Short Form

No short form is provided for this message type

Description

None

Message ID : DAO01342E

Severity

Error

Message ID : DAO01335E

Long Form

LDT Schedule {0} not found

Short Form

No short form is provided for this message type

Description

None

Message ID : DAO01343E

Severity

Error

Long Form

LDT Schedule {0} already exists

Short Form

No short form is provided for this message type

Message ID : DAO01342E

Description

None

Message ID : DAO01344E**Severity**

Error

Long Form

LDT Schedule {0} is associated with {1}, cannot be deleted

Short Form

No short form is provided for this message type

Description

None

Message ID : DAO01346E**Severity**

Error

Message ID : DAO01343E

Long Form

System defined LDT Schedule {0} cannot be modified

Short Form

No short form is provided for this message type

Description

None

Message ID : DAO01347E

Severity

Error

Long Form

System defined LDT Schedule {0} cannot be deleted

Short Form

No short form is provided for this message type

Description

None

Message ID : DAO01348E

Severity

Error

Long Form

LDT is not enabled for host {0}

Short Form

No short form is provided for this message type

Description

None

Message ID : DAO01349E

Severity

Error

Message ID : DAO01347E

Long Form

Audit log configuration exists for Docker Host {0} for imageId {1} containerId {2}

Short Form

No short form is provided for this message type

Description

None

Message ID : DAO01350E

Severity

Error

Long Form

Cannot delete non docker audit log configuration for Host {0} with audit log configuration id {1}

Short Form

No short form is provided for this message type

Message ID : DAO01349E

Description

None

Message ID : DAO01351E

Severity

Error

Long Form

User {0} updated docker meta data for host {1}

Short Form

No short form is provided for this message type

Description

None

Message ID : DAO01384E

Severity

Error

Message ID : DAO01350E

Long Form

Unauthorized domain

Short Form

No short form is provided for this message type

Description

None

Message ID : DAO01392E

Severity

Error

Long Form

Non unique key shares found. The key shares should be unique.

Short Form

No short form is provided for this message type

Description

None

Message ID : DAO01400E

Severity

Error

Long Form

Attribute {0} value is not unique

Short Form

No short form is provided for this message type

Description

None

Message ID : DAO01518E

Severity

Error

Message ID : DAO01392E

Long Form

FS Communication Port cannot be the same as VDE Communication Port

Short Form

No short form is provided for this message type

Description

None

Message ID : DAO01658E

Severity

Error

Long Form

Attribute MUID value is not unique

Short Form

No short form is provided for this message type

Description

None

Message ID : DAO01659E

Severity

Error

Long Form

Attribute EXT_KID value is not unique

Short Form

No short form is provided for this message type

Description

None

Message ID : DAO0226E

Severity

Error

Message ID : DAO01658E

Long Form

Hibernate internal error.

Short Form

No short form is provided for this message type

Description

None

Message ID : DAO0242E

Severity

Error

Long Form

Host or host group "{0}" has already been guarded by policy "{1}".

Short Form

No short form is provided for this message type

Description

None

Message ID : DAO0246E**Severity**

Error

Long Form

Host or host group "{0}" is not guarded by policy "{1}". Nothing was done with the unguard operation.

Short Form

No short form is provided for this message type

Description

None

Message ID : DAO0247E**Severity**

Error

Message ID : DAO0242E

Long Form

Host "{0}" is not guarded by policy "{1}". Nothing was done with the update operation.

Short Form

No short form is provided for this message type

Description

None

Message ID : DAO0249E

Severity

Error

Long Form

Policy "{0}" does not exist.

Short Form

No short form is provided for this message type

Description

None

Message ID : DAO0250E**Severity**

Error

Long Form

There is no policy to guard host "{0}".

Short Form

No short form is provided for this message type

Description

None

Message ID : DAO0268E**Severity**

Error

Message ID : DAO0249E

Long Form

Administrator "{0}" account is locked due to multiple failed login attempts.

Short Form

account locked - multiple failed logins

Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name

Description

None

Message ID : DAO0291E

Severity

Error

Long Form

The host or host group "{0}" has already had an enabled guard with another offline policy.

Message ID : DAO0268E

Short Form

No short form is provided for this message type

Description

None

Message ID : DAO0297E

Severity

Error

Long Form

Administrator "{0}" failed to login at {1} from client with IP address {2}.

Short Form

login failed from client with IP address {5}

Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name

Message ID : DAO0291E

Label	CEF Label	Type	Usage

Description

None

Message ID : DAO0304E

Severity

Error

Long Form

Server node already exists with name "{0}". Server node name is case insensitive.

Short Form

No short form is provided for this message type

Description

None

Message ID : DAO0297E

Message ID : DAO0671E

Severity

Error

Long Form

The host with ID {0} agent type "{1}" is already in use. Specify a different host and agent type.

Short Form

No short form is provided for this message type

Description

None

Message ID : DAO0705E

Severity

Error

Long Form

The report template is invalid.

Short Form

No short form is provided for this message type

Description

None

Message ID : DAO0706E

Severity

Error

Long Form

Failed to retrieve report results.

Short Form

No short form is provided for this message type

Description

None

Message ID : DAO0807E

Severity

Error

Long Form

The same license has already been imported.

Short Form

No short form is provided for this message type

Description

None

Message ID : DAO0855E

Severity

Error

Long Form

Host license type can not be changed.

Short Form

No short form is provided for this message type

Description

None

Message ID : DAO1632E

Severity

Error

Long Form

Invalid Input Data.

Short Form

No short form is provided for this message type

Description

None

Message ID : DAO1633E

Severity

Error

Long Form

Registration Shared Secret not found.

Short Form

No short form is provided for this message type

Description

None

Message ID : DAO1634E

Severity

Error

Long Form

Cannot delete Registration Shared Secret, Since its HostGroup is shared from external.

Short Form

No short form is provided for this message type

Description

None

Message ID : DAO1635E

Severity

Error

Long Form

Registration Shared Secret not created.

Short Form

No short form is provided for this message type

Description

None

Message ID : DAO1634E

Message ID : DAO1636E

Severity

Error

Long Form

Secret not created.

Short Form

No short form is provided for this message type

Description

None

Message ID : DAO1666E

Severity

Error

Long Form

Failed adding new HA node, check if the node is reachable on port 5432, or an 'ha cleanup' from CLI is required.

Short Form

No short form is provided for this message type

Description

None

Message ID : DAO1718E

Severity

Error

Long Form

Disable Administrator settings "{0}" by administrator "{1}".

Short Form

No short form is provided for this message type

Description

None

Message ID : DAO1727E

Severity

Error

Long Form

The host is unreachable, please run network check port for host on port 5432

Short Form

No short form is provided for this message type

Description

None

Message ID : DAO1750E

Severity

Error

Long Form

Failed to generate registration token.

Message ID : DAO1727E

Short Form

No short form is provided for this message type

Description

None

Message ID : DAO1867E

Severity

Error

Long Form

This server is already in this HA cluster. You cannot add a DSM server twice to an HA cluster.

Short Form

No short form is provided for this message type

Description

None

Message ID : DAO1750E

Logger DAO: Information

Message ID : DAO0045I

Severity

Information

Long Form

Administrator "{0}" added host "{1}".

Short Form

add host

Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
shost	shost	Text	Source host name

Description

None

Message ID : DAO0046I

Severity

Information

Long Form

Administrator "{0}" deleted host "{1}".

Short Form

delete host

Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
shost	shost	Text	Source host name

Description

None

Message ID : DAO0047I

Severity

Information

Long Form

Administrator "{0}" renamed host "{1}" to "{2}".

Short Form

rename host

Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
shost	shost	Text	Source host name
altHost	vds_altHost	Text	Alternate host name in rename operations

Description

None

Message ID : DAO0048I

Severity

Information

Long Form

Administrator "{0}" updated host "{1}".

Short Form

update host

Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
shost	shost	Text	Source host name

Description

None

Message ID : DAO0049I

Severity

Information

Long Form

Administrator "{0}" updated host "{1}" unregistered agent "{2}".

Short Form

unregister agent

Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
shost	shost	Text	Source host name
agent	agent	Text	The short identifier of the agent software

Description

None

Message ID : DAO0052I

Severity

Information

Long Form

Administrator "{0}" added host group "{1}".

Short Form

add host group

Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
group	vds_group	Text	Group name

Description

None

Message ID : DAO0053I

Severity

Information

Long Form

Administrator "{0}" deleted host group "{1}".

Short Form

delete host group

Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
group	vds_group	Text	Group name

Description

None

Message ID : DAO0055I

Severity

Information

Long Form

Administrator "{0}" updated host group "{1}".

Short Form

update host group

Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
group	vds_group	Text	Group name

Description

None

Message ID : DAO0061I

Severity

Information

Long Form

Administrator "{0}" created offline policy "{1}".

Short Form

create offline policy

Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
pol	cs1	Text	Policy name

Description

None

Message ID : DAO0062I

Severity

Information

Long Form

Administrator "{0}" deleted offline policy "{1}".

Short Form

delete offline policy

Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
pol	cs1	Text	Policy name

Description

None

Message ID : DAO0063I

Severity

Information

Long Form

Administrator "{0}" updated offline policy "{1}" and renamed the policy to "{2}".

Short Form

update/rename offline policy

Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
pol	cs1	Text	Policy name
altPol	vds_altPol	Text	Alternate policy name in rename operations

Description

None

Message ID : DAO0064I

Severity

Information

Long Form

Administrator "{0}" updated offline policy "{1}".

Short Form

update offline policy

Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
pol	cs1	Text	Policy name

Description

None

Message ID : DAO00711

Severity

Information

Long Form

{0} at "{1}" created Key Pair "{2}".

Short Form

create key pair

Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
shost	shost	Text	Source host name
key	cs3	Text	Name of key or key pair

Description

None

Message ID : DAO0072I

Severity

Information

Long Form

{0} at "{1}" deleted Key Pair "{2}".

Short Form

delete key pair

Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
shost	shost	Text	Source host name
key	cs3	Text	Name of key or key pair

Description

None

Message ID : DAO0073I

Severity

Information

Long Form

Administrator "{0}" added Public Key "{1}".

Short Form

add public key

Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
key	cs3	Text	Name of key or key pair

Description

None

Message ID : DAO0074I

Severity

Information

Long Form

Administrator "{0}" deleted Public Key "{1}".

Short Form

delete public key

Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
key	cs3	Text	Name of key or key pair

Description

None

Message ID : DAO0075I

Severity

Information

Long Form

Affiliated Key "{0}" is updated. It is renamed to "{1}".

Short Form

No short form is provided for this message type

Description

None

Message ID : DAO0076I

Severity

Information

Long Form

Affiliated Key "{0}" is updated.

Short Form

No short form is provided for this message type

Description

None

Message ID : DAO0077I

Severity

Information

Long Form

Administrator "{0}" created Key Group "{1}".

Short Form

create key group

Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
group	vds_group	Text	Group name

Message ID : DAO0076I

Label	CEF Label	Type	Usage

Description

None

Message ID : DAO0078I

Severity

Information

Long Form

Administrator "{0}" deleted Key Group "{1}".

Short Form

delete key group

Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
group	vds_group	Text	Group name

Message ID : DAO0077I

Description

None

Message ID : DAO0079I

Severity

Information

Long Form

Administrator "{0}" updated Key Group "{1}" is updated. It is renamed to "{2}".

Short Form

rename key group

Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
group	vds_group	Text	Group name
altGroup	vds_altGroup	Text	Name of alternate group for multi-group operations

Description

None

Message ID : DAO0080I

Severity

Information

Long Form

Administrator "{0}" updated Key Group "{1}".

Short Form

update key group

Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
group	vds_group	Text	Group name

Description

None

Message ID : DAO0082I

Severity

Information

Long Form

Administrator "{0}" updated Security Server configuration "{1}" from "{2}" to "{3}".

Short Form

update config value

Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name

Description

None

Message ID : DAO0080I

Message ID : DAO0083I

Severity

Information

Long Form

Administrator "{0}" added agent logging configuration for Host "{1}".

Short Form

No short form is provided for this message type

Description

None

Message ID : DAO0084I

Severity

Information

Long Form

Administrator "{0}" updated agent logging configuration for Host "{1}".

Short Form

audit config updated

Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
shost	shost	Text	Source host name

Description

None

Message ID : DAO0085I

Severity

Information

Long Form

Administrator "{0}" deleted agent logging configuration for Host "{1}".

Short Form

No short form is provided for this message type

Description

None

Message ID : DAO0086I

Severity

Information

Long Form

Administrator "{0}" updated logging configuration for the default Agent.

Short Form

No short form is provided for this message type

Description

None

Message ID : DAO0089I

Severity

Information

Long Form

Administrator "{0}" added a new {3}administrator "{1}" of user type "{2}" into the Security Server.

Short Form

add admin user

Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
user	suser	Text	User name

Description

None

Message ID : DAO0090I

Severity

Information

Long Form

Administrator "{0}" deleted {2} administrator "{1}" of user type "{3}" from the Security Server.

Short Form

delete admin user

Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
user	suser	Text	User name

Description

None

Message ID : DAO0091I

Severity

Information

Long Form

Administrator "{0}" updated administrator "{1}" in the Security Server{2}.

Short Form

updated admin user

Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
user	suser	Text	User name

Description

None

Message ID : DAO0092I

Severity

Information

Long Form

Administrator "{0}" resets the password for administrator "{1}".

Short Form

reset admin user password

Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
user	suser	Text	User name

Description

None

Message ID : DAO0093I

Severity

Information

Long Form

Administrator "{0}" resets his/her own password.

Short Form

reset own password

Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name

Description

None

Message ID : DAO01286I

Severity

Information

Long Form

Status updated for host {0}

Short Form

```
{0} {1} CEF:0|Vormetric, Inc.|dsm|{3}|DAO13001I|host status updated|3|cs4Label=logger cs4=DAO spid={2} rt={4} dvchost={1}
```

Parameters

Label	CEF Label	Type	Usage
shost	shost	Text	Source host name

Description

None

Message ID : DAO01287I

Severity

Information

Message ID : DAO01286I

Long Form

"{0} certificates with issuer ID {1} were deleted".

Short Form

delete certificate

Parameters

No parameters are provided for this message type

Description

None

Message ID : DAO01332I

Severity

Information

Long Form

User {0} generated a symmetric key {1}.

Short Form

generated a symmetric key

Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
key	cs3	Text	Name of key or key pair

Description

None

Message ID : DAO01333I

Severity

Information

Long Form

User {0} manually created a symmetric key {1}.

Message ID : DAO01332I

Short Form

manually created a symmetric key

Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
key	cs3	Text	Name of key or key pair

Description

None

Message ID : DAO01340I

Severity

Information

Long Form

Administrator {0} created LDT Schedule {1}

Message ID : DAO01333I

Short Form

created LDT Schedule

Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name

Description

None

Message ID : DAO01341I

Severity

Information

Long Form

Administrator {0} updated LDT Schedule {1}

Short Form

updated LDT Schedule

Message ID : DAO01340I

Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name

Description

None

Message ID : DAO01345I

Severity

Information

Long Form

Administrator {0} deleted LDT Schedule {1}

Short Form

deleted LDT Schedule

Parameters

Label	CEF Label	Type	Usage
-------	-----------	------	-------

Message ID : DAO01341I

user	suser	Text	User name
------	-------	------	--------------

Description

None

Message ID : DAO01379I

Severity

Information

Long Form

Wrapper Key history created

Short Form

No short form is provided for this message type

Description

None

Message ID : DAO01345I

Message ID : DAO01380I

Severity

Information

Long Form

Wrapper Key history made current

Short Form

No short form is provided for this message type

Description

None

Message ID : DAO01381I

Severity

Information

Long Form

User Key shares for domain "{0}" deleted

Message ID : DAO01380I

Short Form

No short form is provided for this message type

Description

None

Message ID : DAO01382I

Severity

Information

Long Form

User Key shares for users "{0}" deleted

Short Form

No short form is provided for this message type

Description

None

Message ID : DAO01381I

Message ID : DAO01383I

Severity

Information

Long Form

This wrapper Key already exists for this domain

Short Form

No short form is provided for this message type

Description

None

Message ID : DAO01384I

Severity

Information

Long Form

{0} generated key based on password with "{1}" in DSM

Short Form

key generated

Parameters

No parameters are provided for this message type

Description

None

Message ID : DAO01385I

Severity

Information

Long Form

{0} deleted DSM generated key based on password with "{1}" in DSM

Short Form

{0} {1} CEF:0|Vormetric, Inc.|dsm|{3}|DAO0700I|delete password-based symmetric key|3|cs4Label=logger cs4=DAO
spid={2} rt={4} dvchost={1}

Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
key	cs3	Text	Name of key or key pair

Description

None

Message ID : DAO01386I

Severity

Information

Long Form

{0} generated SaaS key "{1}" in DSM

Short Form

No short form is provided for this message type

Message ID : DAO01385I

Description

None

Message ID : DAO01387I**Severity**

Information

Long Form

{0} retrieved DSM generated key based on password with "{1}" in DSM

Short Form

No short form is provided for this message type

Description

None

Message ID : DAO01388I**Severity**

Information

Message ID : DAO01386I

Long Form

{0} retrieved SaaS key "{1}" from DSM

Short Form

No short form is provided for this message type

Description

None

Message ID : DAO01389I

Severity

Information

Long Form

{0} deleted SaaS key "{1}" from DSM

Short Form

No short form is provided for this message type

Description

None

Message ID : DAO01509I

Severity

Information

Long Form

User {0} requested security configuration re-push for host {1}

Short Form

No short form is provided for this message type

Description

None

Message ID : DAO01510I

Severity

Information

Message ID : DAO01389I

Long Form

User "{0}" imported policy "{1}"

Short Form

imported policy

Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name

Description

None

Message ID : DAO01519I

Severity

Information

Long Form

Administrator "{0}" updated host group settings for the host "{1}" with host group "{2}" settings.

Message ID : DAO01510I

Short Form

No short form is provided for this message type

Description

None

Message ID : DAO01520I

Severity

Information

Long Form

Administrator "{0}" removed the host group host settings inheritance for "{1}".

Short Form

No short form is provided for this message type

Description

None

Message ID : DAO01519I

Message ID : DAO01542I

Severity

Information

Long Form

Certificate with Id = {0} deleted by {1} of {2}.

Short Form

No short form is provided for this message type

Description

None

Message ID : DAO0227I

Severity

Information

Long Form

User "{0}" deleted the signature for file "{1}".

Short Form

delete file signature

Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
filePath	filePath	Text	Full path to file

Description

None

Message ID : DAO0228I

Severity

Information

Long Form

Signature added by "{0}" to signature reference "{1}".

Short Form

add signature to set

Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
set	vds_set	Text	A set name in a policy for user, resource, process, or time sets

Description

None

Message ID : DAO0229I

Severity

Information

Long Form

Administrator "{0}" added guardpoint "{1}" with policy "{2}" on host "{3}".

Short Form

add guardpoint

Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
gp	fileId	Text	Guardpoint base directory
pol	cs1	Text	Policy name
shost	shost	Text	Source host name

Description

None

Message ID : DAO0230I

Severity

Information

Long Form

Administrator "{0}" added guardpoint "{1}" with policy "{2}" on host "{3}". The guardpoint is disabled because the same path is already guarded.

Message ID : DAO0229I

Short Form

add disabled guardpoint

Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
gp	fileId	Text	Guardpoint base directory
pol	cs1	Text	Policy name
shost	shost	Text	Source host name

Description

None

Message ID : DAO02311

Severity

Information

Long Form

Administrator "{0}" added guardpoint "{1}" with policy "{2}" on host group "{3}".

Message ID : DAO02301

Short Form

add group guardpoint

Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
gp	fileId	Text	Guardpoint base directory
pol	cs1	Text	Policy name
group	vds_group	Text	Group name

Description

None

Message ID : DAO0232I

Severity

Information

Long Form

Administrator "{0}" added guardpoint "{1}" with policy "{2}" on host group "{3}". The guardpoint is disabled because the same path is already guarded by policy "{2}".

Message ID : DAO0231I

Short Form

add disabled group guardpoint

Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
gp	fileId	Text	Guardpoint base directory
pol	cs1	Text	Policy name
group	vds_group	Text	Group name

Description

None

Message ID : DAO0233I

Severity

Information

Long Form

Host "{0}" is guarded due to the guardpoint "{1}" with policy "{2}" configured on host group "{3}".

Message ID : DAO0232I

Short Form

No short form is provided for this message type

Description

None

Message ID : DAO0234I

Severity

Information

Long Form

The inherited host group "{3}" guardpoint "{1}" with policy "{2}" on Host "{0}" is disabled due to conflict.

Short Form

No short form is provided for this message type

Description

None

Message ID : DAO0235I

Severity

Information

Long Form

Administrator "{0}" updated guardpoint "{1}" with policy "{2}" on host "{3}".

Short Form

update guardpoint

Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
gp	fileId	Text	Guardpoint base directory
pol	cs1	Text	Policy name
shost	shost	Text	Source host name

Description

None

Message ID : DAO0236I

Severity

Information

Long Form

Administrator "{0}" updated guardpoint "{1}" with policy "{2}" on host group "{3}".

Short Form

update group guardpoint

Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
gp	fileId	Text	Guardpoint base directory
pol	cs1	Text	Policy name
group	vds_group	Text	Group name

Description

None

Message ID : DAO0237I

Severity

Information

Long Form

Administrator "{0}" deleted guardpoint "{1}" with policy "{2}" on host "{3}".

Short Form

delete guardpoint

Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
gp	fileId	Text	Guardpoint base directory
pol	cs1	Text	Policy name
shost	shost	Text	Source host name

Description

None

Message ID : DAO0238I

Severity

Information

Long Form

Administrator "{0}" deleted guardpoint "{1}" with policy "{2}" on host group "{3}".

Short Form

delete group guardpoint

Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
gp	fileId	Text	Guardpoint base directory
pol	cs1	Text	Policy name
group	vds_group	Text	Group name

Description

None

Message ID : DAO0239I

Severity

Information

Long Form

{0} at "{1}" created Symmetric Key "{2}".

Short Form

create symmetric key

Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
shost	shost	Text	Source host name
key	cs3	Text	Name of key or key pair

Description

None

Message ID : DAO0240I

Severity

Information

Long Form

{0} at "{1}" deleted Symmetric Key "{2}".

Short Form

delete symmetric key

Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
shost	shost	Text	Source host name
key	cs3	Text	Name of key or key pair

Description

None

Message ID : DAO0241I

Severity

Information

Long Form

Administrator "{0}" guarded host "{1}" with policy "{2}".

Short Form

add host guard

Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
shost	shost	Text	Source host name
pol	cs1	Text	Policy name

Description

None

Message ID : DAO0243I

Severity

Information

Long Form

Administrator "{0}" guarded host group "{1}" with policy "{2}".

Short Form

add host group guard

Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
group	vds_group	Text	Group name
pol	cs1	Text	Policy name

Description

None

Message ID : DAO0244I

Severity

Information

Long Form

Administrator "{0}" removed the guarding of host "{1}" by policy "{2}".

Short Form

remove host guard

Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
shost	shost	Text	Source host name
pol	cs1	Text	Policy name

Description

None

Message ID : DAO0245I

Severity

Information

Long Form

Administrator "{0}" removed the guarding of host group "{1}" by policy "{2}".

Short Form

remove host group guard

Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
group	vds_group	Text	Group name
pol	cs1	Text	Policy name

Description

None

Message ID : DAO0248I

Severity

Information

Long Form

Administrator "{0}" enabled the guarding of host "{1}" by policy "{2}".

Short Form

enable host guard

Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
shost	shost	Text	Source host name
pol	cs1	Text	Policy name

Description

None

Message ID : DAO0251I

Severity

Information

Long Form

Administrator "{0}" enabled the guarding of host group "{1}" by policy "{2}".

Short Form

enable host group guard

Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
group	vds_group	Text	Group name
pol	cs1	Text	Policy name

Description

None

Message ID : DAO0252I

Severity

Information

Long Form

Administrator "{0}" disabled the guarding of host group "{1}" by policy "{2}".

Short Form

disable host group guard

Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
group	vds_group	Text	Group name
pol	cs1	Text	Policy name

Description

None

Message ID : DAO0253I

Severity

Information

Long Form

Administrator "{0}" disabled the guarding of host "{1}" by policy "{2}".

Short Form

disable host guard

Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
shost	shost	Text	Source host name
pol	cs1	Text	Policy name

Description

None

Message ID : DAO0254I

Severity

Information

Long Form

Administrator "{0}" added host "{1}" into host group "{2}".

Short Form

add host to group

Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
shost	shost	Text	Source host name
group	vds_group	Text	Group name

Description

None

Message ID : DAO0255I

Severity

Information

Long Form

Administrator "{0}" removed host "{1}" from host group "{2}".

Short Form

remove host from group

Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
shost	shost	Text	Source host name
group	vds_group	Text	Group name

Description

None

Message ID : DAO0256I

Severity

Information

Long Form

Administrator "{0}" added server node "{1}".

Short Form

No short form is provided for this message type

Description

None

Message ID : DAO0257I

Severity

Information

Long Form

Administrator "{0}" deleted server node "{1}".

Short Form

No short form is provided for this message type

Description

None

Message ID : DAO0258I

Severity

Information

Long Form

The node "{0}" of the Security Server is initialized successfully.

Short Form

No short form is provided for this message type

Description

None

Message ID : DAO0257I

Message ID : DAO0259I

Severity

Information

Long Form

Administrator "{0}" deleted the guarding of host "{1}" inherited from host group "{2}".

Short Form

No short form is provided for this message type

Description

None

Message ID : DAO0260I

Severity

Information

Long Form

Administrator "{0}" added the guarding of host "{1}" inherited from host group "{2}".

Short Form

No short form is provided for this message type

Description

None

Message ID : DAO0261I

Severity

Information

Long Form

Host "{0}" was updated due to properties inherited from host group "{1}".

Short Form

No short form is provided for this message type

Description

None

Message ID : DAO0260I

Message ID : DAO0263I

Severity

Information

Long Form

The Primary Node "{0}" of the Security Server is initialized successfully.

Short Form

No short form is provided for this message type

Description

None

Message ID : DAO0267I

Severity

Information

Long Form

{4}User "{0}", a {2} logged in at {1} from client with IP address {3}; trusted channel established.

Short Form

user logged in

Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
stime	start	Text	A start time stamp

Description

None

Message ID : DAO0269I

Severity

Information

Long Form

Administrator "{0}" account is unlocked.

Message ID : DAO0267I

Short Form

account unlocked

Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name

Description

None

Message ID : DAO0280I

Severity

Information

Long Form

Administrator "{0}" created online policy "{1}".

Short Form

create online policy

Message ID : DAO0269I

Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
pol	cs1	Text	Policy name

Description

None

Message ID : DAO0281I

Severity

Information

Long Form

Administrator "{0}" deleted online policy "{1}".

Short Form

delete online policy

Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
pol	cs1	Text	Policy name

Description

None

Message ID : DAO0282I

Severity

Information

Long Form

Administrator "{0}" updated online policy "{1}".

Short Form

update online policy

Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
pol	cs1	Text	Policy name

Description

None

Message ID : DAO0305I

Severity

Information

Long Form

Administrator "{0}" updated the password policy to "{1}".

Short Form

update password policy

Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name

Description

None

Message ID : DAO0317I

Severity

Information

Long Form

User "{0}" changed the password.

Short Form

change password

Parameters

Label	CEF Label	Type	Usage
-------	-----------	------	-------

Message ID : DAO0305I

user	suser	Text	User name
------	-------	------	-----------

Description

None

Message ID : DAO0401I

Severity

Information

Long Form

System Administrator {0} created domain {1}.

Short Form

create domain

Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
domain	dntdom	Text	A domain name (policy, network, users, etc)

Message ID : DAO0317I

Label	CEF Label	Type	Usage

Description

None

Message ID : DAO0402I

Severity

Information

Long Form

System Administrator {0} deleted domain {1}.

Short Form

delete domain

Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
domain	dntdom	Text	A domain name (policy, network, users, etc)

Message ID : DAO0401I

Description

None

Message ID : DAO0404I

Severity

Information

Long Form

System Administrator {0} updated domain {1}.

Short Form

update domain

Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
domain	dntdom	Text	A domain name (policy, network, users, etc)

Description

None

Message ID : DAO0405I

Severity

Information

Long Form

Administrator {0} added user {1} with roles {3} to the domain {2}.

Short Form

add user to domain

Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
user	suser	Text	User name
domain	dntdom	Text	A domain name (policy, network, users, etc)

Message ID : DAO0404I

Description

None

Message ID : DAO0406I

Severity

Information

Long Form

Domain Administrator {0} removed user {1} from the domain.

Short Form

remove user from domain

Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
user	suser	Text	User name

Message ID : DAO0405I

Description

None

Message ID : DAO0407I

Severity

Information

Long Form

Administrator "{0}" updated domain "{1}" {2} default license type for registration shared secret from {3} to {4}.

Short Form

updated default license type for registration shared secret

Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
domain	dntdom	Text	A domain name (policy, network, users, etc)

Description

None

Message ID : DAO0408I

Severity

Information

Long Form

Administrator "{0}" initialized domain "{1}" {2} default license type for registration shared secret to {3}.

Short Form

initialized default license type for registration shared secret

Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
domain	dntdom	Text	A domain name (policy, network, users, etc)

Description

None

Message ID : DAO0412I

Severity

Information

Long Form

Security Administrator "{0}" allowed host "{1}" to be shared with domain "{2}".

Short Form

allow host share with domain

Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
shost	shost	Text	Source host name
domain	dntdom	Text	A domain name (policy, network, users, etc)

Message ID : DAO0408I

Description

None

Message ID : DAO0413I

Severity

Information

Long Form

Security Administrator "{0}" disallowed host "{1}" to be shared with domain "{2}".

Short Form

disallow host share with domain

Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
shost	shost	Text	Source host name
domain	dntdom	Text	A domain name (policy, network, users, etc)

Message ID : DAO0412I

Description

None

Message ID : DAO0414I

Severity

Information

Long Form

Security Administrator "{0}" allowed host group "{1}" to be shared with domain "{2}".

Short Form

allow host group share with domain

Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
group	vds_group	Text	Group name
domain	dntdom	Text	A domain name (policy, network, users, etc)

Message ID : DAO0413I

Description

None

Message ID : DAO0415I

Severity

Information

Long Form

Security Administrator "{0}" disallowed host group "{1}" to be shared with domain "{2}".

Short Form

disallow host group share with domain

Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
group	vds_group	Text	Group name
domain	dntdom	Text	A domain name (policy, network, users, etc)

Description

None

Message ID : DAO0423I

Severity

Information

Long Form

Administrator {0} is disabled in domain {1} because of password reset.

Short Form

admin disabled in domain

Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
domain	dntdom	Text	A domain name (policy, network, users, etc)

Description

None

Message ID : DAO0424I

Severity

Information

Long Form

Administrator {0} disabled user {1} in the domain.

Short Form

disable user in domain

Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
user	suser	Text	User name

Message ID : DAO0423I

Description

None

Message ID : DAO0425I

Severity

Information

Long Form

Administrator {0} enabled user {1} in the domain {2}.

Short Form

enable user in domain

Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
user	suser	Text	User name

Message ID : DAO0424I

Description

None

Message ID : DAO0426I

Severity

Information

Long Form

The Administrator "{0}" switched to the domain at {1}.

Short Form

switch domain

Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name

Description

None

Message ID : DAO0425I

Message ID : DAO0445I

Severity

Information

Long Form

Administrator {0} added SysLog Host {1}.

Short Form

add syslog host

Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
shost	shost	Text	Source host name

Description

None

Message ID : DAO0446I

Severity

Information

Long Form

Administrator {0} deleted SysLog Host {1}.

Short Form

delete syslog host

Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
shost	shost	Text	Source host name

Description

None

Message ID : DAO0447I

Severity

Information

Long Form

OTP token {0} binding updated by user {1}.

Short Form

OTP binding update

Parameters

Label	CEF Label	Type	Usage
token	vds_token	Text	A token name (e.g. for one-time-passwords)
user	suser	Text	User name

Description

None

Message ID : DAO0449I

Severity

Information

Long Form

OTP configuration updated its property {0}.

Short Form

OTP configuration update

Parameters

Label	CEF Label	Type	Usage
property	vds_property	Text	A property name (e.g. for one-time-passwords)

Description

None

Message ID : DAO0460I

Severity

Information

Long Form

SNMP MIB entry updated: {0} = {1}.

Short Form

snmp mib update

Parameters

Label	CEF Label	Type	Usage
oid	vds_oid	Text	Object ID (e.g. for SNMP MIB)
val	vds_val	Numeric	A value string (e.g. for SNMP MIB)

Description

None

Message ID : DAO0461I

Severity

Information

Long Form

Allowed SNMP host {0} added.

Short Form

allowed SNMP host add

Parameters

Label	CEF Label	Type	Usage
shost	shost	Text	Source host name

Description

None

Message ID : DAO0462I

Severity

Information

Message ID : DAO0461I

Long Form

Allowed SNMP host {0} deleted.

Short Form

allowed SNMP host delete

Parameters

Label	CEF Label	Type	Usage
shost	shost	Text	Source host name

Description

None

Message ID : DAO0501I

Severity

Information

Long Form

Administrator "{0}" marked guardpoint "{1}" with policy "{2}" pending delete on host "{3}".

Message ID : DAO0462I

Short Form

marked guardpoint pending delete

Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
gp	fileId	Text	Guardpoint base directory
pol	cs1	Text	Policy name
shost	shost	Text	Source host name

Description

None

Message ID : DAO0502I

Severity

Information

Long Form

Administrator "{0}" deleted pending guardpoint "{1}" with policy "{2}" on host "{3}".

Message ID : DAO0501I

Short Form

delete pending guardpoint

Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
gp	fileId	Text	Guardpoint base directory
pol	cs1	Text	Policy name
shost	shost	Text	Source host name

Description

None

Message ID : DAO0518I

Severity

Information

Long Form

Administrator "{0}" exported server backup key.

Message ID : DAO0502I

Short Form

export server backup key

Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name

Description

None

Message ID : DAO0519I

Severity

Information

Long Form

Number of key shares or users is null, empty, or do not equal each other.

Short Form

No short form is provided for this message type

Message ID : DAO0518I

Description

None

Message ID : DAO0546I

Severity

Information

Long Form

Administrator "{0}" submitted a server backup key share.

Short Form

submit server backup key share

Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name

Description

None

Message ID : DAO0519I

Message ID : DAO0560I

Severity

Information

Long Form

Administrator "{0}" created resource set "{1}" with {2}.

Short Form

create resource set

Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
set	vds_set	Text	A set name in a policy for user, resource, process, or time sets

Description

None

Message ID : DAO0561I

Severity

Information

Long Form

Administrator "{0}" deleted resource set "{1}".

Short Form

delete resource set

Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
set	vds_set	Text	A set name in a policy for user, resource, process, or time sets

Description

None

Message ID : DAO0562I

Severity

Information

Long Form

Administrator "{0}" updated resource set "{1}" with {2}.

Short Form

update resource set

Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
set	vds_set	Text	A set name in a policy for user, resource, process, or time sets

Description

None

Message ID : DAO0563I

Severity

Information

Long Form

Administrator "{0}" created process set "{1}" with {2}.

Short Form

create process set

Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
set	vds_set	Text	A set name in a policy for user, resource, process, or time sets

Description

None

Message ID : DAO0564I

Severity

Information

Long Form

Administrator "{0}" deleted process set "{1}".

Short Form

delete process set

Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
set	vds_set	Text	A set name in a policy for user, resource, process, or time sets

Description

None

Message ID : DAO0565I

Severity

Information

Long Form

Administrator "{0}" updated process set "{1}" with {2}.

Short Form

update process set

Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
set	vds_set	Text	A set name in a policy for user, resource, process, or time sets

Description

None

Message ID : DAO0566I

Severity

Information

Long Form

Administrator "{0}" created user set "{1}" with {2}.

Short Form

create user set

Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
set	vds_set	Text	A set name in a policy for user, resource, process, or time sets

Description

None

Message ID : DAO0567I

Severity

Information

Long Form

Administrator "{0}" deleted user set "{1}".

Short Form

delete user set

Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
set	vds_set	Text	A set name in a policy for user, resource, process, or time sets

Description

None

Message ID : DAO0568I

Severity

Information

Long Form

Administrator "{0}" updated user set "{1}" with {2}.

Short Form

update user set

Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
set	vds_set	Text	A set name in a policy for user, resource, process, or time sets

Description

None

Message ID : DAO0569I

Severity

Information

Long Form

Administrator "{0}" created time set "{1}" with {2}.

Short Form

create time set

Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
set	vds_set	Text	A set name in a policy for user, resource, process, or time sets

Description

None

Message ID : DAO0570I

Severity

Information

Long Form

Administrator "{0}" deleted time set "{1}".

Short Form

delete time set

Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
set	vds_set	Text	A set name in a policy for user, resource, process, or time sets

Description

None

Message ID : DAO0571I

Severity

Information

Long Form

Administrator "{0}" updated time set "{1}" with {2}.

Short Form

update time set

Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
set	vds_set	Text	A set name in a policy for user, resource, process, or time sets

Description

None

Message ID : DAO0573I

Severity

Information

Long Form

Host "{0}" assigned to Server Node "{1}".

Short Form

assign host to server

Parameters

Label	CEF Label	Type	Usage
shost	shost	Text	Source host name
shost	shost	Text	Source host name

Description

None

Message ID : DAO0576I

Severity

Information

Long Form

Administrator "{0}" updated key "{1}".

Short Form

update key

Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
key	cs3	Text	Name of key or key pair

Description

None

Message ID : DAO0578I

Severity

Information

Long Form

User "{0}" added the signature reference "{1}".

Short Form

add signature set

Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
set	vds_set	Text	A set name in a policy for user, resource, process, or time sets

Description

None

Message ID : DAO0579I

Severity

Information

Long Form

User "{0}" deleted the signature reference "{1}".

Short Form

delete signature set

Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
set	vds_set	Text	A set name in a policy for user, resource, process, or time sets

Description

None

Message ID : DAO0606I

Severity

Information

Long Form

Administrator "{0}" notified all hosts.

Short Form

notify all hosts

Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name

Description

None

Message ID : DAO0638I

Severity

Information

Long Form

Administrator "{0}" created CA with URL "{1}".

Short Form

create CA

Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
url	request	Text	A uniform resource location

Description

None

Message ID : DAO0639I

Severity

Information

Long Form

Administrator "{0}" deleted CA with URL "{1}".

Short Form

delete CA

Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
url	request	Text	A uniform resource location

Description

None

Message ID : DAO0640I

Severity

Information

Long Form

Administrator "{0}" updated CA with URL "{1}".

Short Form

update CA

Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
url	request	Text	A uniform resource location

Description

None

Message ID : DAO0641I

Severity

Information

Long Form

Administrator "{0}" retrieved CA with URL "{1}".

Short Form

retrieve CA

Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
url	request	Text	A uniform resource location

Description

None

Message ID : DAO0659I

Severity

Information

Long Form

Administrator {0} updated SysLog Host {1}.

Short Form

update syslog host

Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
shost	shost	Text	Source host name

Description

None

Message ID : DAO0672I

Severity

Information

Long Form

Administrator "{0}" registered the agent for the agent type "{1}".

Short Form

register agent

Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
agent	deviceProcessName	Text	The short identifier of the agent software

Description

None

Message ID : DAO0673I

Severity

Information

Long Form

Administrator "{0}" updated agent for the agent type "{1}".

Short Form

update agent

Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
agent	deviceProcessName	Text	The short identifier of the agent software

Description

None

Message ID : DAO0674I

Severity

Information

Long Form

{0} at "{1}" created Key Attribute "{2}".

Short Form

create key attribute

Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
shost	shost	Text	Source host name
showStr	reason	Text	Code specifying reason for allowing access, if any

Description

None

Message ID : DAO0675I

Message ID : DAO0674I

Severity

Information

Long Form

{0} at "{1}" deleted Key Attribute "{2}".

Short Form

delete key attribute

Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
shost	shost	Text	Source host name
showStr	reason	Text	Code specifying reason for allowing access, if any

Description

None

Message ID : DAO0676I

Message ID : DAO0675I

Severity

Information

Long Form

{0} at "{1}" updated Key Attribute "{2}".

Short Form

update key Attribute

Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
shost	shost	Text	Source host name
showStr	reason	Text	Code specifying reason for allowing access, if any

Description

None

Message ID : DAO0677I

Message ID : DAO0676I

Severity

Information

Long Form

{0} at "{1}" updated Key Attribute "{2}". It is renamed to "{3}".

Short Form

update key Attribute which is renamed

Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
shost	shost	Text	Source host name
showStr	reason	Text	Code specifying reason for allowing access, if any
altAttr	vds_altAttr	Text	Name of alternate attribute for multi-attribute operations

Description

None

Message ID : DAO0678I

Severity

Information

Long Form

Administrator "{0}" created Key Template "{1}".

Short Form

create key template

Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
template	vds_template	Text	Key template name

Description

None

Message ID : DAO0679I

Severity

Information

Long Form

Administrator "{0}" updated Key Template "{1}".

Short Form

update key template

Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
template	vds_template	Text	Key template name

Description

None

Message ID : DAO0680I

Severity

Information

Long Form

Administrator "{0}" updated Key Template "{1}" is updated. It is renamed to "{2}".

Short Form

updated/rename key template

Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
template	vds_template	Text	Key template name
altTemplate	vds_altTemplate	Text	Alternate template name in rename operations

Description

None

Message ID : DAO0681I

Severity

Information

Long Form

Administrator "{0}" deleted Key Template "{1}".

Short Form

delete key template

Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
template	vds_template	Text	Key template name

Description

None

Message ID : DAO0682I

Severity

Information

Long Form

Administrator "{0}" created Key Template Attribute "{1}".

Short Form

create key template attribute

Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
showStr	reason	Text	Code specifying reason for allowing access, if any

Description

None

Message ID : DAO0683I

Severity

Information

Long Form

Administrator "{0}" updated Key Template Attribute "{1}".

Short Form

update key template attribute

Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
showStr	reason	Text	Code specifying reason for allowing access, if any

Description

None

Message ID : DAO0684I

Severity

Information

Long Form

Administrator "{0}" updated Key Template Attribute "{1}" is updated. It is renamed to "{2}".

Short Form

update/rename key template attribute

Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
showStr	reason	Text	Code specifying reason for allowing access, if any
altAttr	vds_altAttr	Text	Name of alternate attribute for multi-attribute operations

Description

None

Message ID : DAO0685I

Severity

Information

Long Form

Administrator "{0}" deleted Key Template Attribute "{1}".

Short Form

delete key template attribute

Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
showStr	reason	Text	Code specifying reason for allowing access, if any

Description

None

Message ID : DAO0697I

Severity

Information

Long Form

The user "{0}" created vault Key Pair "{1}".

Short Form

create vault key pair

Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
key	cs3	Text	Name of key or key pair

Description

None

Message ID : DAO0699I

Severity

Information

Long Form

Administrator "{0}" deleted Vault Key Pair "{1}".

Short Form

delete vault key pair

Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
key	cs3	Text	Name of key or key pair

Description

None

Message ID : DAO0700I

Severity

Information

Long Form

Administrator "{0}" deleted Vault Symmetric Key "{1}".

Short Form

delete vault symmetric key

Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
key	cs3	Text	Name of key or key pair

Description

None

Message ID : DAO0701I

Severity

Information

Long Form

Administrator "{0}" deleted opaque-object "{1}".

Short Form

delete opaque-object

Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
key	cs3	Text	Name of key or key pair

Description

None

Message ID : DAO0715I

Severity

Information

Long Form

LDAP configuration updated.

Short Form

update ldap configuration

Parameters

No parameters are provided for this message type

Description

None

Message ID : DAO0716I

Severity

Information

Message ID : DAO0715I

Long Form

LDAP user "{0}" is mapped to Security Server user "{1}".

Short Form

LDAP user mapped to Security Server

Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name

Description

None

Message ID : DAO0720I

Severity

Information

Long Form

Administrator "{0}" defined the following SMTP server: "{1}".

Message ID : DAO0716I

Short Form

define SMTP server

Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
shost	shost	Text	Source host name

Description

None

Message ID : DAO0721I

Severity

Information

Long Form

Administrator "{0}" deleted the SMTP server.

Short Form

delete SMTP server

Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name

Description

None

Message ID : DAO0722I

Severity

Information

Long Form

Administrator "{0}" updated the SMTP server from "{2}" to "{1}".

Short Form

update SMTP server

Message ID : DAO0721I

Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
shost	shost	Text	Source host name

Description

None

Message ID : DAO0723I

Severity

Information

Long Form

Administrator "{0}" added email notification group "{1}".

Short Form

add email notification group

Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
group	vds_group	Text	Group name

Description

None

Message ID : DAO0724I

Severity

Information

Long Form

Administrator "{0}" deleted email notification group "{1}".

Short Form

delete email notification group

Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
group	vds_group	Text	Group name

Description

None

Message ID : DAO0725I

Severity

Information

Long Form

Administrator "{0}" updated email notification group "{1}" from old value "{2}" to to new value "{3}".

Short Form

update email notification group

Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
group	vds_group	Text	Group name

Description

None

Message ID : DAO0790I

Severity

Information

Long Form

"Vaulted certificate {0}".

Short Form

vaulted certificate

Message ID : DAO0725I

Parameters

Label	CEF Label	Type	Usage
cert	vds_cert	Text	Certificate type or name

Description

None

Message ID : DAO0791I

Severity

Information

Long Form

{5}Certificate with Subject {0}, Issuer {1} and Id = {2} was deleted by {3} of {4}.

Short Form

delete certificate

Parameters

Label	CEF Label	Type	Usage
-------	-----------	------	-------

Message ID : DAO0790I

cert	vds_cert	Text	Certificate type or name
------	----------	------	--------------------------

Description

None

Message ID : DAO0792I

Severity

Information

Long Form

"Certificate with ID = {0} was updated".

Short Form

update certificate

Parameters

Label	CEF Label	Type	Usage
cert	vds_cert	Text	Certificate type or name

Message ID : DAO0791I

Description

None

Message ID : DAO0803I

Severity

Information

Long Form

{0} at "{1}" created Vault Symmetric Key "{2}".

Short Form

create vault symmetric key

Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
shost	shost	Text	Source host name
key	cs3	Text	Name of key or key pair

Message ID : DAO0792I

Description

None

Message ID : DAO0804I**Severity**

Information

Long Form

Administrator already exists.

Short Form

No short form is provided for this message type

Description

None

Message ID : DAO0850I**Severity**

Information

Message ID : DAO0803I

Long Form

Administrator "{0}" updated host "{1}" license type to {2}.

Short Form

update host license type

Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
shost	shost	Text	Source host name
lType	vds_lType	Text	A license type

Description

None

Message ID : DAO1265I

Severity

Information

Message ID : DAO0850I

Long Form

The user "{0}" imported {1} vault Key Pairs.

Short Form

```
import vault key pairs
```

Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
keys	vds_keys	Text	List of key names

Description

None

Message ID : DAO1266I

Severity

Information

Message ID : DAO1265I

Long Form

{0} at "{1}" imported {2} Symmetric Keys.

Short Form

```
import symmetric keys
```

Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
shost	shost	Text	Source host name
keys	vds_keys	Text	List of key names

Description

None

Message ID : DAO1281I

Severity

Information

Message ID : DAO1266I

Long Form

Administrator "{0}" assigned roles {3} to user "{1}" in the domain "{2}" to replace old roles {4}.

Short Form

```
{0} {1} CEF:0|Vormetric, Inc.|dsm|{3}|DAO0405I|assigned roles to user in domain|3|cs4Label=logger cs4=DAO spid={2}  
rt={4} dvchost={1}
```

Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
user	suser	Text	User name
domain	dntdom	Text	A domain name (policy, network, users, etc)

Description

None

Message ID : DAO1353I

Severity

Information

Message ID : DAO1281I

Long Form

Administrator "{0}" updated host password for host "{1}".

Short Form

update host password

Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
shost	shost	Text	Source host name

Description

None

Message ID : DAO1364I

Severity

Information

Message ID : DAO1353I

Long Form

Administrator "{0}" update "{1}" log setting from "{2}" to "{3}".

Short Form

update log setting

Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
shost	shost	Text	Source host name

Description

None

Message ID : DAO1410I

Severity

Information

Message ID : DAO1364I

Long Form

All Administrators disabled in domain "{0}".

Short Form

No short form is provided for this message type

Description

None

Message ID : DAO1500I

Severity

Information

Long Form

{0} at "{1}" updated Key Attributes "{2}" for key "{3}".

Short Form

update key Attributes

Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
shost	shost	Text	Source host name
showStr	reason	Text	Code specifying reason for allowing access, if any

Description

None

Message ID : DAO1524I

Severity

Information

Long Form

{0} at "{1}" updated key-state from "{2}" to "{3}" for key "{4}" with version "{5}" and UUID "{6}".

Short Form

key-state updated

Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
shost	shost	Text	Source host name
showStr	reason	Text	Code specifying reason for allowing access, if any
key	key	Text	Name of key or key pair
version	version	Text	Software version string

Description

None

Message ID : DAO1530I

Severity

Information

Long Form

{0} at "{1}" updated key-state-action from "{2}" to "{3}" for key "{4}" with version "{5}" and UUID "{6}".

Short Form

key-state-action updated

Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
shost	shost	Text	Source host name
showStr	reason	Text	Code specifying reason for allowing access, if any
key	key	Text	Name of key or key pair
version	version	Text	Software version string

Description

None

Message ID : DAO1536I

Severity

Information

Message ID : DAO1530I

Long Form

{0} retrieved SaaS asymmetric key with "{1}" in DSM

Short Form

No short form is provided for this message type

Description

None

Message ID : DAO1537I

Severity

Information

Long Form

{0} generated SaaS asymmetric key with name "{2}" with "{1}" host in DSM

Short Form

No short form is provided for this message type

Message ID : DAO1536I

Description

None

Message ID : DAO1538I

Severity

Information

Long Form

{0} deleted SaaS asymmetric key with name "{2}" with "{1}" domain in DSM

Short Form

No short form is provided for this message type

Description

None

Message ID : DAO1539I

Severity

Information

Message ID : DAO1537I

Long Form

certificates for domain with Id {0} and type {1} are deleted.

Short Form

No short form is provided for this message type

Description

None

Message ID : DAO1541I

Severity

Information

Long Form

{0} with Subject {1}, Issuer {2} and Id = {3} was added by {4} of {5}.

Short Form

No short form is provided for this message type

Description

None

Message ID : DAO1560I

Severity

Information

Long Form

{0} imported external symmetric key with name "{2}" with "{1}" host in DSM.

Short Form

imported external symmetric key

Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
shost	shost	Text	Source host name
key	key	Text	Name of key or key pair

Description

None

Message ID : DAO1624I

Severity

Information

Long Form

User "{0}" created identity "{1}".

Short Form

created identity

Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name

Description

None

Message ID : DAO1560I

Message ID : DAO1625I

Severity

Information

Long Form

User "{0}" updated identity "{1}".

Short Form

updated identity

Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name

Description

None

Message ID : DAO1626I

Severity

Information

Long Form

User "{0}" deleted identity "{1}".

Short Form

deleted identity

Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name

Description

None

Message ID : DAO1739I

Severity

Information

Message ID : DAO1626I

Long Form

Administrator "{0}" updated online policy "{1}" with key rule changes.

Short Form

update online policy with key rule changes

Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
pol	cs1	Text	Policy name

Description

None

Message ID : DAO1774I

Severity

Information

Message ID : DAO1739I

Long Form

LDAP configuration deleted.

Short Form

delete ldap configuration

Parameters

No parameters are provided for this message type

Description

None

Message ID : DAO1828I

Severity

Information

Long Form

Administrator "{0}" updated host "{1}" and Host settings are updated.

Short Form

update host and host settings

Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
shost	shost	Text	Source host name

Description

None

Message ID : DAO1832I

Severity

Information

Long Form

Administrator "{0}" updated silo with "{1}" for host "{2}".

Short Form

No short form is provided for this message type

Description

None

Message ID : DAO1834I

Severity

Information

Long Form

User "{0}" updated the signature reference "{1}".

Short Form

updated signature set

Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
set	vds_set	Text	A set name in a policy for user, resource, process, or time sets

Message ID : DAO1832I

Label	CEF Label	Type	Usage

Description

None

Message ID : DAO1837I

Severity

Information

Long Form

Administrator "{0}" added a new LDAP group "{1}" of user type "{2}" into the Security Server.

Short Form

add LDAP group

Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
user	suser	Text	

Message ID : DAO1834I

Label	CEF Label	Type	Usage
			User name

Description

None

Message ID : DAO1847I

Severity

Information

Long Form

Administrator "{0}" purged all destroyed keys.

Short Form

purge all destroyed keys

Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name

Message ID : DAO1837I

Label	CEF Label	Type	Usage

Description

None

Message ID : DAO1848I

Severity

Information

Long Form

Administrator "{0}" purged destroyed key "{1}".

Short Form

purge destroyed key

Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
key	cs3	Text	Name of key or key pair

Message ID : DAO1847I

Label	CEF Label	Type	Usage

Description

None

Message ID : DAO1861I

Severity

Information

Long Form

Administrator "{0}" removed from the allowed KMIP operations list of host "{1}": {2}

Short Form

remove from allowed KMIP operations

Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
shost	shost	Text	Source host name

Description

None

Message ID : DAO1862I

Severity

Information

Long Form

Administrator "{0}" added to the allowed KMIP operations list of host "{1}": {2}

Short Form

add to allowed KMIP operations

Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
shost	shost	Text	Source host name

Description

None

Logger DAO: Warnings

Message ID : DAO01319W

Severity

Warning

Long Form

Unable to archive previous version of policy {0} because its content exceeds the 1GB limit. However the change to the policy and the meta-data of the previous version have been saved successfully

Short Form

No short form is provided for this message type

Description

None

Message ID : DAO1869W

Severity

Warning

Long Form

{0} agent on host "{1}" is still using an old client certificate.

Short Form

No short form is provided for this message type

Description

None

Logger DGV: Errors

Message ID : DGV6001E

Severity

Error

Long Form

Memory allocation failed in [{}] at line [{}]

Short Form

Out of memory

Parameters

No parameters are provided for this message type

Description

None

Message ID : DGV6002E

Severity

Error

Long Form

Data governance exception with error [{0}] in [{1}] at line [{2}]

Short Form

Exception

Parameters

No parameters are provided for this message type

Description

None

Message ID : DGV6003E

Severity

Error

Long Form

Invalid data governance connector type {0}

Short Form

Invalid connector

Parameters

No parameters are provided for this message type

Description

None

Message ID : DGV6004E

Severity

Error

Long Form

Invalid data governance data source type {0}

Short Form

Invalid data source type

Parameters

No parameters are provided for this message type

Description

None

Message ID : DGV6005E

Severity

Error

Long Form

HTTP request {0} failed with the status code {1} and message {2}

Short Form

HTTP request failed

Parameters

No parameters are provided for this message type

Description

None

Message ID : DGV6006E

Severity

Error

Long Form

UUID creation failed with error {0}

Short Form

UUID creation failed

Parameters

No parameters are provided for this message type

Message ID : DGV6005E

Description

None

Message ID : DGV6007E

Severity

Error

Long Form

Type {0} is not found

Short Form

Type not found

Parameters

No parameters are provided for this message type

Description

None

Message ID : DGV6006E

Message ID : DGV6008E

Severity

Error

Long Form

Attribute {0} value is not found

Short Form

Attribute value not found

Parameters

No parameters are provided for this message type

Description

None

Message ID : DGV6009E

Severity

Error

Message ID : DGV6008E

Long Form

Failed to get attributes for {0} with error {1}

Short Form

Failed to get file attributes

Parameters

No parameters are provided for this message type

Description

None

Message ID : DGV6010E

Severity

Error

Long Form

Failed to create the tag directory {0} with error {1}

Short Form

Failed to create tag directory

Parameters

No parameters are provided for this message type

Description

None

Message ID : DGV6011E

Severity

Error

Long Form

User {0} in domain {1} failed to connect to network path {2}. Error code {3}

Short Form

Net connect error

Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
domain	dntdom	Text	A domain name (policy, network, users, etc)
url	request	Text	A uniform resource location
ecode	cn1	Numeric	An error code

Description

None

Message ID : DGV6012E

Severity

Error

Long Form

AWS request exception {0}. Error message {1}

Short Form

AWS request error

Message ID : DGV6011E

Parameters

No parameters are provided for this message type

Description

None

Message ID : DGV6013E

Severity

Error

Long Form

Failed to add tag {0} to {1}. Error message {2}

Short Form

Failed to add tag

Parameters

No parameters are provided for this message type

Description

None

Message ID : DGV6014E

Severity

Error

Long Form

Failed to delete tag {0} from {1}. Error message {2}

Short Form

Failed to delete tag

Parameters

No parameters are provided for this message type

Description

None

Message ID : DGV6013E

Message ID : DGV6015E

Severity

Error

Long Form

Failed to initialize tag for {0}

Short Form

Failed to initialize tag

Parameters

No parameters are provided for this message type

Description

None

Message ID : DGV6016E

Severity

Error

Message ID : DGV6015E

Long Form

Failed to process tagging event. Error message {0}

Short Form

Failed to process tagging event

Parameters

No parameters are provided for this message type

Description

None

Message ID : DGV6017E

Severity

Error

Long Form

Atlas REST failed with SSL. Error message {0}

Short Form

Atlas REST failed with SSL

Parameters

No parameters are provided for this message type

Description

None

Message ID : DGV6018E

Severity

Error

Long Form

Failed to get uuid for {0}

Short Form

Failed to get uuid

Parameters

No parameters are provided for this message type

Description

None

Logger DGV: Information

Message ID : DGV6019I

Severity

Information

Long Form

Starting scan of {0}

Short Form

Starting scan

Parameters

No parameters are provided for this message type

Description

None

Message ID : DGV6020I

Severity

Information

Long Form

Finished scan of {0} in {1} seconds

Short Form

Finished scan

Parameters

No parameters are provided for this message type

Description

None

Logger DMG: Errors

Message ID : DMG0549E

Severity

Error

Long Form

Unable to remove directory "{0}".

Short Form

No short form is provided for this message type

Description

None

Message ID : DMG0550E

Severity

Error

Long Form

Unable to create directory "{0}".

Short Form

No short form is provided for this message type

Description

None

Message ID : DMG0551E

Severity

Error

Long Form

Unable to extract from the uploaded file "{0}".

Short Form

No short form is provided for this message type

Description

None

Message ID : DMG0552E**Severity**

Error

Long Form

Unable to extract policies from the archive "{0}".

Short Form

No short form is provided for this message type

Description

None

Message ID : DMG0553E**Severity**

Error

Message ID : DMG0551E

Long Form

Internal error encountered. Please check the log file for details.

Short Form

No short form is provided for this message type

Description

None

Message ID : DMG0554E

Severity

Error

Long Form

Data migration needs to be performed on a clean install. The module {0} contains data.

Short Form

No short form is provided for this message type

Description

None

Logger DMG: Information

Message ID : DMG0575I

Severity

Information

Long Form

Successfully imported Server Configuration Data.

Short Form

imported config data

Parameters

No parameters are provided for this message type

Description

None

Logger DXF: Debug messages

Message ID : DXF4308D

Severity

Debug

Long Form

No files found in directory {0}

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4310D

Severity

Debug

Long Form

Starting data transform of {0}

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4311D

Severity

Debug

Long Form

Finished data transform of {0}

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4473D

Severity

Debug

Long Form

Process {0}: error {1} opening lock file at {2}. This may be due to an already running data transform instance

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4475D

Severity

Debug

Message ID : DXF4311D

Long Form

Starting scan of {0}

Short Form

No short form is provided for this message type

Description

None

Logger DXF: Errors

Message ID : DXF3205E

Severity

Error

Long Form

The kernel component doesn't support online data transform on "{0}". Please run the data transform utility without --oxf option to transform the data offline.

Short Form

No online Xform support.

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

Description

None

Message ID : DXF3206E

Severity

Error

Long Form

Deep Scan operation is not supported with online data transformation. Please run deep scan without --oxf option.

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF3207E

Severity

Error

Long Form

Cannot open or create current status file {0} : {1}

Short Form

No current status file

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file
showStr	reason	Text	Code specifying reason for allowing access, if any

Description

None

Message ID : DXF3208E

Severity

Error

Long Form

Cannot write current status file {0} : {1}

Message ID : DXF3207E

Short Form

current status file write error

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file
showStr	reason	Text	Code specifying reason for allowing access, if any

Description

None

Message ID : DXF3209E

Severity

Error

Long Form

Invalid data in current status file {0}

Message ID : DXF3208E

Short Form

Bad current status file content

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : DXF3215E

Severity

Error

Long Form

File "{0}" Invalid xf mode.

Short Form

Invalid xf mode.

Message ID : DXF3209E

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : DXF3216E

Severity

Error

Long Form

File "{0}" vmfs get file system failed.

Short Form

vmfs get file system failed.

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Message ID : DXF3215E

Label	CEF Label	Type	Usage

Description

None

Message ID : DXF3217E

Severity

Error

Long Form

File "{0}" start self access failed.

Short Form

start self access failed.

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : DXF3218E

Severity

Error

Long Form

File "{0}" File handle is invalid.

Short Form

File handle is invalid.

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : DXF3217E

Message ID : DXF3219E

Severity

Error

Long Form

File "{0}" failed to get the inode.

Short Form

inode failure

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : DXF3220E

Severity

Error

Long Form

File "{0}" failed to get the GuardPoint MD.

Short Form

failed to get the GuardPoint MD.

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : DXF3221E

Severity

Error

Message ID : DXF3220E

Long Form

File "{0}" failed to get the inode INF information.

Short Form

inode INF failure

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : DXF3222E

Severity

Error

Long Form

File "{0}" Inode is null.

Message ID : DXF3221E

Short Form

Inode is null.

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : DXF3223E

Severity

Error

Long Form

File "{0}" failed to get the file name.

Short Form

inode name failure.

Message ID : DXF3222E

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : DXF3224E

Severity

Error

Long Form

File "{0}" validation of MD failed.

Short Form

validation of MD failed.

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Message ID : DXF3223E

Label	CEF Label	Type	Usage

Description

None

Message ID : DXF3225E

Severity

Error

Long Form

File "{0}" file MD is null.

Short Form

file MD is null.

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : DXF3226E

Severity

Error

Long Form

File "{0}" File MD is in the error state.

Short Form

File MD is in the error state.

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : DXF3225E

Message ID : DXF3227E

Severity

Error

Long Form

File "{0}" Access check failed. Please check your policy.

Short Form

Access check failed. Please check your policy.

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : DXF3228E

Severity

Error

Long Form

File "{0}" failed while quering the MD from the stream file.

Short Form

failed while quering the MD from the stream file.

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : DXF3229E

Severity

Error

Message ID : DXF3228E

Long Form

File "{0}" Invalid GP meta data.

Short Form

Invalid GP meta data.

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : DXF3230E

Severity

Error

Long Form

File "{0}" failed to get the GuardPoint file system.

Message ID : DXF3229E

Short Form

failed to get the GuardPoint file system.

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : DXF3231E

Severity

Error

Long Form

File "{0}" GuardPoint MD is null.

Short Form

GuardPoint MD is null.

Message ID : DXF3230E

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : DXF3232E

Severity

Error

Long Form

File "{0}" Rekey failed.

Short Form

Rekey failed.

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Message ID : DXF3231E

Label	CEF Label	Type	Usage

Description

None

Message ID : DXF3233E

Severity

Error

Long Form

File "{0}" Opening the file handle failed.

Short Form

Opening the file handle failed.

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Message ID : DXF3232E

Description

None

Message ID : DXF3238E

Severity

Error

Long Form

LDT-ALERT: Scan error on [{0}] removing MDS guard for relaunching dataxform.

Short Form

LDT scan error

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

Description

None

Message ID : DXF3233E

Message ID : DXF3239E

Severity

Error

Long Form

LDT-ALERT: Online Dataxfrom failed during post scan stage on [{0}]

Short Form

LDT postscan failure

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

Description

None

Message ID : DXF3240E

Severity

Error

Long Form

Failed to initialize the context for container {0}.

Short Form

failed to initialize container

Parameters

Label	Type	Usage
dockerid	Text	Docker image or container id

Description

None

Message ID : DXF3241E

Severity

Error

Message ID : DXF3240E

Long Form

The container {0} is not running.

Short Form

container not running

Parameters

Label	Type	Usage
dockerid	Text	Docker image or container id

Description

None

Message ID : DXF3242E

Severity

Error

Long Form

Verify this is a guard point with valid data transformation policy, and check the system log files for any other problems. It may be due to one or more of following reasons; 1.policy has no valid key rule(s), and/or 2. policy has no key_op rule, and/or 3. policy has

Message ID : DXF3241E

valid permit rule(s), and/or 4. policy rule that contains key_op in the action field also specifies other actions, and/or 5. verify that user has not enabled Header Style guardpoint as Offline transformation does not support header based guardpoints.

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4100E

Severity

Error

Long Form

. --deep_scan Perform scan as above with additional file

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4101E

Severity

Error

Long Form

. access checks, and estimate time required to

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4102E

Severity

Error

Message ID : DXF4100E

Long Form

. complete data transformation of guard point

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4105E

Severity

Error

Long Form

Number of files previously in error for an unknown reason: {0}

Short Form

Prev unknown file errors

Parameters

Label	CEF Label	Type	Usage
count	vds_count	Numeric	A generic count value

Description

None

Message ID : DXF4106E

Severity

Error

Long Form

Number of files in error for an unknown reason: {0}

Short Form

Unknown file errors

Parameters

Label	CEF Label	Type	Usage
count	vds_count	Numeric	A generic count value

Message ID : DXF4105E

Label	CEF Label	Type	Usage

Description

None

Message ID : DXF4107E

Severity

Error

Long Form

The file {0} was previously in error for an unknown reason

Short Form

Prev error - unknown

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Message ID : DXF4106E

Description

None

Message ID : DXF4108E

Severity

Error

Long Form

The file {0} was in error for an unknown reason

Short Form

Prev xform file in error

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : DXF4107E

Message ID : DXF4109E

Severity

Error

Long Form

Error "{0}" opening lock file in {1}

Short Form

Lock file error

Parameters

Label	CEF Label	Type	Usage
showStr	reason	Text	Code specifying reason for allowing access, if any
filePath	filePath	Text	Full path to file

Description

None

Message ID : DXF4111E

Severity

Error

Long Form

Process {0}: error "{1}" opening lock file at {2}. This may be due to an already running data transform instance

Short Form

Lock file open error

Parameters

Label	CEF Label	Type	Usage
ecode	cn1	Numeric	An error code
showStr	reason	Text	Code specifying reason for allowing access, if any
filePath	filePath	Text	Full path to file

Description

None

Message ID : DXF4112E

Severity

Error

Long Form

Error "{0}" creating lock file in {1}

Short Form

Lock file create fail

Parameters

Label	CEF Label	Type	Usage
showStr	reason	Text	Code specifying reason for allowing access, if any
filePath	filePath	Text	Full path to file

Description

None

Message ID : DXF4113E

Severity

Error

Long Form

Cannot create the data transform recovery/status file {0}, {1}

Short Form

Status file create error

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file
showStr	reason	Text	Code specifying reason for allowing access, if any

Description

None

Message ID : DXF4114E

Severity

Error

Long Form

Error "{0}" getting file info for {1}

Short Form

Stat fail

Parameters

Label	CEF Label	Type	Usage
showStr	reason	Text	Code specifying reason for allowing access, if any
filePath	filePath	Text	Full path to file

Description

None

Message ID : DXF4115E

Severity

Error

Long Form

Error "{0}" getting file attributes for {1}

Short Form

Attr fail

Parameters

Label	CEF Label	Type	Usage
showStr	reason	Text	Code specifying reason for allowing access, if any
filePath	filePath	Text	Full path to file

Description

None

Message ID : DXF4116E

Severity

Error

Long Form

Error "{0}" setting file attributes for {1}

Short Form

Attr set error

Parameters

Label	CEF Label	Type	Usage
showStr	reason	Text	Code specifying reason for allowing access, if any
filePath	filePath	Text	Full path to file

Description

None

Message ID : DXF4117E

Severity

Error

Long Form

Cannot find files in {0}, {1}

Short Form

File first error

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file
showStr	reason	Text	Code specifying reason for allowing access, if any

Description

None

Message ID : DXF4119E

Severity

Error

Long Form

Error "{0}" setting file time for {1}

Short Form

Time set error

Parameters

Label	CEF Label	Type	Usage
showStr	reason	Text	Code specifying reason for allowing access, if any
filePath	filePath	Text	Full path to file

Description

None

Message ID : DXF4120E

Severity

Error

Long Form

Cannot recover previous session as file list is missing

Short Form

Missing file list

Parameters

No parameters are provided for this message type

Description

None

Message ID : DXF4121E

Severity

Error

Long Form

Cannot perform data transform for {0}, not a directory

Short Form

Not a dir

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

Description

None

Message ID : DXF4124E

Severity

Error

Long Form

The file {0} was skipped. There was insufficient memory to process it

Message ID : DXF4121E

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4125E

Severity

Error

Long Form

The file {0} was previously skipped. There was insufficient memory to process it

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4124E

Message ID : DXF4133E

Severity

Error

Long Form

The file {0} was in error. dataxform had insufficient permission

Short Form

Bad perms

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : DXF4134E

Severity

Error

Long Form

The file {0} was previously in error. dataxform had insufficient permission

Short Form

Prev error bad perms

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : DXF4135E

Severity

Error

Message ID : DXF4134E

Long Form

Number of files in error due to insufficient permission: {0}

Short Form

Perm errors

Parameters

Label	CEF Label	Type	Usage
count	vds_count	Numeric	A generic count value

Description

None

Message ID : DXF4136E

Severity

Error

Long Form

Number of files previously in error due to insufficient permission: {0}

Message ID : DXF4135E

Short Form

Prev perm errors

Parameters

Label	CEF Label	Type	Usage
count	vds_count	Numeric	A generic count value

Description

None

Message ID : DXF4137E

Severity

Error

Long Form

The file {0} was in error. There was insufficient memory to process it

Short Form

Out of memory

Message ID : DXF4136E

Parameters

No parameters are provided for this message type

Description

None

Message ID : DXF4138E

Severity

Error

Long Form

The file {0} was previously in error. There was insufficient memory to process it

Short Form

Prev error - no memory

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Message ID : DXF4137E

Description

None

Message ID : DXF4139E

Severity

Error

Long Form

Number of files in error due to insufficient memory: {0}

Short Form

No-memory files skipped

Parameters

Label	CEF Label	Type	Usage
count	vds_count	Numeric	A generic count value

Description

None

Message ID : DXF4138E

Message ID : DXF4140E

Severity

Error

Long Form

Number of files previously in error due to insufficient memory: {0}

Short Form

Prev no-memory files skipped

Parameters

Label	CEF Label	Type	Usage
count	vds_count	Numeric	A generic count value

Description

None

Message ID : DXF4141E

Severity

Error

Long Form

Directory path too long: {0}

Short Form

Dir too long

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : DXF4142E

Severity

Error

Message ID : DXF4141E

Long Form

Unable to process directory {0}

Short Form

Dir in error

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : DXF4149E

Severity

Error

Long Form

. --preserve_sparse_files Don't encrypt file holes. Not the default

Message ID : DXF4142E

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4150E

Severity

Error

Long Form

Removal of data transformation status files completed

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4149E

Message ID : DXF4151E

Severity

Error

Long Form

Removal of data transformation status files abandoned

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4152E

Severity

Error

Long Form

Cleanup-on-success option is only valid with rekey operations

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4153E

Severity

Error

Long Form

. --cleanup_on_success Remove status files upon success

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4152E

Message ID : DXF4155E

Severity

Error

Long Form

The rekey list file provided contains an invalid entry "{0}". Please remove or correct the entry then try again.

Short Form

Invalid rekey file list entry

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : DXF4156E

Severity

Error

Long Form

. --unrecoverable Perform rekey without recording recovery data,

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4157E

Severity

Error

Long Form

. which may run considerably faster than a normal

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4158E

Severity

Error

Long Form

. rekey, but if it fails restoration of the guarded

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4159E

Severity

Error

Long Form

. data from backup will be required.

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4160E

Severity

Error

Long Form

Cannot continue a previous recoverable run with the "--unrecoverable" option set

Short Form

Prev op was recoverable rekey

Parameters

No parameters are provided for this message type

Description

None

Message ID : DXF4162E

Severity

Error

Long Form

Cannot perform data transform for {0}, failed to get HDFS file name

Short Form

Failed to get HDFS file name

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : DXF4163E

Severity

Error

Long Form

The file {0} was previously in error. Failed to get HDFS file name

Short Form

Prev error - failed to get HDFS file name

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Message ID : DXF4162E

Label	CEF Label	Type	Usage

Description

None

Message ID : DXF4164E

Severity

Error

Long Form

Number of files in error due to failure getting HDFS file name: {0}

Short Form

HDFS file name errors

Parameters

Label	CEF Label	Type	Usage
count	vds_count	Numeric	A generic count value

Message ID : DXF4163E

Description

None

Message ID : DXF4165E

Severity

Error

Long Form

Number of files previously in error due to failure getting HDFS file name: {0}

Short Form

Prev HDFS file name errors

Parameters

Label	CEF Label	Type	Usage
count	vds_count	Numeric	A generic count value

Description

None

Message ID : DXF4164E

Message ID : DXF4166E

Severity

Error

Long Form

The file {0} was in error. There was insufficient disk space to process it

Short Form

Out of disk space

Parameters

No parameters are provided for this message type

Description

None

Message ID : DXF4167E

Severity

Error

Long Form

. --cid Specify Docker container id.

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4168E

Severity

Error

Long Form

. --migrate Migrate Data from Protect File Encryption.

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4215E

Severity

Error

Long Form

The file {0} was in error. It was open and could not be modified safely

Short Form

Error open file

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : DXF4168E

Message ID : DXF4227E

Severity

Error

Long Form

The options `--preserve_sparse_files` and `--encrypt_sparse_file_holes` are mutually exclusive

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4228E

Severity

Error

Long Form

`. --preserve_sparse_files` Don't encrypt file holes. Default behavior

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4229E

Severity

Error

Long Form

. --encrypt_sparse_file_holes The opposite of --preserve_sparse_files

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4228E

Message ID : DXF4230E

Severity

Error

Long Form

. This option has the potential to increase

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4231E

Severity

Error

Long Form

. the amount of space files take up on disk

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4232E

Severity

Error

Long Form

. --buf_size Performance tuning: The size, in KB, of the

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4231E

Message ID : DXF4233E

Severity

Error

Long Form

. buffer used for transforming data

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4234E

Severity

Error

Long Form

. Range: [4..128]. Default: 128

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4235E

Severity

Error

Long Form

. --mt Performance tuning: The max. number of

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4234E

Message ID : DXF4236E

Severity

Error

Long Form

. threads that the kernel can use per file

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4237E

Severity

Error

Long Form

. Range: [1..16]. Default: 16

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4238E

Severity

Error

Long Form

. --thd Performance tuning: The max. number of

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4237E

Message ID : DXF4239E

Severity

Error

Long Form

. files to transform at once

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4240E

Severity

Error

Long Form

. Range: [1..32]. Defaults: unix:28 win:8

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4241E

Severity

Error

Long Form

More than {0} files were encountered in the directory {1}. This will consume excessive system resources. Aborting. No files have been transformed. To disable this check, rerun with the "--disable_memory_checking" flag

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4240E

Message ID : DXF4243E

Severity

Error

Long Form

. --status_interval The frequency, in seconds, of how often to

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4244E

Severity

Error

Long Form

. report status to the logs. Default: 300

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4247E

Severity

Error

Long Form

Cannot open or create directory listing file {0} : {1}

Short Form

No dir file

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file
showStr	reason	Text	Code specifying reason for allowing access, if any

Message ID : DXF4244E

Label	CEF Label	Type	Usage

Description

None

Message ID : DXF4248E

Severity

Error

Long Form

Cannot re-use invalid directory listing file {0}

Short Form

Bad dir file

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Message ID : DXF4247E

Description

None

Message ID : DXF4249E

Severity

Error

Long Form

Failed to cleanly close directory listing file {0} : {1}

Short Form

Close dir file error

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file
showStr	reason	Text	Code specifying reason for allowing access, if any

Description

None

Message ID : DXF4250E

Severity

Error

Long Form

Cannot rename directory listing file from {0} to {1} :{2}

Short Form

Rename dir file error

Parameters

Label	CEF Label	Type	Usage
oldFilePath	oldFilePath	Text	Previous path to file (for rename and link)
filePath	filePath	Text	Full path to file
showStr	reason	Text	Code specifying reason for allowing access, if any

Description

None

Message ID : DXF4251E

Severity

Error

Long Form

Invalid data in listing file {0}

Short Form

Bad dir file content

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : DXF4250E

Message ID : DXF4252E

Severity

Error

Long Form

Cannot write directory listing file {0} : {1}

Short Form

Dir file write error

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file
showStr	reason	Text	Code specifying reason for allowing access, if any

Description

None

Message ID : DXF4255E

Severity

Error

Long Form

Inconsistent data in recovery files {0} and {1}.

Short Form

Inconsistent recovery files

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file
filePath	filePath	Text	Full path to file

Description

None

Message ID : DXF4266E

Severity

Error

Long Form

Error "{0}" updating status file {1}

Short Form

File update error

Parameters

Label	CEF Label	Type	Usage
showStr	reason	Text	Code specifying reason for allowing access, if any
filePath	filePath	Text	Full path to file

Description

None

Message ID : DXF4270E

Severity

Error

Long Form

Number of files in error due to kernel component stopping data transform: {0}

Short Form

Kernel stop files errors

Parameters

Label	CEF Label	Type	Usage
count	vds_count	Numeric	A generic count value

Description

None

Message ID : DXF4271E

Severity

Error

Long Form

Number of files in error due to a signal stopping the dataxform: {0}

Short Form

Signal stop files errors

Parameters

Label	CEF Label	Type	Usage
count	vds_count	Numeric	A generic count value

Description

None

Message ID : DXF4272E

Severity

Error

Message ID : DXF4271E

Long Form

Number of files in error due to being open and could not be modified safely: {0}

Short Form

Unsafe file errors

Parameters

Label	CEF Label	Type	Usage
count	vds_count	Numeric	A generic count value

Description

None

Message ID : DXF4282E

Severity

Error

Long Form

Error "{0}" reading directory entry {1}

Message ID : DXF4272E

Short Form

Read dir error

Parameters

Label	CEF Label	Type	Usage
showStr	reason	Text	Code specifying reason for allowing access, if any
filePath	filePath	Text	Full path to file

Description

None

Message ID : DXF4286E

Severity

Error

Long Form

Number of files previously in error due to kernel component stopping data transform: {0}

Message ID : DXF4282E

Short Form

Prev kernel stop files errors

Parameters

Label	CEF Label	Type	Usage
count	vds_count	Numeric	A generic count value

Description

None

Message ID : DXF4287E

Severity

Error

Long Form

Number of files previously in error due to a signal stopping the dataxform: {0}

Short Form

Prev signal stop files errors

Message ID : DXF4286E

Parameters

Label	CEF Label	Type	Usage
count	vds_count	Numeric	A generic count value

Description

None

Message ID : DXF4288E

Severity

Error

Long Form

Number of files previously in error due to being open and could not be modified safely: {0}

Short Form

Prev unsafe file errors

Parameters

Label	CEF Label	Type	Usage
count	vds_count	Numeric	A generic count value

Message ID : DXF4287E

Label	CEF Label	Type	Usage

Description

None

Message ID : DXF4289E

Severity

Error

Long Form

Unable to read {0}: {1}

Short Form

Read info error

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file
showStr	reason	Text	Code specifying reason for allowing access, if any

Message ID : DXF4288E

Description

None

Message ID : DXF4290E

Severity

Error

Long Form

Unable to create simulation file {0}: {1}

Short Form

Create sim file error

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file
showStr	reason	Text	Code specifying reason for allowing access, if any

Description

None

Message ID : DXF4291E

Severity

Error

Long Form

Error creating directory {0}: {1}

Short Form

Create sim dir error

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file
showStr	reason	Text	Code specifying reason for allowing access, if any

Description

None

Message ID : DXF4292E

Severity

Error

Long Form

Error removing directory {0}: {1}

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4294E

Severity

Error

Message ID : DXF4291E

Long Form

About to perform a deep scan

Short Form

Deep scan start

Parameters

No parameters are provided for this message type

Description

None

Message ID : DXF4295E

Severity

Error

Long Form

-- To enable consistent results, do not access the directory during the scan

Message ID : DXF4294E

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4296E

Severity

Error

Long Form

-- Transformation simulations will be performed, which may take some time

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4295E

Message ID : DXF4297E

Severity

Error

Long Form

Filesystem containing {0} is too full to perform simulations

Short Form

FS too full

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : DXF4298E

Severity

Error

Long Form

Filesystem containing {0} is too full to create file lists

Short Form

FS too fill

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : DXF4299E

Severity

Error

Message ID : DXF4298E

Long Form

Verify this is a guard point with valid data transformation policy, and check the system log files for any other problems. It may be due to one or more of following reasons; 1.policy has no valid key rule(s), and/or 2. policy has no key_op rule, and/or 3. policy has valid permit rule(s), and/or 4. policy rule that contains key_op in the action field also specifies other actions.

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4300E

Severity

Error

Long Form

Out of Memory

Short Form

Out of memory

Parameters

No parameters are provided for this message type

Description

None

Message ID : DXF4301E

Severity

Error

Long Form

The kernel component doesn't support data transform on {0}

Short Form

No xform support

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

Message ID : DXF4300E

Description

None

Message ID : DXF4302E

Severity

Error

Long Form

Error {0} opening configuration file in {1}

Short Form

Config file error

Parameters

Label	CEF Label	Type	Usage
ecode	cn1	Numeric	An error code
filePath	filePath	Text	Full path to file

Message ID : DXF4301E

Description

None

Message ID : DXF4303E

Severity

Error

Long Form

Error {0} opening lock file in {1}

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4304E

Severity

Error

Message ID : DXF4302E

Long Form

Error {0} creating lock file in {1}

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4306E

Severity

Error

Long Form

Error invalid version {0} for configuration file in {1}

Short Form

Bad config version

Parameters

Label	CEF Label	Type	Usage
verno	vds_verno	Numeric	A version number
filePath	filePath	Text	Full path to file

Description

None

Message ID : DXF4312E

Severity

Error

Long Form

A file or directory in {0} may be corrupt or unreachable

Short Form

File inaccessible

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : DXF4313E

Severity

Error

Long Form

There was an invalid parameter while processing directory {0}

Short Form

Invalid dir param

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Message ID : DXF4312E

Label	CEF Label	Type	Usage

Description

None

Message ID : DXF4314E

Severity

Error

Long Form

Out of memory while processing directory {0}

Short Form

Out of memory processing dir

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Message ID : DXF4313E

Description

None

Message ID : DXF4315E

Severity

Error

Long Form

Error code {0} while processing directory {1}

Short Form

Dir processing error

Parameters

Label	CEF Label	Type	Usage
ecode	cn1	Numeric	An error code
filePath	filePath	Text	Full path to file

Description

None

Message ID : DXF4325E

Severity

Error

Long Form

Cannot perform data transform for {0}, does not exist

Short Form

Does not exist

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

Description

None

Message ID : DXF4315E

Message ID : DXF4326E

Severity

Error

Long Form

Cannot perform data transform for {0}, access denied

Short Form

Access denied

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

Description

None

Message ID : DXF4328E

Severity

Error

Long Form

Kernel component gave unexpected status {0}

Short Form

Unexpected kernel error

Parameters

Label	CEF Label	Type	Usage
ecode	cn1	Numeric	An error code

Description

None

Message ID : DXF4330E

Severity

Error

Message ID : DXF4328E

Long Form

No file name provided to hold recovery file list

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4331E

Severity

Error

Long Form

Cannot open {0} to get recovery file list

Short Form

List access fail

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : DXF4334E

Severity

Error

Long Form

No value provided for command line parameter {0}

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4331E

Message ID : DXF4335E

Severity

Error

Long Form

Unknown command line option {0}

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4336E

Severity

Error

Long Form

Command line must specify an operation

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4340E

Severity

Error

Long Form

Command line must specify a guard point

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4336E

Message ID : DXF4341E

Severity

Error

Long Form

Directory specified on command line does not exist, {0}

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4342E

Severity

Error

Long Form

Only one command line operation is allowed if scan is selected

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4343E

Severity

Error

Long Form

Attempt to normalize directory {0} got error code {1}

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4342E

Message ID : DXF4346E

Severity

Error

Long Form

The command line is not valid

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4347E

Severity

Error

Long Form

Unable to create the progress-reporting thread

Short Form

Thread create fail

Parameters

No parameters are provided for this message type

Description

None

Message ID : DXF4349E

Severity

Error

Long Form

Cannot set up data transform recovery/status files

Short Form

Status file setup fail

Message ID : DXF4347E

Parameters

No parameters are provided for this message type

Description

None

Message ID : DXF4350E

Severity

Error

Long Form

Cannot delete data transform status and lock files

Short Form

Status/lock file delete fail

Parameters

No parameters are provided for this message type

Description

None

Message ID : DXF4353E

Severity

Error

Long Form

Check the recovery files for errors, or run "--cleanup" option to remove them.

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4354E

Severity

Error

Message ID : DXF4350E

Long Form

Make sure any files already transformed are restored before a cleanup is done.

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4355E

Severity

Error

Long Form

As the previous dataxform run used the "--unrecoverable" option, you need to restore the GuardPoint from a backup, then use the "--cleanup" option before running the rekey operation again.

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4356E

Severity

Error

Long Form

Could not notify kernel component about data transform on {0}

Short Form

Kernel notify fail

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

Description

None

Message ID : DXF4355E

Message ID : DXF4357E

Severity

Error

Long Form

Could not restrict access to {0}

Short Form

Access restrict fail

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

Description

None

Message ID : DXF4358E

Severity

Error

Long Form

Could not allow access to {0}

Short Form

Access allow fail

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

Description

None

Message ID : DXF4360E

Severity

Error

Message ID : DXF4358E

Long Form

Could not complete data transform, the policy for guard point {0} changed

Short Form

Policy changed

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

Description

None

Message ID : DXF4367E

Severity

Error

Long Form

Data transform got errors on some files

Message ID : DXF4360E

Short Form

Prev xform fail

Parameters

No parameters are provided for this message type

Description

None

Message ID : DXF4368E

Severity

Error

Long Form

The file {0} could not be transformed in the previous data transform, it will not be transformed

Short Form

Prev file xform fail

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : DXF4376E

Severity

Error

Long Form

Data transform in guard point {0} failed for {1} files

Short Form

Prev xform failures

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

Message ID : DXF4368E

Label	CEF Label	Type	Usage
nfile	vds_nfile	Numeric	The number of files processed

Description

None

Message ID : DXF4377E

Severity

Error

Long Form

Error while scanning for hard links in directory {0}

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4379E

Severity

Error

Long Form

Error scanning guard point {0} while processing directory {1}

Short Form

Scan error

Parameters

Label	CEF Label	Type	Usage
showStr	reason	Text	Code specifying reason for allowing access, if any
filePath	filePath	Text	Full path to file

Description

None

Message ID : DXF4381E

Severity

Error

Long Form

Error scanning guard point {0}

Short Form

Scan fail

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

Description

None

Message ID : DXF4382E

Severity

Error

Long Form

Automatic data transform cannot be performed on {0}

Short Form

No xform support

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

Description

None

Message ID : DXF4391E

Severity

Error

Message ID : DXF4382E

Long Form

Data transform of files listed in {0} for guard point {1} failed

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4392E

Severity

Error

Long Form

Error {0} opening configuration file in {1}: does not exist

Short Form

Cfg file error

Parameters

Label	CEF Label	Type	Usage
ecode	cn1	Numeric	An error code
filePath	filePath	Text	Full path to file

Description

None

Message ID : DXF4393E

Severity

Error

Long Form

Error {0} opening lock file in {1}: does not exist

Short Form

Lock file error

Parameters

Label	CEF Label	Type	Usage
ecode	cn1	Numeric	An error code
filePath	filePath	Text	Full path to file

Description

None

Message ID : DXF4394E

Severity

Error

Long Form

Error {0} creating lock file in {1}: does not exist

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4395E

Severity

Error

Long Form

Error {0} getting file info for {1}

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4396E

Severity

Error

Message ID : DXF4394E

Long Form

Error {0} getting file attributes for {1}

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4400E

Severity

Error

Long Form

Error trying to create a worker thread

Short Form

Threadcreate fail

Message ID : DXF4396E

Parameters

No parameters are provided for this message type

Description

None

Message ID : DXF4401E

Severity

Error

Long Form

Error {0} ({1}) trying to delete file {2}

Short Form

Delete file error

Parameters

Label	CEF Label	Type	Usage
ecode	cn1	Numeric	An error code
showStr	reason	Text	Code specifying reason for allowing access, if any

Message ID : DXF4400E

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : DXF4403E

Severity

Error

Long Form

No path provided for recovery information file

Short Form

Missing recovery info

Parameters

No parameters are provided for this message type

Description

None

Message ID : DXF4404E

Severity

Error

Long Form

Error {0} setting file attributes for {1}

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4405E

Severity

Error

Message ID : DXF4403E

Long Form

Error {0} setting file time for {1}

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4407E

Severity

Error

Long Form

Could not determine the Windows installation directory

Short Form

Cannot determine install dir

Parameters

No parameters are provided for this message type

Description

None

Message ID : DXF4408E

Severity

Error

Long Form

Internal error: thread index {0} is not valid

Short Form

Bad thread id

Parameters

No parameters are provided for this message type

Message ID : DXF4407E

Description

None

Message ID : DXF4409E

Severity

Error

Long Form

Cannot find files in {0}, error {1}

Short Form

Find first error

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file
ecode	cn1	Numeric	An error code

Description

None

Message ID : DXF4427E

Severity

Error

Long Form

Failed to authorize this program with the kernel

Short Form

Cannot protect PID

Parameters

No parameters are provided for this message type

Description

None

Message ID : DXF4409E

Message ID : DXF4430E

Severity

Error

Long Form

The data transformation process was denied permission to access the directory {0}

Short Form

Dir access denied

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : DXF4432E

Severity

Error

Long Form

Build version: {0}

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4433E

Severity

Error

Long Form

Build ID: {0}

Message ID : DXF4432E

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4434E

Severity

Error

Long Form

Build Date: {0}

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4433E

Message ID : DXF4435E

Severity

Error

Long Form

About to perform the requested data transform operation

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4436E

Severity

Error

Long Form

-- Be sure to back up your data

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4437E

Severity

Error

Long Form

-- Please do not access files in the guard point during the transform process

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4436E

Message ID : DXF4438E

Severity

Error

Long Form

-- Please do not attempt to terminate the application

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4439E

Severity

Error

Long Form

Do you wish to continue (y/n)?

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4440E

Severity

Error

Long Form

.Usage:

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4441E

Severity

Error

Long Form

. dataxform {operation} {operation options}

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4442E

Severity

Error

Long Form

. where {operation} is the desired operation

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4443E

Severity

Error

Long Form

. --rekey Rekey the files in guard point

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4442E

Message ID : DXF4444E

Severity

Error

Long Form

. --rekey_supported Report if rekey is supported on guard point

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4445E

Severity

Error

Long Form

. --scan Display number of files and directories in

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4446E

Severity

Error

Long Form

. the guard point

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4447E

Severity

Error

Long Form

. --check_links Scan guard point and report any hard links

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4448E

Severity

Error

Long Form

. --cleanup Remove existing status files from a previous

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4449E

Severity

Error

Long Form

. rekey session

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4450E

Severity

Error

Long Form

. --recovery Generate a list of files already rekeyed in

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4451E

Severity

Error

Long Form

. guard point

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4452E

Severity

Error

Long Form

. --rekey_list Only rekey files listed in directive file

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4451E

Message ID : DXF4453E

Severity

Error

Long Form

. --version Display the version number

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4454E

Severity

Error

Long Form

. where {operation options} are parameters for the operation

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4455E

Severity

Error

Long Form

. --gp Specify name of guard point

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4456E

Severity

Error

Long Form

. Required for all operations except --version

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4457E

Severity

Error

Long Form

. --file_list Specify fully qualified name of directive

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4458E

Severity

Error

Long Form

. file for --rekey_list and --recovery

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4459E

Severity

Error

Long Form

. Defaults to dataxform_files in the guard

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4460E

Severity

Error

Long Form

. point directory

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4461E

Severity

Error

Long Form

. --dir_recovery Specify location for status file

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4462E

Severity

Error

Long Form

. Defaults to use log file location if there

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4463E

Severity

Error

Long Form

. is no --status_gp option

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4464E

Severity

Error

Long Form

About to remove the data transformation status files

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4463E

Message ID : DXF4465E

Severity

Error

Long Form

Shutting down data transform: received fatal signal {0}

Short Form

Xform killed by sigal

Parameters

Label	CEF Label	Type	Usage
sig	vds_sig	Numeric	A signal value

Description

None

Message ID : DXF4466E

Severity

Error

Long Form

Could not complete data transform for guard point {0}, data transform was interrupted by a signal

Short Form

Xform interrupted by signal

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

Description

None

Message ID : DXF4467E

Severity

Error

Message ID : DXF4466E

Long Form

. --preserve_access_time Preserve file access time after rekey

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4468E

Severity

Error

Long Form

. --preserve_modified_time Preserve file modified time after rekey

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4469E

Severity

Error

Long Form

. --nq Suppress prompts

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4470E

Severity

Error

Message ID : DXF4468E

Long Form

. --print_stat Display data transform statistics

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4471E

Severity

Error

Long Form

. --status_gp Write status file to the guard point

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4472E

Severity

Error

Long Form

. directory

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4474E

Severity

Error

Message ID : DXF4471E

Long Form

Process {0}: error {1} opening lock file at {2}. This may be due to an already running data transform instance

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4476E

Severity

Error

Long Form

The file {0} could not be transformed

Short Form

Prev xform file fail

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : DXF4477E

Severity

Error

Long Form

The file {0} could not be transformed, it had error in the previous data transform

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4476E

Message ID : DXF4478E

Severity

Error

Long Form

The file {0} could not be transformed, it was in progress in the previous data transform

Short Form

Prev xform file in progress

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : DXF4479E

Severity

Error

Long Form

The file {0} could not be transformed, the kernel component stopped the data transform

Short Form

Prev xform file stopped by kernel

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : DXF4480E

Severity

Error

Message ID : DXF4479E

Long Form

The file {0} could not be transformed, a signal stopped the data transform

Short Form

Prev xform file stopped by signal

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : DXF4482E

Severity

Error

Long Form

Cannot create the data transform recovery/status file {0}, errno {1}

Message ID : DXF4480E

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4483E

Severity

Error

Long Form

Cannot create the data transform recovery/status file {0}, the file name is too long

Short Form

File too long

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Message ID : DXF4482E

Description

None

Message ID : DXF4484E

Severity

Error

Long Form

Verify this is a guard point with a data transformation rule, and check the system log files for any other problems

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4486E

Severity

Error

Message ID : DXF4483E

Long Form

Invalid format in recovery file {0}

Short Form

Bad recovery file

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : DXF4494E

Severity

Error

Long Form

The file {0} was previously in error. The kernel component stopped the data transform

Message ID : DXF4486E

Short Form

Prev error - kernel stop

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : DXF4498E

Severity

Error

Long Form

The file {0} was previously in error. A signal stopped the dataxform

Short Form

Prev skipped - signal stop

Message ID : DXF4494E

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : DXF4499E

Severity

Error

Long Form

The file {0} was previously in error. It was open and could not be modified safely

Short Form

Prev error file open

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Message ID : DXF4498E

Label	CEF Label	Type	Usage

Description

None

Logger DXF: Fatal errors

Message ID : DXF4431F

Severity

Fatal error

Long Form

Unable to determine the fully qualified host name of this machine: {0}. Please examine your machine's configuration.

Short Form

No short form is provided for this message type

Description

None

Logger DXF: Information

Message ID : DXF3211I

Severity

Information

Long Form

File {0} is being mapped or no-viewed, so it is skipped temporarily and moving on to next file

Short Form

File is being mapped or no-viewed

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : DXF3235I

Severity

Information

Long Form

LDT: Live data transform scan phase ran from {0} until {1}

Short Form

OXF run

Parameters

Label	CEF Label	Type	Usage
stime	start	Text	A start time stamp
etime	end	Text	An end time stamp

Description

None

Message ID : DXF3236I

Severity

Information

Long Form

LDT: Live data transform scan operation took {0} hours, {1} minutes and {2} seconds

Short Form

OXF duration

Parameters

Label	CEF Label	Type	Usage
hours	vds_hours	Numeric	Elapsed hours
mins	vds_mins	Numeric	Elaped minutes
secs	vds_secs	Numeric	Elapsed seconds

Description

None

Message ID : DXF3237I

Severity

Information

Long Form

LDT: Live data transformation scan operation took {0} hours, {1} minutes and {2} seconds

Short Form

OXF op duration

Parameters

Label	CEF Label	Type	Usage
hours	vds_hours	Numeric	Elapsed hours
mins	vds_mins	Numeric	Elaped minutes
secs	vds_secs	Numeric	Elapsed seconds

Description

None

Message ID : DXF4122I

Severity

Information

Long Form

Number of files skipped due to insufficient memory: {0}

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4123I

Severity

Information

Long Form

Number of files previously skipped due to insufficient memory: {0}

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4126I

Severity

Information

Long Form

-- This is an estimated time using actual data transformations on test files

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4123I

Message ID : DXF4127I

Severity

Information

Long Form

-- This is an estimated time using simulated data transformations on test files

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4128I

Severity

Information

Long Form

-- The actual transformation time may be more or less than this estimate

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4129I

Severity

Information

Long Form

The file {0} was skipped. It was excluded by policy

Short Form

Skipped file by policy

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : DXF4130I

Severity

Information

Long Form

The file {0} was previously skipped. It was excluded by policy

Short Form

Prev skipped file by policy

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : DXF4129I

Message ID : DXF4131I

Severity

Information

Long Form

Number of files skipped due to policy exclusion: {0}

Short Form

Skipped files by policy

Parameters

Label	CEF Label	Type	Usage
count	vds_count	Numeric	A generic count value

Description

None

Message ID : DXF4132I

Severity

Information

Long Form

Number of files previously skipped due to policy exclusion: {0}

Short Form

Prev skipped files by policy

Parameters

Label	CEF Label	Type	Usage
count	vds_count	Numeric	A generic count value

Description

None

Message ID : DXF4143I

Severity

Information

Message ID : DXF4132I

Long Form

{0} is not a guard point with a rekey policy applied

Short Form

Xform not supported

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

Description

None

Message ID : DXF4144I

Severity

Information

Long Form

The deep scan will emulate transformation to derive timing estimates

Message ID : DXF4143I

Short Form

Emulating xforms

Parameters

No parameters are provided for this message type

Description

None

Message ID : DXF4145I

Severity

Information

Long Form

The file {0} was skipped. It does not exist

Short Form

File missing

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : DXF4146I

Severity

Information

Long Form

Number of files skipped due to not existing: {0}

Short Form

Files missing

Parameters

Label	CEF Label	Type	Usage
count	vds_count	Numeric	A generic count value

Message ID : DXF4145I

Label	CEF Label	Type	Usage

Description

None

Message ID : DXF4147I

Severity

Information

Long Form

Number of files previously skipped due to not existing: {0}

Short Form

Prev files missing

Parameters

Label	CEF Label	Type	Usage
count	vds_count	Numeric	A generic count value

Description

None

Message ID : DXF4148I

Severity

Information

Long Form

The file {0} was previously skipped. It does not exist

Short Form

Prev error - file missing

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : DXF4147I

Message ID : DXF4154I

Severity

Information

Long Form

The data transform program ran from {0} until {1}

Short Form

Xform run

Parameters

Label	CEF Label	Type	Usage
stime	start	Text	A start time stamp
etime	end	Text	An end time stamp

Description

None

Message ID : DXF4161I

Severity

Information

Long Form

Skipping junction point {0}

Short Form

Junction point

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : DXF4200I

Severity

Information

Long Form

The file {0} was skipped. It was an additional hard link

Short Form

Skipped dup hard link

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : DXF4201I

Severity

Information

Message ID : DXF4200I

Long Form

The file {0} was skipped. It was a soft link

Short Form

Skipped soft link

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : DXF4202I

Severity

Information

Long Form

The file {0} was skipped. It was a dataxform internal file

Message ID : DXF4201I

Short Form

Skipped internal file

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : DXF4203I

Severity

Information

Long Form

The file {0} was skipped. dataxform had insufficient permission

Short Form

No short form is provided for this message type

Message ID : DXF4202I

Description

None

Message ID : DXF4204I

Severity

Information

Long Form

The file {0} was skipped. It had an ambiguous name

Short Form

Skipped bad name

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : DXF4203I

Message ID : DXF4205I

Severity

Information

Long Form

The file {0} was skipped. It was a special file

Short Form

Skipped special file

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : DXF4206I

Severity

Information

Long Form

The file {0} was skipped. It was exempt from data transform

Short Form

Skipped except file

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : DXF4207I

Severity

Information

Message ID : DXF4206I

Long Form

The file {0} was skipped. It was a compressed file

Short Form

Skipped compressed file

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : DXF4208I

Severity

Information

Long Form

The file {0} was skipped. It was an encrypted file

Message ID : DXF4207I

Short Form

Skipped encrypted file

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : DXF4209I

Severity

Information

Long Form

The file {0} was skipped. It was not a regular file

Short Form

Skipped non-file

Message ID : DXF4208I

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : DXF4210I

Severity

Information

Long Form

The file {0} was skipped. There was insufficient memory to process it

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4209I

Message ID : DXF4211I

Severity

Information

Long Form

The file {0} was skipped. It could not be classified

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4212I

Severity

Information

Long Form

The file {0} was skipped. It was no longer present when a transform was attempted

Short Form

File gone away

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : DXF4213I

Severity

Information

Long Form

The file {0} was skipped. A transform would have used the same key

Short Form

Skipped - same key

Message ID : DXF4212I

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : DXF4214I

Severity

Information

Long Form

The file {0} was skipped. Rekey was not supported for this file

Short Form

Skipped unsupported file

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Message ID : DXF4213I

Label	CEF Label	Type	Usage

Description

None

Message ID : DXF4216I

Severity

Information

Long Form

The file {0} was previously skipped. It was an additional hard link

Short Form

Prev skipped dup link

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : DXF4217I

Severity

Information

Long Form

The file {0} was previously skipped. It was a soft link

Short Form

Prev skipped soft link

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : DXF4216I

Message ID : DXF4218I

Severity

Information

Long Form

The file {0} was previously skipped. It was a dataxform internal file

Short Form

Prev skipped internal file

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : DXF4219I

Severity

Information

Long Form

The file {0} was previously skipped. dataxform had insufficient permission

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4220I

Severity

Information

Long Form

The file {0} was previously skipped. It had an ambiguous name

Message ID : DXF4219I

1114

Short Form

Prev skipped bad name

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : DXF4221I

Severity

Information

Long Form

The file {0} was previously skipped. It was a special file

Short Form

Prev skipped special file

Message ID : DXF4220I

1115

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : DXF4222I

Severity

Information

Long Form

The file {0} was previously skipped. It was exempt from data transform

Short Form

Prev skipped exempt file

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Message ID : DXF4221I

Label	CEF Label	Type	Usage

Description

None

Message ID : DXF4223I

Severity

Information

Long Form

The file {0} was previously skipped. It was a compressed file

Short Form

Prev skipped compressed file

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : DXF4224I

Severity

Information

Long Form

The file {0} was previously skipped. It was an encrypted file

Short Form

Prev skipped encrypted file

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : DXF4223I

Message ID : DXF4225I

Severity

Information

Long Form

Automatic data transform for guard point {0} deferred, no configuration file

Short Form

No config file

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

Description

None

Message ID : DXF4226I

Severity

Information

Long Form

The file {0} has the same "to" and "from" keys; skipping

Short Form

Skipping same keys

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : DXF4253I

Severity

Information

Message ID : DXF4226I

Long Form

There is no partial data transform for {0} to recover

Short Form

Nothing to recover

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

Description

None

Message ID : DXF4257I

Severity

Information

Long Form

Number of additional hard links skipped: {0}

Message ID : DXF4253I

Short Form

Hardlinks skipped

Parameters

Label	CEF Label	Type	Usage
count	vds_count	Numeric	A generic count value

Description

None

Message ID : DXF4258I

Severity

Information

Long Form

Number of soft links skipped: {0}

Short Form

Softlinks skipped

Message ID : DXF4257I

Parameters

Label	CEF Label	Type	Usage
count	vds_count	Numeric	A generic count value

Description

None

Message ID : DXF4259I

Severity

Information

Long Form

Number of files skipped due to insufficient permission: {0}

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4258I

Message ID : DXF4260I

Severity

Information

Long Form

Number of files skipped due to an ambiguous name: {0}

Short Form

Bad name errors

Parameters

Label	CEF Label	Type	Usage
count	vds_count	Numeric	A generic count value

Description

None

Message ID : DXF4261I

Severity

Information

Long Form

Number of special files skipped: {0}

Short Form

Special files skipped

Parameters

Label	CEF Label	Type	Usage
count	vds_count	Numeric	A generic count value

Description

None

Message ID : DXF4262I

Severity

Information

Message ID : DXF4261I

Long Form

Number of files exempt from data transform skipped: {0}

Short Form

Exempt files skipped

Parameters

Label	CEF Label	Type	Usage
count	vds_count	Numeric	A generic count value

Description

None

Message ID : DXF4263I

Severity

Information

Long Form

Number of compressed files skipped: {0}

Message ID : DXF4262I

Short Form

Compressed files skipped

Parameters

Label	CEF Label	Type	Usage
count	vds_count	Numeric	A generic count value

Description

None

Message ID : DXF4264I

Severity

Information

Long Form

Number of encrypted files skipped: {0}

Short Form

Encrypted files skipped

Message ID : DXF4263I

Parameters

Label	CEF Label	Type	Usage
count	vds_count	Numeric	A generic count value

Description

None

Message ID : DXF4265I

Severity

Information

Long Form

Number of non-regular files skipped: {0}

Short Form

Non-reg files skipped

Parameters

Label	CEF Label	Type	Usage
count	vds_count	Numeric	A generic count value

Message ID : DXF4264I

Label	CEF Label	Type	Usage

Description

None

Message ID : DXF4267I

Severity

Information

Long Form

Number of files skipped due to being no longer present when transform attempted: {0}

Short Form

Files gone away

Parameters

Label	CEF Label	Type	Usage
count	vds_count	Numeric	A generic count value

Description

None

Message ID : DXF4268I

Severity

Information

Long Form

Number of files skipped due to a duplicate key: {0}

Short Form

Files with dup key

Parameters

Label	CEF Label	Type	Usage
count	vds_count	Numeric	A generic count value

Description

None

Message ID : DXF4267I

Message ID : DXF4269I

Severity

Information

Long Form

Number of files skipped due to rekey not supported for this file: {0}

Short Form

Unsupported files skipped

Parameters

Label	CEF Label	Type	Usage
count	vds_count	Numeric	A generic count value

Description

None

Message ID : DXF4273I

Severity

Information

Long Form

Number of additional hard links previously skipped: {0}

Short Form

Prev hardlinks skipped

Parameters

Label	CEF Label	Type	Usage
count	vds_count	Numeric	A generic count value

Description

None

Message ID : DXF4274I

Severity

Information

Message ID : DXF4273I

Long Form

Number of soft links previously skipped: {0}

Short Form

Prev softlinks skipped

Parameters

Label	CEF Label	Type	Usage
count	vds_count	Numeric	A generic count value

Description

None

Message ID : DXF4275I

Severity

Information

Long Form

Number of files previously skipped due to insufficient permission: {0}

Message ID : DXF4274I

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4276I

Severity

Information

Long Form

Number of files previously skipped due to an ambiguous name: {0}

Short Form

Prev bad name errors

Parameters

Label	CEF Label	Type	Usage
count	vds_count	Numeric	A generic count value

Message ID : DXF4275I

Description

None

Message ID : DXF4277I

Severity

Information

Long Form

Number of special files previously skipped: {0}

Short Form

Prev special files skipped

Parameters

Label	CEF Label	Type	Usage
count	vds_count	Numeric	A generic count value

Description

None

Message ID : DXF4276I

Message ID : DXF4278I

Severity

Information

Long Form

Number of files exempt from data transform previously skipped: {0}

Short Form

Prev exempt files skipped

Parameters

Label	CEF Label	Type	Usage
count	vds_count	Numeric	A generic count value

Description

None

Message ID : DXF4279I

Severity

Information

Long Form

Number of compressed files previously skipped: {0}

Short Form

Prev compressed files skipped

Parameters

Label	CEF Label	Type	Usage
count	vds_count	Numeric	A generic count value

Description

None

Message ID : DXF4280I

Severity

Information

Message ID : DXF4279I

Long Form

Number of encrypted files previously skipped: {0}

Short Form

Prev encrypted files skipped

Parameters

Label	CEF Label	Type	Usage
count	vds_count	Numeric	A generic count value

Description

None

Message ID : DXF4281I

Severity

Information

Long Form

Number of non-regular files previously skipped: {0}

Message ID : DXF4280I

Short Form

Prev non-reg files skipped

Parameters

Label	CEF Label	Type	Usage
count	vds_count	Numeric	A generic count value

Description

None

Message ID : DXF4283I

Severity

Information

Long Form

Number of files previously skipped due to being no longer present when transform attempted: {0}

Short Form

Prev files gone away

Message ID : DXF4281I

Parameters

Label	CEF Label	Type	Usage
count	vds_count	Numeric	A generic count value

Description

None

Message ID : DXF4284I

Severity

Information

Long Form

Number of files previously skipped due to a duplicate key: {0}

Short Form

Prev files with dup key

Parameters

Label	CEF Label	Type	Usage
count	vds_count	Numeric	A generic count value

Message ID : DXF4283I

Label	CEF Label	Type	Usage

Description

None

Message ID : DXF4285I

Severity

Information

Long Form

Number of files previously skipped due to rekey not supported for this file: {0}

Short Form

Prev unsupported files skipped

Parameters

Label	CEF Label	Type	Usage
count	vds_count	Numeric	A generic count value

Description

None

Message ID : DXF4293I

Severity

Information

Long Form

Estimated data transformation time for {0} is {1}

Short Form

Estimate duration

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory
rt	rt	Text	Time of event

Description

None

Message ID : DXF4309I

Severity

Information

Long Form

Building the list of previously transformed files in {0}

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4316I

Severity

Information

Message ID : DXF4293I

Long Form

Status information for directories in guard point

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4317I

Severity

Information

Long Form

Finished processing directory {0}

Short Form

Completed dir

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : DXF4318I

Severity

Information

Long Form

Partially processed directory {0}

Short Form

Partially processed dir

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Message ID : DXF4317I

Label	CEF Label	Type	Usage

Description

None

Message ID : DXF4319I

Severity

Information

Long Form

Skipping directory {0}

Short Form

Skipped dir

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Message ID : DXF4318I

1146

Description

None

Message ID : DXF4320I

Severity

Information

Long Form

Skipping empty directory {0}

Short Form

Empty dir

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : DXF4319I

Message ID : DXF4321I

Severity

Information

Long Form

Skipping exempt directory {0}

Short Form

Exempt dir

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : DXF4322I

Severity

Information

Long Form

Unknown status for directory {0}

Short Form

Dir bad status

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : DXF4323I

Severity

Information

Message ID : DXF4322I

Long Form

Directory {0} contains {1} files ({2})

Short Form

Xform to do

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file
nfile	vds_nfile	Numeric	The number of files processed

Description

None

Message ID : DXF4329I

Severity

Information

Message ID : DXF4323I

Long Form

Finished check for hard links in {0}

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4332I

Severity

Information

Long Form

Setting recovery-file-list to {0}

Short Form

No short form is provided for this message type

Message ID : DXF4329I

Description

None

Message ID : DXF4344I

Severity

Information

Long Form

Data transform version {0}

Short Form

Datatform

Parameters

Label	CEF Label	Type	Usage
version	vds_version	Text	Software version string

Description

None

Message ID : DXF4332I

Message ID : DXF4345I

Severity

Information

Long Form

Data transform version {0}, using policy {1} on guard point {2}

Short Form

Auto dataxform

Parameters

Label	CEF Label	Type	Usage
version	vds_version	Text	Software version string
pol	cs1	Text	Policy name
gp	fileId	Text	Guardpoint base directory

Description

None

Message ID : DXF4352I

Severity

Information

Long Form

Data transform for {0} was previously completed

Short Form

Xform prev complete

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

Description

None

Message ID : DXF4361I

Severity

Information

Long Form

Data transform for guard point {0} finished

Short Form

Xform done

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

Description

None

Message ID : DXF4362I

Severity

Information

Message ID : DXF4361I

Long Form

Data transform for guard point {0} finished but {1} files were not processed due to errors

Short Form

Xform done with errors

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory
count	vds_count	Numeric	A generic count value

Description

None

Message ID : DXF4363I

Severity

Information

Message ID : DXF4362I

1156

Long Form

Data transform for guard point {0} finished but {1} files were skipped

Short Form

Xform done with skips

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory
count	vds_count	Numeric	A generic count value

Description

None

Message ID : DXF4364I

Severity

Information

Message ID : DXF4363I

1157

Long Form

Data transform for guard point {0} finished but {1} files were not processed due to errors and {2} files were skipped

Short Form

Xform done with errors and skips

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory
count	vds_count	Numeric	A generic count value
count	vds_count	Numeric	A generic count value

Description

None

Message ID : DXF4365I

Severity

Information

Message ID : DXF4364I

1158

Long Form

The data transform operation took {0} hours, {1} minutes and {2} seconds

Short Form

Xform duration

Parameters

Label	CEF Label	Type	Usage
hours	vds_hours	Numeric	Elapsed hours
mins	vds_mins	Numeric	Elaped minutes
secs	vds_secs	Numeric	Elapsed seconds

Description

None

Message ID : DXF4366I

Severity

Information

Message ID : DXF4365I

Long Form

The current operation took {0} hours, {1} minutes and {2} seconds

Short Form

Xform op duration

Parameters

Label	CEF Label	Type	Usage
hours	vds_hours	Numeric	Elapsed hours
mins	vds_mins	Numeric	Elaped minutes
secs	vds_secs	Numeric	Elapsed seconds

Description

None

Message ID : DXF4369I

Severity

Information

Message ID : DXF4366I

1160

Long Form

Data transform had some files in progress

Short Form

Prev xform incomplete

Parameters

No parameters are provided for this message type

Description

None

Message ID : DXF4370I

Severity

Information

Long Form

The file {0} was in progress in the previous data transform, it will not be transformed

Short Form

Prev xform file inprogress

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : DXF4371I

Severity

Information

Long Form

Data transform skipped some files

Short Form

No short form is provided for this message type

Message ID : DXF4370I

Description

None

Message ID : DXF4372I

Severity

Information

Long Form

The file {0} was skipped in the previous data transform, it will be skipped

Short Form

Prev xform file skipped

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : DXF4371I

Message ID : DXF4375I

Severity

Information

Long Form

Data transform last successfully transformed the file {0}

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4378I

Severity

Information

Long Form

Scan found {0} files ({1}) in {2} directories for guard point {3}

Short Form

Scan result

Parameters

Label	CEF Label	Type	Usage
nfile	vds_nfile	Numeric	The number of files processed
ndir	vds_ndir	Numeric	The number of directories processed
gp	fileId	Text	Guardpoint base directory

Description

None

Message ID : DXF4380I

Severity

Information

Long Form

Transformed {0} files ({1}) of {2} files ({3}) for guard point {4}

Message ID : DXF4378I

1165

Short Form

Scan stats

Parameters

Label	CEF Label	Type	Usage
nfile	vds_nfile	Numeric	The number of files processed
space	vds_space	Text	A string representation of file or disk space
nfiles	vds_nfiles	Numeric	The total number of files in an operation
space	vds_space	Text	A string representation of file or disk space
gp	fileId	Text	Guardpoint base directory

Description

None

Message ID : DXF4383I

Severity

Information

Message ID : DXF4380I

1166

Long Form

Generating list of files previously transformed on {0}

Short Form

Recovery gen

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

Description

None

Message ID : DXF4384I

Severity

Information

Long Form

Automatic data transform status for {0}: previous attempt completed

Message ID : DXF4383I

Short Form

Prev auto xform done

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

Description

None

Message ID : DXF4385I

Severity

Information

Long Form

Automatic data transform status for {0}: previous attempt did not complete

Short Form

Prev auto xform fail

Message ID : DXF4384I

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

Description

None

Message ID : DXF4386I

Severity

Information

Long Form

Automatic data transform from host {0} for {1}: previous attempt completed

Short Form

Prev auto xform done

Parameters

Label	CEF Label	Type	Usage
shost	shost	Text	Source host name

Message ID : DXF4385I

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

Description

None

Message ID : DXF4387I

Severity

Information

Long Form

Automatic data transform from host {0} for {1}: previous attempt did not complete

Short Form

Prev auto xform fail

Parameters

Label	CEF Label	Type	Usage
shost	shost	Text	Source host name

Message ID : DXF4386I

1170

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

Description

None

Message ID : DXF4388I

Severity

Information

Long Form

Automatic data transform for {0}: could not get status

Short Form

Auto xform stat fail

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

Message ID : DXF4387I

1171

Description

None

Message ID : DXF4389I

Severity

Information

Long Form

Starting data transform of {0} for files listed in {1}

Short Form

Rekey file start

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory
filePath	filePath	Text	Full path to file

Description

None

Message ID : DXF4390I

Severity

Information

Long Form

Data transform of {0} of {1} files listed in {2} for guard point {3}

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4397I

Severity

Information

Message ID : DXF4389I

Long Form

Found {0} references to hard link

Short Form

Hardlink count

Parameters

Label	CEF Label	Type	Usage
count	vds_count	Numeric	A generic count value

Description

None

Message ID : DXF4399I

Severity

Information

Long Form

Hardlink reference {0} {1}

Message ID : DXF4397I

Short Form

Hardlink refs

Parameters

Label	CEF Label	Type	Usage
count	vds_count	Numeric	A generic count value
filePath	filePath	Text	Full path to file

Description

None

Message ID : DXF4414I

Severity

Information

Long Form

Executing script {0}

Message ID : DXF4399I

1175

Short Form

Exec fail

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : DXF4415I

Severity

Information

Long Form

Generating list of files transformed during previous session for guard point {0}

Short Form

List create

Message ID : DXF4414I

1176

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

Description

None

Message ID : DXF4416I

Severity

Information

Long Form

Writing list of files transformed during previous session for guard point {0}

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4415I

Message ID : DXF4417I

Severity

Information

Long Form

Checking if {0} is a guard point with a rekey policy applied

Short Form

Checking supported

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

Description

None

Message ID : DXF4418I

Severity

Information

Long Form

Preparing data transform

Short Form

Prepare xform

Parameters

No parameters are provided for this message type

Description

None

Message ID : DXF4419I

Severity

Information

Long Form

Preparing data transform for next phase of execution

Short Form

xform thread idle

Parameters

No parameters are provided for this message type

Description

None

Message ID : DXF4420I

Severity

Information

Long Form

Generating list of files to transform in directory {0}

Short Form

Generating list

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : DXF4421I

Severity

Information

Long Form

Scanning for hard links in directory {0}

Short Form

Check links

Message ID : DXF4420I

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : DXF4422I

Severity

Information

Long Form

Processing the list of files specified in {0}

Short Form

Processing list

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Message ID : DXF4421I

Label	CEF Label	Type	Usage

Description

None

Message ID : DXF4423I

Severity

Information

Long Form

Processed {0} files ({1}) of {2} files ({3}) in {4}

Short Form

Processed files

Parameters

Label	CEF Label	Type	Usage
nfile	vds_nfile	Numeric	The number of files processed
nfiles	vds_nfiles	Numeric	The total number of files in an operation

Message ID : DXF4422I

1183

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : DXF4424I

Severity

Information

Long Form

Processed {0} files ({1}) of {2} files ({3}) in {4}, in progress {5}, completed {6}

Short Form

Processing files

Parameters

Label	CEF Label	Type	Usage
nfile	vds_nfile	Numeric	The number of files processed
nfiles	vds_nfiles	Numeric	The total number of files in an operation

Message ID : DXF4423I

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file
scount	vds_scount	Text	A generic count as a string
scount	vds_scount	Text	A generic count as a string

Description

None

Message ID : DXF4425I

Severity

Information

Long Form

Processed {0} files of {1} files specified by {2} in guard point {3}

Short Form

Processed list

Parameters

Label	CEF Label	Type	Usage
nfile	vds_nfile	Numeric	The number of files processed
nfiles	vds_nfiles	Numeric	The total number of files in an operation
filePath	filePath	Text	Full path to file
gp	fileId	Text	Guardpoint base directory

Description

None

Message ID : DXF4429I

Severity

Information

Long Form

{0} is a guard point with a rekey policy applied

Short Form

Xform supported

Message ID : DXF4425I

1186

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

Description

None

Message ID : DXF4481I

Severity

Information

Long Form

The file {0} was skipped

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4429I

Message ID : DXF4485I

Severity

Information

Long Form

Data transform last processing was on the file {0}

Short Form

Last file xformed

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : DXF4487I

Severity

Information

Long Form

The file {0} could not be transformed, it was skipped in a previous data transform

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4488I

Severity

Information

Long Form

Previous status information relates to a --rekey_file operation.

Short Form

Prev op was rekey

Parameters

No parameters are provided for this message type

Description

None

Message ID : DXF4489I

Severity

Information

Long Form

Previous status information does not relate to a --rekey_file operation.

Short Form

Prev op was rekey_file

Parameters

No parameters are provided for this message type

Description

None

Message ID : DXF4490I

Severity

Information

Long Form

Previous status information will be ignored

Short Form

Prev status ignored

Parameters

No parameters are provided for this message type

Message ID : DXF4489I

Description

None

Message ID : DXF4491I

Severity

Information

Long Form

The file {0} was previously skipped. It was not a regular file

Short Form

Prev skipped non-file

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : DXF4490I

Message ID : DXF4492I

Severity

Information

Long Form

The file {0} was previously skipped. There was insufficient memory to process it

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4493I

Severity

Information

Long Form

The file {0} was previously skipped. It could not be classified

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4495I

Severity

Information

Long Form

The file {0} was previously skipped. It was no longer present when a transform was attempted

Short Form

Prev error - file gone

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : DXF4496I

Severity

Information

Long Form

The file {0} was previously skipped. A transform would have used the same key

Short Form

Prev skipped - same key

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : DXF4495I

Message ID : DXF4497I

Severity

Information

Long Form

The file {0} was previously skipped. Rekey was not supported for this file

Short Form

Prev skipped unsupported file

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Logger DXF: Warnings

Message ID : DXF3210W

Severity

Warning

Long Form

If Shadow Copy was used on your system, you must back up your data before attempting to run dataxform. Once DataXform has been completed, you may restart Shadow Copy. Note, however, that all Shadow Copy backups made prior to running dataxform will be unusable and should be discarded. Attempting to restore your cleartext Shadow Copy backups made prior to running dataxform into your encrypted data will result in data corruption.

Short Form

Shadow copy

Parameters

No parameters are provided for this message type

Description

None

Message ID : DXF4103W

Severity

Warning

Long Form

Transformation time estimation will be simulated as guard point does not support rekeying

Short Form

No rekey support

Parameters

No parameters are provided for this message type

Description

None

Message ID : DXF4104W

Severity

Warning

Long Form

Missing {0} references to hard link {1}

Short Form

Missing hardlink refs

Parameters

Label	CEF Label	Type	Usage
count	vds_count	Numeric	A generic count value
filePath	filePath	Text	Full path to file

Description

None

Message ID : DXF4118W

Severity

Warning

Message ID : DXF4104W

Long Form

Could not return file time for {0} to its original value, got error {1}

Short Form

Time restore error

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file
showStr	reason	Text	Code specifying reason for allowing access, if any

Description

None

Message ID : DXF4242W

Severity

Warning

Long Form

More than {0} files were encountered in the directory {1}. Dataxform may consume excessive system resources while operating upon this directory. Proceeding

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4254W

Severity

Warning

Long Form

Note: data from a previous dataxform run is being used

Short Form

Prev run data in use

Parameters

No parameters are provided for this message type

Description

None

Message ID : DXF4307W

Severity

Warning

Long Form

Skipping previously transformed directory {0}

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4324W

Severity

Warning

Long Form

Cannot perform data transform for {0} with identical key

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4327W

Severity

Warning

Long Form

Kernel component returned stop-data-transform status

Short Form

Stopped by kernel

Parameters

No parameters are provided for this message type

Description

None

Message ID : DXF4333W

Severity

Warning

Long Form

Unknown version for recovery file list

Short Form

Bad version

Parameters

No parameters are provided for this message type

Description

None

Message ID : DXF4337W

Severity

Warning

Long Form

Resetting read buffer size to {0}KB

Short Form

Setting buf size

Parameters

Label	CEF Label	Type	Usage
slen	in	Numeric	Input byte count or length

Message ID : DXF4333W

Description

None

Message ID : DXF4338W

Severity

Warning

Long Form

Resetting the maximum number of kernel threads to {0}

Short Form

Number kthreads

Parameters

Label	CEF Label	Type	Usage
count	vds_count	Numeric	A generic count value

Description

None

Message ID : DXF4337W

Message ID : DXF4339W

Severity

Warning

Long Form

Resetting the maximum number of utility threads to {0}

Short Form

Max uthreads

Parameters

Label	CEF Label	Type	Usage
count	vds_count	Numeric	A generic count value

Description

None

Message ID : DXF4351W

Severity

Warning

Long Form

Could not load previous data transform information

Short Form

Recovery file load fail

Parameters

No parameters are provided for this message type

Description

None

Message ID : DXF4359W

Severity

Warning

Long Form

Could not notify kernel component that data transform completed on {0}

Short Form

Kernel notify complete fail

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

Description

None

Message ID : DXF4373W

Severity

Warning

Long Form

Data transform was previously run on guard point {0}

Message ID : DXF4359W

Short Form

Xform prev completed

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

Description

None

Message ID : DXF4398W

Severity

Warning

Long Form

Found {0} references to hard link but expected {1}

Short Form

Hardlink count error

Message ID : DXF4373W

Parameters

Label	CEF Label	Type	Usage
count	vds_count	Numeric	A generic count value
count	vds_count	Numeric	A generic count value

Description

None

Message ID : DXF4406W

Severity

Warning

Long Form

Could not return file time for {0} to its original value, got error code {1}

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4410W

Severity

Warning

Long Form

Could not read the Windows registry, section {0}

Short Form

Read read fail

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : DXF4406W

Message ID : DXF4413W

Severity

Warning

Long Form

Attempted to restrict access to unknown object ID {0}

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4428W

Severity

Warning

Long Form

Unable to contact Key Manager; will perform all logging to the local log file

Short Form

No short form is provided for this message type

Description

None

Logger FIP: Fatal errors

Message ID : FIP0625F

Severity

Fatal error

Long Form

FIPS self-test complete. Result: FAIL. Failure in "{0}" test. The Security Server cannot continue and will be shutdown.

Short Form

FIPS self-test failed

Parameters

Label	CEF Label	Type	Usage
showStr	reason	Text	Code specifying reason for allowing access, if any

Description

None

Message ID : FIP0626F

Severity

Fatal error

Long Form

An unexpected error occurred during FIPS self-test. The Security Server cannot continue and will be shutdown.

Short Form

FIPS self-test failed

Parameters

No parameters are provided for this message type

Description

None

Logger FIP: Information

Message ID : FIP0624I

Severity

Information

Long Form

FIPS self-test complete. Result: PASS.

Short Form

FIPS self-test complete ok

Parameters

No parameters are provided for this message type

Description

None

Logger GEN: Errors

Message ID : GEN1253E

Severity

Error

Long Form

Invalid date format: {0}

Short Form

No short form is provided for this message type

Description

None

Message ID : GEN1280E

Severity

Error

Long Form

Failed to establish trusted connection to {0}. Reason: {1}

Short Form

failed to establish trusted connection

Parameters

Label	CEF Label	Type	Usage
shost	shost	Text	Source host name
showStr	reason	Text	Code specifying reason for allowing access, if any

Description

None

Logger GEN: Information

Message ID : GEN1276I

Severity

Information

Long Form

Data Security Manager was started successfully at {0}.

Short Form

server started

Parameters

Label	CEF Label	Type	Usage
stime	start	Text	A start time stamp

Description

None

Message ID : GEN1279I

Severity

Information

Long Form

Trusted channel established to {0}.

Short Form

trusted channel established

Parameters

Label	CEF Label	Type	Usage
shost	shost	Text	Source host name

Description

None

Logger IEP: Errors

Message ID : IEP0321E

Severity

Error

Long Form

The Security Server failed to retrieve the public key from the keystore.

Short Form

No short form is provided for this message type

Description

None

Message ID : IEP0322E

Severity

Error

Long Form

The Security Server failed to retrieve the private key from the keystore.

Short Form

No short form is provided for this message type

Description

None

Message ID : IEP0323E

Severity

Error

Long Form

The Security Server failed to decrypt the symmetric key that was used to protect the imported key data.

Short Form

No short form is provided for this message type

Message ID : IEP0322E

Description

None

Message ID : IEP0324E

Severity

Error

Long Form

The Security Server failed to write the imported key data into a temporary file. Check the server file system disk space.

Short Form

No short form is provided for this message type

Description

None

Message ID : IEP0325E

Severity

Error

Message ID : IEP0323E

Long Form

The Security Server failed to decrypt the imported keys.

Short Form

No short form is provided for this message type

Description

None

Message ID : IEP0326E

Severity

Error

Long Form

The Security server failed to open the file "{0}" for writing data.

Short Form

No short form is provided for this message type

Description

None

Message ID : IEP0327E**Severity**

Error

Long Form

The Security server failed to read the decrypted key data file.

Short Form

No short form is provided for this message type

Description

None

Message ID : IEP0328E**Severity**

Error

Message ID : IEP0326E

Long Form

The Security server will not import the keys into the server because the imported data has been tampered.

Short Form

No short form is provided for this message type

Description

None

Message ID : IEP0329E

Severity

Error

Long Form

The Security Server failed to connect to database cgssdb.

Short Form

No short form is provided for this message type

Description

None

Message ID : IEP0330E**Severity**

Error

Long Form

The Security Server failed to obtain server configuration from database.

Short Form

No short form is provided for this message type

Description

None

Message ID : IEP0331E**Severity**

Error

Message ID : IEP0329E

Long Form

The Security Server failed to export the public key.

Short Form

No short form is provided for this message type

Description

None

Message ID : IEP0332E

Severity

Error

Long Form

The Security Server failed to read key data.

Short Form

No short form is provided for this message type

Description

None

Logger IEP: Information

Message ID : IEP0577I

Severity

Information

Long Form

Configuration summary exported by {0}.

Short Form

configuration summary exported

Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name

Description

None

Logger IEP: Warnings

Message ID : IEP0338W

Severity

Warning

Long Form

There was key name conflict while importing keys. The key has been renamed: {0}.

Short Form

key renamed

Parameters

Label	CEF Label	Type	Usage
key	cs3	Text	Name of key or key pair

Description

None

Message ID : IEP0342W

Severity

Warning

Long Form

The unique to host key or clear key importing is not supported. The key {0} has been ignored.

Short Form

key ignored

Parameters

Label	CEF Label	Type	Usage
key	cs3	Text	Name of key or key pair

Description

None

Message ID : IEP0343W

Severity

Warning

Long Form

Duplicate key names encountered. Renamed imported keys. Please check the Management Console Log for details.

Short Form

No short form is provided for this message type

Description

None

Message ID : IEP0344W

Severity

Warning

Long Form

vormetric_clear key has been encountered but is not imported. Please check the Management Console Log for details.

Short Form

No short form is provided for this message type

Description

None

Message ID : IEP0345W

Severity

Warning

Long Form

There were key name conflicts and clear key encountered. Please check the Management Console Log for details.

Short Form

No short form is provided for this message type

Description

None

Logger KMG: Errors

Message ID : KMG0065E

Severity

Error

Long Form

Clear Key "{0}" cannot be deleted from the Security Server.

Short Form

No short form is provided for this message type

Description

None

Message ID : KMG0068E

Severity

Error

Long Form

Key Group Name "{0}" is already in use on this server. Specify a different name.

Short Form

No short form is provided for this message type

Description

None

Message ID : KMG0094E

Severity

Error

Long Form

The Security Server failed to save the key. Ensure that the Security Server database is functional. Contact support if the problem persists.

Short Form

No short form is provided for this message type

Message ID : KMG0068E

1237

Description

None

Message ID : KMG0095E

Severity

Error

Long Form

The Security Server failed to retrieve keys from the database. Previously saved keys are not lost. Ensure the Security Server database is functional. Contact support if the problem persists.

Short Form

No short form is provided for this message type

Description

None

Message ID : KMG0096E

Severity

Error

Long Form

The Security Server failed to delete one or more keys. Retry the operation. Ensure the Security Server database is functional. Contact support if the problem persists.

Short Form

No short form is provided for this message type

Description

None

Message ID : KMG0097E

Severity

Error

Long Form

The specified key(s) was not found in the database. The key(s) may have been deleted by another user.

Short Form

No short form is provided for this message type

Description

None

Message ID : KMG0098E

Severity

Error

Long Form

The Security Server could not find key "{0}" in the database. The key may have been deleted.

Short Form

No short form is provided for this message type

Description

None

Message ID : KMG0097E

Message ID : KMG0099E

Severity

Error

Long Form

The Security Server failed to create a key for the key name "{0}". Retry the operation. Contact support if the problem persists.

Short Form

No short form is provided for this message type

Description

None

Message ID : KMG0100E

Severity

Error

Long Form

The Security Server failed to retrieve the Backup encryption key from the header. This could be caused by a corrupt backup image. Contact support.

Message ID : KMG0099E

1241

Short Form

No short form is provided for this message type

Description

None

Message ID : KMG0101E

Severity

Error

Long Form

The specified key group(s) was not found in the database. The key group(s) may have been deleted by another user. Refresh the page and retry the operation.

Short Form

No short form is provided for this message type

Description

None

Message ID : KMG0100E

Message ID : KMG0102E

Severity

Error

Long Form

The Security Server could not delete Key Group "{0}". Please remove member keys and/or associated client identities and retry the operation.

Short Form

No short form is provided for this message type

Description

None

Message ID : KMG0103E

Severity

Error

Long Form

The Security Server could not delete Key "{0}". The Key is currently in use by some security policies.

Short Form

No short form is provided for this message type

Description

None

Message ID : KMG0104E

Severity

Error

Long Form

The Security Server could not create an empty Key Group. The Key Group must have at least one local key or an Affiliate key.

Short Form

No short form is provided for this message type

Description

None

Message ID : KMG0105E

Severity

Error

Long Form

The Security Server failed to delete affiliate key. Retry the operation. Ensure the Security Server database is functional. Contact support if the problem persists.

Short Form

No short form is provided for this message type

Description

None

Message ID : KMG0106E

Severity

Error

Long Form

The Security Server failed to retrieve key groups from the database. Previously saved key groups are not lost. Ensure the Security Server database is functional. Contact support if the problem persists.

Short Form

No short form is provided for this message type

Description

None

Message ID : KMG0107E

Severity

Error

Long Form

The Security Server failed to create the key group "{0}". Retry the operation. Ensure the Security Server database is functional. Contact support if the problem persists.

Short Form

No short form is provided for this message type

Description

None

Message ID : KMG0108E

Severity

Error

Long Form

The Security Server failed to update key group "{0}". Retry the operation. Ensure the Security Server database is functional. Contact support if the problem persists.

Short Form

No short form is provided for this message type

Description

None

Message ID : KMG0107E

1247

Message ID : KMG0109E

Severity

Error

Long Form

The Security Server failed to delete key group(s). Retry the operation. Ensure the key group or key(s) in the group is not used in an existing policy. Ensure the Security Server database is functional. Contact support if the problem persists.

Short Form

No short form is provided for this message type

Description

None

Message ID : KMG0110E

Severity

Error

Long Form

The Security Server failed to import the public key input. The public key input was invalid. Choose from a different file and retry the operation.

Short Form

No short form is provided for this message type

Description

None

Message ID : KMG0111E

Severity

Error

Long Form

Header information provided by agent indicates a version that can not be handled by this server. Please update the server to a later version.

Short Form

unsupported version in header info

Message ID : KMG0110E

1249

Parameters

No parameters are provided for this message type

Description

None

Message ID : KMG0112E

Severity

Error

Long Form

The Security Server failed to retrieve the header version. Restore operation will be aborted. Contact support.

Short Form

failed to retrieve header version

Parameters

No parameters are provided for this message type

Message ID : KMG0111E

Description

None

Message ID : KMG0113E

Severity

Error

Long Form

The encryption mode for key name "{0}" cannot be updated.

Short Form

No short form is provided for this message type

Description

None

Message ID : KMG0114E

Severity

Error

Message ID : KMG0112E

Long Form

The user does not have permission to delete this key.

Short Form

No short form is provided for this message type

Description

None

Message ID : KMG0220E

Severity

Error

Long Form

Key Name "{0}" is already in use on this server. Specify a different key name.

Short Form

No short form is provided for this message type

Description

None

Message ID : KMG0221E

Severity

Error

Long Form

{0} is not a correct length for an asymmetric key.

Short Form

No short form is provided for this message type

Description

None

Message ID : KMG0222E

Severity

Error

Message ID : KMG0220E

Long Form

Key UUID "{0}" is already in use on this server. Specify a different key UUID.

Short Form

No short form is provided for this message type

Description

None

Message ID : KMG0256E

Severity

Error

Long Form

Unsupported symmetric key type for key "{0}"

Short Form

No short form is provided for this message type

Description

None

Message ID : KMG0257E

Severity

Error

Long Form

Unsupported symmetric key type for key "{0}". CBC or CBC_CS1 encryption modes are used for AES keys only.

Short Form

No short form is provided for this message type

Description

None

Message ID : KMG0258E

Severity

Error

Message ID : KMG0256E

Long Form

The key "{0}" that you are trying to add to the vault uses CBC CS1 encryption mode which is not supported.

Short Form

No short form is provided for this message type

Description

None

Message ID : KMG0262E

Severity

Error

Long Form

The Security Server failed to access the server key store. Refer to cgss.log and server.log for details. Call support if necessary.

Short Form

No short form is provided for this message type

Description

None

Message ID : KMG0265E

Severity

Error

Long Form

The Security Server failed to generate symmetric key "{0}".

Short Form

No short form is provided for this message type

Description

None

Message ID : KMG0273E

Severity

Error

Message ID : KMG0262E

Long Form

The Security Server failed to perform encryption using a symmetric key.

Short Form

No short form is provided for this message type

Description

None

Message ID : KMG0274E

Severity

Error

Long Form

Invalid key type to export. The Security Server only supports export of the public keys.

Short Form

No short form is provided for this message type

Message ID : KMG0273E

Description

None

Message ID : KMG0285E

Severity

Error

Long Form

The Security Server failed to create the backup header for offline protection. Refer to cgss.log and server.log for details. Call support if necessary.

Short Form

No short form is provided for this message type

Description

None

Message ID : KMG0301E

Severity

Error

Long Form

The Security Server could not delete Key "{0}". The Key is currently in key group(s).

Short Form

No short form is provided for this message type

Description

None

Message ID : KMG0307E

Severity

Error

Long Form

The Security Server could not get the fingerprint of the CA certificate.

Short Form

No short form is provided for this message type

Description

None

Message ID : KMG0524E

Severity

Error

Long Form

Invalid Query. Cannot specify multiple KeyIdentifiers for query

Short Form

No short form is provided for this message type

Description

None

Message ID : KMG0615E

Severity

Error

Long Form

File to import has unexpected format.

Short Form

No short form is provided for this message type

Description

None

Message ID : KMG0616E

Severity

Error

Long Form

Format of the file to import is newer than the format this Security Server supports.

Short Form

No short form is provided for this message type

Description

None

Message ID : KMG0686E

Severity

Error

Long Form

Key Attribute ID "{0}" is already in use on this server. Specify a different key attribute id.

Short Form

No short form is provided for this message type

Description

None

Message ID : KMG0687E

Severity

Error

Long Form

The specified key attribute(s) was not found in the database. The key attribute(s) may have been deleted by another user.

Short Form

No short form is provided for this message type

Description

None

Message ID : KMG0688E

Severity

Error

Long Form

Key template name "{0}" in the domain is already in use on this server. Please specify a different key template name in the domain.

Short Form

No short form is provided for this message type

Description

None

Message ID : KMG0689E

Severity

Error

Long Form

The specified key template was not found in the database. The key template(s) may have been deleted by another user.

Short Form

No short form is provided for this message type

Description

None

Message ID : KMG0690E

Severity

Error

Long Form

Key Template Attribute ID "{0}" is already in use on this server. Specify a different key template attribute id.

Short Form

No short form is provided for this message type

Description

None

Message ID : KMG0691E

Severity

Error

Long Form

The specified key template attribute was not found in the database. The key template attribute(s) may have been deleted by another user.

Short Form

No short form is provided for this message type

Description

None

Message ID : KMG0692E

Severity

Error

Long Form

The specified key ID was not found in the database. The key attribute may have been deleted by another user.

Short Form

No short form is provided for this message type

Description

None

Message ID : KMG0693E

Severity

Error

Long Form

Key string confirmation failed.

Short Form

No short form is provided for this message type

Description

None

Message ID : KMG0694E

Severity

Error

Long Form

The specified key attribute(s) was found in the database.

Short Form

No short form is provided for this message type

Description

None

Message ID : KMG0695E

Severity

Error

Long Form

The Security Server failed to import the private key input. The private key input was invalid. Choose from a different file and retry the operation.

Short Form

No short form is provided for this message type

Description

None

Message ID : KMG0694E

Message ID : KMG0696E

Severity

Error

Long Form

The duplicated attribute name is not allowed.

Short Form

No short form is provided for this message type

Description

None

Message ID : KMG0698E

Severity

Error

Long Form

The Security Server failed to import the public key and private key input. Either the public key or the private key input was invalid. Choose from a different file and retry the operation.

Message ID : KMG0696E

1270

Short Form

No short form is provided for this message type

Description

None

Message ID : KMG0699E

Severity

Error

Long Form

The Security Server failed to create the key template.

Short Form

No short form is provided for this message type

Description

None

Message ID : KMG0700E

Severity

Error

Long Form

Key template name needs to be specified.

Short Form

No short form is provided for this message type

Description

None

Message ID : KMG0708E

Severity

Error

Long Form

The Security Server failed to validate public key. Please see cgss.log or server.log for details.

Short Form

No short form is provided for this message type

Description

None

Message ID : KMG0709E

Severity

Error

Long Form

The Security Server failed to validate private key. Either private key format is invalid or public key and private key are not a key pair.

Short Form

No short form is provided for this message type

Description

None

Message ID : KMG0708E

Message ID : KMG0726E

Severity

Error

Long Form

The Security Server failed to validate the vault key pair.

Short Form

No short form is provided for this message type

Description

None

Message ID : KMG0727E

Severity

Error

Long Form

The Security Server failed to validate the vault key pair. The specified key type (length) does not match actual key type (length).

Short Form

No short form is provided for this message type

Description

None

Message ID : KMG0728E

Severity

Error

Long Form

Unique identifier is not specified.

Short Form

No short form is provided for this message type

Description

None

Message ID : KMG0727E

1275

Message ID : KMG0729E

Severity

Error

Long Form

Invalid unique identifier.

Short Form

No short form is provided for this message type

Description

None

Message ID : KMG0730E

Severity

Error

Long Form

The name and value cannot be null.

Short Form

No short form is provided for this message type

Description

None

Message ID : KMG0731E

Severity

Error

Long Form

Client is not allowed to perform the specified operation.

Short Form

No short form is provided for this message type

Description

None

Message ID : KMG0732E

Severity

Error

Long Form

Cannot destroy the managed key object in database.rm -rf /opt

Short Form

No short form is provided for this message type

Description

None

Message ID : KMG0733E

Severity

Error

Long Form

The operation {0} is not available on a failover server.

Short Form

No short form is provided for this message type

Description

None

Message ID : KMG0734E

Severity

Error

Long Form

Server does not support operation. Operation Not Supported on key length {0}.

Short Form

No short form is provided for this message type

Description

None

Message ID : KMG0735E

Severity

Error

Long Form

Server does not support operation. Operation Not Supported on the cryptographic algorithm {0}.

Short Form

No short form is provided for this message type

Description

None

Message ID : KMG0736E

Severity

Error

Long Form

Object Type is not recognized. Invalid Field on {0}.

Short Form

No short form is provided for this message type

Description

None

Message ID : KMG0737E

Severity

Error

Long Form

Cannot store the key data into the database.

Short Form

No short form is provided for this message type

Description

None

Message ID : KMG0736E

Message ID : KMG0738E

Severity

Error

Long Form

Error Creating Cryptographic Object.

Short Form

No short form is provided for this message type

Description

None

Message ID : KMG0739E

Severity

Error

Long Form

Non-existing attributes, attributes that the server does not understand or templates that do not exist are given in the request.

Short Form

No short form is provided for this message type

Description

None

Message ID : KMG0740E

Severity

Error

Long Form

The Key Management Web Service does not allow duplicate key attributes.

Short Form

No short form is provided for this message type

Description

None

Message ID : KMG0741E

Severity

Error

Long Form

Cannot locate the key data in the database.

Short Form

No short form is provided for this message type

Description

None

Message ID : KMG0742E

Severity

Error

Long Form

Item Deleted.

Short Form

No short form is provided for this message type

Description

None

Message ID : KMG0743E

Severity

Error

Long Form

Item Out Of Range.

Short Form

No short form is provided for this message type

Description

None

Message ID : KMG0742E

1285

Message ID : KMG0744E

Severity

Error

Long Form

Object does not exist.

Short Form

No short form is provided for this message type

Description

None

Message ID : KMG0745E

Severity

Error

Long Form

Cannot find the key data in database.

Short Form

No short form is provided for this message type

Description

None

Message ID : KMG0746E

Severity

Error

Long Form

No object with the specified Unique Identifier exists.

Short Form

No short form is provided for this message type

Description

None

Message ID : KMG0747E

Severity

Error

Long Form

Cannot add the key attribute in database.

Short Form

No short form is provided for this message type

Description

None

Message ID : KMG0748E

Severity

Error

Long Form

Cannot modify the key attribute in database.

Short Form

No short form is provided for this message type

Description

None

Message ID : KMG0749E

Severity

Error

Long Form

Attempt to delete a read-only/REQUIRED attribute.

Short Form

No short form is provided for this message type

Description

None

Message ID : KMG0750E

Severity

Error

Long Form

No attribute with the specified name exists.

Short Form

No short form is provided for this message type

Description

None

Message ID : KMG0751E

Severity

Error

Long Form

Cannot delete the key attribute in database.

Short Form

No short form is provided for this message type

Description

None

Message ID : KMG0752E

Severity

Error

Long Form

Cannot encrypt the data from the key agent.

Short Form

No short form is provided for this message type

Description

None

Message ID : KMG0753E

Severity

Error

Long Form

Cannot decrypt the data from the key agent.

Short Form

No short form is provided for this message type

Description

None

Message ID : KMG0754E

Severity

Error

Long Form

Cannot sign the data from the key agent.

Short Form

No short form is provided for this message type

Description

None

Message ID : KMG0755E

Severity

Error

Long Form

Cannot encrypt the data with rsa key from the key agent.

Short Form

No short form is provided for this message type

Description

None

Message ID : KMG0756E

Severity

Error

Long Form

Cannot decrypt the data with rsa key from the key agent.

Short Form

No short form is provided for this message type

Description

None

Message ID : KMG0757E

Severity

Error

Long Form

The Expiry Date cannot be the same or earlier than the creation date. Please correct the problem and try again.

Short Form

No short form is provided for this message type

Description

None

Message ID : KMG0758E

Severity

Error

Long Form

REQUIRED field(s) "{0}" is missing.

Short Form

No short form is provided for this message type

Description

None

Message ID : KMG0760E

Severity

Error

Long Form

The {0} timestamp is invalid.

Short Form

No short form is provided for this message type

Description

None

Message ID : KMG0762E

Severity

Error

Long Form

The attribute name entry is duplicated with the existing attribute name {0}.

Short Form

No short form is provided for this message type

Description

None

Message ID : KMG0765E

Severity

Error

Long Form

The key string with key name {0} must contain 48 hex characters for 3DES; or 32 hex characters for AES128 or ARIA128; or 64 hex characters for AES256 or ARIA256.

Short Form

No short form is provided for this message type

Description

None

Message ID : KMG0762E

1297

Message ID : KMG0766E

Severity

Error

Long Form

The key value with key name {0} is not in hex format. Please correct the problem and try again.

Short Form

No short form is provided for this message type

Description

None

Message ID : KMG0767E

Severity

Error

Long Form

The symmetric key entry is too big. The maximum key size is 399 bytes.

Short Form

No short form is provided for this message type

Description

None

Message ID : KMG0768E

Severity

Error

Long Form

The public key entry is too big. The maximum public key size is 5000 bytes.

Short Form

No short form is provided for this message type

Description

None

Message ID : KMG0769E

Severity

Error

Long Form

The private key entry is too big. The maximum private key size is 7487 bytes.

Short Form

No short form is provided for this message type

Description

None

Message ID : KMG0770E

Severity

Error

Long Form

The key string with key name {0} must contain 48 hex characters for 3DES; or 32 hex characters for AES128 or ARIA128; or 64 hex characters for AES256 or ARIA256. If CBC_CS1 or XTS encryption mode is used for AES keys, the expected key length is

doubled.

Short Form

No short form is provided for this message type

Description

None

Message ID : KMG0773E

Severity

Error

Long Form

Wrapper Key is corrupt. Import or generate a new one.

Short Form

No short form is provided for this message type

Description

None

Message ID : KMG0770E

Message ID : KMG0775E

Severity

Error

Long Form

The Security Server could not delete the vault key "{0}". The vault key is currently in use by a policy.

Short Form

No short form is provided for this message type

Description

None

Message ID : KMG1252E

Severity

Error

Long Form

The creation date for the key cannot be future date and time.

Short Form

No short form is provided for this message type

Description

None

Message ID : KMG1255E

Severity

Error

Long Form

Cannot import the symmetric agent key "{0}" with unique to host set to true.

Short Form

No short form is provided for this message type

Description

None

Message ID : KMG1258E

Severity

Error

Long Form

Both public key and private key are null. Please correct the problem and try again.

Short Form

No short form is provided for this message type

Description

None

Message ID : KMG1267E

Severity

Error

Long Form

Unsupported certificate encoding.

Short Form

No short form is provided for this message type

Description

None

Message ID : KMG1268E

Severity

Error

Long Form

No such algorithm.

Short Form

No short form is provided for this message type

Description

None

Message ID : KMG1269E

Severity

Error

Long Form

No such provider.

Short Form

No short form is provided for this message type

Description

None

Message ID : KMG1270E

Severity

Error

Long Form

The key is invalid.

Short Form

No short form is provided for this message type

Description

None

Message ID : KMG1271E

Severity

Error

Long Form

No subject alternative names present.

Short Form

No short form is provided for this message type

Description

None

Message ID : KMG1270E

Message ID : KMG1272E

Severity

Error

Long Form

The signatures are not matching.

Short Form

No short form is provided for this message type

Description

None

Message ID : KMG1273E

Severity

Error

Long Form

General security error.

Short Form

No short form is provided for this message type

Description

None

Message ID : KMG1274E

Severity

Error

Long Form

Unable to parse the certificate.

Short Form

No short form is provided for this message type

Description

None

Message ID : KMG1273E

Message ID : KMG1282E

Severity

Error

Long Form

Operation Not Supported on the managed object: the symmetric key is not specified.

Short Form

No short form is provided for this message type

Description

None

Message ID : KMG1283E

Severity

Error

Long Form

Operation Not Supported on the managed object: the public exponent and modulus for the public key are not specified.

Short Form

No short form is provided for this message type

Description

None

Message ID : KMG1284E

Severity

Error

Long Form

Operation Not Supported on the managed object: the private exponent and modulus for the private key are not specified.

Short Form

No short form is provided for this message type

Description

None

Message ID : KMG1338E

Severity

Error

Long Form

No such algorithm for message digest (SHA-384).

Short Form

No short form is provided for this message type

Description

None

Message ID : KMG1339E

Severity

Error

Long Form

The expiration date cannot be before today.

Message ID : KMG1338E

Short Form

No short form is provided for this message type

Description

None

Message ID : KMG1340E

Severity

Error

Long Form

Encryption failed, public key is null.

Short Form

No short form is provided for this message type

Description

None

Message ID : KMG1339E

Message ID : KMG1341E

Severity

Error

Long Form

Encryption failed, empty payload.

Short Form

No short form is provided for this message type

Description

None

Message ID : KMG1380E

Severity

Error

Long Form

The symmetric key {0} does not exist. Please use another symmetric key name for the key rotation.

Short Form

No short form is provided for this message type

Description

None

Message ID : KMG1382E

Severity

Error

Long Form

Key [Name: {0}, Description: {1}] versioning failed. Reason: {2}

Short Form

No short form is provided for this message type

Description

None

Message ID : KMG1383E

Severity

Error

Long Form

Key "{0}" is not enabled for versioning in domain {1}.

Short Form

No short form is provided for this message type

Description

None

Message ID : KMG1384E

Severity

Error

Long Form

The symmetric key (name:{0}, version :{1}) version does not exist

Short Form

No short form is provided for this message type

Description

None

Message ID : KMG1385E

Severity

Error

Long Form

Key version life span is between 2 and 99999 inclusively.

Short Form

No short form is provided for this message type

Description

None

Message ID : KMG1387E

Severity

Error

Long Form

Administrator "{0}" failed to version key [Name: {1}, Description: {2}].

Short Form

No short form is provided for this message type

Description

None

Message ID : KMG1388E

Severity

Error

Long Form

Key Refresh Period value for "{0}" can be between {1} and {2} inclusively.

Short Form

No short form is provided for this message type

Description

None

Message ID : KMG1394E

Severity

Error

Long Form

Template enforcement is in effect, cannot modify expiration time

Short Form

No short form is provided for this message type

Description

None

Message ID : KMG1409E

Severity

Error

Long Form

Key(s) import failed. A problem could be that you do not have the right wrapper key installed.

Short Form

No short form is provided for this message type

Description

None

Message ID : KMG1410E

Severity

Error

Long Form

Server does not support the operation "{0}" at this time.

Short Form

No short form is provided for this message type

Description

None

Message ID : KMG1411E

Severity

Error

Long Form

The key type "{0}" is not supported.

Short Form

No short form is provided for this message type

Description

None

Message ID : KMG1412E

Severity

Error

Long Form

No such key wrapping specification.

Short Form

No short form is provided for this message type

Description

None

Message ID : KMG1413E

Severity

Error

Long Form

The block cipher mode "{0}" is not supported.

Short Form

No short form is provided for this message type

Description

None

Message ID : KMG1414E

Severity

Error

Long Form

The key identifier "{0}" is not recognized.

Short Form

No short form is provided for this message type

Description

None

Message ID : KMG1416E

Severity

Error

Long Form

Key Agent at {1} is not authorized to access key "{0}".

Short Form

No short form is provided for this message type

Description

None

Message ID : KMG1417E

Severity

Error

Long Form

Cannot encrypt the password.

Message ID : KMG1416E

Short Form

No short form is provided for this message type

Description

None

Message ID : KMG1418E

Severity

Error

Long Form

The format of the password does not conform to the password policy.

Short Form

No short form is provided for this message type

Description

None

Message ID : KMG1417E

Message ID : KMG1430E

Severity

Error

Long Form

Key {0} is not enabled for versioning. Only versioned keys can be rotated

Short Form

No short form is provided for this message type

Description

None

Message ID : KMG1512E

Severity

Error

Long Form

Certificate "{0}" has expired.

Short Form

No short form is provided for this message type

Description

None

Message ID : KMG1518E

Severity

Error

Long Form

Client must provide a non zero random byte size.

Short Form

No short form is provided for this message type

Description

None

Message ID : KMG1521E

Severity

Error

Long Form

Attribute "{0}" requires epoch time as long integer attribute value.

Short Form

No short form is provided for this message type

Description

None

Message ID : KMG1522E

Severity

Error

Long Form

Value of "{0}" cannot be null or empty

Short Form

No short form is provided for this message type

Description

None

Message ID : KMG1523E

Severity

Error

Long Form

Unable to update key-state. Invalid key-state transition from "{0}" to "{1}" was attempted.

Short Form

No short form is provided for this message type

Description

None

Message ID : KMG1525E

Severity

Error

Long Form

Cannot add the key attribute. Key already enabled for versioning

Short Form

No short form is provided for this message type

Description

None

Message ID : KMG1526E

Severity

Error

Long Form

Cannot add/modify the key attribute "{0}" due to potential invalid key-state transition from "{1}" to "{2}".

Short Form

No short form is provided for this message type

Description

None

Message ID : KMG1527E

Severity

Error

Long Form

Failed to generate unique external key identifier after retries. Please try again later or contact Support for assistance.

Short Form

No short form is provided for this message type

Description

None

Message ID : KMG1528E

Severity

Error

Long Form

Unable to generate random integer for external key identifier.

Short Form

No short form is provided for this message type

Description

None

Message ID : KMG1529E

Severity

Error

Long Form

Cannot add/modify attribute "{0}" due to potential invalid key-state-action transition from "{1}" to "{2}".

Short Form

No short form is provided for this message type

Description

None

Message ID : KMG1531E

Severity

Error

Long Form

Unable to update key-state-action. Invalid key-state-action transition from "{0}" to "{1}" was attempted.

Short Form

No short form is provided for this message type

Description

None

Message ID : KMG1532E

Severity

Error

Long Form

Unsupported key attribute "{0}" was found in create template.

Short Form

No short form is provided for this message type

Description

None

Message ID : KMG1533E

Severity

Error

Long Form

Cannot accept past date for attribute "{0}".

Short Form

No short form is provided for this message type

Description

None

Message ID : KMG1534E

Severity

Error

Long Form

Date attribute "{0}" value cannot be greater than or equal to date attribute "{1}" value.

Short Form

No short form is provided for this message type

Description

None

Message ID : KMG1535E

Severity

Error

Long Form

Invalid key-state-action transition was attempted. Key is not in 'ACTIVE' state.

Short Form

No short form is provided for this message type

Description

None

Message ID : KMG1536E

Severity

Error

Long Form

Cannot accept destroy date without de-activation date.

Short Form

No short form is provided for this message type

Description

None

Message ID : KMG1537E

Severity

Error

Long Form

Invalid date for "{0}". Value must be greater than x-activation-date but lower than x-suspend-date, x-deactivation-date, x-destroy-date.

Short Form

No short form is provided for this message type

Description

None

Message ID : KMG1536E

1337

Message ID : KMG1538E

Severity

Error

Long Form

Cannot delete attribute "{0}" that has epoch time in the past. This indicates that associated jobs may already have been executed and therefore attribute must be retained at server for audit log purposes.

Short Form

No short form is provided for this message type

Description

None

Message ID : KMG1539E

Severity

Error

Long Form

Version {0} already exists for key {1}

Short Form

No short form is provided for this message type

Description

None

Message ID : KMG1540E

Severity

Error

Long Form

Cannot add versions to non-versioned key {0}

Short Form

No short form is provided for this message type

Description

None

Message ID : KMG1541E**Severity**

Error

Long Form

Opaque Object not specified

Short Form

No short form is provided for this message type

Description

None

Message ID : KMG1542E**Severity**

Error

Message ID : KMG1540E

Long Form

Opaque Object not found for id {0}

Short Form

No short form is provided for this message type

Description

None

Message ID : KMG1544E

Severity

Error

Long Form

One or more of the specified key attribute(s) is read-only and cannot be deleted.

Short Form

No short form is provided for this message type

Description

None

Message ID : KMG1545E

Severity

Error

Long Form

The opaque object size is too big. The maximum opaque object size supported is {0} bytes.

Short Form

No short form is provided for this message type

Description

None

Message ID : KMG1546E

Severity

Error

Message ID : KMG1544E

Long Form

Cannot perform encryption in "{0}" key state.

Short Form

No short form is provided for this message type

Description

None

Message ID : KMG1547E

Severity

Error

Long Form

Cannot clone external key.

Short Form

No short form is provided for this message type

Message ID : KMG1546E

Description

None

Message ID : KMG1566E

Severity

Error

Long Form

Unexpected key usage value "{0}". Expected values are:"{1}"

Short Form

No short form is provided for this message type

Description

None

Message ID : KMG1591E

Severity

Error

Message ID : KMG1547E

Long Form

unwrapping key is not provided.

Short Form

No short form is provided for this message type

Description

None

Message ID : KMG1592E

Severity

Error

Long Form

unwrapping payload of type {0} is not supported as of now.

Short Form

No short form is provided for this message type

Description

None

Message ID : KMG1593E

Severity

Error

Long Form

unwrapping with keys of format {0} is not supported as of now .

Short Form

No short form is provided for this message type

Description

None

Message ID : KMG1594E

Severity

Error

Message ID : KMG1592E

Long Form

The Security Server failed to perform decryption using a symmetric key.

Short Form

No short form is provided for this message type

Description

None

Message ID : KMG1595E

Severity

Error

Long Form

The wrapped key bytes are not provided.

Short Form

No short form is provided for this message type

Message ID : KMG1594E

Description

None

Message ID : KMG1596E

Severity

Error

Long Form

The Key format is not provided.

Short Form

No short form is provided for this message type

Description

None

Message ID : KMG1597E

Severity

Error

Message ID : KMG1595E

Long Form

The Host Name and Agent Type are not provided.

Short Form

No short form is provided for this message type

Description

None

Message ID : KMG1598E

Severity

Error

Long Form

Host Not Found.

Short Form

No short form is provided for this message type

Message ID : KMG1597E

Description

None

Message ID : KMG1599E

Severity

Error

Long Form

Unwrapped Keylength {0} does not match the length {1} provided in template attributes.

Short Form

No short form is provided for this message type

Description

None

Message ID : KMG1600E

Severity

Error

Message ID : KMG1598E

Long Form

Unwrapping versioned keys is not supported.

Short Form

No short form is provided for this message type

Description

None

Message ID : KMG1610E

Severity

Error

Long Form

Cryptographic Mask is not specified for the key you are trying to export.

Short Form

No short form is provided for this message type

Description

None

Message ID : KMG1612E**Severity**

Error

Long Form

Unable to parse the public key.

Short Form

No short form is provided for this message type

Description

None

Message ID : KMG1613E**Severity**

Error

Message ID : KMG1610E

Long Form

Invalid unwrapping key.

Short Form

No short form is provided for this message type

Description

None

Message ID : KMG1618E

Severity

Error

Long Form

default key template(s)cannot be deleted.

Short Form

No short form is provided for this message type

Description

None

Message ID : KMG1619E

Severity

Error

Long Form

Key attributes "{0}" does not match with key template "{1}" attributes

Short Form

No short form is provided for this message type

Description

None

Message ID : KMG1620E

Severity

Error

Message ID : KMG1618E

Long Form

Asymmetric key can not created with template "{0}" algorithm type "{1}"

Short Form

No short form is provided for this message type

Description

None

Message ID : KMG1621E

Severity

Error

Long Form

SAAS key(s) or clear_key are not eligible for export

Short Form

No short form is provided for this message type

Description

None

Message ID : KMG1622E

Severity

Error

Long Form

Export failed. Possible payload contains SAAS key(s), clear_key or non-existing keys. SAAS keys, clear_key are not eligible for export

Short Form

No short form is provided for this message type

Description

None

Message ID : KMG1624E

Severity

Error

Long Form

Default key template attribute can not be modified

Short Form

No short form is provided for this message type

Description

None

Message ID : KMG1625E

Severity

Error

Long Form

Neither keyid or keyname are specified.

Short Form

No short form is provided for this message type

Description

None

Message ID : KMG1626E

Severity

Error

Long Form

Key state value "{0}" is not valid keystate.

Short Form

No short form is provided for this message type

Description

None

Message ID : KMG1633E

Severity

Error

Long Form

Key attribute name "{0}" is a system reserved name and read only. Please choose a different name for this new attribute.

Short Form

No short form is provided for this message type

Description

None

Message ID : KMG1635E

Severity

Error

Long Form

Key Name cannot be longer than {0} characters

Short Form

No short form is provided for this message type

Description

None

Message ID : KMG1636E

Severity

Error

Long Form

Invalid key name. Only alpha numeric characters, dot("."), underscore("_"), slash("/"), equal sign("="), plus("+") and ("-") are allowed and key name must start with letter or number

Short Form

No short form is provided for this message type

Description

None

Message ID : KMG1637E

Severity

Error

Long Form

Key description cannot be longer than {0} characters

Short Form

No short form is provided for this message type

Description

None

Message ID : KMG1638E

Severity

Error

Long Form

KMIP is not enabled

Message ID : KMG1637E

Short Form

No short form is provided for this message type

Description

None

Message ID : KMG1639E

Severity

Error

Long Form

Could not create the KMIP key

Short Form

No short form is provided for this message type

Description

None

Message ID : KMG1638E

Message ID : KMG1640E

Severity

Error

Long Form

Key length mismatch

Short Form

No short form is provided for this message type

Description

None

Message ID : KMG1641E

Severity

Error

Long Form

Activation date cannot be in the past

Short Form

No short form is provided for this message type

Description

None

Message ID : KMG1642E

Severity

Error

Long Form

Deactivation date cannot be in the past

Short Form

No short form is provided for this message type

Description

None

Message ID : KMG1641E

Message ID : KMG1643E

Severity

Error

Long Form

Deactivation date cannot be before the activation date

Short Form

No short form is provided for this message type

Description

None

Message ID : KMG1644E

Severity

Error

Long Form

Invalid size of {0} for key

Message ID : KMG1643E

Short Form

No short form is provided for this message type

Description

None

Message ID : KMG1647E

Severity

Error

Long Form

KMIP key of UUID "{0}" deletion failed. Error: "{1}"

Short Form

No short form is provided for this message type

Description

None

Message ID : KMG1648E

Severity

Error

Long Form

KMIP object of UUID "{0}" not found

Short Form

No short form is provided for this message type

Description

None

Message ID : KMG1650E

Severity

Error

Long Form

Key template with key usage "CACHE_ON_HOST" or "STORED_ON_SERVER" eligible for symmetric keys only

Short Form

No short form is provided for this message type

Description

None

Message ID : KMG1651E

Severity

Error

Long Form

RSA Publickey of size should be 2048 bits or larger.

Short Form

No short form is provided for this message type

Description

None

Message ID : KMG1653E

Severity

Error

Long Form

Key version number must be numeric.

Short Form

No short form is provided for this message type

Description

None

Message ID : KMG1654E

Severity

Error

Long Form

Key version number must be greater or equal to zero.

Short Form

No short form is provided for this message type

Description

None

Message ID : KMG1660E

Severity

Error

Long Form

Cannot add versionLifeSpan to non-versioned key {0}

Short Form

No short form is provided for this message type

Description

None

Message ID : KMG1661E

Severity

Error

Long Form

Cannot add restricted key {0}

Short Form

No short form is provided for this message type

Description

None

Message ID : KMG1666E

Severity

Error

Long Form

Provided key format is unexpected, expected format is "RSA PUBLIC KEY" as "PEM"

Short Form

No short form is provided for this message type

Description

None

Message ID : KMG1667E

Severity

Error

Long Form

Imported Key Name "{0}" is already in use on this server. Delete the existing key and import again.

Short Form

No short form is provided for this message type

Description

None

Message ID : KMG1670E

Severity

Error

Long Form

Unsupported symmetric key type for key "{0}". {1} encryption mode is used for AES256 keys only.

Short Form

No short form is provided for this message type

Description

None

Message ID : KMG1674E

Severity

Error

Long Form

Encryption mode must be set for AES keys

Short Form

No short form is provided for this message type

Description

None

Message ID : KMG1675E

Severity

Error

Long Form

KMIP accessible key "{0}" contains invalid client attribute names. A valid KMIP client attribute name shall have a prefix of "x-".

Short Form

No short form is provided for this message type

Description

None

Message ID : KMG1676E

Severity

Error

Long Form

Invalid key template "{0}" for key "{1}"

Short Form

No short form is provided for this message type

Description

None

Message ID : KMG1677E

Severity

Error

Long Form

Invalid key type "{0}/{1}" of usage "{2}" for KMIP accessible key "{3}"

Short Form

No short form is provided for this message type

Description

None

Message ID : KMG1694E

Severity

Error

Long Form

Missing Link attribute for KMIP accessible key {0}

Short Form

No short form is provided for this message type

Description

None

Message ID : KMG1677E

Message ID : KMG1695E

Severity

Error

Long Form

Updating key {0} in KMIP failed: {1}.

Short Form

No short form is provided for this message type

Description

None

Message ID : KMG1696E

Severity

Error

Long Form

Deleting key attribute "{0}" in KMIP is not allowed.

Short Form

No short form is provided for this message type

Description

None

Message ID : KMG1698E

Severity

Error

Long Form

Cannot encrypt data using private key.

Short Form

No short form is provided for this message type

Description

None

Message ID : KMG1696E

Message ID : KMG1699E

Severity

Error

Long Form

Cannot decrypt data using public key.

Short Form

No short form is provided for this message type

Description

None

Message ID : KMG1700E

Severity

Error

Long Form

Cannot sign data using public key.

Short Form

No short form is provided for this message type

Description

None

Message ID : KMG1701E

Severity

Error

Long Form

Cannot verify the signed data using private key.

Short Form

No short form is provided for this message type

Description

None

Message ID : KMG1720E

Severity

Error

Long Form

Invalid {0} algorithm.

Short Form

No short form is provided for this message type

Description

None

Message ID : KMG1728E

Severity

Error

Long Form

The Security Server could not allow exporting affiliate key "{0}".

Short Form

No short form is provided for this message type

Description

None

Message ID : KMG1745E

Severity

Error

Long Form

Key Governance is enabled so key cannot be modified

Short Form

No short form is provided for this message type

Description

None

Message ID : KMG1728E

Message ID : KMG1762E

Severity

Error

Long Form

EXT_KID key attribute can only consist alphanumeric and dash (-) characters, cannot be empty or longer than {0} characters.

Short Form

No short form is provided for this message type

Description

None

Message ID : KMG1763E

Severity

Error

Long Form

The specified key(s) "{0}" was not found in the DSM.

Short Form

No short form is provided for this message type

Description

None

Message ID : KMG1764E

Severity

Error

Long Form

The specified key(s) with algorithms "{0}" not supported.

Short Form

No short form is provided for this message type

Description

None

Message ID : KMG1765E

Severity

Error

Long Form

Wrapping for "clear_key" not supported.

Short Form

No short form is provided for this message type

Description

None

Message ID : KMG1766E

Severity

Error

Long Form

Duplicate keys present in the request.

Short Form

No short form is provided for this message type

Description

None

Message ID : KMG1767E

Severity

Error

Long Form

The specified key(s) "{0}" are not exportable.

Short Form

No short form is provided for this message type

Description

None

Message ID : KMG1768E

Severity

Error

Long Form

The specified key(s) "{0}" state is DESTROYED.

Short Form

No short form is provided for this message type

Description

None

Message ID : KMG1771E

Severity

Error

Long Form

Size of RSA Public key should be 2048 bits, 3072 bits or 4096 bits.

Short Form

No short form is provided for this message type

Description

None

Message ID : KMG1772E

Severity

Error

Long Form

Invalid Subject Alternative Type provided in the SAN "{0}". Allowed types can be EMAIL, URI, DNS, IP, or OID.

Short Form

No short form is provided for this message type

Description

None

Message ID : KMG1771E

Message ID : KMG1773E

Severity

Error

Long Form

Invalid character found in SAN "{0}" or the SAN value is not a valid format. Multiple Subject Alternative Names should be entered in a separate line with a new line as a delimiter. Wildcard characters are not allowed.

Short Form

No short form is provided for this message type

Description

None

Message ID : KMG1782E

Severity

Error

Long Form

Invalid Subject Alternative format provided in the SAN "{0}". It should be in the format: ":". Allowed types can be EMAIL, URI, DNS, IP, or OID.

Short Form

No short form is provided for this message type

Description

None

Message ID : KMG1849E

Severity

Error

Long Form

The key "{0}" cannot be modified as it is in the DESTROYED state.

Short Form

No short form is provided for this message type

Description

None

Message ID : KMG1850E

Severity

Error

Long Form

The key "{0}" cannot be purged as it is not in the DESTROYED state.

Short Form

No short form is provided for this message type

Description

None

Message ID : KMG1868E

Severity

Error

Message ID : KMG1849E

Long Form

The expiration date cannot be today.

Short Form

No short form is provided for this message type

Description

None

Logger KMG: Information

Message ID : KMG0547I

Severity

Information

Long Form

Bad input. Expecting hex string.

Short Form

No short form is provided for this message type

Description

None

Message ID : KMG0610I

Severity

Information

Long Form

Administrator "{0}" exported {1} agent keys to a file with sha256={2} and size={3} bytes, containing the following keys: {4}

Short Form

exported agent

Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
dlen	out	Numeric	Output byte count or length
keys	vds_keys	Text	List of key names

Description

None

Message ID : KMG0611I

Severity

Information

Message ID : KMG0610I

1394

Long Form

Administrator "{0}" imported the following {1} symmetric key(s): {2} and following {3} asymmetric key(s): {4}

Short Form

admin imported symmetric keys

Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
keys	vds_keys	Text	List of key names

Description

None

Message ID : KMG0761I

Severity

Information

Long Form

The RSA key pair used for encryption/decryption has been expired on {0}.

Short Form

rsa key pair expired

Parameters

Label	CEF Label	Type	Usage
etime	end	Text	An end time stamp

Description

None

Message ID : KMG1220I

Severity

Information

Long Form

Please [login to DSM server](#) to view the "Keys" report for detail.

Message ID : KMG0761I

Short Form

No short form is provided for this message type

Description

None

Message ID : KMG1221I

Severity

Information

Long Form

Please [login to DSM server](#) to view the "Keys" report for detail.

Short Form

No short form is provided for this message type

Description

None

Message ID : KMG1361I**Severity**

Information

Long Form

Agent key "{0}" has expired today.

Short Form

No short form is provided for this message type

Description

None

Message ID : KMG1362I**Severity**

Information

Message ID : KMG1221I

Long Form

Vault key "{0}" has expired today.

Short Form

No short form is provided for this message type

Description

None

Message ID : KMG1381I

Severity

Information

Long Form

Key [Name: {0}, Description: {1}] versioned successfully.

Short Form

No short form is provided for this message type

Description

None

Message ID : KMG1386I

Severity

Information

Long Form

Administrator "{0}" successfully versioned key [Name: {1}, Description: {2}].

Short Form

No short form is provided for this message type

Description

None

Message ID : KMG1543I

Severity

Information

Message ID : KMG1381I

Long Form

{0} at "{1}" created Opaque Object {2} with uuid {3}.

Short Form

No short form is provided for this message type

Description

None

Message ID : KMG1645I

Severity

Information

Long Form

KMIP key with name "{0}" and UUID "{1}" created

Short Form

No short form is provided for this message type

Description

None

Message ID : KMG1646I

Severity

Information

Long Form

KMIP key of UUID "{0}" deleted

Short Form

No short form is provided for this message type

Description

None

Logger KMG: Warnings

Message ID : KMG0596W

Severity

Warning

Long Form

Key needed to unwrap package not found. Please import appropriate wrapper key and try again.

Short Form

No short form is provided for this message type

Description

None

Message ID : KMG0774W

Severity

Warning

Long Form

Wrapper Key needed to proceed is not found. Please import wrapper key with identifier {0}.

Short Form

No short form is provided for this message type

Description

None

Message ID : KMG1200W

Severity

Warning

Long Form

{0} agent keys will expire {2} {1} days.

Short Form

agent keys will expire

Parameters

No parameters are provided for this message type

Description

Agent keys will expire soon. Rekey using dataxform.

Message ID : KMG1201W

Severity

Warning

Long Form

{0} agent key will expire {2} {1} days.

Short Form

agent key will expire

Parameters

Label	CEF Label	Type	Usage
key	cs3	Text	Name of key or key pair

Message ID : KMG1200W

Description

An agent key will expire soon. Rekey using dataxform.

Message ID : KMG1202W

Severity

Warning

Long Form

{0} vault keys will expire {2} {1} days.

Short Form

vault keys will expire

Parameters

No parameters are provided for this message type

Description

Vault keys will expire soon. Renew key soon.

Message ID : KMG1203W

Severity

Warning

Long Form

{0} vault key will expire {2} {1} days.

Short Form

vault key will expire

Parameters

Label	CEF Label	Type	Usage
key	cs3	Text	Name of key or key pair

Description

A vault key will expire soon. Renew key soon.

Message ID : KMG1210W

Severity

Warning

Long Form

{0} agent keys have been expired for {1} days.

Short Form

agent keys expired

Parameters

No parameters are provided for this message type

Description

Agent keys have expired. Rekey using dataxform.

Message ID : KMG1211W

Severity

Warning

Long Form

{0} agent key has been expired for {1} days.

Short Form

agent key expired

Parameters

Label	CEF Label	Type	Usage
key	cs3	Text	Name of key or key pair

Description

An agent key has expired. Renew key soon

Message ID : KMG1212W

Severity

Warning

Long Form

{0} vault keys have been expired for {1} days.

Message ID : KMG1211W

Short Form

vault keys expired

Parameters

No parameters are provided for this message type

Description

None

Message ID : KMG1213W

Severity

Warning

Long Form

{0} vault key has been expired for {1} days.

Short Form

vault key expired

Parameters

Label	CEF Label	Type	Usage
key	cs3	Text	Name of key or key pair

Description

A vault key has expired. Renew key soon

Message ID : KMG1295W

Severity

Warning

Long Form

The key vault feature is disabled in the license.

Short Form

No short form is provided for this message type

Description

None

Message ID : KMG1213W

Message ID : KMG1300W

Severity

Warning

Long Form

No such wrapper key.

Short Form

No short form is provided for this message type

Description

None

Message ID : KMG1512W

Severity

Warning

Long Form

Certificate "{0}" will expire on "{1}".

Short Form

No short form is provided for this message type

Description

None

Logger LIC: Errors

Message ID : LIC0276E

Severity

Error

Long Form

Error while setting client option for Vendor id {0} and Nodelock file {1}.

Short Form

No short form is provided for this message type

Description

None

Message ID : LIC0277E

Severity

Error

Long Form

Error while initializing License Use Management with license transaction status {0}

Short Form

No short form is provided for this message type

Description

None

Message ID : LIC0278E

Severity

Error

Long Form

The Security Server was unable to find a proper nodelock license file for this installation. The Security Server will now shutdown. This can occur if the nodelock file has been removed or manually modified. Restore the original nodelock file and restart the Security Server.

Short Form

No short form is provided for this message type

Message ID : LIC0277E

Description

None

Message ID : LIC0279E

Severity

Error

Long Form

An internal error occurred on the Security Server. Refer to cgss.log and server.log for details. Call support if necessary.

Short Form

No short form is provided for this message type

Description

None

Message ID : LIC0580E

Severity

Error

Message ID : LIC0278E

Long Form

Invalid license signature. {0}

Short Form

No short form is provided for this message type

Description

None

Message ID : LIC0581E

Severity

Error

Long Form

License not found.

Short Form

No short form is provided for this message type

Message ID : LIC0580E

Description

None

Message ID : LIC0582E**Severity**

Error

Long Form

Operation exceeds limits of current license.

Short Form

No short form is provided for this message type

Description

None

Message ID : LIC0586E**Severity**

Error

Message ID : LIC0581E

Long Form

License has expired.

Short Form

license expired

Parameters

No parameters are provided for this message type

Description

None

Message ID : LIC1160E

Severity

Error

Long Form

The term license for {0} agent in domain {1} has expired

Short Form

domain license expired

Parameters

Label	CEF Label	Type	Usage
lType	vds_lType	Text	A license type
agent	deviceProcessName	Text	The short identifier of the agent software

Description

None

Message ID : LIC1161E

Severity

Error

Long Form

The number of registered {0} agents with {1} license on this server has reached the license limit {2}.

Message ID : LIC1160E

1420

Short Form

No short form is provided for this message type

Description

License reallocation or upgrade recommended.

Message ID : LIC1162E

Severity

Error

Long Form

The number of registered {0} agents with {1} license in domain {2} on this server has reached the license limit {3}.

Short Form

No short form is provided for this message type

Description

None

Message ID : LIC1163E

Severity

Error

Long Form

The required {0} license for {1} agent is not installed

Short Form

No short form is provided for this message type

Description

None

Message ID : LIC1164E

Severity

Error

Long Form

The required {0} license for {1} agent is not installed in domain {2}

Message ID : LIC1163E

Short Form

No short form is provided for this message type

Description

None

Message ID : LIC1165E

Severity

Error

Long Form

The available {0} license quota for the {1} agent is insufficient

Short Form

No short form is provided for this message type

Description

None

Message ID : LIC1166E

Severity

Error

Long Form

The license expiration date for {0} agent is invalid

Short Form

No short form is provided for this message type

Description

None

Message ID : LIC1167E

Severity

Error

Long Form

The license quota {0} for {1} agent is invalid

Message ID : LIC1166E

Short Form

No short form is provided for this message type

Description

None

Message ID : LIC1261E

Severity

Error

Long Form

The number of available CPU cores for the {0} agents with {1} license is {2}, which is NOT enough for the number of registering host's CPU cores {3}.

Short Form

No short form is provided for this message type

Description

None

Message ID : LIC1167E

1425

Message ID : LIC1291E

Severity

Error

Long Form

The term license for {0} agent has expired.

Short Form

No short form is provided for this message type

Description

None

Message ID : LIC1292E

Severity

Error

Long Form

The CPU core hour usage of {0} agents with {1} license on this server has reached the license limit {2}.

Short Form

No short form is provided for this message type

Description

None

Message ID : LIC1293E

Severity

Error

Long Form

The CPU core hour usage of {0} agents with {1} license in domain {2} on this server has reached the license limit {3}.

Short Form

No short form is provided for this message type

Description

None

Message ID : LIC1292E

Message ID : LIC1298E

Severity

Error

Long Form

A KMIP enabled license cannot be installed while user domains exist.

Short Form

No short form is provided for this message type

Description

None

Message ID : LIC1324E

Severity

Error

Long Form

LDT license not found.

Short Form

No short form is provided for this message type

Description

None

Message ID : LIC1325E

Severity

Error

Long Form

The number of registered agents {0} with LDT license on this server has reached the license limit {1}.

Short Form

No short form is provided for this message type

Description

None

Message ID : LIC1324E

Message ID : LIC1326E

Severity

Error

Long Form

Docker license not found.

Short Form

No short form is provided for this message type

Description

None

Message ID : LIC1327E

Severity

Error

Long Form

The number of registered agents {0} with Docker license on this server has reached the license limit {1}.

Message ID : LIC1326E

Short Form

No short form is provided for this message type

Description

None

Message ID : LIC1621E

Severity

Error

Long Form

Key rotation feature is not licensed. DSM requires either VAE or LDT license to allow key rotation operation.

Short Form

No short form is provided for this message type

Description

None

Message ID : LIC1327E

Message ID : LIC1690E

Severity

Error

Long Form

FF1 license not found.

Short Form

No short form is provided for this message type

Description

None

Message ID : LIC1691E

Severity

Error

Long Form

The number of registered agents {0} with FF1 license on this server has reached the license limit {1}.

Message ID : LIC1690E

Short Form

No short form is provided for this message type

Description

None

Message ID : LIC1736E

Severity

Error

Long Form

Efficient Storage license not found.

Short Form

No short form is provided for this message type

Description

None

Message ID : LIC1691E

Message ID : LIC1737E

Severity

Error

Long Form

The number of registered agents {0} with Efficient Storage licenses on this server has reached the license limit {1}.LUP0113E=The security server failed to initialize its configuration. The server will not function correctly. Please restart the system. If the problem persists, contact support.

Short Form

No short form is provided for this message type

Description

None

Logger LIC: Information

Message ID : LIC0587I

Severity

Information

Long Form

Administrator {0} successfully installed license.

Short Form

installed license ok

Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name

Description

None

Logger LIC: Warnings

Message ID : LIC1323W

Severity

Warning

Long Form

RA license cannot be installed on a DSM in SuiteB mode.

Short Form

No short form is provided for this message type

Description

None

Logger LOG: Errors

Message ID : LOG0138E

Severity

Error

Long Form

The Security Server failed to retrieve audit logs from the database. Verify that the database is functional and retry the operation.

Short Form

failed to retrieve audit logs from database

Parameters

No parameters are provided for this message type

Description

None

Message ID : LOG0139E

Severity

Error

Long Form

The Security Server failed to purge the debug messages from the database. Verify that the database is functional and retry the operation.

Short Form

failed to purge debug messages from database

Parameters

No parameters are provided for this message type

Description

None

Message ID : LOG0287E

Severity

Error

Long Form

The Security Server failed to retrieve the number of denied backup and restore operations because of internal error. Please try it again.

Short Form

No short form is provided for this message type

Description

None

Logger LOG: Information

Message ID : LOG0140I

Severity

Information

Long Form

Administrator "{0}" has exported {1} log messages.

Short Form

exported log messages

Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name

Description

None

Message ID : LOG0141I

Severity

Information

Long Form

The Security Server has pruned and exported {0} log messages into file "{1}". These log messages have been deleted from the Security Server.

Short Form

server has pruned and exported log messages into file

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : LOG0541I

Severity

Information

Long Form

Administrator "{0}" has deleted {1} log messages.

Short Form

deleted log messages

Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name

Description

None

Message ID : LOG0669I

Severity

Information

Message ID : LOG0541I

Long Form

Route to syslog server UP: {0} ({1})

Short Form

route to syslog server UP

Parameters

Label	CEF Label	Type	Usage
port	spt	Numeric	A socket port number

Description

None

Logger LOG: Warnings

Message ID : LOG0668W

Severity

Warning

Long Form

Route to syslog server DOWN: {0} ({1}) ({2})

Short Form

route to syslog server DOWN

Parameters

Label	CEF Label	Type	Usage
port	spt	Numeric	A socket port number
showStr	reason	Text	Code specifying reason for allowing access, if any

Description

None

Message ID : LOG1318W

Severity

Warning

Long Form

Syslog message back logged: {0} ({1}) ({2})

Short Form

syslog message back logged

Parameters

Label	CEF Label	Type	Usage
port	spt	Numeric	A socket port number
showStr	reason	Text	Code specifying reason for allowing access, if any

Description

None

Logger LUP: Errors

Message ID : LUP0114E

Severity

Error

Long Form

The security server failed to initialize the system to process messages from hosts. This is caused by an internal error or an incorrect server configuration. Please restart your system. If the problem persists, contact support.

Short Form

failed to initialize system

Parameters

No parameters are provided for this message type

Description

None

Message ID : LUP0117E

Severity

Error

Long Form

The security server failed to parse the log file from a host. The file had an invalid format and has been moved to the .../auditlog/badlogs directory. The messages in the file will not be saved to database. The server will continue to log files from the host.

Short Form

failed to parse log file

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : LUP0118E

Severity

Error

Long Form

The security server received a host log file with an incorrect timestamp format while processing an uploaded log file from a host. The timestamp on the document received was {0}. The log file will not be saved to the database.

Short Form

No short form is provided for this message type

Description

None

Message ID : LUP0119E

Severity

Error

Long Form

The security server failed to convert the message time stamp or the arguments were incorrect, while processing the message from host. The message: "{0}, {1}, {2}, {3}" will be not be saved.

Short Form

failed to parse log message

Parameters

Label	CEF Label	Type	Usage
showStr	reason	Text	Code specifying reason for allowing access, if any

Description

None

Message ID : LUP0120E

Severity

Error

Long Form

The security server failed to convert the time zone offset while processing the message from host. The message: "{0}, {1}, {2},

Message ID : LUP0119E

1449

{3}" will be not be saved.

Short Form

bad time zone

Parameters

Label	CEF Label	Type	Usage
showStr	reason	Text	Code specifying reason for allowing access, if any

Description

None

Message ID : LUP0121E

Severity

Error

Long Form

The security server could not find the message id in the message resource for the Agent. The message: "{0}, {1}, {2}, {3}" will not be saved. Please update the message resource file for the Agent.

Short Form

unknown message id

Parameters

Label	CEF Label	Type	Usage
showStr	reason	Text	Code specifying reason for allowing access, if any

Description

None

Message ID : LUP0122E

Severity

Error

Long Form

The security server failed to open the message resource file {0} for the Agent. Check if the message resource file is missing. The server will not be able to process logs uploaded from the Agent.

Short Form

failed to open resource file

Message ID : LUP0121E

1451

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : LUP0123E

Severity

Error

Long Form

The security server failed to process the message : "{0}, {1}, {2}, {3}" from a host. The format of the message is invalid. The message will not be saved.

Short Form

invalid message format

Parameters

Label	CEF Label	Type	Usage
-------	-----------	------	-------

Message ID : LUP0122E

showStr	reason	Text	Code specifying reason for allowing access, if any
---------	--------	------	--

Description

None

Message ID : LUP0128E

Severity

Error

Long Form

The security server encountered a message with an incorrect timestamp format while processing the message. The timestamp received was {0}. The message will not be saved to the database.

Short Form

message with incorrect timestamp

Parameters

Label	CEF Label	Type	Usage
showStr	reason	Text	Code specifying reason for allowing access, if any

Description

None

Message ID : LUP0131E

Severity

Error

Long Form

The security server has an internal error. The server will not be able to process uploaded log files. Please restart your server. If the problem persists, contact support.

Short Form

internal error

Parameters

No parameters are provided for this message type

Description

None

Message ID : LUP0128E

1454

Message ID : LUP0132E

Severity

Error

Long Form

The security server cannot find the uploaded log file {0} for processing. Messages in this file will not be saved. If the problem persists, please contact support.

Short Form

cannot find log file

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : LUP0133E

Severity

Error

Long Form

The security Server failed to open the uploaded log file {0} for processing. Messages in this file will not be saved. If the problem persists, please contact support.

Short Form

cannot open log file

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : LUP0134E

Severity

Error

Message ID : LUP0133E

Long Form

The security server could not initialize the message queue {0} for handling messages from Agents. This could be caused by an internal error or if the server's configuration was changed manually. The Server will not process log files uploaded from Agents. Please contact support.

Short Form

cannot initialize message queue

Parameters

Label	CEF Label	Type	Usage
queue	vds_queue	Text	A message queue identifier

Description

None

Message ID : LUP0135E

Severity

Error

Long Form

The security server encountered an error while clearing a message queue. Ignore the messages that complains not found files. The server will continue to process uploaded log files correctly.

Short Form

cannot clear message queue

Parameters

No parameters are provided for this message type

Description

None

Message ID : LUP0136E

Severity

Error

Long Form

The security server failed to queue unprocessed message files for processing. These message files will not be saved to the database. If the problem persists, contact support.

Short Form

No short form is provided for this message type

Description

None

Message ID : LUP0299E

Severity

Error

Long Form

The security server failed to save the messages from a host. Please check your database. This message file will be processed when the server is restarted.

Short Form

failed to save host messages

Parameters

No parameters are provided for this message type

Description

None

Logger LUP: Fatal errors

Message ID : LUP0124F

Severity

Fatal error

Long Form

The security server's Logging system is unable to connect to the database to save messages. The logging system will sleep {0} seconds and retry the operation.

Short Form

Logging system unable to connect to database

Parameters

No parameters are provided for this message type

Description

None

Message ID : LUP0126F

Severity

Fatal error

Long Form

An internal error occurred while the Security Server reinitialized the message system to process messages from hosts. Please restart the server. If the problem persists, contact support.

Short Form

internal error

Parameters

No parameters are provided for this message type

Description

None

Message ID : LUP0127F

Severity

Fatal error

Long Form

The security server failed to queue the message file {0} for processing. Some messages may be lost. If the problem persists, contact support.

Short Form

failed to queue message file

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : LUP0129F

Severity

Fatal error

Message ID : LUP0127F

Long Form

The security server has an internal error. The server will not be able to process uploaded log files. Please restart your server. If the problem persists, contact support.

Short Form

internal error

Parameters

No parameters are provided for this message type

Description

None

Message ID : LUP0130F

Severity

Fatal error

Long Form

The security server has an internal error. The server will not be able to handle uploaded log files. Please restart your server. If the problem persists, contact support.

Message ID : LUP0129F

1464

Short Form

internal error

Parameters

No parameters are provided for this message type

Description

None

Message ID : LUP0137F

Severity

Fatal error

Long Form

The security server received a log file upload request that contain an incorrect header. The server will ignore the upload request. If the problem persists, contact support.

Short Form

incorrect header in log file upload request

Parameters

No parameters are provided for this message type

Description

None

Logger LUP: Information

Message ID : LUP0115I

Severity

Information

Long Form

The uploaded log file has been processed successfully.

Short Form

No short form is provided for this message type

Description

None

Message ID : LUP0116I

Severity

Information

Long Form

The security server has successfully initialized the logging system to log messages from hosts. The server can now log messages from hosts.

Short Form

initialized logging system

Parameters

No parameters are provided for this message type

Description

None

Message ID : LUP0125I

Severity

Information

Long Form

The message file {0} has been sent for processing.

Message ID : LUP0116I

1468

Short Form

message file submitted

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : LUP0428I

Severity

Information

Long Form

The log file received atfter host "{0}" was deleted.

Short Form

No short form is provided for this message type

Message ID : LUP0125I

Description

None

Logger PLC: Errors

Message ID : PLC0179E

Severity

Error

Long Form

A policy with name "{0}" already exists in domain "{1}". Please specify a different name.

Short Form

No short form is provided for this message type

Description

None

Message ID : PLC0180E

Severity

Error

Long Form

Online Policy with name "{0}" does not exist.

Short Form

No short form is provided for this message type

Description

None

Message ID : PLC0183E

Severity

Error

Long Form

Action Set name "{0}" is already in use in the domain. Please specify a different name.

Short Form

No short form is provided for this message type

Description

None

Message ID : PLC0184E**Severity**

Error

Long Form

Process Set with name "{0}" already exists in domain "{1}". Please specify a different name.

Short Form

No short form is provided for this message type

Description

None

Message ID : PLC0185E**Severity**

Error

Message ID : PLC0183E

Long Form

Resource Set with name "{0}" already exists in domain "{1}". Please specify a different name.

Short Form

No short form is provided for this message type

Description

None

Message ID : PLC0186E

Severity

Error

Long Form

Time Set with name "{0}" already exists in domain "{1}". Please specify a different name.

Short Form

No short form is provided for this message type

Description

None

Message ID : PLC0187E

Severity

Error

Long Form

User Set with name "{0}" already exists in domain "{1}". Please specify a different name.

Short Form

No short form is provided for this message type

Description

None

Message ID : PLC0188E

Severity

Error

Message ID : PLC0186E

Long Form

Name "{0}" is too long.

Short Form

No short form is provided for this message type

Description

None

Message ID : PLC0189E

Severity

Error

Long Form

Offline Policy with name "{0}" no longer exists.

Short Form

No short form is provided for this message type

Description

None

Message ID : PLC0190E

Severity

Error

Long Form

No applicable policy can be found for the target.

Short Form

No short form is provided for this message type

Description

None

Message ID : PLC0191E

Severity

Error

Message ID : PLC0189E

Long Form

Symmetric Key "{0}" does not exist in the database.

Short Form

No short form is provided for this message type

Description

None

Message ID : PLC0192E

Severity

Error

Long Form

Action Set "{0}" does not exist in the database.

Short Form

No short form is provided for this message type

Description

None

Message ID : PLC0193E

Severity

Error

Long Form

Process Set "{0}" does not exist in the database.

Short Form

No short form is provided for this message type

Description

None

Message ID : PLC0194E

Severity

Error

Message ID : PLC0192E

Long Form

Resource Set "{0}" does not exist in the database.

Short Form

No short form is provided for this message type

Description

None

Message ID : PLC0195E

Severity

Error

Long Form

Time Set "{0}" does not exist in the database.

Short Form

No short form is provided for this message type

Description

None

Message ID : PLC0196E

Severity

Error

Long Form

User Set "{0}" does not exist in the database.

Short Form

No short form is provided for this message type

Description

None

Message ID : PLC0288E

Severity

Error

Message ID : PLC0195E

Long Form

The rule name "{0}" is already in use. Specify a different name.

Short Form

No short form is provided for this message type

Description

None

Message ID : PLC0302E

Severity

Error

Long Form

The Security Server could not delete policy "{0}". Hosts or host groups are guarded by the policy.

Short Form

No short form is provided for this message type

Description

None

Message ID : PLC0548E

Severity

Error

Long Form

Policy "{0}" cannot be imported. The XML contains a tag which is no longer supported.

Short Form

No short form is provided for this message type

Description

None

Message ID : PLC0604E

Severity

Error

Message ID : PLC0302E

Long Form

Signature Set "{0}" does not exist in the database.

Short Form

No short form is provided for this message type

Description

None

Message ID : PLC0764E

Severity

Error

Long Form

The policy {0} xml body cannot be empty. Please correct the problem and try again.

Short Form

No short form is provided for this message type

Description

None

Message ID : PLC0806E

Severity

Error

Long Form

The key in policy {0} does not exist in domain.

Short Form

No short form is provided for this message type

Description

None

Message ID : PLC1301E

Severity

Error

Message ID : PLC0764E

Long Form

Policy name cannot be empty.

Short Form

No short form is provided for this message type

Description

None

Message ID : PLC1302E

Severity

Error

Long Form

Process Set "{0}" cannot be deleted because it is referenced in at least one policy.

Short Form

No short form is provided for this message type

Message ID : PLC1301E

Description

None

Message ID : PLC1303E

Severity

Error

Long Form

Resource Set "{0}" cannot be deleted because it is referenced in at least one policy.

Short Form

No short form is provided for this message type

Description

None

Message ID : PLC1304E

Severity

Error

Message ID : PLC1302E

Long Form

Time Set "{0}" cannot be deleted because it is referenced in at least one policy.

Short Form

No short form is provided for this message type

Description

None

Message ID : PLC1305E

Severity

Error

Long Form

User Set "{0}" cannot be deleted because it is referenced in at least one policy.

Short Form

No short form is provided for this message type

Description

None

Message ID : PLC1306E

Severity

Error

Long Form

Invalid Policy Schema Version. Allowed values are 0 or 1.

Short Form

No short form is provided for this message type

Description

None

Message ID : PLC1309E

Severity

Error

Message ID : PLC1305E

Long Form

Apply key in security rule has not been covered by any key rule.

Short Form

No short form is provided for this message type

Description

None

Message ID : PLC1313E

Severity

Error

Long Form

Key Selection Rules #{0} are being applied to the same Resource.

Short Form

No short form is provided for this message type

Description

None

Message ID : PLC1316E

Severity

Error

Long Form

You must specify a valid policy name. (It must be in alpha-numeric characters with a maximum length of 64. It cannot begin with a digit or contain spaces, '*' or '!'.)

Short Form

No short form is provided for this message type

Description

None

Message ID : PLC1317E

Severity

Error

Long Form

Data Transformation Rules #{0} are being applied to the same Resource.

Short Form

No short form is provided for this message type

Description

None

Message ID : PLC1320E

Severity

Error

Long Form

Policy with Id "{0}" does not exist in the database.

Message ID : PLC1317E

Short Form

No short form is provided for this message type

Description

None

Message ID : PLC1321E

Severity

Error

Long Form

Policy with Id "{0}" and version "{1}" does not exist in the database.

Short Form

No short form is provided for this message type

Description

None

Message ID : PLC1500E

Severity

Error

Long Form

LDT Policy {0} cannot be associated with LDT disabled host {1}

Short Form

No short form is provided for this message type

Description

None

Message ID : PLC1501E

Severity

Error

Long Form

Versioned key {0} cannot be used in a Standard policy {1}.

Short Form

No short form is provided for this message type

Description

None

Message ID : PLC1502E

Severity

Error

Long Form

Versioned key {0} cannot be used as Current_Key in a Live Data Transformation policy {1}.

Short Form

No short form is provided for this message type

Description

None

Message ID : PLC1501E

Message ID : PLC1503E

Severity

Error

Long Form

Non-Versioned key {0} cannot be used as Next_Key in a Live Data Transformation policy {1}.

Short Form

No short form is provided for this message type

Description

None

Message ID : PLC1505E

Severity

Error

Long Form

Required set {0} ({1}) for policy {2} not found.

Short Form

No short form is provided for this message type

Description

None

Message ID : PLC1506E

Severity

Error

Long Form

Policy {0} cannot be saved, with missing keys: {1}, missing sets: {2}, and or other validation errors: {3}.

Short Form

No short form is provided for this message type

Description

None

Message ID : PLC1505E

Message ID : PLC1507E

Severity

Error

Long Form

Host "{0}" does not support the CBC_CS1 encryption mode, you cannot create a GuardPoint with a Policy "{1}" that contains a key that uses this encryption mode.

Short Form

No short form is provided for this message type

Description

None

Message ID : PLC1508E

Severity

Error

Long Form

Not all the registered Hosts in Host Group "{0}" support the CBC_CS1 encryption mode, you cannot create a GuardPoint with a Policy "{1}" that contains a key that uses this encryption mode.

Short Form

No short form is provided for this message type

Description

None

Message ID : PLC1509E

Severity

Error

Long Form

Raw or Block Device (Manual and Auto Guard) guardpoints are incompatible with Policy "{0}" that contains a key that uses the CBC_CS1 encryption mode.

Short Form

No short form is provided for this message type

Message ID : PLC1508E

1499

Description

None

Message ID : PLC1512E

Severity

Error

Long Form

LDT Policy {0} cannot contain a security rule that is missing the "Apply key" effect.

Short Form

No short form is provided for this message type

Description

None

Message ID : PLC1515E

Severity

Error

Message ID : PLC1509E

Long Form

LDT Policy {0} must have at least one non-exclusion key rule.

Short Form

No short form is provided for this message type

Description

None

Message ID : PLC1516E

Severity

Error

Long Form

Cloud Object Storage Policy {0} can only contain one key rule.

Short Form

No short form is provided for this message type

Description

None

Message ID : PLC1517E

Severity

Error

Long Form

Cloud Object Storage Policy {0} must have at least one CBC-CS1 key rule.

Short Form

No short form is provided for this message type

Description

None

Message ID : PLC1518E

Severity

Error

Message ID : PLC1516E

Long Form

Policy type "{0}" is not a valid policy type.

Short Form

No short form is provided for this message type

Description

None

Message ID : PLC1623E

Severity

Error

Long Form

"Raw or Block Device " not supported for LDT Policy {0}

Short Form

No short form is provided for this message type

Description

None

Message ID : PLC1624E

Severity

Error

Long Form

IDT Policy {0} supports only "Raw or Block Device or incorrect IDT setting"

Short Form

No short form is provided for this message type

Description

None

Message ID : PLC1671E

Severity

Error

Message ID : PLC1623E

Long Form

Key Selection Rules cannot contain more than two keys in XTS encryption mode.

Short Form

No short form is provided for this message type

Description

None

Message ID : PLC1672E

Severity

Error

Long Form

Keys in XTS encryption mode in Key Selection Rules cannot apply to non-empty Resource.

Short Form

No short form is provided for this message type

Description

None

Message ID : PLC1673E

Severity

Error

Long Form

Efficient Storage GuardPoint must use a Standard/IDT policy that contains one key. That key must use the {0} encryption mode with KMIP Accessible enabled.

Short Form

No short form is provided for this message type

Description

None

Message ID : PLC1678E

Severity

Error

Long Form

Host "{0}" does not support the {2} encryption mode, you cannot create a GuardPoint with a Policy "{1}" that contains a key that uses this encryption mode.

Short Form

No short form is provided for this message type

Description

None

Message ID : PLC1679E

Severity

Error

Long Form

Not all the registered Hosts in Host Group "{0}" support the {2} encryption mode, you cannot create a GuardPoint with a Policy "{1}" that contains a key that uses this encryption mode.

Message ID : PLC1678E

1507

Short Form

No short form is provided for this message type

Description

None

Message ID : PLC1680E

Severity

Error

Long Form

Raw or Block Device (Manual and Auto Guard) GuardPoints are incompatible with Policy "{0}" that contains a key with {1} encryption mode.

Short Form

No short form is provided for this message type

Description

None

Message ID : PLC1679E

Message ID : PLC1681E

Severity

Error

Long Form

A policy that contains a key that uses the XTS encryption mode is applicable only for Efficient Storage and In-place Data Transformation - Device GuardPoints.

Short Form

No short form is provided for this message type

Description

None

Message ID : PLC1682E

Severity

Error

Long Form

Directory Device (Manual and Auto Guard) guardpoints are incompatible with Policy "{0}" that contains a key with {1} encryption mode.

Short Form

No short form is provided for this message type

Description

None

Message ID : PLC1688E

Severity

Error

Long Form

Current key and Transformation key are not identical They must be the same and Resource set is mandatory for an exclusion rule in LDT-enabled policy.

Short Form

No short form is provided for this message type

Message ID : PLC1682E

1510

Description

None

Message ID : PLC1704E

Severity

Error

Long Form

All FS agents in this group must be version 6.2.0 or higher to support selected LDT policy with exclusion key rule. Please perform an upgrade of FS agent to 6.2.0 or later.

Short Form

No short form is provided for this message type

Description

None

Message ID : PLC1719E

Severity

Error

Long Form

Cannot create a Cloud Object Storage guardpoint because HostGroup "{0}" has incompatible existing host members.

Short Form

No short form is provided for this message type

Description

None

Message ID : PLC1743E

Severity

Error

Long Form

FS (VTE) agent must be version 6.2.0 or higher to support selected LDT policy with exclusion key rule. Perform an upgrade of FS (VTE) agent to 6.2.0 or later.

Message ID : PLC1719E

1512

Short Form

No short form is provided for this message type

Description

None

Message ID : PLC1751E

Severity

Error

Long Form

GuardPoint with both Efficient-Storage and In-place data transformation - Device is not allowed.

Short Form

No short form is provided for this message type

Description

None

Message ID : PLC1743E

Message ID : PLC1752E

Severity

Error

Long Form

Current Key and New Key cannot be identical in Key Selection Rules of IDT policy.

Short Form

No short form is provided for this message type

Description

None

Message ID : PLC1753E

Severity

Error

Long Form

The Current Key after key rule transition should match the New Key before the transition.

Short Form

No short form is provided for this message type

Description

None

Message ID : PLC1754E

Severity

Error

Long Form

Current Key should be associated with a resource. The New Key, in an IDT policy, should not be associated with a resource.

Short Form

No short form is provided for this message type

Description

None

Message ID : PLC1753E

Message ID : PLC1755E

Severity

Error

Long Form

IDT policy should have two keys.

Short Form

No short form is provided for this message type

Description

None

Message ID : PLC1756E

Severity

Error

Long Form

IDT policy only allows "read" "write" "all_ops" actions in security rules.

Short Form

No short form is provided for this message type

Description

None

Message ID : PLC1757E

Severity

Error

Long Form

Learn Mode is not allowed for IDT policy.

Short Form

No short form is provided for this message type

Description

None

Message ID : PLC1756E

Message ID : PLC1779E

Severity

Error

Long Form

IDT Policy "{0}" for "{1}" cannot contain a "clear_key" and can only contain an XTS key.

Short Form

No short form is provided for this message type

Description

None

Message ID : PLC1780E

Severity

Error

Long Form

IDT Policy "{0}" for "{1}" can only contain either a "clear_key" or an XTS key.

Short Form

No short form is provided for this message type

Description

None

Message ID : PLC1781E

Severity

Error

Long Form

Cloud Object Storage Policy "{0}" only allows "READ_FILE", "WRITE_FILE", "REMOVE_FILE", "READ_DIRECTORY" and "ALL_OPERATIONS" actions in security rules.

Short Form

No short form is provided for this message type

Description

None

Message ID : PLC1780E

Message ID : PLC1783E

Severity

Error

Long Form

Key operations (key_op) in security rule have not been covered by key selection rule and data transformation rule.

Short Form

No short form is provided for this message type

Description

None

Message ID : PLC1785E

Severity

Error

Long Form

Policy "{0}" must have at least one data transformation key rule when key_op action is selected in security rule.

Short Form

No short form is provided for this message type

Description

None

Message ID : PLC1786E

Severity

Error

Long Form

Policy "{0}" must have at least one backup key rule when "Apply Backup Key" effect is selected in security rule.

Short Form

No short form is provided for this message type

Description

None

Message ID : PLC1787E

Severity

Error

Long Form

Efficient Encrypted Backup Capability is not enabled. Policy with "Apply Backup Key" effect in security rule is not supported.

Short Form

No short form is provided for this message type

Description

None

Message ID : PLC1788E

Severity

Error

Long Form

Policy with "Apply Backup Key" effect in security rule is compatible only with Directory Device (Manual and Auto Guard) guardpoints.

Message ID : PLC1787E

Short Form

No short form is provided for this message type

Description

None

Message ID : PLC1789E

Severity

Error

Long Form

Policy with "Apply Backup Key" effect in security rule is compatible only with Standard policy type.POL0142I_CEF=shost={0}

Short Form

No short form is provided for this message type

Description

None

Message ID : PLC1788E

Message ID : PLC1820E

Severity

Error

Long Form

Policy with "Apply Backup Key" effect in security rule is not supported.

Short Form

No short form is provided for this message type

Description

None

Logger PLC: Information

Message ID : PLC1511I

Severity

Information

Long Form

User "{0}" exported policy "{1}"

Short Form

exported policy

Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name

Description

None

Message ID : PLC1513I

Severity

Information

Long Form

{0} in the path and in the object(id) do not match

Short Form

No short form is provided for this message type

Description

None

Message ID : PLC1514I

Severity

Information

Long Form

Policy in the path and in the object(id) do not match

Short Form

No short form is provided for this message type

Description

None

Logger PLC: Warnings

Message ID : PLC0181W

Severity

Warning

Long Form

Some Action Sets, Process Sets, Resource Sets, Time Sets and/or User Sets have been updated by other processes.

Short Form

No short form is provided for this message type

Description

None

Message ID : PLC0182W

Severity

Warning

Long Form

Policy "{0}" has been updated by other processes.

Short Form

No short form is provided for this message type

Description

None

Message ID : PLC1318W

Severity

Warning

Long Form

Learn mode is enabled.

Short Form

No short form is provided for this message type

Description

None

Message ID : PLC1319W

Severity

Warning

Long Form

A "Permit" effect is not accompanied by an "Apply key" effect in the security rule. Use of that rule will NOT encrypt/decrypt the data.

Short Form

No short form is provided for this message type

Description

None

Message ID : PLC1369W

Severity

Warning

Long Form

The new security rule #{0} has been added, but the security rule #{1} has same object sets as security rule #{2} with similar effect. The security rule #{3} may not take effect. Please review security rules carefully before proceeding.

Short Form

No short form is provided for this message type

Description

None

Message ID : PLC1370W

Severity

Warning

Long Form

The security rule #{0} has been updated, but the security rule #{1} has same object sets as security rule #{2} with similar effect. The security rule #{3} may not take effect. Please review security rules carefully before proceeding.

Short Form

No short form is provided for this message type

Description

None

Message ID : PLC1371W

Severity

Warning

Long Form

The new security rule #{0} has been added, but the security rule #{1} has same object sets as security rule #{2} with conflict effect. The security rule #{3} may not take effect. Please review security rules carefully before proceeding.

Short Form

No short form is provided for this message type

Description

None

Message ID : PLC1370W

1532

Message ID : PLC1372W

Severity

Warning

Long Form

The security rule #{0} has been updated, but the security rule #{1} has same object sets as security rule #{2} with conflict effect. The security rule #{3} may not take effect. Please review security rules carefully before proceeding.

Short Form

No short form is provided for this message type

Description

None

Message ID : PLC1373W

Severity

Warning

Long Form

The new security rule #{0} has been added, but the security rule #{1} object sets supersede security rule #{2} object sets. The security rule #{3} may not take effect. Please review security rules carefully before proceeding.

Short Form

No short form is provided for this message type

Description

None

Message ID : PLC1374W

Severity

Warning

Long Form

The security rule #{0} has been updated, but the security rule #{1} object sets supersede security rule #{2} object sets. The security rule #{3} may not take effect. Please review security rules carefully before proceeding.

Short Form

No short form is provided for this message type

Message ID : PLC1373W

1534

Description

None

Logger POL: Errors

Message ID : POL4556E

Severity

Error

Long Form

ACCESS DENIED on request to {0} database {1}, on hostname {2}. Instance name is {3}, partition {4}, catnode {5}. The timestamp is {6}, and the DB2 version is {7}. The request protocol version is {8}.

Short Form

Access denied by policy

Parameters

Label	CEF Label	Type	Usage
act	act	Text	Action being requested or performed
dbname	vds_dbname	Text	Database name
shost	shost	Text	Source host name
dbinstance	vds_dbinstance	Text	Database instance
dbpart	vds_dbpart	Numeric	Database partition

Label	CEF Label	Type	Usage
node	vds_node	Numeric	A node identifier
rt	rt	Text	Time of event
dbver	vds_dbver	Numeric	Database version
version	vds_version	Text	Software version string

Description

None

Message ID : POL4580E

Severity

Error

Long Form

ACCESS DENIED on request to perform {0} for hostname {1}. Server name is {2}, server number {3}, object id {4}. The timestamp is {5}. The request protocol version is {6}.

Short Form

No short form is provided for this message type

Description

None

Message ID : POL4613E

Severity

Error

Long Form

ACCESS DENIED on request to perform {0} for hostname {1}. Server name is {2}, server number {3}. The timestamp is {4}. The request protocol version is {5}.

Short Form

Access denied

Parameters

Label	CEF Label	Type	Usage
act	act	Text	Action being requested or performed
shost	shost	Text	Source host name
dbinstance	vds_dbinstance	Text	Database instance
dbpart	vds_dbpart	Numeric	Database partition

Label	CEF Label	Type	Usage
rt	rt	Text	Time of event
version	vds_version	Text	Software version string

Description

An online policy blocked access. Details of the attempted access are provided in the message fields.

Message ID : POL4701E

Severity

Error

Long Form

Memory allocation failed in [{0}] at line [{1}]

Short Form

Out of memory

Parameters

No parameters are provided for this message type

Description

None

Message ID : POL4704E

Severity

Error

Long Form

EVENT: {0}

Short Form

Event

Parameters

Label	CEF Label	Type	Usage
showStr	reason	Text	Code specifying reason for allowing access, if any

Description

None

Message ID : POL4701E

Logger POL: Fatal errors

Message ID : POL4510F

Severity

Fatal error

Long Form

Fatal error while evaluating policy to {0} database {1}, on hostname {2}. Instance name is {3}, partition {4}, catnode {5}. The timestamp is {6}, and the DB2 version is {7}. The request protocol version is {8}.

Short Form

Policy eval error

Parameters

Label	CEF Label	Type	Usage
act	act	Text	Action being requested or performed
dbname	vds_dbname	Text	Database name
shost	shost	Text	Source host name
dbinstance	vds_dbinstance	Text	Database instance
dbpart	vds_dbpart	Numeric	Database partition

Label	CEF Label	Type	Usage
node	vds_node	Numeric	A node identifier
rt	rt	Text	Time of event
dbver	vds_dbver	Numeric	Database version
version	vds_version	Text	Software version string

Description

None

Message ID : POL4516F

Severity

Fatal error

Long Form

Attribute "{0}" parsing error in policy evaluation request.

Short Form

Req parse error

Parameters

Label	CEF Label	Type	Usage
showStr	reason	Text	Code specifying reason for allowing access, if any

Description

None

Message ID : POL4528F

Severity

Fatal error

Long Form

Attribute "{0}" parsing error in policy evaluation response.

Short Form

Resp parse error

Parameters

Label	CEF Label	Type	Usage
showStr	reason	Text	Code specifying reason for allowing access, if any

Message ID : POL4516F

Label	CEF Label	Type	Usage

Description

None

Message ID : POL4530F

Severity

Fatal error

Long Form

Global restore header invalid. Data corruption has possibly occurred. The restore operation will fail.

Short Form

Global restore header invalid

Parameters

No parameters are provided for this message type

Description

None

Message ID : POL4528F

Message ID : POL4545F

Severity

Fatal error

Long Form

Restore failed: Backup image created with future version.

Short Form

Restore fail - future image

Parameters

No parameters are provided for this message type

Description

None

Message ID : POL4564F

Severity

Fatal error

Long Form

The agent could not allocate enough memory. Contact support.

Short Form

Out of memory

Parameters

No parameters are provided for this message type

Description

None

Message ID : POL4581F

Severity

Fatal error

Long Form

Fatal error while evaluating policy to perform {0} for hostname {1}. Server name is {2}, server number {3}, object id {4}. The timestamp is {5}. The request protocol version is {6}.

Short Form

No short form is provided for this message type

Description

None

Message ID : POL4593F

Severity

Fatal error

Long Form

The agent could not evaluate policy. Contact support.

Short Form

Cannot eval policy

Parameters

No parameters are provided for this message type

Description

None

Message ID : POL4614F

Severity

Fatal error

Long Form

Fatal error while evaluating policy to perform {0} for hostname {1}. Server name is {2}, server number {3}. The timestamp is {4}. The request protocol version is {5}.

Short Form

Policy eval error

Parameters

Label	CEF Label	Type	Usage
act	act	Text	Action being requested or performed
shost	shost	Text	Source host name
dbinstance	vds_dbinstance	Text	Database instance
dbpart	vds_dbpart	Numeric	Database partition

Label	CEF Label	Type	Usage
rt	rt	Text	Time of event
version	vds_version	Text	Software version string

Description

None

Logger POL: Information

Message ID : POL0142I

Severity

Information

Long Form

The Security Server received a request from an unrecognized host ({}). The request will be denied.

Short Form

request from unrecognized host

Parameters

No parameters are provided for this message type

Description

None

Message ID : POL0143I

Severity

Information

Long Form

The Security Server could not find any matching policies for the host ({}). The request will be denied.

Short Form

could not find matching policies for host

Parameters

Label	CEF Label	Type	Usage
shost	shost	Text	Source host name

Description

None

Message ID : POL0144I

Severity

Information

Message ID : POL0143I

Long Form

The Security Server matched policy ({0}) and rule ({1}) for the {2} request from host ({3}), the database instance {4}, alias {5} and partition {6}.

Short Form

matched policy/rule from host

Parameters

Label	CEF Label	Type	Usage
pol	cs1	Text	Policy name
rule	vds_rule	Text	Name of policy rule set
act	act	Text	Action being requested or performed
shost	shost	Text	Source host name
dbinstance	vds_dbinstance	Text	Database instance
dbalias	vds_dbalias	Text	Database alias
dbpart	vds_dbpart	Numeric	Database partition

Description

None

Message ID : POL0145I

Severity

Information

Long Form

The Security Server could not match any policies for the {0} request from host ({1}), the database instance {2}, alias {3} and partition {4}. The request will be denied.

Short Form

request denied

Parameters

Label	CEF Label	Type	Usage
act	act	Text	Action being requested or performed
shost	shost	Text	Source host name
dbinstance	vds_dbinstance	Text	Database instance
dbalias	vds_dbalias	Text	Database alias
dbpart	vds_dbpart	Numeric	Database partition

Description

None

Message ID : POL0146I

Severity

Information

Long Form

The Security Server matched policy ({0}) for the {2} request from host ({3}), database instance {4}, alias {5} and partition {6}. But the policy did not contain any {1} rules. The request will be denied.

Short Form

policy contains no rules

Parameters

Label	CEF Label	Type	Usage
pol	cs1	Text	Policy name
act	act	Text	Action being requested or performed
shost	shost	Text	Source host name
dbinstance	vds_dbinstance	Text	Database instance

Label	CEF Label	Type	Usage
dbalias	vds_dbalias	Text	Database alias
dbpart	vds_dbpart	Numeric	Database partition
rt	rt	Text	Time of event
etime	end	Text	An end time stamp

Description

None

Message ID : POL0147I

Severity

Information

Long Form

The Security Server matched rule ({0}) to the {1} request for host {2}, database instance {3}, alias {4} and partition {5}. But, the request time {6} is after the end time {7} in the Rule. The rule will not be applied.

Short Form

request time after end time

Parameters

Label	CEF Label	Type	Usage
rule	vds_rule	Text	Name of policy rule set
act	act	Text	Action being requested or performed
shost	shost	Text	Source host name
dbinstance	vds_dbinstance	Text	Database instance
dbalias	vds_dbalias	Text	Database alias
dbpart	vds_dbpart	Numeric	Database partition
rt	rt	Text	Time of event
etime	end	Text	An end time stamp

Description

None

Message ID : POL0148I

Severity

Information

Message ID : POL0147I

1556

Long Form

The Security Server matched rule ({0}) to the {1} request for host {2}, database instance {3}, alias {4} and partition {5}. But, the request time {6} is before the start time {7} in the Rule. The rule will not be applied.

Short Form

request time before start time

Parameters

Label	CEF Label	Type	Usage
rule	vds_rule	Text	Name of policy rule set
act	act	Text	Action being requested or performed
shost	shost	Text	Source host name
dbinstance	vds_dbinstance	Text	Database instance
dbalias	vds_dbalias	Text	Database alias
dbpart	vds_dbpart	Numeric	Database partition
rt	rt	Text	Time of event
stime	start	Text	A start time stamp

Description

None

Message ID : POL0149I

Severity

Information

Long Form

The Security Server matched rule ({0}) to the {1} request for host {2}, database instance {3}, alias {4} and partition {5}. But the conditions do not match. The rule will not be applied.

Short Form

conditions do not match

Parameters

Label	CEF Label	Type	Usage
rule	vds_rule	Text	Name of policy rule set
act	act	Text	Action being requested or performed
shost	shost	Text	Source host name
dbinstance	vds_dbinstance	Text	Database instance
dbalias	vds_dbalias	Text	Database alias
dbpart	vds_dbpart	Numeric	Database partition

Description

None

Message ID : POL0150I

Severity

Information

Long Form

The Security Server matched policy ({0}) and rule ({1}) for the {2} request from host ({3}), the server name {4} and Server Number {6}.

Short Form

No short form is provided for this message type

Description

None

Message ID : POL0151I

Severity

Information

Long Form

The Security Server could not match any policies for the {0} request from host ({1}), the server name {2} and Server Number {4}. The request will be denied.

Short Form

No short form is provided for this message type

Description

None

Message ID : POL0152I

Severity

Information

Long Form

The Security Server matched policy ({0}) for the {2} request from host ({3}), server name {4} and Server Number {6}. But the policy did not contain any {1} rules. The request will be denied.

Message ID : POL0151I

1560

Short Form

No short form is provided for this message type

Description

None

Message ID : POL0153I

Severity

Information

Long Form

The Security Server matched rule ({0}) to the {1} request for host {2}, server name {3} and Server Number {5}. But, the request time {6} is after the end time {7} in the Rule. The rule will not be applied.

Short Form

No short form is provided for this message type

Description

None

Message ID : POL0152I

1561

Message ID : POL0154I

Severity

Information

Long Form

The Security Server matched rule ({0}) to the {1} request for host {2}, server name {3} and Server Number {5}. But, the request time {6} is before the start time {7} in the Rule. The rule will not be applied.

Short Form

No short form is provided for this message type

Description

None

Message ID : POL0155I

Severity

Information

Long Form

The Security Server matched rule ({0}) to the {1} request for host {2}, server name {3} and Server Number {5}. But the conditions do not match. The rule will not be applied

Short Form

No short form is provided for this message type

Description

None

Message ID : POL4537I

Severity

Information

Long Form

ACCESS GRANTED on request to {0} database {1}, on hostname {2}. Instance name is {3}, partition {4}, catnode {5}. The timestamp is {6}, and the DB2 version is {7}. The request protocol version is {8}.

Short Form

Access granted

Parameters

Label	CEF Label	Type	Usage
act	act	Text	Action being requested or performed
dbname	vds_dbname	Text	Database name
shost	shost	Text	Source host name
dbinstance	vds_dbinstance	Text	Database instance
dbpart	vds_dbpart	Numeric	Database partition
node	vds_node	Numeric	A node identifier
rt	rt	Text	Time of event
dbver	vds_dbver	Numeric	Database version
version	vds_version	Text	Software version string

Description

None

Message ID : POL4553I

Severity

Information

Message ID : POL4537I

Long Form

Internal initialization successful.

Short Form

SDK Init OK

Parameters

No parameters are provided for this message type

Description

None

Message ID : POL4573I

Severity

Information

Long Form

Backup failed.

Short Form

Backup fail

Parameters

No parameters are provided for this message type

Description

None

Message ID : POL4574I

Severity

Information

Long Form

Restore failed.

Short Form

Restore fail

Parameters

No parameters are provided for this message type

Description

None

Message ID : POL4575I

Severity

Information

Long Form

Backup completed successfully.

Short Form

Backup complete OK

Parameters

No parameters are provided for this message type

Message ID : POL4574I

1567

Description

None

Message ID : POL4576I

Severity

Information

Long Form

Restore completed successfully.

Short Form

Restore complete OK

Parameters

No parameters are provided for this message type

Description

None

Message ID : POL4575I

1568

Message ID : POL4582I

Severity

Information

Long Form

ACCESS GRANTED on request to perform {0} for hostname {1}. Server name is {2}, server number {3}, object id {4}. The timestamp is {5}. The request protocol version is {6}.

Short Form

No short form is provided for this message type

Description

None

Message ID : POL4615I

Severity

Information

Long Form

ACCESS GRANTED on request to perform {0} for hostname {1}. Server name is {2}, server number {3}. The timestamp is {4}. The request protocol version is {5}.

Short Form

Access granted

Parameters

Label	CEF Label	Type	Usage
act	act	Text	Action being requested or performed
shost	shost	Text	Source host name
dbinstance	vds_dbinstance	Text	Database instance
dbpart	vds_dbpart	Numeric	Database partition
rt	rt	Text	Time of event
version	vds_version	Text	Software version string

Description

None

Message ID : POL4702I

Severity

Information

Long Form

EVENT: {0}

Short Form

Event

Parameters

Label	CEF Label	Type	Usage
showStr	reason	Text	Code specifying reason for allowing access, if any

Description

None

Logger POL: Warnings

Message ID : POL4703W

Severity

Warning

Long Form

EVENT: {0}

Short Form

Event

Parameters

Label	CEF Label	Type	Usage
showStr	reason	Text	Code specifying reason for allowing access, if any

Description

None

Logger SDK: Errors

Message ID : SDK0197E

Severity

Error

Long Form

Host "{0}" is unknown to the Management Server.

Short Form

No short form is provided for this message type

Description

None

Message ID : SDK0198E

Severity

Error

Long Form

Host Group "{0}" is unknown to the Management Server.

Short Form

No short form is provided for this message type

Description

None

Message ID : SDK0199E

Severity

Error

Long Form

Unable to guard "{0}" on host "{1}" because a GuardPoint with a nested guard path exists.

Short Form

No short form is provided for this message type

Description

None

Message ID : SDK0200E

Severity

Error

Long Form

Unable to guard "{0}" on host group "{1}" because a GuardPoint with a nested guard path exists.

Short Form

No short form is provided for this message type

Description

None

Message ID : SDK0201E

Severity

Error

Message ID : SDK0199E

Long Form

GuardPoint "{0}" with policy "{1}" was created on host "{2}". It was disabled because the same path is already guarded.

Short Form

No short form is provided for this message type

Description

None

Message ID : SDK0202E

Severity

Error

Long Form

GuardPoint "{0}" with policy "{1}" was created on host group "{2}". It was disabled because the same path is already guarded.

Short Form

No short form is provided for this message type

Description

None

Message ID : SDK0203E

Severity

Error

Long Form

Unable to guard "{0}" on host "{1}" because a GuardPoint with the same guard path and the same policy is already defined.

Short Form

No short form is provided for this message type

Description

None

Message ID : SDK0204E

Severity

Error

Message ID : SDK0202E

Long Form

Unable to guard "{0}" on host group "{1}" because a GuardPoint with the same guard path and the same policy is already defined.

Short Form

No short form is provided for this message type

Description

None

Message ID : SDK0205E

Severity

Error

Long Form

GuardPoint "{0}" on host "{1}" is unknown to the Management Server.

Short Form

No short form is provided for this message type

Description

None

Message ID : SDK0206E**Severity**

Error

Long Form

GuardPoint "{0}" on host group "{1}" is unknown to the Management Server.

Short Form

No short form is provided for this message type

Description

None

Message ID : SDK0207E**Severity**

Error

Message ID : SDK0205E

Long Form

Unable to guard "{0}" on host "{1}" because the same path or a nested path has already been guarded.

Short Form

No short form is provided for this message type

Description

None

Message ID : SDK0208E

Severity

Error

Long Form

Unable to guard "{0}" on host group "{1}" because the same path or a nested path has already been guarded.

Short Form

No short form is provided for this message type

Description

None

Message ID : SDK0283E

Severity

Error

Long Form

Unable to process host security update because the update time "{0}" on host "{1}" is less than the latest security update time.

Short Form

No short form is provided for this message type

Description

None

Message ID : SDK0284E

Severity

Error

Message ID : SDK0208E

Long Form

Unable to process host security update because host "{0}" is already in PENDING status.

Short Form

No short form is provided for this message type

Description

None

Message ID : SDK0286E

Severity

Error

Long Form

Unable to process host security update because host "{0}" 's status is already updated.

Short Form

No short form is provided for this message type

Description

None

Message ID : SDK0403E**Severity**

Error

Long Form

The domain "{0}" does not exist in the server database.

Short Form

No short form is provided for this message type

Description

None

Message ID : SDK0407E**Severity**

Error

Message ID : SDK0286E

Long Form

The user "{0}" is not in the domain "{1}".

Short Form

No short form is provided for this message type

Description

None

Message ID : SDK0408E

Severity

Error

Long Form

There is more than one remaining user assigned to domain "{0}". The domain cannot be deleted. Ensure that there is only one remaining user in the domain before deleting the domain.

Short Form

No short form is provided for this message type

Description

None

Message ID : SDK0410E

Severity

Error

Long Form

Unable to switch domain "{0}". You are either not in the domain or are disabled in the domain.

Short Form

No short form is provided for this message type

Description

None

Message ID : SDK0411E

Severity

Error

Message ID : SDK0408E

Long Form

Host "{0}" is no longer shared with the domain "{1}".

Short Form

No short form is provided for this message type

Description

None

Message ID : SDK0416E

Severity

Error

Long Form

Host Group "{0}" is no longer shared with the domain "{1}".

Short Form

No short form is provided for this message type

Description

None

Message ID : SDK0417E

Severity

Error

Long Form

Unable to stop guarding "{0}" on host "{1}" because the path is guarded by another domain.

Short Form

No short form is provided for this message type

Description

None

Message ID : SDK0418E

Severity

Error

Message ID : SDK0416E

Long Form

Unable to stop guarding "{0}" on host group "{1}" because the path is guarded by another domain.

Short Form

No short form is provided for this message type

Description

None

Message ID : SDK0419E

Severity

Error

Long Form

Unable to guard "{0}" on host "{1}" because the path is guarded by another domain.

Short Form

No short form is provided for this message type

Description

None

Message ID : SDK0420E

Severity

Error

Long Form

Unable to guard "{0}" on host group "{1}" because the path is guarded by another domain.

Short Form

No short form is provided for this message type

Description

None

Message ID : SDK0421E

Severity

Error

Message ID : SDK0419E

Long Form

Unable to enable/disable GuardPoint "{0}" on host "{1}" because the path is guarded by another domain.

Short Form

No short form is provided for this message type

Description

None

Message ID : SDK0422E

Severity

Error

Long Form

Unable to enable/disable GuardPoint "{0}" on host group "{1}" because the path is guarded by another domain.

Short Form

No short form is provided for this message type

Description

None

Message ID : SDK0423E

Severity

Error

Long Form

Host "{0}" cannot join host group "{1}" because the host does not support CBC_CS1.

Short Form

No short form is provided for this message type

Description

None

Message ID : SDK0427E

Severity

Error

Message ID : SDK0422E

Long Form

Domain name "{0}" is already in use. Specify a different name.

Short Form

No short form is provided for this message type

Description

None

Message ID : SDK0437E

Severity

Error

Long Form

Host "{0}" is already shared with domain "{1}".

Short Form

No short form is provided for this message type

Description

None

Message ID : SDK0438E

Severity

Error

Long Form

There are {0} policies remaining in domain {1}, therefore, the domain cannot be deleted. Delete all remaining policies before deleting the domain.

Short Form

No short form is provided for this message type

Description

None

Message ID : SDK0439E

Severity

Error

Long Form

There are {0} hosts remaining in domain {1}, therefore, the domain cannot be deleted. Delete all remaining hosts before deleting the domain.

Short Form

No short form is provided for this message type

Description

None

Message ID : SDK0440E

Severity

Error

Long Form

There are {0} agent keys and/or vault keys remaining in domain {1}, therefore, the domain cannot be deleted. Delete all remaining keys before deleting the domain.

Message ID : SDK0439E

1594

Short Form

No short form is provided for this message type

Description

None

Message ID : SDK0441E

Severity

Error

Long Form

There are {0} host groups remaining in domain {1}, therefore, the domain cannot be deleted. Delete all remaining host groups before deleting the domain.

Short Form

No short form is provided for this message type

Description

None

Message ID : SDK0440E

1595

Message ID : SDK0442E

Severity

Error

Long Form

There are {0} key groups remaining in domain {1}, therefore, the domain cannot be deleted. Delete all remaining key groups before deleting the domain.

Short Form

No short form is provided for this message type

Description

None

Message ID : SDK0443E

Severity

Error

Long Form

SysLog Host name "{0}" is already in use. Specify a different name.

Short Form

No short form is provided for this message type

Description

None

Message ID : SDK0444E

Severity

Error

Long Form

SysLog Host "{0}" does not exist.

Short Form

No short form is provided for this message type

Description

None

Message ID : SDK0447E**Severity**

Error

Long Form

Host Group Id "{0}" does not belong to Domain ID "{1}".

Short Form

No short form is provided for this message type

Description

None

Message ID : SDK0450E**Severity**

Error

Message ID : SDK0444E

Long Form

RSA user name is in use "{0}"

Short Form

No short form is provided for this message type

Description

None

Message ID : SDK0451E

Severity

Error

Long Form

OTP record not found for OTP device "{0}"

Short Form

No short form is provided for this message type

Description

None

Message ID : SDK0503E

Severity

Error

Long Form

Unable to share host "{0}" with own domain "{1}".

Short Form

No short form is provided for this message type

Description

None

Message ID : SDK0504E

Severity

Error

Message ID : SDK0451E

Long Form

Unable to share host group "{0}" with own domain "{1}".

Short Form

No short form is provided for this message type

Description

None

Message ID : SDK0505E

Severity

Error

Long Form

Host group "{0}" is already shared with domain "{1}".

Short Form

No short form is provided for this message type

Description

None

Message ID : SDK0517E

Severity

Error

Long Form

Unable to update domain level. Invalid domain level.

Short Form

No short form is provided for this message type

Description

None

Message ID : SDK0525E

Severity

Error

Message ID : SDK0505E

Long Form

The Security Server was unable to backup the configuration. Check the logs.

Short Form

No short form is provided for this message type

Description

None

Message ID : SDK0526E

Severity

Error

Long Form

The Security Server was unable to restore the configuration. Check the logs.

Short Form

No short form is provided for this message type

Description

None

Message ID : SDK0533E

Severity

Error

Long Form

There are {0} syslog servers remaining in domain {1}, therefore, the domain cannot be deleted. Delete all remaining syslog servers before deleting the domain.

Short Form

No short form is provided for this message type

Description

None

Message ID : SDK0534E

Severity

Error

Long Form

Guard path "{0}" is not allowed on host or host group "{1}".

Short Form

No short form is provided for this message type

Description

None

Message ID : SDK0608E

Severity

Error

Long Form

Host "{0}" is already in host group "{1}".

Short Form

No short form is provided for this message type

Description

None

Message ID : SDK0630E

Severity

Error

Long Form

The Security Server was unable to perform the action. Check the logs.

Short Form

No short form is provided for this message type

Description

None

Message ID : SDK0637E

Severity

Error

Long Form

Operation failed. The Security Server is busy, retry later.

Short Form

No short form is provided for this message type

Description

None

Message ID : SDK0662E

Severity

Error

Long Form

Invalid host password challenge input.

Short Form

No short form is provided for this message type

Description

None

Message ID : SDK0663E

Severity

Error

Long Form

Challenge Response is not supported by host "{0}".

Short Form

No short form is provided for this message type

Description

None

Message ID : SDK0664E

Severity

Error

Long Form

Administrator "{0}" failed to generate host password response for host "{1}".

Short Form

failed to generate host password response

Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
shost	shost	Text	Source host name

Description

None

Message ID : SDK0670E

Severity

Error

Long Form

Agent for the host with id {0} and the agent type "{1}" is unknown to the Management Server.

Short Form

No short form is provided for this message type

Description

None

Message ID : SDK0671E

Severity

Error

Long Form

Host IP "{0}" already exists.

Short Form

No short form is provided for this message type

Description

None

Message ID : SDK0716E

Severity

Error

Long Form

SMTP server already defined.

Short Form

No short form is provided for this message type

Description

None

Message ID : SDK0717E

Severity

Error

Long Form

SMTP server not found.

Short Form

No short form is provided for this message type

Description

None

Message ID : SDK0718E

Severity

Error

Long Form

Email notification group with name "{0}" already defined in domain.

Short Form

No short form is provided for this message type

Description

None

Message ID : SDK0719E

Severity

Error

Long Form

Email notification group with name "{0}" not defined in domain.

Short Form

No short form is provided for this message type

Description

None

Message ID : SDK0776E

Severity

Error

Long Form

Host "{0}" cannot join this group because membership in a cluster host group is exclusive.

Short Form

No short form is provided for this message type

Description

None

Message ID : SDK0777E

Severity

Error

Long Form

Host "{0}" has conflicting GuardPoint "{1}" and cannot join the cluster host group.

Short Form

No short form is provided for this message type

Description

None

Message ID : SDK0778E

Severity

Error

Long Form

The selected guard policy "{0}" is inherited from cluster host group "{1}". It can only be disabled from host group "{2}".

Short Form

No short form is provided for this message type

Description

None

Message ID : SDK0780E

Severity

Error

Long Form

The GuardPoint cannot be enabled because member host "{0}" has a conflicting GuardPoint.

Short Form

No short form is provided for this message type

Description

None

Message ID : SDK0800E

Severity

Error

Long Form

Cannot add an SSL syslog server without certificates.

Short Form

No short form is provided for this message type

Description

None

Message ID : SDK0801E

Severity

Error

Long Form

Invalid format in certificates file. Expecting PEM or DER encoded X.509 certificate(s).

Short Form

No short form is provided for this message type

Description

None

Message ID : SDK0800E

Message ID : SDK1237E

Severity

Error

Long Form

The length of the domain name "{0}" cannot exceed 64 characters.

Short Form

No short form is provided for this message type

Description

None

Message ID : SDK1238E

Severity

Error

Long Form

Unrecognized certificate format, use only supported formats.

Short Form

No short form is provided for this message type

Description

None

Message ID : SDK1239E

Severity

Error

Long Form

Unable to import the certificate.

Short Form

No short form is provided for this message type

Description

None

Message ID : SDK1240E

Severity

Error

Long Form

Unable to import the private key.

Short Form

No short form is provided for this message type

Description

None

Message ID : SDK1241E

Severity

Error

Long Form

Unable to find the certificate with id"{0}".

Short Form

No short form is provided for this message type

Description

None

Message ID : SDK1242E

Severity

Error

Long Form

Unable to export certificates.

Short Form

No short form is provided for this message type

Description

None

Message ID : SDK1243E

Severity

Error

Long Form

Unable to delete certificates.

Short Form

No short form is provided for this message type

Description

None

Message ID : SDK1256E

Severity

Error

Long Form

Invalid Enhanced Usage specified.

Short Form

No short form is provided for this message type

Description

None

Message ID : SDK1262E

Severity

Error

Long Form

Dropped {0} syslog message(s) due to connectivity issue of syslog server "{1}" .

Short Form

No short form is provided for this message type

Description

None

Message ID : SDK1256E

1623

Message ID : SDK1296E

Severity

Error

Long Form

Unable to import error while reading the certificate: {0}.

Short Form

No short form is provided for this message type

Description

None

Message ID : SDK1315E

Severity

Error

Long Form

Vaulting certificate is not supported for GDE DSM.

Short Form

No short form is provided for this message type

Description

None

Message ID : SDK1324E

Severity

Error

Long Form

Your current license does not support certificate vaulting.

Short Form

No short form is provided for this message type

Description

None

Message ID : SDK1340E

Severity

Error

Long Form

GuardPoint policy "{0}" not found on host group "{1}"

Short Form

No short form is provided for this message type

Description

None

Message ID : SDK1365E

Severity

Error

Long Form

GuardPoint "{0}" not found for policy "{1}" on host "{2}"

Short Form

No short form is provided for this message type

Description

None

Message ID : SDK1385E

Severity

Error

Long Form

{0} is enabled for host {1}, therefore, it cannot be disabled.

Short Form

No short form is provided for this message type

Description

None

Message ID : SDK1386E

Severity

Error

Long Form

{0} is not supported for {1} host {2}

Short Form

No short form is provided for this message type

Description

None

Message ID : SDK1387E

Severity

Error

Long Form

{0} not supported for host {1}.

Short Form

No short form is provided for this message type

Description

None

Message ID : SDK1388E

Severity

Error

Long Form

Cannot set GuardPoint, docker not enabled on host {0}

Short Form

No short form is provided for this message type

Description

None

Message ID : SDK1387E

Message ID : SDK1389E

Severity

Error

Long Form

Signature {} cannot be associated with docker. It is associated with host.

Short Form

No short form is provided for this message type

Description

None

Message ID : SDK1390E

Severity

Error

Long Form

Cannot modify docker identifier associated with the Signature {}.

Short Form

No short form is provided for this message type

Description

None

Message ID : SDK1391E

Severity

Error

Long Form

LDT QoS Schedule {0} conflicts with another schedule {1}.

Short Form

No short form is provided for this message type

Description

None

Message ID : SDK1407E

Severity

Error

Long Form

Deleting host "{0}" with registered VDE agent is not allowed

Short Form

No short form is provided for this message type

Description

None

Message ID : SDK1426E

Severity

Error

Long Form

Unable to delete host in domain "{0}" from domain "{1}".

Short Form

No short form is provided for this message type

Description

None

Message ID : SDK1504E

Severity

Error

Long Form

Failed to contact agent on Host {0}. Host cannot be deleted

Short Form

No short form is provided for this message type

Description

None

Message ID : SDK1508E

Severity

Error

Long Form

Cannot delete Host {0}. Stop guarding/disable GuardPoints associated with the LDT policy before deleting the host.

Short Form

No short form is provided for this message type

Description

None

Message ID : SDK1513E

Severity

Error

Long Form

Concise logging feature is not supported for host {0}.

Short Form

No short form is provided for this message type

Description

None

Message ID : SDK1550E

Severity

Error

Long Form

Cert-Chain is not valid

Short Form

No short form is provided for this message type

Description

None

Message ID : SDK1553E

Severity

Error

Long Form

Could not restart the KMIP server

Short Form

No short form is provided for this message type

Description

None

Message ID : SDK1554E

Severity

Error

Long Form

Could not update trusted ca's for the KMIP server.

Short Form

No short form is provided for this message type

Description

None

Message ID : SDK1558E

Severity

Error

Long Form

Upload a certificate which is issued by trusted CA

Short Form

No short form is provided for this message type

Description

None

Message ID : SDK1564E

Severity

Error

Long Form

Certificate is not valid

Short Form

No short form is provided for this message type

Description

None

Message ID : SDK1565E

Severity

Error

Long Form

Certificate {0} is a non-ca certificate, it does not have basic constraints

Short Form

No short form is provided for this message type

Description

None

Message ID : SDK1566E

Severity

Error

Long Form

Certificate {0} certificate cannot be verified with its issuer {1}

Short Form

No short form is provided for this message type

Description

None

Message ID : SDK1567E

Severity

Error

Long Form

Certificate's common name {0} does not match with the hostname {1}

Short Form

No short form is provided for this message type

Description

None

Message ID : SDK1568E

Severity

Error

Long Form

Certificate {0} is not issued by trusted CA

Short Form

No short form is provided for this message type

Description

None

Message ID : SDK1617E

Severity

Error

Long Form

Host "{0}" is not in HostGroup "{1}".

Short Form

No short form is provided for this message type

Description

None

Message ID : SDK1619E

Severity

Error

Long Form

Cannot enable both LDT and Docker on a host {0}.

Short Form

No short form is provided for this message type

Description

None

Message ID : SDK1620E

Severity

Error

Long Form

Host {0} is not approved for this operation yet.

Short Form

No short form is provided for this message type

Description

None

Message ID : SDK1621E

Severity

Error

Long Form

Agent Lock and System Lock settings combination is not valid. Refer to the documentation for details.

Short Form

No short form is provided for this message type

Description

None

Message ID : SDK1622E

Severity

Error

Long Form

"Communication Enabled" cannot be set to true if "Registration Allowed" is disabled or set to false.

Short Form

No short form is provided for this message type

Description

None

Message ID : SDK1623E

Severity

Error

Long Form

System Lock can not be enabled if the FA Agent Lock is disabled. Refer to the documentation for details.

Short Form

No short form is provided for this message type

Description

None

Message ID : SDK1649E

Severity

Error

Long Form

Host "{0}" cannot join host group "{1}" because the host does not support RekeyRate.

Short Form

No short form is provided for this message type

Description

None

Message ID : SDK1652E

Severity

Error

Long Form

Certificate is rejected. This certificate has no client authentication issued by trusted CA.

Short Form

No short form is provided for this message type

Description

None

Message ID : SDK1654E

Severity

Error

Long Form

Unable to process GuardPoint "{0}" creation because the same GuardPoint "{0}" still exists with status: PENDING, in host "{1}".
Try again later.

Short Form

No short form is provided for this message type

Description

None

Message ID : SDK1655E

Severity

Error

Long Form

Host sharing is not allowed for this host agent.

Short Form

No short form is provided for this message type

Description

None

Message ID : SDK1660E

Severity

Error

Long Form

The domain {1} still contains {0} user identity object(s), which need to be deleted before the domain can be deleted.

Short Form

No short form is provided for this message type

Description

None

Message ID : SDK1663E

Severity

Error

Long Form

Host group "{0}" cannot change settings because one of the hosts does not support RekeyRate.

Short Form

No short form is provided for this message type

Description

None

Message ID : SDK1668E

Severity

Error

Long Form

Unable to import some or all keys from an export file. Check logs or contact support.

Short Form

No short form is provided for this message type

Description

None

Message ID : SDK1671E

Severity

Error

Long Form

There are {0} GuardPoints remaining in host group {1}, therefore, the host group cannot be deleted. Remove all remaining GuardPoints before deleting the host group.

Short Form

No short form is provided for this message type

Description

None

Message ID : SDK1672E

Severity

Error

Long Form

There are {0} hosts remaining in host group {1}, therefore, the host group cannot be deleted. Remove all remaining hosts before deleting the host group.

Short Form

No short form is provided for this message type

Description

None

Message ID : SDK1683E

Severity

Error

Long Form

Host "{0}" cannot join host group "{1}" because the host does not support {2}.

Short Form

No short form is provided for this message type

Description

None

Message ID : SDK1706E

Severity

Error

Long Form

Certificate with subject DN "{0}" is a {1} certificate which is not supported in {2} mode.

Short Form

No short form is provided for this message type

Description

None

Message ID : SDK1718E

Severity

Error

Message ID : SDK1683E

Long Form

Cloud Object Storage is not enabled for Host "{0}". The DSM cannot join the cluster host group "{1}" because it contains existing Cloud Object Storage GuardPoints.

Short Form

No short form is provided for this message type

Description

None

Message ID : SDK1731E

Severity

Error

Long Form

Guard path "{0}" can not exceed 64 bytes on host or host group "{1}".

Short Form

No short form is provided for this message type

Description

None

Message ID : SDK1742E

Severity

Error

Long Form

"{0}" is not a valid Cloud Object Storage type guard path.

Short Form

No short form is provided for this message type

Description

None

Message ID : SDK1746E

Severity

Error

Message ID : SDK1731E

Long Form

Secure Start must be enabled if Raw or Block Device is selected.

Short Form

No short form is provided for this message type

Description

None

Message ID : SDK1747E

Severity

Error

Long Form

Efficient Storage feature must be enabled if Raw or Block Device is selected.

Short Form

No short form is provided for this message type

Description

None

Message ID : SDK1760E

Severity

Error

Long Form

Host Group GuardPoint policy "{0}" not found.

Short Form

No short form is provided for this message type

Description

None

Message ID : SDK1761E

Severity

Error

Message ID : SDK1747E

Long Form

Host "{0}" does not support GuardPoint for LDT Policy "{1}" with Raw Device.

Short Form

No short form is provided for this message type

Description

None

Message ID : SDK1769E

Severity

Error

Long Form

Cannot create "{0}" GuardPoint for COS with "{1}" Policy. The same GuardPoint already exists and is enabled with another policy either in the current or in another domain. The DSM allows exactly one COS GuardPoint to be enabled per S3 bucket.

Short Form

No short form is provided for this message type

Description

None

Message ID : SDK1770E

Severity

Error

Long Form

Cannot enable "{0}" GuardPoint for COS with "{1}" Policy. The same GuardPoint is already enabled with another policy either in the current or in another domain. The DSM allows exactly one COS GuardPoint to be enabled per S3 bucket.

Short Form

No short form is provided for this message type

Description

None

Message ID : SDK1795E

Severity

Error

Long Form

GuardPath must follow "Windows" format and it is applicable for Windows agent only if embedded header field is enabled.

Short Form

No short form is provided for this message type

Description

None

Message ID : SDK1796E

Severity

Error

Long Form

GuardPointType must be "AUTO_GUARD_DIRECTORY" if embedded header field is enabled.

Short Form

No short form is provided for this message type

Description

None

Message ID : SDK1797E

Severity

Error

Long Form

Policy must be of "LDT" type if embedded field is enabled.

Short Form

No short form is provided for this message type

Description

None

Message ID : SDK1798E

Severity

Error

Long Form

CIFS share credential already exist for user name "{0}" and user domain "{1}".

Short Form

No short form is provided for this message type

Description

None

Message ID : SDK1801E

Severity

Error

Long Form

CIFS share credential does not exist for credential "{0}".

Short Form

No short form is provided for this message type

Description

None

Message ID : SDK1802E

Severity

Error

Long Form

Unable to create or update CIFS share credential. Please try again later.

Short Form

No short form is provided for this message type

Description

None

Message ID : SDK1803E

Severity

Error

Long Form

CIFS share credential(s) requested for deletion are already in use.

Short Form

No short form is provided for this message type

Description

None

Message ID : SDK1807E

Severity

Error

Long Form

CIFS share credential is mandatory if policy type is LDT, guard type is "AUTO_GUARD_DIRECTORY" and guard path is in CIFS share format.

Short Form

No short form is provided for this message type

Description

None

Message ID : SDK1808E

Severity

Error

Long Form

If CIFS share credential is provided then policy type must be LDT, guard type must be "AUTO_GUARD_DIRECTORY" and guard path must be in CIFS share format.

Short Form

No short form is provided for this message type

Description

None

Message ID : SDK1807E

1664

Message ID : SDK1809E

Severity

Error

Long Form

An internal error occurred on the Security Server. Refer to cgss.log and server.log for details. Call support if necessary.

Short Form

No short form is provided for this message type

Description

None

Message ID : SDK1811E

Severity

Error

Long Form

There are {0} incompatible kernel version hosts in the domain. List of hosts and its status:"{1}".

Short Form

No short form is provided for this message type

Description

None

Message ID : SDK1812E

Severity

Error

Long Form

The json package contains an invalid agent compatibility JSON signature.

Short Form

No short form is provided for this message type

Description

None

Message ID : SDK1814E

Severity

Error

Long Form

RSA User ID [{0}] is in use by another user. Select a different User ID.

Short Form

No short form is provided for this message type

Description

None

Message ID : SDK1815E

Severity

Error

Long Form

Unable to upload the compatibility list because it is the same list or not the current list. {0}.

Short Form

No short form is provided for this message type

Description

None

Message ID : SDK1817E

Severity

Error

Long Form

Compatibility list upload failed. Unable to extract the files.

Short Form

No short form is provided for this message type

Description

None

Message ID : SDK1818E

Severity

Error

Long Form

Uploaded compatibility list file has no data.

Short Form

No short form is provided for this message type

Description

None

Message ID : SDK1819E

Severity

Error

Long Form

Unable to upload the compatibility list because the format of the date or time is not supported. {0}.

Short Form

No short form is provided for this message type

Description

None

Message ID : SDK1821E

Severity

Error

Long Form

A Silo already exists for name "{0}".

Short Form

No short form is provided for this message type

Description

None

Message ID : SDK1822E

Severity

Error

Long Form

A Silo does not exist with siloID "{0}".

Short Form

No short form is provided for this message type

Description

None

Message ID : SDK1823E

Severity

Error

Long Form

A Silo does not exist with silo name "{0}".

Short Form

No short form is provided for this message type

Description

None

Message ID : SDK1824E

Severity

Error

Long Form

Silo(s) requested for deletion are already in use.

Short Form

No short form is provided for this message type

Description

None

Message ID : SDK1829E

Severity

Error

Long Form

You can only register a silo for a VTE agent that is enabled for LDT.

Short Form

No short form is provided for this message type

Description

None

Message ID : SDK1830E

Severity

Error

Long Form

Administrator {0} is unable to upload the malicious compatibility list because it contains an invalid agent compatibility JSON signature.

Short Form

No short form is provided for this message type

Description

None

Message ID : SDK1843E

Severity

Error

Long Form

Host "{0}" does not exist in the domain "{1}".

Short Form

No short form is provided for this message type

Description

None

Message ID : SDK1851E

Severity

Error

Long Form

You can only enable Preferred LGS Primary for a VTE agent that is enabled for LDT.

Short Form

No short form is provided for this message type

Description

None

Message ID : SDK1852E

Severity

Error

Long Form

Host "{0}" does not belong to any domain where user has access.

Short Form

No short form is provided for this message type

Description

None

Message ID : SDK1853E

Severity

Error

Long Form

Signature Set with name "{0}" cannot be found in the domain.

Short Form

No short form is provided for this message type

Description

None

Message ID : SDK1854E

Severity

Error

Long Form

Certificate file is mandatory and upload file key name must be fileCertificate.

Short Form

No short form is provided for this message type

Description

None

Message ID : SDK1855E

Severity

Error

Long Form

Only one entry is allowed for fileCertificate key.

Short Form

No short form is provided for this message type

Description

None

Message ID : SDK1856E

Severity

Error

Long Form

Only one entry is allowed for filePrivateKey key.

Short Form

No short form is provided for this message type

Description

None

Message ID : SDK1857E

Severity

Error

Long Form

Invalid content of uploaded certificate file.

Short Form

No short form is provided for this message type

Description

None

Message ID : SDK1858E

Severity

Error

Long Form

Invalid content of uploaded private key file.

Message ID : SDK1857E

Short Form

No short form is provided for this message type

Description

None

Message ID : SDK1859E

Severity

Error

Long Form

Password is mandatory for PKCS12 format certificate.

Short Form

No short form is provided for this message type

Description

None

Message ID : SDK1860E

Severity

Error

Long Form

Field "{0}" cannot be updated.#

Short Form

No short form is provided for this message type

Description

None

Message ID : SDK1870E

Severity

Error

Long Form

Host "{0}" cannot join host group "{1}" because the host is LDT-Enabled but the host group has a conflict with this.

Short Form

No short form is provided for this message type

Description

None

Message ID : SDK1871E

Severity

Error

Long Form

Host "{0}" cannot join host group "{1}" because the host is Docker-Enabled but the host group has a conflict with this.

Short Form

No short form is provided for this message type

Description

None

Logger SDK: Information

Message ID : SDK0544I

Severity

Information

Long Form

Administrator "{0}" created a server backup key.

Short Form

created server backup key

Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name

Description

None

Message ID : SDK0545I

Severity

Information

Long Form

Administrator "{0}" imported a server backup key.

Short Form

imported server backup key

Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name

Description

None

Message ID : SDK0665I

Severity

Information

Long Form

Administrator "{0}" generated host password response for host "{1}" successfully.

Short Form

generated host password response

Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
shost	shost	Text	Source host name

Description

None

Message ID : SDK1551I

Severity

Information

Long Form

Auth is on

Short Form

No short form is provided for this message type

Description

None

Message ID : SDK1552I

Severity

Information

Long Form

Auth is off

Message ID : SDK1551I

Short Form

No short form is provided for this message type

Description

None

Message ID : SDK1555I

Severity

Information

Long Form

Some or all of the certificates exist. Do you want to delete the following certificates?

Short Form

No short form is provided for this message type

Description

None

Message ID : SDK1552I

Message ID : SDK1556I

Severity

Information

Long Form

There is no change in certificates

Short Form

No short form is provided for this message type

Description

None

Message ID : SDK1557I

Severity

Information

Long Form

The client certificate is issued by trusted CA

Short Form

No short form is provided for this message type

Description

None

Message ID : SDK1559I

Severity

Information

Long Form

The client certificate is not validated because there are no trusted ca's. There could be issues when trusted ca's are added in the future.

Short Form

No short form is provided for this message type

Description

None

Message ID : SDK1557I

1689

Message ID : SDK1560I

Severity

Information

Long Form

No certificates are affected due to this operation.

Short Form

No short form is provided for this message type

Description

None

Message ID : SDK1561I

Severity

Information

Long Form

Client certificate is self signed. It is accepted for now, however, it can create problems when trusted ca's are added in the future.

Short Form

No short form is provided for this message type

Description

None

Message ID : SDK1562I

Severity

Information

Long Form

Certificate and its dependent certificates are deleted

Short Form

No short form is provided for this message type

Description

None

Message ID : SDK1561I

Message ID : SDK1563I

Severity

Information

Long Form

Certificate is deleted

Short Form

No short form is provided for this message type

Description

None

Message ID : SDK1670I

Severity

Information

Long Form

KMIP enabled on domain: {1}, by user {0}.

Short Form

No short form is provided for this message type

Description

None

Message ID : SDK1689I

Severity

Information

Long Form

Host {0} already has FF1 enabled. Once FF1 is enabled, it cannot be disabled.

Short Form

No short form is provided for this message type

Description

None

Message ID : SDK1738I

Severity

Information

Long Form

Cannot enable both {0} and {1} for host {2}.

Short Form

No short form is provided for this message type

Description

None

Message ID : SDK1799I

Severity

Information

Long Form

CIFS share credential created for user name "{1}" and user domain "{2}" by administrator "{0}".

Short Form

CIFS share credential created

Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name

Description

None

Message ID : SDK1800I

Severity

Information

Long Form

CIFS share credential updated for user name "{1}" and user domain "{2}" by administrator "{0}".

Short Form

CIFS share credential updated

Message ID : SDK1799I

1695

Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name

Description

None

Message ID : SDK1810I

Severity

Information

Long Form

Administrator {0} successfully uploaded agent compatibility list JSON "{1}".

Short Form

{0} {1} CEF:0|Vormetric, Inc.|dsm|{3}|SDK1805I|uploaded agent compatibility list ok|3|cs4Label=logger cs4=SDK spid={2} rt={4} dvchost={1}

Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name

Description

None

Message ID : SDK1825I

Severity

Information

Long Form

Silo created for name "{0}" by administrator "{1}".

Short Form

Silo created

Parameters

Label	CEF Label	Type	Usage
-------	-----------	------	-------

Message ID : SDK1810I

user	suser	Text	User name
------	-------	------	-----------

Description

None

Message ID : SDK1826I

Severity

Information

Long Form

Silo updated for name "{0}" by administrator "{1}".

Short Form

Silo updated

Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name

Message ID : SDK1825I

1698

Description

None

Message ID : SDK1831I

Severity

Information

Long Form

Silo deleted for name "{0}" by administrator "{1}".

Short Form

Silo deleted

Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name

Description

None

Message ID : SDK1826I

Message ID : SDK1833I

Severity

Information

Long Form

CIFS share credential deleted for user name "{1}" and user domain "{2}" by administrator "{0}".

Short Form

CIFS share credential deleted

Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name

Description

None

Logger SDK: Warnings

Message ID : SDK0290W

Severity

Warning

Long Form

The following hosts could not be imported: "{0}". Check the import file format. The correct format is: hostname, description, password, allow_fs_agent, allow_db2_agent, allow_ids_agent, allow_kmip_agent. Do NOT include a header row. Also, make sure the host(s) do not already exist.

Short Form

No short form is provided for this message type

Description

None

Message ID : SDK0583W

Severity

Warning

Long Form

Current license has expired.

Short Form

No short form is provided for this message type

Description

None

Message ID : SDK0584W

Severity

Warning

Long Form

The maximum number of servers allowed by the current license has been exceeded.

Short Form

No short form is provided for this message type

Description

None

Message ID : SDK0585W

Severity

Warning

Long Form

The maximum number of agents allowed by the current license has been exceeded.

Short Form

No short form is provided for this message type

Description

None

Message ID : SDK0597W

Severity

Warning

Long Form

Due to name or UUID/Identifier(s) conflicts, one or more of the imported key's names were appended with a number, or the UUIDs/Identifier(s) were regenerated.

Short Form

No short form is provided for this message type

Description

None

Message ID : SDK0779W

Severity

Warning

Long Form

The new GuardPoint is added into cluster host group and disabled because member host "{0}" has a conflicting GuardPoint.

Short Form

No short form is provided for this message type

Description

None

Message ID : SDK1336W

Severity

Warning

Long Form

Failed to create KMIP partition: {0}.

Short Form

No short form is provided for this message type

Description

None

Message ID : SDK1338W

Severity

Warning

Long Form

There are {0} signatures remaining in domain {1}, therefore, the domain cannot be deleted. Delete all remaining signatures before deleting the domain.

Short Form

No short form is provided for this message type

Description

None

Message ID : SDK1368W

Severity

Warning

Long Form

Failed to retrieve partition id for KMIP partition: {0}.

Short Form

No short form is provided for this message type

Description

None

Message ID : SDK1390W

Severity

Warning

Long Form

There are {0} certificates remaining for the domain {1}, therefore, the domain cannot be deleted. Delete all remaining certificates for the domain before deleting the domain.

Short Form

No short form is provided for this message type

Description

None

Message ID : SDK1616W

Severity

Warning

Long Form

Only the current version of the key has been imported. Due to either a name or UUID/Identifier(s) conflict, the name of the key has been appended with a number, or the UUID/Identifier(s) has been regenerated.

Short Form

No short form is provided for this message type

Description

None

Message ID : SDK1617W

Severity

Warning

Long Form

Only the current version of the key has been imported.

Short Form

No short form is provided for this message type

Description

None

Message ID : SDK1669W

Severity

Warning

Long Form

Unable to enable KMIP: {0}.

Short Form

No short form is provided for this message type

Description

None

Logger SIN: Errors

Message ID : SIN0209E

Severity

Error

Long Form

Error while signing the configuration file. The error may be due to invalid private key (or) error while updating data to be signed. Please check the log for more details.

Short Form

No short form is provided for this message type

Description

None

Message ID : SIN0210E

Severity

Error

Long Form

Internal Error. File creation failed. The error may be due to insufficient permissions for creating the file

Short Form

No short form is provided for this message type

Description

None

Message ID : SIN0211E

Severity

Error

Long Form

Unable to get Keypair

Short Form

No short form is provided for this message type

Message ID : SIN0210E

1712

Description

None

Message ID : SIN0212E

Severity

Error

Long Form

Argument or must be supplied

Short Form

No short form is provided for this message type

Description

None

Message ID : SIN0213E

Severity

Error

Message ID : SIN0211E

Long Form

Argument need to specify atleast one file

Short Form

No short form is provided for this message type

Description

None

Message ID : SIN0214E

Severity

Error

Long Form

Internal Error.

Short Form

No short form is provided for this message type

Description

None

Logger SIN: Fatal errors

Message ID : SIN0176F

Severity

Fatal error

Long Form

The Security Server failed to start up due to a failed integrity check. One of the components "{0}" of the Security Server may have been manually altered. Please ensure that original software components of the Security Server are in place.

Short Form

failed integrity check

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : SIN0177F

Severity

Fatal error

Long Form

The Security Server failed to start up due to a missing configuration file. The file "{0}" could not be found. Please ensure that original software components of the Security Server are in place.

Short Form

missing configuration file

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : SIN0178F

Severity

Fatal error

Long Form

The Security Server failed to start up due to missing required steps needed for signing configuration files. Please ensure that all the required steps are completed.

Short Form

No short form is provided for this message type

Description

None

Logger USR: Errors

Message ID : USR0156E

Severity

Error

Long Form

Invalid Username. A valid username should have at least 5 characters and at most 36 characters.

Short Form

No short form is provided for this message type

Description

None

Message ID : USR0157E

Severity

Error

Long Form

Invalid Password. A valid password should have at least 8 characters.

Short Form

No short form is provided for this message type

Description

None

Message ID : USR0158E

Severity

Error

Long Form

User "{0}" cannot be deleted.

Short Form

No short form is provided for this message type

Description

None

Message ID : USR0159E

Severity

Error

Long Form

The password has expired or has been reset. The password needs to be changed.

Short Form

No short form is provided for this message type

Description

None

Message ID : USR0160E

Severity

Error

Message ID : USR0158E

Long Form

User name "{0}" does not exist.

Short Form

No short form is provided for this message type

Description

None

Message ID : USR0161E

Severity

Error

Long Form

User Id "{0}" does not exist.

Short Form

No short form is provided for this message type

Description

None

Message ID : USR0162E

Severity

Error

Long Form

Password should contain at least one digit.

Short Form

No short form is provided for this message type

Description

None

Message ID : USR0163E

Severity

Error

Message ID : USR0161E

Long Form

Password should contain at least one alphabet.

Short Form

No short form is provided for this message type

Description

None

Message ID : USR0164E

Severity

Error

Long Form

Invalid username/password.

Short Form

No short form is provided for this message type

Description

None

Message ID : USR0165E**Severity**

Error

Long Form

User "{0}" does not have sufficient privileges for this operation.

Short Form

No short form is provided for this message type

Description

None

Message ID : USR0166E**Severity**

Error

Message ID : USR0164E

Long Form

Roles for user "{0}" cannot be modified.

Short Form

No short form is provided for this message type

Description

None

Message ID : USR0168E

Severity

Error

Long Form

Invalid one-time passcode.

Short Form

No short form is provided for this message type

Description

None

Message ID : USR0169E**Severity**

Error

Long Form

Setup error in one-time passcode authentication server.

Short Form

No short form is provided for this message type

Description

None

Message ID : USR0170E**Severity**

Error

Message ID : USR0168E

Long Form

Invalid configuration file or unable to reach the RSA server.

Short Form

No short form is provided for this message type

Description

None

Message ID : USR0219E

Severity

Error

Long Form

The session might have timed out. Login again to proceed.

Short Form

No short form is provided for this message type

Description

None

Message ID : USR0266E

Severity

Error

Long Form

The system has locked your account because of too many failed attempts. Your account will be unlocked in {0} minutes.

Short Form

No short form is provided for this message type

Description

None

Message ID : USR0270E

Severity

Error

Message ID : USR0219E

Long Form

An error occurred while getting administrator login information.

Short Form

No short form is provided for this message type

Description

None

Message ID : USR0298E

Severity

Error

Long Form

Invalid administrator "{0}" failed to login at {1} from client with IP address {2}.

Short Form

admin login failed from client with IP address {5}

Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name

Description

None

Message ID : USR0308E

Severity

Error

Long Form

{0} must include at least one uppercase character.

Short Form

No short form is provided for this message type

Description

None

Message ID : USR0298E

Message ID : USR0309E

Severity

Error

Long Form

{0} must include at least one number.

Short Form

No short form is provided for this message type

Description

None

Message ID : USR0310E

Severity

Error

Long Form

{0} must include at least one of the following {1} special characters.

Short Form

No short form is provided for this message type

Description

None

Message ID : USR0311E

Severity

Error

Long Form

{0} should not have consecutive repeat characters or numbers.

Short Form

No short form is provided for this message type

Description

None

Message ID : USR0315E

Severity

Error

Long Form

Internal error occurred during password expiry check.

Short Form

No short form is provided for this message type

Description

None

Message ID : USR0316E

Severity

Error

Long Form

Password is going to expire in {0} days.

Short Form

No short form is provided for this message type

Description

None

Message ID : USR0318E**Severity**

Error

Long Form

Internal error occurred during password history retrieval.

Short Form

No short form is provided for this message type

Description

None

Message ID : USR0319E

Severity

Error

Long Form

Password cannot be the same as one of your previous {0} passwords.

Short Form

No short form is provided for this message type

Description

None

Message ID : USR0320E

Severity

Error

Long Form

Please specify the correct current password.

Short Form

No short form is provided for this message type

Description

None

Message ID : USR0337E

Severity

Error

Long Form

{0} must include at least one lowercase character.

Short Form

No short form is provided for this message type

Description

None

Message ID : USR0340E

Severity

Error

Long Form

{0} length must be at least {1} characters.

Short Form

No short form is provided for this message type

Description

None

Message ID : USR0409E

Severity

Error

Long Form

User "{0}" cannot be deleted because they are in domains.

Short Form

No short form is provided for this message type

Description

None

Message ID : USR0535E

Severity

Error

Long Form

Invalid User description. A valid description should have at most 128 characters.

Short Form

No short form is provided for this message type

Description

None

Message ID : USR0593E

Severity

Error

Long Form

{0} special characters must be the following {1} special characters.

Short Form

No short form is provided for this message type

Description

None

Message ID : USR0632E

Severity

Error

Long Form

User "{0}" failed to login from client with IP address {1}.

Short Form

user login failed from client with IP address {5}

Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name

Description

None

Message ID : USR1230E

Severity

Error

Long Form

Can't find all admin user type

Short Form

No short form is provided for this message type

Message ID : USR0632E

Description

None

Message ID : USR1231E

Severity

Error

Long Form

Can't find default admin user type

Short Form

No short form is provided for this message type

Description

None

Message ID : USR1232E

Severity

Error

Message ID : USR1230E

Long Form

Can't find domain admin user type

Short Form

No short form is provided for this message type

Description

None

Message ID : USR1233E

Severity

Error

Long Form

Can't find domain_security admin user type

Short Form

No short form is provided for this message type

Message ID : USR1232E

Description

None

Message ID : USR1234E**Severity**

Error

Long Form

Can't find security admin user type

Short Form

No short form is provided for this message type

Description

None

Message ID : USR1235E**Severity**

Error

Message ID : USR1233E

Long Form

Can't find system admin user type

Short Form

No short form is provided for this message type

Description

None

Message ID : USR1236E

Severity

Error

Long Form

Can't create default admin in domain mode

Short Form

No short form is provided for this message type

Message ID : USR1235E

1745

Description

None

Message ID : USR1254E

Severity

Error

Long Form

LDAP Login failed...

Short Form

No short form is provided for this message type

Description

None

Message ID : USR1275E

Severity

Error

Message ID : USR1236E

Long Form

The new password must be different from the current password by at least {0} characters.

Short Form

No short form is provided for this message type

Description

None

Message ID : USR1288E

Severity

Error

Long Form

Internal error occurred during password configuration retrieval.

Short Form

No short form is provided for this message type

Description

None

Message ID : USR1289E

Severity

Error

Long Form

Your password was last changed on {0}. Password is not allowed to be changed more than once within {1} day(s).

Short Form

No short form is provided for this message type

Description

None

Message ID : USR1321E

Severity

Error

Message ID : USR1288E

Long Form

Please cleanup the replication before delete...

Short Form

No short form is provided for this message type

Description

None

Message ID : USR1325E

Severity

Error

Long Form

There are multiple colons...

Short Form

No short form is provided for this message type

Message ID : USR1321E

1749

Description

None

Message ID : USR1326E

Severity

Error

Long Form

Cannot validate the host name and the port...

Short Form

No short form is provided for this message type

Description

None

Message ID : USR1327E

Severity

Error

Message ID : USR1325E

Long Form

The port number is invalid.

Short Form

No short form is provided for this message type

Description

None

Message ID : USR1328E

Severity

Error

Long Form

A system admin cannot be assigned to a domain.

Short Form

No short form is provided for this message type

Description

None

Message ID : USR1329E**Severity**

Error

Long Form

The operation cannot be performed out side of the user's domain.

Short Form

No short form is provided for this message type

Description

None

Message ID : USR1330E**Severity**

Error

Message ID : USR1328E

Long Form

Read-Only user cannot be {0} for user type {1}

Short Form

No short form is provided for this message type

Description

None

Message ID : USR1332E

Severity

Error

Long Form

Read-Only user {0} cannot be the first administrator on domain {1}

Short Form

No short form is provided for this message type

Description

None

Message ID : USR1333E**Severity**

Error

Long Form

A security administrator cannot be assigned to an unassigned domain.

Short Form

No short form is provided for this message type

Description

None

Message ID : USR1351E**Severity**

Error

Message ID : USR1332E

Long Form

LDAP User "{0}" failed to login from client with IP address {1}. Reason: {2}

Short Form

LDAP user login failed from client with IP address {5}

Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
showStr	reason	Text	Code specifying reason for allowing access, if any

Description

None

Message ID : USR1385E

Severity

Error

Message ID : USR1351E

1755

Long Form

The item is in a domain that the current user does not have access to.

Short Form

No short form is provided for this message type

Description

None

Message ID : USR1386E

Severity

Error

Long Form

Run Cleanup Replication for each configured failover server and try Restore again

Short Form

No short form is provided for this message type

Description

None

Message ID : USR1387E**Severity**

Error

Long Form

No attached file found

Short Form

No short form is provided for this message type

Description

None

Message ID : USR1388E**Severity**

Error

Message ID : USR1386E

Long Form

Invalid user ID(s) for the domain: [{0}]

Short Form

No short form is provided for this message type

Description

None

Message ID : USR1389E

Severity

Error

Long Form

User with property "{0}" equal "{1}" not found in the domain

Short Form

No short form is provided for this message type

Description

None

Message ID : USR1393E

Severity

Error

Long Form

This key share already exists for the domain

Short Form

No short form is provided for this message type

Description

None

Message ID : USR1396E

Severity

Error

Message ID : USR1389E

Long Form

Backup request for {0} is already in process.

Short Form

No short form is provided for this message type

Description

None

Message ID : USR1397E

Severity

Error

Long Form

Domain {0} is being restored at this time.

Short Form

No short form is provided for this message type

Description

None

Message ID : USR1398E**Severity**

Error

Long Form

System restore is in progress.

Short Form

No short form is provided for this message type

Description

None

Message ID : USR1399E**Severity**

Error

Message ID : USR1397E

Long Form

Wrapper key does not exist. Please create or import a wrapper key first.

Short Form

No short form is provided for this message type

Description

None

Message ID : USR1400E

Severity

Error

Long Form

Minimum shares can not exceed total number of shares

Short Form

No short form is provided for this message type

Message ID : USR1399E

1762

Description

None

Message ID : USR1401E

Severity

Error

Long Form

Minimum number of shares must be greater than 0

Short Form

No short form is provided for this message type

Description

None

Message ID : USR1402E

Severity

Error

Message ID : USR1400E

Long Form

Total number of shares must be greater than 0

Short Form

No short form is provided for this message type

Description

None

Message ID : USR1403E

Severity

Error

Long Form

Total number of shares cannot be greater than 10

Short Form

No short form is provided for this message type

Message ID : USR1402E

Description

None

Message ID : USR1404E**Severity**

Error

Long Form

No users specified

Short Form

No short form is provided for this message type

Description

None

Message ID : USR1405E**Severity**

Error

Message ID : USR1403E

Long Form

Number of custodians does not match number of users

Short Form

No short form is provided for this message type

Description

None

Message ID : USR1406E

Severity

Error

Long Form

Size of wrapper key description is greater than 256 chars

Short Form

No short form is provided for this message type

Description

None

Message ID : USR1408E**Severity**

Error

Long Form

Decryption failed while restoring. Please check if the correct wrapper key is being used.

Short Form

No short form is provided for this message type

Description

None

Message ID : USR1411E**Severity**

Error

Message ID : USR1406E

Long Form

IP address is invalid

Short Form

No short form is provided for this message type

Description

None

Message ID : USR1412E

Severity

Error

Long Form

IP4 address is invalid

Short Form

No short form is provided for this message type

Description

None

Message ID : USR1413E**Severity**

Error

Long Form

IP6 address is invalid

Short Form

No short form is provided for this message type

Description

None

Message ID : USR1414E**Severity**

Error

Message ID : USR1412E

Long Form

Problem in converting key share(s) to key. Key share(s) number or value(s) may not be correct.

Short Form

No short form is provided for this message type

Description

None

Message ID : USR1415E

Severity

Error

Long Form

Problem in converting key share(s) to key. A key share value is not correct.

Short Form

No short form is provided for this message type

Description

None

Message ID : USR1416E**Severity**

Error

Long Form

Registration Shared Secret length must be at least {0} characters.

Short Form

No short form is provided for this message type

Description

None

Message ID : USR1417E**Severity**

Error

Message ID : USR1415E

Long Form

Invalid system backup file

Short Form

No short form is provided for this message type

Description

None

Message ID : USR1418E

Severity

Error

Long Form

Invalid domain backup file

Short Form

No short form is provided for this message type

Description

None

Message ID : USR1419E

Severity

Error

Long Form

Invalid key share input

Short Form

No short form is provided for this message type

Description

None

Message ID : USR1420E

Severity

Error

Message ID : USR1418E

Long Form

Invalid hostname, or ip address, or port

Short Form

No short form is provided for this message type

Description

None

Message ID : USR1421E

Severity

Error

Long Form

Auto backup is not set up

Short Form

No short form is provided for this message type

Description

None

Message ID : USR1422E

Severity

Error

Long Form

Invalid certificate in file

Short Form

No short form is provided for this message type

Description

None

Message ID : USR1424E

Severity

Error

Message ID : USR1421E

Long Form

Unable to connect to {0}

Short Form

No short form is provided for this message type

Description

None

Message ID : USR1425E

Severity

Error

Long Form

SSH connection not set up properly

Short Form

No short form is provided for this message type

Description

None

Message ID : USR1426E

Severity

Error

Long Form

The identity does not have access to the key.

Short Form

No short form is provided for this message type

Description

None

Message ID : USR1427E

Severity

Error

Message ID : USR1425E

Long Form

Domain role is required for selected administrator.

Short Form

No short form is provided for this message type

Description

None

Message ID : USR1428E

Severity

Error

Long Form

Domain role is not compatible for selected administrator.

Short Form

No short form is provided for this message type

Description

None

Message ID : USR1429E

Severity

Error

Long Form

Host role also requires selection of Challenge and Response role.

Short Form

No short form is provided for this message type

Description

None

Message ID : USR1430E

Severity

Error

Message ID : USR1428E

Long Form

Domain administrator cannot have any other roles than domain.

Short Form

No short form is provided for this message type

Description

None

Message ID : USR1431E

Severity

Error

Long Form

Cannot assign role for selected administrator.

Short Form

No short form is provided for this message type

Description

None

Message ID : USR1432E**Severity**

Error

Long Form

The selected administrator must have at least one role.

Short Form

No short form is provided for this message type

Description

None

Message ID : USR1433E**Severity**

Error

Message ID : USR1431E

Long Form

The administrator description cannot be updated.

Short Form

No short form is provided for this message type

Description

None

Message ID : USR1622E

Severity

Error

Long Form

{0} length cannot exceed {1} characters.

Short Form

No short form is provided for this message type

Description

None

Message ID : USR1650E**Severity**

Error

Long Form

"{0}" is an invalid host name or ip address. FQDN size cannot be greater than {1} and local host names cannot be greater than {2}

Short Form

No short form is provided for this message type

Description

None

Message ID : USR1671E**Severity**

Error

Message ID : USR1622E

Long Form

"Restore file has no data."

Short Form

No short form is provided for this message type

Description

None

Message ID : USR1672E

Severity

Error

Long Form

"Restore process for the system or the specific domain is already in progress."

Short Form

No short form is provided for this message type

Description

None

Message ID : USR1673E

Severity

Error

Long Form

"Restore process with id {0} not found"

Short Form

No short form is provided for this message type

Description

None

Message ID : USR1707E

Severity

Error

Message ID : USR1672E

Long Form

Smart card login is not globally enabled, so individual smart card user cannot be created.

Short Form

No short form is provided for this message type

Description

None

Message ID : USR1708E

Severity

Error

Long Form

At least one smart card user mapping criteria must be selected.

Short Form

No short form is provided for this message type

Description

None

Message ID : USR1710E

Severity

Error

Long Form

Smart card login is enabled for user "{0}", so username/password login is not allowed. Disable smart card login for this user if username/password login is needed.

Short Form

No short form is provided for this message type

Description

None

Message ID : USR1711E

Severity

Error

Long Form

Client certificate with subject DN "{0}" cannot be mapped to any user.

Short Form

No short form is provided for this message type

Description

None

Message ID : USR1712E

Severity

Error

Long Form

Client certificate with subject DN "{0}" is mapped to more than one user: {1}.

Short Form

No short form is provided for this message type

Description

None

Message ID : USR1713E

Severity

Error

Long Form

Smart card login is not enabled for user "{0}". Remove the smart card from the reader to login.

Short Form

No short form is provided for this message type

Description

None

Message ID : USR1714E

Severity

Error

Long Form

User "{0}" provided an invalid client certificate for LDAP authentication.

Short Form

No short form is provided for this message type

Description

None

Message ID : USR1715E

Severity

Error

Long Form

User "{0}" provided an invalid client certificate.

Short Form

No short form is provided for this message type

Description

None

Message ID : USR1716E

Severity

Error

Long Form

Remove the invalid smart card from the reader, restart the web browser and login again.

Short Form

No short form is provided for this message type

Description

None

Message ID : USR1717E

Severity

Error

Long Form

The user logged in using a username and password that is different from the owner of the smart card certificate.

Short Form

No short form is provided for this message type

Description

None

Message ID : USR1719E

Severity

Error

Long Form

Smart card login configuration is not enabled

Short Form

No short form is provided for this message type

Description

None

Message ID : USR1721E

Severity

Error

Long Form

To load KMIP certificate for a host the host needs to have "Registration Allowed" & "Communication Enabled".

Short Form

No short form is provided for this message type

Description

None

Message ID : USR1722E

Severity

Error

Long Form

downloaded file has zero size.

Short Form

No short form is provided for this message type

Description

None

Message ID : USR1729E

Severity

Error

Long Form

Use a number between {0} and 10 for "Minimum Custodians Needed"

Short Form

No short form is provided for this message type

Description

None

Message ID : USR1730E

Severity

Error

Long Form

Use a number between {0} and 10 for "Total number of Custodians"

Short Form

No short form is provided for this message type

Description

None

Message ID : USR1836E

Severity

Error

Long Form

Error while updating "Syslog Queue Size" configuration.

Short Form

No short form is provided for this message type

Description

None

Message ID : USR1838E

Severity

Error

Long Form

User "{0}" is found in {1} different LDAP servers.

Short Form

No short form is provided for this message type

Description

None

Message ID : USR1839E

Severity

Error

Long Form

User "{0}" belongs to {1} different LDAP groups that have been imported into DSM.

Short Form

No short form is provided for this message type

Description

None

Message ID : USR1838E

1797

Message ID : USR1840E

Severity

Error

Long Form

User "{0}" is not a member of the given LDAP group "{1}" or the group has not been imported into DSM.

Short Form

No short form is provided for this message type

Description

None

Message ID : USR1843E

Severity

Error

Long Form

A smart card enabled administrator cannot be created for a restricted domain.

Short Form

No short form is provided for this message type

Description

None

Logger USR: Information

Message ID : USR0631I

Severity

Information

Long Form

User "{0}" logged in from client with IP address {1}.

Short Form

user logged in

Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name

Description

None

Message ID : USR1277I

Severity

Information

Long Form

User {0} logged out from client with IP address {1}.

Short Form

user logged out

Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name

Description

None

Message ID : USR1278I

Severity

Information

Long Form

User {0} logged out from client with IP address {1} due to inactivity.

Short Form

user logged out due to inactivity

Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name

Description

None

Message ID : USR1330I

Severity

Information

Message ID : USR1278I

Long Form

This version of the product only allows you to create one domain. Please contact Vormetric for licensing information.

Short Form

No short form is provided for this message type

Description

None

Message ID : USR1331I

Severity

Information

Long Form

Maximum number of domains allowed by the license have been created. No more domains can be created.

Short Form

No short form is provided for this message type

Message ID : USR1330I

1803

Description

None

Logger USR: Warnings

Message ID : USR1615W

Severity

Warning

Long Form

User {0} already logged in from client with IP address {1}.

Short Form

User already logged in

Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name

Description

None

Message ID : USR1709W

Severity

Warning

Long Form

Smart card login is enabled for user "{0}", but there is no user certificate on file.

Short Form

No short form is provided for this message type

Description

None

Logger VAD: Errors

Message ID : VAD4642E

Severity

Error

Long Form

{0}: {1} Failed to establish communication to Key Manager; return code={2}.

Short Form

Failed to establish communication to key manager

Parameters

Label	CEF Label	Type	Usage
func	vds_func	Text	A function name
act	act	Text	Action being requested or performed
ecode	cn1	Numeric	An error code

Description

None

Logger VAD: Information

Message ID : VAD4641I

Severity

Information

Long Form

{0}: {1} Successful communication to Key Manager; time= {2}.

Short Form

Successful communication to key manager

Parameters

Label	CEF Label	Type	Usage
func	vds_func	Text	A function name
act	act	Text	Action being requested or performed
etime	end	Text	An end time stamp

Description

None

Logger VAD: Warnings

Message ID : VAD4643W

Severity

Warning

Long Form

{0}: {1}.

Short Form

Tag: Fault

Parameters

Label	CEF Label	Type	Usage
showStr	reason	Text	Code specifying reason for allowing access, if any
detail	vds_detail	Text	Fault detail

Description

None

Logger VMD: Errors

Message ID : VMD3203E

Severity

Error

Long Form

LDT: Live data transformation pause request from "{0}" failed

Short Form

LDT pause failed

Parameters

Label	CEF Label	Type	Usage
shost	shost	Text	Source host name

Description

None

Message ID : VMD3204E

Severity

Error

Long Form

LDT: Live data transformation resume request from "{0}" failed

Short Form

LDT resume failed

Parameters

Label	CEF Label	Type	Usage
shost	shost	Text	Source host name

Description

None

Message ID : VMD3503E

Severity

Error

Long Form

ReadBioPublicKey Bio_new failed {0}

Short Form

No short form is provided for this message type

Description

None

Message ID : VMD3507E

Severity

Error

Long Form

PEM_read_X509 failed

Short Form

No short form is provided for this message type

Description

None

Message ID : VMD3509E

Severity

Error

Long Form

X509_extract_key failed

Short Form

No short form is provided for this message type

Description

None

Message ID : VMD3510E

Severity

Error

Long Form

vm_generate_certificate: mkcert RSA_generate_key failed

Short Form

No short form is provided for this message type

Description

None

Message ID : VMD3514E

Severity

Error

Long Form

uname: bad machine name len {0}

Short Form

No short form is provided for this message type

Description

None

Message ID : VMD3517E

Severity

Error

Long Form

ReadBioPublicKey X509_extract_key failed {0}

Short Form

No short form is provided for this message type

Description

None

Message ID : VMD3514E

1817

Message ID : VMD3520E

Severity

Error

Long Form

set process sid failed

Short Form

Set SID fail

Parameters

No parameters are provided for this message type

Description

None

Message ID : VMD3525E

Severity

Error

Long Form

ReadBioX509cert Bio_read_filename failed {0}

Short Form

No short form is provided for this message type

Description

None

Message ID : VMD3527E

Severity

Error

Long Form

PEM_read_PrivateKey {0} read

Short Form

No short form is provided for this message type

Message ID : VMD3525E

Description

None

Message ID : VMD3533E**Severity**

Error

Long Form

ReadBioPublicKey failed

Short Form

No short form is provided for this message type

Description

None

Message ID : VMD3544E**Severity**

Error

Message ID : VMD3527E

Long Form

The VMD failed to become a daemon.

Short Form

VMD daemonize fail

Parameters

No parameters are provided for this message type

Description

None

Message ID : VMD3546E

Severity

Error

Long Form

Can't get NIS domain: {0}

Short Form

No short form is provided for this message type

Description

None

Message ID : VMD3550E

Severity

Error

Long Form

ReadBioPrivateKey BIO_new failed {0}

Short Form

No short form is provided for this message type

Description

None

Message ID : VMD3559E

Severity

Error

Long Form

ReadBioPublicKey PEM_read_bio_X509 failed {0}

Short Form

No short form is provided for this message type

Description

None

Message ID : VMD3563E

Severity

Error

Long Form

File {0} open failed ({1})

Short Form

File open error

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file
ecode	cn1	Numeric	An error code

Description

None

Message ID : VMD3572E

Severity

Error

Long Form

ReadBioPrivateKey PEM_read_bio_RSAPrivateKey failed {0}

Message ID : VMD3563E

1824

Short Form

No short form is provided for this message type

Description

None

Message ID : VMD3578E

Severity

Error

Long Form

WriteBioPublicKey PEM_write_bio_X509 failed {0}

Short Form

No short form is provided for this message type

Description

None

Message ID : VMD3572E

Message ID : VMD3581E

Severity

Error

Long Form

WriteBioPrivateKey PEM_write_bio_RSAPrivateKey failed {0}

Short Form

No short form is provided for this message type

Description

None

Message ID : VMD3596E

Severity

Error

Long Form

vm_generate_certificate: Error initializing openssl random number generator

Short Form

No short form is provided for this message type

Description

None

Message ID : VMD3597E

Severity

Error

Long Form

setmntent({0}, r) failed {1}({2})

Short Form

setmntent error

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file
showStr	reason	Text	Code specifying reason for allowing access, if any

Message ID : VMD3596E

Label	CEF Label	Type	Usage
ecode	cn1	Numeric	An error code

Description

None

Message ID : VMD3605E

Severity

Error

Long Form

sysinfo failed for uname errno {0} : {1}

Short Form

No short form is provided for this message type

Description

None

Message ID : VMD3607E

Severity

Error

Long Form

WriteBioPublicKey Bio_new failed {0}

Short Form

No short form is provided for this message type

Description

None

Message ID : VMD3611E

Severity

Error

Long Form

ReadBioPrivateKey BIO_read_filename failed {0}

Short Form

No short form is provided for this message type

Description

None

Message ID : VMD3612E

Severity

Error

Long Form

{0}: check_mount({1}, {2}) malloc({3}) failed {4}

Short Form

No memory

Parameters

No parameters are provided for this message type

Description

None

Message ID : VMD3616E

Severity

Error

Long Form

sysinfo failed for SI_HW_SERIAL errno[{}][{}]

Short Form

No short form is provided for this message type

Description

None

Message ID : VMD3617E

Severity

Error

Message ID : VMD3612E

Long Form

Failed to protect process {0}.

Short Form

Cannot protect process

Parameters

Label	CEF Label	Type	Usage
pid	dvcpid	Numeric	Numeric process ID

Description

None

Message ID : VMD3628E

Severity

Error

Long Form

WriteBioPrivateKey BIO_write_filename failed {0}

Message ID : VMD3617E

Short Form

No short form is provided for this message type

Description

None

Message ID : VMD3629E

Severity

Error

Long Form

WriteBioPublicKey BIO_write_filename failed {0}

Short Form

No short form is provided for this message type

Description

None

Message ID : VMD3633E

Severity

Error

Long Form

ReadBioX509cert PEM_read_bio_X509 failed {0}

Short Form

No short form is provided for this message type

Description

None

Message ID : VMD3644E

Severity

Error

Long Form

NIS get group error: {0}

Short Form

No short form is provided for this message type

Description

None

Message ID : VMD3645E

Severity

Error

Long Form

{0}: check_mount({1}, {2}) realloc({3}) failed {4}

Short Form

No memory

Parameters

No parameters are provided for this message type

Description

None

Message ID : VMD3651E

Severity

Error

Long Form

check_mount: mnttab open failed {0}

Short Form

Mnttab open error

Parameters

Label	CEF Label	Type	Usage
ecode	cn1	Numeric	An error code

Description

None

Message ID : VMD3645E

Message ID : VMD3655E

Severity

Error

Long Form

vm_generate_certificate: mkcert EVP_PKEY_new failed

Short Form

No short form is provided for this message type

Description

None

Message ID : VMD3665E

Severity

Error

Long Form

WriteBioPrivateKey BIO_new failed {0}

Short Form

No short form is provided for this message type

Description

None

Message ID : VMD3666E

Severity

Error

Long Form

ReadBioPrivateKey failed

Short Form

No short form is provided for this message type

Description

None

Message ID : VMD3667E

Severity

Error

Long Form

Error: can't load public key

Short Form

No short form is provided for this message type

Description

None

Message ID : VMD3674E

Severity

Error

Long Form

Failed to alloc mem for Host Key

Message ID : VMD3667E

Short Form

No short form is provided for this message type

Description

None

Message ID : VMD3676E

Severity

Error

Long Form

ReadBioX509cert Bio_new failed {0}

Short Form

No short form is provided for this message type

Description

None

Message ID : VMD3681E

Severity

Error

Long Form

Failed to open {0}

Short Form

No short form is provided for this message type

Description

None

Message ID : VMD3683E

Severity

Error

Long Form

TEST HOST key failed {0}

Message ID : VMD3681E

Short Form

No short form is provided for this message type

Description

None

Message ID : VMD3685E

Severity

Error

Long Form

ReadPrivateKey failed

Short Form

No short form is provided for this message type

Description

None

Message ID : VMD3683E

Message ID : VMD3686E

Severity

Error

Long Form

SET machine id failed {0}

Short Form

No short form is provided for this message type

Description

None

Message ID : VMD3689E

Severity

Error

Long Form

X509 certificate file {0} open failed

Short Form

No short form is provided for this message type

Description

None

Message ID : VMD3697E

Severity

Error

Long Form

vm_generate_certificate: mkcert failed

Short Form

No short form is provided for this message type

Description

None

Message ID : VMD3689E

Message ID : VMD3700E

Severity

Error

Long Form

Unable to create or write to file {0} as part of a policy update. Error code {1}.

Short Form

Policy update error

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file
ecode	cn1	Numeric	An error code

Description

Verify that the secfsd process is running; if not, restart it. If sesfsd is running, please call Vormetric support for assistance.

Message ID : VMD3702E

Severity

Error

Long Form

NIS get passwd error: {0}

Short Form

No short form is provided for this message type

Description

None

Message ID : VMD3707E

Severity

Error

Long Form

vm_generate_certificate: mkcert EVP_PKEY_assign_RSA failed

Short Form

No short form is provided for this message type

Description

None

Message ID : VMD3713E

Severity

Error

Long Form

vm_get_pubkey_from_file: Read key file {0} failed

Short Form

No short form is provided for this message type

Description

None

Message ID : VMD3707E

1847

Message ID : VMD3718E

Severity

Error

Long Form

vm_get_privkey_from_file: Read key file {0} failed

Short Form

No short form is provided for this message type

Description

None

Message ID : VMD3723E

Severity

Error

Long Form

ReadBioPublicKey Bio_read_filename failed {0}

Short Form

No short form is provided for this message type

Description

None

Message ID : VMD3724E

Severity

Error

Long Form

Private Key file {0} open failed

Short Form

No short form is provided for this message type

Description

None

Message ID : VMD3723E

Message ID : VMD3726E

Severity

Error

Long Form

mount_sec: {0} mount failed {1}

Short Form

No short form is provided for this message type

Description

None

Message ID : VMD3730E

Severity

Error

Long Form

sysinfo: failed for SI_HW_SERIAL.

Short Form

No short form is provided for this message type

Description

None

Message ID : VMD3734E

Severity

Error

Long Form

sysinfo failed for SI_SYSNAME errno {0}

Short Form

No short form is provided for this message type

Description

None

Message ID : VMD3736E

Severity

Error

Long Form

hpux_sysinfo: invalid buffer length

Short Form

No short form is provided for this message type

Description

None

Message ID : VMD3747E

Severity

Error

Long Form

can not write to file={0}

Short Form

No short form is provided for this message type

Description

None

Message ID : VMD3748E

Severity

Error

Long Form

Failed to read Host Private Key from file {0}

Short Form

No short form is provided for this message type

Description

None

Message ID : VMD3750E

Severity

Error

Long Form

uname failed! errno[{}][{}]

Short Form

No short form is provided for this message type

Description

None

Message ID : VMD3758E

Severity

Error

Long Form

{0}: {1}

Short Form

No short form is provided for this message type

Description

None

Message ID : VMD3759E

Severity

Error

Long Form

write() ssl error {0}

Short Form

No short form is provided for this message type

Description

None

Message ID : VMD3760E

Severity

Error

Long Form

Server does not support required soap operation: {0}

Short Form

No short form is provided for this message type

Description

None

Message ID : VMD3779E

Severity

Error

Long Form

Unable to create a signature for file {0}; error code {1}.

Short Form

Sig creation error

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file
ecode	cn1	Numeric	An error code

Description

None

Message ID : VMD3780E

Severity

Error

Long Form

Unable to encrypt file {0} with the session key; error code {1}.

Message ID : VMD3779E

1857

Short Form

File encrypt error

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file
ecode	cn1	Numeric	An error code

Description

None

Message ID : VMD3782E

Severity

Error

Long Form

A new security configuration was received, but we failed to implement it. The current security configuration will continue to be used.

Short Form

Config update fail

Parameters

No parameters are provided for this message type

Description

An error occurred while attempting to process a policy push from a Security Server. Details of the failure were logged in the preceding message.

Message ID : VMD3784E

Severity

Error

Long Form

Kernel component failed to provide initialization information to VMD.

Short Form

No config from kernel

Parameters

No parameters are provided for this message type

Description

None

Message ID : VMD3786E

Severity

Error

Long Form

Host file browsing for {0} failed.

Short Form

Host browse fail

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Message ID : VMD3784E

1860

Description

None

Message ID : VMD3787E

Severity

Error

Long Form

Unable to get status from kernel component. Error code {0}.

Short Form

Kernel config fetch error

Parameters

Label	CEF Label	Type	Usage
ecode	cn1	Numeric	An error code

Description

None

Message ID : VMD3786E

Message ID : VMD3788E

Severity

Error

Long Form

Unable to send data to kernel component. Error code {0}.

Short Form

Kernel config send error

Parameters

Label	CEF Label	Type	Usage
ecode	cn1	Numeric	An error code

Description

None

Message ID : VMD3789E

Severity

Error

Long Form

Unable to receive data from kernel component. Error code {0}.

Short Form

No short form is provided for this message type

Description

None

Message ID : VMD3790E

Severity

Error

Long Form

Kernel component did not confirm host-delete operation.

Short Form

No host-delete ACK

Parameters

No parameters are provided for this message type

Description

None

Message ID : VMD3792E

Severity

Error

Long Form

Unable to write authorized file information to disk. Error code {0}.

Short Form

Write auth file error

Parameters

Label	CEF Label	Type	Usage
ecode	cn1	Numeric	An error code

Description

None

Message ID : VMD3795E

Severity

Error

Long Form

Query security config failed.

Short Form

Query config fail

Parameters

No parameters are provided for this message type

Message ID : VMD3792E

1865

Description

None

Message ID : VMD3796E

Severity

Error

Long Form

Kernel component reports failure on host-delete operation.

Short Form

Host delete fail

Parameters

No parameters are provided for this message type

Description

None

Message ID : VMD3795E

1866

Message ID : VMD3799E

Severity

Error

Long Form

Delete host operation failed.

Short Form

No short form is provided for this message type

Description

None

Message ID : VMD3801E

Severity

Error

Long Form

Cannot update service status. Error = {0}

Short Form

Service update error

Parameters

Label	CEF Label	Type	Usage
ecode	cn1	Numeric	An error code

Description

None

Message ID : VMD3802E

Severity

Error

Long Form

Cannot set service status to stopped. Error = {0}

Short Form

Service stop error

Message ID : VMD3801E

1868

Parameters

Label	CEF Label	Type	Usage
ecode	cn1	Numeric	An error code

Description

None

Message ID : VMD3807E

Severity

Error

Long Form

Cannot register service handler. Error = {0}

Short Form

Register server error

Parameters

Label	CEF Label	Type	Usage
ecode	cn1	Numeric	An error code

Message ID : VMD3802E

Label	CEF Label	Type	Usage

Description

None

Message ID : VMD3809E

Severity

Error

Long Form

Cannot start service dispatcher. Error = {0}

Short Form

Start service error

Parameters

Label	CEF Label	Type	Usage
ecode	cn1	Numeric	An error code

Description

None

Message ID : VMD3811E

Severity

Error

Long Form

User {0} in domain {1} failed to connect to network path {2}. Error code {3}.

Short Form

Net connect error

Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
domain	dntdom	Text	A domain name (policy, network, users, etc)
url	request	Text	A uniform resource location
ecode	cn1	Numeric	An error code

Message ID : VMD3809E

1871

Description

None

Message ID : VMD3812E

Severity

Error

Long Form

Failed to enumerate network path {0}. Error code {1}.

Short Form

Net enumeration error

Parameters

Label	CEF Label	Type	Usage
url	request	Text	A uniform resource location
ecode	cn1	Numeric	An error code

Description

None

Message ID : VMD3816E

Severity

Error

Long Form

Failed to initialize the signature request {0}

Short Form

Init sig req fail

Parameters

Label	CEF Label	Type	Usage
showStr	reason	Text	Code specifying reason for allowing access, if any

Description

None

Message ID : VMD3812E

Message ID : VMD3819E

Severity

Error

Long Form

Failed to generate the file list for the signature request {0}

Short Form

Sig file list fail

Parameters

Label	CEF Label	Type	Usage
showStr	reason	Text	Code specifying reason for allowing access, if any

Description

None

Message ID : VMD3822E

Severity

Error

Long Form

Failed to generate the signatures for the signature request {0}

Short Form

Sig gen fail

Parameters

Label	CEF Label	Type	Usage
showStr	reason	Text	Code specifying reason for allowing access, if any

Description

None

Message ID : VMD3828E

Severity

Error

Message ID : VMD3822E

Long Form

Failed the signature request {0}

Short Form

Sig req fail

Parameters

Label	CEF Label	Type	Usage
showStr	reason	Text	Code specifying reason for allowing access, if any

Description

None

Message ID : VMD3830E

Severity

Error

Long Form

Failed to read the file list for the signature request {0}, error code {1}

Message ID : VMD3828E

Short Form

Sig file list read error

Parameters

Label	CEF Label	Type	Usage
showStr	reason	Text	Code specifying reason for allowing access, if any
ecode	cn1	Numeric	An error code

Description

None

Message ID : VMD3831E

Severity

Error

Long Form

Failed to write the file list for the signature request {0}, error code {1}

Message ID : VMD3830E

1877

Short Form

Sig file list write error

Parameters

Label	CEF Label	Type	Usage
showStr	reason	Text	Code specifying reason for allowing access, if any
ecode	cn1	Numeric	An error code

Description

None

Message ID : VMD3833E

Severity

Error

Long Form

Failed to create the signature disk object

Message ID : VMD3831E

1878

Short Form

Create sig disk object fail

Parameters

No parameters are provided for this message type

Description

None

Message ID : VMD3834E

Severity

Error

Long Form

Failed to add the signature {0} and name {1} into the signature disk object

Short Form

Add sig object error

Parameters

Label	CEF Label	Type	Usage
hex	vds_hex	Text	A hex string (e.g. a signature)
filePath	filePath	Text	Full path to file

Description

None

Message ID : VMD3835E

Severity

Error

Long Form

Failed to write the signature disk file

Short Form

Write sig object fail

Message ID : VMD3834E

1880

Parameters

No parameters are provided for this message type

Description

None

Message ID : VMD3837E

Severity

Error

Long Form

Failed to write the signature disk file header

Short Form

Sig write header fail

Parameters

No parameters are provided for this message type

Message ID : VMD3835E

Description

None

Message ID : VMD3838E

Severity

Error

Long Form

Failed to read the signature disk file header

Short Form

Sig read hreader fail

Parameters

No parameters are provided for this message type

Description

None

Message ID : VMD3837E

1882

Message ID : VMD3840E

Severity

Error

Long Form

Failed to push a new signature database to the kernel

Short Form

Sig push to kernel fail

Parameters

No parameters are provided for this message type

Description

None

Message ID : VMD3843E

Severity

Error

Long Form

User browsing for {0} failed.

Short Form

User browse fail

Parameters

Label	CEF Label	Type	Usage
domain	dntdom	Text	A domain name (policy, network, users, etc)

Description

None

Message ID : VMD3844E

Severity

Error

Long Form

Failed to bind to {0}. Error code {1}.

Message ID : VMD3843E

Short Form

Domain bind error

Parameters

Label	CEF Label	Type	Usage
domain	dntdom	Text	A domain name (policy, network, users, etc)
ecode	cn1	Numeric	An error code

Description

None

Message ID : VMD3845E

Severity

Error

Long Form

Failed to query the domain {0} by {1}. Error {2}: {3}.

Short Form

NIS query error

Parameters

Label	CEF Label	Type	Usage
domain	dntdom	Text	A domain name (policy, network, users, etc)
effect	vds_effect	Text	Policy effect
ecode	cnl	Numeric	An error code
showStr	reason	Text	Code specifying reason for allowing access, if any

Description

None

Message ID : VMD3846E

Severity

Error

Long Form

Failed to query the group {0} in the domain {1} by {2}. Error {3}: {4}.

Message ID : VMD3845E

1886

Short Form

NIS group query error

Parameters

Label	CEF Label	Type	Usage
group	vds_group	Text	Group name
domain	dntdom	Text	A domain name (policy, network, users, etc)
effect	vds_effect	Text	Policy effect
ecode	cn1	Numeric	An error code
showStr	reason	Text	Code specifying reason for allowing access, if any

Description

None

Message ID : VMD3848E

Severity

Error

Message ID : VMD3846E

1887

Long Form

Domain browsing failed.

Short Form

Domain browse fail

Parameters

No parameters are provided for this message type

Description

None

Message ID : VMD3849E

Severity

Error

Long Form

Error getting common name: {0}

Short Form

Cannot determine common name

Parameters

Label	CEF Label	Type	Usage
showStr	reason	Text	Code specifying reason for allowing access, if any

Description

None

Message ID : VMD3855E

Severity

Error

Long Form

Failed to send {0} signatures for the signature request {1} to the Key Manager

Short Form

Send sigs error

Message ID : VMD3849E

1889

Parameters

Label	CEF Label	Type	Usage
nsig	vds_nsig	Numeric	The number of signatures generated
showStr	reason	Text	Code specifying reason for allowing access, if any

Description

None

Message ID : VMD3858E

Severity

Error

Long Form

The kernel component was unable to implement the new security configuration

Short Form

New config to kernel fail

Parameters

No parameters are provided for this message type

Description

An error occurred while attempting to apply a policy push from a Security Server.

Message ID : VMD3864E

Severity

Error

Long Form

Unable to parse LDAP URL {0} - error "{1}"

Short Form

Bad LDAP url

Parameters

Label	CEF Label	Type	Usage
url	request	Text	A uniform resource location
showStr	reason	Text	Code specifying reason for allowing access, if any

Message ID : VMD3858E

Label	CEF Label	Type	Usage

Description

None

Message ID : VMD3865E

Severity

Error

Long Form

Unable to query LDAP server {0} - error "{1}"

Short Form

Bad LADP server

Parameters

Label	CEF Label	Type	Usage
url	request	Text	A uniform resource location
showStr	reason	Text	Code specifying reason for allowing access, if any

Message ID : VMD3864E

1892

Description

None

Message ID : VMD3866E

Severity

Error

Long Form

Invalid LDAP posixAccount data returned

Short Form

Invalid LDAP account

Parameters

No parameters are provided for this message type

Description

None

Message ID : VMD3865E

1893

Message ID : VMD3867E

Severity

Error

Long Form

Invalid LDAP posixGroup data returned

Short Form

Invalid LDAP group

Parameters

No parameters are provided for this message type

Description

None

Message ID : VMD3872E

Severity

Error

Message ID : VMD3867E

Long Form

Internal error: bad arguments to kernel component

Short Form

Bad args to kernel

Parameters

No parameters are provided for this message type

Description

An internal error occurred. Please contact Vormetric Support

Message ID : VMD3873E

Severity

Error

Long Form

Internal error: the kernel component does not believe it's talking to the correct VMD

Short Form

Kernel rejecting VMD

Parameters

No parameters are provided for this message type

Description

None

Message ID : VMD3874E

Severity

Error

Long Form

The kernel component is unable to read its private key

Short Form

Kernel priv key fail

Parameters

No parameters are provided for this message type

Description

None

Message ID : VMD3875E

Severity

Error

Long Form

The kernel component unable to obtain its PWD

Short Form

Kernel passwd fail

Parameters

No parameters are provided for this message type

Description

None

Message ID : VMD3876E

Severity

Error

Long Form

The kernel component contains an invalid PWD

Short Form

Kernel passwd bad

Parameters

No parameters are provided for this message type

Description

None

Message ID : VMD3875E

1898

Message ID : VMD3877E

Severity

Error

Long Form

The kernel component was unable to extract the key-encrypting-key

Short Form

Kernel key extract fail

Parameters

No parameters are provided for this message type

Description

None

Message ID : VMD3878E

Severity

Error

Message ID : VMD3877E

Long Form

The kernel component failed to pass internal sanity checks around the key-encrypting-key

Short Form

Kernel key sanity fail

Parameters

No parameters are provided for this message type

Description

None

Message ID : VMD3879E

Severity

Error

Long Form

The kernel component was able to perform all of the crypto operations around the policy push, but was unable to actually apply the new policy configuration

Message ID : VMD3878E

1900

Short Form

Kernel policy apply fail

Parameters

No parameters are provided for this message type

Description

None

Message ID : VMD3888E

Severity

Error

Long Form

Unable to replicate coherent guardpoint info - {0}

Short Form

Unable to replicate coherent GuardPoint info -

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

Description

None

Message ID : VMD3890E

Severity

Error

Long Form

Unable to commit configuration to GPFS cluster

Short Form

Unable to commit configuration to GPFS cluster

Parameters

No parameters are provided for this message type

Message ID : VMD3888E

Description

None

Message ID : VMD3891E

Severity

Error

Long Form

Non-clustered GP {0} not allowed on clustered filesystem

Short Form

Non-clustered GP not allowed on clustered filesystem

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

Description

None

Message ID : VMD3890E

Message ID : VMD3892E

Severity

Error

Long Form

Clustered GP {0} not allowed on non-clustered filesystem

Short Form

Clustered GP not allowed on non-clustered filesystem

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

Description

None

Message ID : VMD3901E

Severity

Error

Long Form

Docker host browsing failed.

Short Form

Docker host browse fail

Parameters

No parameters are provided for this message type

Description

None

Message ID : VMD3903E

Severity

Error

Long Form

Docker host browsing for image {0} failed.

Short Form

Docker host browse fail

Parameters

Label	Type	Usage
dockerid	Text	Docker image or container id

Description

None

Message ID : VMD3905E

Severity

Error

Long Form

Docker image {0} file browsing for {1} failed.

Message ID : VMD3903E

Short Form

Docker image file browse fail

Parameters

Label	CEF Label	Type	Usage
dockerid	dockerid	Text	Docker image or container id
filePath	filePath	Text	Full path to file

Description

None

Message ID : VMD3907E

Severity

Error

Long Form

Docker container {0} file browsing for {1} succeeded.

Short Form

Docker container file browse fail

Parameters

Label	CEF Label	Type	Usage
dockerid	dockerid	Text	Docker image or container id
filePath	filePath	Text	Full path to file

Description

None

Message ID : VMD3909E

Severity

Error

Long Form

User browsing for image {0} with {1} failed.

Short Form

Docker image user browse fail

Parameters

Label	CEF Label	Type	Usage
dockerid	dockerid	Text	Docker image or container id
domain	dntdom	Text	A domain name (policy, network, users, etc)

Description

None

Message ID : VMD3911E

Severity

Error

Long Form

User browsing for container {0} with {1} failed.

Short Form

Docker container user browse fail

Parameters

Label	CEF Label	Type	Usage
dockerid	dockerid	Text	Docker image or container id
domain	dntdom	Text	A domain name (policy, network, users, etc)

Description

None

Message ID : VMD3913E

Severity

Error

Long Form

Domain browsing for image {0} failed.

Message ID : VMD3911E

1910

Short Form

Docker image domain browse fail

Parameters

Label	Type	Usage
dockerid	Text	Docker image or container id

Description

None

Message ID : VMD3915E

Severity

Error

Long Form

Domain browsing for container {0} failed.

Short Form

Docker container domain browse fail

Message ID : VMD3913E

Parameters

Label	Type	Usage
dockerid	Text	Docker image or container id

Description

None

Message ID : VMD3916E

Severity

Error

Long Form

The current docker version "{0} {1}" is not supported.

Short Form

No short form is provided for this message type

Description

None

Message ID : VMD3915E

Message ID : VMD3917E

Severity

Error

Long Form

Failed to connect to the Docker service at {0}. Please make sure the Docker service is up.

Short Form

Failed to connect to Docker

Parameters

Label	CEF Label	Type	Usage
url	request	Text	A uniform resource location

Description

None

Message ID : VMD3918E

Severity

Error

Long Form

An unauthorized attempt to update the authentication signature for file {0} has been prevented

Short Form

Unauthorized signature change

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : VMD3922E

Severity

Error

Message ID : VMD3918E

Long Form

Internal error: unable to determine {0}.

Short Form

Unable to determine

Parameters

Label	CEF Label	Type	Usage
showStr	reason	Text	Code specifying reason for allowing access, if any

Description

None

Message ID : VMD3923E

Severity

Error

Long Form

Error from data governance module: {0}

Message ID : VMD3922E

Short Form

DG error

Parameters

No parameters are provided for this message type

Description

None

Message ID : VMD4245E

Severity

Error

Long Form

Key conversion failure when attempting to upgrade to fips-approved private key file format.

Short Form

Key conv fail

Parameters

No parameters are provided for this message type

Description

None

Message ID : VMD4594E

Severity

Error

Long Form

Failed to strengthen priority of the vmd, may face scheduling problems

Short Form

Cannot raise priority

Parameters

No parameters are provided for this message type

Description

None

Message ID : VMD4606E

Severity

Error

Long Form

vm_read_file: fstat failed {0}

Short Form

Stat error

Parameters

Label	CEF Label	Type	Usage
ecode	cn1	Numeric	An error code

Description

None

Message ID : VMD4594E

Message ID : VMD4607E

Severity

Error

Long Form

vm_read_file: fopen failed for {0} errno {1}

Short Form

Open error

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file
ecode	cn1	Numeric	An error code

Description

None

Message ID : VMD4608E

Severity

Error

Long Form

vm_read_file: malloc for size {0} failed {1}

Short Form

Out of memory

Parameters

Label	CEF Label	Type	Usage
slen	in	Numeric	Input byte count or length
ecode	cn1	Numeric	An error code

Description

None

Message ID : VMD4609E

Severity

Error

Long Form

vm_read_file: read() failed for {0}

Short Form

Read error

Parameters

Label	CEF Label	Type	Usage
ecode	cn1	Numeric	An error code

Description

None

Message ID : VMD4610E

Severity

Error

Long Form

vm_write_file: fopen failed for {0} mode {1} errno {2}

Short Form

File open error

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file
mode	vds_mode	Text	File open mode
ecode	cn1	Numeric	An error code

Description

None

Message ID : VMD4612E

Message ID : VMD4610E

Severity

Error

Long Form

vm_write_file: fwrite() failed error {0}

Short Form

Write error

Parameters

Label	CEF Label	Type	Usage
ecode	cn1	Numeric	An error code

Description

None

Message ID : VMD4617E

Severity

Error

Message ID : VMD4612E

Long Form

The previous message {0} was repeated {1} times

Short Form

Repeat message

Parameters

Label	CEF Label	Type	Usage
msgid	vds_msgid	Text	A unique log message identifier
count	vds_count	Numeric	A generic count value

Description

None

Logger VMD: Fatal errors

Message ID : VMD3767F

Severity

Fatal error

Long Form

No attribute {0} was found in the configuration file located at {1}. Please supply this attribute or re-install the product and try again.

Short Form

Attribute missing

Parameters

Label	CEF Label	Type	Usage
showStr	reason	Text	Code specifying reason for allowing access, if any
filePath	filePath	Text	Full path to file

Description

None

Message ID : VMD3768F

Severity

Fatal error

Long Form

Unable to parse the URL {0}. This attribute is located in the config file at {1}. Please fix the URL or re-install this product.

Short Form

Bad URL in config file

Parameters

Label	CEF Label	Type	Usage
url	request	Text	A uniform resource location
filePath	filePath	Text	Full path to file

Description

None

Message ID : VMD3769F

Severity

Fatal error

Long Form

Internal error: unable to set attribute {0}.

Short Form

Bad attribute

Parameters

Label	CEF Label	Type	Usage
showStr	reason	Text	Code specifying reason for allowing access, if any

Description

None

Message ID : VMD3770F

Severity

Fatal error

Long Form

The VMD failed to establish a communication channel to the Key Manager.

Short Form

Cannot contact server

Parameters

No parameters are provided for this message type

Description

The agent is unable to reach the Security Server. You may see any of the following error messages: COM4583F, COM4633W, VMD3770F, VMD3885I or VMD3886I. You may experience any of the following:

1. Connection to the Security Server is down.
2. The VMD Host has been deleted from the Security Server.
3. The host does not have "Communication Enabled" in the Security Server UI.
4. The VMD's host may be deleted from the Security Server. Run the register_host utility to re-register the VMD with the Security Server.

Message ID : VMD3771F

Severity

Fatal error

Long Form

Logging setup failure. Error code {0}; "{1}"

Short Form

Log setup error

Parameters

Label	CEF Label	Type	Usage
ecode	cn1	Numeric	An error code
showStr	reason	Text	Code specifying reason for allowing access, if any

Description

None

Message ID : VMD3772F

Severity

Fatal error

Long Form

Logging setup failure: VMD logger information not found in Key Manager response.

Short Form

Missing logger info

Parameters

No parameters are provided for this message type

Description

None

Message ID : VMD3797F

Severity

Fatal error

Long Form

The VMD is unable to listen for requests from the Key Manager. Shutting down.

Short Form

Cannot list for server req.

Parameters

No parameters are provided for this message type

Description

None

Message ID : VMD3894F

Severity

Fatal error

Long Form

The server does not support required oneway communications.

Short Form

No short form is provided for this message type

Description

None

Message ID : VMD4595F

Severity

Fatal error

Long Form

The agent could not allocate enough memory. Contact support.

Short Form

Out of memory

Parameters

No parameters are provided for this message type

Description

None

Message ID : VMD4616F

Severity

Fatal error

Long Form

The previous message {0} was repeated {1} times

Short Form

Repeat message

Parameters

Label	CEF Label	Type	Usage
msgid	vds_msgid	Text	A unique log message identifier
count	vds_count	Numeric	A generic count value

Description

None

Logger VMD: Information

Message ID : VMD3201I

Severity

Information

Long Form

LDT: Live data transformation has been paused by "{0}"

Short Form

LDT paused

Parameters

Label	CEF Label	Type	Usage
shost	shost	Text	Source host name

Description

None

Message ID : VMD3202I

Severity

Information

Long Form

LDT: Live data transformation has been resumed by "{0}"

Short Form

LDT resumed

Parameters

Label	CEF Label	Type	Usage
shost	shost	Text	Source host name

Description

None

Message ID : VMD3548I

Severity

Information

Long Form

RSA key verification Failed

Short Form

No short form is provided for this message type

Description

None

Message ID : VMD3558I

Severity

Information

Long Form

RSA key verified

Short Form

No short form is provided for this message type

Description

None

Message ID : VMD3626I

Severity

Information

Long Form

{0} is MOUNTED

Short Form

Mount success

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : VMD3640I

Severity

Information

Long Form

STARTED on {0} PORT {1} VERSION: {2}

Short Form

VMD Startup

Parameters

Label	CEF Label	Type	Usage
osname	cs2	Text	A name identifying the agent operating system
port	spt	Numeric	A socket port number
version	vds_version	Text	Software version string

Description

None

Message ID : VMD3663I

Severity

Information

Long Form

{0} is not mounted

Short Form

Mount fail

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : VMD3640I

Message ID : VMD3773I

Severity

Information

Long Form

The {0} is starting. It was invoked at the command line like this: "{1}"

Short Form

VMD startup

Parameters

Label	CEF Label	Type	Usage
agent	deviceProcessName	Text	The short identifier of the agent software
showStr	reason	Text	Code specifying reason for allowing access, if any

Description

None

Message ID : VMD3778I

Severity

Information

Long Form

The VMD is shutting down.

Short Form

VMD shutdown

Parameters

No parameters are provided for this message type

Description

None

Message ID : VMD3781I

Severity

Information

Long Form

Successfully received and implemented a new security configuration.

Short Form

New Config OK

Parameters

No parameters are provided for this message type

Description

None

Message ID : VMD3785I

Severity

Information

Long Form

Host file browsing for {0} succeeded.

Short Form

Host browse OK

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : VMD3794I

Severity

Information

Long Form

Query security config succeeded.

Short Form

Query config OK

Message ID : VMD3785I

Parameters

No parameters are provided for this message type

Description

None

Message ID : VMD3798I

Severity

Information

Long Form

Delete host operation succeeded.

Short Form

Host delete OK

Parameters

No parameters are provided for this message type

Message ID : VMD3794I

Description

None

Message ID : VMD3800I

Severity

Information

Long Form

RESTARTED SDK Server at PORT {0}.

Short Form

SDK server restart

Parameters

Label	CEF Label	Type	Usage
port	spt	Numeric	A socket port number

Description

None

Message ID : VMD3798I

Message ID : VMD3803I

Severity

Information

Long Form

Shutting down file system service.

Short Form

Service stop

Parameters

No parameters are provided for this message type

Description

None

Message ID : VMD3804I

Severity

Information

Long Form

Stopping file system service...

Short Form

Service shutdown

Parameters

No parameters are provided for this message type

Description

None

Message ID : VMD3814I

Severity

Information

Long Form

Initializing the signature request {0}

Short Form

Init sig req start

Parameters

Label	CEF Label	Type	Usage
showStr	reason	Text	Code specifying reason for allowing access, if any

Description

None

Message ID : VMD3815I

Severity

Information

Long Form

Finished initializing the signature request {0}

Short Form

Init sig req end

Message ID : VMD3814I

Parameters

Label	CEF Label	Type	Usage
showStr	reason	Text	Code specifying reason for allowing access, if any

Description

None

Message ID : VMD3817I

Severity

Information

Long Form

Generating the file list for the signature request {0}

Short Form

Gen sig file list

Parameters

Label	CEF Label	Type	Usage
showStr	reason	Text	Code specifying reason for allowing access, if any

Message ID : VMD3815I

1950

Label	CEF Label	Type	Usage

Description

None

Message ID : VMD3818I

Severity

Information

Long Form

Finished generating the file list for the signature request {0}. Number of files in the list: {1}

Short Form

Sig file list complete

Parameters

Label	CEF Label	Type	Usage
showStr	reason	Text	Code specifying reason for allowing access, if any
nfile	vds_nfile	Numeric	The number of files processed

Message ID : VMD3817I

1951

Description

None

Message ID : VMD3820I

Severity

Information

Long Form

Generating the signatures for the signature request {0}

Short Form

Generating sigs

Parameters

Label	CEF Label	Type	Usage
showStr	reason	Text	Code specifying reason for allowing access, if any

Description

None

Message ID : VMD3818I

Message ID : VMD3821I

Severity

Information

Long Form

Finished generating the signatures for the signature request {0}. Number of processed files: {1}. Number of generated signatures: {2}. Number of failed files: {3}

Short Form

Generated sigs

Parameters

Label	CEF Label	Type	Usage
showStr	reason	Text	Code specifying reason for allowing access, if any
nfile	vds_nfile	Numeric	The number of files processed
nsig	vds_nsig	Numeric	The number of signatures generated
nerror	vds_nerror	Numeric	The number of errors encountered

Description

None

Message ID : VMD3823I

Severity

Information

Long Form

Failed to get the file attributes for {0}, error code {1}, error message: {2}

Short Form

Sig file attr error

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file
ecode	cn1	Numeric	An error code
showStr	reason	Text	Code specifying reason for allowing access, if any

Description

None

Message ID : VMD3825I

Severity

Information

Long Form

Generating the signatures for the signature request {0}, {1} out of {2} files have been processed

Short Form

Sig progress

Parameters

Label	CEF Label	Type	Usage
showStr	reason	Text	Code specifying reason for allowing access, if any
nsig	vds_nsig	Numeric	The number of signatures generated
nfile	vds_nfile	Numeric	The number of files processed

Message ID : VMD3823I

1955

Description

None

Message ID : VMD3827I

Severity

Information

Long Form

Completed the signature request {0} successfully

Short Form

Sig sig req done

Parameters

Label	CEF Label	Type	Usage
showStr	reason	Text	Code specifying reason for allowing access, if any

Description

None

Message ID : VMD3825I

Message ID : VMD3829I

Severity

Information

Long Form

Canceled the signature request {0}

Short Form

Sig req cancelled

Parameters

Label	CEF Label	Type	Usage
showStr	reason	Text	Code specifying reason for allowing access, if any

Description

None

Message ID : VMD3832I

Severity

Information

Long Form

Generating the file list for the signature request {0}, {1} files have been written to the list

Short Form

Sig file generation in progress

Parameters

Label	CEF Label	Type	Usage
showStr	reason	Text	Code specifying reason for allowing access, if any
nfile	vds_nfile	Numeric	The number of files processed

Description

None

Message ID : VMD3836I

Severity

Information

Long Form

Finished writing the signature disk file

Short Form

Sig write complete

Parameters

No parameters are provided for this message type

Description

None

Message ID : VMD3839I

Severity

Information

Long Form

Finished pushing a new signature database to the kernel

Short Form

Sig push to kernel OK

Parameters

No parameters are provided for this message type

Description

None

Message ID : VMD3841I

Severity

Information

Long Form

opendir failed for {0} for the signature request {1}, error code {2}

Short Form

Sig opendir error

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file
showStr	reason	Text	Code specifying reason for allowing access, if any
ecode	cnl	Numeric	An error code

Description

None

Message ID : VMD3842I

Severity

Information

Long Form

User browsing for {0} succeeded.

Message ID : VMD3841I

1961

Short Form

User browse OK

Parameters

Label	CEF Label	Type	Usage
domain	dntdom	Text	A domain name (policy, network, users, etc)

Description

None

Message ID : VMD3847I

Severity

Information

Long Form

Domain browsing succeeded.

Short Form

Domain browse OK

Message ID : VMD3842I

Parameters

No parameters are provided for this message type

Description

None

Message ID : VMD3851I

Severity

Information

Long Form

Canceling the signature request {0}

Short Form

Sig req cancelled

Parameters

Label	CEF Label	Type	Usage
showStr	reason	Text	Code specifying reason for allowing access, if any

Description

None

Message ID : VMD3852I

Severity

Information

Long Form

Querying the status of the signature request {0}

Short Form

Sig req status query

Parameters

Label	CEF Label	Type	Usage
showStr	reason	Text	Code specifying reason for allowing access, if any

Description

None

Message ID : VMD3851I

Message ID : VMD3853I

Severity

Information

Long Form

Sending {0} signatures for the signature request {1} to the Key Manager

Short Form

Sending sigs

Parameters

Label	CEF Label	Type	Usage
nsig	vds_nsig	Numeric	The number of signatures generated
showStr	reason	Text	Code specifying reason for allowing access, if any

Description

None

Message ID : VMD3854I

Severity

Information

Long Form

{0} signatures of the signature request {1} have been sent to the Key Manager

Short Form

Sent sigs

Parameters

Label	CEF Label	Type	Usage
nsig	vds_nsig	Numeric	The number of signatures generated
showStr	reason	Text	Code specifying reason for allowing access, if any

Description

None

Message ID : VMD3856I

Severity

Information

Long Form

The Key Manager canceled the signature data push

Short Form

Send sigs cancelled

Parameters

No parameters are provided for this message type

Description

None

Message ID : VMD3857I

Severity

Information

Long Form

Got the signature data push from the Key Manager. Number of signatures in the push: {0}. Total number of signatures from the Key Manager: {1}

Short Form

Sig push from server

Parameters

Label	CEF Label	Type	Usage
nsig	vds_nsig	Numeric	The number of signatures generated
nfile	vds_nfile	Numeric	The number of files processed

Description

None

Message ID : VMD3859I

Severity

Information

Message ID : VMD3857I

1968

Long Form

Completed the signature request {0} with some failed files

Short Form

Sig reg partially done

Parameters

Label	CEF Label	Type	Usage
showStr	reason	Text	Code specifying reason for allowing access, if any

Description

None

Message ID : VMD3861I

Severity

Information

Long Form

The Key Manager canceled the signature sending for the signature request {0}

Message ID : VMD3859I

Short Form

Sig req cancelled

Parameters

Label	CEF Label	Type	Usage
showStr	reason	Text	Code specifying reason for allowing access, if any

Description

None

Message ID : VMD3862I

Severity

Information

Long Form

Running in FIPS 140-2 mode, using {0}

Short Form

FIPS 140-2 mode

Message ID : VMD3861I

1970

Parameters

Label	CEF Label	Type	Usage
version	vds_version	Text	Software version string

Description

None

Message ID : VMD3863I

Severity

Information

Long Form

Generating the file list for the signature request {0}, {1} files and directories have been scanned

Short Form

Sig scan in progress

Parameters

Label	CEF Label	Type	Usage
showStr	reason	Text	Code specifying reason for allowing access, if any

Message ID : VMD3862I

Label	CEF Label	Type	Usage
nfile	vds_nfile	Numeric	The number of files processed

Description

None

Message ID : VMD3868I

Severity

Information

Long Form

LDAP search of {0}/{1} for {2} returned "{3}"

Short Form

LDAP search error

Parameters

Label	CEF Label	Type	Usage
url	request	Text	A uniform resource location

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file
effect	vds_effect	Text	Policy effect
showStr	reason	Text	Code specifying reason for allowing access, if any

Description

None

Message ID : VMD3870I

Severity

Information

Long Form

Configuration data was supplied by "{0}".

Short Form

Config source

Parameters

Label	CEF Label	Type	Usage
-------	-----------	------	-------

Message ID : VMD3868I

1973

url	request	Text	A uniform resource location
-----	---------	------	-----------------------------

Description

None

Message ID : VMD3880I

Severity

Information

Long Form

The Key Manager was upgraded recently; informing it that this agent is challenge-response aware

Short Form

Try new host password req

Parameters

No parameters are provided for this message type

Description

None

Message ID : VMD3870I

Message ID : VMD3881I

Severity

Information

Long Form

The new certificate set has been activated

Short Form

New certs activated

Parameters

No parameters are provided for this message type

Description

None

Message ID : VMD3883I

Severity

Information

Long Form

Certificates for the {0} agent expire in {1} days

Short Form

Certificate lifetime

Parameters

Label	CEF Label	Type	Usage
agent	deviceProcessName	Text	The short identifier of the agent software
daysleft	vds_daysleft	Numeric	Days until certificate expiry

Description

None

Message ID : VMD3885I

Severity

Information

Message ID : VMD3883I

1976

Long Form

The VMD failed to initialize with the Key Manager. This may indicate that the connection to the server is down, the VMD's host has been deleted from the Key Manager, or "Communication Enabled" for the host has not been enabled in the Key Manager UI.

Short Form

VMD/Server init fail

Parameters

No parameters are provided for this message type

Description

The agent is unable to reach the Security Server. You may see any of the following error messages: COM4583F, COM4633W, VMD3770F, VMD3885I or VMD3886I. You may experience any of the following:

1. Connection to the Security Server is down.
2. The VMD Host has been deleted from the Security Server.
3. The host does not have "Communication Enabled" in the Security Server UI.
4. The VMD's host may be deleted from the Security Server. Run the register_host utility to re-register the VMD with the Security Server.

Message ID : VMD3886I

Severity

Information

Long Form

The VMD's host may no longer be registered with a Key Manager. The VMD's host may have been deleted from the Key Manager. You may want to run the register_host utility to re-register the VMD with a Key Manager.

Short Form

VMD poss unregistered

Parameters

No parameters are provided for this message type

Description

The agent is unable to reach the Security Server. You may see any of the following error messages: COM4583F, COM4633W, VMD3770F, VMD3885I or VMD3886I. You may experience any of the following:

1. Connection to the Security Server is down.
2. The VMD Host has been deleted from the Security Server.
3. The host does not have "Communication Enabled" in the Security Server UI.
4. The VMD's host may be deleted from the Security Server. Run the register_host utility to re-register the VMD with the Security Server.

Message ID : VMD3893I

Severity

Information

Long Form

Clustered property of GP {0} is honored per Key Manager

Short Form

Clustered property of GP is honored per Key Manager

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

Description

None

Message ID : VMD3895I

Severity

Information

Long Form

RSA certificates detected for the {0} agent, will renew with EC certificates

Short Form

Switching to EC certs

Parameters

Label	CEF Label	Type	Usage
agent	deviceProcessName	Text	The short identifier of the agent software

Description

None

Message ID : VMD3896I

Severity

Information

Long Form

RSA certificates detected for the {0} agent, will not renew with EC certificates as ports 8446/7 not open to Key Manager

Short Form

No Switch to EC certs due to missing 8446/7 ports

Parameters

Label	CEF Label	Type	Usage
agent	deviceProcessName	Text	The short identifier of the agent software

Description

None

Message ID : VMD3897I

Severity

Information

Message ID : VMD3896I

1981

Long Form

New comms session with {0} using token {1}

Short Form

Comms session

Parameters

Label	CEF Label	Type	Usage
shost	shost	Text	Source host name
token	vds_token	Text	A token name (e.g. for one-time-passwords)

Description

None

Message ID : VMD3898I

Severity

Information

Message ID : VMD3897I

Long Form

STARTED on {0} VERSION: {1}

Short Form

VMD Startup

Parameters

Label	CEF Label	Type	Usage
osname	cs2	Text	A name identifying the agent operating system
version	vds_version	Text	Software version string

Description

None

Message ID : VMD3900I

Severity

Information

Message ID : VMD3898I

1983

Long Form

Docker host browsing succeeded.

Short Form

Docker host browse OK

Parameters

No parameters are provided for this message type

Description

None

Message ID : VMD3902I

Severity

Information

Long Form

Docker host browsing for image {0} succeeded.

Short Form

Docker host browse OK

Parameters

Label	Type	Usage
dockerid	Text	Docker image or container id

Description

None

Message ID : VMD3904I

Severity

Information

Long Form

Docker image {0} file browsing for {1} succeeded.

Short Form

Docker image file browse OK

Message ID : VMD3902I

1985

Parameters

Label	CEF Label	Type	Usage
dockerid	dockerid	Text	Docker image or container id
filePath	filePath	Text	Full path to file

Description

None

Message ID : VMD3906I

Severity

Information

Long Form

Docker container {0} file browsing for {1} succeeded.

Short Form

Docker container file browse OK

Parameters

Label	CEF Label	Type	Usage
dockerid	dockerid	Text	Docker image or container id
filePath	filePath	Text	Full path to file

Description

None

Message ID : VMD3908I

Severity

Information

Long Form

User browsing for image {0} with {1} succeeded.

Short Form

Docker image user browse OK

Parameters

Label	CEF Label	Type	Usage
dockerid	dockerid	Text	Docker image or container id
domain	dntdom	Text	A domain name (policy, network, users, etc)

Description

None

Message ID : VMD3910I

Severity

Information

Long Form

User browsing for container {0} with {1} succeeded.

Short Form

Docker container user browse OK

Parameters

Label	CEF Label	Type	Usage
dockerid	dockerid	Text	Docker image or container id
domain	dntdom	Text	A domain name (policy, network, users, etc)

Description

None

Message ID : VMD3912I

Severity

Information

Long Form

Domain browsing for image {0} succeeded.

Short Form

Docker image domain browse OK

Parameters

Label	Type	Usage
dockerid	Text	Docker image or container id

Description

None

Message ID : VMD3914I

Severity

Information

Long Form

Domain browsing for container {0} succeeded.

Short Form

Docker container domain browse OK

Parameters

Label	Type	Usage
dockerid	Text	Docker image or container id

Message ID : VMD3912I

Label	Type	Usage

Description

None

Message ID : VMD3919I

Severity

Information

Long Form

Policy "{0}" version {1} received from Key Manager

Short Form

Policy update

Parameters

Label	CEF Label	Type	Usage
pol	cs1	Text	Policy name
verno	vds_verno	Numeric	A version number

Description

None

Message ID : VMD4246I

Severity

Information

Long Form

Detected upgrade situation from pre-FIPS (4.4.0) to post-FIPS (4.4.1). Converting the private key format now.

Short Form

Key converted

Parameters

No parameters are provided for this message type

Description

None

Message ID : VMD3919I

1992

Message ID : VMD4611I

Severity

Information

Long Form

vm_write_file: Empty write buffer

Short Form

Empty write buf

Parameters

No parameters are provided for this message type

Description

None

Message ID : VMD4619I

Severity

Information

Long Form

The previous message {0} was repeated {1} times

Short Form

Repeat message

Parameters

Label	CEF Label	Type	Usage
msgid	vds_msgid	Text	A unique log message identifier
count	vds_count	Numeric	A generic count value

Description

None

Message ID : VMD4620I

Severity

Information

Long Form

The space available for log files in {0} is low ({1} MB)

Short Form

Log space low

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file
count	vds_count	Numeric	A generic count value

Description

None

Logger VMD: Warnings

Message ID : VMD3714W

Severity

Warning

Long Form

check_mount: {0} {1}{2} match failed({3})

Short Form

No short form is provided for this message type

Description

None

Message ID : VMD3805W

Severity

Warning

Long Form

Unhandled service opcode seen. Opcode = {0}

Short Form

Unhandled opcode

Parameters

Label	CEF Label	Type	Usage
ecode	cn1	Numeric	An error code

Description

None

Message ID : VMD3806W

Severity

Warning

Long Form

Unrecognized service opcode seen. Opcode = {0}

Message ID : VMD3805W

Short Form

Unknown opcode

Parameters

Label	CEF Label	Type	Usage
ecode	cn1	Numeric	An error code

Description

None

Message ID : VMD3813W

Severity

Warning

Long Form

The VMD is shutting down.

Short Form

VMD Shutdown

Message ID : VMD3806W

Parameters

No parameters are provided for this message type

Description

System shutdown, reboot or system re-registration will cause this message to display because the Vormetric daemon process was terminated.

Message ID : VMD3824W

Severity

Warning

Long Form

Failed to create the signature for {0} for the signature request {1}, error code {2}

Short Form

Sig creation error

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Label	CEF Label	Type	Usage
showStr	reason	Text	Code specifying reason for allowing access, if any
ecode	cn1	Numeric	An error code

Description

None

Message ID : VMD3826W

Severity

Warning

Long Form

{0} is invalid for the signature request {1}

Short Form

Bad sig file

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Message ID : VMD3824W

2000

Label	CEF Label	Type	Usage
showStr	reason	Text	Code specifying reason for allowing access, if any

Description

None

Message ID : VMD3850W

Severity

Warning

Long Form

Could not find the signature request {0}

Short Form

Sig req mismatch

Parameters

Label	CEF Label	Type	Usage
showStr	reason	Text	Code specifying reason for allowing access, if any

Message ID : VMD3826W

2001

Description

None

Message ID : VMD3860W

Severity

Warning

Long Form

The signature request {0} is already initialized

Short Form

Sig req duplicated

Parameters

Label	CEF Label	Type	Usage
showStr	reason	Text	Code specifying reason for allowing access, if any

Description

None

Message ID : VMD3850W

Message ID : VMD3869W

Severity

Warning

Long Form

No LDAP server details were found (missing or incomplete ldap.conf)

Short Form

No LDAP server

Parameters

No parameters are provided for this message type

Description

No LDAP configuration data was found on the host system. This usually occurs because LDAP services have not been installed or configured properly.

Message ID : VMD3871W

Severity

Warning

Long Form

Unauthorized communication attempt from "{0}" rejected

Short Form

Unauth comms rejected

Parameters

Label	CEF Label	Type	Usage
url	request	Text	A uniform resource location

Description

None

Message ID : VMD3882W

Severity

Warning

Message ID : VMD3871W

Long Form

An error occurred with a new certificate set so the previous set has been restored

Short Form

Backup certs restored

Parameters

No parameters are provided for this message type

Description

None

Message ID : VMD3887W

Severity

Warning

Long Form

Unable to initialize/join Vormetric Cluster Group - proceeding unclustered

Short Form

initialize/join CipherTrust Cluster Group - proceeding unclustered

Parameters

No parameters are provided for this message type

Description

None

Message ID : VMD3889W

Severity

Warning

Long Form

Cluster coherent GP {0} not allowed on unclustered node

Short Form

Cluster coherent GP not allowed on unclustered node

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	Guardpoint base directory

Description

None

Message ID : VMD3899W

Severity

Warning

Long Form

The authentication signature for file {0} has changed

Short Form

Signature changed

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Message ID : VMD3889W

Label	CEF Label	Type	Usage

Description

None

Message ID : VMD3920W

Severity

Warning

Long Form

Agent failing over to server "{0}"

Short Form

Failover

Parameters

Label	CEF Label	Type	Usage
shost	shost	Text	Source host name

Description

None

Message ID : VMD3921W

Severity

Warning

Long Form

Agent reverting to assigned server "{0}"

Short Form

Failover end

Parameters

Label	CEF Label	Type	Usage
shost	shost	Text	Source host name

Description

None

Message ID : VMD3920W

Message ID : VMD3924W

Severity

Warning

Long Form

Unknown key manager in URL {0} will be ignored. This attribute is located in the config file at {1}.

Short Form

Unknown URL in config file

Parameters

Label	CEF Label	Type	Usage
url	request	Text	A uniform resource location
filePath	filePath	Text	Full path to file

Description

None

Message ID : VMD3925W

Severity

Warning

Long Form

Certificate renewal not possible due to missing external cert directory and no saved CSR

Short Form

Cert renewal impossible

Parameters

No parameters are provided for this message type

Description

None

Message ID : VMD4618W

Severity

Warning

Long Form

The previous message {0} was repeated {1} times

Short Form

Repeat message

Parameters

Label	CEF Label	Type	Usage
msgid	vds_msgid	Text	A unique log message identifier
count	vds_count	Numeric	A generic count value

Description

None

Message ID : VMD4621W

Severity

Warning

Long Form

The space available for log files in {0} is dangerously low ({1} MB)

Short Form

Log space low

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file
count	vds_count	Numeric	A generic count value

Description

The directory used to process log files is low on space. The "filePath" field gives the path and directory. The "count" field gives the remaining space (in MB).

When space is low audit trails may become compromised, and error conditions may be unreported. This should be resolved immediately.

Message ID : VMD4622W

Severity

Warning

Long Form

Raising drop log message level to {0} because space consumed is now greater than {1}% and less than or equal to {2}%.

Short Form

Raise drop space level

Parameters

Label	CEF Label	Type	Usage
showStr	reason	Text	Code specifying reason for allowing access, if any
count	vds_count	Numeric	A generic count value
count	vds_count	Numeric	A generic count value

Description

The space that holds log files uploaded to the Security Server is increasing. Logging levels are automatically modified to accommodate the load. The "reason" field details the change being imposed, and the two "count" fields depict the lower and upper "percentage full" values that caused this condition. The following strings may occur on the "reason" field:

Reason	Meaning
--------	---------

Drop None	No adjustments currently in force
Speed Up	The agent will try to upload logs to the Security Server in larger batches
Drop Info	No INFO level logs will be uploaded
Drop Warn	No WARN level logs will be uploaded
Drop Error	No ERROR level logs will be uploaded

Message ID : VMD4623W

Severity

Warning

Long Form

Raising drop log message level to {0} because number of files is now greater than {1}% and less than or equal to {2}%.

Short Form

Raise drop file level

Parameters

Label	CEF Label	Type	Usage
showStr	reason	Text	Code specifying reason for allowing access, if any

Label	CEF Label	Type	Usage
count	vds_count	Numeric	A generic count value
count	vds_count	Numeric	A generic count value

Description

Files pending upload to the Security Server are increasing, so the agent has temporarily adjusted the logging parameters to handle the situation. The "reason" field details the change imposed, and the two "count" fields indicate the lower and upper percentages of the maximum permitted number of files. See VMD4622W for usage of the "reason" field.

Message ID : VMD4624W

Severity

Warning

Long Form

Lowering drop log message level to {0} because space consumed is now greater than {1}% and less than or equal to {2}%.

Short Form

Lower drop space level

Parameters

Label	CEF Label	Type	Usage
showStr	reason	Text	Code specifying reason for allowing access, if any
count	vds_count	Numeric	A generic count value
count	vds_count	Numeric	A generic count value

Description

The space used to hold log files for uploading to the Security Server is decreasing, so the agent has temporarily adjusted the logging parameters to handle the situation. See VMD4622W for details about the fields used.

Message ID : VMD4625W

Severity

Warning

Long Form

Lowering drop log message level to {0} because number of files is now greater than {1}% and less than or equal to {2}%.

Short Form

Lower drop file level

Parameters

Label	CEF Label	Type	Usage
showStr	reason	Text	Code specifying reason for allowing access, if any
count	vds_count	Numeric	A generic count value
count	vds_count	Numeric	A generic count value

Description

The number of files pending upload to the Security Server is decreasing, so the agent has temporarily adjusted the logging parameters to handle the situation. See VMD4623W for details about the fields used.

Message ID : VMD4636W

Severity

Warning

Long Form

Unable to determine expiry date from certificate {0}

Short Form

Cannot get expiry date

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : VMD4639W

Severity

Warning

Long Form

Corrupt log data from kernel in file {0} - some records lost

Short Form

Corrupt log file

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Message ID : VMD4636W

Label	CEF Label	Type	Usage

Description

None

Message ID : VMD4640W

Severity

Warning

Long Form

Invalid directory in log directory. {0} Please remove.

Short Form

Invalid directory in log directory.

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Logger XFM: Errors

Message ID : XFM4501E

Severity

Error

Long Form

Decompression failure: the size of the data resulting from decompression is not the same size as before compression. Possible data corruption.

Short Form

Size mismatch

Parameters

No parameters are provided for this message type

Description

None

Message ID : XFM4502E

Severity

Error

Long Form

Compression setup failure: module not initialized.

Short Form

Compression init fail

Parameters

No parameters are provided for this message type

Description

None

Message ID : XFM4504E

Severity

Error

Long Form

Compression setup failure: no applicable module initialized.

Short Form

Compression setup fail

Parameters

No parameters are provided for this message type

Description

None

Message ID : XFM4535E

Severity

Error

Long Form

Decompression got corrupted buffer (invalid size of encrypted data).

Short Form

Encryption buffer corrupt

Parameters

No parameters are provided for this message type

Description

None

Message ID : XFM4568E

Severity

Error

Long Form

Compression failure: destination buffer too small: {0} < {1}.

Short Form

Buffer too small

Parameters

Label	CEF Label	Type	Usage
slen	in	Numeric	Input byte count or length
dlen	out	Numeric	Output byte count or length

Description

None

Message ID : XFM4589E

Severity

Error

Long Form

Unable to initialize the message digest subsystem. The operation will fail.

Short Form

Digest setup fail

Parameters

No parameters are provided for this message type

Description

None

Message ID : XFM4590E

Severity

Error

Long Form

Unable to compute the message digest value.

Short Form

Cannot compute digest

Parameters

No parameters are provided for this message type

Description

None

Message ID : XFM4591E

Severity

Error

Long Form

Unable to the retrieve the message digest value.

Short Form

Cannot extract digest

Parameters

No parameters are provided for this message type

Description

None

Message ID : XFM4590E

2028

Logger XFM: Fatal errors

Message ID : XFM4508F

Severity

Fatal error

Long Form

Unable to find chunk headers; possible data corruption.

Short Form

Missing chunk hdr

Parameters

No parameters are provided for this message type

Description

None

Message ID : XFM4509F

Severity

Fatal error

Long Form

Decompression/decryption failure: output buffer size ({0} bytes) is too small.

Short Form

Decomp/decrypt buffer too small

Parameters

Label	CEF Label	Type	Usage
dlen	out	Numeric	Output byte count or length

Description

None

Message ID : XFM4518F

Severity

Fatal error

Message ID : XFM4509F

Long Form

Invalid encryption key size received from Key Manager. The operation will fail.

Short Form

Invalid encr. key size

Parameters

No parameters are provided for this message type

Description

None

Message ID : XFM4519F

Severity

Fatal error

Long Form

The agent could not allocate enough memory. Contact support.

Short Form

Out of memory

Parameters

No parameters are provided for this message type

Description

None

Message ID : XFM4525F

Severity

Fatal error

Long Form

Decryption fatal error: {0}. The restore operation will fail.

Short Form

Decryption error

Parameters

Label	CEF Label	Type	Usage
ecode	cn1	Numeric	An error code

Description

None

Message ID : XFM4532F

Severity

Fatal error

Long Form

Decryption information mismatch; possible data corruption.

Short Form

Decryption info mismatch

Parameters

No parameters are provided for this message type

Message ID : XFM4525F

Description

None

Message ID : XFM4536F

Severity

Fatal error

Long Form

Compression module returned fatal error: {0}. The operation will fail.

Short Form

Compression error

Parameters

Label	CEF Label	Type	Usage
ecode	cn1	Numeric	An error code

Description

None

Message ID : XFM4532F

Message ID : XFM4539F

Severity

Fatal error

Long Form

Unable to set up encryption subsystem. The operation will fail.

Short Form

Encryption setup fail

Parameters

No parameters are provided for this message type

Description

None

Message ID : XFM4540F

Severity

Fatal error

Long Form

Decompression information mismatch; possible data corruption.

Short Form

Decompression info mismatch

Parameters

No parameters are provided for this message type

Description

None

Message ID : XFM4541F

Severity

Fatal error

Long Form

Data read problem: corrupted buffer header. Data corruption has possibly occurred. The restore operation will fail.

Short Form

Corrupt buffer header

Parameters

No parameters are provided for this message type

Description

None

Message ID : XFM4544F

Severity

Fatal error

Long Form

Unable to set up compression subsystem. The operation will fail.

Short Form

Compression setup fail

Parameters

No parameters are provided for this message type

Description

None

Message ID : XFM4546F

Severity

Fatal error

Long Form

Compression module initialization failure. The backup operation will fail.

Short Form

Compression init fail

Parameters

No parameters are provided for this message type

Message ID : XFM4544F

Description

None

Message ID : XFM4561F

Severity

Fatal error

Long Form

Decompression fatal error: {0}. The restore operation will fail.

Short Form

Decompression error

Parameters

Label	CEF Label	Type	Usage
ecode	cn1	Numeric	An error code

Description

None

Message ID : XFM4546F

Message ID : XFM4565F

Severity

Fatal error

Long Form

Input data length does not match buffer length: {0} != {1}. Data corruption has possible occurred. The restore operation will fail.

Short Form

Data lenght mismatch

Parameters

Label	CEF Label	Type	Usage
slen	in	Numeric	Input byte count or length
dlen	out	Numeric	Output byte count or length

Description

None

Logger XFM: Information

Message ID : XFM4507I

Severity

Information

Long Form

Using no encryption.

Short Form

Using no encryption

Parameters

No parameters are provided for this message type

Description

None

Message ID : XFM4517I

Severity

Information

Long Form

Shutting down compression/decompression subsystem.

Short Form

Comp/decomp shutdown

Parameters

No parameters are provided for this message type

Description

None

Message ID : XFM4522I

Severity

Information

Long Form

Data transformation code now using single-threaded algorithm.

Short Form

Single-thread transform

Parameters

No parameters are provided for this message type

Description

None

Message ID : XFM4526I

Severity

Information

Long Form

Using no compression.

Short Form

Using no compression

Parameters

No parameters are provided for this message type

Description

None

Message ID : XFM4549I

Severity

Information

Long Form

Using compression.

Short Form

Using compression

Parameters

No parameters are provided for this message type

Description

None

Message ID : XFM4557I

Severity

Information

Long Form

Using {0} encryption algorithm.

Short Form

Using enc algorithm

Parameters

Label	CEF Label	Type	Usage
key	cs3	Text	Name of key or key pair

Message ID : XFM4549I

Description

None

Message ID : XFM4559I

Severity

Information

Long Form

Shutting down encryption/decryption subsystem.

Short Form

Encrypt/decrypt shutdown

Parameters

No parameters are provided for this message type

Description

None

Message ID : XFM4557I

2046

Logger XFM: Warnings

Message ID : XFM4550W

Severity

Warning

Long Form

Compression initialization failure: failed to initialize algorithm {0} upon startup.

Short Form

Compression init fail

Parameters

No parameters are provided for this message type

Description

None