



CipherTrust Data Security Platform

CipherTrust Data Security Event and Log Messages Guide

Release 7.8.0

Document Version 1

June 17, 2025

All information herein is either public information or is the property of and owned solely by Thales DIS France S.A. and/or its subsidiaries or affiliates who shall have and keep the sole right to file patent applications or any other kind of intellectual property protection in connection with such information.

Nothing herein shall be construed as implying or granting to you any rights, by license, grant or otherwise, under any intellectual and/or industrial property rights of or concerning any of Thales DIS France S.A. and any of its subsidiaries and affiliates (collectively referred to herein after as "Thales") information.

This document can be used for informational, non-commercial, internal and personal use only provided that:

- The copyright notice below, the confidentiality and proprietary legend and this full warning notice appear in all copies.
- This document shall not be posted on any network computer or broadcast in any media and no modification of any part of this document shall be made.

Use for any other purpose is expressly prohibited and may result in severe civil and criminal liabilities.

The information contained in this document is provided "AS IS" without any warranty of any kind. Unless otherwise expressly agreed in writing, Thales makes no warranty as to the value or accuracy of information contained herein.

The document could include technical inaccuracies or typographical errors. Changes are periodically added to the information herein. Furthermore, Thales reserves the right to make any change or improvement in the specifications data, information, and the like described herein, at any time.

Thales hereby disclaims all warranties and conditions with regard to the information contained herein, including all implied warranties of merchantability, fitness for a particular purpose, title and non-infringement. In no event shall Thales be liable, whether in contract, tort or otherwise, for any indirect, special or consequential damages or any damages whatsoever including but not limited to damages resulting from loss of use, data, profits, revenues, or customers, arising out of or in connection with the use or performance of information contained in this document.

Thales does not and shall not warrant that this product will be resistant to all possible attacks and shall not incur, and disclaims, any liability in this respect. Even if each product is compliant with current security standards in force on the date of their design, security mechanisms' resistance necessarily evolves according to the state of the art in security and notably under the emergence of new attacks. Under no circumstances, shall Thales be held liable for any third party actions and in particular in case of any successful attack against systems or equipment incorporating Thales products. Thales disclaims any liability with respect to security for direct, indirect, incidental or consequential damages that result from any use of its products. It is further stressed that independent testing and verification by the person using the product is particularly encouraged, especially in any application in which defective, incorrect or insecure functioning could result in damage to persons or property, denial of service or loss of privacy.

Copyright © 2009 - 2025 Thales Group. All rights reserved. Thales and the Thales logo are trademarks and service marks of Thales and/or its subsidiaries and affiliates and are registered in certain countries. All other trademarks and service marks, whether registered or not in specific countries, are the properties of their respective owners.

Table of Contents

<u>Logger CGA: Errors</u>	1
<u>Message ID : CGA2614E</u>	1
<u>Message ID : CGA2617E</u>	1
<u>Message ID : CGA2618E</u>	2
<u>Message ID : CGA2619E</u>	3
<u>Message ID : CGA2620E</u>	3
<u>Message ID : CGA2621E</u>	4
<u>Message ID : CGA2624E</u>	5
<u>Message ID : CGA2625E</u>	6
<u>Message ID : CGA2626E</u>	6
<u>Message ID : CGA2627E</u>	7
<u>Message ID : CGA2628E</u>	8
<u>Message ID : CGA2629E</u>	9
<u>Message ID : CGA2634E</u>	10
<u>Message ID : CGA2635E</u>	11
<u>Message ID : CGA2636E</u>	12
<u>Message ID : CGA2637E</u>	13
<u>Message ID : CGA2638E</u>	13
<u>Message ID : CGA2639E</u>	14
<u>Message ID : CGA2645E</u>	15
<u>Message ID : CGA2648E</u>	16
<u>Message ID : CGA2649E</u>	17
<u>Message ID : CGA2650E</u>	18
<u>Message ID : CGA2651E</u>	19
<u>Message ID : CGA2652E</u>	20
<u>Message ID : CGA2653E</u>	21
<u>Message ID : CGA2654E</u>	22

Table of Contents

Logger CGA: Errors

<u>Message ID : CGA2655E</u>	23
<u>Message ID : CGA2656E</u>	24
<u>Message ID : CGA2657E</u>	25
<u>Message ID : CGA2658E</u>	26
<u>Message ID : CGA2659E</u>	27
<u>Message ID : CGA2662E</u>	28
<u>Message ID : CGA3003E</u>	28
<u>Message ID : CGA3004E</u>	29
<u>Message ID : CGA3007E</u>	30
<u>Message ID : CGA3008E</u>	31
<u>Message ID : CGA3009E</u>	32
<u>Message ID : CGA3010E</u>	33
<u>Message ID : CGA3011E</u>	34
<u>Message ID : CGA3012E</u>	35
<u>Message ID : CGA3013E</u>	35
<u>Message ID : CGA3014E</u>	36
<u>Message ID : CGA3015E</u>	37
<u>Message ID : CGA3016E</u>	37
<u>Message ID : CGA3017E</u>	38
<u>Message ID : CGA3018E</u>	39
<u>Message ID : CGA3021E</u>	40
<u>Message ID : CGA3022E</u>	41
<u>Message ID : CGA3023E</u>	42
<u>Message ID : CGA3024E</u>	42
<u>Message ID : CGA3059E</u>	43
<u>Message ID : CGA3060E</u>	44

Table of Contents

Logger CGA: Errors

<u>Message ID : CGA3061E</u>	45
<u>Message ID : CGA3062E</u>	46
<u>Message ID : CGA3063E</u>	47
<u>Message ID : CGA3064E</u>	48
<u>Message ID : CGA3065E</u>	49
<u>Message ID : CGA3066E</u>	50
<u>Message ID : CGA3067E</u>	50
<u>Message ID : CGA3068E</u>	51
<u>Message ID : CGA3069E</u>	52
<u>Message ID : CGA3070E</u>	53
<u>Message ID : CGA3071E</u>	54
<u>Message ID : CGA3072E</u>	55
<u>Message ID : CGA3073E</u>	56
<u>Message ID : CGA3074E</u>	56
<u>Message ID : CGA3075E</u>	57
<u>Message ID : CGA3076E</u>	58
<u>Message ID : CGA3077E</u>	59
<u>Message ID : CGA3078E</u>	60
<u>Message ID : CGA3079E</u>	61
<u>Message ID : CGA3080E</u>	62
<u>Message ID : CGA3081E</u>	62
<u>Message ID : CGA3082E</u>	63
<u>Message ID : CGA3083E</u>	64
<u>Message ID : CGA3084E</u>	65
<u>Message ID : CGA3085E</u>	66
<u>Message ID : CGA3086E</u>	67

Table of Contents

Logger CGA: Errors

<u>Message ID : CGA3087E</u>	68
<u>Message ID : CGA3088E</u>	69
<u>Message ID : CGA3089E</u>	70
<u>Message ID : CGA3090E</u>	71
<u>Message ID : CGA3091E</u>	72
<u>Message ID : CGA3092E</u>	72
<u>Message ID : CGA3093E</u>	73
<u>Message ID : CGA3094E</u>	74
<u>Message ID : CGA3095E</u>	75
<u>Message ID : CGA3096E</u>	76
<u>Message ID : CGA3097E</u>	77
<u>Message ID : CGA3098E</u>	78
<u>Message ID : CGA3099E</u>	78
<u>Message ID : CGA3100E</u>	79
<u>Message ID : CGA3101E</u>	80
<u>Message ID : CGA3102E</u>	81
<u>Message ID : CGA3103E</u>	82
<u>Message ID : CGA3109E</u>	83
<u>Message ID : CGA3110E</u>	84
<u>Message ID : CGA3111E</u>	84
<u>Message ID : CGA3112E</u>	85
<u>Message ID : CGA3113E</u>	86
<u>Message ID : CGA3114E</u>	87
<u>Message ID : CGA3115E</u>	88
<u>Message ID : CGA3116E</u>	89
<u>Message ID : CGA3117E</u>	90

Table of Contents

Logger CGA: Errors

<u>Message ID : CGA3118E</u>	91
<u>Message ID : CGA3119E</u>	92
<u>Message ID : CGA3120E</u>	93
<u>Message ID : CGA3121E</u>	94
<u>Message ID : CGA3122E</u>	95
<u>Message ID : CGA3123E</u>	96
<u>Message ID : CGA3124E</u>	97
<u>Message ID : CGA3125E</u>	97
<u>Message ID : CGA3126E</u>	98
<u>Message ID : CGA3127E</u>	99
<u>Message ID : CGA3128E</u>	100
<u>Message ID : CGA3129E</u>	101
<u>Message ID : CGA3130E</u>	102
<u>Message ID : CGA3131E</u>	103
<u>Message ID : CGA3132E</u>	104
<u>Message ID : CGA3133E</u>	105
<u>Message ID : CGA3134E</u>	106
<u>Message ID : CGA3135E</u>	107
<u>Message ID : CGA3136E</u>	108
<u>Message ID : CGA3137E</u>	109
<u>Message ID : CGA3138E</u>	110
<u>Message ID : CGA3139E</u>	110
<u>Message ID : CGA3140E</u>	111
<u>Message ID : CGA3141E</u>	112
<u>Message ID : CGA3142E</u>	113
<u>Message ID : CGA3143E</u>	114

Table of Contents

Logger CGA: Errors

<u>Message ID : CGA3144E</u>	115
<u>Message ID : CGA3145E</u>	116
<u>Message ID : CGA3146E</u>	117
<u>Message ID : CGA3147E</u>	118
<u>Message ID : CGA3148E</u>	119
<u>Message ID : CGA3149E</u>	120
<u>Message ID : CGA3150E</u>	121
<u>Message ID : CGA3151E</u>	122
<u>Message ID : CGA3152E</u>	123
<u>Message ID : CGA3153E</u>	123
<u>Message ID : CGA3154E</u>	124
<u>Message ID : CGA3155E</u>	125
<u>Message ID : CGA3156E</u>	126
<u>Message ID : CGA3157E</u>	127
<u>Message ID : CGA3158E</u>	128
<u>Message ID : CGA3159E</u>	129
<u>Message ID : CGA3160E</u>	130
<u>Message ID : CGA3161E</u>	131
<u>Message ID : CGA3162E</u>	132
<u>Message ID : CGA3163E</u>	133
<u>Message ID : CGA3164E</u>	134
<u>Message ID : CGA3165E</u>	135
<u>Message ID : CGA3166E</u>	136
<u>Message ID : CGA3167E</u>	136
<u>Message ID : CGA3168E</u>	137
<u>Message ID : CGA3169E</u>	138

Table of Contents

Logger CGA: Errors

<u>Message ID : CGA3170E</u>	139
<u>Message ID : CGA3171E</u>	140
<u>Message ID : CGA3172E</u>	141
<u>Message ID : CGA3173E</u>	142
<u>Message ID : CGA3174E</u>	143
<u>Message ID : CGA3175E</u>	144
<u>Message ID : CGA3176E</u>	145
<u>Message ID : CGA3177E</u>	146
<u>Message ID : CGA3178E</u>	147
<u>Message ID : CGA3179E</u>	148
<u>Message ID : CGA3180E</u>	149
<u>Message ID : CGA3181E</u>	149
<u>Message ID : CGA3182E</u>	150
<u>Message ID : CGA3184E</u>	151
<u>Message ID : CGA3185E</u>	152
<u>Message ID : CGA3187E</u>	153
<u>Message ID : CGA3188E</u>	154
<u>Message ID : CGA3189E</u>	155
<u>Message ID : CGA3190E</u>	156
<u>Message ID : CGA3191E</u>	156
<u>Message ID : CGA3192E</u>	157
<u>Message ID : CGA3206E</u>	158
<u>Message ID : CGA3212E</u>	159
<u>Message ID : CGA3218E</u>	160
<u>Message ID : CGA3220E</u>	161
<u>Message ID : CGA3222E</u>	162

Table of Contents

Logger CGA: Errors

<u>Message ID : CGA3223E</u>	163
<u>Message ID : CGA3227E</u>	164
<u>Message ID : CGA3228E</u>	165
<u>Message ID : CGA3229E</u>	166
<u>Message ID : CGA3230E</u>	167
<u>Message ID : CGA3232E</u>	168
<u>Message ID : CGA3233E</u>	169
<u>Message ID : CGA3235E</u>	170
<u>Message ID : CGA3236E</u>	170
<u>Message ID : CGA3237E</u>	171
<u>Message ID : CGA3238E</u>	172
<u>Message ID : CGA3239E</u>	173
<u>Message ID : CGA3252E</u>	174
<u>Message ID : CGA3256E</u>	175
<u>Message ID : CGA3272E</u>	176
<u>Message ID : CGA3274E</u>	177
<u>Message ID : CGA3275E</u>	178
<u>Message ID : CGA3278E</u>	179
<u>Message ID : CGA3279E</u>	180
<u>Message ID : CGA3280E</u>	180
<u>Message ID : CGA3282E</u>	181
<u>Message ID : CGA3284E</u>	182
<u>Message ID : CGA3289E</u>	183
<u>Message ID : CGA3292E</u>	184
<u>Message ID : CGA3295E</u>	185
<u>Message ID : CGA3298E</u>	186

Table of Contents

Logger CGA: Errors

<u>Message ID : CGA3301E</u>	187
<u>Message ID : CGA3304E</u>	187
<u>Message ID : CGA3306E</u>	188
<u>Message ID : CGA3307E</u>	189
<u>Message ID : CGA3308E</u>	190
<u>Message ID : CGA3309E</u>	191
<u>Message ID : CGA3310E</u>	192
<u>Message ID : CGA3356E</u>	193
<u>Message ID : CGA3361E</u>	194

Logger CGA: Information.....196

<u>Message ID : CGA2622I</u>	196
<u>Message ID : CGA2630I</u>	196
<u>Message ID : CGA2631I</u>	197
<u>Message ID : CGA2632I</u>	198
<u>Message ID : CGA2633I</u>	198
<u>Message ID : CGA2640I</u>	199
<u>Message ID : CGA2641I</u>	200
<u>Message ID : CGA2642I</u>	200
<u>Message ID : CGA2643I</u>	201
<u>Message ID : CGA2644I</u>	202
<u>Message ID : CGA2646I</u>	202
<u>Message ID : CGA2647I</u>	203
<u>Message ID : CGA2660I</u>	204
<u>Message ID : CGA2661I</u>	205
<u>Message ID : CGA3001I</u>	206

Table of Contents

Logger CGA: Information

<u>Message ID : CGA3005I</u>	207
<u>Message ID : CGA3006I</u>	207
<u>Message ID : CGA3019I</u>	208
<u>Message ID : CGA3020I</u>	209
<u>Message ID : CGA3058I</u>	210
<u>Message ID : CGA3105I</u>	211
<u>Message ID : CGA3183I</u>	212
<u>Message ID : CGA3186I</u>	213
<u>Message ID : CGA3193I</u>	214
<u>Message ID : CGA3194I</u>	214
<u>Message ID : CGA3195I</u>	215
<u>Message ID : CGA3196I</u>	216
<u>Message ID : CGA3197I</u>	217
<u>Message ID : CGA3198I</u>	218
<u>Message ID : CGA3199I</u>	219
<u>Message ID : CGA3200I</u>	220
<u>Message ID : CGA3201I</u>	221
<u>Message ID : CGA3202I</u>	222
<u>Message ID : CGA3203I</u>	222
<u>Message ID : CGA3204I</u>	223
<u>Message ID : CGA3205I</u>	224
<u>Message ID : CGA3207I</u>	225
<u>Message ID : CGA3208I</u>	226
<u>Message ID : CGA3209I</u>	227
<u>Message ID : CGA3210I</u>	228
<u>Message ID : CGA3211I</u>	229

Table of Contents

Logger CGA: Information

<u>Message ID : CGA3213I</u>	229
<u>Message ID : CGA3214I</u>	230
<u>Message ID : CGA3215I</u>	231
<u>Message ID : CGA3216I</u>	232
<u>Message ID : CGA3217I</u>	233
<u>Message ID : CGA3219I</u>	234
<u>Message ID : CGA3221I</u>	234
<u>Message ID : CGA3224I</u>	236
<u>Message ID : CGA3225I</u>	237
<u>Message ID : CGA3226I</u>	237
<u>Message ID : CGA3240I</u>	238
<u>Message ID : CGA3241I</u>	239
<u>Message ID : CGA3242I</u>	240
<u>Message ID : CGA3244I</u>	241
<u>Message ID : CGA3245I</u>	242
<u>Message ID : CGA3246I</u>	243
<u>Message ID : CGA3247I</u>	244
<u>Message ID : CGA3248I</u>	244
<u>Message ID : CGA3257I</u>	245
<u>Message ID : CGA3258I</u>	246
<u>Message ID : CGA3269I</u>	247
<u>Message ID : CGA3270I</u>	248
<u>Message ID : CGA3271I</u>	249
<u>Message ID : CGA3273I</u>	250
<u>Message ID : CGA3281I</u>	251
<u>Message ID : CGA3283I</u>	252

Table of Contents

Logger CGA: Information

<u>Message ID : CGA3287I</u>	252
<u>Message ID : CGA3288I</u>	253
<u>Message ID : CGA3290I</u>	254
<u>Message ID : CGA3291I</u>	255
<u>Message ID : CGA3293I</u>	256
<u>Message ID : CGA3294I</u>	257
<u>Message ID : CGA3296I</u>	258
<u>Message ID : CGA3297I</u>	259
<u>Message ID : CGA3299I</u>	260
<u>Message ID : CGA3300I</u>	261
<u>Message ID : CGA3305I</u>	262
<u>Message ID : CGA3343I</u>	263

Logger CGA: Warnings.....264

<u>Message ID : CGA2615W</u>	264
<u>Message ID : CGA2616W</u>	264
<u>Message ID : CGA2623W</u>	265
<u>Message ID : CGA2901W</u>	266
<u>Message ID : CGA3002W</u>	267
<u>Message ID : CGA3104W</u>	268
<u>Message ID : CGA3106W</u>	269
<u>Message ID : CGA3107W</u>	270
<u>Message ID : CGA3108W</u>	270
<u>Message ID : CGA3231W</u>	271
<u>Message ID : CGA3243W</u>	272
<u>Message ID : CGA3265W</u>	273

Table of Contents

Logger CGA: Warnings

<u>Message ID : CGA3276W</u>	274
<u>Message ID : CGA3285W</u>	275
<u>Message ID : CGA3286W</u>	276
<u>Message ID : CGA3346W</u>	277
<u>Message ID : CGA3352W</u>	278
<u>Message ID : CGA3353W</u>	279

Logger CGP: Errors.....280

<u>Message ID : CGP2602E</u>	280
<u>Message ID : CGP2604E</u>	281
<u>Message ID : CGP2606E</u>	282
<u>Message ID : CGP2608E</u>	284
<u>Message ID : CGP2610E</u>	285

Logger CGP: Information.....287

<u>Message ID : CGP2601I</u>	287
<u>Message ID : CGP2603I</u>	288
<u>Message ID : CGP2605I</u>	289
<u>Message ID : CGP2607I</u>	291
<u>Message ID : CGP2609I</u>	292

Logger CGS: Errors.....294

<u>Message ID : CGS2613E</u>	294
<u>Message ID : CGS3025E</u>	294
<u>Message ID : CGS3026E</u>	295
<u>Message ID : CGS3027E</u>	296

Table of Contents

Logger CGS: Errors

<u>Message ID : CGS3028E</u>	297
<u>Message ID : CGS3031E</u>	298
<u>Message ID : CGS3032E</u>	299
<u>Message ID : CGS3033E</u>	300
<u>Message ID : CGS3034E</u>	301
<u>Message ID : CGS3035E</u>	302
<u>Message ID : CGS3038E</u>	303
<u>Message ID : CGS3039E</u>	303
<u>Message ID : CGS3042E</u>	304
<u>Message ID : CGS3043E</u>	305
<u>Message ID : CGS3044E</u>	306
<u>Message ID : CGS3045E</u>	307
<u>Message ID : CGS3047E</u>	308
<u>Message ID : CGS3048E</u>	309
<u>Message ID : CGS3049E</u>	310
<u>Message ID : CGS3050E</u>	310
<u>Message ID : CGS3051E</u>	311
<u>Message ID : CGS3052E</u>	312
<u>Message ID : CGS3053E</u>	313
<u>Message ID : CGS3054E</u>	314
<u>Message ID : CGS3055E</u>	315
<u>Message ID : CGS3057E</u>	316
<u>Message ID : CGS3234E</u>	317
<u>Message ID : CGS3253E</u>	318
<u>Message ID : CGS3259E</u>	319
<u>Message ID : CGS3260E</u>	320

Table of Contents

Logger CGS: Errors

<u>Message ID : CGS3261E</u>	320
<u>Message ID : CGS3262E</u>	321
<u>Message ID : CGS3263E</u>	322
<u>Message ID : CGS3264E</u>	323
<u>Message ID : CGS3266E</u>	324
<u>Message ID : CGS3304E</u>	325
<u>Message ID : CGS3305E</u>	326
<u>Message ID : CGS3306E</u>	327
<u>Message ID : CGS3307E</u>	328
<u>Message ID : CGS3308E</u>	329
<u>Message ID : CGS3309E</u>	330
<u>Message ID : CGS3311E</u>	330
<u>Message ID : CGS3312E</u>	331
<u>Message ID : CGS3313E</u>	332
<u>Message ID : CGS3314E</u>	333
<u>Message ID : CGS3315E</u>	334
<u>Message ID : CGS3316E</u>	335
<u>Message ID : CGS3317E</u>	336
<u>Message ID : CGS3319E</u>	337
<u>Message ID : CGS3327E</u>	338
<u>Message ID : CGS3328E</u>	338
<u>Message ID : CGS3329E</u>	340
<u>Message ID : CGS3331E</u>	341
<u>Message ID : CGS3335E</u>	342
<u>Message ID : CGS3336E</u>	343
<u>Message ID : CGS3337E</u>	343

Table of Contents

Logger CGS: Errors

<u>Message ID : CGS3338E</u>	344
<u>Message ID : CGS3339E</u>	345
<u>Message ID : CGS3340E</u>	346
<u>Message ID : CGS3341E</u>	347
<u>Message ID : CGS3342E</u>	348
<u>Message ID : CGS3344E</u>	349
<u>Message ID : CGS3349E</u>	350
<u>Message ID : CGS3354E</u>	351
<u>Message ID : CGS3358E</u>	352
<u>Message ID : CGS3360E</u>	353
<u>Message ID : CGS3362E</u>	353
<u>Message ID : CGS3364E</u>	355
<u>Message ID : CGS3365E</u>	356
<u>Message ID : CGS3370E</u>	357
<u>Message ID : CGS3371E</u>	357

Logger CGS: Information.....359

<u>Message ID : CGS3029I</u>	359
<u>Message ID : CGS3030I</u>	360
<u>Message ID : CGS3036I</u>	360
<u>Message ID : CGS3037I</u>	361
<u>Message ID : CGS3040I</u>	362
<u>Message ID : CGS3041I</u>	363
<u>Message ID : CGS3046I</u>	364
<u>Message ID : CGS3056I</u>	365
<u>Message ID : CGS3249I</u>	366

Table of Contents

Logger CGS: Information

<u>Message ID : CGS3250I</u>	366
<u>Message ID : CGS3251I</u>	367
<u>Message ID : CGS3254I</u>	368
<u>Message ID : CGS3255I</u>	369
<u>Message ID : CGS3277I</u>	370
<u>Message ID : CGS3318I</u>	371
<u>Message ID : CGS3320I</u>	372
<u>Message ID : CGS3322I</u>	373
<u>Message ID : CGS3324I</u>	373
<u>Message ID : CGS3325I</u>	374
<u>Message ID : CGS3347I</u>	375
<u>Message ID : CGS3348I</u>	376
<u>Message ID : CGS3350I</u>	377
<u>Message ID : CGS3355I</u>	378
<u>Message ID : CGS3357I</u>	379
<u>Message ID : CGS3359I</u>	379

Logger CGS: Warnings.....**381**

<u>Message ID : CGS3267W</u>	381
<u>Message ID : CGS3268W</u>	382
<u>Message ID : CGS3302W</u>	383
<u>Message ID : CGS3303W</u>	384
<u>Message ID : CGS3310W</u>	385
<u>Message ID : CGS3321W</u>	385
<u>Message ID : CGS3323W</u>	386
<u>Message ID : CGS3326W</u>	387

Table of Contents

Logger CGS: Warnings

<u>Message ID : CGS3330W</u>	388
<u>Message ID : CGS3332W</u>	389
<u>Message ID : CGS3333W</u>	390
<u>Message ID : CGS3334W</u>	391
<u>Message ID : CGS3345W</u>	392
<u>Message ID : CGS3351W</u>	393
<u>Message ID : CGS3363W</u>	394
<u>Message ID : CGS3369W</u>	394

Logger COM: Errors.....**396**

<u>Message ID : COM4547E</u>	396
<u>Message ID : COM4631E</u>	396
<u>Message ID : COM4638E</u>	397
<u>Message ID : COM4644E</u>	398

Logger COM: Fatal errors.....**400**

<u>Message ID : COM4503F</u>	400
<u>Message ID : COM4506F</u>	400
<u>Message ID : COM4511F</u>	401
<u>Message ID : COM4512F</u>	402
<u>Message ID : COM4513F</u>	403
<u>Message ID : COM4514F</u>	404
<u>Message ID : COM4515F</u>	405
<u>Message ID : COM4521F</u>	405
<u>Message ID : COM4523F</u>	406
<u>Message ID : COM4527F</u>	407

Table of Contents

Logger COM: Fatal errors

<u>Message ID : COM4529F</u>	408
<u>Message ID : COM4531F</u>	409
<u>Message ID : COM4533F</u>	410
<u>Message ID : COM4534F</u>	410
<u>Message ID : COM4538F</u>	411
<u>Message ID : COM4542F</u>	412
<u>Message ID : COM4548F</u>	413
<u>Message ID : COM4551F</u>	414
<u>Message ID : COM4552F</u>	415
<u>Message ID : COM4554F</u>	415
<u>Message ID : COM4558F</u>	416
<u>Message ID : COM4562F</u>	417
<u>Message ID : COM4563F</u>	418
<u>Message ID : COM4567F</u>	419
<u>Message ID : COM4569F</u>	420
<u>Message ID : COM4571F</u>	421
<u>Message ID : COM4577F</u>	422
<u>Message ID : COM4578F</u>	422
<u>Message ID : COM4579F</u>	423
<u>Message ID : COM4583F</u>	424
<u>Message ID : COM4584F</u>	425
<u>Message ID : COM4586F</u>	426
<u>Message ID : COM4587F</u>	426
<u>Message ID : COM4588F</u>	427
<u>Message ID : COM4592F</u>	428
<u>Message ID : COM4599F</u>	429

Table of Contents

<u>Logger COM: Fatal errors</u>	
<u>Message ID : COM4600F</u>	430
<u>Message ID : COM4603F</u>	431
<u>Message ID : COM4604F</u>	432
<u>Message ID : COM4628F</u>	433
<u>Message ID : COM4629F</u>	434
<u>Message ID : COM4630F</u>	434
<u>Message ID : COM4637F</u>	436
<u>Logger COM: Information</u>	437
<u>Message ID : COM4601I</u>	437
<u>Message ID : COM4602I</u>	438
<u>Message ID : COM4626I</u>	438
<u>Message ID : COM4627I</u>	439
<u>Logger COM: Warnings</u>	441
<u>Message ID : COM4596W</u>	441
<u>Message ID : COM4597W</u>	442
<u>Message ID : COM4605W</u>	442
<u>Message ID : COM4632W</u>	443
<u>Message ID : COM4633W</u>	444
<u>Message ID : COM4634W</u>	446
<u>Message ID : COM4635W</u>	447
<u>Logger DGV: Errors</u>	449
<u>Message ID : DGV6001E</u>	449
<u>Message ID : DGV6002E</u>	449

Table of Contents

Logger DGV: Errors

<u>Message ID : DGV6003E</u>	450
<u>Message ID : DGV6004E</u>	451
<u>Message ID : DGV6005E</u>	452
<u>Message ID : DGV6006E</u>	453
<u>Message ID : DGV6007E</u>	454
<u>Message ID : DGV6008E</u>	455
<u>Message ID : DGV6009E</u>	455
<u>Message ID : DGV6010E</u>	456
<u>Message ID : DGV6011E</u>	457
<u>Message ID : DGV6012E</u>	458
<u>Message ID : DGV6013E</u>	459
<u>Message ID : DGV6014E</u>	460
<u>Message ID : DGV6015E</u>	461
<u>Message ID : DGV6016E</u>	461
<u>Message ID : DGV6017E</u>	462
<u>Message ID : DGV6018E</u>	463
<u>Message ID : DGV7007E</u>	464
<u>Message ID : DGV7009E</u>	465
<u>Message ID : DGV7011E</u>	466
<u>Message ID : DGV7012E</u>	467
<u>Message ID : DGV7014E</u>	468
<u>Message ID : DGV7019E</u>	469
<u>Message ID : DGV7023E</u>	469
<u>Message ID : DGV7030E</u>	470
<u>Message ID : DGV7033E</u>	471
<u>Message ID : DGV7038E</u>	472

Table of Contents

Logger DGV: Errors

<u>Message ID : DGV7041E</u>	473
<u>Message ID : DGV7046E</u>	474
<u>Message ID : DGV7054E</u>	474

Logger DGV: Information.....476

<u>Message ID : DGV6019I</u>	476
<u>Message ID : DGV6020I</u>	476
<u>Message ID : DGV6022I</u>	477
<u>Message ID : DGV7001I</u>	478
<u>Message ID : DGV7002I</u>	479
<u>Message ID : DGV7004I</u>	480
<u>Message ID : DGV7005I</u>	481
<u>Message ID : DGV7006I</u>	482
<u>Message ID : DGV7008I</u>	482
<u>Message ID : DGV7010I</u>	483
<u>Message ID : DGV7013I</u>	484
<u>Message ID : DGV7016I</u>	485
<u>Message ID : DGV7017I</u>	486
<u>Message ID : DGV7018I</u>	487
<u>Message ID : DGV7020I</u>	487
<u>Message ID : DGV7021I</u>	488
<u>Message ID : DGV7022I</u>	489
<u>Message ID : DGV7024I</u>	490
<u>Message ID : DGV7025I</u>	491
<u>Message ID : DGV7026I</u>	492
<u>Message ID : DGV7027I</u>	492

Table of Contents

Logger DGV: Information

<u>Message ID : DGV7028I</u>	493
<u>Message ID : DGV7029I</u>	494
<u>Message ID : DGV7031I</u>	495
<u>Message ID : DGV7032I</u>	496
<u>Message ID : DGV7034I</u>	497
<u>Message ID : DGV7035I</u>	497
<u>Message ID : DGV7036I</u>	498
<u>Message ID : DGV7037I</u>	499
<u>Message ID : DGV7039I</u>	500
<u>Message ID : DGV7040I</u>	501
<u>Message ID : DGV7042I</u>	502
<u>Message ID : DGV7043I</u>	502
<u>Message ID : DGV7044I</u>	503
<u>Message ID : DGV7045I</u>	504
<u>Message ID : DGV7049I</u>	505
<u>Message ID : DGV7050I</u>	506
<u>Message ID : DGV7051I</u>	507
<u>Message ID : DGV7052I</u>	507
<u>Message ID : DGV7053I</u>	508

Logger DGV: Warnings.....510

<u>Message ID : DGV6021W</u>	510
<u>Message ID : DGV7003W</u>	510
<u>Message ID : DGV7015W</u>	511
<u>Message ID : DGV7047W</u>	512
<u>Message ID : DGV7048W</u>	513

Table of Contents

<u>Logger DXF: Debug messages</u>	515
<u>Message ID : DXF4308D</u>	515
<u>Message ID : DXF4310D</u>	515
<u>Message ID : DXF4311D</u>	516
<u>Message ID : DXF4473D</u>	517
<u>Message ID : DXF4475D</u>	517
<u>Logger DXF: Errors</u>	519
<u>Message ID : DXF3205E</u>	519
<u>Message ID : DXF3206E</u>	520
<u>Message ID : DXF3207E</u>	520
<u>Message ID : DXF3208E</u>	521
<u>Message ID : DXF3209E</u>	522
<u>Message ID : DXF3215E</u>	523
<u>Message ID : DXF3216E</u>	524
<u>Message ID : DXF3217E</u>	525
<u>Message ID : DXF3218E</u>	526
<u>Message ID : DXF3219E</u>	526
<u>Message ID : DXF3220E</u>	527
<u>Message ID : DXF3221E</u>	528
<u>Message ID : DXF3222E</u>	529
<u>Message ID : DXF3223E</u>	530
<u>Message ID : DXF3224E</u>	531
<u>Message ID : DXF3225E</u>	532
<u>Message ID : DXF3226E</u>	532
<u>Message ID : DXF3227E</u>	533
<u>Message ID : DXF3228E</u>	534

Table of Contents

Logger DXF: Errors

<u>Message ID : DXF3229E.....</u>	535
<u>Message ID : DXF3230E.....</u>	536
<u>Message ID : DXF3231E.....</u>	537
<u>Message ID : DXF3232E.....</u>	538
<u>Message ID : DXF3233E.....</u>	538
<u>Message ID : DXF3238E.....</u>	539
<u>Message ID : DXF3239E.....</u>	540
<u>Message ID : DXF3240E.....</u>	541
<u>Message ID : DXF3241E.....</u>	542
<u>Message ID : DXF3242E.....</u>	543
<u>Message ID : DXF3243E.....</u>	544
<u>Message ID : DXF3244E.....</u>	544
<u>Message ID : DXF3245E.....</u>	545
<u>Message ID : DXF3246E.....</u>	546
<u>Message ID : DXF3247E.....</u>	547
<u>Message ID : DXF3248E.....</u>	548
<u>Message ID : DXF3249E.....</u>	549
<u>Message ID : DXF3250E.....</u>	550
<u>Message ID : DXF3251E.....</u>	550
<u>Message ID : DXF3252E.....</u>	551
<u>Message ID : DXF4100E.....</u>	552
<u>Message ID : DXF4101E.....</u>	553
<u>Message ID : DXF4102E.....</u>	554
<u>Message ID : DXF4105E.....</u>	554
<u>Message ID : DXF4106E.....</u>	555
<u>Message ID : DXF4107E.....</u>	556

Table of Contents

Logger DXF: Errors

<u>Message ID : DXF4108E</u>	557
<u>Message ID : DXF4109E</u>	558
<u>Message ID : DXF4111E</u>	559
<u>Message ID : DXF4112E</u>	560
<u>Message ID : DXF4113E</u>	561
<u>Message ID : DXF4114E</u>	562
<u>Message ID : DXF4115E</u>	563
<u>Message ID : DXF4116E</u>	564
<u>Message ID : DXF4117E</u>	565
<u>Message ID : DXF4119E</u>	566
<u>Message ID : DXF4120E</u>	567
<u>Message ID : DXF4121E</u>	567
<u>Message ID : DXF4124E</u>	568
<u>Message ID : DXF4125E</u>	569
<u>Message ID : DXF4133E</u>	570
<u>Message ID : DXF4134E</u>	570
<u>Message ID : DXF4135E</u>	571
<u>Message ID : DXF4136E</u>	572
<u>Message ID : DXF4137E</u>	573
<u>Message ID : DXF4138E</u>	574
<u>Message ID : DXF4139E</u>	575
<u>Message ID : DXF4140E</u>	576
<u>Message ID : DXF4141E</u>	576
<u>Message ID : DXF4142E</u>	577
<u>Message ID : DXF4149E</u>	578
<u>Message ID : DXF4150E</u>	579

Table of Contents

Logger DXF: Errors

<u>Message ID : DXF4151E</u>	580
<u>Message ID : DXF4152E</u>	580
<u>Message ID : DXF4153E</u>	581
<u>Message ID : DXF4155E</u>	582
<u>Message ID : DXF4156E</u>	582
<u>Message ID : DXF4157E</u>	583
<u>Message ID : DXF4158E</u>	584
<u>Message ID : DXF4159E</u>	585
<u>Message ID : DXF4160E</u>	585
<u>Message ID : DXF4162E</u>	586
<u>Message ID : DXF4163E</u>	587
<u>Message ID : DXF4164E</u>	588
<u>Message ID : DXF4165E</u>	589
<u>Message ID : DXF4166E</u>	589
<u>Message ID : DXF4167E</u>	590
<u>Message ID : DXF4168E</u>	591
<u>Message ID : DXF4169E</u>	592
<u>Message ID : DXF4170E</u>	592
<u>Message ID : DXF4171E</u>	593
<u>Message ID : DXF4172E</u>	594
<u>Message ID : DXF4173E</u>	594
<u>Message ID : DXF4174E</u>	595
<u>Message ID : DXF4215E</u>	596
<u>Message ID : DXF4227E</u>	597
<u>Message ID : DXF4228E</u>	597
<u>Message ID : DXF4229E</u>	598

Table of Contents

Logger DXF: Errors

<u>Message ID : DXF4230E</u>	599
<u>Message ID : DXF4231E</u>	599
<u>Message ID : DXF4232E</u>	600
<u>Message ID : DXF4233E</u>	601
<u>Message ID : DXF4234E</u>	601
<u>Message ID : DXF4235E</u>	602
<u>Message ID : DXF4236E</u>	603
<u>Message ID : DXF4237E</u>	603
<u>Message ID : DXF4238E</u>	604
<u>Message ID : DXF4239E</u>	605
<u>Message ID : DXF4240E</u>	605
<u>Message ID : DXF4241E</u>	606
<u>Message ID : DXF4243E</u>	607
<u>Message ID : DXF4244E</u>	607
<u>Message ID : DXF4247E</u>	608
<u>Message ID : DXF4248E</u>	609
<u>Message ID : DXF4249E</u>	610
<u>Message ID : DXF4250E</u>	611
<u>Message ID : DXF4251E</u>	612
<u>Message ID : DXF4252E</u>	612
<u>Message ID : DXF4255E</u>	613
<u>Message ID : DXF4266E</u>	614
<u>Message ID : DXF4270E</u>	615
<u>Message ID : DXF4271E</u>	616
<u>Message ID : DXF4272E</u>	617
<u>Message ID : DXF4282E</u>	618

Table of Contents

Logger DXF: Errors

<u>Message ID : DXF4286E</u>	619
<u>Message ID : DXF4287E</u>	620
<u>Message ID : DXF4288E</u>	621
<u>Message ID : DXF4289E</u>	622
<u>Message ID : DXF4290E</u>	623
<u>Message ID : DXF4291E</u>	624
<u>Message ID : DXF4292E</u>	625
<u>Message ID : DXF4294E</u>	625
<u>Message ID : DXF4295E</u>	626
<u>Message ID : DXF4296E</u>	627
<u>Message ID : DXF4297E</u>	627
<u>Message ID : DXF4298E</u>	628
<u>Message ID : DXF4299E</u>	629
<u>Message ID : DXF4300E</u>	630
<u>Message ID : DXF4301E</u>	631
<u>Message ID : DXF4302E</u>	632
<u>Message ID : DXF4303E</u>	633
<u>Message ID : DXF4304E</u>	633
<u>Message ID : DXF4306E</u>	634
<u>Message ID : DXF4312E</u>	635
<u>Message ID : DXF4313E</u>	636
<u>Message ID : DXF4314E</u>	636
<u>Message ID : DXF4315E</u>	637
<u>Message ID : DXF4325E</u>	638
<u>Message ID : DXF4326E</u>	639
<u>Message ID : DXF4328E</u>	640

Table of Contents

Logger DXF: Errors

<u>Message ID : DXF4330E</u>	641
<u>Message ID : DXF4331E</u>	642
<u>Message ID : DXF4334E</u>	642
<u>Message ID : DXF4335E</u>	643
<u>Message ID : DXF4336E</u>	644
<u>Message ID : DXF4340E</u>	645
<u>Message ID : DXF4341E</u>	645
<u>Message ID : DXF4342E</u>	646
<u>Message ID : DXF4343E</u>	647
<u>Message ID : DXF4346E</u>	647
<u>Message ID : DXF4347E</u>	648
<u>Message ID : DXF4349E</u>	649
<u>Message ID : DXF4350E</u>	650
<u>Message ID : DXF4353E</u>	650
<u>Message ID : DXF4354E</u>	651
<u>Message ID : DXF4355E</u>	652
<u>Message ID : DXF4356E</u>	652
<u>Message ID : DXF4357E</u>	653
<u>Message ID : DXF4358E</u>	654
<u>Message ID : DXF4360E</u>	655
<u>Message ID : DXF4367E</u>	656
<u>Message ID : DXF4368E</u>	657
<u>Message ID : DXF4376E</u>	658
<u>Message ID : DXF4377E</u>	659
<u>Message ID : DXF4379E</u>	659
<u>Message ID : DXF4381E</u>	660

Table of Contents

Logger DXF: Errors

<u>Message ID : DXF4382E</u>	661
<u>Message ID : DXF4391E</u>	662
<u>Message ID : DXF4392E</u>	663
<u>Message ID : DXF4393E</u>	664
<u>Message ID : DXF4394E</u>	665
<u>Message ID : DXF4395E</u>	665
<u>Message ID : DXF4396E</u>	666
<u>Message ID : DXF4400E</u>	667
<u>Message ID : DXF4401E</u>	667
<u>Message ID : DXF4403E</u>	668
<u>Message ID : DXF4404E</u>	669
<u>Message ID : DXF4405E</u>	670
<u>Message ID : DXF4407E</u>	671
<u>Message ID : DXF4408E</u>	671
<u>Message ID : DXF4409E</u>	672
<u>Message ID : DXF4427E</u>	673
<u>Message ID : DXF4430E</u>	674
<u>Message ID : DXF4432E</u>	675
<u>Message ID : DXF4433E</u>	676
<u>Message ID : DXF4434E</u>	676
<u>Message ID : DXF4435E</u>	677
<u>Message ID : DXF4436E</u>	678
<u>Message ID : DXF4437E</u>	678
<u>Message ID : DXF4438E</u>	679
<u>Message ID : DXF4439E</u>	680
<u>Message ID : DXF4440E</u>	680

Table of Contents

Logger DXF: Errors

<u>Message ID : DXF4441E</u>	681
<u>Message ID : DXF4442E</u>	682
<u>Message ID : DXF4443E</u>	682
<u>Message ID : DXF4444E</u>	683
<u>Message ID : DXF4445E</u>	684
<u>Message ID : DXF4446E</u>	684
<u>Message ID : DXF4447E</u>	685
<u>Message ID : DXF4448E</u>	686
<u>Message ID : DXF4449E</u>	686
<u>Message ID : DXF4450E</u>	687
<u>Message ID : DXF4451E</u>	688
<u>Message ID : DXF4452E</u>	688
<u>Message ID : DXF4453E</u>	689
<u>Message ID : DXF4454E</u>	690
<u>Message ID : DXF4455E</u>	690
<u>Message ID : DXF4456E</u>	691
<u>Message ID : DXF4457E</u>	692
<u>Message ID : DXF4458E</u>	692
<u>Message ID : DXF4459E</u>	693
<u>Message ID : DXF4460E</u>	694
<u>Message ID : DXF4461E</u>	694
<u>Message ID : DXF4462E</u>	695
<u>Message ID : DXF4463E</u>	696
<u>Message ID : DXF4464E</u>	696
<u>Message ID : DXF4465E</u>	697
<u>Message ID : DXF4466E</u>	698

Table of Contents

Logger DXF: Errors

<u>Message ID : DXF4467E</u>	699
<u>Message ID : DXF4468E</u>	699
<u>Message ID : DXF4469E</u>	700
<u>Message ID : DXF4470E</u>	701
<u>Message ID : DXF4471E</u>	701
<u>Message ID : DXF4472E</u>	702
<u>Message ID : DXF4474E</u>	703
<u>Message ID : DXF4476E</u>	703
<u>Message ID : DXF4477E</u>	704
<u>Message ID : DXF4478E</u>	705
<u>Message ID : DXF4479E</u>	706
<u>Message ID : DXF4480E</u>	706
<u>Message ID : DXF4482E</u>	707
<u>Message ID : DXF4483E</u>	708
<u>Message ID : DXF4484E</u>	709
<u>Message ID : DXF4486E</u>	710
<u>Message ID : DXF4494E</u>	710
<u>Message ID : DXF4498E</u>	711
<u>Message ID : DXF4499E</u>	712

Logger DXF: Fatal errors.....714

<u>Message ID : DXF4431E</u>	714
------------------------------------	-----

Logger DXF: Information.....715

<u>Message ID : DXF3211I</u>	715
<u>Message ID : DXF3235I</u>	716

Table of Contents

Logger DXF: Information

<u>Message ID : DXF3236I</u>	717
<u>Message ID : DXF3237I</u>	718
<u>Message ID : DXF4122I</u>	719
<u>Message ID : DXF4123I</u>	719
<u>Message ID : DXF4126I</u>	720
<u>Message ID : DXF4127I</u>	721
<u>Message ID : DXF4128I</u>	721
<u>Message ID : DXF4129I</u>	722
<u>Message ID : DXF4130I</u>	723
<u>Message ID : DXF4131I</u>	724
<u>Message ID : DXF4132I</u>	724
<u>Message ID : DXF4143I</u>	725
<u>Message ID : DXF4144I</u>	726
<u>Message ID : DXF4145I</u>	727
<u>Message ID : DXF4146I</u>	728
<u>Message ID : DXF4147I</u>	729
<u>Message ID : DXF4148I</u>	730
<u>Message ID : DXF4154I</u>	730
<u>Message ID : DXF4161I</u>	732
<u>Message ID : DXF4200I</u>	732
<u>Message ID : DXF4201I</u>	733
<u>Message ID : DXF4202I</u>	734
<u>Message ID : DXF4203I</u>	735
<u>Message ID : DXF4204I</u>	736
<u>Message ID : DXF4205I</u>	737
<u>Message ID : DXF4206I</u>	737

Table of Contents

Logger DXF: Information

<u>Message ID : DXF4207I</u>	738
<u>Message ID : DXF4208I</u>	739
<u>Message ID : DXF4209I</u>	740
<u>Message ID : DXF4210I</u>	741
<u>Message ID : DXF4211I</u>	742
<u>Message ID : DXF4212I</u>	742
<u>Message ID : DXF4213I</u>	743
<u>Message ID : DXF4214I</u>	744
<u>Message ID : DXF4216I</u>	745
<u>Message ID : DXF4217I</u>	746
<u>Message ID : DXF4218I</u>	746
<u>Message ID : DXF4219I</u>	747
<u>Message ID : DXF4220I</u>	748
<u>Message ID : DXF4221I</u>	749
<u>Message ID : DXF4222I</u>	750
<u>Message ID : DXF4223I</u>	751
<u>Message ID : DXF4224I</u>	751
<u>Message ID : DXF4225I</u>	752
<u>Message ID : DXF4226I</u>	753
<u>Message ID : DXF4253I</u>	754
<u>Message ID : DXF4257I</u>	755
<u>Message ID : DXF4258I</u>	756
<u>Message ID : DXF4259I</u>	757
<u>Message ID : DXF4260I</u>	757
<u>Message ID : DXF4261I</u>	758
<u>Message ID : DXF4262I</u>	759

Table of Contents

Logger DXF: Information

<u>Message ID : DXF4263I</u>	760
<u>Message ID : DXF4264I</u>	761
<u>Message ID : DXF4265I</u>	761
<u>Message ID : DXF4267I</u>	762
<u>Message ID : DXF4268I</u>	763
<u>Message ID : DXF4269I</u>	764
<u>Message ID : DXF4273I</u>	765
<u>Message ID : DXF4274I</u>	766
<u>Message ID : DXF4275I</u>	767
<u>Message ID : DXF4276I</u>	767
<u>Message ID : DXF4277I</u>	768
<u>Message ID : DXF4278I</u>	769
<u>Message ID : DXF4279I</u>	770
<u>Message ID : DXF4280I</u>	771
<u>Message ID : DXF4281I</u>	771
<u>Message ID : DXF4283I</u>	772
<u>Message ID : DXF4284I</u>	773
<u>Message ID : DXF4285I</u>	774
<u>Message ID : DXF4293I</u>	775
<u>Message ID : DXF4309I</u>	776
<u>Message ID : DXF4316I</u>	777
<u>Message ID : DXF4317I</u>	777
<u>Message ID : DXF4318I</u>	778
<u>Message ID : DXF4319I</u>	779
<u>Message ID : DXF4320I</u>	780
<u>Message ID : DXF4321I</u>	781

Table of Contents

Logger DXF: Information

<u>Message ID : DXF4322I</u>	781
<u>Message ID : DXF4323I</u>	782
<u>Message ID : DXF4329I</u>	783
<u>Message ID : DXF4332I</u>	784
<u>Message ID : DXF4344I</u>	785
<u>Message ID : DXF4345I</u>	786
<u>Message ID : DXF4352I</u>	787
<u>Message ID : DXF4361I</u>	787
<u>Message ID : DXF4362I</u>	788
<u>Message ID : DXF4363I</u>	789
<u>Message ID : DXF4364I</u>	790
<u>Message ID : DXF4365I</u>	791
<u>Message ID : DXF4366I</u>	792
<u>Message ID : DXF4369I</u>	793
<u>Message ID : DXF4370I</u>	794
<u>Message ID : DXF4371I</u>	795
<u>Message ID : DXF4372I</u>	796
<u>Message ID : DXF4375I</u>	797
<u>Message ID : DXF4378I</u>	797
<u>Message ID : DXF4380I</u>	798
<u>Message ID : DXF4383I</u>	799
<u>Message ID : DXF4384I</u>	800
<u>Message ID : DXF4385I</u>	801
<u>Message ID : DXF4386I</u>	802
<u>Message ID : DXF4387I</u>	803
<u>Message ID : DXF4388I</u>	804

Table of Contents

Logger DXF: Information

<u>Message ID : DXF4389I</u>	805
<u>Message ID : DXF4390I</u>	806
<u>Message ID : DXF4397I</u>	806
<u>Message ID : DXF4399I</u>	807
<u>Message ID : DXF4414I</u>	808
<u>Message ID : DXF4415I</u>	809
<u>Message ID : DXF4416I</u>	810
<u>Message ID : DXF4417I</u>	810
<u>Message ID : DXF4418I</u>	811
<u>Message ID : DXF4419I</u>	812
<u>Message ID : DXF4420I</u>	813
<u>Message ID : DXF4421I</u>	814
<u>Message ID : DXF4422I</u>	815
<u>Message ID : DXF4423I</u>	815
<u>Message ID : DXF4424I</u>	816
<u>Message ID : DXF4425I</u>	818
<u>Message ID : DXF4429I</u>	819
<u>Message ID : DXF4481I</u>	819
<u>Message ID : DXF4485I</u>	820
<u>Message ID : DXF4487I</u>	821
<u>Message ID : DXF4488I</u>	822
<u>Message ID : DXF4489I</u>	823
<u>Message ID : DXF4490I</u>	823
<u>Message ID : DXF4491I</u>	824
<u>Message ID : DXF4492I</u>	825
<u>Message ID : DXF4493I</u>	826

Table of Contents

Logger DXF: Information

<u>Message ID : DXF4495I</u>	826
<u>Message ID : DXF4496I</u>	827
<u>Message ID : DXF4497I</u>	828

Logger DXF: Warnings.....830

<u>Message ID : DXF3210W</u>	830
<u>Message ID : DXF4103W</u>	831
<u>Message ID : DXF4104W</u>	831
<u>Message ID : DXF4118W</u>	832
<u>Message ID : DXF4242W</u>	833
<u>Message ID : DXF4254W</u>	834
<u>Message ID : DXF4307W</u>	835
<u>Message ID : DXF4324W</u>	836
<u>Message ID : DXF4327W</u>	836
<u>Message ID : DXF4333W</u>	837
<u>Message ID : DXF4337W</u>	838
<u>Message ID : DXF4338W</u>	839
<u>Message ID : DXF4339W</u>	840
<u>Message ID : DXF4351W</u>	840
<u>Message ID : DXF4359W</u>	841
<u>Message ID : DXF4373W</u>	842
<u>Message ID : DXF4398W</u>	843
<u>Message ID : DXF4406W</u>	844
<u>Message ID : DXF4410W</u>	845
<u>Message ID : DXF4413W</u>	846
<u>Message ID : DXF4428W</u>	846

Table of Contents

<u>Logger FAM: Information</u>	848
<u>Message ID : FAM7001I</u>	848
<u>Message ID : FAM7004I</u>	848
<u>Message ID : FAM7005I</u>	850
<u>Message ID : FAM7006I</u>	852
<u>Message ID : FAM7007I</u>	853
<u>Logger FAM: Warnings</u>	855
<u>Message ID : FAM7002W</u>	855
<u>Logger FUS: Errors</u>	856
<u>Message ID : FUS3368E</u>	856
<u>Logger FUS: Information</u>	857
<u>Message ID : FUS3366I</u>	857
<u>Logger FUS: Warnings</u>	858
<u>Message ID : FUS3367W</u>	858
<u>Logger POL: Errors</u>	859
<u>Message ID : POL4556E</u>	859
<u>Message ID : POL4580E</u>	860
<u>Message ID : POL4613E</u>	861
<u>Message ID : POL4701E</u>	862
<u>Message ID : POL4704E</u>	863

Table of Contents

<u>Logger POL: Fatal errors</u>	864
<u>Message ID : POL4510F</u>	864
<u>Message ID : POL4516F</u>	865
<u>Message ID : POL4528F</u>	866
<u>Message ID : POL4530F</u>	867
<u>Message ID : POL4545F</u>	868
<u>Message ID : POL4564F</u>	868
<u>Message ID : POL4581F</u>	869
<u>Message ID : POL4593F</u>	870
<u>Message ID : POL4614F</u>	871
<u>Logger POL: Information</u>	873
<u>Message ID : POL4537I</u>	873
<u>Message ID : POL4553I</u>	874
<u>Message ID : POL4573I</u>	875
<u>Message ID : POL4574I</u>	876
<u>Message ID : POL4575I</u>	877
<u>Message ID : POL4576I</u>	877
<u>Message ID : POL4582I</u>	878
<u>Message ID : POL4615I</u>	879
<u>Message ID : POL4702I</u>	880
<u>Logger POL: Warnings</u>	882
<u>Message ID : POL4703W</u>	882

Table of Contents

<u>Logger VAD: Errors</u>	883
<u>Message ID : VAD4642E</u>	883
<u>Logger VAD: Information</u>	885
<u>Message ID : VAD4641I</u>	885
<u>Logger VAD: Warnings</u>	887
<u>Message ID : VAD4643W</u>	887
<u>Logger VMD: Errors</u>	888
<u>Message ID : VMD3203E</u>	888
<u>Message ID : VMD3204E</u>	889
<u>Message ID : VMD3503E</u>	889
<u>Message ID : VMD3507E</u>	890
<u>Message ID : VMD3509E</u>	891
<u>Message ID : VMD3510E</u>	892
<u>Message ID : VMD3514E</u>	892
<u>Message ID : VMD3517E</u>	893
<u>Message ID : VMD3520E</u>	894
<u>Message ID : VMD3525E</u>	894
<u>Message ID : VMD3527E</u>	895
<u>Message ID : VMD3533E</u>	896
<u>Message ID : VMD3544E</u>	896
<u>Message ID : VMD3546E</u>	897
<u>Message ID : VMD3550E</u>	898
<u>Message ID : VMD3559E</u>	899
<u>Message ID : VMD3563E</u>	899

Table of Contents

Logger VMD: Errors

<u>Message ID : VMD3572E</u>	900
<u>Message ID : VMD3578E</u>	901
<u>Message ID : VMD3581E</u>	902
<u>Message ID : VMD3596E</u>	902
<u>Message ID : VMD3597E</u>	903
<u>Message ID : VMD3605E</u>	904
<u>Message ID : VMD3607E</u>	905
<u>Message ID : VMD3611E</u>	905
<u>Message ID : VMD3612E</u>	906
<u>Message ID : VMD3616E</u>	907
<u>Message ID : VMD3617E</u>	907
<u>Message ID : VMD3628E</u>	908
<u>Message ID : VMD3629E</u>	909
<u>Message ID : VMD3633E</u>	910
<u>Message ID : VMD3644E</u>	910
<u>Message ID : VMD3645E</u>	911
<u>Message ID : VMD3651E</u>	912
<u>Message ID : VMD3655E</u>	913
<u>Message ID : VMD3665E</u>	913
<u>Message ID : VMD3666E</u>	914
<u>Message ID : VMD3667E</u>	915
<u>Message ID : VMD3674E</u>	915
<u>Message ID : VMD3676E</u>	916
<u>Message ID : VMD3681E</u>	917
<u>Message ID : VMD3683E</u>	917
<u>Message ID : VMD3685E</u>	918

Table of Contents

Logger VMD: Errors

<u>Message ID : VMD3686E</u>	919
<u>Message ID : VMD3689E</u>	919
<u>Message ID : VMD3697E</u>	920
<u>Message ID : VMD3700E</u>	921
<u>Message ID : VMD3702E</u>	922
<u>Message ID : VMD3707E</u>	922
<u>Message ID : VMD3713E</u>	923
<u>Message ID : VMD3718E</u>	924
<u>Message ID : VMD3723E</u>	924
<u>Message ID : VMD3724E</u>	925
<u>Message ID : VMD3726E</u>	926
<u>Message ID : VMD3730E</u>	926
<u>Message ID : VMD3734E</u>	927
<u>Message ID : VMD3736E</u>	928
<u>Message ID : VMD3747E</u>	928
<u>Message ID : VMD3748E</u>	929
<u>Message ID : VMD3750E</u>	930
<u>Message ID : VMD3758E</u>	930
<u>Message ID : VMD3759E</u>	931
<u>Message ID : VMD3760E</u>	932
<u>Message ID : VMD3761E</u>	932
<u>Message ID : VMD3779E</u>	933
<u>Message ID : VMD3780E</u>	934
<u>Message ID : VMD3782E</u>	935
<u>Message ID : VMD3784E</u>	936
<u>Message ID : VMD3786E</u>	937

Table of Contents

Logger VMD: Errors

<u>Message ID : VMD3787E</u>	938
<u>Message ID : VMD3788E</u>	938
<u>Message ID : VMD3789E</u>	939
<u>Message ID : VMD3790E</u>	940
<u>Message ID : VMD3792E</u>	941
<u>Message ID : VMD3795E</u>	942
<u>Message ID : VMD3796E</u>	943
<u>Message ID : VMD3799E</u>	943
<u>Message ID : VMD3801E</u>	944
<u>Message ID : VMD3802E</u>	945
<u>Message ID : VMD3807E</u>	946
<u>Message ID : VMD3809E</u>	947
<u>Message ID : VMD3811E</u>	947
<u>Message ID : VMD3812E</u>	949
<u>Message ID : VMD3816E</u>	950
<u>Message ID : VMD3819E</u>	950
<u>Message ID : VMD3822E</u>	951
<u>Message ID : VMD3828E</u>	952
<u>Message ID : VMD3830E</u>	953
<u>Message ID : VMD3831E</u>	954
<u>Message ID : VMD3833E</u>	955
<u>Message ID : VMD3834E</u>	956
<u>Message ID : VMD3835E</u>	957
<u>Message ID : VMD3837E</u>	958
<u>Message ID : VMD3838E</u>	958
<u>Message ID : VMD3840E</u>	959

Table of Contents

Logger VMD: Errors

<u>Message ID : VMD3843E</u>	960
<u>Message ID : VMD3844E</u>	961
<u>Message ID : VMD3845E</u>	962
<u>Message ID : VMD3846E</u>	963
<u>Message ID : VMD3848E</u>	964
<u>Message ID : VMD3849E</u>	965
<u>Message ID : VMD3855E</u>	966
<u>Message ID : VMD3858E</u>	967
<u>Message ID : VMD3864E</u>	968
<u>Message ID : VMD3865E</u>	969
<u>Message ID : VMD3866E</u>	970
<u>Message ID : VMD3867E</u>	970
<u>Message ID : VMD3872E</u>	971
<u>Message ID : VMD3873E</u>	972
<u>Message ID : VMD3874E</u>	973
<u>Message ID : VMD3875E</u>	974
<u>Message ID : VMD3876E</u>	975
<u>Message ID : VMD3877E</u>	975
<u>Message ID : VMD3878E</u>	976
<u>Message ID : VMD3879E</u>	977
<u>Message ID : VMD3888E</u>	978
<u>Message ID : VMD3890E</u>	979
<u>Message ID : VMD3891E</u>	980
<u>Message ID : VMD3892E</u>	980
<u>Message ID : VMD3901E</u>	981
<u>Message ID : VMD3903E</u>	982

Table of Contents

Logger VMD: Errors

<u>Message ID : VMD3905E</u>	983
<u>Message ID : VMD3907E</u>	984
<u>Message ID : VMD3909E</u>	985
<u>Message ID : VMD3911E</u>	986
<u>Message ID : VMD3913E</u>	987
<u>Message ID : VMD3915E</u>	988
<u>Message ID : VMD3916E</u>	989
<u>Message ID : VMD3917E</u>	989
<u>Message ID : VMD3918E</u>	990
<u>Message ID : VMD3922E</u>	991
<u>Message ID : VMD3923E</u>	992
<u>Message ID : VMD3927E</u>	993
<u>Message ID : VMD3929E</u>	994
<u>Message ID : VMD3932E</u>	994
<u>Message ID : VMD4245E</u>	995
<u>Message ID : VMD4594E</u>	996
<u>Message ID : VMD4606E</u>	997
<u>Message ID : VMD4607E</u>	998
<u>Message ID : VMD4608E</u>	999
<u>Message ID : VMD4609E</u>	1000
<u>Message ID : VMD4610E</u>	1001
<u>Message ID : VMD4612E</u>	1002
<u>Message ID : VMD4617E</u>	1002

Table of Contents

<u>Logger VMD: Fatal errors</u>	1004
<u>Message ID : VMD3767F</u>	1004
<u>Message ID : VMD3768F</u>	1005
<u>Message ID : VMD3769F</u>	1006
<u>Message ID : VMD3770F</u>	1006
<u>Message ID : VMD3771F</u>	1008
<u>Message ID : VMD3772F</u>	1009
<u>Message ID : VMD3797F</u>	1009
<u>Message ID : VMD3894F</u>	1010
<u>Message ID : VMD4595F</u>	1011
<u>Message ID : VMD4616F</u>	1012
<u>Logger VMD: Information</u>	1014
<u>Message ID : VMD3201I</u>	1014
<u>Message ID : VMD3202I</u>	1015
<u>Message ID : VMD3548I</u>	1015
<u>Message ID : VMD3558I</u>	1016
<u>Message ID : VMD3626I</u>	1017
<u>Message ID : VMD3640I</u>	1018
<u>Message ID : VMD3663I</u>	1019
<u>Message ID : VMD3773I</u>	1020
<u>Message ID : VMD3778I</u>	1021
<u>Message ID : VMD3781I</u>	1021
<u>Message ID : VMD3785I</u>	1022
<u>Message ID : VMD3794I</u>	1023
<u>Message ID : VMD3798I</u>	1024
<u>Message ID : VMD3800I</u>	1025

Table of Contents

Logger VMD: Information

<u>Message ID : VMD3803I</u>	1026
<u>Message ID : VMD3804I</u>	1026
<u>Message ID : VMD3814I</u>	1027
<u>Message ID : VMD3815I</u>	1028
<u>Message ID : VMD3817I</u>	1029
<u>Message ID : VMD3818I</u>	1030
<u>Message ID : VMD3820I</u>	1031
<u>Message ID : VMD3821I</u>	1032
<u>Message ID : VMD3823I</u>	1033
<u>Message ID : VMD3825I</u>	1034
<u>Message ID : VMD3827I</u>	1035
<u>Message ID : VMD3829I</u>	1036
<u>Message ID : VMD3832I</u>	1036
<u>Message ID : VMD3836I</u>	1037
<u>Message ID : VMD3839I</u>	1038
<u>Message ID : VMD3841I</u>	1039
<u>Message ID : VMD3842I</u>	1040
<u>Message ID : VMD3847I</u>	1041
<u>Message ID : VMD3851I</u>	1042
<u>Message ID : VMD3852I</u>	1043
<u>Message ID : VMD3853I</u>	1044
<u>Message ID : VMD3854I</u>	1045
<u>Message ID : VMD3856I</u>	1046
<u>Message ID : VMD3857I</u>	1046
<u>Message ID : VMD3859I</u>	1047
<u>Message ID : VMD3861I</u>	1048

Table of Contents

Logger VMD: Information

<u>Message ID : VMD3862I</u>	1049
<u>Message ID : VMD3863I</u>	1050
<u>Message ID : VMD3868I</u>	1051
<u>Message ID : VMD3870I</u>	1052
<u>Message ID : VMD3880I</u>	1053
<u>Message ID : VMD3881I</u>	1054
<u>Message ID : VMD3883I</u>	1054
<u>Message ID : VMD3885I</u>	1055
<u>Message ID : VMD3886I</u>	1057
<u>Message ID : VMD3893I</u>	1058
<u>Message ID : VMD3895I</u>	1059
<u>Message ID : VMD3896I</u>	1059
<u>Message ID : VMD3897I</u>	1060
<u>Message ID : VMD3898I</u>	1061
<u>Message ID : VMD3900I</u>	1062
<u>Message ID : VMD3902I</u>	1063
<u>Message ID : VMD3904I</u>	1064
<u>Message ID : VMD3906I</u>	1065
<u>Message ID : VMD3908I</u>	1066
<u>Message ID : VMD3910I</u>	1067
<u>Message ID : VMD3912I</u>	1068
<u>Message ID : VMD3914I</u>	1069
<u>Message ID : VMD3919I</u>	1070
<u>Message ID : VMD3926I</u>	1071
<u>Message ID : VMD3930I</u>	1072
<u>Message ID : VMD3934I</u>	1072

Table of Contents

Logger VMD: Information

<u>Message ID : VMD3935I</u>	1073
<u>Message ID : VMD4246I</u>	1074
<u>Message ID : VMD4611I</u>	1075
<u>Message ID : VMD4619I</u>	1076
<u>Message ID : VMD4620I</u>	1077

Logger VMD: Warnings.....**1078**

<u>Message ID : VMD3714W</u>	1078
<u>Message ID : VMD3762W</u>	1078
<u>Message ID : VMD3805W</u>	1079
<u>Message ID : VMD3806W</u>	1080
<u>Message ID : VMD3813W</u>	1081
<u>Message ID : VMD3824W</u>	1082
<u>Message ID : VMD3826W</u>	1083
<u>Message ID : VMD3850W</u>	1084
<u>Message ID : VMD3860W</u>	1085
<u>Message ID : VMD3869W</u>	1085
<u>Message ID : VMD3871W</u>	1086
<u>Message ID : VMD3882W</u>	1087
<u>Message ID : VMD3887W</u>	1088
<u>Message ID : VMD3889W</u>	1089
<u>Message ID : VMD3899W</u>	1090
<u>Message ID : VMD3920W</u>	1091
<u>Message ID : VMD3921W</u>	1091
<u>Message ID : VMD3924W</u>	1092
<u>Message ID : VMD3925W</u>	1093

Table of Contents

Logger VMD: Warnings

<u>Message ID : VMD3928W</u>	1094
<u>Message ID : VMD3931W</u>	1095
<u>Message ID : VMD3933W</u>	1096
<u>Message ID : VMD4618W</u>	1097
<u>Message ID : VMD4621W</u>	1098
<u>Message ID : VMD4622W</u>	1099
<u>Message ID : VMD4623W</u>	1100
<u>Message ID : VMD4624W</u>	1101
<u>Message ID : VMD4625W</u>	1102
<u>Message ID : VMD4636W</u>	1103
<u>Message ID : VMD4639W</u>	1104
<u>Message ID : VMD4640W</u>	1105

Logger XFM: Errors.....1107

<u>Message ID : XFM4501E</u>	1107
<u>Message ID : XFM4502E</u>	1108
<u>Message ID : XFM4504E</u>	1108
<u>Message ID : XFM4535E</u>	1109
<u>Message ID : XFM4568E</u>	1110
<u>Message ID : XFM4589E</u>	1111
<u>Message ID : XFM4590E</u>	1112
<u>Message ID : XFM4591E</u>	1113

Logger XFM: Fatal errors.....1114

<u>Message ID : XFM4508E</u>	1114
<u>Message ID : XFM4509E</u>	1114

Table of Contents

Logger XFM: Fatal errors

<u>Message ID : XFM4518F</u>	1115
<u>Message ID : XFM4519F</u>	1116
<u>Message ID : XFM4525F</u>	1117
<u>Message ID : XFM4532F</u>	1118
<u>Message ID : XFM4536F</u>	1119
<u>Message ID : XFM4539F</u>	1120
<u>Message ID : XFM4540F</u>	1120
<u>Message ID : XFM4541F</u>	1121
<u>Message ID : XFM4544F</u>	1122
<u>Message ID : XFM4546F</u>	1123
<u>Message ID : XFM4561F</u>	1124
<u>Message ID : XFM4565F</u>	1125

Logger XFM: Information.....1126

<u>Message ID : XFM4507I</u>	1126
<u>Message ID : XFM4517I</u>	1126
<u>Message ID : XFM4522I</u>	1127
<u>Message ID : XFM4526I</u>	1128
<u>Message ID : XFM4549I</u>	1129
<u>Message ID : XFM4557I</u>	1130
<u>Message ID : XFM4559I</u>	1131

Logger XFM: Warnings.....1132

<u>Message ID : XFM4550W</u>	1132
------------------------------------	------

Logger CGA: Errors

Message ID : CGA2614E

Severity

Error

Long Form

Syntax error: Domain name '*' is reserved

Short Form

No short form is provided for this message type

Description

None

Message ID : CGA2617E

Severity

Error

Long Form

[[{0}]] Set [{1}] used but not defined

Short Form

No short form is provided for this message type

Description

None

Message ID : CGA2618E

Severity

Error

Long Form

Failed to import password object

Short Form

No short form is provided for this message type

Message ID : CGA2617E

Description

None

Message ID : CGA2619E

Severity

Error

Long Form

Policy [{0}]: Invalid policy

Short Form

No short form is provided for this message type

Description

None

Message ID : CGA2620E

Severity

Error

Message ID : CGA2618E

Long Form

Policy [{0}]: Invalid policy length

Short Form

No short form is provided for this message type

Description

None

Message ID : CGA2621E

Severity

Error

Long Form

Policy [{0}]: Policy import failed

Short Form

No short form is provided for this message type

Message ID : CGA2620E

Description

None

Message ID : CGA2624E

Severity

Error

Long Form

Policy [{0}]: Failed to import Name Identifier

Short Form

Name import failed

Parameters

Label	CEF Label	Type	Usage
pol	cs1	Text	Policy name

Description

None

Message ID : CGA2621E

Message ID : CGA2625E

Severity

Error

Long Form

Failed to import keys

Short Form

Keys import failed

Parameters

No parameters are provided for this message type

Description

None

Message ID : CGA2626E

Severity

Error

Message ID : CGA2625E

Long Form

Policy [{0}]: Invalid root path

Short Form

Invalid rootpath

Parameters

Label	CEF Label	Type	Usage
pol	cs1	Text	Policy name

Description

None

Message ID : CGA2627E

Severity

Error

Long Form

Policy [{0}]: Failed to import root path

Message ID : CGA2626E

Short Form

Import rootpath fail

Parameters

Label	CEF Label	Type	Usage
pol	cs1	Text	Policy name

Description

None

Message ID : CGA2628E

Severity

Error

Long Form

Policy [{0}]: [{1}] Set [{2}] not defined

Short Form

Undefined policy type/set

Message ID : CGA2627E

Parameters

Label	CEF Label	Type	Usage
pol	cs1	Text	Policy name
oType	vds_oType	Text	Object type in policy rule
oName	vds_oName	Text	Object name in policy rule

Description

None

Message ID : CGA2629E

Severity

Error

Long Form

Policy [{0}]: Key rule not yet built

Short Form

Invalid key rule

Message ID : CGA2628E

Parameters

Label	CEF Label	Type	Usage
pol	cs1	Text	Policy name

Description

None

Message ID : CGA2634E

Severity

Error

Long Form

Policy [{0}]: Invalid Rule

Short Form

Invalid rules object

Parameters

Label	CEF Label	Type	Usage
pol	cs1	Text	Policy name

Message ID : CGA2629E

Description

None

Message ID : CGA2635E

Severity

Error

Long Form

Policy [{0}]: Invalid syntax for key effect [{1}]

Short Form

Invalid key effect

Parameters

Label	CEF Label	Type	Usage
pol	cs1	Text	Policy name
act	act	Text	Action being requested or performed

Message ID : CGA2634E

Description

None

Message ID : CGA2636E

Severity

Error

Long Form

Policy [{0}]: Invalid name and/or access

Short Form

Invalid name/access

Parameters

Label	CEF Label	Type	Usage
pol	cs1	Text	Policy name

Description

None

Message ID : CGA2635E

Message ID : CGA2637E

Severity

Error

Long Form

Policy [{0}]: Invalid rule syntax: Effect not defined

Short Form

Undefined effect

Parameters

Label	CEF Label	Type	Usage
pol	cs1	Text	Policy name

Description

None

Message ID : CGA2638E

Severity

Error

Long Form

Policy [{0}]: Invalid rule syntax: Action [{1}] not defined

Short Form

Undefined action

Parameters

Label	CEF Label	Type	Usage
pol	cs1	Text	Policy name
act	act	Text	Action being requested or performed

Description

None

Message ID : CGA2639E

Message ID : CGA2638E

Severity

Error

Long Form

Policy [{0}]: Invalid rule syntax: GoTo label [{1}] not defined

Short Form

Undefined label

Parameters

Label	CEF Label	Type	Usage
pol	cs1	Text	Policy name
label	vds_label	Text	Label in rule sequence

Description

None

Message ID : CGA2645E

Message ID : CGA2639E

Severity

Error

Long Form

Policy [{0}]: Recursive GoTo detected at rule number [{1}]

Short Form

Recursive goto

Parameters

Label	CEF Label	Type	Usage
pol	cs1	Text	Policy name
ruleNo	vds_ruleNo	Numeric	Index into policy rule set

Description

None

Message ID : CGA2648E

Message ID : CGA2645E

Severity

Error

Long Form

Policy [{0}]: Invalid GoTo - Missing destination label

Short Form

Invalid goto

Parameters

Label	CEF Label	Type	Usage
pol	cs1	Text	Policy name

Description

None

Message ID : CGA2649E

Severity

Error

Message ID : CGA2648E

Long Form

Policy [{0}]: Invalid effect syntax [{1}]

Short Form

Invalid syntax

Parameters

Label	CEF Label	Type	Usage
pol	cs1	Text	Policy name
act	act	Text	Action being requested or performed

Description

None

Message ID : CGA2650E

Severity

Error

Message ID : CGA2649E

Long Form

Policy [{0}]: Invalid action syntax [{1}]

Short Form

Invalid action

Parameters

Label	CEF Label	Type	Usage
pol	cs1	Text	Policy name
act	act	Text	Action being requested or performed

Description

None

Message ID : CGA2651E

Severity

Error

Message ID : CGA2650E

Long Form

No policy defined for [{0}] set [{1}]

Short Form

Undefined policy set

Parameters

Label	CEF Label	Type	Usage
oType	vds_oType	Text	Object type in policy rule
oName	vds_oName	Text	Object name in policy rule

Description

None

Message ID : CGA2652E

Severity

Error

Message ID : CGA2651E

Long Form

Policy [{0}]: old and new key rule numbers do not match [old {1}, new {2}]

Short Form

Mismatched rule numbers

Parameters

Label	CEF Label	Type	Usage
pol	cs1	Text	Policy name
ruleNo	vds_ruleNo	Numeric	Index into policy rule set
altRuleNo	vds_altRuleNo	Numeric	Alternate rule number

Description

None

Message ID : CGA2653E

Severity

Error

Message ID : CGA2652E

Long Form

Policy [{0}]: old and new key names do not match [key rule {1}, old {2}, new {3}]

Short Form

Mismatched key names

Parameters

Label	CEF Label	Type	Usage
pol	cs1	Text	Policy name
ruleNo	vds_ruleNo	Numeric	Index into policy rule set
key	cs3	Text	Name of key or key pair
altKey	vds_altKey	Text	Name of alternate key for multi-key operations

Description

None

Message ID : CGA2654E

Severity

Error

Message ID : CGA2653E

Long Form

Policy [{0}]: old and new key resources do not match [key rule {1}]

Short Form

Mismatched key resource

Parameters

Label	CEF Label	Type	Usage
pol	cs1	Text	Policy name
ruleNo	vds_ruleNo	Numeric	Index into policy rule set

Description

None

Message ID : CGA2655E

Severity

Error

Message ID : CGA2654E

Long Form

Failed to import key [{0}]

Short Form

Key import failed

Parameters

Label	CEF Label	Type	Usage
key	cs3	Text	Name of key or key pair

Description

None

Message ID : CGA2656E

Severity

Error

Long Form

Failed to find encryption key [%lld]

Message ID : CGA2655E

Short Form

Encryption key not found

Parameters

No parameters are provided for this message type

Description

None

Message ID : CGA2657E

Severity

Error

Long Form

Failed to validate policy on [{0}], rekey in progress

Short Form

Policy failure, rekey in progress

Message ID : CGA2656E

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : CGA2658E

Severity

Error

Long Form

Failed to validate policy on [{0}]

Short Form

Policy validation failure

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Message ID : CGA2657E

Description

None

Message ID : CGA2659E

Severity

Error

Long Form

Unsupported key type in policy on [{0}]

Short Form

Unsupported key type in policy

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : CGA2658E

Message ID : CGA2662E

Severity

Error

Long Form

Failed to validate key [{0}]

Short Form

Key validation failed

Parameters

Label	CEF Label	Type	Usage
key	cs3	Text	Name of key or key pair

Description

None

Message ID : CGA3003E

Message ID : CGA2662E

Severity

Error

Long Form

EVENT: {0}

Short Form

Event

Parameters

Label	CEF Label	Type	Usage
showStr	reason	Text	Code specifying reason for allowing access, if any

Description

None

Message ID : CGA3004E

Severity

Error

Message ID : CGA3003E

Long Form

An invalid host password was entered

Short Form

Invalid host password

Parameters

No parameters are provided for this message type

Description

None

Message ID : CGA3007E

Severity

Error

Long Form

NOTUSED

Message ID : CGA3004E

Short Form

No short form is provided for this message type

Description

None

Message ID : CGA3008E

Severity

Error

Long Form

Pid [{0}] has not been initialized properly in [{1}]

Short Form

Bad caller

Parameters

Label	CEF Label	Type	Usage
pid	dvcpid	Numeric	Numeric process ID

Message ID : CGA3007E

Label	CEF Label	Type	Usage
func	vds_func	Text	A function name

Description

Internal error; try start/stop of agent or reinstallation of agent.

Message ID : CGA3009E

Severity

Error

Long Form

NOTUSED

Short Form

No short form is provided for this message type

Description

An internal error occurred. Please contact Thales Support.

Message ID : CGA3010E

Severity

Error

Long Form

Failed to write to file [{0}] in [{1}]

Short Form

Write fail

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file
func	vds_func	Text	A function name

Description

None

Message ID : CGA3011E

Severity

Error

Long Form

Failed to read file [{0}] in [{1}]

Short Form

Read fail

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file
func	vds_func	Text	A function name

Description

None

Message ID : CGA3012E

Severity

Error

Long Form

NOTUSED

Short Form

No short form is provided for this message type

Description

None

Message ID : CGA3013E

Severity

Error

Long Form

NOTUSED

Message ID : CGA3012E

Short Form

No short form is provided for this message type

Description

None

Message ID : CGA3014E

Severity

Error

Long Form

NOTUSED

Short Form

No short form is provided for this message type

Description

None

Message ID : CGA3013E

Message ID : CGA3015E

Severity

Error

Long Form

Bad version [{0}] in configuration

Short Form

Bad config version

Parameters

Label	CEF Label	Type	Usage
verno	vds_verno	Numeric	A version number

Description

None

Message ID : CGA3016E

Severity

Error

Long Form

NOTUSED

Short Form

No short form is provided for this message type

Description

None

Message ID : CGA3017E

Severity

Error

Long Form

Failed to apply new security configuration

Message ID : CGA3016E

Short Form

Security config update failed

Parameters

No parameters are provided for this message type

Description

None

Message ID : CGA3018E

Severity

Error

Long Form

Challenge/Response: An invalid challenge/response was entered

Short Form

Invalid challenge/response

Message ID : CGA3017E

Parameters

No parameters are provided for this message type

Description

None

Message ID : CGA3021E

Severity

Error

Long Form

Challenge/Response: Error processing challenge/response

Short Form

Challenge/Response encryption error

Parameters

No parameters are provided for this message type

Message ID : CGA3018E

Description

None

Message ID : CGA3022E

Severity

Error

Long Form

Key Protection: Key integrity check failed in [{0}]

Short Form

Key integrity check failed

Parameters

Label	CEF Label	Type	Usage
func	vds_func	Text	A function name

Description

None

Message ID : CGA3021E

Message ID : CGA3023E

Severity

Error

Long Form

NOTUSED

Short Form

No short form is provided for this message type

Description

None

Message ID : CGA3024E

Severity

Error

Long Form

Key Protection: Extract rkey: Hardware signature has changed

Message ID : CGA3023E

Short Form

Hardware signature changed

Parameters

No parameters are provided for this message type

Description

None

Message ID : CGA3059E

Severity

Error

Long Form

[AUDIT] Process[{0}] Pid[{1}] Uid[{2}] Operation[{3}] File[{4}] Failure[{5}] Effect[PERMIT]

Short Form

Sysfile modified error

Message ID : CGA3024E

Parameters

Label	CEF Label	Type	Usage
command	command	Text	Task struct comm field
pid	dvcpid	Numeric	Numeric process ID
uid	suid	Numeric	User id
op_name	op_name	Text	Operation name
filePath	filePath	Text	Full path to file
ecode	cn1	Numeric	An error code

Description

None

Message ID : CGA3060E

Severity

Error

Long Form

[ALARM] Process[{0}] Pid[{1}] Uid[{2}] Operation[{3}] File[{4}] Effect[DENIED]

Message ID : CGA3059E

Short Form

Sysfile protected

Parameters

Label	CEF Label	Type	Usage
command	command	Text	Task struct comm field
pid	dvcpid	Numeric	Numeric process ID
uid	suid	Numeric	User id
op_name	op_name	Text	Operation name
filePath	filePath	Text	Full path to file

Description

None

Message ID : CGA3061E

Severity

Error

Message ID : CGA3060E

Long Form

Key Protection: Encryption/Decryption: Bad arguments in function [{0}]

Short Form

En/Decrypt BadArgs

Parameters

Label	CEF Label	Type	Usage
func	vds_func	Text	A function name

Description

None

Message ID : CGA3062E

Severity

Error

Long Form

Key Protection: Private key write: Null key in function [{0}]

Message ID : CGA3061E

Short Form

PrivKeyWrite NullKey

Parameters

Label	CEF Label	Type	Usage
func	vds_func	Text	A function name

Description

None

Message ID : CGA3063E

Severity

Error

Long Form

Key Protection: Private key write: Invalid key length in function [{0}]

Short Form

PrivKeyWrite InvalKeylen

Message ID : CGA3062E

Parameters

Label	CEF Label	Type	Usage
func	vds_func	Text	A function name

Description

None

Message ID : CGA3064E

Severity

Error

Long Form

Key Protection: Verify sanity: Bad configuration directory and/or session key arguments in function [{0}]

Short Form

VrfySan BadArgs

Parameters

Label	CEF Label	Type	Usage
func	vds_func	Text	A function name

Message ID : CGA3063E

Description

None

Message ID : CGA3065E

Severity

Error

Long Form

Key Protection: Verify password: Bad configuration directory and/or password arguments in function [{0}]

Short Form

VrfyPwd BadArgs

Parameters

Label	CEF Label	Type	Usage
func	vds_func	Text	A function name

Description

None

Message ID : CGA3064E

Message ID : CGA3066E

Severity

Error

Long Form

Key Protection: Get salt: Bad configuration directory argument in function [{0}]

Short Form

GetSalt BadArg

Parameters

Label	CEF Label	Type	Usage
func	vds_func	Text	A function name

Description

None

Message ID : CGA3067E

Severity

Error

Long Form

Key Protection: Shared secret: Bad configuration directory argument in function [{0}]

Short Form

ShrdSecret BadArg

Parameters

Label	CEF Label	Type	Usage
func	vds_func	Text	A function name

Description

None

Message ID : CGA3068E

Severity

Error

Message ID : CGA3067E

Long Form

Key Protection: Key integrity check: Bad arguments in function [{0}]

Short Form

KeyIntegChk BadArgs

Parameters

Label	CEF Label	Type	Usage
func	vds_func	Text	A function name

Description

None

Message ID : CGA3069E

Severity

Error

Long Form

Key Protection: Key integrity check: Invalid key length in function [{0}]

Message ID : CGA3068E

Short Form

KeyIntegChk BadLen

Parameters

Label	CEF Label	Type	Usage
func	vds_func	Text	A function name

Description

None

Message ID : CGA3070E

Severity

Error

Long Form

Key Protection: Extract rkey: Bad arguments in function [{0}]

Short Form

ExtrRkey BadArgs

Message ID : CGA3069E

Parameters

Label	CEF Label	Type	Usage
func	vds_func	Text	A function name

Description

None

Message ID : CGA3071E

Severity

Error

Long Form

Key Protection: Extract rkey: Invalid extraction method in function [{0}]

Short Form

ExtrRkey BadMeth

Parameters

Label	CEF Label	Type	Usage
func	vds_func	Text	A function name

Message ID : CGA3070E

Description

None

Message ID : CGA3072E

Severity

Error

Long Form

Key Protection: Policy key update: Bad configuration directory argument in function [{0}]

Short Form

PolKeyUpd BadArg

Parameters

Label	CEF Label	Type	Usage
func	vds_func	Text	A function name

Description

None

Message ID : CGA3071E

Message ID : CGA3073E

Severity

Error

Long Form

Key Protection: Signature update: Bad signature update argument in function [{0}]

Short Form

SigUpd BadArg

Parameters

Label	CEF Label	Type	Usage
func	vds_func	Text	A function name

Description

None

Message ID : CGA3074E

Severity

Error

Long Form

Key Protection: Session key decryption: Bad arguments in function [{0}]

Short Form

SessKeyDcrpt BadArgs

Parameters

Label	CEF Label	Type	Usage
func	vds_func	Text	A function name

Description

None

Message ID : CGA3075E

Severity

Error

Message ID : CGA3074E

Long Form

Key Protection: Host password: Invalid argument in function [{0}]

Short Form

HostPwd BadArg

Parameters

Label	CEF Label	Type	Usage
func	vds_func	Text	A function name

Description

None

Message ID : CGA3076E

Severity

Error

Long Form

Key Protection: Challenge 256: Invalid argument in function [{0}]

Message ID : CGA3075E

Short Form

Chlng256 BadArg

Parameters

Label	CEF Label	Type	Usage
func	vds_func	Text	A function name

Description

None

Message ID : CGA3077E

Severity

Error

Long Form

Key Protection: Challenge: Invalid argument in function [{0}]

Short Form

ChlngBadArg

Message ID : CGA3076E

Parameters

Label	CEF Label	Type	Usage
func	vds_func	Text	A function name

Description

None

Message ID : CGA3078E

Severity

Error

Long Form

Key Protection: Failed to write private key in function [{0}]

Short Form

PrivKeyWr Fail

Parameters

Label	CEF Label	Type	Usage
func	vds_func	Text	A function name

Message ID : CGA3077E

Description

None

Message ID : CGA3079E

Severity

Error

Long Form

Key Protection: Failed to read private key in function [{0}]

Short Form

PrivkeyRd Fail

Parameters

Label	CEF Label	Type	Usage
func	vds_func	Text	A function name

Description

None

Message ID : CGA3078E

Message ID : CGA3080E

Severity

Error

Long Form

Key Protection: Extract password: Private key unavailable in function [{0}]

Short Form

ExtrPwd PrivKeyUnavail

Parameters

Label	CEF Label	Type	Usage
func	vds_func	Text	A function name

Description

None

Message ID : CGA3081E

Severity

Error

Long Form

Key Protection: Verify configuration sanity: Private key unavailable in function [{0}]

Short Form

VrfyConfig: PrivKeyUnavail

Parameters

Label	CEF Label	Type	Usage
func	vds_func	Text	A function name

Description

None

Message ID : CGA3082E

Severity

Error

Message ID : CGA3081E

Long Form

Key Protection: Extract rkey: Private key unavailable in function [{0}]

Short Form

ExtrRkey PrivKeyUnavail

Parameters

Label	CEF Label	Type	Usage
func	vds_func	Text	A function name

Description

None

Message ID : CGA3083E

Severity

Error

Long Form

Key Protection: Extract password: Failed to decrypt using private key in function [{0}]

Message ID : CGA3082E

Short Form

ExtrPwd PrivKeyDcrpt Fail

Parameters

Label	CEF Label	Type	Usage
func	vds_func	Text	A function name

Description

None

Message ID : CGA3084E

Severity

Error

Long Form

Key Protection: Verify configuration sanity: Failed to decrypt using private key in function [{0}]

Short Form

VrfyCfg PrivKeyDcrpt Fail

Message ID : CGA3083E

Parameters

Label	CEF Label	Type	Usage
func	vds_func	Text	A function name

Description

None

Message ID : CGA3085E

Severity

Error

Long Form

Key Protection: Extract rkey CR256: Failed to decrypt using private key in function [{0}]

Short Form

ExtrRkey256 PrivKeyDcrpt Fail

Parameters

Label	CEF Label	Type	Usage
func	vds_func	Text	A function name

Message ID : CGA3084E

Description

None

Message ID : CGA3086E

Severity

Error

Long Form

Key Protection: Extract rkey: Failed to decrypt using private key in function [{0}]

Short Form

ExtrRkey PrivKeyDecrypt Fail

Parameters

Label	CEF Label	Type	Usage
func	vds_func	Text	A function name

Description

None

Message ID : CGA3085E

Message ID : CGA3087E

Severity

Error

Long Form

Key Protection: Verify configuration sanity: Bad session key in file [{0}], function [{1}] line [{2}]

Short Form

VrfyCfg BadSessKey

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file
func	vds_func	Text	A function name

Description

None

Message ID : CGA3088E

Severity

Error

Long Form

Key Protection: Verify configuration sanity: Failed HMAX verification in file [{0}], function [{1}] line [{2}]

Short Form

VrfyCfg FailHMAXVrfy Fail

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file
func	vds_func	Text	A function name

Description

None

Message ID : CGA3089E

Severity

Error

Long Form

Key Protection: Verify configuration sanity: Bad rkey in file [{0}], function [{1}] line [{2}]

Short Form

VrfyCfg BadRkey

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file
func	vds_func	Text	A function name

Description

None

Message ID : CGA3090E

Severity

Error

Long Form

Key Protection: File session key decrypt: Failed description in file [{0}] in function [{1}]

Short Form

FileSessKeyDcrpt Fail

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file
func	vds_func	Text	A function name

Description

None

Message ID : CGA3091E

Severity

Error

Long Form

Key Protection: Extract rkey: Bad password in function [{0}]

Short Form

ExtrRkey BadPwd

Parameters

Label	CEF Label	Type	Usage
func	vds_func	Text	A function name

Description

None

Message ID : CGA3092E

Severity

Error

Long Form

Key Protection: Policy key update: Bad password in function [{0}]

Short Form

PolKeyUpd BadPwd

Parameters

Label	CEF Label	Type	Usage
func	vds_func	Text	A function name

Description

None

Message ID : CGA3093E

Severity

Error

Message ID : CGA3092E

Long Form

Key Protection: Policy key update: Extract rkey failure in function [{0}]

Short Form

PolKeyUpd ExtrRkey Fail

Parameters

Label	CEF Label	Type	Usage
func	vds_func	Text	A function name

Description

None

Message ID : CGA3094E

Severity

Error

Long Form

Compare dir key: Failed to get dir

Message ID : CGA3093E

Short Form

CmpDirKey FailGetDir

Parameters

No parameters are provided for this message type

Description

None

Message ID : CGA3095E

Severity

Error

Long Form

Compare dir key: Failed to add keyset

Short Form

CmpDirKey FailAddKeyset

Message ID : CGA3094E

Parameters

No parameters are provided for this message type

Description

None

Message ID : CGA3096E

Severity

Error

Long Form

Get keyid: Invalid key object in [{0}] at [{1}]

Short Form

GetKeyid InvalKeyObj

Parameters

Label	CEF Label	Type	Usage
func	vds_func	Text	A function name

Message ID : CGA3095E

Description

None

Message ID : CGA3097E

Severity

Error

Long Form

Get keyid: Local key get failed in [{0}] at [{1}]

Short Form

GetKeyid LclKeyGet Fail

Parameters

Label	CEF Label	Type	Usage
func	vds_func	Text	A function name

Description

None

Message ID : CGA3096E

Message ID : CGA3098E

Severity

Error

Long Form

Policy validation failed

Short Form

PolVald Fail

Parameters

No parameters are provided for this message type

Description

None

Message ID : CGA3099E

Severity

Error

Message ID : CGA3098E

Long Form

LDT: Failed to start

Short Form

LDT: Fail to start

Parameters

No parameters are provided for this message type

Description

None

Message ID : CGA3100E

Severity

Error

Long Form

LDT: Failed to stop

Message ID : CGA3099E

Short Form

LDT: Fail to stop

Parameters

No parameters are provided for this message type

Description

None

Message ID : CGA3101E

Severity

Error

Long Form

LDT: Failed to exit

Short Form

LDT: Fail to exit

Parameters

No parameters are provided for this message type

Description

None

Message ID : CGA3102E

Severity

Error

Long Form

LDT: Cross guard point key compare failed

Short Form

LDT: Cross guard point key compare failed

Parameters

No parameters are provided for this message type

Message ID : CGA3101E

Description

None

Message ID : CGA3103E

Severity

Error

Long Form

LDT: Not enough disk space for file [{0}], aborting transformation

Short Form

LDT: Out of disk space

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : CGA3102E

Message ID : CGA3109E

Severity

Error

Long Form

Not guarding path [{0}] from container [{1}] (Reason: Simulation mode)

Short Form

IgnrCntnrGrd SimMode

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	GuardPoint base directory
dockerid	dockerid	Text	Docker image or container id

Description

None

Message ID : CGA3110E

Severity

Error

Long Form

Not guarding path [{0}] (Reason: Simulation mode)

Short Form

IgnrGrd SimMode

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	GuardPoint base directory

Description

None

Message ID : CGA3111E

Severity

Error

Long Form

Not guarding path [{0}] from container [{1}] (Reason: Contains symlinks or is malformed)

Short Form

IgnrCntnrGrd HasSymlnks

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	GuardPoint base directory
dockerid	dockerid	Text	Docker image or container id

Description

None

Message ID : CGA3112E

Message ID : CGA3111E

Severity

Error

Long Form

Not guarding path [{0}] (Reason: Contains symlinks or is malformed)

Short Form

IgnrGrd HasSymlnks

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	GuardPoint base directory

Description

None

Message ID : CGA3113E

Severity

Error

Message ID : CGA3112E

Long Form

Not guarding path [{0}] from container [{1}] (Reason: Can't guard root)

Short Form

IgnrCntnrGrd NoRoot

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	GuardPoint base directory
dockerid	dockerid	Text	Docker image or container id

Description

None

Message ID : CGA3114E

Severity

Error

Message ID : CGA3113E

Long Form

Not guarding path [{0}] (Reason: Can't guard root)

Short Form

IgnrGrd NoRoot

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	GuardPoint base directory

Description

None

Message ID : CGA3115E

Severity

Error

Long Form

Not guarding path [{0}] from container [{1}] (Reason: Path too long)

Message ID : CGA3114E

Short Form

IgnrCntnrGrd PathLong

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	GuardPoint base directory
dockerid	dockerid	Text	Docker image or container id

Description

None

Message ID : CGA3116E

Severity

Error

Long Form

Not guarding path [{0}] (Reason: Path too long)

Message ID : CGA3115E

Short Form

IgnrGrd PathLong

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	GuardPoint base directory

Description

None

Message ID : CGA3117E

Severity

Error

Long Form

Not guarding path [{0}] from container [{1}] (Reason: AUTOFS, but type is not automount)

Short Form

IgnrCntnrGrd AUTOFS

Message ID : CGA3116E

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	GuardPoint base directory
dockerid	dockerid	Text	Docker image or container id

Description

None

Message ID : CGA3118E

Severity

Error

Long Form

Not guarding path [{0}] (Reason: AUTOFS, but type is not automount)

Short Form

IgnrGrd AUTOFS

Message ID : CGA3117E

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	GuardPoint base directory

Description

None

Message ID : CGA3119E

Severity

Error

Long Form

Not guarding path [{0}] from container [{1}] (Reason: Not allowed)

Short Form

IgnrCntnrGrd IsInval

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	GuardPoint base directory

Message ID : CGA3118E

Label	CEF Label	Type	Usage
dockerid	dockerid	Text	Docker image or container id

Description

None

Message ID : CGA3120E

Severity

Error

Long Form

Not guarding path [{0}] (Reason: Not allowed)

Short Form

IgnrGrd IsInval

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	GuardPoint base directory

Message ID : CGA3119E

Description

None

Message ID : CGA3121E

Severity

Error

Long Form

Not guarding path [{0}] from container [{1}] (Reason: Raw device not supported)

Short Form

IgnrCntnrGrd RawDev

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	GuardPoint base directory
dockerid	dockerid	Text	Docker image or container id

Message ID : CGA3120E

Description

None

Message ID : CGA3122E

Severity

Error

Long Form

Not guarding path [{0}] (Reason: Raw device not supported)

Short Form

IgnrGrd RawDev

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	GuardPoint base directory

Description

None

Message ID : CGA3121E

Message ID : CGA3123E

Severity

Error

Long Form

Not guarding path [{0}] from container [{1}] (Reason: Unknown)

Short Form

IgnrCntnrGrd BadFlag

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	GuardPoint base directory
dockerid	dockerid	Text	Docker image or container id

Description

None

Message ID : CGA3123E

Message ID : CGA3124E

Severity

Error

Long Form

Not guarding path [{0}] (Reason: Unknown)

Short Form

IgnrCntnrGrd BadFlag

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	GuardPoint base directory

Description

None

Message ID : CGA3125E

Severity

Error

Long Form

Not unguarding path [{0}] from container [{1}] (Reason: Unknown)

Short Form

IgnrCntnrUngrd BadFlag

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	GuardPoint base directory
dockerid	dockerid	Text	Docker image or container id

Description

None

Message ID : CGA3126E

Message ID : CGA3125E

Severity

Error

Long Form

Not unguarding path [{0}] (Reason: Unknown)

Short Form

IgnrUngrd BadFlag

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	GuardPoint base directory

Description

None

Message ID : CGA3127E

Severity

Error

Message ID : CGA3126E

Long Form

Not guarding path [{0}] from container [{1}] (Reason: Nested paths not allowed)

Short Form

BadCntnrGrdPath IsNested

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	GuardPoint base directory
dockerid	dockerid	Text	Docker image or container id

Description

None

Message ID : CGA3128E

Severity

Error

Message ID : CGA3127E

Long Form

Not guarding path [{0}] (Reason: Nested paths not allowed)

Short Form

BadGrdPath IsNested

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	GuardPoint base directory

Description

None

Message ID : CGA3129E

Severity

Error

Long Form

Not guarding path [{0}] from container [{1}] (Reason: Busy, will continue to retry)

Message ID : CGA3128E

Short Form

BadCntnrGrdPath IsBusy

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	GuardPoint base directory
dockerid	dockerid	Text	Docker image or container id

Description

None

Message ID : CGA3130E

Severity

Error

Long Form

Not guarding path [{0}] (Reason: Busy, will continue to retry)

Message ID : CGA3129E

Short Form

BadGrdPath IsBusy

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	GuardPoint base directory

Description

None

Message ID : CGA3131E

Severity

Error

Long Form

Not unguarding path [{0}] from container [{1}] (Reason: Busy, will continue to retry)

Short Form

BadCntnrUngrdPath IsBusy

Message ID : CGA3130E

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	GuardPoint base directory
dockerid	dockerid	Text	Docker image or container id

Description

None

Message ID : CGA3132E

Severity

Error

Long Form

Not unguarding path [{0}] (Reason: Busy, will continue to retry)

Short Form

BadUngrdPath IsBusy

Message ID : CGA3131E

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	GuardPoint base directory

Description

None

Message ID : CGA3133E

Severity

Error

Long Form

Not guarding path [{0}] from container [{1}] (Reason: Does not exist)

Short Form

BadCntnrGrdPath NotExist

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	GuardPoint base directory

Message ID : CGA3132E

Label	CEF Label	Type	Usage
dockerid	dockerid	Text	Docker image or container id

Description

None

Message ID : CGA3134E

Severity

Error

Long Form

Not guarding path [{0}] (Reason: Does not exist)

Short Form

BadGrdPath NotExist

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	GuardPoint base directory

Message ID : CGA3133E

Description

None

Message ID : CGA3135E

Severity

Error

Long Form

Not unguarding path [{0}] from container [{1}] (Reason: Does not exist)

Short Form

BadCntnrUngrdPath NotExist

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	GuardPoint base directory
dockerid	dockerid	Text	Docker image or container id

Message ID : CGA3134E

Description

None

Message ID : CGA3136E

Severity

Error

Long Form

Not unguarding path [{0}] (Reason: Does not exist)

Short Form

BadUngrdPath NotExist

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	GuardPoint base directory

Description

None

Message ID : CGA3135E

Message ID : CGA3137E

Severity

Error

Long Form

Not guarding path [{0}] from container [{1}] (Reason: Already mounted)

Short Form

BadCntnrGrdPath AlreadyMounted

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	GuardPoint base directory
dockerid	dockerid	Text	Docker image or container id

Description

None

Message ID : CGA3138E

Severity

Error

Long Form

Not guarding path [{0}] (Reason: Already mounted)

Short Form

BadGrdPath AlreadyMounted

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	GuardPoint base directory

Description

None

Message ID : CGA3139E

Severity

Error

Long Form

Not guarding path [{0}] from container [{1}] (Reason: Max guard point limit reached)

Short Form

BadCntnrGrd MaxGrds

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	GuardPoint base directory
dockerid	dockerid	Text	Docker image or container id

Description

None

Message ID : CGA3140E

Message ID : CGA3139E

Severity

Error

Long Form

Not guarding path [{0}] (Reason: Max guard point limit reached)

Short Form

BadGrd MaxGrds

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	GuardPoint base directory

Description

None

Message ID : CGA3141E

Severity

Error

Message ID : CGA3140E

Long Form

Not guarding path [{0}] from container [{1}] (Reason: Resource not available)

Short Form

BadCntnrGrd ResrcUnavail

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	GuardPoint base directory
dockerid	dockerid	Text	Docker image or container id

Description

None

Message ID : CGA3142E

Severity

Error

Message ID : CGA3141E

Long Form

Not guarding path [{0}] (Reason: Resource not available)

Short Form

BadGrd ResrcUnavail

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	GuardPoint base directory

Description

None

Message ID : CGA3143E

Severity

Error

Long Form

Not guarding path [{0}] from container [{1}] (Reason: Operation timed out, retrying)

Message ID : CGA3142E

Short Form

BadCntnrGrd TimedOut

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	GuardPoint base directory
dockerid	dockerid	Text	Docker image or container id

Description

None

Message ID : CGA3144E

Severity

Error

Long Form

Not guarding path [{0}] (Reason: Operation timed out, retrying)

Message ID : CGA3143E

Short Form

BadGrd TimedOut

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	GuardPoint base directory

Description

None

Message ID : CGA3145E

Severity

Error

Long Form

Not unguarding path [{0}] from container [{1}] (Reason: Operation timed out, retrying)

Short Form

BadCntnrUngrd TimedOut

Message ID : CGA3144E

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	GuardPoint base directory
dockerid	dockerid	Text	Docker image or container id

Description

None

Message ID : CGA3146E

Severity

Error

Long Form

Not unguarding path [{0}] (Reason: Operation timed out, retrying)

Short Form

BadUngrd TimedOut

Message ID : CGA3145E

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	GuardPoint base directory

Description

None

Message ID : CGA3147E

Severity

Error

Long Form

Not guarding path [{0}] from container [{1}] (Reason: Invalid guard point)

Short Form

BadCntnrGrdPath InvalGrdPath

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	GuardPoint base directory

Message ID : CGA3146E

Label	CEF Label	Type	Usage
dockerid	dockerid	Text	Docker image or container id

Description

None

Message ID : CGA3148E

Severity

Error

Long Form

Not guarding path [{0}] (Reason: Invalid guard point)

Short Form

BadGrdPath InvalGrdPath

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	GuardPoint base directory

Message ID : CGA3147E

Description

None

Message ID : CGA3149E

Severity

Error

Long Form

Not guarding path [{0}] from container [{1}] (Reason: Invalid, AUTOFS but type is not automount)

Short Form

BadCntnrGrdPath AUTOFSNoAuto

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	GuardPoint base directory
dockerid	dockerid	Text	Docker image or container id

Message ID : CGA3148E

Description

None

Message ID : CGA3150E

Severity

Error

Long Form

Not guarding path [{0}] (Reason: Invalid, AUTOFS but type is not automount)

Short Form

BadGrdPath AUTOFSNoAuto

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	GuardPoint base directory

Description

None

Message ID : CGA3149E

Message ID : CGA3151E

Severity

Error

Long Form

Not guarding path [{0}] from container [{1}] (Reason: Partially guarded)

Short Form

BadCntnrGrd PartialGrd

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	GuardPoint base directory
dockerid	dockerid	Text	Docker image or container id

Description

None

Message ID : CGA3152E

Severity

Error

Long Form

Not guarding path [{0}] (Reason: Partially guarded)

Short Form

BadGrd PartialGrd

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	GuardPoint base directory

Description

None

Message ID : CGA3153E

Severity

Error

Long Form

Not guarding path [{0}] from container [{1}] (Reason: Logical drive or path compressed)

Short Form

BadCntnrGrd IsCompressed

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	GuardPoint base directory
dockerid	dockerid	Text	Docker image or container id

Description

None

Message ID : CGA3154E

Message ID : CGA3153E

Severity

Error

Long Form

Not guarding path [{0}] (Reason: Logical drive or path compressed)

Short Form

BadGrd IsCompressed

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	GuardPoint base directory

Description

None

Message ID : CGA3155E

Severity

Error

Message ID : CGA3154E

Long Form

Not guarding path [{0}] from container [{1}] (Reason: Logical drive or path encrypted)

Short Form

BadCntnrGrd IsEncrypt

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	GuardPoint base directory
dockerid	dockerid	Text	Docker image or container id

Description

None

Message ID : CGA3156E

Severity

Error

Message ID : CGA3155E

Long Form

Not guarding path [{0}] (Reason: Logical drive or path encrypted)

Short Form

BadGrd IsEncrypt

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	GuardPoint base directory

Description

None

Message ID : CGA3157E

Severity

Error

Long Form

Not guarding path [{0}] from container [{1}] (Reason: System Error/Module not present)

Message ID : CGA3156E

Short Form

BadCntnrGrd SysError

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	GuardPoint base directory
dockerid	dockerid	Text	Docker image or container id

Description

None

Message ID : CGA3158E

Severity

Error

Long Form

Not guarding path [{0}] (Reason: System Error/Module not present)

Message ID : CGA3157E

Short Form

BadGrd SysError

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	GuardPoint base directory

Description

None

Message ID : CGA3159E

Severity

Error

Long Form

Not unguarding path [{0}] from container [{1}] (Reason: System Error/Module not present)

Short Form

BadCntnrUngrd SysError

Message ID : CGA3158E

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	GuardPoint base directory
dockerid	dockerid	Text	Docker image or container id

Description

None

Message ID : CGA3160E

Severity

Error

Long Form

Not unguarding path [{0}] (Reason: System Error/Module not present)

Short Form

BadUngrd SysError

Message ID : CGA3159E

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	GuardPoint base directory

Description

None

Message ID : CGA3161E

Severity

Error

Long Form

Not guarding path [{0}] from container [{1}] (Reason: Protected file system is stale)

Short Form

BadCntnrGrdPath StaleFS

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	GuardPoint base directory

Message ID : CGA3160E

Label	CEF Label	Type	Usage
dockerid	dockerid	Text	Docker image or container id

Description

None

Message ID : CGA3162E

Severity

Error

Long Form

Not guarding path [{0}] (Reason: Protected file system is stale)

Short Form

BadGrdPath StaleFS

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	GuardPoint base directory

Message ID : CGA3161E

Description

None

Message ID : CGA3163E

Severity

Error

Long Form

Not guarding path [{0}] from container [{1}] (Reason: Unsupported filesystem type)

Short Form

BadCntnrGrdPath FSNotSupp

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	GuardPoint base directory
dockerid	dockerid	Text	Docker image or container id

Message ID : CGA3162E

Description

None

Message ID : CGA3164E

Severity

Error

Long Form

Not guarding path [{0}] (Reason: Unsupported filesystem type)

Short Form

BadGrdPath FSNotSupp

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	GuardPoint base directory

Description

None

Message ID : CGA3163E

Message ID : CGA3165E

Severity

Error

Long Form

Not guarding path [{0}] from container [{1}] (Reason: Guard point has metadata, only Live Data Transform policy allowed)

Short Form

BadCntnrGrd BadPol

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	GuardPoint base directory
dockerid	dockerid	Text	Docker image or container id

Description

None

Message ID : CGA3166E

Severity

Error

Long Form

Not guarding path [{0}] (Reason: Guard point has metadata, only Live Data Transform policy allowed)

Short Form

BadGrd BadPol

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	GuardPoint base directory

Description

None

Message ID : CGA3167E

Severity

Error

Long Form

Not guarding path [{0}] from container [{1}] (Reason: Filesystem type is not supported with Live Data Transform policy)

Short Form

BadCntnrGrd BadFS

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	GuardPoint base directory
dockerid	dockerid	Text	Docker image or container id

Description

None

Message ID : CGA3168E

Message ID : CGA3167E

Severity

Error

Long Form

Not guarding path [{0}] (Reason: Filesystem type is not supported with Live Data Transform policy)

Short Form

BadGrd BadFS

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	GuardPoint base directory

Description

None

Message ID : CGA3169E

Severity

Error

Message ID : CGA3168E

Long Form

Not guarding path [{0}] from container [{1}] (Reason: File system not mounted with Extended attribute support)

Short Form

BadCntnrGrd XattrDisabled

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	GuardPoint base directory
dockerid	dockerid	Text	Docker image or container id

Description

None

Message ID : CGA3170E

Severity

Error

Message ID : CGA3169E

Long Form

Not guarding path [{0}] (Reason: File system not mounted with Extended attribute support)

Short Form

BadGrd XattrDisabled

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	GuardPoint base directory

Description

None

Message ID : CGA3171E

Severity

Error

Long Form

Not guarding path [{0}] from container [{1}] (Reason: Nested mount path not allowed for LDT)

Message ID : CGA3170E

Short Form

BadCntnrGrd NestMount

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	GuardPoint base directory
dockerid	dockerid	Text	Docker image or container id

Description

None

Message ID : CGA3172E

Severity

Error

Long Form

Not guarding path [{0}] (Reason: Nested mount path not allowed for LDT)

Message ID : CGA3171E

Short Form

BadGrd NestMount

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	GuardPoint base directory

Description

None

Message ID : CGA3173E

Severity

Error

Long Form

Not unguarding path [{0}] from container [{1}] (Reason: LDT metadata removal in progress)

Short Form

BadCntnrGrd LDTMetadata

Message ID : CGA3172E

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	GuardPoint base directory
dockerid	dockerid	Text	Docker image or container id

Description

None

Message ID : CGA3174E

Severity

Error

Long Form

Not unguarding path [{0}] (Reason: LDT metadata removal in progress)

Short Form

BadGrd LDTMetadata

Message ID : CGA3173E

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	GuardPoint base directory

Description

None

Message ID : CGA3175E

Severity

Error

Long Form

Not guarding path [{0}] from container [{1}] (Reason: Inactive)

Short Form

BadCntnrGrd Inactive

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	GuardPoint base directory

Message ID : CGA3174E

Label	CEF Label	Type	Usage
dockerid	dockerid	Text	Docker image or container id

Description

None

Message ID : CGA3176E

Severity

Error

Long Form

Not guarding path [{0}] (Reason: Inactive)

Short Form

BadGrd Inactive

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	GuardPoint base directory

Message ID : CGA3175E

Description

None

Message ID : CGA3177E

Severity

Error

Long Form

Not unguarding path [{0}] from container [{1}] (Reason: Inactive)

Short Form

BadCntnrUngrd Inactive

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	GuardPoint base directory
dockerid	dockerid	Text	Docker image or container id

Message ID : CGA3176E

Description

None

Message ID : CGA3178E

Severity

Error

Long Form

Not unguarding path [{0}] (Reason: Inactive)

Short Form

BadUngrd Inactive

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	GuardPoint base directory

Description

None

Message ID : CGA3177E

Message ID : CGA3179E

Severity

Error

Long Form

Not guarding path [{0}] from container [{1}] (Reason: Unknown)

Short Form

BadCntnrGrd BadFlag

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	GuardPoint base directory
dockerid	dockerid	Text	Docker image or container id

Description

None

Message ID : CGA3180E

Severity

Error

Long Form

Not guarding path [{0}] (Reason: Unknown)

Short Form

BadGrd BadFlag

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	GuardPoint base directory

Description

None

Message ID : CGA3181E

Severity

Error

Long Form

Not unguarding path [{0}] from container [{1}] (Reason: Unknown)

Short Form

BadCntnrUngrd BadFlag

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	GuardPoint base directory
dockerid	dockerid	Text	Docker image or container id

Description

None

Message ID : CGA3182E

Message ID : CGA3181E

Severity

Error

Long Form

Not unguarding path [{0}] (Reason: Unknown)

Short Form

BadUngrd BadFlag

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	GuardPoint base directory

Description

None

Message ID : CGA3184E

Severity

Error

Message ID : CGA3182E

Long Form

Failed to guard path [{0}] (Reason: [{1}] file system not supported)

Short Form

FS NotSupp

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	GuardPoint base directory

Description

None

Message ID : CGA3185E

Severity

Error

Long Form

Not guarding path [{0}] (Reason: Can't guard root)

Message ID : CGA3184E

Short Form

GrdPath IsRoot

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	GuardPoint base directory

Description

None

Message ID : CGA3187E

Severity

Error

Long Form

An encryption policy was applied to a folder containing NTFS compressed files, [{0}]. NTFS compressed files are not encrypted

Short Form

Folder IsCompressed

Message ID : CGA3185E

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	GuardPoint base directory

Description

None

Message ID : CGA3188E

Severity

Error

Long Form

An encryption policy was applied to a folder containing NTFS encrypted files, [{0}]. NTFS encrypted files are not encrypted

Short Form

Folder IsCrypt

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	GuardPoint base directory

Message ID : CGA3187E

Description

None

Message ID : CGA3189E

Severity

Error

Long Form

Guard path [{0}]: Guard point has metadata, only Live Data Transform policy allowed

Short Form

Bad GrdPath Pol

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	GuardPoint base directory

Description

None

Message ID : CGA3188E

Message ID : CGA3190E

Severity

Error

Long Form

Guard path [{0}]: Wrong fs type for this guard point

Short Form

Bad GrdPath FS

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	GuardPoint base directory

Description

None

Message ID : CGA3191E

Severity

Error

Long Form

Guard path [{0}]: Extended attribute not enabled for guard point

Short Form

GrdPath XattrDisabled

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	GuardPoint base directory

Description

None

Message ID : CGA3192E

Severity

Error

Message ID : CGA3191E

Long Form

Guard path [{0}]: Nested mount not allowed for Live Data Transform

Short Form

GrdPath NestMount

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	GuardPoint base directory

Description

None

Message ID : CGA3206E

Severity

Error

Long Form

LDT: failed to encrypt data

Message ID : CGA3192E

Short Form

LDT Crypt Fail

Parameters

No parameters are provided for this message type

Description

None

Message ID : CGA3212E

Severity

Error

Long Form

LDT-ALERT: Error in scanning guardpoint [{0}].

Short Form

LDT-ALERT: Error in scanning guardpoint

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	GuardPoint base directory

Description

None

Message ID : CGA3218E

Severity

Error

Long Form

LDT: Skipping transformation of file [{0}], due to pre-check error.

Short Form

LDT: Skipping transformation of file, due to pre-check error

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Message ID : CGA3212E

Description

None

Message ID : CGA3220E

Severity

Error

Long Form

LDT: Error recovering ranges from previous transformation for file [{0}].

Short Form

LDT: Error recovering ranges from previous transformation for file

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : CGA3218E

Message ID : CGA3222E

Severity

Error

Long Form

[AUDIT] Process[{0}] Pid[{1}] Uid[{2}] Operation[{3}] File[{4}] ContainerID[{5}] Failure[{6}] Effect[PERMIT]

Short Form

Sysfile modified error

Parameters

Label	CEF Label	Type	Usage
command	command	Text	Task struct comm field
pid	dvcpid	Numeric	Numeric process ID
uid	suid	Numeric	User id
op_name	op_name	Text	Operation name
filePath	filePath	Text	Full path to file
cid	cid	Text	Container ID
ecode	cn1	Numeric	An error code

Description

None

Message ID : CGA3223E

Severity

Error

Long Form

[ALARM] Process[{0}] Pid[{1}] Uid[{2}] Operation[{3}] File[{4}] ContainerID[{5}] Effect[DENIED]

Short Form

Sysfile protected

Parameters

Label	CEF Label	Type	Usage
command	command	Text	Task struct comm field
pid	dvcpid	Numeric	Numeric process ID
uid	suid	Numeric	User id
op_name	op_name	Text	Operation name

Message ID : CGA3222E

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file
cid	cid	Text	Container ID

Description

None

Message ID : CGA3227E

Severity

Error

Long Form

LDT: Error while rekeying guardpoint [{0}]

Short Form

LDT: Error while rekeying guardpoint

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	GuardPoint base directory

Message ID : CGA3223E

Description

None

Message ID : CGA3228E

Severity

Error

Long Form

Ptrace denied on authenticator [{0}] pid [{1}]

Short Form

Ptrace authenticator denied

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file
pid	dvcpid	Numeric	Numeric process ID

Message ID : CGA3227E

Description

None

Message ID : CGA3229E

Severity

Error

Long Form

Ptrace denied on protected process [{0}] pid [{1}]

Short Form

Ptrace protected denied

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file
pid	dvcpid	Numeric	Numeric process ID

Message ID : CGA3228E

Description

None

Message ID : CGA3230E

Severity

Error

Long Form

LDT: Terminating rekey ON [{0}] due to data corruption

Short Form

LDT: terminated, corruption

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	GuardPoint base directory

Description

None

Message ID : CGA3229E

Message ID : CGA3232E

Severity

Error

Long Form

LDT: Data transformation is aborted on file [{0}]. Error : {1}

Short Form

LDT: Data transformation is aborted on file

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file
ecode	cn1	Numeric	An error code

Description

None

Message ID : CGA3233E

Severity

Error

Long Form

LDT: Data transformation is aborted on file [{0}]. Error : {1}. Reason : {2}

Short Form

LDT: Data transformation is aborted on file

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file
ecode	cn1	Numeric	An error code
showStr	reason	Text	Code specifying reason for allowing access, if any

Description

None

Message ID : CGA3235E

Severity

Error

Long Form

Key Protection: Failed to generate derived key in function [{0}]

Short Form

Generate derived key failed

Parameters

Label	CEF Label	Type	Usage
func	vds_func	Text	A function name

Description

None

Message ID : CGA3236E

Severity

Error

Long Form

Key Protection: Encryption error in function [{0}]

Short Form

Encryption error

Parameters

Label	CEF Label	Type	Usage
func	vds_func	Text	A function name

Description

None

Message ID : CGA3237E

Severity

Error

Message ID : CGA3236E

Long Form

Key Protection: Invalid access file in [{0}] at [{1}]

Short Form

Invalid access file

Parameters

Label	CEF Label	Type	Usage
func	vds_func	Text	A function name

Description

None

Message ID : CGA3238E

Severity

Error

Long Form

Not re-guarding path [{0}] from container [{1}] (Reason: Guard point initialization already in progress)

Message ID : CGA3237E

Short Form

BadCntnrGrd InProgress

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	GuardPoint base directory
dockerid	dockerid	Text	Docker image or container id

Description

None

Message ID : CGA3239E

Severity

Error

Long Form

Not re-guarding path [{0}] (Reason: Guard point initialization already in progress)

Message ID : CGA3238E

Short Form

BadGrd InProgress

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	GuardPoint base directory

Description

None

Message ID : CGA3252E

Severity

Error

Long Form

LDT-ALERT: Cannot enable guard point [{0}], LDT initialization failed with error [{1}]

Short Form

LDT: enable failure

Message ID : CGA3239E

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	GuardPoint base directory
ecode	cn1	Numeric	An error code

Description

None

Message ID : CGA3256E

Severity

Error

Long Form

LDT-ALERT: Error initializing resources, LDT will not be operational.

Short Form

LDT init fail

Message ID : CGA3252E

Parameters

No parameters are provided for this message type

Description

None

Message ID : CGA3272E

Severity

Error

Long Form

{0} does not have UUID

Short Form

UUID does not exist

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Message ID : CGA3256E

Description

None

Message ID : CGA3274E

Severity

Error

Long Form

Failed to write classification {0} to {1}

Short Form

Failed to write

Parameters

Label	CEF Label	Type	Usage
tag	tag	Text	Tag
filePath	filePath	Text	Full path to file

Message ID : CGA3272E

Description

None

Message ID : CGA3275E

Severity

Error

Long Form

Data classification transaction {0} failed for operation {1} with {2} : {3}

Short Form

Classification transaction failed

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file
filePath	filePath	Text	Full path to file

Message ID : CGA3274E

Description

None

Message ID : CGA3278E

Severity

Error

Long Form

Key Conflict for File [{0}]: key information in LDT metadata does not match with the key specified under policy

Short Form

Mismatch policy

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : CGA3275E

Message ID : CGA3279E

Severity

Error

Long Form

ESG/IDT-ALERT: IO error on header for ESG/IDT-Capable device [{0}]

Short Form

header IO error

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	GuardPoint base directory

Description

None

Message ID : CGA3280E

Severity

Error

Long Form

ESG/IDT-ALERT: Data transformation failure on ESG/IDT-Capable device [{0}]

Short Form

IDT fail

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	GuardPoint base directory

Description

None

Message ID : CGA3282E

Severity

Error

Message ID : CGA3280E

Long Form

ESG/IDT-ALERT: Failed to update new device size on ESG/IDT-Capable device [{0}]

Short Form

resize fail

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	GuardPoint base directory

Description

None

Message ID : CGA3284E

Severity

Error

Long Form

LDT: Failed to flag GuardPoint [{0}] for deferred key rotation, error [{1}]

Message ID : CGA3282E

Short Form

Defer rotate fail

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	GuardPoint base directory
ecode	cn1	Numeric	An error code

Description

None

Message ID : CGA3289E

Severity

Error

Long Form

Failed to have permission to remediate {0}

Message ID : CGA3284E

Short Form

Failed to have permission to remediate

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : CGA3292E

Severity

Error

Long Form

Failed to prepare remediation for {0}

Short Form

Failed to prepare remediation

Message ID : CGA3289E

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : CGA3295E

Severity

Error

Long Form

Failed to remediate {0} offline

Short Form

Failed to remediate offline

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Message ID : CGA3292E

Description

None

Message ID : CGA3298E

Severity

Error

Long Form

Failed to commit remediation for {0}

Short Form

Failed to commit remediation

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : CGA3295E

Message ID : CGA3301E

Severity

Error

Long Form

Failed to remediate {0} online

Short Form

Failed to remediate online

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : CGA3304E

Severity

Error

Long Form

ESG-ALERT: Process [{0}] disallowed on ESG device [{1}]

Short Form

Disallow ESG

Parameters

Label	CEF Label	Type	Usage
sproc	sproc	Text	Source process
gp	fileId	Text	GuardPoint base directory

Description

None

Message ID : CGA3306E

Message ID : CGA3304E

Severity

Error

Long Form

LDT: Skipping transformation of file [{0}], Unable to retrieve the File Information MD.

Short Form

LDT: Skipped invalid INF

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : CGA3307E

Severity

Error

Message ID : CGA3306E

Long Form

LDT: Skipping transformation of file [{0}], As failed to validate LDT file MetaData. Please contact support for more information.

Short Form

LDT: Skipped invalid metadata

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : CGA3308E

Severity

Error

Long Form

LDT: Skipping transformation of file [{0}], Key in the policy doesn't match with the key in the MD. Please contact support for more information.

Message ID : CGA3307E

Short Form

LDT: Skipped key mismatch

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : CGA3309E

Severity

Error

Long Form

LDT: Skipping transformation of file [{0}],file is being restored or exclusively accessed by the application. Please retrigger the rekey again after application finishes the processing on the file.

Short Form

LDT: Skipped restore

Message ID : CGA3308E

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : CGA3310E

Severity

Error

Long Form

LDT: Skipping transformation of file [{0}],As failed to remove the read-only attribute of the file. Please retrigger the rekey again after checking the file permissions.

Short Form

LDT: Skipped read only

Parameters

Label	CEF Label	Type	Usage
-------	-----------	------	-------

Message ID : CGA3309E

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : CGA3356E

Severity

Error

Long Form

Not guarding path [{0}] (Reason: Can't guard directory inside a system folder)

Short Form

IgnrGrd InsideRoot

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	GuardPoint base directory

Message ID : CGA3310E

Description

None

Message ID : CGA3361E

Severity

Error

Long Form

[ALARM] User[{0},uid={1},gid={2}] Process[{3}] Action[{4}] Res[{5}{6}] Effect[MFA {7}]

Short Form

MFA denied

Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
uid	suid	Numeric	User id
gid	vds_gid	Numeric	Group id
command	command	Text	Task struct comm field

Message ID : CGA3356E

Label	CEF Label	Type	Usage
op_name	op_name	Text	Operation name
gp	fileId	Text	GuardPoint base directory
filePath	filePath	Text	Full path to file
showStr	reason	Text	Code specifying reason for allowing access, if any

Description

None

Logger CGA: Information

Message ID : CGA2622I

Severity

Information

Long Form

Access Check Tracing: Invalid policy, use default policy object

Short Form

No short form is provided for this message type

Description

None

Message ID : CGA2630I

Severity

Information

Long Form

Policy [{0}]: Key match file is [{1}]

Short Form

No short form is provided for this message type

Description

None

Message ID : CGA2631I

Severity

Information

Long Form

Policy [{0}]: Key match resource domain is [{1}]

Short Form

No short form is provided for this message type

Message ID : CGA2630I

Description

None

Message ID : CGA2632I

Severity

Information

Long Form

Policy [{0}]: Using Key [{1}] of rule number [{2}]

Short Form

No short form is provided for this message type

Description

None

Message ID : CGA2633I

Severity

Information

Message ID : CGA2631I

Long Form

Policy [{0}]: No key rule matched: Using clear key

Short Form

No short form is provided for this message type

Description

None

Message ID : CGA2640I

Severity

Information

Long Form

Access check tracing: Policy [{0}]: Proc[{1}] Gen[{2}] User[{3} {4} {5}] Res[{6}]

Short Form

No short form is provided for this message type

Message ID : CGA2633I

Description

None

Message ID : CGA2641I

Severity

Information

Long Form

Access check tracing: Policy [{0}]: Empty rules table

Short Form

No short form is provided for this message type

Description

None

Message ID : CGA2642I

Severity

Information

Message ID : CGA2640I

Long Form

Access check tracing: Policy [{0}]: [{1}] Domain [{2}] matched

Short Form

No short form is provided for this message type

Description

None

Message ID : CGA2643I

Severity

Information

Long Form

Access check tracing: Policy [{0}]: Rule number [{1}] matched

Short Form

No short form is provided for this message type

Message ID : CGA2642I

Description

None

Message ID : CGA2644I

Severity

Information

Long Form

Access check tracing: Policy [{0}]: GoTo rule number [{1}]

Short Form

No short form is provided for this message type

Description

None

Message ID : CGA2646I

Severity

Information

Message ID : CGA2643I

Long Form

Access checkK tracing: Policy [{0}]: No rule matched - default action is [Deny]

Short Form

No short form is provided for this message type

Description

None

Message ID : CGA2647I

Severity

Information

Long Form

Access checkK tracing: Policy [{0}]: Using effect of rule number [{1}]: [{2} {3} {4}]

Short Form

No short form is provided for this message type

Description

None

Message ID : CGA2660I

Severity

Information

Long Form

Policy [{0}]: Set [{1}] empty with no [{2}]

Short Form

Empty policy set

Parameters

Label	CEF Label	Type	Usage
pol	cs1	Text	Policy name
oType	vds_oType	Text	Object type in policy rule
oName	vds_oName	Text	Object name in policy rule

Message ID : CGA2647I

Description

None

Message ID : CGA2661I

Severity

Information

Long Form

Policy: Set [{0}] empty with no [{1}]

Short Form

Empty policy set

Parameters

Label	CEF Label	Type	Usage
oType	vds_oType	Text	Object type in policy rule
oName	vds_oName	Text	Object name in policy rule

Description

None

Message ID : CGA3001I

Severity

Information

Long Form

EVENT: {0}

Short Form

Event

Parameters

Label	CEF Label	Type	Usage
showStr	reason	Text	Code specifying reason for allowing access, if any

Description

None

Message ID : CGA2661I

Message ID : CGA3005I

Severity

Information

Long Form

Host password successfully supplied

Short Form

Host password accepted.

Parameters

No parameters are provided for this message type

Description

None

Message ID : CGA3006I

Severity

Information

Message ID : CGA3005I

Long Form

A host password was entered, but was not required

Short Form

Host password not required

Parameters

No parameters are provided for this message type

Description

None

Message ID : CGA3019I

Severity

Information

Long Form

Challenge/Response: Successfully unlocked keys

Short Form

Challenge/Response successful

Parameters

No parameters are provided for this message type

Description

None

Message ID : CGA3020I

Severity

Information

Long Form

Challenge/Response: Challenge/response was entered, but was not required

Short Form

Challenge/Response not required

Parameters

No parameters are provided for this message type

Description

None

Message ID : CGA3058I

Severity

Information

Long Form

[AUDIT] Process[{0}] Pid[{1}] Uid[{2}] Operation[{3}] File[{4}] Effect[PERMIT]

Short Form

Sysfile modified

Parameters

Label	CEF Label	Type	Usage
command	command	Text	Task struct comm field
pid	dvcpid	Numeric	Numeric process ID

Message ID : CGA3020I

Label	CEF Label	Type	Usage
uid	suid	Numeric	User id
op_name	op_name	Text	Operation name
filePath	filePath	Text	Full path to file

Description

None

Message ID : CGA3105I

Severity

Information

Long Form

LDT: Error deleting stale metadata for [{0}]. Delete existing metadata before guarding with a production or data transform policy.

Short Form

LDT: Error deleting stale metadata

Parameters

Label	CEF Label	Type	Usage
-------	-----------	------	-------

Message ID : CGA3058I

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : CGA3183I

Severity

Information

Long Form

Successfully unguarded path [{0}]

Short Form

Ungrd Success

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Message ID : CGA3105I

Description

None

Message ID : CGA3186I

Severity

Information

Long Form

Successfully configured automount for path [{0}]

Short Form

Automnt Success

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	GuardPoint base directory

Description

None

Message ID : CGA3183I

Message ID : CGA3193I

Severity

Information

Long Form

Successfully guarded [{0}]

Short Form

Grd Success

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	GuardPoint base directory

Description

None

Message ID : CGA3194I

Severity

Information

Long Form

Successfully guarded [{0}] in simulation mode

Short Form

SimMode Grd Success

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	GuardPoint base directory

Description

None

Message ID : CGA3195I

Severity

Information

Message ID : CGA3194I

Long Form

Successfully guarded [{0}] from container [{1}]

Short Form

Cntnr Grd Success

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	GuardPoint base directory
dockerid	dockerid	Text	Docker image or container id

Description

None

Message ID : CGA3196I

Severity

Information

Message ID : CGA3195I

Long Form

Successfully guarded [{0}] from container [{1}] in simulation mode

Short Form

SimMode Cntnr Grd Success

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	GuardPoint base directory
dockerid	dockerid	Text	Docker image or container id

Description

None

Message ID : CGA3197I

Severity

Information

Message ID : CGA3196I

Long Form

[{0}] System lock enabled

Short Form

System lock enabled

Parameters

Label	CEF Label	Type	Usage
stime	start	Text	A start time stamp

Description

None

Message ID : CGA3198I

Severity

Information

Long Form

[{0}] System lock disabled

Message ID : CGA3197I

Short Form

SysLock Disabled

Parameters

Label	CEF Label	Type	Usage
stime	start	Text	A start time stamp

Description

None

Message ID : CGA3199I

Severity

Information

Long Form

[{0}] FS agent lock enabled

Short Form

FSAgentLock Enabled

Message ID : CGA3198I

Parameters

Label	CEF Label	Type	Usage
stime	start	Text	A start time stamp

Description

None

Message ID : CGA3200I

Severity

Information

Long Form

[{0}] FS agent lock disabled

Short Form

FSAgentLock Disabled

Parameters

Label	CEF Label	Type	Usage
stime	start	Text	A start time stamp

Message ID : CGA3199I

Description

None

Message ID : CGA3201I

Severity

Information

Long Form

[{0}] Concise logging enabled

Short Form

ConsLog Enabled

Parameters

Label	CEF Label	Type	Usage
stime	start	Text	A start time stamp

Description

None

Message ID : CGA3200I

Message ID : CGA3202I

Severity

Information

Long Form

[{0}] Concise logging disabled

Short Form

ConsLog Disabled

Parameters

Label	CEF Label	Type	Usage
stime	start	Text	A start time stamp

Description

None

Message ID : CGA3203I

Severity

Information

Long Form

Policy [{0}] took effect or was modified

Short Form

Pol Modified

Parameters

Label	CEF Label	Type	Usage
pol	cs1	Text	Policy name

Description

None

Message ID : CGA3204I

Severity

Information

Message ID : CGA3203I

Long Form

Successfully unguarded [{0}] from container [{1}]

Short Form

Cntnr Ungrd Success

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	GuardPoint base directory
dockerid	dockerid	Text	Docker image or container id

Description

None

Message ID : CGA3205I

Severity

Information

Message ID : CGA3204I

Long Form

Successfully unguarded [{0}]

Short Form

Ungrd Success

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	GuardPoint base directory

Description

None

Message ID : CGA3207I

Severity

Information

Long Form

FS Agent lock successful

Message ID : CGA3205I

Short Form

FSAgent Lock Success

Parameters

No parameters are provided for this message type

Description

None

Message ID : CGA3208I

Severity

Information

Long Form

FS Agent unlock successful

Short Form

FSAgent Unlock Success

Message ID : CGA3207I

Parameters

No parameters are provided for this message type

Description

None

Message ID : CGA3209I

Severity

Information

Long Form

System is now locked

Short Form

System Lock Success

Parameters

No parameters are provided for this message type

Message ID : CGA3208I

Description

None

Message ID : CGA3210I

Severity

Information

Long Form

System is now unlocked

Short Form

System Unlock Success

Parameters

No parameters are provided for this message type

Description

None

Message ID : CGA3209I

Message ID : CGA3211I

Severity

Information

Long Form

McAfee Host Intrusion Prevention is disabled while the system is unlocked

Short Form

HIPS Disabled

Parameters

No parameters are provided for this message type

Description

None

Message ID : CGA3213I

Severity

Information

Message ID : CGA3211I

Long Form

LDT: Completed scanning guardpoint [{0}].

Short Form

LDT: Completed scanning guardpoint

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	GuardPoint base directory

Description

None

Message ID : CGA3214I

Severity

Information

Long Form

LDT: Starting transformation for guardpoint [{0}].

Message ID : CGA3213I

Short Form

LDT: Starting transformation for guardpoint

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	GuardPoint base directory

Description

None

Message ID : CGA3215I

Severity

Information

Long Form

LDT: Completed transformation for guardpoint [{0}].

Short Form

LDT: Completed transformation for guardpoint

Message ID : CGA3214I

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	GuardPoint base directory

Description

None

Message ID : CGA3216I

Severity

Information

Long Form

LDT: Skipping transformation of passthrough file [{0}].

Short Form

LDT: Skipping transformation of passthrough file

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Message ID : CGA3215I

Description

None

Message ID : CGA3217I

Severity

Information

Long Form

LDT: Skipping transformation of read-only file [{0}].

Short Form

LDT: Skipping transformation of read-only file

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : CGA3216I

Message ID : CGA3219I

Severity

Information

Long Form

LDT: Starting transformation of file [{0}].

Short Form

LDT: Starting trasformation of file

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : CGA3221I

Severity

Information

Long Form

[AUDIT] Process[{0}] Pid[{1}] Uid[{2}] Operation[{3}] File[{4}] ContainerID[{5}] Effect[PERMIT]

Short Form

Sysfile modified

Parameters

Label	CEF Label	Type	Usage
command	command	Text	Task struct comm field
pid	dvcpid	Numeric	Numeric process ID
uid	suid	Numeric	User id
op_name	op_name	Text	Operation name
filePath	filePath	Text	Full path to file
cid	cid	Text	Container ID

Description

None

Message ID : CGA3221I

Message ID : CGA3224I

Severity

Information

Long Form

LDT: Completed transformation of guardpoint [{0}] {1}

Short Form

LDT: Completed transformation of guardpoint

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	GuardPoint base directory
ldt_stats	ldt_stats	Text	LDT statistics

Description

None

Message ID : CGA3225I

Severity

Information

Long Form

LDT: Skipping transformation of reparse point or link [{0}].

Short Form

LDT: Skipping transformation of reparse point

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : CGA3226I

Severity

Information

Long Form

LDT: Scan completed for guardpoint [{0}]. Data statistics for guard point: {1}.

Short Form

LDT: GP stats:

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	GuardPoint base directory
ldt_stats	ldt_stats	Text	LDT statistics

Description

None

Message ID : CGA3240I

Message ID : CGA3226I

Severity

Information

Long Form

LDT: Skipping transformation of passthrough file [{0}]. The file resides in the boot directory. CTE cannot encrypt boot directory files.

Short Form

LDT: Skipping passthrough bootdir

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : CGA3241I

Severity

Information

Message ID : CGA3240I

Long Form

LDT: Skipping transformation of passthrough file [{0}]. CTE cannot encrypt these files. They are already encrypted using NTFS encryption or compressed.

Short Form

LDT: Skipping passthrough encrypted

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : CGA3242I

Severity

Information

Long Form

LDT: Skipping transformation of passthrough file [{0}]. File is not in a GuardPoint directory.

Message ID : CGA3241I

Short Form

LDT: Skipping passthrough notfiltered

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : CGA3244I

Severity

Information

Long Form

Volume [{0}] is being mounted. Guard points on this volume will be protected by Thales CTE

Short Form

Volume is being mounted

Message ID : CGA3242I

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : CGA3245I

Severity

Information

Long Form

CTE upgrade enabled

Short Form

VTE upgrade enabled

Parameters

No parameters are provided for this message type

Message ID : CGA3244I

Description

None

Message ID : CGA3246I

Severity

Information

Long Form

CTE upgrade disabled

Short Form

VTE upgrade disabled

Parameters

No parameters are provided for this message type

Description

None

Message ID : CGA3245I

Message ID : CGA3247I

Severity

Information

Long Form

CTE upgrade canceled

Short Form

VTE upgrade canceled

Parameters

No parameters are provided for this message type

Description

None

Message ID : CGA3248I

Severity

Information

Message ID : CGA3247I

Long Form

CTE upgraded on reboot

Short Form

VTE upgraded on reboot

Parameters

No parameters are provided for this message type

Description

None

Message ID : CGA3257I

Severity

Information

Long Form

LDT: Exclusive access for rekey delayed on inode [%lld].

Short Form

LDT exclusive delayed

Parameters

Label	CEF Label	Type	Usage
node	vds_node	Numeric	A node identifier

Description

None

Message ID : CGA3258I

Severity

Information

Long Form

LDT: Exclusive access for rekey granted after delay on inode [%lld].

Short Form

LDT exclusive granted

Message ID : CGA3257I

Parameters

Label	CEF Label	Type	Usage
node	vds_node	Numeric	A node identifier

Description

None

Message ID : CGA3269I

Severity

Information

Long Form

Key change detected on {0} with Operation [{1}] and classification {2}

Short Form

Classification key change

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Message ID : CGA3258I

Label	CEF Label	Type	Usage
tag_op	tag_op	Text	Tag operation
tag	tag	Text	Tag

Description

None

Message ID : CGA3270I

Severity

Information

Long Form

Operation {0} failed because data classification is not enabled on {1}

Short Form

Classification not enabled

Parameters

Label	CEF Label	Type	Usage
tag_op	tag_op	Text	Tag operation

Message ID : CGA3269I

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : CGA3271I

Severity

Information

Long Form

Data classification initialization has not been finished for guard point {0}

Short Form

classification not initialized

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	GuardPoint base directory

Message ID : CGA3270I

Description

None

Message ID : CGA3273I

Severity

Information

Long Form

Succeeded to write classification {0} to {1}

Short Form

Succeeded to write

Parameters

Label	CEF Label	Type	Usage
tag	tag	Text	Tag
filePath	filePath	Text	Full path to file

Message ID : CGA3271I

Description

None

Message ID : CGA3281I

Severity

Information

Long Form

ESG/IDT-INFO: Data transformation complete on ESG/IDT-Capable device [{0}]

Short Form

IDT ok

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	GuardPoint base directory

Description

None

Message ID : CGA3273I

Message ID : CGA3283I

Severity

Information

Long Form

LDT: Deferred key rotation on GuardPoint [{0}] until after completion of current transformation

Short Form

Defer rotate ok

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	GuardPoint base directory

Description

None

Message ID : CGA3287I

Severity

Information

Long Form

Acquiring permission to remediate {0}

Short Form

Acquiring permission to remediate

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : CGA3288I

Severity

Information

Message ID : CGA3287I

Long Form

Got permission to remediate {0}

Short Form

Got permission to remediate

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : CGA3290I

Severity

Information

Long Form

Preparing to remediate {0}

Message ID : CGA3288I

Short Form

Preparing to remediate

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : CGA3291I

Severity

Information

Long Form

Ready to remediate {0}

Short Form

Ready to remediate

Message ID : CGA3290I

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : CGA3293I

Severity

Information

Long Form

Remediating {0} from {1} to {2} offline

Short Form

Remediating offline

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Message ID : CGA3291I

Label	CEF Label	Type	Usage
key	cs3	Text	Name of key or key pair
key	cs3	Text	Name of key or key pair

Description

None

Message ID : CGA3294I

Severity

Information

Long Form

Remediated {0} from {1} to {2} offline

Short Form

Remediated offline

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Message ID : CGA3293I

Label	CEF Label	Type	Usage
key	cs3	Text	Name of key or key pair
key	cs3	Text	Name of key or key pair

Description

None

Message ID : CGA3296I

Severity

Information

Long Form

Committing remediation for {0}

Short Form

Committing remediation

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Message ID : CGA3294I

Description

None

Message ID : CGA3297I

Severity

Information

Long Form

Committed remediation for {0}

Short Form

Committed remediation

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : CGA3296I

Message ID : CGA3299I

Severity

Information

Long Form

Remediating {0} from {1} to {2} online

Short Form

Remediating online

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file
key	cs3	Text	Name of key or key pair
key	cs3	Text	Name of key or key pair

Description

None

Message ID : CGA3300I

Severity

Information

Long Form

Remediated {0} from {1} to {2} online

Short Form

Remediated online

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file
key	cs3	Text	Name of key or key pair
key	cs3	Text	Name of key or key pair

Description

None

Message ID : CGA3305I

Severity

Information

Long Form

ESG-INFO: Process [{0}] allowed on ESG device [{1}]

Short Form

Allow ESG

Parameters

Label	CEF Label	Type	Usage
sproc	sproc	Text	Source process
gp	fileId	Text	GuardPoint base directory

Description

None

Message ID : CGA3343I

Severity

Information

Long Form

Remediation is being done on other cte client for {0}

Short Form

Remediation on nfs

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Logger CGA: Warnings

Message ID : CGA2615W

Severity

Warning

Long Form

[{0} {1}]: Sub-domain [{2}] not found

Short Form

No short form is provided for this message type

Description

None

Message ID : CGA2616W

Severity

Warning

Long Form

[{0} {1}]: Undefined sub-domain [{2}]

Short Form

No short form is provided for this message type

Description

None

Message ID : CGA2623W

Severity

Warning

Long Form

Policy [{0}]: Rename problem: source [{1}] is encrypted by key [{2}] but destination [{3}] by key [{4}]

Short Form

Policy rename failed

Parameters

Label	CEF Label	Type	Usage
pol	cs1	Text	Policy name
oldFilePath	oldFilePath	Text	Previous path to file (for rename and link)
key	cs3	Text	Name of key or key pair
filePath	filePath	Text	Full path to file
altKey	vds_altKey	Text	Name of alternate key for multi-key operations

Description

None

Message ID : CGA2901W

Severity

Warning

Long Form

Challenge/Response: Challenge/response requested to decrypt keys

Short Form

Challenge/Response requested to decrypt keys

Parameters

No parameters are provided for this message type

Description

None

Message ID : CGA3002W

Severity

Warning

Long Form

EVENT: {0}

Short Form

Event

Parameters

Label	CEF Label	Type	Usage
showStr	reason	Text	Code specifying reason for allowing access, if any

Description

None

Message ID : CGA3104W

Severity

Warning

Long Form

LDT: Volume dismounted. Aborting transformation at file [{0}]

Short Form

LDT: Stopping on dismount

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Message ID : CGA3002W

Description

None

Message ID : CGA3106W

Severity

Warning

Long Form

LDT: The guard point [{0}] does not have a valid transformation policy, there is no new key rule

Short Form

LDT: no new key rule

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	GuardPoint base directory

Description

None

Message ID : CGA3104W

Message ID : CGA3107W

Severity

Warning

Long Form

LDT: The guard point [{0}] does not have a valid transformation policy, there is no key_op rule

Short Form

LDT: no key_op rule

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	GuardPoint base directory

Description

None

Message ID : CGA3108W

Severity

Warning

Long Form

LDT: The guard point [{0}] does not support Live Data Transform, only file operations from the Offline Data Transform process will be allowed

Short Form

LDT: online rekey not supported

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	GuardPoint base directory

Description

None

Message ID : CGA3231W

Severity

Warning

Message ID : CGA3108W

Long Form

Failed to get a HDFS file name for {0}. Check the secfsd.log and the vor-hdfs-stderr.log for more details, and make sure the NameNode is running

Short Form

Failed to get HDFS file name

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : CGA3243W

Severity

Warning

Long Form

Volume [{0}] is getting dismounted. Guard Points on this volume will not be protected by Thales CTE

Message ID : CGA3231W

Short Form

Volume is getting dismounted

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : CGA3265W

Severity

Warning

Long Form

FSADM-ALERT: ESG/IDT required Signature Set for system utilities may have to be resigned {0}

Short Form

FSADM-ALERT: Resigning of file system binaries is required

Message ID : CGA3243W

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : CGA3276W

Severity

Warning

Long Form

Denied access to {0}{1} during classification initialization

Short Form

File access denied during initialization

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Message ID : CGA3265W

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : CGA3285W

Severity

Warning

Long Form

Denied access to data classification internal file {0}{1}

Short Form

Internal file access denied

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file
filePath	filePath	Text	Full path to file

Message ID : CGA3276W

Description

None

Message ID : CGA3286W

Severity

Warning

Long Form

Denied access to {0}{1} during data remediation

Short Form

File access denied during remediation

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file
filePath	filePath	Text	Full path to file

Description

None

Message ID : CGA3346W

Severity

Warning

Long Form

Ptrace allowed on process [{0}] pid [{1}]

Short Form

Ptrace Attach Allowed

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file
pid	dvcpid	Numeric	Numeric process ID

Message ID : CGA3286W

Description

None

Message ID : CGA3352W

Severity

Warning

Long Form

LDT-NFS-ACCESSONLY-ALERT: Policy/key version validation failed for GuardPoint [{0}].Policy/Key version information doesn't match with primary node.

Short Form

LDT-NFS-ACCESSONLY-ALERT: Policy/key version mismatched

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	GuardPoint base directory

Description

None

Message ID : CGA3346W

Message ID : CGA3353W

Severity

Warning

Long Form

LDT-NFS-ACCESSIONLY-ALERT: Unable to perform the Policy/key validation for GuardPoint [{0}] , Disable->Enable the GuardPoints.

Short Form

LDT-NFS-ACCESSIONLY-ALERT: Policy/key validation failed

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	GuardPoint base directory

Description

None

Logger CGP: Errors

Message ID : CGP2602E

Severity

Error

Long Form

{0} Policy[{1}] User[{2}] Process[{3}] Action[{4}] Res[{5}{6}] Key[{7}] Effect[{8} {9}]

Short Form

Reject access

Parameters

Label	CEF Label	Type	Usage
cat	cat	Text	Event Category (e.g. AUDIT, TRACE)
pol	cs1	Text	Policy name
user	suser	Text	User name
sproc	sproc	Text	Source process
act	act	Text	Action being requested or performed

Label	CEF Label	Type	Usage
gp	fileId	Text	GuardPoint base directory
filePath	filePath	Text	Full path to file
key	cs3	Text	Name of key or key pair
denyStr	msg	Text	Code specifying reason for denying access, if any
showStr	reason	Text	Code specifying reason for allowing access, if any

Description

A GuardPoint policy has blocked access to encrypted data.The reason for blocking the attempt is provided in the message fields.

Message ID : CGP2604E

Severity

Error

Long Form

{0} Policy[{1}] User[{2}] Process[{3}] Action[{4}] Res[{5}{6}] {7} Effect[{8} {9}]

Short Form

Reject access

Parameters

Label	CEF Label	Type	Usage
cat	cat	Text	Event Category (e.g. AUDIT, TRACE)
pol	cs1	Text	Policy name
user	suser	Text	User name
sproc	sproc	Text	Source process
act	act	Text	Action being requested or performed
gp	fileId	Text	GuardPoint base directory
filePath	filePath	Text	Full path to file
denyStr	msg	Text	Code specifying reason for denying access, if any
showStr	reason	Text	Code specifying reason for allowing access, if any

Description

A GuardPoint policy has blocked access to encrypted data. The reason for blocking the attempt is provided in the message fields.

Message ID : CGP2606E

Severity

Error

Message ID : CGP2604E

Long Form

{0} Policy[{1}] User[{2}] Process[{3}] Action[{4}] Res[{5}{6}] Effect[{7} {8}]

Short Form

Reject node

Parameters

Label	CEF Label	Type	Usage
cat	cat	Text	Event Category (e.g. AUDIT, TRACE)
pol	cs1	Text	Policy name
user	suser	Text	User name
sproc	sproc	Text	Source process
act	act	Text	Action being requested or performed
gp	fileId	Text	GuardPoint base directory
filePath	filePath	Text	Full path to file
denyStr	msg	Text	Code specifying reason for denying access, if any
showStr	reason	Text	Code specifying reason for allowing access, if any

Description

A GuardPoint policy has blocked access to encrypted data. The reason for blocking the attempt is provided in the message fields.

Message ID : CGP2608E

Severity

Error

Long Form

{0} Policy[{1}] User[{2}] Process[{3}] Action[{4}] Res[{5}{6}] [{7}{8}] Effect[{9} {10}]

Short Form

Reject link

Parameters

Label	CEF Label	Type	Usage
cat	cat	Text	Event Category (e.g. AUDIT, TRACE)
pol	cs1	Text	Policy name
user	suser	Text	User name
sproc	sproc	Text	Source process

Label	CEF Label	Type	Usage
act	act	Text	Action being requested or performed
gp	fileId	Text	GuardPoint base directory
oldFilePath	oldFilePath	Text	Previous path to file (for rename and link)
filePath	filePath	Text	Full path to file
denyStr	msg	Text	Code specifying reason for denying access, if any
showStr	reason	Text	Code specifying reason for allowing access, if any

Description

None

Message ID : CGP2610E

Severity

Error

Long Form

{0} Policy[{1}] User[{2}] Process[{3}] Action[{4}] Res[{5}{6}] [{7}{8}] Effect[{9} {10}]

Short Form

Reject rename

Parameters

Label	CEF Label	Type	Usage
cat	cat	Text	Event Category (e.g. AUDIT, TRACE)
pol	cs1	Text	Policy name
user	suser	Text	User name
sproc	sproc	Text	Source process
act	act	Text	Action being requested or performed
gp	fileId	Text	GuardPoint base directory
oldFilePath	oldFilePath	Text	Previous path to file (for rename and link)
filePath	filePath	Text	Full path to file
denyStr	msg	Text	Code specifying reason for denying access, if any
showStr	reason	Text	Code specifying reason for allowing access, if any

Description

None

Logger CGP: Information

Message ID : CGP2601I

Severity

Information

Long Form

{0} Policy[{1}] User[{2}] Process[{3}] Action[{4}] Res[{5}{6}] Key[{7}] Effect[{8} {9}]

Short Form

Audit access

Parameters

Label	CEF Label	Type	Usage
cat	cat	Text	Event Category (e.g. AUDIT, TRACE)
pol	cs1	Text	Policy name
user	suser	Text	User name
sproc	sproc	Text	Source process
act	act	Text	Action being requested or performed

Label	CEF Label	Type	Usage
gp	fileId	Text	GuardPoint base directory
filePath	filePath	Text	Full path to file
key	cs3	Text	Name of key or key pair
denyStr	msg	Text	Code specifying reason for denying access, if any
showStr	reason	Text	Code specifying reason for allowing access, if any

Description

None

Message ID : CGP2603I

Severity

Information

Long Form

{0} Policy[{1}] User[{2}] Process[{3}] Action[{4}] Res[{5}{6}] {7} Effect[{8} {9}]

Short Form

Audit access

Message ID : CGP2601I

Parameters

Label	CEF Label	Type	Usage
cat	cat	Text	Event Category (e.g. AUDIT, TRACE)
pol	cs1	Text	Policy name
user	suser	Text	User name
sproc	sproc	Text	Source process
act	act	Text	Action being requested or performed
gp	fileId	Text	GuardPoint base directory
filePath	filePath	Text	Full path to file
denyStr	msg	Text	Code specifying reason for denying access, if any
showStr	reason	Text	Code specifying reason for allowing access, if any

Description

None

Message ID : CGP2605I

Severity

Information

Message ID : CGP2603I

Long Form

{0} Policy[{1}] User[{2}] Process[{3}] Action[{4}] Res[{5}{6}] Effect[{7} {8}]

Short Form

Audit node

Parameters

Label	CEF Label	Type	Usage
cat	cat	Text	Event Category (e.g. AUDIT, TRACE)
pol	cs1	Text	Policy name
user	suser	Text	User name
sproc	sproc	Text	Source process
act	act	Text	Action being requested or performed
gp	fileId	Text	GuardPoint base directory
filePath	filePath	Text	Full path to file
denyStr	msg	Text	Code specifying reason for denying access, if any
showStr	reason	Text	Code specifying reason for allowing access, if any

Description

None

Message ID : CGP2607I

Severity

Information

Long Form

{0} Policy[{1}] User[{2}] Process[{3}] Action[{4}] Res[{5}{6}] [{7}{8}] Effect[{9} {10}]

Short Form

Audit link

Parameters

Label	CEF Label	Type	Usage
cat	cat	Text	Event Category (e.g. AUDIT, TRACE)
pol	cs1	Text	Policy name
user	suser	Text	User name
sproc	sproc	Text	Source process

Message ID : CGP2605I

Label	CEF Label	Type	Usage
act	act	Text	Action being requested or performed
gp	fileId	Text	GuardPoint base directory
oldFilePath	oldFilePath	Text	Previous path to file (for rename and link)
filePath	filePath	Text	Full path to file
denyStr	msg	Text	Code specifying reason for denying access, if any
showStr	reason	Text	Code specifying reason for allowing access, if any

Description

None

Message ID : CGP2609I

Severity

Information

Long Form

{0} Policy[{1}] User[{2}] Process[{3}] Action[{4}] Res[{5}{6}] [{7}{8}] Effect[{9} {10}]

Message ID : CGP2607I

Short Form

Audit rename

Parameters

Label	CEF Label	Type	Usage
cat	cat	Text	Event Category (e.g. AUDIT, TRACE)
pol	cs1	Text	Policy name
user	suser	Text	User name
sproc	sproc	Text	Source process
act	act	Text	Action being requested or performed
gp	fileId	Text	GuardPoint base directory
oldFilePath	oldFilePath	Text	Previous path to file (for rename and link)
filePath	filePath	Text	Full path to file
denyStr	msg	Text	Code specifying reason for denying access, if any
showStr	reason	Text	Code specifying reason for allowing access, if any

Description

None

Logger CGS: Errors

Message ID : CGS2613E

Severity

Error

Long Form

Memory allocation failed in [{0}] at line [{1}]

Short Form

Out of memory

Parameters

No parameters are provided for this message type

Description

None

Message ID : CGS3025E

Severity

Error

Long Form

LDT: Unable to remove LDT extended attribute on [{0}]. Error: [{1}]

Short Form

Extended attr delete

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file
showStr	reason	Text	Code specifying reason for allowing access, if any

Description

None

Message ID : CGS3026E

Severity

Error

Long Form

LDT-ALERT: QoS failed to start

Short Form

QoS failed to start

Parameters

No parameters are provided for this message type

Description

None

Message ID : CGS3027E

Severity

Error

Message ID : CGS3026E

Long Form

LDT-ALERT: Failed to launch transformation on [{0}]

Short Form

LDT: launch failure

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	GuardPoint base directory

Description

None

Message ID : CGS3028E

Severity

Error

Long Form

LDT: Encryption key for file [{0}] unavailable for LDT, possibly due to loss of communication to DSM

Message ID : CGS3027E

Short Form

LDT: Key unavailable

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : CGS3031E

Severity

Error

Long Form

LDT: Rekey failed for file [{0}] on guard point [{1}]. Error {2}

Short Form

LDT: failed

Message ID : CGS3028E

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file
gp	fileId	Text	GuardPoint base directory
ecode	cn1	Numeric	An error code

Description

None

Message ID : CGS3032E

Severity

Error

Long Form

LDT-ALERT: Key rotation failed on guard point [{0}]

Short Form

LDT: Key rotation failed

Message ID : CGS3031E

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	GuardPoint base directory

Description

None

Message ID : CGS3033E

Severity

Error

Long Form

LDT-ALERT: Failed to update LDT attribute on guard point [{0}]. Error: [{1}]

Short Form

LDT: Key rotation failure, EA

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Message ID : CGS3032E

Label	CEF Label	Type	Usage
ecode	cn1	Numeric	An error code

Description

None

Message ID : CGS3034E

Severity

Error

Long Form

LDT-ALERT: Failed to suspend rekey on guard point [{0}]

Short Form

LDT: suspend failure

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	GuardPoint base directory

Message ID : CGS3033E

Description

None

Message ID : CGS3035E

Severity

Error

Long Form

LDT: Failed to suspend rekey on all guard points

Short Form

LDT: suspend failure: all

Parameters

No parameters are provided for this message type

Description

None

Message ID : CGS3034E

Message ID : CGS3038E

Severity

Error

Long Form

LDT-ALERT: Failed to resume rekey on guard point [{0}]

Short Form

LDT: resume failure

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	GuardPoint base directory

Description

None

Message ID : CGS3039E

Severity

Error

Long Form

LDT-ALERT: Failed to resume rekey on all guard points

Short Form

LDT: resume failure: all

Parameters

No parameters are provided for this message type

Description

None

Message ID : CGS3042E

Severity

Error

Message ID : CGS3039E

Long Form

LDT: Skipped LDT recovery on read-only file system [{0}]

Short Form

Skipped LDT recovery: ROFS

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	GuardPoint base directory

Description

None

Message ID : CGS3043E

Severity

Error

Long Form

LDT-ALERT: MDS file [{0}] exceeded diskpace quota on gp [{1}]

Message ID : CGS3042E

Short Form

MDS ENOSPC

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file
gp	fileId	Text	GuardPoint base directory

Description

None

Message ID : CGS3044E

Severity

Error

Long Form

LDT: Insufficient memory condition encountered during LDT on guard point [{0}]

Message ID : CGS3043E

Short Form

MDS ENOMEM

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	GuardPoint base directory

Description

None

Message ID : CGS3045E

Severity

Error

Long Form

LDT-ALERT: Failed to update LDT attribute

Short Form

LDT: xattr failure

Message ID : CGS3044E

Parameters

No parameters are provided for this message type

Description

None

Message ID : CGS3047E

Severity

Error

Long Form

LDT-ALERT: Aborting rekey of file [{0}] due to insufficient disk space

Short Form

LDT:SFS ENOSPC

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Message ID : CGS3045E

Description

None

Message ID : CGS3048E

Severity

Error

Long Form

LDT: Aborting rekey of file [{0}] due to lack of free memory. Try closing other applications to resolve the issue

Short Form

LDT:SFS ENOMEM

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : CGS3047E

Message ID : CGS3049E

Severity

Error

Long Form

LDT-ALERT: Skipped key rotation on guard point [{0}]. It is on a read-only file system

Short Form

LDT: Skipped ROFS

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	GuardPoint base directory

Description

None

Message ID : CGS3050E

Severity

Error

Long Form

LDT-ALERT: Skipped key rotation on guard point [{0}] due to insufficient disk space

Short Form

LDT: Skipped ENOSPC

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	GuardPoint base directory

Description

None

Message ID : CGS3051E

Severity

Error

Message ID : CGS3050E

Long Form

LDT-ALERT: Failed to rotate key on guard point [{0}]. Another rekey operation is already in progress

Short Form

LDT: Skipped EBUSY

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	GuardPoint base directory

Description

None

Message ID : CGS3052E

Severity

Error

Long Form

LDT-ALERT: Skipped key rotation on guard point [{0}]. Error: [{1}]

Message ID : CGS3051E

Short Form

LDT: Skipped, error

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	GuardPoint base directory
ecode	cn1	Numeric	An error code

Description

None

Message ID : CGS3053E

Severity

Error

Long Form

LDT-ALERT: Failed to rotate key on guard point [{0}] during pre-commit

Message ID : CGS3052E

Short Form

LDT: pre-commit failed

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	GuardPoint base directory

Description

None

Message ID : CGS3054E

Severity

Error

Long Form

LDT-ALERT: Failed to rotate key on guard point [{0}] during commit

Short Form

LDT: commit failed

Message ID : CGS3053E

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	GuardPoint base directory

Description

None

Message ID : CGS3055E

Severity

Error

Long Form

LDT: Failed to abort key rotation on guard point [{0}]

Short Form

LDT: abort failed

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	GuardPoint base directory

Message ID : CGS3054E

Description

None

Message ID : CGS3057E

Severity

Error

Long Form

LDT: Extended attribute of inode [%lld] is corrupted under guard point [{0}]

Short Form

LDT: xattr corrupted

Parameters

Label	CEF Label	Type	Usage
node	vds_node	Numeric	A node identifier
gp	fileId	Text	GuardPoint base directory

Message ID : CGS3055E

Description

None

Message ID : CGS3234E

Severity

Error

Long Form

LDT: Rekey failed for file [{0}] on guard point [{1}]. Error {2}. Reason :{3}

Short Form

LDT: failed

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file
gp	fileId	Text	GuardPoint base directory
ecode	cn1	Numeric	An error code
showStr	reason	Text	Code specifying reason for allowing access, if any

Message ID : CGS3057E

Description

None

Message ID : CGS3253E

Severity

Error

Long Form

LDT: Extended attribute of inode [%lld] is missing under guard point [{0}]

Short Form

LDT: xattr missing

Parameters

Label	CEF Label	Type	Usage
node	vds_node	Numeric	A node identifier
gp	fileId	Text	GuardPoint base directory

Message ID : CGS3234E

Description

None

Message ID : CGS3259E

Severity

Error

Long Form

IV of file [{0}] is corrupted

Short Form

file IV corrupted

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : CGS3253E

Message ID : CGS3260E

Severity

Error

Long Form

IV of file [{0}] is mismatched(file may be restored to wrong fs)

Short Form

file IV mismatched

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : CGS3261E

Severity

Error

Long Form

LDT-ALERT: failed to rekey segment [{0}] of [{1}]. Error: [{2}]

Short Form

LDT: failure to rekey segment

Parameters

Label	CEF Label	Type	Usage
segID	vds_segID	Numeric	Segment ID
filePath	filePath	Text	Full path to file
ecode	cn1	Numeric	An error code

Description

None

Message ID : CGS3262E

Message ID : CGS3261E

Severity

Error

Long Form

LDT-ALERT: Skipped rekeying [{0}] on guard point [{1}]. Error: [{2}]

Short Form

LDT: skipped rekey on file

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file
gp	fileId	Text	GuardPoint base directory
ecode	cn1	Numeric	An error code

Description

None

Message ID : CGS3263E

Message ID : CGS3262E

Severity

Error

Long Form

LDT-ALERT: LDT recovery failure on guard point [{0}]. Error: [{1}]

Short Form

LDT-ALERT: LDT recovery failure

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	GuardPoint base directory
ecode	cn1	Numeric	An error code

Description

None

Message ID : CGS3264E

Message ID : CGS3263E

Severity

Error

Long Form

LDT-ALERT: Restore of LDT protected file [{0}] not allowed by policy.

Short Form

LDT-ALERT: LDT restore denied

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : CGS3266E

Severity

Error

Message ID : CGS3264E

Long Form

LDT-ALERT: Cannot enable guard point [{0}] due to inconsistencies in underlying file system encountered during LDT recovery.
Status [{1}]

Short Form

LDT-ALERT: LDT recovery failure

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	GuardPoint base directory
count	vds_count	Numeric	A generic count value

Description

None

Message ID : CGS3304E

Severity

Error

Message ID : CGS3266E

Long Form

IDT-TD-ALERT: Node {0} did not respond to pcl command

Short Form

IDT-TD-ALERT: Remote node did not respond to pcl

Parameters

Label	CEF Label	Type	Usage
shost	shost	Text	Source host name

Description

None

Message ID : CGS3305E

Severity

Error

Long Form

IDT-TD-ALERT: Node {0} failed to perform voradmin task

Message ID : CGS3304E

Short Form

IDT-TD-ALERT: voradmin failed on remote node

Parameters

Label	CEF Label	Type	Usage
shost	shost	Text	Source host name

Description

None

Message ID : CGS3306E

Severity

Error

Long Form

IDT-TD-ALERT: Failed to find clique for disk {0}

Short Form

IDT-TD-ALERT: Failed to find clique

Message ID : CGS3305E

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	GuardPoint base directory

Description

None

Message ID : CGS3307E

Severity

Error

Long Form

IDT-TD-ALERT: Failed to distribute IDT-Capable metadata file to remote nodes

Short Form

IDT-TD-ALERT: Failed to distribute IDT-Capable metadata

Parameters

No parameters are provided for this message type

Message ID : CGS3306E

Description

None

Message ID : CGS3308E

Severity

Error

Long Form

IDT-TD-ALERT: Failed to move or rename IDT-Capable metadata file on remote nodes

Short Form

IDT-TD-ALERT: Failed to move or rename IDT-Capable metadata

Parameters

No parameters are provided for this message type

Description

None

Message ID : CGS3307E

Message ID : CGS3309E

Severity

Error

Long Form

IDT-TD-ALERT: Failed to get GuardPoint status on remote nodes

Short Form

IDT-TD-ALERT: Failed to get GuardPoint status

Parameters

No parameters are provided for this message type

Description

None

Message ID : CGS3311E

Severity

Error

Long Form

IDT-TD-ALERT: Failed to complete rekey on remote nodes

Short Form

IDT-TD-ALERT: Failed to complete rekey

Parameters

No parameters are provided for this message type

Description

None

Message ID : CGS3312E

Severity

Error

Long Form

LDT-NFS-ALERT: Host waiting to take over NFS GuardPoint {0} for LDT

Message ID : CGS3311E

Short Form

Waiting to take over

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	GuardPoint base directory

Description

None

Message ID : CGS3313E

Severity

Error

Long Form

LDT-ALERT: Cannot enable GuardPoint due to wrong policy applied to [{0}]

Short Form

Incorrect policy

Message ID : CGS3312E

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	GuardPoint base directory

Description

None

Message ID : CGS3314E

Severity

Error

Long Form

LDT: Cannot enable [{0}] due to stale policy

Short Form

LDT: stale policy

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	GuardPoint base directory

Message ID : CGS3313E

Description

None

Message ID : CGS3315E

Severity

Error

Long Form

LDT-NFS-ALERT: Cannot enable GuardPoint [{0}] on a read-only file system

Short Form

LDT-NFS: Guarding ROFS

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	GuardPoint base directory

Description

None

Message ID : CGS3314E

Message ID : CGS3316E

Severity

Error

Long Form

LDT-ALERT: Failed to process directory rename for {0}, error {1}

Short Form

LDT: dir rename failed

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	GuardPoint base directory
ecode	cn1	Numeric	An error code

Description

None

Message ID : CGS3317E

Severity

Error

Long Form

LDT-ALERT: Failed to rekey {0} file(s) in directory {1}

Short Form

LDT: dir rekey errors

Parameters

Label	CEF Label	Type	Usage
count	vds_count	Numeric	A generic count value
gp	fileId	Text	GuardPoint base directory

Description

None

Message ID : CGS3319E

Severity

Error

Long Form

LDT-NFS-ALERT: Failed to start or stop rekey on GuardPoint [{0}] over NAS, error [{1}]

Short Form

LDT-NFS-ALERT: start or stop failed

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	GuardPoint base directory
ecode	cn1	Numeric	An error code

Description

None

Message ID : CGS3327E

Severity

Error

Long Form

LDT-ALERT: Election of this host for LDT Group Primary role has failed for GuardPoint [{0}]

Short Form

LDT-NFS-ALERT: primary election failed

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	GuardPoint base directory

Description

None

Message ID : CGS3328E

Severity

Error

Long Form

LDT-NFS-ALERT: File operation recovery failed on new primary host after primary election, GuardPoint [{0}] objID [%llu] error [{1}] source [{2}]

Short Form

LDT-NFS-ALERT: fop recovery failed

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	GuardPoint base directory
node	vds_node	Numeric	A node identifier
ecode	cn1	Numeric	An error code
count	vds_count	Numeric	A generic count value

Description

None

Message ID : CGS3329E

Severity

Error

Long Form

LDT-NFS-ALERT: LDT recovery failed on new primary host after primary election, GuardPoint [{0}] objID [%llu] error [{1}]

Short Form

LDT-NFS-ALERT: LDT recovery failed

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	GuardPoint base directory
node	vds_node	Numeric	A node identifier
ecode	cn1	Numeric	An error code

Description

None

Message ID : CGS3331E

Severity

Error

Long Form

LDT-NFS-ALERT: File operation failed on secondary host, GuardPoint [{0}] objID [%llu] error [{1}] source [{2}]

Short Form

LDT-NFS-ALERT: fop failed on secondary

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	GuardPoint base directory
node	vds_node	Numeric	A node identifier
ecode	cn1	Numeric	An error code
count	vds_count	Numeric	A generic count value

Description

None

Message ID : CGS3335E

Severity

Error

Long Form

LDT-ALERT: Failed to check rekey status on file {0}, error {1}

Short Form

LDT: monitor failed

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file
ecode	cn1	Numeric	An error code

Description

None

Message ID : CGS3336E

Severity

Error

Long Form

LDT-ALERT: Failed to enable/apply GuardPoint [{0}]

Short Form

Guard failed

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	GuardPoint base directory

Description

None

Message ID : CGS3337E

Severity

Error

Long Form

LDT-ALERT: Failed to disable/delete GuardPoint [{0}]

Short Form

Unguard failed

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	GuardPoint base directory

Description

None

Message ID : CGS3338E

Severity

Error

Message ID : CGS3337E

Long Form

LDT-ALERT: Failed to join GuardPoint group [{0}]

Short Form

LGS join failed

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	GuardPoint base directory

Description

None

Message ID : CGS3339E

Severity

Error

Long Form

LDT-ALERT: Failed to leave GuardPoint group [{0}]

Message ID : CGS3338E

Short Form

LGS leave failed

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	GuardPoint base directory

Description

None

Message ID : CGS3340E

Severity

Error

Long Form

LDT-ALERT: Failed to enumerate GuardPoint [{0}], please verify the provided CIFS credentials. CIFS credentials may be expired or may not have permission to access.

Short Form

Invalid creds

Message ID : CGS3339E

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	GuardPoint base directory

Description

None

Message ID : CGS3341E

Severity

Error

Long Form

LDT-ALERT: Failed to authenticate a user.

Short Form

CIFS Login error

Parameters

No parameters are provided for this message type

Message ID : CGS3340E

Description

None

Message ID : CGS3342E

Severity

Error

Long Form

LDT-NFS-ALERT: Error processing LDTC message for GuardPoint [{0}], error [{1}], source [{2}]

Short Form

LDT-NFS-ALERT: bad msg

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	GuardPoint base directory
ecode	cn1	Numeric	An error code
count	vds_count	Numeric	A generic count value

Message ID : CGS3341E

Description

None

Message ID : CGS3344E

Severity

Error

Long Form

LDT-NFS-ALERT: Not guarding path [{0}] (Reason: LDT version installed on host is incompatible with version on primary host)

Short Form

LDT-NFS-ALERT: msg ver mismatch

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	GuardPoint base directory

Description

None

Message ID : CGS3342E

Message ID : CGS3349E

Severity

Error

Long Form

LDT-NFS-ALERT: Demotion of Primary host of GuardPoint [{0}] failed, error [{1}]

Short Form

LDT-NFS-ALERT: Primary host demotion failed

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	GuardPoint base directory
ecode	cn1	Numeric	An error code

Description

None

Message ID : CGS3354E

Severity

Error

Long Form

LDT-NFS-ALERT: Manual recovery of DEMOTED GuardPoint failed, GuardPoint [{0}] objID [%llu] error [{1}]

Short Form

LDT-NFS-ALERT: Primary DEMOTION recovery failed

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	GuardPoint base directory
node	vds_node	Numeric	A node identifier
ecode	cn1	Numeric	An error code

Description

None

Message ID : CGS3358E

Severity

Error

Long Form

LDT-NFS-ALERT: DEMOTED GuardPoint [{0}] being recovered while the old demoted primary host is still alive, objID [%llu]

Short Form

LDT-NFS-ALERT: Primary DEMOTION admin recovery, old primary still alive

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	GuardPoint base directory
node	vds_node	Numeric	A node identifier

Description

None

Message ID : CGS3360E

Severity

Error

Long Form

LDT-RAW: Write operation to relocation zone on [/dev/secvm{0}] blocked

Short Form

LDT-RAW: write blocked

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	GuardPoint base directory

Description

None

Message ID : CGS3362E

Severity

Error

Long Form

RWP-RW-ALERT: Potential Ransomware activity[{0}] detected in process ID [{1}], Process name: [{2}]. Num original files written to disk: [{3}]. Sensitivity: [{4}] Mode: [{5}] Reboot or remount on separate VM to access clear files on disk. Prev Code Path: [0x{6}] Latest Code Path: [0x{7}]. Last file checked is [{8}], AlgoSuspect:1 proc flags: [{9}]

Short Form

RWP: Ransomware detected

Parameters

Label	CEF Label	Type	Usage
rwtype	rwtype	Text	string type of RW proocess flags
pid	dvcpid	Numeric	Numeric process ID
pname	pname	Text	Process name
nfiles	vds_nfiles	Numeric	The total number of files in an operation
rwsensvty	rwsensvty	Numeric	Numeric value of RWP sensitivity
rwmode	rwmode	Text	string mode of RW : alert/block
rwcodepath	rwcodepath	Numeric	hex code for tracing RW detection
rwcodepath	rwcodepath	Numeric	hex code for tracing RW detection

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file
rwflags	rwflags	Numeric	bitmap for RW

Description

None

Message ID : CGS3364E

Severity

Error

Long Form

LDT-ALERT: Couldn't elect the primary during failover for [{0}], check DPS config.

Short Form

LDT-ALERT: Couldn't elect primary during failover, please check DPS config

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	GuardPoint base directory

Message ID : CGS3362E

Description

None

Message ID : CGS3365E

Severity

Error

Long Form

LDT-ALERT: No primary exists to join GuardPoint group [{0}]

Short Form

LGS join failed no primary

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	GuardPoint base directory

Description

None

Message ID : CGS3364E

Message ID : CGS3370E

Severity

Error

Long Form

LDT-NFS-ALERT: Rekey started on LDT GuardPoint Group [{0}] containing different CTE versions

Short Form

LDT-NFS-ALERT: mixed mode rekey

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	GuardPoint base directory

Description

None

Message ID : CGS3371E

Severity

Error

Long Form

LDT-NFS-ALERT: GuardPoint Group Service recovery failed for [{0}] error [{1}]

Short Form

LDT-NFS-ALERT: Group Service recovery failed

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	GuardPoint base directory
ecode	cn1	Numeric	An error code

Description

None

Logger CGS: Information

Message ID : CGS3029I

Severity

Information

Long Form

LDT: Cannot enable guard point [{0}] during LDT clean-up process

Short Form

LDT: EA removing

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	GuardPoint base directory

Description

None

Message ID : CGS3030I

Severity

Information

Long Form

LDT: Successfully rekeyed file [{0}]

Short Form

Successfully rekeyed

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : CGS3036I

Severity

Information

Long Form

LDT: Successfully suspended rekey on guard point [{0}]

Short Form

LDT: suspend success

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	GuardPoint base directory

Description

None

Message ID : CGS3037I

Severity

Information

Message ID : CGS3036I

Long Form

LDT: Rekey will be suspended on all applicable guard points

Short Form

LDT: suspend success: all

Parameters

No parameters are provided for this message type

Description

None

Message ID : CGS3040I

Severity

Information

Long Form

LDT: Successfully resumed rekey on guard point [{0}]

Short Form

LDT: resume success

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	GuardPoint base directory

Description

None

Message ID : CGS3041I

Severity

Information

Long Form

LDT: Rekey will be resumed on all applicable guard points

Short Form

LDT: resume success: all

Message ID : CGS3040I

Parameters

No parameters are provided for this message type

Description

None

Message ID : CGS3046I

Severity

Information

Long Form

LDT-ALERT: Suspending rekey of binary file [{0}] during its execution

Short Form

LDT:SFS EXTBUSY

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Message ID : CGS3041I

Description

None

Message ID : CGS3056I

Severity

Information

Long Form

LDT: Rekey operation completed on guard point [{0}]

Short Form

LDT: completed

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	GuardPoint base directory

Description

None

Message ID : CGS3046I

Message ID : CGS3249I

Severity

Information

Long Form

LDT-ALERT: Skipped key rotation on guard point [{0}] on a read-only file system

Short Form

LDT: Skipped ROFS

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	GuardPoint base directory

Description

None

Message ID : CGS3250I

Severity

Information

Long Form

LDT-ALERT: Skipped key rotation on guard point [{0}] due to insufficient disk space

Short Form

LDT: Skipped ENOSPC

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	GuardPoint base directory

Description

None

Message ID : CGS3251I

Severity

Information

Message ID : CGS3250I

Long Form

LDT-ALERT: Skipped key rotation on guard point [{0}] while another rekey operation is in progress

Short Form

LDT: Skipped EBUSY

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	GuardPoint base directory

Description

None

Message ID : CGS3254I

Severity

Information

Long Form

LDT: Metadata will start getting removed from all files in guard point [{0}]

Message ID : CGS3251I

Short Form

Extended attr will be deleted from gp

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	GuardPoint base directory

Description

None

Message ID : CGS3255I

Severity

Information

Long Form

LDT: Metadata has been removed from all files in guard point [{0}]

Short Form

Extended attr deleted from gp

Message ID : CGS3254I

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	GuardPoint base directory

Description

None

Message ID : CGS3277I

Severity

Information

Long Form

LDT-ALERT: Low space on guard point [{0}], increase free space or LDT will be suspended.

Short Form

low disk

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	GuardPoint base directory

Message ID : CGS3255I

Description

None

Message ID : CGS3318I

Severity

Information

Long Form

LDT-NFS-ALERT: Failed to preserve time stamps: GuardPoint [{0}] objID [{1}] error [{2}]

Short Form

LDT-NFS-ALERT: PTS Access

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	GuardPoint base directory
node	vds_node	Numeric	A node identifier
ecode	cn1	Numeric	An error code

Message ID : CGS3277I

Description

None

Message ID : CGS3320I

Severity

Information

Long Form

LDT: Skipping transformation of NOVIEW file [{0}]. File was opened with NOVIEW access.

Short Form

LDT: Skipping NOVIEW

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : CGS3318I

Message ID : CGS3322I

Severity

Information

Long Form

LDT-NFS-ALERT: LDT Communication Master is up

Short Form

LDT-NFS-ALERT: comm group master up

Parameters

No parameters are provided for this message type

Description

None

Message ID : CGS3324I

Severity

Information

Message ID : CGS3322I

Long Form

LDT-NFS-ALERT: LDT Group Primary host has been elected for GuardPoint [{0}]

Short Form

LDT-NFS-ALERT: group primary elected

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	GuardPoint base directory

Description

None

Message ID : CGS3325I

Severity

Information

Long Form

LDT-NFS-ALERT: This host has been promoted to LDT Group Primary role for GuardPoint [{0}]

Message ID : CGS3324I

Short Form

LDT-NFS-ALERT: group primary promoted

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	GuardPoint base directory

Description

None

Message ID : CGS3347I

Severity

Information

Long Form

LDT-NFS-ALERT: Primary host of GuardPoint [{0}] demoting

Short Form

LDT-NFS-ALERT: Primary host demoting

Message ID : CGS3325I

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	GuardPoint base directory

Description

None

Message ID : CGS3348I

Severity

Information

Long Form

LDT-NFS-ALERT: Primary host of GuardPoint [{0}] demoted

Short Form

LDT-NFS-ALERT: Primary host demoted

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	GuardPoint base directory

Message ID : CGS3347I

Description

None

Message ID : CGS3350I

Severity

Information

Long Form

LDT-NFS-ALERT: LDT Communication Master is going down gracefully

Short Form

LDT-NFS-ALERT: Comm group master down gracefully

Parameters

No parameters are provided for this message type

Description

None

Message ID : CGS3348I

Message ID : CGS3355I

Severity

Information

Long Form

LDT-NFS-ALERT: File marked as INCOMPLETE after DEMOTION. Admin intervention is required for recovery, GuardPoint
[{}0}] objID [%llu] error [{}1}]

Short Form

LDT-NFS-ALERT: Primary DEMOTION partial recovery

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	GuardPoint base directory
node	vds_node	Numeric	A node identifier
ecode	cn1	Numeric	An error code

Description

None

Message ID : CGS3357I

Severity

Information

Long Form

LDT-NFS-ALERT: Manual recovery invoked on the DEMOTED GuardPoint [{0}]

Short Form

LDT-NFS-ALERT: Primary DEMOTION full ADMIN recovery

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	GuardPoint base directory

Description

None

Message ID : CGS3359I

Severity

Information

Long Form

LDT-NFS-ALERT: Secondary host DEMOTED due to loss of NAS connection, GuardPoint [{0}]

Short Form

LDT-NFS-ALERT: Secondary host demoted

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	GuardPoint base directory

Description

None

Logger CGS: Warnings

Message ID : CGS3267W

Severity

Warning

Long Form

LDT-ALERT: LDT manual recovery on guard point [{0}] completed with [{1}] errors.

Short Form

LDT-ALERT: LDT manual recovery forced

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	GuardPoint base directory
count	vds_count	Numeric	A generic count value

Description

None

Message ID : CGS3268W

Severity

Warning

Long Form

LDT-ALERT: encrypted data detected in filename [{0}] inode [%lld] in guard point [{1}] under clear exclusion key rule

Short Form

LDT-ALERT: encrypted data in clear file

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file
node	vds_node	Numeric	A node identifier
gp	fileId	Text	GuardPoint base directory

Description

None

Message ID : CGS3302W

Severity

Warning

Long Form

LDT-ALERT: Rekey is restarting due to previous transient error on guard point [{0}]. Error: [{1}]

Short Form

Res acc issue

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	GuardPoint base directory
ecode	cn1	Numeric	An error code

Description

None

Message ID : CGS3303W

Severity

Warning

Long Form

LDT-ALERT: Rekey is restarting due to previous transient error on guard point [{0}]. Error: [{1}] Reason: [{2}]

Short Form

Res acc issue desc

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	GuardPoint base directory
ecode	cn1	Numeric	An error code
showStr	reason	Text	Code specifying reason for allowing access, if any

Description

None

Message ID : CGS3310W

Severity

Warning

Long Form

IDT-TD-WARNING: Failed to delete IDT-Capable metadata file on remote nodes

Short Form

IDT-TD-WARNING: Failed to delete IDT-Capable metadata

Parameters

No parameters are provided for this message type

Description

None

Message ID : CGS3321W

Severity

Warning

Long Form

LDT-NFS-ALERT: LDT Communication Master is down

Short Form

LDT-NFS-ALERT: Comm group master down

Parameters

No parameters are provided for this message type

Description

None

Message ID : CGS3323W

Severity

Warning

Long Form

LDT-NFS-ALERT: LDT Group Primary host left the group for GuardPoint [{0}]

Short Form

LDT-NFS-ALERT: group primary left

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	GuardPoint base directory

Description

None

Message ID : CGS3326W

Severity

Warning

Long Form

LDT-NFS-ALERT: This host cannot be promoted to LDT Group Primary role for GuardPoint [{0}]

Short Form

LDT-NFS-ALERT: refused primary role

Message ID : CGS3323W

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	GuardPoint base directory

Description

None

Message ID : CGS3330W

Severity

Warning

Long Form

LDT-NFS-ALERT: Promotion process taking too long causing delay in file operation, GuardPoint [{0}] objID [%llu]

Short Form

LDT-NFS-ALERT: Promotion taking too long

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	GuardPoint base directory

Message ID : CGS3326W

Label	CEF Label	Type	Usage
node	vds_node	Numeric	A node identifier

Description

None

Message ID : CGS3332W

Severity

Warning

Long Form

LDT-NFS-ALERT: Some members of LDT GuardPoint Group for [{0}] have not received latest key version

Short Form

LDT-NFS-ALERT: group doesn't have the same key

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	GuardPoint base directory

Message ID : CGS3330W

Description

None

Message ID : CGS3333W

Severity

Warning

Long Form

LDT-NFS-ALERT: Lazy rekey operation failed to rekey file [{0}], error [{1}]

Short Form

LDT-NFS-ALERT: lazy rekey failed

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file
ecode	cn1	Numeric	An error code

Message ID : CGS3332W

Description

None

Message ID : CGS3334W

Severity

Warning

Long Form

LDT-NFS-ALERT: LDT remote operation failed across LDT GuardPoint Group for GuardPoint [{0}], ino [%lld], filename [{1}], error [{2}], remote op [{3}]

Short Form

LDT-NFS-ALERT: remote op failed

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	GuardPoint base directory
node	vds_node	Numeric	A node identifier
filePath	filePath	Text	Full path to file
ecode	cn1	Numeric	An error code

Message ID : CGS3333W

Label	CEF Label	Type	Usage
count	vds_count	Numeric	A generic count value

Description

None

Message ID : CGS3345W

Severity

Warning

Long Form

LDT-ALERT: LDT rekey status on files in GuardPoint [{0}] have been manually edited.

Short Form

LDT: rkea_status edited

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	GuardPoint base directory

Message ID : CGS3334W

Description

None

Message ID : CGS3351W

Severity

Warning

Long Form

LDT-NFS-ALERT: LDT Communication Cluster is down

Short Form

LDT-NFS-ALERT: Comm group cluster is down

Parameters

No parameters are provided for this message type

Description

None

Message ID : CGS3345W

Message ID : CGS3363W

Severity

Warning

Long Form

LDT-NFS-ALERT: Dynamically added resource-set is not supported on NFS Guardpoint [{0}].

Short Form

LDT-NFS-ALERT: Dyn resourceset not supp

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	GuardPoint base directory

Description

None

Message ID : CGS3369W

Severity

Warning

Long Form

LDT-NFS-ALERT: GuardPoint Group for [{0}] is in mixed mode; cannot start rekey

Short Form

LDT-NFS-ALERT: key rotation mixed mode

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	GuardPoint base directory

Description

None

Logger COM: Errors

Message ID : COM4547E

Severity

Error

Long Form

Internal error: Invalid configuration type given to communications subsystem. Contact support.

Short Form

No short form is provided for this message type

Description

None

Message ID : COM4631E

Severity

Error

Long Form

OPENSSL ERROR: {0}

Short Form

OpenSSL error

Parameters

Label	CEF Label	Type	Usage
showStr	reason	Text	Code specifying reason for allowing access, if any

Description

None

Message ID : COM4638E

Severity

Error

Long Form

We have detected a change in the system hardware. Communication to the Key Manager has been disabled. This condition can be fixed by re-registering this agent with the Key Manager.

Message ID : COM4631E

Short Form

Hardware Change

Parameters

No parameters are provided for this message type

Description

None

Message ID : COM4644E

Severity

Error

Long Form

An invalid REST object has been received - {0}

Short Form

Bad REST object

Message ID : COM4638E

Parameters

Label	CEF Label	Type	Usage
detail	vds_detail	Text	Fault detail

Description

None

Logger COM: Fatal errors

Message ID : COM4503F

Severity

Fatal error

Long Form

Communications module initialization failure. Contact support.

Short Form

Comms init fail

Parameters

No parameters are provided for this message type

Description

None

Message ID : COM4506F

Severity

Fatal error

Long Form

Failed to set up logger "{0}". Contact support.

Short Form

Logger setup error

Parameters

Label	CEF Label	Type	Usage
showStr	reason	Text	Code specifying reason for allowing access, if any

Description

None

Message ID : COM4511F

Severity

Fatal error

Message ID : COM4506F

Long Form

The communication request to the Key Manager was garbled or otherwise incorrect: error {0}. Contact support.

Short Form

Bad policy request

Parameters

Label	CEF Label	Type	Usage
ecode	cn1	Numeric	An error code

Description

None

Message ID : COM4512F

Severity

Fatal error

Long Form

Policy response garbled: unable to find attribute "{0}".

Message ID : COM4511F

Short Form

Resp attr missing

Parameters

Label	CEF Label	Type	Usage
showStr	reason	Text	Code specifying reason for allowing access, if any

Description

None

Message ID : COM4513F

Severity

Fatal error

Long Form

Unable to configure secure communication channel. Contact support.

Short Form

No short form is provided for this message type

Message ID : COM4512F

Description

None

Message ID : COM4514F

Severity

Fatal error

Long Form

The communication request to the Key Manager was garbled or otherwise incorrect: error {0}. Contact support.

Short Form

Server init req error

Parameters

Label	CEF Label	Type	Usage
ecode	cn1	Numeric	An error code

Description

None

Message ID : COM4513F

Message ID : COM4515F

Severity

Fatal error

Long Form

There was a communication failure with the Key Manager. The server returned a fault: {0}{1}; "{2}"; Subcode: "{3}"; Reason: "{4}"; Detail: "{5}".

Short Form

No short form is provided for this message type

Description

None

Message ID : COM4521F

Severity

Fatal error

Long Form

Internal version not supported, version required: {0}.

Short Form

Bad SDK version

Parameters

Label	CEF Label	Type	Usage
version	vds_version	Text	Software version string

Description

None

Message ID : COM4523F

Severity

Fatal error

Long Form

Unable to establish a connection to a Key Manager for the purpose of policy evaluation. Verify that the configuration file has the correct URL(s) to the server.

Message ID : COM4521F

Short Form

Policy info missing

Parameters

No parameters are provided for this message type

Description

None

Message ID : COM4527F

Severity

Fatal error

Long Form

The Agent could not obtain configuration information. The Agent failed to initialize. Verify connectivity to the Key Manager and retry the operation.

Short Form

Agent config missing

Message ID : COM4523F

Parameters

No parameters are provided for this message type

Description

None

Message ID : COM4529F

Severity

Fatal error

Long Form

Unable to establish an initial connection to any Key Manager. Verify that the configuration file has the correct URL(s) to the server.

Short Form

No config from server

Parameters

No parameters are provided for this message type

Message ID : COM4527F

Description

None

Message ID : COM4531F

Severity

Fatal error

Long Form

Unable to configure secure communication channel. Contact support.

Short Form

SSL setup fail

Parameters

No parameters are provided for this message type

Description

None

Message ID : COM4529F

Message ID : COM4533F

Severity

Fatal error

Long Form

{0} from file does not match that from backup. File: "{1}". Backup: "{2}".

Short Form

Backup opaque data mismatch

Parameters

No parameters are provided for this message type

Description

None

Message ID : COM4534F

Severity

Fatal error

Message ID : COM4533F

Long Form

File type mismatch: {0} must be a directory.

Short Form

Not a dir

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : COM4538F

Severity

Fatal error

Long Form

The Key Manager URL ({0}) must start with "https:".

Message ID : COM4534F

Short Form

Invalid URL

Parameters

Label	CEF Label	Type	Usage
url	request	Text	A uniform resource location

Description

None

Message ID : COM4542F

Severity

Fatal error

Long Form

The agent could not allocate enough memory. Contact support.

Short Form

Out of memory

Message ID : COM4538F

Parameters

No parameters are provided for this message type

Description

None

Message ID : COM4548F

Severity

Fatal error

Long Form

Policy request garbled: unable to find attribute "{0}".

Short Form

Req attr missing

Parameters

Label	CEF Label	Type	Usage
showStr	reason	Text	Code specifying reason for allowing access, if any

Message ID : COM4542F

Description

None

Message ID : COM4551F

Severity

Fatal error

Long Form

The Agent failed to initialize, reporting "{0}". Verify the logging configuration on the Key Manager and retry the operation. If the problem persists, contact support.

Short Form

Agent init error

Parameters

Label	CEF Label	Type	Usage
showStr	reason	Text	Code specifying reason for allowing access, if any

Description

None

Message ID : COM4548F

Message ID : COM4552F

Severity

Fatal error

Long Form

Communication with the Key Manager was established, but an invalid response (error {0}) was received. The requested operation cannot continue. Contact support.

Short Form

Bad policy response

Parameters

Label	CEF Label	Type	Usage
ecode	cn1	Numeric	An error code

Description

None

Message ID : COM4554F

Severity

Fatal error

Long Form

Communication with the Key Manager was established, but an invalid response (error {0}) was received. The requested operation cannot continue. Contact support.

Short Form

Comms response error

Parameters

Label	CEF Label	Type	Usage
ecode	cn1	Numeric	An error code

Description

None

Message ID : COM4558F

Severity

Fatal error

Message ID : COM4554F

Long Form

Key Manager communications failure. URL: {0}. Check the URL in the agent.conf file. Verify that the server url is correct and retry the operation.

Short Form

Bad config from server

Parameters

Label	CEF Label	Type	Usage
url	request	Text	A uniform resource location

Description

None

Message ID : COM4562F

Severity

Fatal error

Long Form

The communication request to the Key Manager was garbled or otherwise incorrect: error {0}. Contact support.

Message ID : COM4558F

Short Form

Comms init error

Parameters

Label	CEF Label	Type	Usage
ecode	cn1	Numeric	An error code

Description

None

Message ID : COM4563F

Severity

Fatal error

Long Form

Key Manager connection failure. Check the URL in the agent.conf file. Verify that the server url is correct and retry the operation.

Short Form

No short form is provided for this message type

Message ID : COM4562F

Description

None

Message ID : COM4567F

Severity

Fatal error

Long Form

Communication with the Key Manager was established, but an invalid response (error {0}) was received. The requested operation cannot continue. Contact support.

Short Form

SDK response error

Parameters

Label	CEF Label	Type	Usage
ecode	cn1	Numeric	An error code

Description

None

Message ID : COM4563F

Message ID : COM4569F

Severity

Fatal error

Long Form

The Key Manager URL is too long. It is {0} characters, while the maximum size is {1} characters. The URL is {2}.

Short Form

URL too long

Parameters

Label	CEF Label	Type	Usage
slen	in	Numeric	Input byte count or length
dlen	out	Numeric	Output byte count or length
url	request	Text	A uniform resource location

Description

None

Message ID : COM4569F

Message ID : COM4571F

Severity

Fatal error

Long Form

File access failure: Unable to open {0}: {1}.

Short Form

Open error

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file
showStr	reason	Text	Code specifying reason for allowing access, if any

Description

None

Message ID : COM4577F

Severity

Fatal error

Long Form

Error adding host {0} information to server.

Short Form

No short form is provided for this message type

Description

None

Message ID : COM4578F

Severity

Fatal error

Long Form

Request from {0} to add host is invalid.

Message ID : COM4577F

Short Form

No short form is provided for this message type

Description

None

Message ID : COM4579F

Severity

Fatal error

Long Form

Response to add host request from {0} is invalid: {1}.

Short Form

No short form is provided for this message type

Description

None

Message ID : COM4578F

Message ID : COM4583F

Severity

Fatal error

Long Form

Error initializing agent.

Short Form

Agent init fail

Parameters

No parameters are provided for this message type

Description

The agent is unable to reach the key manager. You may see any of the following error messages: COM4583F, COM4633W, VMD3770F, VMD3885I or VMD3886I. You may experience any of the following:

1. Connection to the key manager is down.
2. The VMD Host has been deleted from the key manager.
3. The host does not have "Communication Enabled" in the key manager UI.
4. The VMD's host may be deleted from the key manager. Run the register_host utility to re-register the VMD with the key manager.

Message ID : COM4584F

Severity

Fatal error

Long Form

Initialize Agent request invalid, {0} ({1}).

Short Form

Invalid config

Parameters

Label	CEF Label	Type	Usage
ecode	cn1	Numeric	An error code
showStr	reason	Text	Code specifying reason for allowing access, if any

Description

None

Message ID : COM4586F

Severity

Fatal error

Long Form

Error evaluating policy.

Short Form

Policy eval fail

Parameters

No parameters are provided for this message type

Description

None

Message ID : COM4587F

Severity

Fatal error

Message ID : COM4586F

Long Form

Error evaluating policy request, {0}.

Short Form

Policy eval error

Parameters

Label	CEF Label	Type	Usage
ecode	cn1	Numeric	An error code

Description

None

Message ID : COM4588F

Severity

Fatal error

Long Form

Error evaluating policy response, {0}.

Message ID : COM4587F

Short Form

Policy response error

Parameters

Label	CEF Label	Type	Usage
ecode	cn1	Numeric	An error code

Description

None

Message ID : COM4592F

Severity

Fatal error

Long Form

Error running VMSDK server, {0} (port: {1}).

Short Form

VMSDK server error

Message ID : COM4588F

Parameters

Label	CEF Label	Type	Usage
ecode	cn1	Numeric	An error code
port	spt	Numeric	A socket port number

Description

None

Message ID : COM4599F

Severity

Fatal error

Long Form

An error was encountered when trying to listen to requests from the server. The listening interface is "{0}" and the port is {1}.
Error: {2}.

Short Form

No short form is provided for this message type

Message ID : COM4592F

Description

None

Message ID : COM4600F

Severity

Fatal error

Long Form

There was a communication failure with the Key Manager ({0}). The server returned a fault: {1}{2}; "{3}"; Subcode: "{4}"; Reason: "{5}"; Detail: "{6}".

Short Form

SOAP client error

Parameters

Label	CEF Label	Type	Usage
url	request	Text	A uniform resource location
showStr	reason	Text	Code specifying reason for allowing access, if any
ecode	cn1	Numeric	An error code
context	vds_context	Text	Fault context

Message ID : COM4599F

Label	CEF Label	Type	Usage
subcode	vds_subcode	Text	Fault subcode
showStr	reason	Text	Code specifying reason for allowing access, if any
detail	vds_detail	Text	Fault detail

Description

None

Message ID : COM4603F

Severity

Fatal error

Long Form

Unable to parse the URL {0}. This attribute is located in the config file at {1}. Please fix the URL or re-install this product.

Short Form

Bad URL

Parameters

Label	CEF Label	Type	Usage
-------	-----------	------	-------

Message ID : COM4600F

Label	CEF Label	Type	Usage
url	request	Text	A uniform resource location
filePath	filePath	Text	Full path to file

Description

None

Message ID : COM4604F

Severity

Fatal error

Long Form

Internal error: unable to set attribute {0}.

Short Form

Cannot set attr

Parameters

Label	CEF Label	Type	Usage
showStr	reason	Text	Code specifying reason for allowing access, if any

Message ID : COM4603F

Description

None

Message ID : COM4628F

Severity

Fatal error

Long Form

Unable to connect to a Key Manager. URL: {0}. Please verify that the agent host is registered with a Key Manager.

Short Form

Server connect fail

Parameters

Label	CEF Label	Type	Usage
url	request	Text	A uniform resource location

Description

None

Message ID : COM4604F

Message ID : COM4629F

Severity

Fatal error

Long Form

The server at {0} attempted to contact this machine, but it was denied access due to an invalid certificate.

Short Form

Bad cert from server

Parameters

Label	CEF Label	Type	Usage
url	request	Text	A uniform resource location

Description

None

Message ID : COM4630F

Severity

Fatal error

Long Form

A machine identifying itself as {0} tried to contact the VMD, but there was an error: {1}{2}; "{3}"; Subcode: "{4}"; Reason: "{5}"; Detail: "{6}".

Short Form

SOAP server error

Parameters

Label	CEF Label	Type	Usage
url	request	Text	A uniform resource location
showStr	reason	Text	Code specifying reason for allowing access, if any
ecode	cn1	Numeric	An error code
context	vds_context	Text	Fault context
subcode	vds_subcode	Text	Fault subcode
showStr	reason	Text	Code specifying reason for allowing access, if any
detail	vds_detail	Text	Fault detail

Description

None

Message ID : COM4637F

Severity

Fatal error

Long Form

Failed to bind to port {0}. Please ensure that this port is not in use by another program.

Short Form

SDK bind error

Parameters

Label	CEF Label	Type	Usage
port	spt	Numeric	A socket port number

Description

None

Message ID : COM4630F

Logger COM: Information

Message ID : COM4601I

Severity

Information

Long Form

Successful Agent init with Key Manager ({0}).

Short Form

Comms init OK

Parameters

Label	CEF Label	Type	Usage
url	request	Text	A uniform resource location

Description

None

Message ID : COM4602I

Severity

Information

Long Form

Failed Agent init with Key Manager ({0}).

Short Form

Comms init fail

Parameters

Label	CEF Label	Type	Usage
url	request	Text	A uniform resource location

Description

None

Message ID : COM4626I

Severity

Information

Long Form

The agent failed to initialize with the Key Manager. This may indicate that the connection to the server is down, the agent's host has been deleted from the Key Manager, or "Communication Enabled" for the host has not been enabled in the Key Manager UI.

Short Form

No short form is provided for this message type

Description

None

Message ID : COM4627I

Severity

Information

Long Form

The agent's host may no longer be registered with a Key Manager. The agent's host may have been deleted from the Key Manager. You may want to run the register_host utility to re-register the agent with a Key Manager.

Message ID : COM4626I

Short Form

Agent not registered

Parameters

No parameters are provided for this message type

Description

None

Logger COM: Warnings

Message ID : COM4596W

Severity

Warning

Long Form

{0} Logging discarded due to backlog of {1} MB

Short Form

Backlog high

Parameters

Label	CEF Label	Type	Usage
logger	cs4	Text	Name of originating logger
count	vds_count	Numeric	A generic count value

Description

None

Message ID : COM4597W

Severity

Warning

Long Form

{0} Logging resumed due to reduced backlog

Short Form

Backlog OK

Parameters

Label	CEF Label	Type	Usage
logger	cs4	Text	Name of originating logger

Description

None

Message ID : COM4605W

Severity

Warning

Long Form

Logging destination changed from {0} to {1}

Short Form

Upload dest change

Parameters

Label	CEF Label	Type	Usage
shost	shost	Text	Source host name
url	request	Text	A uniform resource location

Description

None

Message ID : COM4632W

Message ID : COM4605W

Severity

Warning

Long Form

There was a communication failure with the Key Manager. The server returned a fault: {0}{1}; "{2}"; Subcode: "{3}"; Reason: "{4}"; Detail: "{5}".

Short Form

No short form is provided for this message type

Description

None

Message ID : COM4633W

Severity

Warning

Long Form

There was a communication failure with the Key Manager ({0}). The server returned a fault: {1}{2}; "{3}"; Subcode: "{4}"; Reason: "{5}"; Detail: "{6}".

Message ID : COM4632W

Short Form

SOAP client error

Parameters

Label	CEF Label	Type	Usage
url	request	Text	A uniform resource location
showStr	reason	Text	Code specifying reason for allowing access, if any
ecode	cn1	Numeric	An error code
context	vds_context	Text	Fault context
subcode	vds_subcode	Text	Fault subcode
showStr	reason	Text	Code specifying reason for allowing access, if any
detail	vds_detail	Text	Fault detail

Description

The agent is unable to reach the key manager. You may see any of the following error messages: COM4583F, COM4633W, VMD3770F, VMD3885I or VMD3886I. You may experience any of the following:

1. Connection to the key manager is down.
2. The VMD Host has been deleted from the key manager.
3. The host does not have "Communication Enabled" in the key manager UI.
4. The VMD's host may be deleted from the key manager. Run the register_host utility to re-register the VMD with the key manager.

Message ID : COM4634W

Severity

Warning

Long Form

The server at {0} attempted to contact this machine, but it was denied access due to an invalid certificate.

Short Form

Bad cert from server

Parameters

Label	CEF Label	Type	Usage
url	request	Text	A uniform resource location

Description

An attempt to contact the agent was rejected. This may be due to attempting to register an agent with a new key manager after that agent was registered with a different key manager. A COM4635W log message may give more details.

Message ID : COM4635W

Severity

Warning

Long Form

A machine identifying itself as {0} tried to contact the VMD, but there was an error: {1}{2}; "{3}"; Subcode: "{4}"; Reason: "{5}"; Detail: "{6}".

Short Form

SOAP server error

Parameters

Label	CEF Label	Type	Usage
url	request	Text	A uniform resource location
showStr	reason	Text	Code specifying reason for allowing access, if any
ecode	cn1	Numeric	An error code
context	vds_context	Text	Fault context
subcode	vds_subcode	Text	Fault subcode
showStr	reason	Text	Code specifying reason for allowing access, if any
detail	vds_detail	Text	Fault detail

Description

The key manager tried to contact the agent but did not succeed. The "reason" field tells you why the certificate was rejected, and the "detail" field tells you what action was attempted at the time.

Logger DGV: Errors

Message ID : DGV6001E

Severity

Error

Long Form

Memory allocation failed in [{0}] at line [{1}]

Short Form

Out of memory

Parameters

No parameters are provided for this message type

Description

None

Message ID : DGV6002E

Severity

Error

Long Form

Data governance exception with error [{0}] in [{1}] at line [{2}]

Short Form

Exception

Parameters

No parameters are provided for this message type

Description

None

Message ID : DGV6003E

Severity

Error

Message ID : DGV6002E

Long Form

Invalid data governance connector type {0}

Short Form

Invalid connector

Parameters

No parameters are provided for this message type

Description

None

Message ID : DGV6004E

Severity

Error

Long Form

Invalid data governance data source type {0}

Message ID : DGV6003E

Short Form

Invalid data source type

Parameters

No parameters are provided for this message type

Description

None

Message ID : DGV6005E

Severity

Error

Long Form

HTTP request {0} failed with the status code {1} and message {2}

Short Form

HTTP request failed

Parameters

No parameters are provided for this message type

Description

None

Message ID : DGV6006E

Severity

Error

Long Form

UUID creation failed with error {0}

Short Form

UUID creation failed

Parameters

No parameters are provided for this message type

Message ID : DGV6005E

Description

None

Message ID : DGV6007E

Severity

Error

Long Form

Type {0} is not found

Short Form

Type not found

Parameters

No parameters are provided for this message type

Description

None

Message ID : DGV6006E

Message ID : DGV6008E

Severity

Error

Long Form

Attribute {0} value is not found

Short Form

Attribute value not found

Parameters

No parameters are provided for this message type

Description

None

Message ID : DGV6009E

Severity

Error

Message ID : DGV6008E

Long Form

Failed to get attributes for {0} with error {1}

Short Form

Failed to get file attributes

Parameters

No parameters are provided for this message type

Description

None

Message ID : DGV6010E

Severity

Error

Long Form

Failed to create the tag directory {0} with error {1}

Message ID : DGV6009E

Short Form

Failed to create tag directory

Parameters

No parameters are provided for this message type

Description

None

Message ID : DGV6011E

Severity

Error

Long Form

User {0} in domain {1} failed to connect to network path {2}. Error code {3}

Short Form

Net connect error

Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
domain	dntdom	Text	A domain name (policy, network, users, etc)
url	request	Text	A uniform resource location
ecode	cn1	Numeric	An error code

Description

None

Message ID : DGV6012E

Severity

Error

Long Form

AWS request exception {0}. Error message {1}

Short Form

AWS request error

Message ID : DGV6011E

Parameters

No parameters are provided for this message type

Description

None

Message ID : DGV6013E

Severity

Error

Long Form

Failed to add tag {0} to {1}. Error message {2}

Short Form

Failed to add tag

Parameters

No parameters are provided for this message type

Message ID : DGV6012E

Description

None

Message ID : DGV6014E

Severity

Error

Long Form

Failed to delete tag {0} from {1}. Error message {2}

Short Form

Failed to delete tag

Parameters

No parameters are provided for this message type

Description

None

Message ID : DGV6013E

Message ID : DGV6015E

Severity

Error

Long Form

Failed to initialize tag for {0}

Short Form

Failed to initialize tag

Parameters

No parameters are provided for this message type

Description

None

Message ID : DGV6016E

Severity

Error

Message ID : DGV6015E

Long Form

Failed to process tagging event. Error message {0}

Short Form

Failed to process tagging event

Parameters

No parameters are provided for this message type

Description

None

Message ID : DGV6017E

Severity

Error

Long Form

Atlas REST failed with SSL. Error message {0}

Message ID : DGV6016E

Short Form

Atlas REST failed with SSL

Parameters

No parameters are provided for this message type

Description

None

Message ID : DGV6018E

Severity

Error

Long Form

Failed to get uuid for {0}

Short Form

Failed to get uuid

Message ID : DGV6017E

Parameters

No parameters are provided for this message type

Description

None

Message ID : DGV7007E

Severity

Error

Long Form

DDC machine learning exception with error [{0}] in [{1}] at line [{2}]

Short Form

Machine learning exception

Parameters

No parameters are provided for this message type

Message ID : DGV6018E

Description

None

Message ID : DGV7009E

Severity

Error

Long Form

Failed to open {0} with errno {1} for the machine learning request {2}

Short Form

Machine learning open error

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file
ecode	cn1	Numeric	An error code

Message ID : DGV7007E

Description

None

Message ID : DGV7011E

Severity

Error

Long Form

Failed to write {0} with errno {1} for the machine learning request {2}

Short Form

Machine learning write error

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file
ecode	cn1	Numeric	An error code

Message ID : DGV7009E

Description

None

Message ID : DGV7012E

Severity

Error

Long Form

Failed to read {0} with errno {1} for the machine learning request {2}

Short Form

Machine learning read error

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file
ecode	cn1	Numeric	An error code

Message ID : DGV7011E

Description

None

Message ID : DGV7014E

Severity

Error

Long Form

DDC machine learning REST failed with SSL. Error message {0}

Short Form

Machine learning REST failed with SSL

Parameters

No parameters are provided for this message type

Description

None

Message ID : DGV7012E

Message ID : DGV7019E

Severity

Error

Long Form

Failed to download the machine learning model {0} for the request {1}

Short Form

Failed to download machine learning model

Parameters

No parameters are provided for this message type

Description

None

Message ID : DGV7023E

Severity

Error

Message ID : DGV7019E

Long Form

Invalid scan filter {0}

Short Form

Machine learning invalid scan filter

Parameters

No parameters are provided for this message type

Description

None

Message ID : DGV7030E

Severity

Error

Long Form

Failed to create the machine learning model {0} for the request {1}

Message ID : DGV7023E

Short Form

Failed to create machine learning model

Parameters

No parameters are provided for this message type

Description

None

Message ID : DGV7033E

Severity

Error

Long Form

Failed to extract text from {0} for the machine learning request {1}

Short Form

Machine learning failed to extract text

Message ID : DGV7030E

Parameters

No parameters are provided for this message type

Description

None

Message ID : DGV7038E

Severity

Error

Long Form

Failed the method {0} of the machine learning model {1} for the request {2}: batch size {3}, data size {4} bytes, source {5}

Short Form

Failed the machine learning model method

Parameters

No parameters are provided for this message type

Message ID : DGV7033E

Description

None

Message ID : DGV7041E

Severity

Error

Long Form

Skipped the folder {0}({1}) for the data store {2}({3}) for the machine learning request {4}

Short Form

Machine learning skipped the folder

Parameters

No parameters are provided for this message type

Description

None

Message ID : DGV7038E

Message ID : DGV7046E

Severity

Error

Long Form

The checksum does not match for {0} of {1} for the machine learning request {2}

Short Form

Machine learning checksum verification failed

Parameters

No parameters are provided for this message type

Description

None

Message ID : DGV7054E

Severity

Error

Message ID : DGV7046E

Long Form

Failed to send the event: {0}

Short Form

Failed to send the event

Parameters

No parameters are provided for this message type

Description

None

Logger DGV: Information

Message ID : DGV6019I

Severity

Information

Long Form

Starting scan of {0}

Short Form

Starting scan

Parameters

No parameters are provided for this message type

Description

None

Message ID : DGV6020I

Severity

Information

Long Form

Finished scan of {0} in {1} seconds

Short Form

Finished scan

Parameters

No parameters are provided for this message type

Description

None

Message ID : DGV6022I

Severity

Information

Message ID : DGV6020I

Long Form

LDT rekey requested for path [{0}]

Short Form

LDT rekey request

Parameters

No parameters are provided for this message type

Description

None

Message ID : DGV7001I

Severity

Information

Long Form

Starting the machine learning request {0}

Message ID : DGV6022I

Short Form

Starting machine learning

Parameters

No parameters are provided for this message type

Description

None

Message ID : DGV7002I

Severity

Information

Long Form

Canceled the machine learning request {0}

Short Form

Canceled machine learning

Message ID : DGV7001I

Parameters

No parameters are provided for this message type

Description

None

Message ID : DGV7004I

Severity

Information

Long Form

Finished the machine learning request {0}

Short Form

Finished machine learning

Parameters

No parameters are provided for this message type

Message ID : DGV7002I

Description

None

Message ID : DGV7005I

Severity

Information

Long Form

Initializing the machine learning model for the request {0}

Short Form

Initializing machine learning model

Parameters

No parameters are provided for this message type

Description

None

Message ID : DGV7004I

Message ID : DGV7006I

Severity

Information

Long Form

Initialized the machine learning model for the request {0}

Short Form

Initialized machine learning model

Parameters

No parameters are provided for this message type

Description

None

Message ID : DGV7008I

Severity

Information

Message ID : DGV7006I

Long Form

Processed {0} files for the machine learning request {1}

Short Form

Machine learning processed

Parameters

No parameters are provided for this message type

Description

None

Message ID : DGV7010I

Severity

Information

Long Form

Paused the machine learning request {0}

Message ID : DGV7008I

Short Form

Paused machine learning

Parameters

No parameters are provided for this message type

Description

None

Message ID : DGV7013I

Severity

Information

Long Form

Write {0} files to scan list for the machine learning request {1}

Short Form

Machine learning scanned

Message ID : DGV7010I

Parameters

No parameters are provided for this message type

Description

None

Message ID : DGV7016I

Severity

Information

Long Form

Stopped the machine learning request {0}

Short Form

Stopped machine learning

Parameters

No parameters are provided for this message type

Message ID : DGV7013I

Description

None

Message ID : DGV7017I

Severity

Information

Long Form

Downloading the machine learning model {0} for the request {1}

Short Form

Downloading machine learning model

Parameters

No parameters are provided for this message type

Description

None

Message ID : DGV7016I

Message ID : DGV7018I

Severity

Information

Long Form

Downloaded the machine learning model {0} for the request {1}

Short Form

Downloaded machine learning model

Parameters

No parameters are provided for this message type

Description

None

Message ID : DGV7020I

Severity

Information

Message ID : DGV7018I

Long Form

The machine learning library is started on host {0}

Short Form

Machine learning library started

Parameters

No parameters are provided for this message type

Description

None

Message ID : DGV7021I

Severity

Information

Long Form

The machine learning library is stopped on host {0}

Message ID : DGV7020I

Short Form

Machine learning library stopped

Parameters

No parameters are provided for this message type

Description

None

Message ID : DGV7022I

Severity

Information

Long Form

The machine learning library is idle on host {0}

Short Form

Machine learning library idle

Message ID : DGV7021I

Parameters

No parameters are provided for this message type

Description

None

Message ID : DGV7024I

Severity

Information

Long Form

The language {0} of {1} does not match the model {2} for the machine learning request {3}

Short Form

Machine learning model language mismatch

Parameters

No parameters are provided for this message type

Message ID : DGV7022I

Description

None

Message ID : DGV7025I

Severity

Information

Long Form

The file type {0} of {1} does not match the model {2} for the machine learning request {3}

Short Form

Machine learning model file type mismatch

Parameters

No parameters are provided for this message type

Description

None

Message ID : DGV7024I

Message ID : DGV7026I

Severity

Information

Long Form

Downloading {0} of {1} for the machine learning request {2}

Short Form

Downloading machine learning file

Parameters

No parameters are provided for this message type

Description

None

Message ID : DGV7027I

Severity

Information

Message ID : DGV7026I

Long Form

Downloaded {0} of {1} for the machine learning request {2}

Short Form

Downloaded machine learning file

Parameters

No parameters are provided for this message type

Description

None

Message ID : DGV7028I

Severity

Information

Long Form

Creating the machine learning model {0} for the request {1}

Message ID : DGV7027I

Short Form

Creating machine learning model

Parameters

No parameters are provided for this message type

Description

None

Message ID : DGV7029I

Severity

Information

Long Form

Created the machine learning model {0} for the request {1}

Short Form

Created machine learning model

Message ID : DGV7028I

Parameters

No parameters are provided for this message type

Description

None

Message ID : DGV7031I

Severity

Information

Long Form

Extracting text from {0} for the machine learning request {1}

Short Form

Machine learning extracting text

Parameters

No parameters are provided for this message type

Message ID : DGV7029I

Description

None

Message ID : DGV7032I

Severity

Information

Long Form

Extracted text from {0} for the machine learning request {1} in {2} milliseconds

Short Form

Machine learning extracted text

Parameters

No parameters are provided for this message type

Description

None

Message ID : DGV7031I

Message ID : DGV7034I

Severity

Information

Long Form

Generating file list under the folder {0} for the machine learning request {1}

Short Form

Machine learning generating file list

Parameters

No parameters are provided for this message type

Description

None

Message ID : DGV7035I

Severity

Information

Message ID : DGV7034I

Long Form

Generated file list under the folder {0} for the machine learning request {1}

Short Form

Machine learning generated file list

Parameters

No parameters are provided for this message type

Description

None

Message ID : DGV7036I

Severity

Information

Long Form

Calling the method {0} of the machine learning model {1} for the request {2}: batch size {3}, data size {4} bytes, source {5}

Short Form

Calling the machine learning model method

Parameters

No parameters are provided for this message type

Description

None

Message ID : DGV7037I

Severity

Information

Long Form

Finished the method {0} of the machine learning model {1} for the request {2} in {3} milliseconds: batch size {4}, data size {5} bytes, source {6}

Short Form

Called the machine learning model method

Message ID : DGV7036I

Parameters

No parameters are provided for this message type

Description

None

Message ID : DGV7039I

Severity

Information

Long Form

Extracted {0} from {1} for the machine learning request {2}

Short Form

Machine learning extracted archive

Parameters

No parameters are provided for this message type

Message ID : DGV7037I

Description

None

Message ID : DGV7040I

Severity

Information

Long Form

The machine learning agent has processed {0} predictions. Suggest to restart the agent.

Short Form

Machine learning processed predictions

Parameters

No parameters are provided for this message type

Description

None

Message ID : DGV7039I

Message ID : DGV7042I

Severity

Information

Long Form

Resumed the machine learning request {0}

Short Form

Resumed machine learning

Parameters

No parameters are provided for this message type

Description

None

Message ID : DGV7043I

Severity

Information

Message ID : DGV7042I

Long Form

Automatically paused the machine learning request {0}

Short Form

Automatically paused machine learning

Parameters

No parameters are provided for this message type

Description

None

Message ID : DGV7044I

Severity

Information

Long Form

Automatically resumed the machine learning request {0}

Message ID : DGV7043I

Short Form

Automatically resumed machine learning

Parameters

No parameters are provided for this message type

Description

None

Message ID : DGV7045I

Severity

Information

Long Form

The text of {0} is empty for the machine learning request {1}

Short Form

Empty machine learning text

Message ID : DGV7044I

Parameters

No parameters are provided for this message type

Description

None

Message ID : DGV7049I

Severity

Information

Long Form

The machine learning agent certificate has been changed.

Short Form

Machine learning agent certificate changed

Parameters

No parameters are provided for this message type

Message ID : DGV7045I

Description

None

Message ID : DGV7050I

Severity

Information

Long Form

The agent is slowing down because the machine has {0} percent memory available.

Short Form

Available memory

Parameters

No parameters are provided for this message type

Description

None

Message ID : DGV7049I

Message ID : DGV7051I

Severity

Information

Long Form

Skipped {0} for the machine learning request {1} because of the file type {2}.

Short Form

Skipped scan due to the file type

Parameters

No parameters are provided for this message type

Description

None

Message ID : DGV7052I

Severity

Information

Message ID : DGV7051I

Long Form

Generating the embeddings with the machine learning model {0} for the request {1}: entity number {2}, remaining entity number {3}, source {4}

Short Form

Generating entity embeddings

Parameters

No parameters are provided for this message type

Description

None

Message ID : DGV7053I

Severity

Information

Long Form

Generated the embeddings with the machine learning model {0} for the request {1} in {2} milliseconds: entity number {3}, remaining entity number {4}, source {5}

Message ID : DGV7052I

Short Form

Generated entity embeddings

Parameters

No parameters are provided for this message type

Description

None

Logger DGV: Warnings

Message ID : DGV6021W

Severity

Warning

Long Form

Skipping tags [{0}] for file [{1}]

Short Form

Skipping tags

Parameters

No parameters are provided for this message type

Description

None

Message ID : DGV7003W

Severity

Warning

Long Form

Finished the machine learning request {0} with error

Short Form

Finished machine learning with error

Parameters

No parameters are provided for this message type

Description

None

Message ID : DGV7015W

Severity

Warning

Message ID : DGV7003W

Long Form

DDC machine learning does not have value for the configuration {0}

Short Form

Machine learning configuration missing

Parameters

No parameters are provided for this message type

Description

None

Message ID : DGV7047W

Severity

Warning

Long Form

{0} is an embedding model specified in the prediction request {1} without similarity search enabled.

Short Form

Embedding model without similarity search

Parameters

No parameters are provided for this message type

Description

None

Message ID : DGV7048W

Severity

Warning

Long Form

Skipped {0} for the machine learning request {1} because the file has the character set {2}.

Short Form

Skipped scan due to the character set

Message ID : DGV7047W

Parameters

No parameters are provided for this message type

Description

None

Logger DXF: Debug messages

Message ID : DXF4308D

Severity

Debug

Long Form

No files found in directory {0}

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4310D

Severity

Debug

Long Form

Starting data transform of {0}

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4311D

Severity

Debug

Long Form

Finished data transform of {0}

Short Form

No short form is provided for this message type

Message ID : DXF4310D

Description

None

Message ID : DXF4473D

Severity

Debug

Long Form

Process {0}: error {1} opening lock file at {2}. This may be due to an already running data transform instance

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4475D

Severity

Debug

Message ID : DXF4311D

Long Form

Starting scan of {0}

Short Form

No short form is provided for this message type

Description

None

Logger DXF: Errors

Message ID : DXF3205E

Severity

Error

Long Form

The secfs component doesn't support online data transform on "{0}". Please run the data transform utility without --oxf option to transform the data offline.

Short Form

No online Xform support.

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	GuardPoint base directory

Description

None

Message ID : DXF3206E

Severity

Error

Long Form

Deep Scan operation is not supported with online data transformation. Please run deep scan without --oxf option.

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF3207E

Severity

Error

Long Form

Cannot open or create current status file {0} : {1}

Short Form

No current status file

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file
showStr	reason	Text	Code specifying reason for allowing access, if any

Description

None

Message ID : DXF3208E

Severity

Error

Long Form

Cannot write current status file {0} : {1}

Message ID : DXF3207E

Short Form

current status file write error

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file
showStr	reason	Text	Code specifying reason for allowing access, if any

Description

None

Message ID : DXF3209E

Severity

Error

Long Form

Invalid data in current status file {0}

Message ID : DXF3208E

Short Form

Bad current status file content

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : DXF3215E

Severity

Error

Long Form

File "{0}" Invalid xf mode.

Short Form

Invalid xf mode.

Message ID : DXF3209E

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : DXF3216E

Severity

Error

Long Form

File "{0}" vmfs get file system failed.

Short Form

vmfs get file system failed.

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Message ID : DXF3215E

Description

None

Message ID : DXF3217E

Severity

Error

Long Form

File "{0}" start self access failed.

Short Form

start self access failed.

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : DXF3216E

Message ID : DXF3218E

Severity

Error

Long Form

File "{0}" File handle is invalid.

Short Form

File handle is invalid.

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : DXF3219E

Severity

Error

Long Form

File "{0}" failed to get the inode.

Short Form

inode failure

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : DXF3220E

Severity

Error

Message ID : DXF3219E

Long Form

File "{0}" failed to get the GuardPoint MD.

Short Form

failed to get the GuardPoint MD.

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : DXF3221E

Severity

Error

Long Form

File "{0}" failed to get the inode INF information.

Message ID : DXF3220E

Short Form

inode INF failure

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : DXF3222E

Severity

Error

Long Form

File "{0}" Inode is null.

Short Form

Inode is null.

Message ID : DXF3221E

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : DXF3223E

Severity

Error

Long Form

File "{0}" failed to get the file name.

Short Form

inode name failure.

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Message ID : DXF3222E

Description

None

Message ID : DXF3224E

Severity

Error

Long Form

File "{0}" validation of MD failed.

Short Form

validation of MD failed.

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : DXF3223E

Message ID : DXF3225E

Severity

Error

Long Form

File "{0}" file MD is null.

Short Form

file MD is null.

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : DXF3226E

Severity

Error

Long Form

File "{0}" File MD is in the error state.

Short Form

File MD is in the error state.

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : DXF3227E

Severity

Error

Message ID : DXF3226E

Long Form

File "{0}" Access check failed. Please check your policy.

Short Form

Access check failed. Please check your policy.

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : DXF3228E

Severity

Error

Long Form

File "{0}" failed while quering the MD from the stream file.

Message ID : DXF3227E

Short Form

failed while quering the MD from the stream file.

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : DXF3229E

Severity

Error

Long Form

File "{0}" Invalid GP meta data.

Short Form

Invalid GP meta data.

Message ID : DXF3228E

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : DXF3230E

Severity

Error

Long Form

File "{0}" failed to get the GuardPoint file system.

Short Form

failed to get the GuardPoint file system.

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Message ID : DXF3229E

Description

None

Message ID : DXF3231E

Severity

Error

Long Form

File "{0}" GuardPoint MD is null.

Short Form

GuardPoint MD is null.

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : DXF3230E

Message ID : DXF3232E

Severity

Error

Long Form

File "{0}" Rekey failed.

Short Form

Rekey failed.

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : DXF3233E

Severity

Error

Long Form

File "{0}" Opening the file handle failed.

Short Form

Opening the file handle failed.

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : DXF3238E

Severity

Error

Message ID : DXF3233E

Long Form

LDT-ALERT: Scan error on [{0}] removing MDS guard for relaunching dataxform.

Short Form

LDT scan error

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	GuardPoint base directory

Description

None

Message ID : DXF3239E

Severity

Error

Long Form

LDT-ALERT: Online Dataxfrom failed during post scan stage on [{0}]

Message ID : DXF3238E

Short Form

LDT postscan failure

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	GuardPoint base directory

Description

None

Message ID : DXF3240E

Severity

Error

Long Form

Failed to initialize the context for container {0}.

Short Form

failed to initialize container

Message ID : DXF3239E

Parameters

Label	Type	Usage
dockerid	Text	Docker image or container id

Description

None

Message ID : DXF3241E

Severity

Error

Long Form

The container {0} is not running.

Short Form

container not running

Parameters

Label	Type	Usage
dockerid	Text	Docker image or container id

Message ID : DXF3240E

Description

None

Message ID : DXF3242E

Severity

Error

Long Form

Verify this is a guard point with valid data transformation policy, and check the system log files for any other problems. It may be due to one or more of following reasons; 1.policy has no valid key rule(s), and/or 2. policy has no key_op rule, and/or 3. policy has valid permit rule(s), and/or 4. policy rule that contains key_op in the action field also specifies other actions, and/or 5. verify that user has not enabled Header Style guardpoint as Offline transformation does not support header based guardpoints 6. Verify if guarding CIFS share with standard policy (new CBC-CS1 Key) for vmfiltr.

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF3241E

Message ID : DXF3243E

Severity

Error

Long Form

The file {0} has an invalid header; skipping

Short Form

Skipping invalid header

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : DXF3244E

Severity

Error

Long Form

The file {0} was skipped. It has an invalid header

Short Form

Skipped - invalid header

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : DXF3245E

Severity

Error

Message ID : DXF3244E

Long Form

The file {0} was previously skipped. It has an invalid header

Short Form

Prev skipped - invalid header

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : DXF3246E

Severity

Error

Long Form

Number of files skipped due to an invalid header: {0}

Message ID : DXF3245E

Short Form

Files with invalid header

Parameters

Label	CEF Label	Type	Usage
count	vds_count	Numeric	A generic count value

Description

None

Message ID : DXF3247E

Severity

Error

Long Form

Number of files previously skipped due to an invalid header: {0}

Short Form

Prev files with invalid header

Message ID : DXF3246E

Parameters

Label	CEF Label	Type	Usage
count	vds_count	Numeric	A generic count value

Description

None

Message ID : DXF3248E

Severity

Error

Long Form

The file {0} is encrypted with a wrong key; skipping

Short Form

Skipping wrong key

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Message ID : DXF3247E

Description

None

Message ID : DXF3249E

Severity

Error

Long Form

The file {0} was skipped. It is encrypted with a wrong key

Short Form

Skipped - wrong key

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : DXF3248E

Message ID : DXF3250E

Severity

Error

Long Form

The file {0} was previously skipped. It is encrypted with a wrong key

Short Form

Prev skipped - wrong key

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : DXF3251E

Severity

Error

Long Form

Number of files skipped due to a wrong key: {0}

Short Form

Files with wrong key

Parameters

Label	CEF Label	Type	Usage
count	vds_count	Numeric	A generic count value

Description

None

Message ID : DXF3252E

Severity

Error

Message ID : DXF3251E

Long Form

Number of files previously skipped due to a wrong key: {0}

Short Form

Prev files with wrong key

Parameters

Label	CEF Label	Type	Usage
count	vds_count	Numeric	A generic count value

Description

None

Message ID : DXF4100E

Severity

Error

Long Form

. --deep_scan Perform scan as above with additional file

Message ID : DXF3252E

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4101E

Severity

Error

Long Form

. access checks, and estimate time required to

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4100E

Message ID : DXF4102E

Severity

Error

Long Form

. complete data transformation of guard point

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4105E

Severity

Error

Long Form

Number of files previously in error for an unknown reason: {0}

Short Form

Prev unknown file errors

Parameters

Label	CEF Label	Type	Usage
count	vds_count	Numeric	A generic count value

Description

None

Message ID : DXF4106E

Severity

Error

Long Form

Number of files in error for an unknown reason: {0}

Short Form

Unknown file errors

Message ID : DXF4105E

Parameters

Label	CEF Label	Type	Usage
count	vds_count	Numeric	A generic count value

Description

None

Message ID : DXF4107E

Severity

Error

Long Form

The file {0} was previously in error for an unknown reason

Short Form

Prev error - unknown

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Message ID : DXF4106E

Description

None

Message ID : DXF4108E

Severity

Error

Long Form

The file {0} was in error for an unknown reason

Short Form

Prev xform file in error

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : DXF4107E

Message ID : DXF4109E

Severity

Error

Long Form

Error "{0}" opening lock file in {1}

Short Form

Lock file error

Parameters

Label	CEF Label	Type	Usage
showStr	reason	Text	Code specifying reason for allowing access, if any
filePath	filePath	Text	Full path to file

Description

None

Message ID : DXF4111E

Severity

Error

Long Form

Process {0}: error "{1}" opening lock file at {2}. This may be due to an already running data transform instance

Short Form

Lock file open error

Parameters

Label	CEF Label	Type	Usage
ecode	cn1	Numeric	An error code
showStr	reason	Text	Code specifying reason for allowing access, if any
filePath	filePath	Text	Full path to file

Description

None

Message ID : DXF4112E

Severity

Error

Long Form

Error "{0}" creating lock file in {1}

Short Form

Lock file create fail

Parameters

Label	CEF Label	Type	Usage
showStr	reason	Text	Code specifying reason for allowing access, if any
filePath	filePath	Text	Full path to file

Description

None

Message ID : DXF4113E

Severity

Error

Long Form

Cannot create the data transform recovery/status file {0}, {1}

Short Form

Status file create error

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file
showStr	reason	Text	Code specifying reason for allowing access, if any

Description

None

Message ID : DXF4114E

Severity

Error

Long Form

Error "{0}" getting file info for {1}

Short Form

Stat fail

Parameters

Label	CEF Label	Type	Usage
showStr	reason	Text	Code specifying reason for allowing access, if any
filePath	filePath	Text	Full path to file

Description

None

Message ID : DXF4115E

Severity

Error

Long Form

Error "{0}" getting file attributes for {1}

Short Form

Attr fail

Parameters

Label	CEF Label	Type	Usage
showStr	reason	Text	Code specifying reason for allowing access, if any
filePath	filePath	Text	Full path to file

Description

None

Message ID : DXF4116E

Severity

Error

Long Form

Error "{0}" setting file attributes for {1}

Short Form

Attr set error

Parameters

Label	CEF Label	Type	Usage
showStr	reason	Text	Code specifying reason for allowing access, if any
filePath	filePath	Text	Full path to file

Description

None

Message ID : DXF4117E

Severity

Error

Long Form

Cannot find files in {0}, {1}

Short Form

File first error

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file
showStr	reason	Text	Code specifying reason for allowing access, if any

Description

None

Message ID : DXF4119E

Severity

Error

Long Form

Error "{0}" setting file time for {1}

Short Form

Time set error

Parameters

Label	CEF Label	Type	Usage
showStr	reason	Text	Code specifying reason for allowing access, if any
filePath	filePath	Text	Full path to file

Description

None

Message ID : DXF4120E

Severity

Error

Long Form

Cannot recover previous session as file list is missing

Short Form

Missing file list

Parameters

No parameters are provided for this message type

Description

None

Message ID : DXF4121E

Severity

Error

Message ID : DXF4120E

Long Form

Cannot perform data transform for {0}, not a directory

Short Form

Not a dir

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	GuardPoint base directory

Description

None

Message ID : DXF4124E

Severity

Error

Long Form

The file {0} was skipped. There was insufficient memory to process it

Message ID : DXF4121E

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4125E

Severity

Error

Long Form

The file {0} was previously skipped. There was insufficient memory to process it

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4124E

Message ID : DXF4133E

Severity

Error

Long Form

The file {0} was in error. dataxform had insufficient permission

Short Form

Bad perms

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : DXF4134E

Severity

Error

Long Form

The file {0} was previously in error. dataxform had insufficient permission

Short Form

Prev error bad perms

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : DXF4135E

Severity

Error

Message ID : DXF4134E

Long Form

Number of files in error due to insufficient permission: {0}

Short Form

Perm errors

Parameters

Label	CEF Label	Type	Usage
count	vds_count	Numeric	A generic count value

Description

None

Message ID : DXF4136E

Severity

Error

Long Form

Number of files previously in error due to insufficient permission: {0}

Message ID : DXF4135E

Short Form

Prev perm errors

Parameters

Label	CEF Label	Type	Usage
count	vds_count	Numeric	A generic count value

Description

None

Message ID : DXF4137E

Severity

Error

Long Form

The file {0} was in error. There was insufficient memory to process it

Short Form

Out of memory

Message ID : DXF4136E

Parameters

No parameters are provided for this message type

Description

None

Message ID : DXF4138E

Severity

Error

Long Form

The file {0} was previously in error. There was insufficient memory to process it

Short Form

Prev error - no memory

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Message ID : DXF4137E

Description

None

Message ID : DXF4139E

Severity

Error

Long Form

Number of files in error due to insufficient memory: {0}

Short Form

No-memory files skipped

Parameters

Label	CEF Label	Type	Usage
count	vds_count	Numeric	A generic count value

Description

None

Message ID : DXF4138E

Message ID : DXF4140E

Severity

Error

Long Form

Number of files previously in error due to insufficient memory: {0}

Short Form

Prev no-memory files skipped

Parameters

Label	CEF Label	Type	Usage
count	vds_count	Numeric	A generic count value

Description

None

Message ID : DXF4141E

Severity

Error

Long Form

Directory path too long: {0}

Short Form

Dir too long

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : DXF4142E

Severity

Error

Message ID : DXF4141E

Long Form

Unable to process directory {0}

Short Form

Dir in error

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : DXF4149E

Severity

Error

Long Form

. --preserve_sparse_files Don't encrypt file holes. Not the default

Message ID : DXF4142E

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4150E

Severity

Error

Long Form

Removal of data transformation status files completed

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4149E

Message ID : DXF4151E

Severity

Error

Long Form

Removal of data transformation status files abandoned

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4152E

Severity

Error

Long Form

Cleanup-on-success option is only valid with rekey operations

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4153E

Severity

Error

Long Form

. --cleanup_on_success Remove status files upon success

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4152E

Message ID : DXF4155E

Severity

Error

Long Form

The rekey list file provided contains an invalid entry "{0}". Please remove or correct the entry then try again.

Short Form

Invalid rekey file list entry

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : DXF4156E

Severity

Error

Long Form

. --unrecoverable Perform rekey without recording recovery data,

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4157E

Severity

Error

Long Form

. which may run considerably faster than a normal

Message ID : DXF4156E

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4158E

Severity

Error

Long Form

. rekey, but if it fails restoration of the guarded

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4157E

Message ID : DXF4159E

Severity

Error

Long Form

. data from backup will be required.

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4160E

Severity

Error

Long Form

Cannot continue a previous recoverable run with the "--unrecoverable" option set

Short Form

Prev op was recoverable rekey

Parameters

No parameters are provided for this message type

Description

None

Message ID : DXF4162E

Severity

Error

Long Form

Cannot perform data transform for {0}, failed to get HDFS file name

Short Form

Failed to get HDFS file name

Message ID : DXF4160E

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : DXF4163E

Severity

Error

Long Form

The file {0} was previously in error. Failed to get HDFS file name

Short Form

Prev error - failed to get HDFS file name

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Message ID : DXF4162E

Description

None

Message ID : DXF4164E

Severity

Error

Long Form

Number of files in error due to failure getting HDFS file name: {0}

Short Form

HDFS file name errors

Parameters

Label	CEF Label	Type	Usage
count	vds_count	Numeric	A generic count value

Description

None

Message ID : DXF4163E

Message ID : DXF4165E

Severity

Error

Long Form

Number of files previously in error due to failure getting HDFS file name: {0}

Short Form

Prev HDFS file name errors

Parameters

Label	CEF Label	Type	Usage
count	vds_count	Numeric	A generic count value

Description

None

Message ID : DXF4166E

Severity

Error

Long Form

The file {0} was in error. There was insufficient disk space to process it

Short Form

Out of disk space

Parameters

No parameters are provided for this message type

Description

None

Message ID : DXF4167E

Severity

Error

Message ID : DXF4166E

Long Form

. --cid Specify Docker container id.

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4168E

Severity

Error

Long Form

. --migrate Migrate Data from Protect File Encryption.

Short Form

No short form is provided for this message type

Message ID : DXF4167E

Description

None

Message ID : DXF4169E

Severity

Error

Long Form

. --embed Convert all the files to CTE-U embedded header.

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4170E

Severity

Error

Message ID : DXF4168E

Long Form

. --update_keyid Update to new keyid after a key migration.

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4171E

Severity

Error

Long Form

. --console_level Change the logging level to the console.

Short Form

No short form is provided for this message type

Message ID : DXF4170E

Description

None

Message ID : DXF4172E

Severity

Error

Long Form

. Range: [ALL, TRACE, DEBUG, INFO, WARN, ERROR, OFF] Default: ERROR

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4173E

Severity

Error

Message ID : DXF4171E

Long Form

. --applog_level Override the logging level for the dataxform logs.

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4174E

Severity

Error

Long Form

. Range: [ALL, TRACE, DEBUG, INFO, WARN, ERROR, OFF] Default: VMD setting

Short Form

No short form is provided for this message type

Message ID : DXF4173E

Description

None

Message ID : DXF4215E

Severity

Error

Long Form

The file {0} was in error. It was open and could not be modified safely

Short Form

Error open file

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : DXF4174E

Message ID : DXF4227E

Severity

Error

Long Form

The options --preserve_sparse_files and --encrypt_sparse_file_holes are mutually exclusive

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4228E

Severity

Error

Long Form

. --preserve_sparse_files Don't encrypt file holes. Default behavior

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4229E

Severity

Error

Long Form

. --encrypt_sparse_file_holes The opposite of --preserve_sparse_files

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4228E

Message ID : DXF4230E

Severity

Error

Long Form

. This option has the potential to increase

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4231E

Severity

Error

Long Form

. the amount of space files take up on disk

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4232E

Severity

Error

Long Form

. --buf_size Performance tuning: The size, in KB, of the

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4231E

Message ID : DXF4233E

Severity

Error

Long Form

. buffer used for transforming data

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4234E

Severity

Error

Long Form

. Range: [4..128]. Default: 128

Message ID : DXF4233E

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4235E

Severity

Error

Long Form

. --mt Performance tuning: The max. number of

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4234E

Message ID : DXF4236E

Severity

Error

Long Form

. threads that the secfs can use per file

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4237E

Severity

Error

Long Form

. Range: [1..16]. Default: 16

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4238E

Severity

Error

Long Form

. --thd Performance tuning: The max. number of

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4237E

Message ID : DXF4239E

Severity

Error

Long Form

. files to transform at once

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4240E

Severity

Error

Long Form

. Range: [1..32]. Defaults: unix:28 win:8

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4241E

Severity

Error

Long Form

More than {0} files were encountered in the directory {1}. This will consume excessive system resources. Aborting. No files have been transformed. To disable this check, rerun with the "--disable_memory_checking" flag

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4240E

Message ID : DXF4243E

Severity

Error

Long Form

. --status_interval The frequency, in seconds, of how often to

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4244E

Severity

Error

Long Form

. report status to the logs. Default: 300

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4247E

Severity

Error

Long Form

Cannot open or create directory listing file {0} : {1}

Short Form

No dir file

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file
showStr	reason	Text	Code specifying reason for allowing access, if any

Message ID : DXF4244E

Description

None

Message ID : DXF4248E

Severity

Error

Long Form

Cannot re-use invalid directory listing file {0}

Short Form

Bad dir file

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : DXF4247E

Message ID : DXF4249E

Severity

Error

Long Form

Failed to cleanly close directory listing file {0} : {1}

Short Form

Close dir file error

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file
showStr	reason	Text	Code specifying reason for allowing access, if any

Description

None

Message ID : DXF4250E

Severity

Error

Long Form

Cannot rename directory listing file from {0} to {1} :{2}

Short Form

Rename dir file error

Parameters

Label	CEF Label	Type	Usage
oldFilePath	oldFilePath	Text	Previous path to file (for rename and link)
filePath	filePath	Text	Full path to file
showStr	reason	Text	Code specifying reason for allowing access, if any

Description

None

Message ID : DXF4251E

Severity

Error

Long Form

Invalid data in listing file {0}

Short Form

Bad dir file content

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : DXF4252E

Severity

Error

Long Form

Cannot write directory listing file {0} : {1}

Short Form

Dir file write error

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file
showStr	reason	Text	Code specifying reason for allowing access, if any

Description

None

Message ID : DXF4255E

Message ID : DXF4252E

Severity

Error

Long Form

Inconsistent data in recovery files {0} and {1}.

Short Form

Inconsistent recovery files

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file
filePath	filePath	Text	Full path to file

Description

None

Message ID : DXF4266E

Message ID : DXF4255E

Severity

Error

Long Form

Error "{0}" updating status file {1}

Short Form

File update error

Parameters

Label	CEF Label	Type	Usage
showStr	reason	Text	Code specifying reason for allowing access, if any
filePath	filePath	Text	Full path to file

Description

None

Message ID : DXF4270E

Severity

Error

Long Form

Number of files in error due to secfs component stopping data transform: {0}

Short Form

Secfs stop files errors

Parameters

Label	CEF Label	Type	Usage
count	vds_count	Numeric	A generic count value

Description

None

Message ID : DXF4271E

Severity

Error

Message ID : DXF4270E

Long Form

Number of files in error due to a signal stopping the dataxform: {0}

Short Form

Signal stop files errors

Parameters

Label	CEF Label	Type	Usage
count	vds_count	Numeric	A generic count value

Description

None

Message ID : DXF4272E

Severity

Error

Long Form

Number of files in error due to being open and could not be modified safely: {0}

Message ID : DXF4271E

Short Form

Unsafe file errors

Parameters

Label	CEF Label	Type	Usage
count	vds_count	Numeric	A generic count value

Description

None

Message ID : DXF4282E

Severity

Error

Long Form

Error "{0}" reading directory entry {1}

Short Form

Read dir error

Message ID : DXF4272E

Parameters

Label	CEF Label	Type	Usage
showStr	reason	Text	Code specifying reason for allowing access, if any
filePath	filePath	Text	Full path to file

Description

None

Message ID : DXF4286E

Severity

Error

Long Form

Number of files previously in error due to secfs component stopping data transform: {0}

Short Form

Prev secfs stop files errors

Message ID : DXF4282E

Parameters

Label	CEF Label	Type	Usage
count	vds_count	Numeric	A generic count value

Description

None

Message ID : DXF4287E

Severity

Error

Long Form

Number of files previously in error due to a signal stopping the dataxform: {0}

Short Form

Prev signal stop files errors

Parameters

Label	CEF Label	Type	Usage
count	vds_count	Numeric	A generic count value

Message ID : DXF4286E

Description

None

Message ID : DXF4288E

Severity

Error

Long Form

Number of files previously in error due to being open and could not be modified safely: {0}

Short Form

Prev unsafe file errors

Parameters

Label	CEF Label	Type	Usage
count	vds_count	Numeric	A generic count value

Description

None

Message ID : DXF4287E

Message ID : DXF4289E

Severity

Error

Long Form

Unable to read {0}: {1}

Short Form

Read info error

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file
showStr	reason	Text	Code specifying reason for allowing access, if any

Description

None

Message ID : DXF4290E

Severity

Error

Long Form

Unable to create simulation file {0}: {1}

Short Form

Create sim file error

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file
showStr	reason	Text	Code specifying reason for allowing access, if any

Description

None

Message ID : DXF4291E

Severity

Error

Long Form

Error creating directory {0}: {1}

Short Form

Create sim dir error

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file
showStr	reason	Text	Code specifying reason for allowing access, if any

Description

None

Message ID : DXF4292E

Severity

Error

Long Form

Error removing directory {0}: {1}

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4294E

Severity

Error

Long Form

About to perform a deep scan

Message ID : DXF4292E

Short Form

Deep scan start

Parameters

No parameters are provided for this message type

Description

None

Message ID : DXF4295E

Severity

Error

Long Form

-- To enable consistent results, do not access the directory during the scan

Short Form

No short form is provided for this message type

Message ID : DXF4294E

Description

None

Message ID : DXF4296E

Severity

Error

Long Form

-- Transformation simulations will be performed, which may take some time

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4297E

Severity

Error

Message ID : DXF4295E

Long Form

Filesystem containing {0} is too full to perform simulations

Short Form

FS too full for sim

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : DXF4298E

Severity

Error

Long Form

Filesystem containing {0} is too full to create file lists

Message ID : DXF4297E

Short Form

FS too full

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : DXF4299E

Severity

Error

Long Form

Verify this is a guard point with valid data transformation policy, and check the system log files for any other problems. It may be due to one or more of following reasons; 1.policy has no valid key rule(s), and/or 2. policy has no key_op rule, and/or 3. policy has valid permit rule(s), and/or 4. policy rule that contains key_op in the action field also specifies other actions.

Message ID : DXF4298E

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4300E

Severity

Error

Long Form

Out of Memory

Short Form

Out of memory

Parameters

No parameters are provided for this message type

Message ID : DXF4299E

Description

None

Message ID : DXF4301E

Severity

Error

Long Form

The secfs component doesn't support data transform on {0}

Short Form

No xform support

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	GuardPoint base directory

Description

None

Message ID : DXF4300E

Message ID : DXF4302E

Severity

Error

Long Form

Error {0} opening configuration file in {1}

Short Form

Config file error

Parameters

Label	CEF Label	Type	Usage
ecode	cn1	Numeric	An error code
filePath	filePath	Text	Full path to file

Description

None

Message ID : DXF4303E

Severity

Error

Long Form

Error {0} opening lock file in {1}

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4304E

Severity

Error

Long Form

Error {0} creating lock file in {1}

Message ID : DXF4303E

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4306E

Severity

Error

Long Form

Error invalid version {0} for configuration file in {1}

Short Form

Bad config version

Parameters

Label	CEF Label	Type	Usage
verno	vds_verno	Numeric	A version number
filePath	filePath	Text	Full path to file

Message ID : DXF4304E

Description

None

Message ID : DXF4312E

Severity

Error

Long Form

A file or directory in {0} may be corrupt or unreachable

Short Form

File inaccessible

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : DXF4306E

Message ID : DXF4313E

Severity

Error

Long Form

There was an invalid parameter while processing directory {0}

Short Form

Invalid dir param

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : DXF4314E

Severity

Error

Long Form

Out of memory while processing directory {0}

Short Form

Out of memory processing dir

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : DXF4315E

Severity

Error

Message ID : DXF4314E

Long Form

Error code {0} while processing directory {1}

Short Form

Dir processing error

Parameters

Label	CEF Label	Type	Usage
ecode	cn1	Numeric	An error code
filePath	filePath	Text	Full path to file

Description

None

Message ID : DXF4325E

Severity

Error

Message ID : DXF4315E

Long Form

Cannot perform data transform for {0}, does not exist

Short Form

Does not exist

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	GuardPoint base directory

Description

None

Message ID : DXF4326E

Severity

Error

Long Form

Cannot perform data transform for {0}, access denied

Message ID : DXF4325E

Short Form

Access denied

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	GuardPoint base directory

Description

None

Message ID : DXF4328E

Severity

Error

Long Form

Secfs component gave unexpected status {0}

Short Form

Unexpected Secfs error

Message ID : DXF4326E

Parameters

Label	CEF Label	Type	Usage
ecode	cn1	Numeric	An error code

Description

None

Message ID : DXF4330E

Severity

Error

Long Form

No file name provided to hold recovery file list

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4328E

Message ID : DXF4331E

Severity

Error

Long Form

Cannot open {0} to get recovery file list

Short Form

List access fail

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : DXF4334E

Severity

Error

Long Form

No value provided for command line parameter {0}

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4335E

Severity

Error

Long Form

Unknown command line option {0}

Message ID : DXF4334E

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4336E

Severity

Error

Long Form

Command line must specify an operation

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4335E

Message ID : DXF4340E

Severity

Error

Long Form

Command line must specify a guard point

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4341E

Severity

Error

Long Form

Directory specified on command line does not exist, {0}

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4342E

Severity

Error

Long Form

Only one command line operation is allowed if scan is selected

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4341E

Message ID : DXF4343E

Severity

Error

Long Form

Attempt to normalize directory {0} got error code {1}

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4346E

Severity

Error

Long Form

The command line is not valid

Message ID : DXF4343E

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4347E

Severity

Error

Long Form

Unable to create the progress-reporting thread

Short Form

Thread create fail

Parameters

No parameters are provided for this message type

Message ID : DXF4346E

Description

None

Message ID : DXF4349E

Severity

Error

Long Form

Cannot set up data transform recovery/status files

Short Form

Status file setup fail

Parameters

No parameters are provided for this message type

Description

None

Message ID : DXF4347E

Message ID : DXF4350E

Severity

Error

Long Form

Cannot delete data transform status and lock files

Short Form

Status/lock file delete fail

Parameters

No parameters are provided for this message type

Description

None

Message ID : DXF4353E

Severity

Error

Long Form

Check the recovery files for errors, or run "--cleanup" option to remove them.

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4354E

Severity

Error

Long Form

Make sure any files already transformed are restored before a cleanup is done.

Short Form

No short form is provided for this message type

Message ID : DXF4353E

Description

None

Message ID : DXF4355E

Severity

Error

Long Form

As the previous dataxform run used the "--unrecoverable" option, you need to restore the GuardPoint from a backup, then use the "--cleanup" option before running the rekey operation again.

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4356E

Severity

Error

Long Form

Could not notify secfs component about data transform on {0}

Short Form

Secfs notify fail

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	GuardPoint base directory

Description

None

Message ID : DXF4357E

Severity

Error

Message ID : DXF4356E

Long Form

Could not restrict access to {0}

Short Form

Access restrict fail

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	GuardPoint base directory

Description

None

Message ID : DXF4358E

Severity

Error

Long Form

Could not allow access to {0}

Message ID : DXF4357E

Short Form

Access allow fail

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	GuardPoint base directory

Description

None

Message ID : DXF4360E

Severity

Error

Long Form

Could not complete data transform, the policy for guard point {0} changed

Short Form

Policy changed

Message ID : DXF4358E

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	GuardPoint base directory

Description

None

Message ID : DXF4367E

Severity

Error

Long Form

Data transform got errors on some files

Short Form

Prev xform fail

Parameters

No parameters are provided for this message type

Message ID : DXF4360E

Description

None

Message ID : DXF4368E

Severity

Error

Long Form

The file {0} could not be transformed in the previous data transform, it will not be transformed

Short Form

Prev file xform fail

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : DXF4367E

Message ID : DXF4376E

Severity

Error

Long Form

Data transform in guard point {0} failed for {1} files

Short Form

Prev xform failures

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	GuardPoint base directory
nfile	vds_nfile	Numeric	The number of files processed

Description

None

Message ID : DXF4377E

Severity

Error

Long Form

Error while scanning for hard links in directory {0}

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4379E

Severity

Error

Long Form

Error scanning guard point {0} while processing directory {1}

Short Form

Scan error

Parameters

Label	CEF Label	Type	Usage
showStr	reason	Text	Code specifying reason for allowing access, if any
filePath	filePath	Text	Full path to file

Description

None

Message ID : DXF4381E

Severity

Error

Long Form

Error scanning guard point {0}

Message ID : DXF4379E

Short Form

Scan fail

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	GuardPoint base directory

Description

None

Message ID : DXF4382E

Severity

Error

Long Form

Automatic data transform cannot be performed on {0}

Short Form

No xform support

Message ID : DXF4381E

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	GuardPoint base directory

Description

None

Message ID : DXF4391E

Severity

Error

Long Form

Data transform of files listed in {0} for guard point {1} failed

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4382E

Message ID : DXF4392E

Severity

Error

Long Form

Error {0} opening configuration file in {1}: does not exist

Short Form

Cfg file error

Parameters

Label	CEF Label	Type	Usage
ecode	cn1	Numeric	An error code
filePath	filePath	Text	Full path to file

Description

None

Message ID : DXF4393E

Severity

Error

Long Form

Error {0} opening lock file in {1}: does not exist

Short Form

Lock file error

Parameters

Label	CEF Label	Type	Usage
ecode	cn1	Numeric	An error code
filePath	filePath	Text	Full path to file

Description

None

Message ID : DXF4394E

Severity

Error

Long Form

Error {0} creating lock file in {1}: does not exist

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4395E

Severity

Error

Long Form

Error {0} getting file info for {1}

Message ID : DXF4394E

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4396E

Severity

Error

Long Form

Error {0} getting file attributes for {1}

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4395E

Message ID : DXF4400E

Severity

Error

Long Form

Error trying to create a worker thread

Short Form

Threadcreate fail

Parameters

No parameters are provided for this message type

Description

None

Message ID : DXF4401E

Severity

Error

Message ID : DXF4400E

Long Form

Error {0} ({1}) trying to delete file {2}

Short Form

Delete file error

Parameters

Label	CEF Label	Type	Usage
ecode	cn1	Numeric	An error code
showStr	reason	Text	Code specifying reason for allowing access, if any
filePath	filePath	Text	Full path to file

Description

None

Message ID : DXF4403E

Severity

Error

Message ID : DXF4401E

Long Form

No path provided for recovery information file

Short Form

Missing recovery info

Parameters

No parameters are provided for this message type

Description

None

Message ID : DXF4404E

Severity

Error

Long Form

Error {0} setting file attributes for {1}

Message ID : DXF4403E

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4405E

Severity

Error

Long Form

Error {0} setting file time for {1}

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4404E

Message ID : DXF4407E

Severity

Error

Long Form

Could not determine the Windows installation directory

Short Form

Cannot determine install dir

Parameters

No parameters are provided for this message type

Description

None

Message ID : DXF4408E

Severity

Error

Message ID : DXF4407E

Long Form

Internal error: thread index {0} is not valid

Short Form

Bad thread id

Parameters

No parameters are provided for this message type

Description

None

Message ID : DXF4409E

Severity

Error

Long Form

Cannot find files in {0}, error {1}

Message ID : DXF4408E

Short Form

Find first error

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file
ecode	cn1	Numeric	An error code

Description

None

Message ID : DXF4427E

Severity

Error

Long Form

Failed to authorize this program with the secfs

Message ID : DXF4409E

Short Form

Cannot protect PID

Parameters

No parameters are provided for this message type

Description

None

Message ID : DXF4430E

Severity

Error

Long Form

The data transformation process was denied permission to access the directory {0}

Short Form

Dir access denied

Message ID : DXF4427E

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : DXF4432E

Severity

Error

Long Form

Build version: {0}

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4430E

Message ID : DXF4433E

Severity

Error

Long Form

Build ID: {0}

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4434E

Severity

Error

Long Form

Build Date: {0}

Message ID : DXF4433E

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4435E

Severity

Error

Long Form

About to perform the requested data transform operation

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4434E

Message ID : DXF4436E

Severity

Error

Long Form

-- Be sure to back up your data

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4437E

Severity

Error

Long Form

-- Please do not access files in the guard point during the transform process

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4438E

Severity

Error

Long Form

-- Please do not attempt to terminate the application

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4437E

Message ID : DXF4439E

Severity

Error

Long Form

Do you wish to continue (y/n)?

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4440E

Severity

Error

Long Form

.Usage:

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4441E

Severity

Error

Long Form

. dataxform {operation} {operation options}

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4440E

Message ID : DXF4442E

Severity

Error

Long Form

. where {operation} is the desired operation

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4443E

Severity

Error

Long Form

. --rekey Rekey the files in guard point

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4444E

Severity

Error

Long Form

. --rekey_supported Report if rekey is supported on guard point

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4443E

Message ID : DXF4445E

Severity

Error

Long Form

. --scan Display number of files and directories in

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4446E

Severity

Error

Long Form

. the guard point

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4447E

Severity

Error

Long Form

. --check_links Scan guard point and report any hard links

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4446E

Message ID : DXF4448E

Severity

Error

Long Form

. --cleanup Remove existing status files from a previous

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4449E

Severity

Error

Long Form

. rekey session

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4450E

Severity

Error

Long Form

. --recovery Generate a list of files already rekeyed in

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4449E

Message ID : DXF4451E

Severity

Error

Long Form

. guard point

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4452E

Severity

Error

Long Form

. --rekey_list Only rekey files listed in directive file

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4453E

Severity

Error

Long Form

. --version Display the version number

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4452E

Message ID : DXF4454E

Severity

Error

Long Form

. where {operation options} are parameters for the operation

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4455E

Severity

Error

Long Form

. --gp Specify name of guard point

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4456E

Severity

Error

Long Form

. Required for all operations except --version

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4455E

Message ID : DXF4457E

Severity

Error

Long Form

. --file_list Specify fully qualified name of directive

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4458E

Severity

Error

Long Form

. file for --rekey_list and --recovery

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4459E

Severity

Error

Long Form

. Defaults to dataxform_files in the guard

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4458E

Message ID : DXF4460E

Severity

Error

Long Form

. point directory

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4461E

Severity

Error

Long Form

. --dir_recovery Specify location for status file

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4462E

Severity

Error

Long Form

. Defaults to use log file location if there

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4461E

Message ID : DXF4463E

Severity

Error

Long Form

. is no --status_gp option

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4464E

Severity

Error

Long Form

About to remove the data transformation status files

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4465E

Severity

Error

Long Form

Shutting down data transform: received fatal signal {0}

Short Form

Xform killed by sigal

Parameters

Label	CEF Label	Type	Usage
sig	vds_sig	Numeric	A signal value

Message ID : DXF4464E

Description

None

Message ID : DXF4466E

Severity

Error

Long Form

Could not complete data transform for guard point {0}, data transform was interrupted by a signal

Short Form

Xform interrupted by signal

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	GuardPoint base directory

Description

None

Message ID : DXF4465E

Message ID : DXF4467E

Severity

Error

Long Form

. --preserve_access_time Preserve file access time after rekey

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4468E

Severity

Error

Long Form

. --preserve_modified_time Preserve file modified time after rekey

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4469E

Severity

Error

Long Form

. --nq Suppress prompts

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4468E

Message ID : DXF4470E

Severity

Error

Long Form

. --print_stat Display data transform statistics

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4471E

Severity

Error

Long Form

. --status_gp Write status file to the guard point

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4472E

Severity

Error

Long Form

. directory

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4471E

Message ID : DXF4474E

Severity

Error

Long Form

Process {0}: error {1} opening lock file at {2}. This may be due to an already running data transform instance

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4476E

Severity

Error

Long Form

The file {0} could not be transformed

Message ID : DXF4474E

Short Form

Prev xform file fail

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : DXF4477E

Severity

Error

Long Form

The file {0} could not be transformed, it had error in the previous data transform

Short Form

No short form is provided for this message type

Message ID : DXF4476E

Description

None

Message ID : DXF4478E

Severity

Error

Long Form

The file {0} could not be transformed, it was in progress in the previous data transform

Short Form

Prev xform file in progress

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : DXF4477E

Message ID : DXF4479E

Severity

Error

Long Form

The file {0} could not be transformed, the secfs component stopped the data transform

Short Form

Prev xform file stopped by Secfs

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : DXF4480E

Severity

Error

Long Form

The file {0} could not be transformed, a signal stopped the data transform

Short Form

Prev xform file stopped by signal

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : DXF4482E

Severity

Error

Message ID : DXF4480E

Long Form

Cannot create the data transform recovery/status file {0}, errno {1}

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4483E

Severity

Error

Long Form

Cannot create the data transform recovery/status file {0}, the file name is too long

Short Form

File too long

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : DXF4484E

Severity

Error

Long Form

Verify this is a guard point with a data transformation rule, and check the system log files for any other problems

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4483E

Message ID : DXF4486E

Severity

Error

Long Form

Invalid format in recovery file {0}

Short Form

Bad recovery file

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : DXF4494E

Severity

Error

Long Form

The file {0} was previously in error. The secfs component stopped the data transform

Short Form

Prev error - secfs stop

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : DXF4498E

Severity

Error

Message ID : DXF4494E

Long Form

The file {0} was previously in error. A signal stopped the dataxform

Short Form

Prev skipped - signal stop

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : DXF4499E

Severity

Error

Long Form

The file {0} was previously in error. It was open and could not be modified safely

Message ID : DXF4498E

Short Form

Prev error file open

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Logger DXF: Fatal errors

Message ID : DXF4431F

Severity

Fatal error

Long Form

Unable to determine the fully qualified host name of this machine: {0}. Please examine your machine's configuration.

Short Form

No short form is provided for this message type

Description

None

Logger DXF: Information

Message ID : DXF3211I

Severity

Information

Long Form

File {0} is being mapped or no-viewed, so it is skipped temporarily and moving on to next file

Short Form

File is being mapped or no-viewed

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : DXF3235I

Severity

Information

Long Form

LDT: Live data transform scan phase ran from {0} until {1}

Short Form

OXF run

Parameters

Label	CEF Label	Type	Usage
stime	start	Text	A start time stamp
etime	end	Text	An end time stamp

Description

None

Message ID : DXF3236I

Severity

Information

Long Form

LDT: Live data transform scan operation took {0} hours, {1} minutes and {2} seconds

Short Form

OXF duration

Parameters

Label	CEF Label	Type	Usage
hours	vds_hours	Numeric	Elapsed hours
mins	vds_mins	Numeric	Elapsed minutes
secs	vds_secs	Numeric	Elapsed seconds

Description

None

Message ID : DXF3236I

Message ID : DXF3237I

Severity

Information

Long Form

LDT: Live data transformation scan operation took {0} hours, {1} minutes and {2} seconds

Short Form

OXF op duration

Parameters

Label	CEF Label	Type	Usage
hours	vds_hours	Numeric	Elapsed hours
mins	vds_mins	Numeric	Elaped minutes
secs	vds_secs	Numeric	Elapsed seconds

Description

None

Message ID : DXF3237I

Message ID : DXF4122I

Severity

Information

Long Form

Number of files skipped due to insufficient memory: {0}

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4123I

Severity

Information

Long Form

Number of files previously skipped due to insufficient memory: {0}

Message ID : DXF4122I

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4126I

Severity

Information

Long Form

-- This is an estimated time using actual data transformations on test files

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4123I

Message ID : DXF4127I

Severity

Information

Long Form

-- This is an estimated time using simulated data transformations on test files

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4128I

Severity

Information

Long Form

-- The actual transformation time may be more or less than this estimate

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4129I

Severity

Information

Long Form

The file {0} was skipped. It was excluded by policy

Short Form

Skipped file by policy

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Message ID : DXF4128I

Description

None

Message ID : DXF4130I

Severity

Information

Long Form

The file {0} was previously skipped. It was excluded by policy

Short Form

Prev skipped file by policy

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : DXF4129I

Message ID : DXF4131I

Severity

Information

Long Form

Number of files skipped due to policy exclusion: {0}

Short Form

Skipped files by policy

Parameters

Label	CEF Label	Type	Usage
count	vds_count	Numeric	A generic count value

Description

None

Message ID : DXF4132I

Severity

Information

Long Form

Number of files previously skipped due to policy exclusion: {0}

Short Form

Prev skipped files by policy

Parameters

Label	CEF Label	Type	Usage
count	vds_count	Numeric	A generic count value

Description

None

Message ID : DXF4143I

Severity

Information

Message ID : DXF4132I

Long Form

{0} is not a guard point with a rekey policy applied

Short Form

Xform not supported

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	GuardPoint base directory

Description

None

Message ID : DXF4144I

Severity

Information

Long Form

The deep scan will emulate transformation to derive timing estimates

Message ID : DXF4143I

Short Form

Emulating xforms

Parameters

No parameters are provided for this message type

Description

None

Message ID : DXF4145I

Severity

Information

Long Form

The file {0} was skipped. It does not exist

Short Form

File missing

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : DXF4146I

Severity

Information

Long Form

Number of files skipped due to not existing: {0}

Short Form

Files missing

Parameters

Label	CEF Label	Type	Usage
count	vds_count	Numeric	A generic count value

Message ID : DXF4145I

Description

None

Message ID : DXF4147I

Severity

Information

Long Form

Number of files previously skipped due to not existing: {0}

Short Form

Prev files missing

Parameters

Label	CEF Label	Type	Usage
count	vds_count	Numeric	A generic count value

Description

None

Message ID : DXF4146I

Message ID : DXF4148I

Severity

Information

Long Form

The file {0} was previously skipped. It does not exist

Short Form

Prev error - file missing

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : DXF4154I

Severity

Information

Long Form

The data transform program ran from {0} until {1}

Short Form

Xform run

Parameters

Label	CEF Label	Type	Usage
stime	start	Text	A start time stamp
etime	end	Text	An end time stamp

Description

None

Message ID : DXF4161I

Severity

Information

Long Form

Skipping junction point {0}

Short Form

Junction point

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : DXF4200I

Severity

Information

Long Form

The file {0} was skipped. It was an additional hard link

Short Form

Skipped dup hard link

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : DXF4201I

Severity

Information

Message ID : DXF4200I

Long Form

The file {0} was skipped. It was a soft link

Short Form

Skipped soft link

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : DXF4202I

Severity

Information

Long Form

The file {0} was skipped. It was a dataxform internal file

Message ID : DXF4201I

Short Form

Skipped internal file

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : DXF4203I

Severity

Information

Long Form

The file {0} was skipped. dataxform had insufficient permission

Short Form

No short form is provided for this message type

Message ID : DXF4202I

Description

None

Message ID : DXF4204I

Severity

Information

Long Form

The file {0} was skipped. It had an ambiguous name

Short Form

Skipped bad name

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : DXF4203I

Message ID : DXF4205I

Severity

Information

Long Form

The file {0} was skipped. It was a special file

Short Form

Skipped special file

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : DXF4206I

Severity

Information

Long Form

The file {0} was skipped. It was exempt from data transform

Short Form

Skipped except file

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : DXF4207I

Severity

Information

Message ID : DXF4206I

Long Form

The file {0} was skipped. It was a compressed file

Short Form

Skipped compressed file

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : DXF4208I

Severity

Information

Long Form

The file {0} was skipped. It was an encrypted file

Message ID : DXF4207I

Short Form

Skipped encrypted file

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : DXF4209I

Severity

Information

Long Form

The file {0} was skipped. It was not a regular file

Short Form

Skipped non-file

Message ID : DXF4208I

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : DXF4210I

Severity

Information

Long Form

The file {0} was skipped. There was insufficient memory to process it

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4209I

Message ID : DXF4211I

Severity

Information

Long Form

The file {0} was skipped. It could not be classified

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4212I

Severity

Information

Long Form

The file {0} was skipped. It was no longer present when a transform was attempted

Message ID : DXF4211I

Short Form

File gone away

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : DXF4213I

Severity

Information

Long Form

The file {0} was skipped. A transform would have used the same key

Short Form

Skipped - same key

Message ID : DXF4212I

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : DXF4214I

Severity

Information

Long Form

The file {0} was skipped. Rekey was not supported for this file

Short Form

Skipped unsupported file

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Message ID : DXF4213I

Description

None

Message ID : DXF4216I

Severity

Information

Long Form

The file {0} was previously skipped. It was an additional hard link

Short Form

Prev skipped dup link

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : DXF4214I

Message ID : DXF4217I

Severity

Information

Long Form

The file {0} was previously skipped. It was a soft link

Short Form

Prev skipped soft link

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : DXF4218I

Severity

Information

Long Form

The file {0} was previously skipped. It was a dataxform internal file

Short Form

Prev skipped internal file

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : DXF4219I

Severity

Information

Message ID : DXF4218I

Long Form

The file {0} was previously skipped. dataxform had insufficient permission

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4220I

Severity

Information

Long Form

The file {0} was previously skipped. It had an ambiguous name

Short Form

Prev skipped bad name

Message ID : DXF4219I

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : DXF4221I

Severity

Information

Long Form

The file {0} was previously skipped. It was a special file

Short Form

Prev skipped special file

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Message ID : DXF4220I

Description

None

Message ID : DXF4222I

Severity

Information

Long Form

The file {0} was previously skipped. It was exempt from data transform

Short Form

Prev skipped excempt file

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : DXF4221I

Message ID : DXF4223I

Severity

Information

Long Form

The file {0} was previously skipped. It was a compressed file

Short Form

Prev skipped compressed file

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : DXF4224I

Severity

Information

Long Form

The file {0} was previously skipped. It was an encrypted file

Short Form

Prev skipped encrypted file

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : DXF4225I

Severity

Information

Message ID : DXF4224I

Long Form

Automatic data transform for guard point {0} deferred, no configuration file

Short Form

No config file

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	GuardPoint base directory

Description

None

Message ID : DXF4226I

Severity

Information

Long Form

The file {0} has the same "to" and "from" keys; skipping

Message ID : DXF4225I

Short Form

Skipping same keys

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : DXF4253I

Severity

Information

Long Form

There is no partial data transform for {0} to recover

Short Form

Nothing to recover

Message ID : DXF4226I

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	GuardPoint base directory

Description

None

Message ID : DXF4257I

Severity

Information

Long Form

Number of additional hard links skipped: {0}

Short Form

Hardlinks skipped

Parameters

Label	CEF Label	Type	Usage
count	vds_count	Numeric	A generic count value

Message ID : DXF4253I

Description

None

Message ID : DXF4258I

Severity

Information

Long Form

Number of soft links skipped: {0}

Short Form

Softlinks skipped

Parameters

Label	CEF Label	Type	Usage
count	vds_count	Numeric	A generic count value

Description

None

Message ID : DXF4257I

Message ID : DXF4259I

Severity

Information

Long Form

Number of files skipped due to insufficient permission: {0}

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4260I

Severity

Information

Long Form

Number of files skipped due to an ambiguous name: {0}

Message ID : DXF4259I

Short Form

Bad name errors

Parameters

Label	CEF Label	Type	Usage
count	vds_count	Numeric	A generic count value

Description

None

Message ID : DXF4261I

Severity

Information

Long Form

Number of special files skipped: {0}

Short Form

Special files skipped

Message ID : DXF4260I

Parameters

Label	CEF Label	Type	Usage
count	vds_count	Numeric	A generic count value

Description

None

Message ID : DXF4262I

Severity

Information

Long Form

Number of files exempt from data transform skipped: {0}

Short Form

Exempt files skipped

Parameters

Label	CEF Label	Type	Usage
count	vds_count	Numeric	A generic count value

Message ID : DXF4261I

Description

None

Message ID : DXF4263I

Severity

Information

Long Form

Number of compressed files skipped: {0}

Short Form

Compressed files skipped

Parameters

Label	CEF Label	Type	Usage
count	vds_count	Numeric	A generic count value

Description

None

Message ID : DXF4262I

Message ID : DXF4264I

Severity

Information

Long Form

Number of encrypted files skipped: {0}

Short Form

Encrypted files skipped

Parameters

Label	CEF Label	Type	Usage
count	vds_count	Numeric	A generic count value

Description

None

Message ID : DXF4265I

Severity

Information

Long Form

Number of non-regular files skipped: {0}

Short Form

Non-reg files skipped

Parameters

Label	CEF Label	Type	Usage
count	vds_count	Numeric	A generic count value

Description

None

Message ID : DXF4267I

Severity

Information

Message ID : DXF4265I

Long Form

Number of files skipped due to being no longer present when transform attempted: {0}

Short Form

Files gone away

Parameters

Label	CEF Label	Type	Usage
count	vds_count	Numeric	A generic count value

Description

None

Message ID : DXF4268I

Severity

Information

Long Form

Number of files skipped due to a duplicate key: {0}

Message ID : DXF4267I

Short Form

Files with dup key

Parameters

Label	CEF Label	Type	Usage
count	vds_count	Numeric	A generic count value

Description

None

Message ID : DXF4269I

Severity

Information

Long Form

Number of files skipped due to rekey not supported for this file: {0}

Short Form

Unsupported files skipped

Message ID : DXF4268I

Parameters

Label	CEF Label	Type	Usage
count	vds_count	Numeric	A generic count value

Description

None

Message ID : DXF4273I

Severity

Information

Long Form

Number of additional hard links previously skipped: {0}

Short Form

Prev hardlinks skipped

Parameters

Label	CEF Label	Type	Usage
count	vds_count	Numeric	A generic count value

Message ID : DXF4269I

Description

None

Message ID : DXF4274I

Severity

Information

Long Form

Number of soft links previously skipped: {0}

Short Form

Prev softlinks skipped

Parameters

Label	CEF Label	Type	Usage
count	vds_count	Numeric	A generic count value

Description

None

Message ID : DXF4273I

Message ID : DXF4275I

Severity

Information

Long Form

Number of files previously skipped due to insufficient permission: {0}

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4276I

Severity

Information

Long Form

Number of files previously skipped due to an ambiguous name: {0}

Message ID : DXF4275I

Short Form

Prev bad name errors

Parameters

Label	CEF Label	Type	Usage
count	vds_count	Numeric	A generic count value

Description

None

Message ID : DXF4277I

Severity

Information

Long Form

Number of special files previously skipped: {0}

Short Form

Prev special files skipped

Message ID : DXF4276I

Parameters

Label	CEF Label	Type	Usage
count	vds_count	Numeric	A generic count value

Description

None

Message ID : DXF4278I

Severity

Information

Long Form

Number of files exempt from data transform previously skipped: {0}

Short Form

Prev exempt files skipped

Parameters

Label	CEF Label	Type	Usage
count	vds_count	Numeric	A generic count value

Message ID : DXF4277I

Description

None

Message ID : DXF4279I

Severity

Information

Long Form

Number of compressed files previously skipped: {0}

Short Form

Prev compressed files skipped

Parameters

Label	CEF Label	Type	Usage
count	vds_count	Numeric	A generic count value

Description

None

Message ID : DXF4278I

Message ID : DXF4280I

Severity

Information

Long Form

Number of encrypted files previously skipped: {0}

Short Form

Prev encrypted files skipped

Parameters

Label	CEF Label	Type	Usage
count	vds_count	Numeric	A generic count value

Description

None

Message ID : DXF4281I

Severity

Information

Long Form

Number of non-regular files previously skipped: {0}

Short Form

Prev non-reg files skipped

Parameters

Label	CEF Label	Type	Usage
count	vds_count	Numeric	A generic count value

Description

None

Message ID : DXF4283I

Severity

Information

Message ID : DXF4281I

Long Form

Number of files previously skipped due to being no longer present when transform attempted: {0}

Short Form

Prev files gone away

Parameters

Label	CEF Label	Type	Usage
count	vds_count	Numeric	A generic count value

Description

None

Message ID : DXF4284I

Severity

Information

Long Form

Number of files previously skipped due to a duplicate key: {0}

Message ID : DXF4283I

Short Form

Prev files with dup key

Parameters

Label	CEF Label	Type	Usage
count	vds_count	Numeric	A generic count value

Description

None

Message ID : DXF4285I

Severity

Information

Long Form

Number of files previously skipped due to rekey not supported for this file: {0}

Short Form

Prev unsupported files skipped

Message ID : DXF4284I

Parameters

Label	CEF Label	Type	Usage
count	vds_count	Numeric	A generic count value

Description

None

Message ID : DXF4293I

Severity

Information

Long Form

Estimated data transformation time for {0} is {1}

Short Form

Estimate duration

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	GuardPoint base directory

Message ID : DXF4285I

Label	CEF Label	Type	Usage
rt	rt	Text	Time of event

Description

None

Message ID : DXF4309I

Severity

Information

Long Form

Building the list of previously transformed files in {0}

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4316I

Severity

Information

Long Form

Status information for directories in guard point

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4317I

Severity

Information

Long Form

Finished processing directory {0}

Short Form

Completed dir

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : DXF4318I

Severity

Information

Long Form

Partially processed directory {0}

Short Form

Partially processed dir

Message ID : DXF4317I

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : DXF4319I

Severity

Information

Long Form

Skipping directory {0}

Short Form

Skipped dir

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Message ID : DXF4318I

Description

None

Message ID : DXF4320I

Severity

Information

Long Form

Skipping empty directory {0}

Short Form

Empty dir

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : DXF4319I

Message ID : DXF4321I

Severity

Information

Long Form

Skipping exempt directory {0}

Short Form

Exempt dir

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : DXF4322I

Severity

Information

Long Form

Unknown status for directory {0}

Short Form

Dir bad status

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : DXF4323I

Severity

Information

Message ID : DXF4322I

Long Form

Directory {0} contains {1} files ({2})

Short Form

Xform to do

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file
nfile	vds_nfile	Numeric	The number of files processed

Description

None

Message ID : DXF4329I

Severity

Information

Message ID : DXF4323I

Long Form

Finished check for hard links in {0}

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4332I

Severity

Information

Long Form

Setting recovery-file-list to {0}

Short Form

No short form is provided for this message type

Message ID : DXF4329I

Description

None

Message ID : DXF4344I

Severity

Information

Long Form

Data transform version {0}

Short Form

Datatform

Parameters

Label	CEF Label	Type	Usage
version	vds_version	Text	Software version string

Description

None

Message ID : DXF4332I

Message ID : DXF4345I

Severity

Information

Long Form

Data transform version {0}, using policy {1} on guard point {2}

Short Form

Auto dataxform

Parameters

Label	CEF Label	Type	Usage
version	vds_version	Text	Software version string
pol	cs1	Text	Policy name
gp	fileId	Text	GuardPoint base directory

Description

None

Message ID : DXF4352I

Severity

Information

Long Form

Data transform for {0} was previously completed

Short Form

Xform prev complete

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	GuardPoint base directory

Description

None

Message ID : DXF4361I

Severity

Information

Long Form

Data transform for guard point {0} finished

Short Form

Xform done

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	GuardPoint base directory

Description

None

Message ID : DXF4362I

Severity

Information

Message ID : DXF4361I

Long Form

Data transform for guard point {0} finished but {1} files were not processed due to errors

Short Form

Xform done with errors

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	GuardPoint base directory
count	vds_count	Numeric	A generic count value

Description

None

Message ID : DXF4363I

Severity

Information

Message ID : DXF4362I

Long Form

Data transform for guard point {0} finished but {1} files were skipped

Short Form

Xform done with skips

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	GuardPoint base directory
count	vds_count	Numeric	A generic count value

Description

None

Message ID : DXF4364I

Severity

Information

Message ID : DXF4363I

Long Form

Data transform for guard point {0} finished but {1} files were not processed due to errors and {2} files were skipped

Short Form

Xform done with errors and skips

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	GuardPoint base directory
count	vds_count	Numeric	A generic count value
count	vds_count	Numeric	A generic count value

Description

None

Message ID : DXF4365I

Severity

Information

Message ID : DXF4364I

Long Form

The data transform operation took {0} hours, {1} minutes and {2} seconds

Short Form

Xform duration

Parameters

Label	CEF Label	Type	Usage
hours	vds_hours	Numeric	Elapsed hours
mins	vds_mins	Numeric	Elapsed minutes
secs	vds_secs	Numeric	Elapsed seconds

Description

None

Message ID : DXF4366I

Severity

Information

Message ID : DXF4365I

Long Form

The current operation took {0} hours, {1} minutes and {2} seconds

Short Form

Xform op duration

Parameters

Label	CEF Label	Type	Usage
hours	vds_hours	Numeric	Elapsed hours
mins	vds_mins	Numeric	Elapsed minutes
secs	vds_secs	Numeric	Elapsed seconds

Description

None

Message ID : DXF4369I

Severity

Information

Message ID : DXF4366I

Long Form

Data transform had some files in progress

Short Form

Prev xform incomplete

Parameters

No parameters are provided for this message type

Description

None

Message ID : DXF4370I

Severity

Information

Long Form

The file {0} was in progress in the previous data transform, it will not be transformed

Message ID : DXF4369I

Short Form

Prev xform file inprogress

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : DXF4371I

Severity

Information

Long Form

Data transform skipped some files

Short Form

No short form is provided for this message type

Message ID : DXF4370I

Description

None

Message ID : DXF4372I

Severity

Information

Long Form

The file {0} was skipped in the previous data transform, it will be skipped

Short Form

Prev xform file skipped

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : DXF4371I

Message ID : DXF4375I

Severity

Information

Long Form

Data transform last successfully transformed the file {0}

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4378I

Severity

Information

Long Form

Scan found {0} files ({1}) in {2} directories for guard point {3}

Message ID : DXF4375I

Short Form

Scan result

Parameters

Label	CEF Label	Type	Usage
nfile	vds_nfile	Numeric	The number of files processed
ndir	vds_ndir	Numeric	The number of directories processed
gp	fileId	Text	GuardPoint base directory

Description

None

Message ID : DXF4380I

Severity

Information

Long Form

Transformed {0} files ({1}) of {2} files ({3}) for guard point {4}

Message ID : DXF4378I

Short Form

Scan stats

Parameters

Label	CEF Label	Type	Usage
nfile	vds_nfile	Numeric	The number of files processed
space	vds_space	Text	A string representation of file or disk space
nfiles	vds_nfiles	Numeric	The total number of files in an operation
space	vds_space	Text	A string representation of file or disk space
gp	fileId	Text	GuardPoint base directory

Description

None

Message ID : DXF4383I

Severity

Information

Message ID : DXF4380I

Long Form

Generating list of files previously transformed on {0}

Short Form

Recovery gen

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	GuardPoint base directory

Description

None

Message ID : DXF4384I

Severity

Information

Long Form

Automatic data transform status for {0}: previous attempt completed

Message ID : DXF4383I

Short Form

Prev auto xform done

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	GuardPoint base directory

Description

None

Message ID : DXF4385I

Severity

Information

Long Form

Automatic data transform status for {0}: previous attempt did not complete

Short Form

Prev auto xform fail

Message ID : DXF4384I

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	GuardPoint base directory

Description

None

Message ID : DXF4386I

Severity

Information

Long Form

Automatic data transform from host {0} for {1}: previous attempt completed

Short Form

Prev auto xform done

Parameters

Label	CEF Label	Type	Usage
shost	shost	Text	Source host name

Message ID : DXF4385I

Label	CEF Label	Type	Usage
gp	fileId	Text	GuardPoint base directory

Description

None

Message ID : DXF4387I

Severity

Information

Long Form

Automatic data transform from host {0} for {1}: previous attempt did not complete

Short Form

Prev auto xform fail

Parameters

Label	CEF Label	Type	Usage
shost	shost	Text	Source host name
gp	fileId	Text	GuardPoint base directory

Message ID : DXF4386I

Description

None

Message ID : DXF4388I

Severity

Information

Long Form

Automatic data transform for {0}: could not get status

Short Form

Auto xform stat fail

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	GuardPoint base directory

Description

None

Message ID : DXF4387I

Message ID : DXF4389I

Severity

Information

Long Form

Starting data transform of {0} for files listed in {1}

Short Form

Rekey file start

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	GuardPoint base directory
filePath	filePath	Text	Full path to file

Description

None

Message ID : DXF4390I

Severity

Information

Long Form

Data transform of {0} of {1} files listed in {2} for guard point {3}

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4397I

Severity

Information

Long Form

Found {0} references to hard link

Short Form

Hardlink count

Parameters

Label	CEF Label	Type	Usage
count	vds_count	Numeric	A generic count value

Description

None

Message ID : DXF4399I

Severity

Information

Long Form

Hardlink reference {0} {1}

Short Form

Hardlink refs

Message ID : DXF4397I

Parameters

Label	CEF Label	Type	Usage
count	vds_count	Numeric	A generic count value
filePath	filePath	Text	Full path to file

Description

None

Message ID : DXF4414I

Severity

Information

Long Form

Executing script {0}

Short Form

Exec fail

Message ID : DXF4399I

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : DXF4415I

Severity

Information

Long Form

Generating list of files transformed during previous session for guard point {0}

Short Form

List create

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	GuardPoint base directory

Message ID : DXF4414I

Description

None

Message ID : DXF4416I

Severity

Information

Long Form

Writing list of files transformed during previous session for guard point {0}

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4417I

Severity

Information

Message ID : DXF4415I

Long Form

Checking if {0} is a guard point with a rekey policy applied

Short Form

Checking supported

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	GuardPoint base directory

Description

None

Message ID : DXF4418I

Severity

Information

Long Form

Preparing data transform

Message ID : DXF4417I

Short Form

Prepare xform

Parameters

No parameters are provided for this message type

Description

None

Message ID : DXF4419I

Severity

Information

Long Form

Preparing data transform for next phase of execution

Short Form

xform thread idle

Parameters

No parameters are provided for this message type

Description

None

Message ID : DXF4420I

Severity

Information

Long Form

Generating list of files to transform in directory {0}

Short Form

Generating list

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Message ID : DXF4419I

Description

None

Message ID : DXF4421I

Severity

Information

Long Form

Scanning for hard links in directory {0}

Short Form

Check links

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : DXF4420I

Message ID : DXF4422I

Severity

Information

Long Form

Processing the list of files specified in {0}

Short Form

Processing list

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : DXF4423I

Severity

Information

Long Form

Processed {0} files ({1}) of {2} files ({3}) in {4}

Short Form

Processed files

Parameters

Label	CEF Label	Type	Usage
nfile	vds_nfile	Numeric	The number of files processed
nfiles	vds_nfiles	Numeric	The total number of files in an operation
filePath	filePath	Text	Full path to file

Description

None

Message ID : DXF4424I

Message ID : DXF4423I

Severity

Information

Long Form

Processed {0} files ({1}) of {2} files ({3}) in {4}, in progress {5}, completed {6}

Short Form

Processing files

Parameters

Label	CEF Label	Type	Usage
nfile	vds_nfile	Numeric	The number of files processed
nfiles	vds_nfiles	Numeric	The total number of files in an operation
filePath	filePath	Text	Full path to file
scount	vds_scount	Text	A generic count as a string
scount	vds_scount	Text	A generic count as a string

Description

None

Message ID : DXF4425I

Severity

Information

Long Form

Processed {0} files of {1} files specified by {2} in guard point {3}

Short Form

Processed list

Parameters

Label	CEF Label	Type	Usage
nfile	vds_nfile	Numeric	The number of files processed
nfiles	vds_nfiles	Numeric	The total number of files in an operation
filePath	filePath	Text	Full path to file
gp	fileId	Text	GuardPoint base directory

Description

None

Message ID : DXF4429I

Severity

Information

Long Form

{0} is a guard point with a rekey policy applied

Short Form

Xform supported

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	GuardPoint base directory

Description

None

Message ID : DXF4481I

Severity

Information

Long Form

The file {0} was skipped

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4485I

Severity

Information

Long Form

Data transform last processing was on the file {0}

Message ID : DXF4481I

Short Form

Last file xformed

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : DXF4487I

Severity

Information

Long Form

The file {0} could not be transformed, it was skipped in a previous data transform

Short Form

No short form is provided for this message type

Message ID : DXF4485I

Description

None

Message ID : DXF4488I

Severity

Information

Long Form

Previous status information relates to a --rekey_file operation.

Short Form

Prev op was rekey

Parameters

No parameters are provided for this message type

Description

None

Message ID : DXF4487I

Message ID : DXF4489I

Severity

Information

Long Form

Previous status information does not relate to a --rekey_file operation.

Short Form

Prev op was rekey_file

Parameters

No parameters are provided for this message type

Description

None

Message ID : DXF4490I

Severity

Information

Message ID : DXF4489I

Long Form

Previous status information will be ignored

Short Form

Prev status ignored

Parameters

No parameters are provided for this message type

Description

None

Message ID : DXF4491I

Severity

Information

Long Form

The file {0} was previously skipped. It was not a regular file

Message ID : DXF4490I

Short Form

Prev skipped non-file

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : DXF4492I

Severity

Information

Long Form

The file {0} was previously skipped. There was insufficient memory to process it

Short Form

No short form is provided for this message type

Message ID : DXF4491I

Description

None

Message ID : DXF4493I

Severity

Information

Long Form

The file {0} was previously skipped. It could not be classified

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4495I

Severity

Information

Message ID : DXF4492I

Long Form

The file {0} was previously skipped. It was no longer present when a transform was attempted

Short Form

Prev error - file gone

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : DXF4496I

Severity

Information

Long Form

The file {0} was previously skipped. A transform would have used the same key

Message ID : DXF4495I

Short Form

Prev skipped - same key

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : DXF4497I

Severity

Information

Long Form

The file {0} was previously skipped. Rekey was not supported for this file

Short Form

Prev skipped unsupported file

Message ID : DXF4496I

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Logger DXF: Warnings

Message ID : DXF3210W

Severity

Warning

Long Form

If Shadow Copy was used on your system, you must back up your data before attempting to run dataxform. Once DataXform has been completed, you may restart Shadow Copy. Note, however, that all Shadow Copy backups made prior to running dataxform will be unusable and should be discarded. Attempting to restore your cleartext Shadow Copy backups made prior to running dataxform into your encrypted data will result in data corruption.

Short Form

Shadow copy

Parameters

No parameters are provided for this message type

Description

None

Message ID : DXF4103W

Severity

Warning

Long Form

Transformation time estimation will be simulated as guard point does not support rekeying

Short Form

No rekey support

Parameters

No parameters are provided for this message type

Description

None

Message ID : DXF4104W

Severity

Warning

Message ID : DXF4103W

Long Form

Missing {0} references to hard link {1}

Short Form

Missing hardlink refs

Parameters

Label	CEF Label	Type	Usage
count	vds_count	Numeric	A generic count value
filePath	filePath	Text	Full path to file

Description

None

Message ID : DXF4118W

Severity

Warning

Message ID : DXF4104W

Long Form

Could not return file time for {0} to its original value, got error {1}

Short Form

Time restore error

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file
showStr	reason	Text	Code specifying reason for allowing access, if any

Description

None

Message ID : DXF4242W

Severity

Warning

Message ID : DXF4118W

Long Form

More than {0} files were encountered in the directory {1}. Dataxform may consume excessive system resources while operating upon this directory. Proceeding

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4254W

Severity

Warning

Long Form

Note: data from a previous dataxform run is being used

Short Form

Prev run data in use

Message ID : DXF4242W

Parameters

No parameters are provided for this message type

Description

None

Message ID : DXF4307W

Severity

Warning

Long Form

Skipping previously transformed directory {0}

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4254W

Message ID : DXF4324W

Severity

Warning

Long Form

Cannot perform data transform for {0} with identical key

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4327W

Severity

Warning

Long Form

Secfs component returned stop-data-transform status

Message ID : DXF4324W

Short Form

Stopped by Secfs

Parameters

No parameters are provided for this message type

Description

None

Message ID : DXF4333W

Severity

Warning

Long Form

Unknown version for recovery file list

Short Form

Bad version

Message ID : DXF4327W

Parameters

No parameters are provided for this message type

Description

None

Message ID : DXF4337W

Severity

Warning

Long Form

Resetting read buffer size to {0}KB

Short Form

Setting buf size

Parameters

Label	CEF Label	Type	Usage
slen	in	Numeric	Input byte count or length

Message ID : DXF4333W

Description

None

Message ID : DXF4338W

Severity

Warning

Long Form

Resetting the maximum number of secfs threads to {0}

Short Form

Number kthreads

Parameters

Label	CEF Label	Type	Usage
count	vds_count	Numeric	A generic count value

Description

None

Message ID : DXF4337W

Message ID : DXF4339W

Severity

Warning

Long Form

Resetting the maximum number of utility threads to {0}

Short Form

Max uthreads

Parameters

Label	CEF Label	Type	Usage
count	vds_count	Numeric	A generic count value

Description

None

Message ID : DXF4351W

Severity

Warning

Long Form

Could not load previous data transform information

Short Form

Recovery file load fail

Parameters

No parameters are provided for this message type

Description

None

Message ID : DXF4359W

Severity

Warning

Message ID : DXF4351W

Long Form

Could not notify secfs component that data transform completed on {0}

Short Form

Secfs notify complete fail

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	GuardPoint base directory

Description

None

Message ID : DXF4373W

Severity

Warning

Long Form

Data transform was previously run on guard point {0}

Message ID : DXF4359W

Short Form

Xform prev completed

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	GuardPoint base directory

Description

None

Message ID : DXF4398W

Severity

Warning

Long Form

Found {0} references to hard link but expected {1}

Short Form

Hardlink count error

Message ID : DXF4373W

Parameters

Label	CEF Label	Type	Usage
count	vds_count	Numeric	A generic count value
count	vds_count	Numeric	A generic count value

Description

None

Message ID : DXF4406W

Severity

Warning

Long Form

Could not return file time for {0} to its original value, got error code {1}

Short Form

No short form is provided for this message type

Message ID : DXF4398W

Description

None

Message ID : DXF4410W

Severity

Warning

Long Form

Could not read the Windows registry, section {0}

Short Form

Read read fail

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : DXF4406W

Message ID : DXF4413W

Severity

Warning

Long Form

Attempted to restrict access to unknown object ID {0}

Short Form

No short form is provided for this message type

Description

None

Message ID : DXF4428W

Severity

Warning

Long Form

Unable to contact Key Manager; will perform all logging to the local log file

Short Form

No short form is provided for this message type

Description

None

Logger FAM: Information

Message ID : FAM7001I

Severity

Information

Long Form

Compact logging enabled

Short Form

CompLog Enabled

Parameters

No parameters are provided for this message type

Description

None

Message ID : FAM7004I

Severity

Information

Long Form

process {0}, action {1}, filePath {2}, oldfilePath {3}, access_code {4}, access_state {5}, action_status {6}, fam_policyname {7}, fam_rule_code {8}, uinfo {9}

Short Form

FAM Audit

Parameters

Label	CEF Label	Type	Usage
sproc	sproc	Text	Source process
act	act	Text	Action being requested or performed
filePath	filePath	Text	Full path to file
oldFilePath	oldFilePath	Text	Previous path to file (for rename and link)
access_code	access_code	Numeric	Error code returned by the action
access_state	access_state	Text	The action state like CTE PERMIT/DENIED or OS PERMIT/DENIED
action_status	action_status	Text	Identifier if an action was success or failed
fam_policy	fam_policy	Text	FAM Policy name

Label	CEF Label	Type	Usage
fam_rule_code	fam_rule_code	Text	FAM Rule trace
user	suser	Text	User name

Description

None

Message ID : FAM7005I

Severity

Information

Long Form

process {0}, action {1}, filePath {2}, oldfilePath {3}, was_decrypted {4}, is_encrypted {5}, access_code {6}, access_state {7}, action_status {8}, fam_policyname {9}, fam_rule_code {10}, cte_policyname {11}, cte_rule_code {12}, uinfo {13}

Short Form

FAM Audit

Parameters

Label	CEF Label	Type	Usage
-------	-----------	------	-------

Message ID : FAM7004I

850

Label	CEF Label	Type	Usage
sproc	sproc	Text	Source process
act	act	Text	Action being requested or performed
filePath	filePath	Text	Full path to file
oldFilePath	oldFilePath	Text	Previous path to file (for rename and link)
was_decrypted	was_decrypted	Text	Flag to specify whether file was decrypted or not
is_encrypted	is_encrypted	Text	Flag to specify whether file is encrypted by operation
access_code	access_code	Numeric	Error code returned by the action
access_state	access_state	Text	The action state like CTE PERMIT/DENIED or OS PERMIT/DENIED
action_status	action_status	Text	Identifier if an action was success or failed
fam_policy	fam_policy	Text	FAM Policy name
fam_rule_code	fam_rule_code	Text	FAM Rule trace
cte_policy	cte_policy	Text	CTE Policy name
cte_rule_code	cte_rule_code	Text	CTE Rule trace
user	suser	Text	User name

Description

None

Message ID : FAM7006I

Severity

Information

Long Form

process {0}, action {1}, filePath {2}, access_code {3}, access_state {4}, action_status {5}, fam_policyname {6}, fam_rule_code {7}, uinfo {8}

Short Form

FAM Audit

Parameters

Label	CEF Label	Type	Usage
sproc	sproc	Text	Source process
act	act	Text	Action being requested or performed
filePath	filePath	Text	Full path to file
access_code	access_code	Numeric	Error code returned by the action
access_state	access_state	Text	The action state like CTE PERMIT/DENIED or OS PERMIT/DENIED
action_status	action_status	Text	Identifier if an action was success or failed

Label	CEF Label	Type	Usage
fam_policy	fam_policy	Text	FAM Policy name
fam_rule_code	fam_rule_code	Text	FAM Rule trace
user	suser	Text	User name

Description

None

Message ID : FAM7007I

Severity

Information

Long Form

process {0}, action {1}, filePath {2}, was_decrypted {3}, is_encrypted {4}, access_code {5}, access_state {6}, action_status {7}, fam_policyname {8}, fam_rule_code {9}, cte_policyname {10}, cte_rule_code {11}, uinfo {12}

Short Form

FAM Audit

Message ID : FAM7006I

853

Parameters

Label	CEF Label	Type	Usage
sproc	sproc	Text	Source process
act	act	Text	Action being requested or performed
filePath	filePath	Text	Full path to file
was_decrypted	was_decrypted	Text	Flag to specify whether file was decrypted or not
is_encrypted	is_encrypted	Text	Flag to specify whether file is encrypted by operation
access_code	access_code	Numeric	Error code returned by the action
access_state	access_state	Text	The action state like CTE PERMIT/DENIED or OS PERMIT/DENIED
action_status	action_status	Text	Identifier if an action was success or failed
fam_policy	fam_policy	Text	FAM Policy name
fam_rule_code	fam_rule_code	Text	FAM Rule trace
cte_policy	cte_policy	Text	CTE Policy name
cte_rule_code	cte_rule_code	Text	CTE Rule trace
user	suser	Text	User name

Description

None

Logger FAM: Warnings

Message ID : FAM7002W

Severity

Warning

Long Form

Compact logging disabled

Short Form

CompLog Disabled

Parameters

No parameters are provided for this message type

Description

None

Logger FUS: Errors

Message ID : FUS3368E

Severity

Error

Long Form

secfs_fuse: {0}

Short Form

secfs_fuse:

Parameters

Label	CEF Label	Type	Usage
showStr	reason	Text	Code specifying reason for allowing access, if any

Description

None

Logger FUS: Information

Message ID : FUS3366I

Severity

Information

Long Form

secfs_fuse: {0}

Short Form

secfs_fuse:

Parameters

Label	CEF Label	Type	Usage
showStr	reason	Text	Code specifying reason for allowing access, if any

Description

None

Logger FUS: Warnings

Message ID : FUS3367W

Severity

Warning

Long Form

secfs_fuse: {0}

Short Form

secfs_fuse:

Parameters

Label	CEF Label	Type	Usage
showStr	reason	Text	Code specifying reason for allowing access, if any

Description

None

Logger POL: Errors

Message ID : POL4556E

Severity

Error

Long Form

ACCESS DENIED on request to {0} database {1}, on hostname {2}. Instance name is {3}, partition {4}, catnode {5}. The timestamp is {6}, and the DB2 version is {7}. The request protocol version is {8}.

Short Form

Access denied by policy

Parameters

Label	CEF Label	Type	Usage
act	act	Text	Action being requested or performed
dbname	vds_dbname	Text	Database name
shost	shost	Text	Source host name
dbinstance	vds_dbinstance	Text	Database instance
dbpart	vds_dbpart	Numeric	Database partition

Label	CEF Label	Type	Usage
node	vds_node	Numeric	A node identifier
rt	rt	Text	Time of event
dbver	vds_dbver	Numeric	Database version
version	vds_version	Text	Software version string

Description

None

Message ID : POL4580E

Severity

Error

Long Form

ACCESS DENIED on request to perform {0} for hostname {1}. Server name is {2}, server number {3}, object id {4}. The timestamp is {5}. The request protocol version is {6}.

Short Form

No short form is provided for this message type

Description

None

Message ID : POL4613E

Severity

Error

Long Form

ACCESS DENIED on request to perform {0} for hostname {1}. Server name is {2}, server number {3}. The timestamp is {4}. The request protocol version is {5}.

Short Form

Access denied

Parameters

Label	CEF Label	Type	Usage
act	act	Text	Action being requested or performed
shost	shost	Text	Source host name
dbinstance	vds_dbinstance	Text	Database instance
dbpart	vds_dbpart	Numeric	Database partition

Message ID : POL4580E

Label	CEF Label	Type	Usage
rt	rt	Text	Time of event
version	vds_version	Text	Software version string

Description

An online policy blocked access. Details of the attempted access are provided in the message fields.

Message ID : POL4701E

Severity

Error

Long Form

Memory allocation failed in [{0}] at line [{1}]

Short Form

Out of memory

Parameters

No parameters are provided for this message type

Description

None

Message ID : POL4704E

Severity

Error

Long Form

EVENT: {0}

Short Form

Event

Parameters

Label	CEF Label	Type	Usage
showStr	reason	Text	Code specifying reason for allowing access, if any

Description

None

Message ID : POL4701E

Logger POL: Fatal errors

Message ID : POL4510F

Severity

Fatal error

Long Form

Fatal error while evaluating policy to {0} database {1}, on hostname {2}. Instance name is {3}, partition {4}, catnode {5}. The timestamp is {6}, and the DB2 version is {7}. The request protocol version is {8}.

Short Form

Policy eval error

Parameters

Label	CEF Label	Type	Usage
act	act	Text	Action being requested or performed
dbname	vds_dbname	Text	Database name
shost	shost	Text	Source host name
dbinstance	vds_dbinstance	Text	Database instance
dbpart	vds_dbpart	Numeric	Database partition

Label	CEF Label	Type	Usage
node	vds_node	Numeric	A node identifier
rt	rt	Text	Time of event
dbver	vds_dbver	Numeric	Database version
version	vds_version	Text	Software version string

Description

None

Message ID : POL4516F

Severity

Fatal error

Long Form

Attribute "{0}" parsing error in policy evaluation request.

Short Form

Req parse error

Message ID : POL4510F

Parameters

Label	CEF Label	Type	Usage
showStr	reason	Text	Code specifying reason for allowing access, if any

Description

None

Message ID : POL4528F

Severity

Fatal error

Long Form

Attribute "{0}" parsing error in policy evaluation response.

Short Form

Resp parse error

Parameters

Label	CEF Label	Type	Usage
showStr	reason	Text	Code specifying reason for allowing access, if any

Message ID : POL4516F

Description

None

Message ID : POL4530F

Severity

Fatal error

Long Form

Global restore header invalid. Data corruption has possibly occurred. The restore operation will fail.

Short Form

Global restore header invalid

Parameters

No parameters are provided for this message type

Description

None

Message ID : POL4528F

Message ID : POL4545F

Severity

Fatal error

Long Form

Restore failed: Backup image created with future version.

Short Form

Restore fail - future image

Parameters

No parameters are provided for this message type

Description

None

Message ID : POL4564F

Severity

Fatal error

Long Form

The agent could not allocate enough memory. Contact support.

Short Form

Out of memory

Parameters

No parameters are provided for this message type

Description

None

Message ID : POL4581F

Severity

Fatal error

Long Form

Fatal error while evaluating policy to perform {0} for hostname {1}. Server name is {2}, server number {3}, object id {4}. The timestamp is {5}. The request protocol version is {6}.

Short Form

No short form is provided for this message type

Description

None

Message ID : POL4593F

Severity

Fatal error

Long Form

The agent could not evaluate policy. Contact support.

Short Form

Cannot eval policy

Parameters

No parameters are provided for this message type

Message ID : POL4581F

Description

None

Message ID : POL4614F

Severity

Fatal error

Long Form

Fatal error while evaluating policy to perform {0} for hostname {1}. Server name is {2}, server number {3}. The timestamp is {4}. The request protocol version is {5}.

Short Form

Policy eval error

Parameters

Label	CEF Label	Type	Usage
act	act	Text	Action being requested or performed
shost	shost	Text	Source host name
dbinstance	vds_dbinstance	Text	Database instance
dbpart	vds_dbpart	Numeric	Database partition

Message ID : POL4593F

Label	CEF Label	Type	Usage
rt	rt	Text	Time of event
version	vds_version	Text	Software version string

Description

None

Logger POL: Information

Message ID : POL4537I

Severity

Information

Long Form

ACCESS GRANTED on request to {0} database {1}, on hostname {2}. Instance name is {3}, partition {4}, catnode {5}. The timestamp is {6}, and the DB2 version is {7}. The request protocol version is {8}.

Short Form

Access granted

Parameters

Label	CEF Label	Type	Usage
act	act	Text	Action being requested or performed
dbname	vds_dbname	Text	Database name
shost	shost	Text	Source host name
dbinstance	vds_dbinstance	Text	Database instance
dbpart	vds_dbpart	Numeric	Database partition

Label	CEF Label	Type	Usage
node	vds_node	Numeric	A node identifier
rt	rt	Text	Time of event
dbver	vds_dbver	Numeric	Database version
version	vds_version	Text	Software version string

Description

None

Message ID : POL4553I

Severity

Information

Long Form

Internal initialization successful.

Short Form

SDK Init OK

Message ID : POL4537I

Parameters

No parameters are provided for this message type

Description

None

Message ID : POL4573I

Severity

Information

Long Form

Backup failed.

Short Form

Backup fail

Parameters

No parameters are provided for this message type

Message ID : POL4553I

Description

None

Message ID : POL4574I

Severity

Information

Long Form

Restore failed.

Short Form

Restore fail

Parameters

No parameters are provided for this message type

Description

None

Message ID : POL4573I

Message ID : POL4575I

Severity

Information

Long Form

Backup completed successfully.

Short Form

Backup complete OK

Parameters

No parameters are provided for this message type

Description

None

Message ID : POL4576I

Severity

Information

Message ID : POL4575I

Long Form

Restore completed successfully.

Short Form

Restore complete OK

Parameters

No parameters are provided for this message type

Description

None

Message ID : POL4582I

Severity

Information

Long Form

ACCESS GRANTED on request to perform {0} for hostname {1}. Server name is {2}, server number {3}, object id {4}. The timestamp is {5}. The request protocol version is {6}.

Message ID : POL4576I

Short Form

No short form is provided for this message type

Description

None

Message ID : POL4615I

Severity

Information

Long Form

ACCESS GRANTED on request to perform {0} for hostname {1}. Server name is {2}, server number {3}. The timestamp is {4}. The request protocol version is {5}.

Short Form

Access granted

Parameters

Label	CEF Label	Type	Usage
act	act	Text	Action being requested or performed

Message ID : POL4582I

Label	CEF Label	Type	Usage
shost	shost	Text	Source host name
dbinstance	vds_dbinstance	Text	Database instance
dbpart	vds_dbpart	Numeric	Database partition
rt	rt	Text	Time of event
version	vds_version	Text	Software version string

Description

None

Message ID : POL4702I

Severity

Information

Long Form

EVENT: {0}

Short Form

Event

Message ID : POL4615I

Parameters

Label	CEF Label	Type	Usage
showStr	reason	Text	Code specifying reason for allowing access, if any

Description

None

Logger POL: Warnings

Message ID : POL4703W

Severity

Warning

Long Form

EVENT: {0}

Short Form

Event

Parameters

Label	CEF Label	Type	Usage
showStr	reason	Text	Code specifying reason for allowing access, if any

Description

None

Logger VAD: Errors

Message ID : VAD4642E

Severity

Error

Long Form

{0}: {1} Failed to establish communication to Key Manager; return code={2}.

Short Form

Failed to establish communication to key manager

Parameters

Label	CEF Label	Type	Usage
func	vds_func	Text	A function name
act	act	Text	Action being requested or performed
ecode	cn1	Numeric	An error code

Description

None

Logger VAD: Information

Message ID : VAD4641I

Severity

Information

Long Form

{0}: {1} Successful communication to Key Manager; time= {2}.

Short Form

Successful communication to key manager

Parameters

Label	CEF Label	Type	Usage
func	vds_func	Text	A function name
act	act	Text	Action being requested or performed
etime	end	Text	An end time stamp

Description

None

Logger VAD: Warnings

Message ID : VAD4643W

Severity

Warning

Long Form

{0}: {1}.

Short Form

Tag: Fault

Parameters

Label	CEF Label	Type	Usage
showStr	reason	Text	Code specifying reason for allowing access, if any
detail	vds_detail	Text	Fault detail

Description

None

Logger VMD: Errors

Message ID : VMD3203E

Severity

Error

Long Form

LDT: Live data transformation pause request from "{0}" failed

Short Form

LDT pause failed

Parameters

Label	CEF Label	Type	Usage
shost	shost	Text	Source host name

Description

None

Message ID : VMD3204E

Severity

Error

Long Form

LDT: Live data transformation resume request from "{0}" failed

Short Form

LDT resume failed

Parameters

Label	CEF Label	Type	Usage
shost	shost	Text	Source host name

Description

None

Message ID : VMD3503E

Severity

Error

Long Form

ReadBioPublicKey Bio_new failed {0}

Short Form

No short form is provided for this message type

Description

None

Message ID : VMD3507E

Severity

Error

Long Form

PEM_read_X509 failed

Message ID : VMD3503E

Short Form

No short form is provided for this message type

Description

None

Message ID : VMD3509E

Severity

Error

Long Form

X509_extract_key failed

Short Form

No short form is provided for this message type

Description

None

Message ID : VMD3507E

Message ID : VMD3510E

Severity

Error

Long Form

vm_generate_certificate: mkcert RSA_generate_key failed

Short Form

No short form is provided for this message type

Description

None

Message ID : VMD3514E

Severity

Error

Long Form

uname: bad machine name len {0}

Message ID : VMD3510E

Short Form

No short form is provided for this message type

Description

None

Message ID : VMD3517E

Severity

Error

Long Form

ReadBioPublicKey X509_extract_key failed {0}

Short Form

No short form is provided for this message type

Description

None

Message ID : VMD3514E

Message ID : VMD3520E

Severity

Error

Long Form

set process sid failed

Short Form

Set SID fail

Parameters

No parameters are provided for this message type

Description

None

Message ID : VMD3525E

Severity

Error

Message ID : VMD3520E

Long Form

ReadBioX509cert Bio_read_filename failed {0}

Short Form

No short form is provided for this message type

Description

None

Message ID : VMD3527E

Severity

Error

Long Form

PEM_read_PrivateKey {0} read

Short Form

No short form is provided for this message type

Message ID : VMD3525E

Description

None

Message ID : VMD3533E

Severity

Error

Long Form

ReadBioPublicKey failed

Short Form

No short form is provided for this message type

Description

None

Message ID : VMD3544E

Severity

Error

Message ID : VMD3527E

Long Form

The VMD failed to become a daemon.

Short Form

VMD daemonize fail

Parameters

No parameters are provided for this message type

Description

None

Message ID : VMD3546E

Severity

Error

Long Form

Can't get NIS domain: {0}

Message ID : VMD3544E

Short Form

No short form is provided for this message type

Description

None

Message ID : VMD3550E

Severity

Error

Long Form

ReadBioPrivateKey BIO_new failed {0}

Short Form

No short form is provided for this message type

Description

None

Message ID : VMD3546E

Message ID : VMD3559E

Severity

Error

Long Form

ReadBioPublicKey PEM_read_bio_X509 failed {0}

Short Form

No short form is provided for this message type

Description

None

Message ID : VMD3563E

Severity

Error

Long Form

File {0} open failed ({1})

Message ID : VMD3559E

Short Form

File open error

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file
ecode	cn1	Numeric	An error code

Description

None

Message ID : VMD3572E

Severity

Error

Long Form

ReadBioPrivateKey PEM_read_bio_RSAPrivateKey failed {0}

Message ID : VMD3563E

Short Form

No short form is provided for this message type

Description

None

Message ID : VMD3578E

Severity

Error

Long Form

WriteBioPublicKey PEM_write_bio_X509 failed {0}

Short Form

No short form is provided for this message type

Description

None

Message ID : VMD3572E

Message ID : VMD3581E

Severity

Error

Long Form

WriteBioPrivateKey PEM_write_bio_RSAPrivateKey failed {0}

Short Form

No short form is provided for this message type

Description

None

Message ID : VMD3596E

Severity

Error

Long Form

vm_generate_certificate: Error initializing openssl random number generator

Message ID : VMD3581E

Short Form

No short form is provided for this message type

Description

None

Message ID : VMD3597E

Severity

Error

Long Form

setmntent({0}, r) failed {1}({2})

Short Form

setmntent error

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file
showStr	reason	Text	Code specifying reason for allowing access, if any

Message ID : VMD3596E

Label	CEF Label	Type	Usage
ecode	cn1	Numeric	An error code

Description

None

Message ID : VMD3605E

Severity

Error

Long Form

sysinfo failed for uname errno {0} : {1}

Short Form

No short form is provided for this message type

Description

None

Message ID : VMD3597E

Message ID : VMD3607E

Severity

Error

Long Form

WriteBioPublicKey Bio_new failed {0}

Short Form

No short form is provided for this message type

Description

None

Message ID : VMD3611E

Severity

Error

Long Form

ReadBioPrivateKey BIO_read_filename failed {0}

Message ID : VMD3607E

Short Form

No short form is provided for this message type

Description

None

Message ID : VMD3612E

Severity

Error

Long Form

{0}: check_mount({1}, {2}) malloc({3}) failed {4}

Short Form

No memory

Parameters

No parameters are provided for this message type

Description

None

Message ID : VMD3616E

Severity

Error

Long Form

sysinfo failed for SI_HW_SERIAL errno[{0}][{1}]

Short Form

No short form is provided for this message type

Description

None

Message ID : VMD3617E

Severity

Error

Message ID : VMD3612E

Long Form

Failed to protect process {0}.

Short Form

Cannot protect process

Parameters

Label	CEF Label	Type	Usage
pid	dvcpid	Numeric	Numeric process ID

Description

None

Message ID : VMD3628E

Severity

Error

Long Form

WriteBioPrivateKey BIO_write_filename failed {0}

Message ID : VMD3617E

Short Form

No short form is provided for this message type

Description

None

Message ID : VMD3629E

Severity

Error

Long Form

WriteBioPublicKey BIO_write_filename failed {0}

Short Form

No short form is provided for this message type

Description

None

Message ID : VMD3628E

Message ID : VMD3633E

Severity

Error

Long Form

ReadBioX509cert PEM_read_bio_X509 failed {0}

Short Form

No short form is provided for this message type

Description

None

Message ID : VMD3644E

Severity

Error

Long Form

NIS get group error: {0}

Message ID : VMD3633E

Short Form

No short form is provided for this message type

Description

None

Message ID : VMD3645E

Severity

Error

Long Form

{0}: check_mount({1}, {2}) realloc({3}) failed {4}

Short Form

No memory

Parameters

No parameters are provided for this message type

Message ID : VMD3644E

Description

None

Message ID : VMD3651E

Severity

Error

Long Form

check_mount: mnttab open failed {0}

Short Form

Mnttab open error

Parameters

Label	CEF Label	Type	Usage
ecode	cn1	Numeric	An error code

Description

None

Message ID : VMD3645E

Message ID : VMD3655E

Severity

Error

Long Form

vm_generate_certificate: mkcert EVP_PKEY_new failed

Short Form

No short form is provided for this message type

Description

None

Message ID : VMD3665E

Severity

Error

Long Form

WriteBioPrivateKey BIO_new failed {0}

Message ID : VMD3655E

Short Form

No short form is provided for this message type

Description

None

Message ID : VMD3666E

Severity

Error

Long Form

ReadBioPrivateKey failed

Short Form

No short form is provided for this message type

Description

None

Message ID : VMD3665E

Message ID : VMD3667E

Severity

Error

Long Form

Error: can't load public key

Short Form

No short form is provided for this message type

Description

None

Message ID : VMD3674E

Severity

Error

Long Form

Failed to alloc mem for Host Key

Message ID : VMD3667E

Short Form

No short form is provided for this message type

Description

None

Message ID : VMD3676E

Severity

Error

Long Form

ReadBioX509cert Bio_new failed {0}

Short Form

No short form is provided for this message type

Description

None

Message ID : VMD3674E

Message ID : VMD3681E

Severity

Error

Long Form

Failed to open {0}

Short Form

No short form is provided for this message type

Description

None

Message ID : VMD3683E

Severity

Error

Long Form

TEST HOST key failed {0}

Message ID : VMD3681E

Short Form

No short form is provided for this message type

Description

None

Message ID : VMD3685E

Severity

Error

Long Form

ReadPrivateKey failed

Short Form

No short form is provided for this message type

Description

None

Message ID : VMD3683E

Message ID : VMD3686E

Severity

Error

Long Form

SET machine id failed {0}

Short Form

No short form is provided for this message type

Description

None

Message ID : VMD3689E

Severity

Error

Long Form

X509 certificate file {0} open failed

Message ID : VMD3686E

Short Form

No short form is provided for this message type

Description

None

Message ID : VMD3697E

Severity

Error

Long Form

vm_generate_certificate: mkcert failed

Short Form

No short form is provided for this message type

Description

None

Message ID : VMD3689E

Message ID : VMD3700E

Severity

Error

Long Form

Unable to create or write to file {0} as part of a policy update. Error code {1}.

Short Form

Policy update error

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file
ecode	cn1	Numeric	An error code

Description

Verify that the secfsd process is running; if not, restart it. If sesfsd is running, please call Thales support for assistance.

Message ID : VMD3702E

Severity

Error

Long Form

NIS get passwd error: {0}

Short Form

No short form is provided for this message type

Description

None

Message ID : VMD3707E

Severity

Error

Long Form

vm_generate_certificate: mkcert EVP_PKEY_assign_RSA failed

Short Form

No short form is provided for this message type

Description

None

Message ID : VMD3713E

Severity

Error

Long Form

vm_get_pubkey_from_file: Read key file {0} failed

Short Form

No short form is provided for this message type

Description

None

Message ID : VMD3707E

Message ID : VMD3718E

Severity

Error

Long Form

vm_get_privkey_from_file: Read key file {0} failed

Short Form

No short form is provided for this message type

Description

None

Message ID : VMD3723E

Severity

Error

Long Form

ReadBioPublicKey Bio_read_filename failed {0}

Message ID : VMD3718E

Short Form

No short form is provided for this message type

Description

None

Message ID : VMD3724E

Severity

Error

Long Form

Private Key file {0} open failed

Short Form

No short form is provided for this message type

Description

None

Message ID : VMD3723E

Message ID : VMD3726E

Severity

Error

Long Form

mount_sec: {0} mount failed {1}

Short Form

No short form is provided for this message type

Description

None

Message ID : VMD3730E

Severity

Error

Long Form

sysinfo: failed for SI_HW_SERIAL.

Short Form

No short form is provided for this message type

Description

None

Message ID : VMD3734E

Severity

Error

Long Form

sysinfo failed for SI_SYSNAME errno {0}

Short Form

No short form is provided for this message type

Description

None

Message ID : VMD3730E

Message ID : VMD3736E

Severity

Error

Long Form

hpux_sysinfo: invalid buffer length

Short Form

No short form is provided for this message type

Description

None

Message ID : VMD3747E

Severity

Error

Long Form

can not write to file={0}

Short Form

No short form is provided for this message type

Description

None

Message ID : VMD3748E

Severity

Error

Long Form

Failed to read Host Private Key from file {0}

Short Form

No short form is provided for this message type

Description

None

Message ID : VMD3747E

Message ID : VMD3750E

Severity

Error

Long Form

uname failed! errno[{0}][{1}]

Short Form

No short form is provided for this message type

Description

None

Message ID : VMD3758E

Severity

Error

Long Form

{0}: {1}

Short Form

No short form is provided for this message type

Description

None

Message ID : VMD3759E

Severity

Error

Long Form

write() ssl error {0}

Short Form

No short form is provided for this message type

Description

None

Message ID : VMD3758E

Message ID : VMD3760E

Severity

Error

Long Form

Server does not support required soap operation: {0}

Short Form

No short form is provided for this message type

Description

None

Message ID : VMD3761E

Severity

Error

Long Form

The server name could not be converted to an IP address. Service will restart.

Message ID : VMD3760E

Short Form

Cannot get server IP

Parameters

No parameters are provided for this message type

Description

None

Message ID : VMD3779E

Severity

Error

Long Form

Unable to create a signature for file {0}; error code {1}.

Short Form

Sig creation error

Message ID : VMD3761E

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file
ecode	cn1	Numeric	An error code

Description

None

Message ID : VMD3780E

Severity

Error

Long Form

Unable to encrypt file {0} with the session key; error code {1}.

Short Form

File encrypt error

Message ID : VMD3779E

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file
ecode	cn1	Numeric	An error code

Description

None

Message ID : VMD3782E

Severity

Error

Long Form

A new security configuration was received, but we failed to implement it. The current security configuration will continue to be used.

Short Form

Config update fail

Message ID : VMD3780E

Parameters

No parameters are provided for this message type

Description

An error occurred while attempting to process a policy push from a key manager. Details of the failure were logged in the preceding message.

Message ID : VMD3784E

Severity

Error

Long Form

Secfs component failed to provide initialization information to VMD.

Short Form

No config from secfs

Parameters

No parameters are provided for this message type

Message ID : VMD3782E

Description

None

Message ID : VMD3786E

Severity

Error

Long Form

Host file browsing for {0} failed.

Short Form

Host browse fail

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : VMD3784E

Message ID : VMD3787E

Severity

Error

Long Form

Unable to get status from secfs component. Error code {0}.

Short Form

Secfs config fetch error

Parameters

Label	CEF Label	Type	Usage
ecode	cn1	Numeric	An error code

Description

None

Message ID : VMD3788E

Severity

Error

Long Form

Unable to send data to secfs component. Error code {0}.

Short Form

Kernel config send error

Parameters

Label	CEF Label	Type	Usage
ecode	cn1	Numeric	An error code

Description

None

Message ID : VMD3789E

Severity

Error

Message ID : VMD3788E

Long Form

Unable to receive data from secfs component. Error code {0}.

Short Form

No short form is provided for this message type

Description

None

Message ID : VMD3790E

Severity

Error

Long Form

Secfs component did not confirm host-delete operation.

Short Form

No host-delete ACK

Parameters

No parameters are provided for this message type

Description

None

Message ID : VMD3792E

Severity

Error

Long Form

Unable to write authorized file information to disk. Error code {0}.

Short Form

Write auth file error

Parameters

Label	CEF Label	Type	Usage
ecode	cn1	Numeric	An error code

Message ID : VMD3790E

Description

None

Message ID : VMD3795E

Severity

Error

Long Form

Query security config failed.

Short Form

Query config fail

Parameters

No parameters are provided for this message type

Description

None

Message ID : VMD3792E

Message ID : VMD3796E

Severity

Error

Long Form

Secfs component reports failure on host-delete operation.

Short Form

Host delete fail

Parameters

No parameters are provided for this message type

Description

None

Message ID : VMD3799E

Severity

Error

Long Form

Delete host operation failed.

Short Form

No short form is provided for this message type

Description

None

Message ID : VMD3801E

Severity

Error

Long Form

Cannot update service status. Error = {0}

Short Form

Service update error

Parameters

Label	CEF Label	Type	Usage
ecode	cn1	Numeric	An error code

Description

None

Message ID : VMD3802E

Severity

Error

Long Form

Cannot set service status to stopped. Error = {0}

Short Form

Service stop error

Parameters

Label	CEF Label	Type	Usage
ecode	cn1	Numeric	An error code

Message ID : VMD3801E

Description

None

Message ID : VMD3807E

Severity

Error

Long Form

Cannot register service handler. Error = {0}

Short Form

Register server error

Parameters

Label	CEF Label	Type	Usage
ecode	cn1	Numeric	An error code

Description

None

Message ID : VMD3802E

Message ID : VMD3809E

Severity

Error

Long Form

Cannot start service dispatcher. Error = {0}

Short Form

Start service error

Parameters

Label	CEF Label	Type	Usage
ecode	cn1	Numeric	An error code

Description

None

Message ID : VMD3811E

Severity

Error

Long Form

User {0} in domain {1} failed to connect to network path {2}. Error code {3}.

Short Form

Net connect error

Parameters

Label	CEF Label	Type	Usage
user	suser	Text	User name
domain	dntdom	Text	A domain name (policy, network, users, etc)
url	request	Text	A uniform resource location
ecode	cn1	Numeric	An error code

Description

None

Message ID : VMD3812E

Severity

Error

Long Form

Failed to enumerate network path {0}. Error code {1}.

Short Form

Net enumeration error

Parameters

Label	CEF Label	Type	Usage
url	request	Text	A uniform resource location
ecode	cn1	Numeric	An error code

Description

None

Message ID : VMD3816E

Severity

Error

Long Form

Failed to initialize the signature request {0}

Short Form

Init sig req fail

Parameters

Label	CEF Label	Type	Usage
showStr	reason	Text	Code specifying reason for allowing access, if any

Description

None

Message ID : VMD3819E

Severity

Error

Long Form

Failed to generate the file list for the signature request {0}

Short Form

Sig file list fail

Parameters

Label	CEF Label	Type	Usage
showStr	reason	Text	Code specifying reason for allowing access, if any

Description

None

Message ID : VMD3822E

Severity

Error

Message ID : VMD3819E

Long Form

Failed to generate the signatures for the signature request {0}

Short Form

Sig gen fail

Parameters

Label	CEF Label	Type	Usage
showStr	reason	Text	Code specifying reason for allowing access, if any

Description

None

Message ID : VMD3828E

Severity

Error

Long Form

Failed the signature request {0}

Message ID : VMD3822E

Short Form

Sig req fail

Parameters

Label	CEF Label	Type	Usage
showStr	reason	Text	Code specifying reason for allowing access, if any

Description

None

Message ID : VMD3830E

Severity

Error

Long Form

Failed to read the file list for the signature request {0}, error code {1}

Short Form

Sig file list read error

Message ID : VMD3828E

Parameters

Label	CEF Label	Type	Usage
showStr	reason	Text	Code specifying reason for allowing access, if any
ecode	cn1	Numeric	An error code

Description

None

Message ID : VMD3831E

Severity

Error

Long Form

Failed to write the file list for the signature request {0}, error code {1}

Short Form

Sig file list write error

Message ID : VMD3830E

Parameters

Label	CEF Label	Type	Usage
showStr	reason	Text	Code specifying reason for allowing access, if any
ecode	cn1	Numeric	An error code

Description

None

Message ID : VMD3833E

Severity

Error

Long Form

Failed to create the signature disk object

Short Form

Create sig disk object fail

Message ID : VMD3831E

Parameters

No parameters are provided for this message type

Description

None

Message ID : VMD3834E

Severity

Error

Long Form

Failed to add the signature {0} and name {1} into the signature disk object

Short Form

Add sig object error

Parameters

Label	CEF Label	Type	Usage
hex	vds_hex	Text	A hex string (e.g. a signature)
filePath	filePath	Text	Full path to file

Message ID : VMD3833E

Description

None

Message ID : VMD3835E

Severity

Error

Long Form

Failed to write the signature disk file

Short Form

Write sig object fail

Parameters

No parameters are provided for this message type

Description

None

Message ID : VMD3834E

Message ID : VMD3837E

Severity

Error

Long Form

Failed to write the signature disk file header

Short Form

Sig write header fail

Parameters

No parameters are provided for this message type

Description

None

Message ID : VMD3838E

Severity

Error

Message ID : VMD3837E

Long Form

Failed to read the signature disk file header

Short Form

Sig read hreader fail

Parameters

No parameters are provided for this message type

Description

None

Message ID : VMD3840E

Severity

Error

Long Form

Failed to push a new signature database

Message ID : VMD3838E

Short Form

Sig push to secfs fail

Parameters

No parameters are provided for this message type

Description

None

Message ID : VMD3843E

Severity

Error

Long Form

User browsing for {0} failed.

Short Form

User browse fail

Message ID : VMD3840E

Parameters

Label	CEF Label	Type	Usage
domain	dntdom	Text	A domain name (policy, network, users, etc)

Description

None

Message ID : VMD3844E

Severity

Error

Long Form

Failed to bind to {0}. Error code {1}.

Short Form

Domain bind error

Parameters

Label	CEF Label	Type	Usage
domain	dntdom	Text	A domain name (policy, network, users, etc)

Message ID : VMD3843E

Label	CEF Label	Type	Usage
ecode	cn1	Numeric	An error code

Description

None

Message ID : VMD3845E

Severity

Error

Long Form

Failed to query the domain {0} by {1}. Error {2}: {3}.

Short Form

NIS query error

Parameters

Label	CEF Label	Type	Usage
domain	dntdom	Text	A domain name (policy, network, users, etc)
effect	vds_effect	Text	Policy effect

Message ID : VMD3844E

Label	CEF Label	Type	Usage
ecode	cn1	Numeric	An error code
showStr	reason	Text	Code specifying reason for allowing access, if any

Description

None

Message ID : VMD3846E

Severity

Error

Long Form

Failed to query the group {0} in the domain {1} by {2}. Error {3}: {4}.

Short Form

NIS group query error

Parameters

Label	CEF Label	Type	Usage
group	vds_group	Text	Group name

Message ID : VMD3845E

Label	CEF Label	Type	Usage
domain	dntdom	Text	A domain name (policy, network, users, etc)
effect	vds_effect	Text	Policy effect
ecode	cn1	Numeric	An error code
showStr	reason	Text	Code specifying reason for allowing access, if any

Description

None

Message ID : VMD3848E

Severity

Error

Long Form

Domain browsing failed.

Short Form

Domain browse fail

Message ID : VMD3846E

Parameters

No parameters are provided for this message type

Description

None

Message ID : VMD3849E

Severity

Error

Long Form

Error getting common name: {0}

Short Form

Cannot determine common name

Parameters

Label	CEF Label	Type	Usage
showStr	reason	Text	Code specifying reason for allowing access, if any

Message ID : VMD3848E

Description

None

Message ID : VMD3855E

Severity

Error

Long Form

Failed to send {0} signatures for the signature request {1} to the Key Manager

Short Form

Send sigs error

Parameters

Label	CEF Label	Type	Usage
nsig	vds_nsig	Numeric	The number of signatures generated
showStr	reason	Text	Code specifying reason for allowing access, if any

Message ID : VMD3849E

Description

None

Message ID : VMD3858E

Severity

Error

Long Form

The Secfs component was unable to implement the new security configuration

Short Form

New config to Secfs fail

Parameters

No parameters are provided for this message type

Description

An error occurred while attempting to apply a policy push from a key manager.

Message ID : VMD3855E

Message ID : VMD3864E

Severity

Error

Long Form

Unable to parse LDAP URL {0} - error "{1}"

Short Form

Bad LDAP url

Parameters

Label	CEF Label	Type	Usage
url	request	Text	A uniform resource location
showStr	reason	Text	Code specifying reason for allowing access, if any

Description

None

Message ID : VMD3865E

Severity

Error

Long Form

Unable to query LDAP server {0} - error "{1}"

Short Form

Bad LADP server

Parameters

Label	CEF Label	Type	Usage
url	request	Text	A uniform resource location
showStr	reason	Text	Code specifying reason for allowing access, if any

Description

None

Message ID : VMD3866E

Severity

Error

Long Form

Invalid LDAP posixAccount data returned

Short Form

Invalid LDAP account

Parameters

No parameters are provided for this message type

Description

None

Message ID : VMD3867E

Severity

Error

Message ID : VMD3866E

Long Form

Invalid LDAP posixGroup data returned

Short Form

Invalid LDAP group

Parameters

No parameters are provided for this message type

Description

None

Message ID : VMD3872E

Severity

Error

Long Form

Internal error: bad arguments to secfs component

Message ID : VMD3867E

Short Form

Bad args to Secfs

Parameters

No parameters are provided for this message type

Description

An internal error occurred. Please contact Thales Support

Message ID : VMD3873E

Severity

Error

Long Form

Internal error: the secfs component does not believe it's talking to the correct VMD

Short Form

Secfs rejecting VMD

Message ID : VMD3872E

Parameters

No parameters are provided for this message type

Description

None

Message ID : VMD3874E

Severity

Error

Long Form

The secfs component is unable to read its private key

Short Form

Secfs priv key fail

Parameters

No parameters are provided for this message type

Message ID : VMD3873E

Description

None

Message ID : VMD3875E

Severity

Error

Long Form

The secfs component unable to obtain its PWD

Short Form

Secfs passwd fail

Parameters

No parameters are provided for this message type

Description

None

Message ID : VMD3874E

Message ID : VMD3876E

Severity

Error

Long Form

The secfs component contains an invalid PWD

Short Form

Secfs passwd bad

Parameters

No parameters are provided for this message type

Description

None

Message ID : VMD3877E

Severity

Error

Long Form

The secfs component was unable to extract the key-encrypting-key

Short Form

Secfs key extract fail

Parameters

No parameters are provided for this message type

Description

None

Message ID : VMD3878E

Severity

Error

Long Form

The secfs component failed to pass internal sanity checks around the key-encrypting-key

Message ID : VMD3877E

Short Form

Secfs key sanity fail

Parameters

No parameters are provided for this message type

Description

None

Message ID : VMD3879E

Severity

Error

Long Form

The secfs component was able to perform all of the crypto operations around the policy push, but was unable to actually apply the new policy configuration

Short Form

Secfs policy apply fail

Message ID : VMD3878E

Parameters

No parameters are provided for this message type

Description

None

Message ID : VMD3888E

Severity

Error

Long Form

Unable to replicate coherent guardpoint info - {0}

Short Form

Unable to replicate coherent GuardPoint info -

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	GuardPoint base directory

Message ID : VMD3879E

Description

None

Message ID : VMD3890E

Severity

Error

Long Form

Unable to commit configuration to GPFS cluster

Short Form

Unable to commit configuration to GPFS cluster

Parameters

No parameters are provided for this message type

Description

None

Message ID : VMD3888E

Message ID : VMD3891E

Severity

Error

Long Form

Non-clustered GP {0} not allowed on clustered filesystem

Short Form

Non-clustered GP not allowed on clustered filesystem

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	GuardPoint base directory

Description

None

Message ID : VMD3892E

Severity

Error

Long Form

Clustered GP {0} not allowed on non-clustered filesystem

Short Form

Clustered GP not allowed on non-clustered filesystem

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	GuardPoint base directory

Description

None

Message ID : VMD3901E

Severity

Error

Message ID : VMD3892E

Long Form

Docker host browsing failed.

Short Form

Docker host browse fail

Parameters

No parameters are provided for this message type

Description

None

Message ID : VMD3903E

Severity

Error

Long Form

Docker host browsing for image {0} failed.

Message ID : VMD3901E

Short Form

Docker host browse fail

Parameters

Label	Type	Usage
dockerid	Text	Docker image or container id

Description

None

Message ID : VMD3905E

Severity

Error

Long Form

Docker image {0} file browsing for {1} failed.

Short Form

Docker image file browse fail

Message ID : VMD3903E

Parameters

Label	CEF Label	Type	Usage
dockerid	dockerid	Text	Docker image or container id
filePath	filePath	Text	Full path to file

Description

None

Message ID : VMD3907E

Severity

Error

Long Form

Docker container {0} file browsing for {1} succeeded.

Short Form

Docker container file browse fail

Message ID : VMD3905E

Parameters

Label	CEF Label	Type	Usage
dockerid	dockerid	Text	Docker image or container id
filePath	filePath	Text	Full path to file

Description

None

Message ID : VMD3909E

Severity

Error

Long Form

User browsing for image {0} with {1} failed.

Short Form

Docker image user browse fail

Message ID : VMD3907E

Parameters

Label	CEF Label	Type	Usage
dockerid	dockerid	Text	Docker image or container id
domain	dntdom	Text	A domain name (policy, network, users, etc)

Description

None

Message ID : VMD3911E

Severity

Error

Long Form

User browsing for container {0} with {1} failed.

Short Form

Docker container user browse fail

Message ID : VMD3909E

Parameters

Label	CEF Label	Type	Usage
dockerid	dockerid	Text	Docker image or container id
domain	dntdom	Text	A domain name (policy, network, users, etc)

Description

None

Message ID : VMD3913E

Severity

Error

Long Form

Domain browsing for image {0} failed.

Short Form

Docker image domain browse fail

Message ID : VMD3911E

Parameters

Label	Type	Usage
dockerid	Text	Docker image or container id

Description

None

Message ID : VMD3915E

Severity

Error

Long Form

Domain browsing for container {0} failed.

Short Form

Docker container domain browse fail

Parameters

Label	Type	Usage
dockerid	Text	Docker image or container id

Message ID : VMD3913E

Description

None

Message ID : VMD3916E

Severity

Error

Long Form

The current docker version "{0} {1}" is not supported.

Short Form

No short form is provided for this message type

Description

None

Message ID : VMD3917E

Severity

Error

Message ID : VMD3915E

Long Form

Failed to connect to the Docker service at {0}. Please make sure the Docker service is up.

Short Form

Failed to connect to Docker

Parameters

Label	CEF Label	Type	Usage
url	request	Text	A uniform resource location

Description

None

Message ID : VMD3918E

Severity

Error

Long Form

An unauthorized attempt to update the authentication signature for file {0} has been prevented

Message ID : VMD3917E

Short Form

Unauthorized signature change

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : VMD3922E

Severity

Error

Long Form

Internal error: unable to determine {0}.

Short Form

Unable to determine

Message ID : VMD3918E

Parameters

Label	CEF Label	Type	Usage
showStr	reason	Text	Code specifying reason for allowing access, if any

Description

None

Message ID : VMD3923E

Severity

Error

Long Form

Error from data governance module: {0}

Short Form

DG error

Parameters

No parameters are provided for this message type

Message ID : VMD3922E

Description

None

Message ID : VMD3927E

Severity

Error

Long Form

An error occurred during certificate renewal: re-registration may be required

Short Form

Cert recovery failed

Parameters

No parameters are provided for this message type

Description

None

Message ID : VMD3923E

Message ID : VMD3929E

Severity

Error

Long Form

Key manager failed to update CA certificate: {0}

Short Form

CA update failed

Parameters

Label	CEF Label	Type	Usage
showStr	reason	Text	Code specifying reason for allowing access, if any

Description

None

Message ID : VMD3932E

Severity

Error

Long Form

The CTE client has failed attestation checks.

Short Form

No short form is provided for this message type

Description

None

Message ID : VMD4245E

Severity

Error

Long Form

Key conversion failure when attempting to upgrade to fips-approved private key file format.

Message ID : VMD3932E

Short Form

Key conv fail

Parameters

No parameters are provided for this message type

Description

None

Message ID : VMD4594E

Severity

Error

Long Form

Failed to strengthen priority of the vmd, may face scheduling problems

Short Form

Cannot raise priority

Message ID : VMD4245E

Parameters

No parameters are provided for this message type

Description

None

Message ID : VMD4606E

Severity

Error

Long Form

vm_read_file: fstat failed {0}

Short Form

Stat error

Parameters

Label	CEF Label	Type	Usage
ecode	cn1	Numeric	An error code

Message ID : VMD4594E

Description

None

Message ID : VMD4607E

Severity

Error

Long Form

vm_read_file: fopen failed for {0} errno {1}

Short Form

Open error

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file
ecode	cn1	Numeric	An error code

Description

None

Message ID : VMD4608E

Severity

Error

Long Form

vm_read_file: malloc for size {0} failed {1}

Short Form

Out of memory

Parameters

Label	CEF Label	Type	Usage
slen	in	Numeric	Input byte count or length
ecode	cn1	Numeric	An error code

Message ID : VMD4607E

Description

None

Message ID : VMD4609E

Severity

Error

Long Form

vm_read_file: read() failed for {0}

Short Form

Read error

Parameters

Label	CEF Label	Type	Usage
ecode	cn1	Numeric	An error code

Description

None

Message ID : VMD4608E

1000

Message ID : VMD4610E

Severity

Error

Long Form

vm_write_file: fopen failed for {0} mode {1} errno {2}

Short Form

File open error

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file
mode	vds_mode	Text	File open mode
ecode	cn1	Numeric	An error code

Description

None

Message ID : VMD4612E

Severity

Error

Long Form

vm_write_file: fwrite() failed error {0}

Short Form

Write error

Parameters

Label	CEF Label	Type	Usage
ecode	cn1	Numeric	An error code

Description

None

Message ID : VMD4617E

Severity

Error

Long Form

The previous message {0} was repeated {1} times

Short Form

Repeat message

Parameters

Label	CEF Label	Type	Usage
msgid	vds_msgid	Text	A unique log message identifier
count	vds_count	Numeric	A generic count value

Description

None

Logger VMD: Fatal errors

Message ID : VMD3767F

Severity

Fatal error

Long Form

No attribute {0} was found in the configuration file located at {1}. Please supply this attribute or re-install the product and try again.

Short Form

Attribute missing

Parameters

Label	CEF Label	Type	Usage
showStr	reason	Text	Code specifying reason for allowing access, if any
filePath	filePath	Text	Full path to file

Description

None

Message ID : VMD3768F

Severity

Fatal error

Long Form

Unable to parse the URL {0}. This attribute is located in the config file at {1}. Please fix the URL or re-install this product.

Short Form

Bad URL in config file

Parameters

Label	CEF Label	Type	Usage
url	request	Text	A uniform resource location
filePath	filePath	Text	Full path to file

Description

None

Message ID : VMD3769F

Severity

Fatal error

Long Form

Internal error: unable to set attribute {0}.

Short Form

Bad attribute

Parameters

Label	CEF Label	Type	Usage
showStr	reason	Text	Code specifying reason for allowing access, if any

Description

None

Message ID : VMD3770F

Severity

Fatal error

Long Form

The VMD failed to establish a communication channel to the Key Manager.

Short Form

Cannot contact server

Parameters

No parameters are provided for this message type

Description

The agent is unable to reach the key manager. You may see any of the following error messages: COM4583F, COM4633W, VMD3770F, VMD3885I or VMD3886I. You may experience any of the following:

1. Connection to the key manager is down.
2. The VMD Host has been deleted from the key manager.
3. The host does not have "Communication Enabled" in the key manager UI.
4. The VMD's host may be deleted from the key manager. Run the register_host utility to re-register the VMD with the key manager.

Message ID : VMD3771F

Severity

Fatal error

Long Form

Logging setup failure. Error code {0}; "{1}"

Short Form

Log setup error

Parameters

Label	CEF Label	Type	Usage
ecode	cn1	Numeric	An error code
showStr	reason	Text	Code specifying reason for allowing access, if any

Description

None

Message ID : VMD3772F

Severity

Fatal error

Long Form

Logging setup failure: VMD logger information not found in Key Manager response.

Short Form

Missing logger info

Parameters

No parameters are provided for this message type

Description

None

Message ID : VMD3797F

Severity

Fatal error

Message ID : VMD3772F

Long Form

The VMD is unable to listen for requests from the Key Manager. Shutting down.

Short Form

Cannot list for server req.

Parameters

No parameters are provided for this message type

Description

None

Message ID : VMD3894F

Severity

Fatal error

Long Form

The server does not support required oneway communications.

Message ID : VMD3797F

Short Form

No short form is provided for this message type

Description

None

Message ID : VMD4595F

Severity

Fatal error

Long Form

The agent could not allocate enough memory. Contact support.

Short Form

Out of memory

Parameters

No parameters are provided for this message type

Message ID : VMD3894F

Description

None

Message ID : VMD4616F

Severity

Fatal error

Long Form

The previous message {0} was repeated {1} times

Short Form

Repeat message

Parameters

Label	CEF Label	Type	Usage
msgid	vds_msgid	Text	A unique log message identifier
count	vds_count	Numeric	A generic count value

Message ID : VMD4595F

Description

None

Logger VMD: Information

Message ID : VMD3201I

Severity

Information

Long Form

LDT: Live data transformation has been paused by "{0}"

Short Form

LDT paused

Parameters

Label	CEF Label	Type	Usage
shost	shost	Text	Source host name

Description

None

Message ID : VMD3202I

Severity

Information

Long Form

LDT: Live data transformation has been resumed by "{0}"

Short Form

LDT resumed

Parameters

Label	CEF Label	Type	Usage
shost	shost	Text	Source host name

Description

None

Message ID : VMD3548I

Severity

Information

Long Form

RSA key verification Failed

Short Form

No short form is provided for this message type

Description

None

Message ID : VMD3558I

Severity

Information

Long Form

RSA key verified

Message ID : VMD3548I

Short Form

No short form is provided for this message type

Description

None

Message ID : VMD3626I

Severity

Information

Long Form

{0} is MOUNTED

Short Form

Mount success

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Message ID : VMD3558I

Description

None

Message ID : VMD3640I

Severity

Information

Long Form

STARTED on {0} PORT {1} VERSION: {2}

Short Form

VMD Startup

Parameters

Label	CEF Label	Type	Usage
osname	cs2	Text	A name identifying the agent operating system
port	spt	Numeric	A socket port number
version	vds_version	Text	Software version string

Message ID : VMD3626I

Description

None

Message ID : VMD3663I

Severity

Information

Long Form

{0} is not mounted

Short Form

Mount fail

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : VMD3640I

Message ID : VMD3773I

Severity

Information

Long Form

The {0} is starting. It was invoked at the command line like this: "{1}"

Short Form

VMD startup

Parameters

Label	CEF Label	Type	Usage
agent	deviceProcessName	Text	The short identifier of the agent software
showStr	reason	Text	Code specifying reason for allowing access, if any

Description

None

Message ID : VMD3778I

Severity

Information

Long Form

The VMD is shutting down.

Short Form

VMD shutdown

Parameters

No parameters are provided for this message type

Description

None

Message ID : VMD3781I

Severity

Information

Message ID : VMD3778I

Long Form

Successfully received and implemented a new security configuration.

Short Form

New Config OK

Parameters

No parameters are provided for this message type

Description

None

Message ID : VMD3785I

Severity

Information

Long Form

Host file browsing for {0} succeeded.

Message ID : VMD3781I

Short Form

Host browse OK

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : VMD3794I

Severity

Information

Long Form

Query security config succeeded.

Short Form

Query config OK

Message ID : VMD3785I

Parameters

No parameters are provided for this message type

Description

None

Message ID : VMD3798I

Severity

Information

Long Form

Delete host operation succeeded.

Short Form

Host delete OK

Parameters

No parameters are provided for this message type

Message ID : VMD3794I

Description

None

Message ID : VMD3800I

Severity

Information

Long Form

RESTARTED SDK Server at PORT {0}.

Short Form

SDK server restart

Parameters

Label	CEF Label	Type	Usage
port	spt	Numeric	A socket port number

Description

None

Message ID : VMD3798I

Message ID : VMD3803I

Severity

Information

Long Form

Shutting down file system service.

Short Form

Service stop

Parameters

No parameters are provided for this message type

Description

None

Message ID : VMD3804I

Severity

Information

Long Form

Stopping file system service...

Short Form

Service shutdown

Parameters

No parameters are provided for this message type

Description

None

Message ID : VMD3814I

Severity

Information

Long Form

Initializing the signature request {0}

Message ID : VMD3804I

Short Form

Init sig req start

Parameters

Label	CEF Label	Type	Usage
showStr	reason	Text	Code specifying reason for allowing access, if any

Description

None

Message ID : VMD3815I

Severity

Information

Long Form

Finished initializing the signature request {0}

Short Form

Init sig req end

Message ID : VMD3814I

Parameters

Label	CEF Label	Type	Usage
showStr	reason	Text	Code specifying reason for allowing access, if any

Description

None

Message ID : VMD3817I

Severity

Information

Long Form

Generating the file list for the signature request {0}

Short Form

Gen sig file list

Parameters

Label	CEF Label	Type	Usage
showStr	reason	Text	Code specifying reason for allowing access, if any

Message ID : VMD3815I

Description

None

Message ID : VMD3818I

Severity

Information

Long Form

Finished generating the file list for the signature request {0}. Number of files in the list: {1}

Short Form

Sig file list complete

Parameters

Label	CEF Label	Type	Usage
showStr	reason	Text	Code specifying reason for allowing access, if any
nfile	vds_nfile	Numeric	The number of files processed

Message ID : VMD3817I

Description

None

Message ID : VMD3820I

Severity

Information

Long Form

Generating the signatures for the signature request {0}

Short Form

Generating sigs

Parameters

Label	CEF Label	Type	Usage
showStr	reason	Text	Code specifying reason for allowing access, if any

Description

None

Message ID : VMD3818I

Message ID : VMD3821I

Severity

Information

Long Form

Finished generating the signatures for the signature request {0}. Number of processed files: {1}. Number of generated signatures: {2}. Number of failed files: {3}

Short Form

Generated sigs

Parameters

Label	CEF Label	Type	Usage
showStr	reason	Text	Code specifying reason for allowing access, if any
nfile	vds_nfile	Numeric	The number of files processed
nsig	vds_nsig	Numeric	The number of signatures generated
nerror	vds_nerror	Numeric	The number of errors encountered

Description

None

Message ID : VMD3823I

Severity

Information

Long Form

Failed to get the file attributes for {0}, error code {1}, error message: {2}

Short Form

Sig file attr error

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file
ecode	cn1	Numeric	An error code
showStr	reason	Text	Code specifying reason for allowing access, if any

Message ID : VMD3821I

Description

None

Message ID : VMD3825I

Severity

Information

Long Form

Generating the signatures for the signature request {0}, {1} out of {2} files have been processed

Short Form

Sig progress

Parameters

Label	CEF Label	Type	Usage
showStr	reason	Text	Code specifying reason for allowing access, if any
nsig	vds_nsig	Numeric	The number of signatures generated
nfile	vds_nfile	Numeric	The number of files processed

Message ID : VMD3823I

Description

None

Message ID : VMD3827I

Severity

Information

Long Form

Completed the signature request {0} successfully

Short Form

Sig sig req done

Parameters

Label	CEF Label	Type	Usage
showStr	reason	Text	Code specifying reason for allowing access, if any

Description

None

Message ID : VMD3825I

Message ID : VMD3829I

Severity

Information

Long Form

Canceled the signature request {0}

Short Form

Sig req cancelled

Parameters

Label	CEF Label	Type	Usage
showStr	reason	Text	Code specifying reason for allowing access, if any

Description

None

Message ID : VMD3832I

Severity

Information

Long Form

Generating the file list for the signature request {0}, {1} files have been written to the list

Short Form

Sig file generation in progress

Parameters

Label	CEF Label	Type	Usage
showStr	reason	Text	Code specifying reason for allowing access, if any
nfile	vds_nfile	Numeric	The number of files processed

Description

None

Message ID : VMD3836I

Severity

Information

Long Form

Finished writing the signature disk file

Short Form

Sig write complete

Parameters

No parameters are provided for this message type

Description

None

Message ID : VMD3839I

Severity

Information

Message ID : VMD3836I

Long Form

Finished pushing a new signature database

Short Form

Sig push to secfs OK

Parameters

No parameters are provided for this message type

Description

None

Message ID : VMD3841I

Severity

Information

Long Form

opendir failed for {0} for the signature request {1}, error code {2}

Message ID : VMD3839I

Short Form

Sig opendir error

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file
showStr	reason	Text	Code specifying reason for allowing access, if any
ecode	cn1	Numeric	An error code

Description

None

Message ID : VMD3842I

Severity

Information

Long Form

User browsing for {0} succeeded.

Message ID : VMD3841I

1040

Short Form

User browse OK

Parameters

Label	CEF Label	Type	Usage
domain	dntdom	Text	A domain name (policy, network, users, etc)

Description

None

Message ID : VMD3847I

Severity

Information

Long Form

Domain browsing succeeded.

Short Form

Domain browse OK

Message ID : VMD3842I

Parameters

No parameters are provided for this message type

Description

None

Message ID : VMD3851I

Severity

Information

Long Form

Canceling the signature request {0}

Short Form

Sig req cancelled

Parameters

Label	CEF Label	Type	Usage
showStr	reason	Text	Code specifying reason for allowing access, if any

Message ID : VMD3847I

Description

None

Message ID : VMD3852I

Severity

Information

Long Form

Querying the status of the signature request {0}

Short Form

Sig req status query

Parameters

Label	CEF Label	Type	Usage
showStr	reason	Text	Code specifying reason for allowing access, if any

Description

None

Message ID : VMD3851I

Message ID : VMD3853I

Severity

Information

Long Form

Sending {0} signatures for the signature request {1} to the Key Manager

Short Form

Sending sigs

Parameters

Label	CEF Label	Type	Usage
nsig	vds_nsig	Numeric	The number of signatures generated
showStr	reason	Text	Code specifying reason for allowing access, if any

Description

None

Message ID : VMD3854I

Severity

Information

Long Form

{0} signatures of the signature request {1} have been sent to the Key Manager

Short Form

Sent sigs

Parameters

Label	CEF Label	Type	Usage
nsig	vds_nsig	Numeric	The number of signatures generated
showStr	reason	Text	Code specifying reason for allowing access, if any

Description

None

Message ID : VMD3856I

Severity

Information

Long Form

The Key Manager canceled the signature data push

Short Form

Send sigs cancelled

Parameters

No parameters are provided for this message type

Description

None

Message ID : VMD3857I

Severity

Information

Message ID : VMD3856I

Long Form

Got the signature data push from the Key Manager. Number of signatures in the push: {0}. Total number of signatures from the Key Manager: {1}

Short Form

Sig push from server

Parameters

Label	CEF Label	Type	Usage
nsig	vds_nsig	Numeric	The number of signatures generated
nfile	vds_nfile	Numeric	The number of files processed

Description

None

Message ID : VMD3859I

Severity

Information

Message ID : VMD3857I

1047

Long Form

Completed the signature request {0} with some failed files

Short Form

Sig reg partially done

Parameters

Label	CEF Label	Type	Usage
showStr	reason	Text	Code specifying reason for allowing access, if any

Description

None

Message ID : VMD3861I

Severity

Information

Long Form

The Key Manager canceled the signature sending for the signature request {0}

Message ID : VMD3859I

Short Form

Sig req cancelled

Parameters

Label	CEF Label	Type	Usage
showStr	reason	Text	Code specifying reason for allowing access, if any

Description

None

Message ID : VMD3862I

Severity

Information

Long Form

Running in FIPS 140-2 mode, using {0}

Short Form

FIPS 140-2 mode

Message ID : VMD3861I

Parameters

Label	CEF Label	Type	Usage
version	vds_version	Text	Software version string

Description

None

Message ID : VMD3863I

Severity

Information

Long Form

Generating the file list for the signature request {0}, {1} files and directories have been scanned

Short Form

Sig scan in progress

Parameters

Label	CEF Label	Type	Usage
showStr	reason	Text	Code specifying reason for allowing access, if any

Message ID : VMD3862I

Label	CEF Label	Type	Usage
nfile	vds_nfile	Numeric	The number of files processed

Description

None

Message ID : VMD3868I

Severity

Information

Long Form

LDAP search of {0}/{1} for {2} returned "{3}"

Short Form

LDAP search error

Parameters

Label	CEF Label	Type	Usage
url	request	Text	A uniform resource location
filePath	filePath	Text	Full path to file

Message ID : VMD3863I

1051

Label	CEF Label	Type	Usage
effect	vds_effect	Text	Policy effect
showStr	reason	Text	Code specifying reason for allowing access, if any

Description

None

Message ID : VMD3870I

Severity

Information

Long Form

Configuration data was supplied by "{0}".

Short Form

Config source

Parameters

Label	CEF Label	Type	Usage
url	request	Text	A uniform resource location

Message ID : VMD3868I

1052

Description

None

Message ID : VMD3880I

Severity

Information

Long Form

The Key Manager was upgraded recently; informing it that this agent is challenge-response aware

Short Form

Try new host password req

Parameters

No parameters are provided for this message type

Description

None

Message ID : VMD3870I

1053

Message ID : VMD3881I

Severity

Information

Long Form

The new certificate set has been activated

Short Form

New certs activated

Parameters

No parameters are provided for this message type

Description

None

Message ID : VMD3883I

Severity

Information

Message ID : VMD3881I

Long Form

Certificates for the {0} agent expire in {1} days

Short Form

Certificate lifetime

Parameters

Label	CEF Label	Type	Usage
agent	deviceProcessName	Text	The short identifier of the agent software
daysleft	vds_daysleft	Numeric	Days until certificate expiry

Description

None

Message ID : VMD3885I

Severity

Information

Message ID : VMD3883I

1055

Long Form

The VMD failed to initialize with the Key Manager. This may indicate that the connection to the server is down, the VMD's host has been deleted from the Key Manager, or "Communication Enabled" for the host has not been enabled in the Key Manager UI.

Short Form

VMD/Server init fail

Parameters

No parameters are provided for this message type

Description

The agent is unable to reach the key manager. You may see any of the following error messages: COM4583F, COM4633W, VMD3770F, VMD3885I or VMD3886I. You may experience any of the following:

1. Connection to the key manager is down.
2. The VMD Host has been deleted from the key manager.
3. The host does not have "Communication Enabled" in the key manager UI.
4. The VMD's host may be deleted from the key manager. Run the register_host utility to re-register the VMD with the key manager.

Message ID : VMD3886I

Severity

Information

Long Form

The VMD's host may no longer be registered with a Key Manager. The VMD's host may have been deleted from the Key Manager. You may want to run the register_host utility to re-register the VMD with a Key Manager.

Short Form

VMD poss unregistered

Parameters

No parameters are provided for this message type

Description

The agent is unable to reach the key manager. You may see any of the following error messages: COM4583F, COM4633W, VMD3770F, VMD3885I or VMD3886I. You may experience any of the following:

1. Connection to the key manager is down.
2. The VMD Host has been deleted from the key manager.
3. The host does not have "Communication Enabled" in the key manager UI.
4. The VMD's host may be deleted from the key manager. Run the register_host utility to re-register the VMD with the key manager.

Message ID : VMD3893I

Severity

Information

Long Form

Clustered property of GP {0} is honored per Key Manager

Short Form

Clustered property of GP is honored per Key Manager

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	GuardPoint base directory

Description

None

Message ID : VMD3895I

Severity

Information

Long Form

RSA certificates detected for the {0} agent, will renew with EC certificates

Short Form

Switching to EC certs

Parameters

Label	CEF Label	Type	Usage
agent	deviceProcessName	Text	The short identifier of the agent software

Description

None

Message ID : VMD3896I

Severity

Information

Long Form

RSA certificates detected for the {0} agent, will not renew with EC certificates as ports 8446/7 not open to Key Manager

Short Form

No Switch to EC certs due to missing 8446/7 ports

Parameters

Label	CEF Label	Type	Usage
agent	deviceProcessName	Text	The short identifier of the agent software

Description

None

Message ID : VMD3897I

Severity

Information

Message ID : VMD3896I

Long Form

New comms session with {0} using token {1}

Short Form

Comms session

Parameters

Label	CEF Label	Type	Usage
shost	shost	Text	Source host name
token	vds_token	Text	A token name (e.g. for one-time-passwords)

Description

None

Message ID : VMD3898I

Severity

Information

Message ID : VMD3897I

Long Form

STARTED on {0} VERSION: {1}

Short Form

VMD Startup

Parameters

Label	CEF Label	Type	Usage
osname	cs2	Text	A name identifying the agent operating system
version	vds_version	Text	Software version string

Description

None

Message ID : VMD3900I

Severity

Information

Message ID : VMD3898I

Long Form

Docker host browsing succeeded.

Short Form

Docker host browse OK

Parameters

No parameters are provided for this message type

Description

None

Message ID : VMD3902I

Severity

Information

Long Form

Docker host browsing for image {0} succeeded.

Short Form

Docker host browse OK

Parameters

Label	Type	Usage
dockerid	Text	Docker image or container id

Description

None

Message ID : VMD3904I

Severity

Information

Long Form

Docker image {0} file browsing for {1} succeeded.

Short Form

Docker image file browse OK

Message ID : VMD3902I

Parameters

Label	CEF Label	Type	Usage
dockerid	dockerid	Text	Docker image or container id
filePath	filePath	Text	Full path to file

Description

None

Message ID : VMD3906I

Severity

Information

Long Form

Docker container {0} file browsing for {1} succeeded.

Short Form

Docker container file browse OK

Message ID : VMD3904I

1065

Parameters

Label	CEF Label	Type	Usage
dockerid	dockerid	Text	Docker image or container id
filePath	filePath	Text	Full path to file

Description

None

Message ID : VMD3908I

Severity

Information

Long Form

User browsing for image {0} with {1} succeeded.

Short Form

Docker image user browse OK

Message ID : VMD3906I

1066

Parameters

Label	CEF Label	Type	Usage
dockerid	dockerid	Text	Docker image or container id
domain	dntdom	Text	A domain name (policy, network, users, etc)

Description

None

Message ID : VMD3910I

Severity

Information

Long Form

User browsing for container {0} with {1} succeeded.

Short Form

Docker container user browse OK

Message ID : VMD3908I

1067

Parameters

Label	CEF Label	Type	Usage
dockerid	dockerid	Text	Docker image or container id
domain	dntdom	Text	A domain name (policy, network, users, etc)

Description

None

Message ID : VMD3912I

Severity

Information

Long Form

Domain browsing for image {0} succeeded.

Short Form

Docker image domain browse OK

Message ID : VMD3910I

1068

Parameters

Label	Type	Usage
dockerid	Text	Docker image or container id

Description

None

Message ID : VMD3914I

Severity

Information

Long Form

Domain browsing for container {0} succeeded.

Short Form

Docker container domain browse OK

Parameters

Label	Type	Usage
dockerid	Text	Docker image or container id

Message ID : VMD3912I

Description

None

Message ID : VMD3919I

Severity

Information

Long Form

Policy "{0}" version {1} received from Key Manager

Short Form

Policy update

Parameters

Label	CEF Label	Type	Usage
pol	cs1	Text	Policy name
verno	vds_verno	Numeric	A version number

Message ID : VMD3914I

1070

Description

None

Message ID : VMD3926I

Severity

Information

Long Form

An partial certificate renewal has been completed successfully

Short Form

Certs recovered OK

Parameters

No parameters are provided for this message type

Description

None

Message ID : VMD3919I

Message ID : VMD3930I

Severity

Information

Long Form

Successfully received and implemented user space part of a new security configuration.

Short Form

Partial Config OK

Parameters

No parameters are provided for this message type

Description

None

Message ID : VMD3934I

Severity

Information

Long Form

The CTE client has passed attestation checks.

Short Form

No short form is provided for this message type

Description

None

Message ID : VMD3935I

Severity

Information

Long Form

Attestation checks to be run on following adapters: {0}

Short Form

Attest run

Message ID : VMD3934I

1073

Parameters

Label	CEF Label	Type	Usage
showStr	reason	Text	Code specifying reason for allowing access, if any

Description

None

Message ID : VMD4246I

Severity

Information

Long Form

Detected upgrade situation from pre-FIPS (4.4.0) to post-FIPS (4.4.1). Converting the private key format now.

Short Form

Key converted

Parameters

No parameters are provided for this message type

Message ID : VMD3935I

Description

None

Message ID : VMD4611I

Severity

Information

Long Form

vm_write_file: Empty write buffer

Short Form

Empty write buf

Parameters

No parameters are provided for this message type

Description

None

Message ID : VMD4246I

1075

Message ID : VMD4619I

Severity

Information

Long Form

The previous message {0} was repeated {1} times

Short Form

Repeat message

Parameters

Label	CEF Label	Type	Usage
msgid	vds_msgid	Text	A unique log message identifier
count	vds_count	Numeric	A generic count value

Description

None

Message ID : VMD4620I

Severity

Information

Long Form

The space available for log files in {0} is low ({1} MB)

Short Form

Log space low

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file
count	vds_count	Numeric	A generic count value

Description

None

Logger VMD: Warnings

Message ID : VMD3714W

Severity

Warning

Long Form

check_mount: {0} {1}{2} match failed({3})

Short Form

No short form is provided for this message type

Description

None

Message ID : VMD3762W

Severity

Warning

Long Form

Keys are not available at time of signing binaries. Check connection to Key Manager or run 'vmsec challenge'

Short Form

No Keys signing binaries.

Parameters

No parameters are provided for this message type

Description

None

Message ID : VMD3805W

Severity

Warning

Long Form

Unhandled service opcode seen. Opcode = {0}

Message ID : VMD3762W

Short Form

Unhandled opcode

Parameters

Label	CEF Label	Type	Usage
ecode	cn1	Numeric	An error code

Description

None

Message ID : VMD3806W

Severity

Warning

Long Form

Unrecognized service opcode seen. Opcode = {0}

Short Form

Unknown opcode

Message ID : VMD3805W

Parameters

Label	CEF Label	Type	Usage
ecode	cn1	Numeric	An error code

Description

None

Message ID : VMD3813W

Severity

Warning

Long Form

The VMD is shutting down.

Short Form

VMD Shutdown

Parameters

No parameters are provided for this message type

Message ID : VMD3806W

Description

System shutdown, reboot or system re-registration will cause this message to display because the CTE daemon process was terminated.

Message ID : VMD3824W

Severity

Warning

Long Form

Failed to create the signature for {0} for the signature request {1}, error code {2}

Short Form

Sig creation error

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file
showStr	reason	Text	Code specifying reason for allowing access, if any
ecode	cn1	Numeric	An error code

Description

None

Message ID : VMD3826W

Severity

Warning

Long Form

{0} is invalid for the signature request {1}

Short Form

Bad sig file

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file
showStr	reason	Text	Code specifying reason for allowing access, if any

Message ID : VMD3824W

Description

None

Message ID : VMD3850W

Severity

Warning

Long Form

Could not find the signature request {0}

Short Form

Sig req mismatch

Parameters

Label	CEF Label	Type	Usage
showStr	reason	Text	Code specifying reason for allowing access, if any

Description

None

Message ID : VMD3826W

Message ID : VMD3860W

Severity

Warning

Long Form

The signature request {0} is already initialized

Short Form

Sig req duplicated

Parameters

Label	CEF Label	Type	Usage
showStr	reason	Text	Code specifying reason for allowing access, if any

Description

None

Message ID : VMD3869W

Severity

Warning

Long Form

No LDAP server details were found (missing or incomplete ldap.conf)

Short Form

No LDAP server

Parameters

No parameters are provided for this message type

Description

No LDAP configuration data was found on the host system. This usually occurs because LDAP services have not been installed or configured properly.

Message ID : VMD3871W

Severity

Warning

Message ID : VMD3869W

1086

Long Form

Unauthorized communication attempt from "{0}" rejected

Short Form

Unauth comms rejected

Parameters

Label	CEF Label	Type	Usage
url	request	Text	A uniform resource location

Description

None

Message ID : VMD3882W

Severity

Warning

Long Form

An error occurred with a new certificate set so the previous set has been restored

Message ID : VMD3871W

Short Form

Backup certs restored

Parameters

No parameters are provided for this message type

Description

None

Message ID : VMD3887W

Severity

Warning

Long Form

Unable to initialize/join Vormetric Cluster Group - proceeding unclustered

Short Form

initialize/join CipherTrust Cluster Group - proceeding unclustered

Message ID : VMD3882W

1088

Parameters

No parameters are provided for this message type

Description

None

Message ID : VMD3889W

Severity

Warning

Long Form

Cluster coherent GP {0} not allowed on unclustered node

Short Form

Cluster coherent GP not allowed on unclustered node

Parameters

Label	CEF Label	Type	Usage
gp	fileId	Text	GuardPoint base directory

Message ID : VMD3887W

Description

None

Message ID : VMD3899W

Severity

Warning

Long Form

The authentication signature for file {0} has changed

Short Form

Signature changed

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : VMD3889W

Message ID : VMD3920W

Severity

Warning

Long Form

Agent failing over to server "{0}"

Short Form

Failover

Parameters

Label	CEF Label	Type	Usage
shost	shost	Text	Source host name

Description

None

Message ID : VMD3921W

Severity

Warning

Long Form

Agent reverting to assigned server "{0}"

Short Form

Failover end

Parameters

Label	CEF Label	Type	Usage
shost	shost	Text	Source host name

Description

None

Message ID : VMD3924W

Severity

Warning

Message ID : VMD3921W

Long Form

Unknown key manager in URL {0} will be ignored. This attribute is located in the config file at {1}.

Short Form

Unknown URL in config file

Parameters

Label	CEF Label	Type	Usage
url	request	Text	A uniform resource location
filePath	filePath	Text	Full path to file

Description

None

Message ID : VMD3925W

Severity

Warning

Long Form

Certificate renewal not possible due to missing external cert directory and no saved CSR

Short Form

Cert renewal impossible

Parameters

No parameters are provided for this message type

Description

None

Message ID : VMD3928W

Severity

Warning

Long Form

Certificate for "{0}" expires in {1} days

Message ID : VMD3925W

Short Form

CA cert expires

Parameters

Label	CEF Label	Type	Usage
agent	deviceProcessName	Text	The short identifier of the agent software
daysleft	vds_daysleft	Numeric	Days until certificate expiry

Description

None

Message ID : VMD3931W

Severity

Warning

Long Form

A required signature set update has not been received from the Key Manager - policy rules may not be enforced correctly.

Message ID : VMD3928W

Short Form

Missing sigset push

Parameters

No parameters are provided for this message type

Description

None

Message ID : VMD3933W

Severity

Warning

Long Form

The CTE client is unable to perform attestation checks.

Short Form

No short form is provided for this message type

Message ID : VMD3931W

Description

None

Message ID : VMD4618W

Severity

Warning

Long Form

The previous message {0} was repeated {1} times

Short Form

Repeat message

Parameters

Label	CEF Label	Type	Usage
msgid	vds_msgid	Text	A unique log message identifier
count	vds_count	Numeric	A generic count value

Message ID : VMD3933W

Description

None

Message ID : VMD4621W

Severity

Warning

Long Form

The space available for log files in {0} is dangerously low ({1} MB)

Short Form

Log space low

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file
count	vds_count	Numeric	A generic count value

Message ID : VMD4618W

Description

The directory used to process log files is low on space. The "filePath" field gives the path and directory. The "count" field gives the remaining space (in MB).

When space is low audit trails may become compromised, and error conditions may be unreported. This should be resolved immediately.

Message ID : VMD4622W

Severity

Warning

Long Form

Raising drop log message level to {0} because space consumed is now greater than {1}% and less than or equal to {2}%.

Short Form

Raise drop space level

Parameters

Label	CEF Label	Type	Usage
showStr	reason	Text	Code specifying reason for allowing access, if any
count	vds_count	Numeric	A generic count value

Label	CEF Label	Type	Usage
count	vds_count	Numeric	A generic count value

Description

The space that holds log files uploaded to the key manager is increasing. Logging levels are automatically modified to accommodate the load. The "reason" field details the change being imposed, and the two "count" fields depict the lower and upper "percentage full" values that caused this condition. The following strings may occur on the "reason" field:

Reason	Meaning
Drop None	No adjustments currently in force
Speed Up	The agent will try to upload logs to the key manager in larger batches
Drop Info	No INFO level logs will be uploaded
Drop Warn	No WARN level logs will be uploaded
Drop Error	No ERROR level logs will be uploaded

Message ID : VMD4623W

Severity

Warning

Long Form

Raising drop log message level to {0} because number of files is now greater than {1}% and less than or equal to {2}%.

Short Form

Raise drop file level

Parameters

Label	CEF Label	Type	Usage
showStr	reason	Text	Code specifying reason for allowing access, if any
count	vds_count	Numeric	A generic count value
count	vds_count	Numeric	A generic count value

Description

Files pending upload to the key manager are increasing, so the agent has temporarily adjusted the logging parameters to handle the situation. The "reason" field details the change imposed, and the two "count" fields indicate the lower and upper percentages of the maximum permitted number of files. See VMD4622W for usage of the "reason" field.

Message ID : VMD4624W

Severity

Warning

Message ID : VMD4623W

1101

Long Form

Lowering drop log message level to {0} because space consumed is now greater than {1}% and less than or equal to {2}%.

Short Form

Lower drop space level

Parameters

Label	CEF Label	Type	Usage
showStr	reason	Text	Code specifying reason for allowing access, if any
count	vds_count	Numeric	A generic count value
count	vds_count	Numeric	A generic count value

Description

The space used to hold log files for uploading to the key manager is decreasing, so the agent has temporarily adjusted the logging parameters to handle the situation. See VMD4622W for details about the fields used.

Message ID : VMD4625W

Severity

Warning

Message ID : VMD4624W

Long Form

Lowering drop log message level to {0} because number of files is now greater than {1}% and less than or equal to {2}%.

Short Form

Lower drop file level

Parameters

Label	CEF Label	Type	Usage
showStr	reason	Text	Code specifying reason for allowing access, if any
count	vds_count	Numeric	A generic count value
count	vds_count	Numeric	A generic count value

Description

The number of files pending upload to the key manager is decreasing, so the agent has temporarily adjusted the logging parameters to handle the situation. See VMD4623W for details about the fields used.

Message ID : VMD4636W

Severity

Warning

Message ID : VMD4625W

Long Form

Unable to determine expiry date from certificate {0}

Short Form

Cannot get expiry date

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : VMD4639W

Severity

Warning

Long Form

Corrupt log data from Secfs in file {0} - some records lost

Message ID : VMD4636W

Short Form

Corrupt log file

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Message ID : VMD4640W

Severity

Warning

Long Form

Invalid directory in log directory. {0} Please remove.

Short Form

Invalid directory in log directory.

Message ID : VMD4639W

Parameters

Label	CEF Label	Type	Usage
filePath	filePath	Text	Full path to file

Description

None

Logger XFM: Errors

Message ID : XFM4501E

Severity

Error

Long Form

Decompression failure: the size of the data resulting from decompression is not the same size as before compression. Possible data corruption.

Short Form

Size mismatch

Parameters

No parameters are provided for this message type

Description

None

Message ID : XFM4502E

Severity

Error

Long Form

Compression setup failure: module not initialized.

Short Form

Compression init fail

Parameters

No parameters are provided for this message type

Description

None

Message ID : XFM4504E

Severity

Error

Long Form

Compression setup failure: no applicable module initialized.

Short Form

Compression setup fail

Parameters

No parameters are provided for this message type

Description

None

Message ID : XFM4535E

Severity

Error

Long Form

Decompression got corrupted buffer (invalid size of encrypted data).

Message ID : XFM4504E

Short Form

Encryption buffer corrupt

Parameters

No parameters are provided for this message type

Description

None

Message ID : XFM4568E

Severity

Error

Long Form

Compression failure: destination buffer too small: {0} < {1}.

Short Form

Buffer too small

Message ID : XFM4535E

1110

Parameters

Label	CEF Label	Type	Usage
slen	in	Numeric	Input byte count or length
dlen	out	Numeric	Output byte count or length

Description

None

Message ID : XFM4589E

Severity

Error

Long Form

Unable to initialize the message digest subsystem. The operation will fail.

Short Form

Digest setup fail

Message ID : XFM4568E

1111

Parameters

No parameters are provided for this message type

Description

None

Message ID : XFM4590E

Severity

Error

Long Form

Unable to compute the message digest value.

Short Form

Cannot compute digest

Parameters

No parameters are provided for this message type

Message ID : XFM4589E

1112

Description

None

Message ID : XFM4591E

Severity

Error

Long Form

Unable to the retrieve the message digest value.

Short Form

Cannot extract digest

Parameters

No parameters are provided for this message type

Description

None

Message ID : XFM4590E

Logger XFM: Fatal errors

Message ID : XFM4508F

Severity

Fatal error

Long Form

Unable to find chunk headers; possible data corruption.

Short Form

Missing chunk hdr

Parameters

No parameters are provided for this message type

Description

None

Message ID : XFM4509F

Severity

Fatal error

Long Form

Decompression/decryption failure: output buffer size ({0} bytes) is too small.

Short Form

Decomp/decrypt buffer too small

Parameters

Label	CEF Label	Type	Usage
dlen	out	Numeric	Output byte count or length

Description

None

Message ID : XFM4518F

Severity

Fatal error

Message ID : XFM4509F

Long Form

Invalid encryption key size received from Key Manager. The operation will fail.

Short Form

Invalid encr. key size

Parameters

No parameters are provided for this message type

Description

None

Message ID : XFM4519F

Severity

Fatal error

Long Form

The agent could not allocate enough memory. Contact support.

Message ID : XFM4518F

Short Form

Out of memory

Parameters

No parameters are provided for this message type

Description

None

Message ID : XFM4525F

Severity

Fatal error

Long Form

Decryption fatal error: {0}. The restore operation will fail.

Short Form

Decryption error

Message ID : XFM4519F

1117

Parameters

Label	CEF Label	Type	Usage
ecode	cn1	Numeric	An error code

Description

None

Message ID : XFM4532F

Severity

Fatal error

Long Form

Decryption information mismatch; possible data corruption.

Short Form

Decryption info mismatch

Parameters

No parameters are provided for this message type

Message ID : XFM4525F

Description

None

Message ID : XFM4536F

Severity

Fatal error

Long Form

Compression module returned fatal error: {0}. The operation will fail.

Short Form

Compression error

Parameters

Label	CEF Label	Type	Usage
ecode	cn1	Numeric	An error code

Description

None

Message ID : XFM4532F

Message ID : XFM4539F

Severity

Fatal error

Long Form

Unable to set up encryption subsystem. The operation will fail.

Short Form

Encryption setup fail

Parameters

No parameters are provided for this message type

Description

None

Message ID : XFM4540F

Severity

Fatal error

Message ID : XFM4539F

Long Form

Decompression information mismatch; possible data corruption.

Short Form

Decompression info mismatch

Parameters

No parameters are provided for this message type

Description

None

Message ID : XFM4541F

Severity

Fatal error

Long Form

Data read problem: corrupted buffer header. Data corruption has possibly occurred. The restore operation will fail.

Message ID : XFM4540F

1121

Short Form

Corrupt buffer header

Parameters

No parameters are provided for this message type

Description

None

Message ID : XFM4544F

Severity

Fatal error

Long Form

Unable to set up compression subsystem. The operation will fail.

Short Form

Compression setup fail

Message ID : XFM4541F

Parameters

No parameters are provided for this message type

Description

None

Message ID : XFM4546F

Severity

Fatal error

Long Form

Compression module initialization failure. The backup operation will fail.

Short Form

Compression init fail

Parameters

No parameters are provided for this message type

Message ID : XFM4544F

Description

None

Message ID : XFM4561F

Severity

Fatal error

Long Form

Decompression fatal error: {0}. The restore operation will fail.

Short Form

Decompression error

Parameters

Label	CEF Label	Type	Usage
ecode	cn1	Numeric	An error code

Description

None

Message ID : XFM4546F

Message ID : XFM4565F

Severity

Fatal error

Long Form

Input data length does not match buffer length: {0} != {1}. Data corruption has possible occurred. The restore operation will fail.

Short Form

Data lenght mismatch

Parameters

Label	CEF Label	Type	Usage
slen	in	Numeric	Input byte count or length
dlen	out	Numeric	Output byte count or length

Description

None

Logger XFM: Information

Message ID : XFM4507I

Severity

Information

Long Form

Using no encryption.

Short Form

Using no encryption

Parameters

No parameters are provided for this message type

Description

None

Message ID : XFM4517I

Severity

Information

Long Form

Shutting down compression/decompression subsystem.

Short Form

Comp/decomp shutdown

Parameters

No parameters are provided for this message type

Description

None

Message ID : XFM4522I

Severity

Information

Message ID : XFM4517I

Long Form

Data transformation code now using single-threaded algorithm.

Short Form

Single-thread transform

Parameters

No parameters are provided for this message type

Description

None

Message ID : XFM4526I

Severity

Information

Long Form

Using no compression.

Message ID : XFM4522I

Short Form

Using no compression

Parameters

No parameters are provided for this message type

Description

None

Message ID : XFM4549I

Severity

Information

Long Form

Using compression.

Short Form

Using compression

Message ID : XFM4526I

Parameters

No parameters are provided for this message type

Description

None

Message ID : XFM4557I

Severity

Information

Long Form

Using {0} encryption algorithm.

Short Form

Using enc algorithm

Parameters

Label	CEF Label	Type	Usage
key	cs3	Text	Name of key or key pair

Message ID : XFM4549I

Description

None

Message ID : XFM4559I

Severity

Information

Long Form

Shutting down encryption/decryption subsystem.

Short Form

Encrypt/decrypt shutdown

Parameters

No parameters are provided for this message type

Description

None

Message ID : XFM4557I

Logger XFM: Warnings

Message ID : XFM4550W

Severity

Warning

Long Form

Compression initialization failure: failed to initialize algorithm {0} upon startup.

Short Form

Compression init fail

Parameters

No parameters are provided for this message type

Description

None